

ةي لودلا مي قرتلا ةطخ تي بثت اهال صاوا هئاطخا فاشكتساوا هنيوكتو

تايوت حمللا

[ةمدقملا](#)

[ةيساساللا تابلطتملا](#)

[تابلطتملا](#)

[ةمدختسملا تانوكملا](#)

[Background تاملعم](#)

[نيوكتلا](#)

[داعإ INNP](#)

[INNP في دونب](#)

[ةحصللا نم ققحتلا](#)

[اهال صاوا ءاطخاللا فاشكتساوا](#)

ةمدقملا

اهال صاوا هئاطخا فاشكتساوا هنيوكتو INNP تي بثت ةيفيكت دننتملا اذه حضوي

اكرمأ في ةيضارتفا مي قرت ةطخ (CUCM) Cisco نم ةدحوملا تالاصتالا ري دم رفوي
كنكمي، ةفلتخملا بلطلا ةطخ تابلطتم تاذا نادلبلل ةبس نلاب (NANP) ةيلامشلا
ةصاخ ةديرف مي قرت ةطخ ءاشنال اهمادختساوا Cisco نم ةيلود بلط ةطخ تي بثت
كتابلطتم.

ةيساساللا تابلطتملا

تابلطتملا

ةيلاتلا عيضاوملاب ةفرعم كي دل نوكت ناب Cisco ي صوت:

- تاملكملا هيحوت
- راسملا ةيفصت لماع

ةمدختسملا تانوكملا

Cisco Unified CallManager 11.5 لىل دننتملا اذه في ةدراولا تامولعملل دننست

ةصاخ ةيلمعم ةئيبي في ةدوجوملا ةزهجالا نم دننتملا اذه في ةدراولا تامولعملل ءاشنال مت
تاناك اذإ. (يضارتفا) حوسمم نيوكتب دننتملا اذه في ةمدختسملا ةزهجالا عيمج تادب
رمأ يال لم تحملا ريثاتلل كمهف نم دكاتف، ةرشابم كتكباش

Background تامول عم

ليزنتب مق، ةيلا مشلا الكيرمأ جراخ نادلب للة ية نطو مي قرت ةطخ تي ب ثت ب موقت تنك اذا رادصإ اب ةصاخلا ةي لودلا بل طاخ يلع يوتحي يذلا Cisco Option Package (COP) فلم يلا لال.

ب: يولا يلع Cisco عقوم يلع رفوت ية م س ت ل ا ح ا ل ط ص ا COP فلم مدختسي

<https://software.cisco.com/download/release.html?mdfid=278719042&softwareid=282074292&os=Linux&release=3.1.33-GB&reind=AVAILABLE&rellifecycle=&reltype=latest>

نيوكتلا

اذه فلم تي ب ثت ب صاخلا ءارجالا وه اذه

ل. ليغش تال ماظن لوؤسم يلا لوخدلا ليحست 1. ةوطخل

The screenshot shows the Cisco Unified Operating System Administration web interface. At the top, there is a navigation bar with the Cisco logo and the text "Cisco Unified Operating System Administration For Cisco Unified Communications Solutions". A navigation menu is visible on the right with "Cisco Unified OS Administration" selected. Below the navigation bar, there is a warning message: "WARNING: No backup device is configured. This is required to recover your system in case of failure." The main content area displays "Cisco Unified Operating System Administration" with "System version: 11.5.1.12018-1" and "VMware Installation: 4 vCPU Intel(R) Xeon(R) CPU E5-4669 v3 @ 2.10GHz, disk 1: 120Gbytes, 5120Mbytes RAM, Partitions aligned". A "Last Successful Logon: Never" message is also present. The footer contains copyright information: "Copyright © 1999 - 2016 Cisco Systems, Inc. All rights reserved."

ة: روصلا ي ف حضوم وه امك، ةي قرت/ تي ب ثت > جم اربلا ةي قرت يلا لقتنا 2. ةوطخل

This screenshot is similar to the previous one but shows a dropdown menu open under the "Software Upgrades" menu item. The menu options are "Install/Upgrade", "TFTP File Management", "Device Load Management", and "Customized Logon Message". The warning message and system information are still visible in the background.

ة. ةي قرت لال/ تي ب ثت لال ذيفنتل SFTP م داخ مدختسن انه: ردصملا دح

ديعبلا تافلما ل ماظن: ردصملا

ل: لال /

ب. تكملا حطس/ لومح م رتوي بمك ل ل IP ناو نع لغشي SFTP قي ب ط ت ا ق ب ا ب جي انه: م داخ ل

SFTP م دختسم مسا: م دختسم ل مسا

SFTP مَدْخْتِ سَم رورم ةمَلَك: مَدْخْتِ سَم ل رورم ةمَلَك

SFTP: ل قنل لوك و توروب

Show Settings Security Software Upgrades Services Help

Software Installation/Upgrade

Cancel Next

Status

Status: Ready

Software Location

Source* Remote Filesystem

Directory* /

Server* 192.168.0.20

User Name* admin

User Password* [REDACTED]

Transfer Protocol* SFTP

SMTP Server

Email Destination

Cancel Next

ةروصل ل ف حِضوم وه امك ةشاشل رهظت مَث لَلاتل ددح 3 ةوطخل

لَلاتل ددحت مَث INNP ل حِصص ل ل طرشل ل فلم ددحت بچي

Software Installation/Upgrade

Cancel Next

Status

Status: Ready

Software Location

Options/Upgrades* dp-ffr.3-1-8.IN.k3.cop.sgn

Invalid Upgrades

Option Names	Status
10.196.120.25_bulk_tftp.pkcs12	Name does not match any filter pattern.
Publisher_tomcat.pkcs12	Name does not match any filter pattern.
CUCM-PUB_tomcat.pkcs12	Name does not match any filter pattern.

لَلاتل ددح. ةروصل ل ف حِضوم وه امك ةشاشل ل ل لصحت

Software Installation/Upgrade

Cancel Next

Status

Warning: To ensure the integrity of the installation file, please verify the MD5 hash value against the Cisco Systems web site

Warning: To ensure the integrity of the installation file, please verify the SHA512 value against the Cisco Systems web site

Warning: You may need to stop some services before you install a locale. You may then restart those services after you complete the locale installation. Refer to your product-specific online help for locale installation details.

File Checksum Details

File dp-ffr.3-1-8.IN.k3.cop.sgn
 MD5 Hash Value 28:36:a4:74:45:48:32:c3:85:3e:3f:8b:b4:40:21:28
 SHA512 Value

Cancel Next

i *- indicates required item.

مدققت ال دي ق تي بثل ال 4. ةوطخل

Cancel

Installation Status

File dp-ffr.3-1-8.IN.k3.cop.sgn
 Start Time Wed Dec 28 15:20:08 IST 2016
 Status Running

Installation Log

```
12/28/2016 15:20:08 sd_cancelInstall.sh|Canceling active side processes done
12/28/2016 15:20:08 sd_cancelInstall.sh|Canceling inactive side processes
12/28/2016 15:20:08 sd_cancelInstall.sh|Skipping IDS shared memory clean up since this is a COP
12/28/2016 15:20:09 sd_cancelInstall.sh|Canceling inactive side processes done
[16/12/28_15:20:14] locale_install.sh: Successful untarring of /common/download//dp-ffr.3-1-8.IN.k3.cop

Call manager version is : master-11.5.1.12018-1.i386
cp: cannot stat `/common/download/IDP': No such file or directory

cp: cannot stat `/common/download/INNP.xml': No such file or directory
```

Cancel

ت. بثل ال لم تك 5. ةوطخل

Install Another

Installation Status

File dp-ffr.3-1-8.IN.k3.cop.sgn
 Start Time Wed Dec 28 15:20:08 IST 2016
 Status Complete

Installation Log

```
installCsv rc[0]
enablenotify dsn[DSN=ccm_super]
enablenotify rc[0]
installdb Success[-c]
[16/12/28_15:20:17] locale_install.sh: Publisher: Starting installdb...
/bin/su -l informix -s /bin/sh -c
"source /usr/local/cm/db/dblenv.bash /usr/local/cm ;
source /usr/local/cm/db/informix/local/ids.env ;
nice /usr/local/cm/bin/installdb -x /usr/local/cm/db/xml/xml"
```

Install Another

ة. وومجمل ماظن في دقعل اعمي جل اهس فن ةي لمعل ذي فن تب مق

اداع INNP

ب. لطل ال ةطخ تبثم > تاملكم ال هي جوت ال لقتنا، Cisco Unified CM ةراد| تحت 1. ةوطخل

Cisco Unified CM Administration
For Cisco Unified Communications Solutions

Navigation: Cisco Unified CM Administration Go

System Call Routing Media Resources Advanced Features Device Application User Management Bulk Administration Help

WARNING: No backup device is configured. This is required to recover your system in case of failure.

Cisco Unified CM Administration
System version: 11.5.1.12018-1
VMware Installation: 4 vCPU Intel(R) Xeon(R) CPU E5-4669 v3 @ 2.10GHz, disk 1: 120Gbytes, 5120Mbytes RAM, Partitions aligned

User c last logged in to this cluster on Wednesday, December 28, 2016 3:03:54 PM IST, to node 10.106.99.199, from 10.196.120.192 using HTTPS

System Route Filter

- Route/Hunt
- SIP Route Pattern
- Class of Control
- Intercom
- Client Matter Codes
- Forced Authorization Codes
- Emergency Location
- Translation Pattern
- Call Park
- Directed Call Park
- Call Pickup Group
- Directory Number
- Meet-Me Number/Pattern
- Conference Now
- Dial Plan Installer**
- Route Plan Report

Advanced Features Device Application User Management Bulk Administration Help

WARNING: No backup device is configured. This is required to recover your system in case of failure.

Cisco Unified CM Administration
System version: 11.5.1.12018-1
VMware Installation: 4 vCPU Intel(R) Xeon(R) CPU E5-4669 v3 @ 2.10GHz, disk 1: 120Gbytes, 5120Mbytes RAM, Partitions aligned

User c last logged in to this cluster on Wednesday, December 28, 2016 3:03:54 PM IST, to node 10.106.99.199, from 10.196.120.192 using HTTPS

Copyright © 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

This product is provided under license from Cisco and/or its affiliates. All rights reserved. Cisco Confidential

Products may be found at our [Export Compliance Product Report](#) web site.

ةروصلال ي ف حضوم وه امك ، INNP ددحو شح ب لىل ع رقنا 2. ةوطخلال

System Call Routing Media Resources Advanced Features Device Application User Management Bulk Administration Help

Find and List Dial Plans

-Status

2 records found

Dial Plan (1 - 2 of 2)

Find Dial Plan where Dial Plan begins with Find Clear Filter

Dial Plan	Description	Installed Version	System Version
CHNP	Switzerland Numbering Plan	1.1(6)	1.1(6)
INNP	India Numbering Plan	1.1(8)	1.1(8)

ت. تيبثت لىل ع رقنا ،ةروصلال ي ف حضوم وه امك 3. ةوطخلال

Dial Plan Configuration

Install Uninstall

Dial Plan Information

Dial Plan* INNP

Description India Numbering Plan

Installed Version 1.1(8)

Available Version 1.1(8)

Install Uninstall

دقعلال ةفاك ىلع CM ةمدخ ليغشت ةداعإب مق ،يطرشلال فلملا تيبتت نم ءاهت نالال درجمب

INNP يف دونب

First understand the clauses in the INNP:

```
# P: Digit pattern -- PATTERN TAG
# T: Type of Number -- I(nternational) or N(ational)
# W: Network Specific Facilities -- OP or OPXXXX(alternate carriers)
# U: Urgent pattern? (Call extended immediately on match)
```

```
# [2-6]XXXXXX
P: [2-6]XXXXXX LOCAL-6-DIGIT
```

```
# [2-6]XXXXXXX
P: [2-6]XXXXXXX LOCAL-7-DIGIT
```

```
# [2-6]XXXXXXXX
P: [2-6]XXXXXXXX LOCAL-8-DIGIT
```

Long Distance Calls

```
# 0+11+[2-6]XXXXXXXX
P: 0 NATIONAL-ACCESS
P: 11 AREA-CODE
P: [2-6]XXXXXXXX LOCAL-8-DIGIT
T: N
```

```
# 0+2[02]+[2-6]XXXXXXXX
P: 0 NATIONAL-ACCESS
P: 2[02] AREA-CODE
P: [2-6]XXXXXXXX LOCAL-8-DIGIT
T: N
```

```
# 0+33+[2-6]XXXXXXXX
P: 0 NATIONAL-ACCESS
P: 33 AREA-CODE
P: [2-6]XXXXXXXX LOCAL-8-DIGIT
T: N
```

Services, Mobile & Non Geographic Calls

```
# 100
P: 100 SERVICE
U: Y
```

```
# 101
P: 101 SERVICE
U: Y
```

```
# 80[01589]X+XXX+XXX
P: 80[01589]X LOCAL-PREFIX-8-MOBILE
P: XXX MOBILE-ACCESS
P: XXX MOBILE-SUBSCRIBER
T: N
```

```
# 81XX+XXX+XXX
P: 81XX LOCAL-PREFIX-8-MOBILE
P: XXX MOBILE-ACCESS
P: XXX MOBILE-SUBSCRIBER
```

T: N

8128+XXX+XXX

P: 8128 LOCAL-PREFIX-8-MOBILE

P: XXX MOBILE-ACCESS

P: XXX MOBILE-SUBSCRIBER

T: N

8149+XXX+XXX

P: 8149 LOCAL-PREFIX-8-MOBILE

P: XXX MOBILE-ACCESS

P: XXX MOBILE-SUBSCRIBER

T: N

INNP: دون ب صاخال طابترالا لى هاندأ عوجرلا عاجرلا ، ليصافتلا نم دي زملا

<http://www.cisco.com/web/software/282074292/122537/INNP.txt>

راسملا ةيفصت لماع ئشننس ، هالعأ ةدراولا تامولعمل اساسا لىلع

لائم:

لاصتالاب طقف حمسي يلمح اعادتسا ةيفصت لماع عاشن يفتك تابلطتم لثمتي
يحمل.

و 8 و 7 نم اءب يلمح لاول فاهال مقرب لاصتالا 3001 Extension لىلع نيعتي :ويراني سل
9.

(ماقرأ 8) يلمح لاضرألا طخال مقرب لاصتالا 3001 قحلم لىلع بجي

يسنجل لاصتالاب ةصاخلاو ةيلودلا تاملكم لبلط رطح 3001 Extension ةمدخ لىلع نيعتي

pt-local - ديجمسق عاشن 1. ةوطخال

مسقلا > مكحتلا ةئف > تاملكم لاهيوت لىلق تنا

Partition Configuration



Save



Delete



Reset



Apply Config



Add New

Status



Status: Ready

Partition Information

Name*

Description

Time Schedule

Time Zone

 Originating Device Specific Time Zone

Save

Delete

Reset

Apply Config

Add New



*- indicates required item.

يحلحـم-CSS - ديـجـ CSS ءاشنـا 2. ةوطـخـلا


ثـحـبـلا ةحـاسـم ءاعـدـتـسـا > مـكـحـتـلا ةئـف > تـامـلـكـمـلا هـيـجـوتـىـلا لـقـتـنا

pt-local مـسـقـلـاب ظـفـتـحـتـنـا، CSS، اذـه يـف

Calling Search Space Configuration

 Save  Delete  Copy  Add New

Status

 Status: Ready

Calling Search Space Information

Name*
Description

Route Partitions for this Calling Search Space

Available Partitions**
Global Learned E164 Numbers
Global Learned E164 Patterns
Global Learned Enterprise Numbers
Global Learned Enterprise Patterns

▼ ▲

Selected Partitions

▼ ▲

هجوم الة في صت لماع عاشن | 3. ةوطخل

راسم الة في صت لماع > تامل الكمل هيجوت ل لقتنا

ةروصل الة في حضم وه امك ، ديدج ةفاض ل ع رقتنا

Find and List Route Filters

 Add New

Route Filter

Find Route Filter where Route Filter Name  


No active query. Please enter your search criteria using the options above.

م يقرت الة ةطخ ددح ، ةروصل الة في حضم وه امك

Route Filter Configuration



Status

 Status: Ready

Route Filter Information

Numbering Plan*

Next

 *- indicates required item.

تابلطتملل اقفوهذه ةيفصتلا لم اوعاشنإ متي.

Route Filter Name*	Local
Numbering Plan	India Numbering Plan
Clause	(LOCAL-PREFIX-7-MOBILE EXISTS AND MOBILE-ACCESS EXISTS AND MOBILE-SUBSCRIBER EXISTS) OR (LOCAL-PREFIX-8-MOBILE EXISTS AND MOBILE-ACCESS EXISTS AND MOBILE-SUBSCRIBER EXISTS) OR (LOCAL-PREFIX-9-MOBILE EXISTS AND MOBILE-ACCESS EXISTS AND MOBILE-SUBSCRIBER EXISTS) OR (LOCAL-8-DIGIT EXISTS)

Clause Information

To add a clause within this Route Filter, click Add Clause.

LOCAL-PREFIX-7-MOBILE

AND

MOBILE-ACCESS

AND

MOBILE-SUBSCRIBER

OR

LOCAL-PREFIX-8-MOBILE

AND

MOBILE-ACCESS

AND

MOBILE-SUBSCRIBER

OR

LOCAL-PREFIX-8-MOBILE	EXISTS	▼	AND
MOBILE-ACCESS	EXISTS	▼	AND
MOBILE-SUBSCRIBER	EXISTS	▼	
OR			
Edit Clause	Remove Clause		
LOCAL-PREFIX-9-MOBILE	EXISTS	▼	AND
MOBILE-ACCESS	EXISTS	▼	AND
MOBILE-SUBSCRIBER	EXISTS	▼	
OR			
Edit Clause	Remove Clause		
LOCAL-8-DIGIT	EXISTS	▼	

راسم طمن عاشن 4. ةوطخل

راسم طمن > تاملكم ال هي جوت/هي جوت > تاملكم ال هي جوت لى لقتنا

Pattern Definition

Route Pattern*	9.@	Here we have created the 9.@ pattern
Route Partition	PT-LOCAL	Keep the PT-LOCAL partition
Description		
Numbering Plan*	INNP	Select the numbering plan
Route Filter	Local	Select the Route Filter created for Local calling.
MLPP Precedence*	Default	
<input type="checkbox"/> Apply Call Blocking Percentage		
Resource Priority Namespace Network Domain	< None >	
Route Class*	Default	
Gateway/Route List*	Chandra-CUCM	(Edit)
Route Option	<input checked="" type="radio"/> Route this pattern <input type="radio"/> Block this pattern No Error	
Call Classification*	OffNet	
External Call Control Profile	< None >	
<input type="checkbox"/> Allow Device Override	<input checked="" type="checkbox"/> Provide Outside Dial Tone	<input type="checkbox"/> Allow Overlap Sending
	<input type="checkbox"/> Urgent Priority	

Connected Party Transformations

Connected Line ID Presentation*	Default
Connected Name Presentation*	Default

Called Party Transformations

Discard Digits	< None >
Called Party Transform Mask	
Prefix Digits (Outgoing Calls)	
Called Party Number Type*	Cisco CallManager
Called Party Numbering Plan*	Cisco CallManager

ISDN Network-Specific Facilities Information Element

Network Service Protocol	-- Not Selected --	
Carrier Identification Code		
Network Service	Service Parameter Name	Service Parameter Value
-- Not Selected --	< Not Exist >	

ححص CSS لى ع يوتحي رابتخالا قحلم نأ نم دكأت ال يجرى (CSS-Local).

Directory Number* 3001 Urgent Priority

Route Partition PT-CUG

Description Phone A

Alerting Name Phone A

ASCII Alerting Name Phone A

External Call Control Profile < None >

Allow Control of Device from CTI

Line Group Test [Edit Line Group](#)

Associated Devices SEP00E16DBA5FD5
MVA [Edit Device](#)
[Edit Line Appearance](#)

Dissociate Devices

Directory Number Settings

Voice Mail Profile < None > (Choose <None> to use system default)

Calling Search Space CSS-Local

ةحصل ال نم ق قحت ال

لېكشنت ال نم ق قحت:


فتاوه ال > لېلحت ال ال لقتنا، ب لطل مقرر لحت 1. ةوطخل

Cisco Unified Communications Manager Dialed Number Analyzer
For Cisco Unified Communications Solutions

Navigation Cisco Unified Communications Manager Serviceability Go

Analysis Service Help

Cisco Unified Communications Manager Dialed Number Analyzer
System version: 11.5.1.12018-1



ثحب قوف رقتناو 3001 ق حلم ال لخدأ.

Analysis Service Help

Find and List Phones

Status **i** 1 records found

Search Options
Find Phone where Directory Number begins with 3001 [Find](#) Search Within Results
Select item or enter search text

Search Results

Device Name(Line)	Description	Device Pool	Extension	Partition	Device Protocol	Status	IP Address
7841 SEP00E16DBA5FD5	Auto 3003	HQ	3001	PT-CUG	SIP	Registered	10.106.99.249

Rows per Page 50

- Device Information (Model = Cisco 7841)

Registration	Registered with Cisco Unified CallManager 10.106.99.199
IP Address	10.106.99.249
MAC Address	00E16DBA5FD5
Device Name	00E16DBA5FD5
Description	Auto 3003
Owner User ID	cisco3
Device Pool	HQ
Call Classification	OnNet
Calling Search Space	None
AAR Calling Search Space	None
Media Resource Group List	None
Device Time Zone	Etc/GMT

Association Information

-  Line [1] - 3001 in PT-CUG
-  Line [2] - 3006 in PT-CUG
-  Line [3] - 8888 (no partition)

- Analyzer Input

Dialed Digit Settings

- Directory URI
- Dialed Digits

وه امك ،ححص حشررم و ل يص افت ل ل ك اه ب ة ح ف ص ره ط ت ، ل ل ح ت ي ل ع ر ق ن ت ت ن أ و . 2 ة و ط خ ل ا ة : ر و ص ل ا ي ف ح ص و م

Cisco Unified Communications Manager Dialed Number Analyzer Results

Expand All

Collapse All

Results Summary

Calling Party Information

- **Dialed Digits** = 944262527
- **Match Result** = RouteThisPattern

Matched Pattern Information

- **Pattern** = 9.@
- **Partition** = PT-LOCAL
- **Time Schedule** =
- **Called Party Number** = 944262527
- **Time Zone** = Etc/GMT
- **End Device** = Chandra-CUCM
- **Call Classification** = OffNet
- **InterDigit Timeout** = NO
- **Device Override** = Disabled
- **Outside Dial Tone** = NO

Call Flow

Route Pattern :Pattern= 9.@

- **Positional Match List** = 9:44262527
- **DialPlan** = India Numbering Plan

Route Filter

- **Filter Name** = Local
- **Filter Clause** = (LOCAL-PREFIX-7-MOBILE EXISTS AND MOBILE-ACCESS EXISTS AND MOBILE-SUBSCRIBER EXISTS) OR (LOCAL-PREFIX-8-MOBILE EXISTS AND MOBILE-ACCESS EXISTS AND MOBILE-SUBSCRIBER EXISTS) OR (LOCAL-PREFIX-9-MOBILE EXISTS AND MOBILE-ACCESS EXISTS AND MOBILE-SUBSCRIBER EXISTS) OR (LOCAL-8-DIGIT EXISTS)
- **Require Forced Authorization Code** = No
- **Authorization Level** = 0

اهحال صإو ءاطخأل فاشكسا

تمق اذإ .ةدحاو ةلكشم هيدل نكلو ديج لكش ب هنيوكت مت يذلا راسملا ةيفصت لماع لمع ي لآح ةيأ ىلع ةملاكمل كل رهظتس ف ،نيمقرلا يذ ةقطنملا زمرب STD مقر بلطب

ةملاكمل هيجوتب موقى هناف ،080 26252728 مقرلا بلطب تمق اذإ :لاثملا لىبس ىلع يلمحلملا ةيفصتلا لماع مادختساب

Cisco Unified Communications Manager Dialed Number Analyzer Results

Expand All Collapse All

Results Summary

Calling Party Information

- Dialed Digits = 908026252728
- Match Result = RouteThisPattern

Matched Pattern Information

- Pattern = 9.@
- Partition = PT-LOCAL
- Time Schedule =
- Called Party Number = 908026252728
- Time Zone = Etc/GMT
- End Device = Chandra-CUCM
- Call Classification = OffNet
- InterDigit Timeout = NO
- Device Override = Disabled
- Outside Dial Tone = NO

Call Flow

Route Pattern :Pattern= 9.@

- Positional Match List = 9:0:80:26252728
- DialPlan = India Numbering Plan

Route Filter

- Filter Name = Local
- Filter Clause = (LOCAL-PREFIX-7-MOBILE EXISTS AND MOBILE-ACCESS EXISTS AND MOBILE-SUBSCRIBER EXISTS) OR (LOCAL-PREFIX-8-MOBILE EXISTS AND MOBILE-ACCESS EXISTS AND MOBILE-SUBSCRIBER EXISTS) OR (LOCAL-PREFIX-9-MOBILE EXISTS AND MOBILE-ACCESS EXISTS AND MOBILE-SUBSCRIBER EXISTS) OR (LOCAL-8-DIGIT EXISTS)

تاناخ 8 مقررلا قباطي و تاناخ 8 نم يلحم مقرر عاعدت ساب حامسلا وه كلذ عارو ب سلا
ةقطنملا زمر ءانثت ساب.

لماع يف ةقطنملا دوكرظحل حيرص لكشب ةيفصتلا لماع فيرعتب انه موقت نأ بجي اذل
يلحملا ةيفصتلا.

اي لحم امقرر 8 ل ريرحتلا ءرابعو هجوملا ةيفصتلا لماع ىلا لقتنا 1. ءوطخلا

Edit Clause **Remove Clause**

LOCAL-8-DIGIT EXISTS

ةروصلال يف حضورم وه امك، حشرملا ظفحا و دوجوم ريغ ةقطنملا زمر ددح 2. ءوطخلا

Clause Information

AREA-CODE

DOES-NOT-EXIST

يلي امك ةيفصتلا لماع ودبي:

Edit Clause	Remove Clause		
AREA-CODE	DOES-NOT-EXIST		AND
LOCAL-8-DIGIT	EXISTS		

Save	Delete	Copy	Reset	Apply Config	Add New
------	--------	------	-------	--------------	---------

نيتناخ يذ ةقطنم زمر مادختساب STD مقررل يوونلا ضمحلل اءارجاب مق 3. ةوطخلا

Cisco Unified Communications Manager Dialed Number Analyzer Results

Expand All Collapse All

- Results Summary
 - Calling Party Information
 - Dialed Digits = 908026252728
 - Match Result = BlockThisPattern
 - Route Block Cause = Unallocated Number
 - Called Party Number =
 - Matched Pattern Information
 - Pattern =
 - Partition =
 - Pattern Type =
 - Time Zone = Etc/GMT
 - Outside Dial Tone = NO
- Call Flow
 - Note: Information Not Available
- Alternate Matches
 - Note: Information Not Available

حيرص لكشب بولطملا ريغ طمنلا رطح بجي: ةطالم

ةمچرتل هذه لوج

ةللأل تاي نقتل نم ةومچم مادختساب دن تسمل اذہ Cisco تچرت
ملاعلاء انءمچي فني مدختسمل معدى وتحم مي دقتل ةيرشبل او
امك ةقيقد نوك تنل ةللأل ةمچرت لصف أن ةظحال مچري. ةصاخل مهتبل ب
Cisco يلخت. فرتحم مچرت مامدقي يتل ةيفارتحال ةمچرتل عم لالحل وه
ىل إأمئاد ةوچرلاب ي صؤت وتامچرتل هذه ةقدنع اهتيل وئسم Cisco
Systems (رفوتم طبارل) ي لصلأل يزي لچن إل دن تسمل