

# Time of Day Access for an SSID on the RV130W

## Objective

Administrators can increase security for a network by configuring Time of Day Access for a specific Service Set Identifier (SSID). An SSID is the unique identifier associated with a wireless network. Time of Day Access allows an administrator to specify when users are permitted to access the network and when users are restricted.

The objective of this document is to explain how to configure the Time of Day Access settings for an SSID on the RV130W.

## Applicable Devices

- RV130W

## Steps of Procedure

Step 1. Log in to the web configuration utility and choose **Wireless > Basic Settings**. The *Basic Settings* page opens:

The screenshot shows the 'Basic Settings' page. The 'Radio' section is checked 'Enable'. 'Wireless Network Mode' is 'B/G/N-Mixed'. 'Wireless Band Selection' is '20MHz'. 'Wireless Channel' is 'Auto'. 'AP Management VLAN' is '1'. 'U-APSD (WMM Power Save)' is checked 'Enable'.

	Enable SSID	SSID Name	SSID Broadcast	Security Mode	MAC Filter	VLAN	Wireless Isolation with SSID	WMM	Max Associated clients	WPS	Captive Portal	
											Portal Profile	Enable
<input type="checkbox"/>	<input checked="" type="checkbox"/>	SSIDName1	<input checked="" type="checkbox"/>	WPA2-Personal	Disabled	3	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	16	<input checked="" type="checkbox"/>	cisco1	<input checked="" type="checkbox"/>
<input type="checkbox"/>	<input type="checkbox"/>	ciscosb2	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	0	<input type="checkbox"/>	Please select a Profile	<input type="checkbox"/>
<input type="checkbox"/>	<input type="checkbox"/>	ciscosb3	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	0	<input type="checkbox"/>	Please select a Profile	<input type="checkbox"/>
<input type="checkbox"/>	<input type="checkbox"/>	ciscosb4	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	0	<input type="checkbox"/>	Please select a Profile	<input type="checkbox"/>

Buttons: Edit, Edit Security Mode, Edit MAC Filtering, Time of Day Access, Edit WPS, Save, Cancel.

Step 2. Check the check box of the Service Set Identifier (SSID) that you want to edit and then click the **Time of Day Access** button to configure *Time of Day Access* for an SSID.

**Basic Settings**

Radio:  Enable

Wireless Network Mode: B/G/N-Mixed

Wireless Band Selection:  20MHz  20/40MHz

Wireless Channel: Auto

AP Management VLAN: 1

U-APSD (WMM Power Save):  Enable

Wireless Table												
<input type="checkbox"/>	Enable SSID	SSID Name	SSID Broadcast	Security Mode	MAC Filter	VLAN	Wireless Isolation with SSID	WMM	Max Associated clients	WPS	Captive Portal	
											Portal Profile	Enable
<input type="checkbox"/>	<input checked="" type="checkbox"/>	SSIDName1	<input checked="" type="checkbox"/>	WPA2-Personal	Disabled	3	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	16	<input checked="" type="checkbox"/>	cisco1	<input checked="" type="checkbox"/>
<input type="checkbox"/>	<input type="checkbox"/>	ciscosb2	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	0	<input type="checkbox"/>	Please select a Profile	<input type="checkbox"/>
<input type="checkbox"/>	<input type="checkbox"/>	ciscosb3	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	0	<input type="checkbox"/>	Please select a Profile	<input type="checkbox"/>
<input type="checkbox"/>	<input type="checkbox"/>	ciscosb4	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	0	<input type="checkbox"/>	Please select a Profile	<input type="checkbox"/>

The *Time of Day Access* page opens:

**Time of Day Access**

**Add / Edit Access Point Configuration**

Active Time:  Enable

Start Time: 12 Hours 0 Minutes AM

Stop Time: 12 Hours 0 Minutes AM

Step 3. In the *Active Time* field, check the **Enable** check box to enable Time of Day Access.

**Time of Day Access**

**Add / Edit Access Point Configuration**

Active Time:  Enable

Start Time: 12 Hours 0 Minutes AM

Stop Time: 12 Hours 0 Minutes AM

Step 4. In the *Start Time* field, specify the time during the day at which the network becomes accessible to users with the provided drop-down lists.

## Time of Day Access

### Add / Edit Access Point Configuration

Active Time:  Enable

Start Time: 12 Hours 0 Minutes AM

Stop Time: 12 Hours 0 Minutes AM

Save

Cancel

Back

Step 5. In the *Stop Time* field, specify the time during the day at which the network becomes restricted to users with the provided drop-down lists.

## Time of Day Access

### Add / Edit Access Point Configuration

Active Time:  Enable

Start Time: 05 Hours 08 Minutes PM

Stop Time: 12 Hours 0 Minutes AM

Save

Cancel

Back

Step 6. Click **Save** to save your settings.

06		28		50	
07		29		51	
08		30		52	
09		31		53	
10		32		54	
11		33		55	
12		34		56	
13		35		57	
14		36		58	
15		37		59	
16		38		60	
17		39		61	
18		40		62	
19		41		63	
20		42		64	
21		43			
22		44			

Save

Cancel

Back