



Cisco Nexus 3000 Series NX-OS Release Notes, Release 6.0(2)U3(4)

Release Date: October 11, 2014
Current Release: Cisco NX-OS Release 6.0(2)U3(4)

This document describes the features, bugs, and limitations for Cisco Nexus 3000 Series and Cisco Nexus 3100 Series switches. Use this document in combination with documents listed in the “[Obtaining Documentation and Submitting a Service Request](#)” section on page 25.



Note

Release notes are sometimes updated with new information about restrictions and bugs. See the following website for the most recent version of the Cisco Nexus 3000 Series release notes: <http://www.cisco.com/c/en/us/support/switches/nexus-3000-series-switches/products-release-notes-list.html>



Note

[Table 1](#) shows the online change history for this document.

Table 1 **Online History Change**

Date	Description
October 11, 2014	Created NX-OS Release 6.0(2)U3(4) release notes.
May 11, 2015	Added Known Behaviors for this Release, page 23 .
July 15, 2015	Moved CSCun87600 to “ Resolved Bugs in this Release ”
November 2, 2015	Added the following footnote: GLC-SX-MMD is supported on all Cisco Nexus 3000 Series Switches except for the Cisco Nexus 3064-T. Please refer to the comparability matrix for all the supported platforms.



Contents

This document includes the following sections:

- [Introduction, page 2](#)
- [System Requirements, page 3](#)
- [New and Changed Features, page 19](#)
- [Upgrade and Downgrade Guidelines, page 20](#)
- [Limitations, page 20](#)
- [Caveats, page 22](#)
- [Obtaining Documentation and Submitting a Service Request, page 25](#)

Introduction

Several new hardware and software features are introduced for the Cisco Nexus 3000 Series and Cisco Nexus 3100 Series devices to improve the performance, scalability, and management of the product line. Cisco NX-OS Release 6.x also supports all hardware and software supported in Cisco NX-OS Release 5.1 and Cisco NX-OS Release 5.0.

Cisco NX-OS offers the following benefits:

- Cisco NX-OS runs on all Cisco data center switch platforms: Cisco Nexus 7000, Nexus 5000, Nexus 4000, Nexus 3000, Nexus 2000, and Nexus 1000V Series switches.
- Cisco NX-OS software interoperates with Cisco products that run any variant of Cisco IOS software and also with any networking operating system that conforms to common networking standards.
- Cisco NX-OS modular processes are triggered on demand, each in a separate protected memory space. Processes are started and system resources are allocated only when a feature is enabled. The modular processes are governed by a real-time preemptive scheduler that helps ensure timely processing of critical functions.
- Cisco NX-OS provides a programmatic XML interface that is based on the NETCONF industry standard. The Cisco NX-OS XML interface provides a consistent API for devices. Cisco NX-OS also provides support for Simple Network Management Protocol (SNMP) Versions 1, 2, and 3 MIBs.
- Cisco NX-OS enables administrators to limit access to switch operations by assigning roles to users. Administrators can customize access and restrict it to the users who require it.

Cisco Nexus 3000 Series Switches

The Cisco Nexus 3000 Series switches are high-performance, high-density, ultra-low-latency Ethernet switches that provide line-rate Layer 2 and Layer 3 switching. The Cisco Nexus 3000 Series includes the following switches:

- The Cisco Nexus 3064 switch is a 1 RU switch that supports 48 1- or 10-Gigabit downlink ports, four Quad Small Form-Factor Pluggable (QSFP+) ports that can be used as a 40 Gigabit Ethernet port or 4 x10-Gigabit Ethernet ports, one 10/100/1000 management port, and one console port.
- The Cisco Nexus 3048 switch is a 1 rack unit (RU) switch that supports 48 10/100/1000 Ethernet server-facing (downlink) ports, four 10-Gigabit network-facing (uplink) ports, one 100/1000 management port, and one console port.

- The Cisco Nexus 3016 is a 1 RU, 16-port QSFP+ switch. Each QSFP+ port can be used as a 40-Gigabit Ethernet port or 4 x 10-Gigabit Ethernet ports.

Each switch includes one or two power supply units and one fan tray module, and each switch can be ordered with either forward (port-side exhaust) airflow or reverse (port-side intake) airflow for cooling. All platforms support both AC and DC power supplies. All combinations of power (AC/DC) and airflow (forward/reverse) are available. The Cisco Nexus 3000 Series switches run the Cisco NX-OS software.

For information about the Cisco Nexus 3000 Series, see the [Cisco Nexus 3000 Series Hardware Installation Guide](#).

Cisco Nexus 3100 Series Switches

The Cisco Nexus 3100 Series switches are high-performance, high-density, ultra-low-latency Ethernet switches that provide line-rate Layer 2 and Layer 3 switching. In Cisco NX-OS Release 6.0(2)U2(2), the Cisco Nexus 3100 Series includes the Cisco Nexus 3132 and Nexus 3172 switches.

The Cisco Nexus 3172PQ switch is a 10-Gbps Enhanced Small Form-Factor Pluggable (SFP+)–based ToR switch with 48 SFP+ ports and 6 Enhanced Quad SFP+ (QSFP+) ports.

The Cisco Nexus 3172TQ switch is a 10GBASE-T switch with 48 10GBASE-T ports and 6 Quad SFP+ (QSFP+) ports.

Each SFP+ port can operate in 100-Mbps, 1-Gbps, or 10-Gbps mode, and each QSFP+ port can operate in native 40-Gbps or 4 x 10-Gbps mode. This switch is a true physical-layer-free (phy-less) switch that is optimized for low latency and low power consumption.

The Cisco Nexus 3132 switch is a 1RU, 40-Gbps QSFP-based switch that supports 32 fixed 40-Gbps QSFP+ ports. It also has 4 SFP+ ports that can be internally multiplexed with the first QSFP port. Each QSFP+ port can operate in the default 40-Gbps mode or 4 x 10-Gbps mode, up to a maximum of 104 10-Gbps ports.

Each switch includes dual redundant power supply units, four redundant fans, one 10/100/1000 management port, and one console port. Each switch can be ordered with either forward (port-side exhaust) airflow or reverse (port-side intake) airflow for cooling. It supports both AC and DC power supplies. All combinations of power (AC/DC) and airflow (forward/reverse) are available. The Cisco Nexus 3100 Series switches run the Cisco NX-OS software.

For information about the Cisco Nexus 3100 Series, see the [Cisco Nexus 3000 Series Hardware Installation Guide](#).

System Requirements

This section includes the following topics:

- [Memory Requirements, page 3](#)
- [Hardware Supported, page 4](#)
- [Twinax Cable Support on Cisco Nexus 3000 Switches, page 18](#)
- [Cisco QSFP 40-Gbps Bidirectional Short-Reach Transceiver, page 19](#)

Memory Requirements

The Cisco NX-OS Release 6.0(2)U3(4) software requires 135 MB of flash memory.

Hardware Supported

Cisco NX-OS Release 6.0(2)U3(4) supports the Cisco Nexus 3000 Series switches. You can find detailed information about supported hardware in the *Cisco Nexus 3000 Series Hardware Installation Guide*.

[Table 2](#) shows the hardware supported by the Cisco NX-OS Release 6.x software. [Table 3](#) shows the hardware supported by the Cisco NX-OS 5.x releases.

[Table 4](#) shows the transceivers supported by the Cisco NX-OS Release 6.x software. [Table 5](#) shows transceivers supported by the Cisco NX-OS 5.x releases.

Table 2 Hardware Supported by Cisco NX-OS Release 6.x Software

Hardware	Part Number	Supported Cisco NX-OS Release	Supported Cisco NX-OS Release	Supported Cisco NX-OS Release
		6.0(2)U1(3) 6.0(2)U1(2) 6.0(2)U1(1a) 6.0(2)U1(1)	6.0(2)U2(6) 6.0(2)U2(5) 6.0(2)U2(4) 6.0(2)U2(3) 6.0(2)U2(2) 6.0(2)U2(1)	6.0(2)U3(4) 6.0(2)U3(3) 6.0(2)U3(2) 6.0(2)U3(1)
Cisco Nexus 3172TQ switch	N3K-C3172TQ-10GT			X
Cisco Nexus 3172PQ switch	N3K-C3172PQ-10GE		X	X
Cisco Nexus 3132Q switch	N3K-C3132Q-40GE		X	X
Cisco Nexus 3016 switch	N3K-C3016Q-40GE	X	X	X
Cisco Nexus 3048 switch	N3K-C3048TP-1GE	X	X	X
Cisco Nexus 3064-TQ switch	N3K-C3064TQ-10GT	X	X	X
Cisco Nexus 3064-X switch	N3K-C3064PQ-10GX	X	X	X
Cisco Nexus 3064-E switch	N3K-C3064PQ-10GE	X	X	X
Cisco Nexus 3064 switch	N3K-C3064PQ	X	X	X
Cisco Nexus 3048 fan module with forward airflow (port-side exhaust)	N3K-C3048-FAN	X	X	X
Cisco Nexus 3048 fan module with reverse airflow (port-side intake)	N3K-C3048-FAN-B	X	X	X
Cisco Nexus 3064-T 500W forward airflow (port-side exhaust) AC power supply	NXA-PAC-500W	X	X	X
Cisco Nexus 3064-T 500W reverse airflow (port-side intake) AC power supply	NXA-PAC-500W-B	X	X	X
Cisco Nexus 3064-X forward airflow (port-side exhaust) AC power supply	N3K-C3064-X-FA-L3	X	X	X
Cisco Nexus 3064-X reversed airflow (port-side intake) AC power supply	N3K-C3064-X-BA-L3	X	X	X

Hardware	Part Number	Supported Cisco NX-OS Release	Supported Cisco NX-OS Release	Supported Cisco NX-OS Release
		6.0(2)U1(3) 6.0(2)U1(2) 6.0(2)U1(1a) 6.0(2)U1(1)	6.0(2)U2(6) 6.0(2)U2(5) 6.0(2)U2(4) 6.0(2)U2(3) 6.0(2)U2(2) 6.0(2)U2(1)	6.0(2)U3(4) 6.0(2)U3(3) 6.0(2)U3(2) 6.0(2)U3(1)
Cisco Nexus 3064-X forward airflow (port-side exhaust) DC power supply	N3K-C3064-X-FD-L3	X	X	X
Cisco Nexus 3064-X forward airflow (port-side intake) DC power supply	N3K-C3064-X-BD-L3	X	X	X
Cisco Nexus 3064 fan module with forward airflow (port-side exhaust); also used in the Cisco Nexus 3016	N3K-C3064-FAN	X	X	X
Cisco Nexus 3064 fan module with reverse airflow (port-side intake); also used in the Cisco Nexus 3016	N3K-C3064-FAN-B	X	X	X
Cisco Nexus 3000 power supply with forward airflow (port-side exhaust)	N2200-PAC-400W	X	X	X
Cisco Nexus 3000 power supply with reverse airflow (port-side intake)	N2200-PAC-400W-B	X	X	X
Cisco Nexus 2000 power supply with forward airflow (port-side exhaust)	N2200-PDC-400W	X	X	X
Cisco Nexus 2000 DC power supply with reverse airflow (port-side intake)	N3K-PDC-350W-B	X	X	X

Table 3 Hardware Supported by Cisco NX-OS Release 5.x Software

Hardware	Part Number	Supported Cisco NX-OS Release						
		5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1)	5.0(3)U4(1)	5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1)	5.0(3)U2(2d) 5.0(3)U2(2c) 5.0(3)U2(2b)	5.0(3)U2(2a)	5.0(3)U2(2) 5.0(3)U2(1) 5.0(3)U1(2a) 5.0(3)U1(2)	5.0(3)U1(1d)
Cisco Nexus 3016 switch	N3K-C3016Q-40GE	X	X	X	X	X	—	—
Cisco Nexus 3048 switch	N3K-C3048TP-1GE	X	X	X	X	—	—	—
Cisco Nexus 3064-TQ switch	N3K-C3064TQ-10GT	X ¹	—	—	—	—	—	—

Table 3 Hardware Supported by Cisco NX-OS Release 5.x Software (continued)

Hardware	Part Number	Supported Cisco NX-OS Release						
		5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1)	5.0(3)U4(1)	5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1)	5.0(3)U2(2d) 5.0(3)U2(2c) 5.0(3)U2(2b)	5.0(3)U2(2a)	5.0(3)U2(2) 5.0(3)U2(1) 5.0(3)U1(2a) 5.0(3)U1(2)	5.0(3)U1(1d)
Cisco Nexus 3064-X switch	N3K-C3064P10GX	X	X	X	—	—	—	—
Cisco Nexus 3064-E switch	N3K-C3064PQ-10GE	X	X	X	X	X	X	—
Cisco Nexus 3064 switch	N3K-C3064PQ	X	X	X	X	X	X	X
Cisco Nexus 3048 fan module with forward airflow (port-side exhaust)	N3K-C3048-FAN	X	X	X	X	—	—	—
Cisco Nexus 3048 fan module with reverse airflow (port-side intake)	N3K-C3048-FAN-B	X	X	X	X	—	—	—
Nexus 3064-T 500W forward airflow (port side exhaust) AC power supply	NXA-PAC-500W	X	X	—	—	—	—	—
Nexus 3064-T 500W reverse airflow (port side intake) AC power supply	NXA-PAC-500W-B	X	X	—	—	—	—	—

Table 3 Hardware Supported by Cisco NX-OS Release 5.x Software (continued)

Hardware	Part Number	Supported Cisco NX-OS Release						
		5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1)	5.0(3)U4(1)	5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1)	5.0(3)U2(2d) 5.0(3)U2(2c) 5.0(3)U2(2b)	5.0(3)U2(2a)	5.0(3)U2(2) 5.0(3)U2(1) 5.0(3)U1(2a) 5.0(3)U1(2)	5.0(3)U1(1d)
Cisco Nexus 3064-X forward airflow (port-side exhaust) AC power supply	N3K-C3064-X-FA-L3	X	X	X	—	—	—	—
Cisco Nexus 3064-X reversed airflow (port-side intake) AC power supply	N3K-C3064-X-BA-L3	X	X	X	—	—	—	—
Cisco Nexus 3064-X forward airflow (port-side exhaust) DC power supply	N3K-C3064-X-FD-L3	X	X	X	—	—	—	—
Cisco Nexus 3064-X forward airflow (port-side intake) DC power supply	N3K-C3064-X-BD-L3	X	X	X	—	—	—	—

Table 3 Hardware Supported by Cisco NX-OS Release 5.x Software (continued)

Hardware	Part Number	Supported Cisco NX-OS Release						
		5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1)	5.0(3)U4(1)	5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1)	5.0(3)U2(2d) 5.0(3)U2(2c) 5.0(3)U2(2b)	5.0(3)U2(2a)	5.0(3)U2(2) 5.0(3)U2(1) 5.0(3)U1(2a) 5.0(3)U1(2)	5.0(3)U1(1d)
Cisco Nexus 3064 fan module with forward airflow (port-side exhaust); also used in the Cisco Nexus 3016	N3K-C3064-FAN	X	X	X	X	X	X	X
Cisco Nexus 3064 fan module with reverse airflow (port-side intake); also used in the Cisco Nexus 3016	N3K-C3064-FAN-B	X	X	X	X	X	X	X
Cisco Nexus 3000 power supply with forward airflow (port-side exhaust)	N2200-PAC-400W	X	X	X	X	X	X	X
Cisco Nexus 3000 power supply with reverse airflow (port-side intake)	N2200-PAC-400W-B	X	X	X	X	X	X	X

Table 3 Hardware Supported by Cisco NX-OS Release 5.x Software (continued)

Hardware	Part Number	Supported Cisco NX-OS Release						
		5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1)	5.0(3)U4(1)	5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1)	5.0(3)U2(2d) 5.0(3)U2(2c) 5.0(3)U2(2b)	5.0(3)U2(2a)	5.0(3)U2(2) 5.0(3)U2(1) 5.0(3)U1(2a) 5.0(3)U1(2)	5.0(3)U1(1d)
Cisco Nexus 2000 power supply with forward airflow (port-side exhaust)	N2200-PDC-400W	X	X	X	X	X	X	X
Cisco Nexus 2000 DC power supply with reverse airflow (port-side intake)	N3K-PDC-350W-B	X	X	X	X	X	X	X

1. Recommended release for Cisco Nexus 3064-TQ switch is Cisco NX-OS Release 5.0(3)U5(1c) or later releases.

Table 4 Transceivers Supported by Cisco NX-OS Release 6.x Software

Transceivers ¹	Part Number	Supported Cisco NX-OS Release		
		6.0(2)U1(3) 6.0(2)U1(2) 6.0(2)U1(1a) 6.0(2)U1(1)	6.0(2)U2(5) 6.0(2)U2(4) 6.0(2)U2(3) 6.0(2)U2(2) 6.0(2)U2(1)	6.0(2)U3(4) 6.0(2)U3(3) 6.0(2)U3(2) 6.0(2)U3(1)
QSFP				
40GBASE-LR4 QSFP40G transceiver module (SMF)	QSFP-40G-LR4			X
40GBASE-CR4 QSFP+ direct-attach copper cable, 7 meters active	QSFP-H40G-ACU7M			X
40GBASE-CR4 QSFP+ direct-attach copper cable, 8 meters active	QSFP-H40G-ACU8M			X

Table 4 Transceivers Supported by Cisco NX-OS Release 6.x Software (continued)

Transceivers ¹	Part Number	Supported Cisco NX-OS Release		
		6.0(2)U1(3) 6.0(2)U1(2) 6.0(2)U1(1a) 6.0(2)U1(1)	6.0(2)U2(5) 6.0(2)U2(4) 6.0(2)U2(3) 6.0(2)U2(2) 6.0(2)U2(1)	6.0(2)U3(4) 6.0(2)U3(3) 6.0(2)U3(2) 6.0(2)U3(1)
40GBASE-CR4 QSFP+ direct-attach copper cable, 9 meters active	QSFP-H40G-ACU9M			X
40GBASE-CR4 QSFP+ direct-attach copper cable, 10 m active	QSFP-H40G-ACU10M			X
40G QSFP direct-attach Active Optical cable, 15 m	QSFP-H40G-AOC15M			X
QSFP to 4 x SFP 10Gbps active optical cable 15 m	QSFP-4X10G-AOC15M			X
QSFP 40G Bidirectional short-reach transceiver	QSFP-40G-SR-BD	X	X	X
QSFP 40G active optical cable 1 m	QSFP-H40G-AOC1M	X	X	X
QSFP 40G active optical cable 2 m	QSFP-H40G-AOC2M	X	X	X
QSFP 40G active optical cable 3 m	QSFP-H40G-AOC3M	X	X	X
QSFP 40G active optical cable 5 m	QSFP-H40G-AOC5M	X	X	X
QSFP 40G active optical cable 7 m	QSFP-H40G-AOC7M	X	X	X
QSFP 40G active optical cable 10 m	QSFP-H40G-AOC10M	X	X	X
QSFP to 4 x SFP 10Gbps active optical cable 1 m	QSFP-4X10G-AOC1M	X	X	X
QSFP to 4 x SFP 10Gbps active optical cable 2 m	QSFP-4X10G-AOC2M	X	X	X
QSFP to 4 x SFP 10Gbps active optical cable 3 m	QSFP-4X10G-AOC3M	X	X	X
QSFP to 4 x SFP 10Gbps active optical cable 5 m	QSFP-4X10G-AOC5M	X	X	X
QSFP to 4 x SFP 10Gbps active optical cable 7 m	QSFP-4X10G-AOC7M	X	X	X
QSFP to 4 x SFP 10Gbps active optical cable 10 m	QSFP-4X10G-AOC10M	X	X	X
Active copper splitter cable 7 m	QSFP-4x10G-AC7M ²	X	X	X
Active copper splitter cable 10 m	QSFP-4x10G-AC10M ¹	X	X	X
Active copper QSFP transceiver module 7 m	QSFP-H40G-ACU7M ¹	X	X	X
Active copper QSFP transceiver module 10 m	QSFP-H40G-ACU10M ¹	X	X	X

Table 4 Transceivers Supported by Cisco NX-OS Release 6.x Software (continued)

Transceivers ¹	Part Number	Supported Cisco NX-OS Release		
		6.0(2)U1(3) 6.0(2)U1(2) 6.0(2)U1(1a) 6.0(2)U1(1)	6.0(2)U2(5) 6.0(2)U2(4) 6.0(2)U2(3) 6.0(2)U2(2) 6.0(2)U2(1)	6.0(2)U3(4) 6.0(2)U3(3) 6.0(2)U3(2) 6.0(2)U3(1)
40GBASE-CSR4 QSFP transceiver module with multifiber push-on (MPO) connector 300 m	QSFP-40G-CSR4 ¹	X	X	X
40GBASE-CSR4 QSFP transceiver module with MPO connector 300 m (using fiber splitter cables)	QSFP-40G-CSR4 ¹	X	X	X
40GBASE-SR4 QSFP transceiver module with MPO connector 100 m	QSFP-40G-SR4 ¹	X	X	X
40GBASE-SR4 QSFP transceiver module with MPO connector 100 m (using fiber splitter cables)	QSFP-40G-SR4 ¹	X	X	X
40GBASE-LR4 QSFP transceiver module with LC connector 10 km (using single mode fiber)	QSFP-40GE-LR4	X	X	X
QSFP to SFP/SFP+ adapter	CVR-QSFP-SFP10G	X	X	X
40GBASE-CR4 passive copper cable, 1 m	QSFP-H40G-CU1M	X	X	X
40GBASE-CR4 passive copper cable, 3 m	QSFP-H40G-CU3M	X	X	X
40GBASE-CR4 passive copper cable, 5 m	QSFP-H40G-CU5M	X	X	X
QSFP to 4xSFP10G passive copper splitter cable, 1 m	QSFP-4SFP10G-CU1M	X	X	X
QSFP to 4xSFP10G passive copper splitter cable, 3 m	QSFP-4SFP10G-CU3M	X	X	X
QSFP to 4xSFP10G passive copper splitter cable, 5 m	QSFP-4SFP10G-CU5M	X	X	X
Revision 2 copper splitter cables 3 m	QSFP-4SFP10G-CU3 (Rev. 2)	X	X	X
Revision 2 copper splitter cables 5 m	QSFP-4SFP10G-CU5 (Rev. 2)	X	X	X
10-Gigabit				
10 db attenuator	FA-920-073-12310			X
10GBASE-ZR SFP+ module (single-mode fiber [SMF])	SFP-10G-ZR			X
Cisco QSFP to SFP/SFP+ Adapter (QSA) module	CVR-QSFP-SFP10G			X

Table 4 Transceivers Supported by Cisco NX-OS Release 6.x Software (continued)

Transceivers ¹	Part Number	Supported Cisco NX-OS Release		
		6.0(2)U1(3) 6.0(2)U1(2) 6.0(2)U1(1a) 6.0(2)U1(1)	6.0(2)U2(5) 6.0(2)U2(4) 6.0(2)U2(3) 6.0(2)U2(2) 6.0(2)U2(1)	6.0(2)U3(4) 6.0(2)U3(3) 6.0(2)U3(2) 6.0(2)U3(1)
Cisco QSFP to SFP/SFP+ Adapter (QSA) module with 10GBASE-DWDM	QSA w/ DWDM			X
10GBASE-DWDM 1558.98 nm SFP+ (100-GHz ITU grid)	DWDM-SFP10G-58.98			X
10GBASE-DWDM 1539.77 nm SFP+ (100-GHz ITU grid)	DWDM-SFP10G-39.77			X
10GBASE-DWDM 1561.41 nm SFP+ (100-GHz ITU grid)	DWDM-SFP10G-61.41			X
10GBASE-DWDM 1542.94 nm SFP+ (100-GHz ITU grid)	DWDM-SFP10G-42.94			X
10GBASE-DWDM 1553.33 nm SFP+ (100-GHz ITU grid)	DWDM-SFP10G-53.33			X
10GBASE-DWDM 1537.40 nm SFP+ (100-GHz ITU grid)	DWDM-SFP10G-37.40			X
10GBASE-DWDM 1542.14 nm SFP+ (100-GHz ITU grid)	DWDM-SFP10G-42.14			X
10GBASE-DWDM 1556.55 nm SFP+ (100-GHz ITU grid)	DWDM-SFP10G-56.55			X
10GBASE-DWDM 1550.92 nm SFP+ (100-GHz ITU grid)	DWDM-SFP10G-50.92			X
10GBASE-DWDM 1531.12 nm SFP+ (100-GHz ITU grid)	DWDM-SFP10G-31.12			X
10GBASE-DWDM long-range transceiver module 80 km with single mode duplex fiber	DWDM-SFP10G-C			X
10GBASE-DWDM long-range transceiver module 80 km with single mode duplex fiber	DWDM-SFP10G	X	X	X
10GBASE-SR SFP+ module (multimode fiber [MMF])	SFP-10G-SR	X	X	X
10GBASE-LR SFP+ module (single-mode fiber [SMF])	SFP-10G-LR	X	X	X
10GBASE-ER SFP+ module (single-mode fiber [SMF])	SFP-10G-ER	X	X	X
10GBASE-ZR SFP+ module (single-mode fiber [SMF]) ³	SFP-10G-ZR ²	X	X	X
10GBASE-DWDM SFP+ module (single-mode fiber [SMF]) ²	10-2767-01 ²	X	X	X

Table 4 Transceivers Supported by Cisco NX-OS Release 6.x Software (continued)

Transceivers ¹	Part Number	Supported Cisco NX-OS Release		
		6.0(2)U1(3) 6.0(2)U1(2) 6.0(2)U1(1a) 6.0(2)U1(1)	6.0(2)U2(5) 6.0(2)U2(4) 6.0(2)U2(3) 6.0(2)U2(2) 6.0(2)U2(1)	6.0(2)U3(4) 6.0(2)U3(3) 6.0(2)U3(2) 6.0(2)U3(1)
Active Twinax cable assembly, 7 m	SFP-H10GB-ACU7M	X	X	X
Active Twinax cable assembly, 10 m	SFP-H10GB-ACU10M	X	X	X
10GBASE-CU SFP+ cable 1 m (Twinax cable)	SFP-H10GB-CU1M	X	X	X
10GBASE-CU SFP+ cable 1.5 m (Twinax cable)	SFP-H10GB-CU1-5M	X	X	X
10GBASE-CU SFP+ cable 2 m (Twinax cable) ³	SFP-H10GB-CU2M ⁴	X	X	X
10GBASE-CU SFP+ cable 3 m (Twinax cable)	SFP-H10GB-CU3M	X	X	X
10GBASE-CU SFP+ cable 5 m (Twinax cable)	SFP-H10GB-CU5M	X	X	X
10GBASE-CU SFP+ cable 2.5 m (Twinax cable) ³	SFP-H10GB-CU2-5M ³	X	X	X
Active optical cable 1 m	SFP-10G-AOC1M ⁴	X	X	X
Active optical cable 2 m	SFP-10G-AOC2M	X	X	X
Active optical cable 3 m	SFP-10G-AOC3M ⁴	X	X	X
Active optical cable 5 m	SFP-10G-AOC5M ⁴	X	X	X
Active optical cable 7 m	SFP-10G-AOC7M ⁴	X	X	X
Active optical cable 10 m	SFP-10G-AOC10M	X	X	X
1-Gigabit Ethernet				
Gigabit Ethernet SFP, LC connector SX transceiver (MMF)	GLC-SX-MMD ⁵			X
Gigabit Ethernet SFP, LC connector LX/LH transceiver (SMF)	GLC-LH-SMD			X
Cisco QSFP to SFP/SFP+ Adapter (QSA) module with GLC-T	QSA w/ GLC-T			X
1000BASE-T SFP	GLC-TE			X
Cisco QSFP to SFP/SFP+ Adapter (QSA) module with GLC-TE	QSA w/ GLC-TE			X
Cisco QSFP to SFP/SFP+ Adapter (QSA) module with SFP-GE-T	QSA w/SFP-GE-T			X
1000Base-BX fiber transceiver	GLC-BX-D ⁴	X	X	X
1000Base-BX fiber transceiver	GLC-BX-U ⁴	X	X	X

Table 4 Transceivers Supported by Cisco NX-OS Release 6.x Software (continued)

Transceivers ¹	Part Number	Supported Cisco NX-OS Release		
		6.0(2)U1(3) 6.0(2)U1(2) 6.0(2)U1(1a) 6.0(2)U1(1)	6.0(2)U2(5) 6.0(2)U2(4) 6.0(2)U2(3) 6.0(2)U2(2) 6.0(2)U2(1)	6.0(2)U3(4) 6.0(2)U3(3) 6.0(2)U3(2) 6.0(2)U3(1)
1000BASE-EX fiber transceiver module, SMF	GLC-EX-SMD	X	X	X
Gigabit Ethernet SFP, LC connector LX/LH transceiver (SMF)	GLC-LH-SM ⁴	X	X	X
1000BASE-LX/LH SFP transceiver module for MMF and SMF	GLC-LH-SMD ⁴	X	X	X
Gigabit Ethernet SFP, LC connector SX transceiver (MMF)	GLC-SX-MM ³	X	X	X
Gigabit Ethernet SFP, LC connector SX transceiver (MMF)	GLC-SX-MMD ⁵	X	X	X
1000BASE-T SFP ⁶	GLC-T ⁴	X	X	X
1000BASE-ZX fiber transceiver module, SMF, 1550 nm	GLC-ZX-SMD	X	X	X
1000BASE-T SFP transceiver module with extended operating temperature range	SFP-GE-T ⁴	X	X	X
100-Mbps Ethernet				
100BASE-FX SFP module for Gigabit Ethernet ports GLC-GE-100FX ⁷	10-2019-02 ⁵ GLC-GE-100FX	X	X	X

- OIR is supported for all optical modules and transceivers in Cisco NX-OS Release 6.02 and later releases.
- Supported on the Cisco Nexus 3016, Cisco Nexus 3064-X, Cisco Nexus 3064-TQ, Cisco Nexus 3064, and Cisco Nexus 3064-E switches.
- Supported on the Cisco Nexus 3064-E and Cisco Nexus 3064-X switches.
- Supported on the Cisco Nexus 3048, Cisco Nexus 3064-X, Cisco Nexus 3064, and Cisco Nexus 3064-E switches.
- GLC-SX-MMD is supported on all Cisco Nexus 3000 Series Switches except for the Cisco Nexus 3064-T. Please refer to the comparability matrix for all the supported platforms.
- Supported on the Cisco Nexus 3048, Cisco Nexus 3064-E, and Cisco Nexus 3064-X switches.
- Supported on the Cisco Nexus 3064, Cisco Nexus 3064-E, and Cisco Nexus 3064-X switches. For the GLC-GE-100FX, only part number 10-2019-02 is supported.



Note The Cisco Nexus 3000 supports 1,000 and 10,000 speeds while using SFP+ with Cisco QSA [CVR-QSFP-SFP10G] (and a maximum of 6 QSAs). The 100 speed is not supported on the SFP+ along with QSA, but using any speed 100 is supported on the SFP+.

Table 5 Transceivers Supported by Cisco NX-OS Release 5.x Software

Transceivers	Part Number	Supported Cisco NX-OS Release						
		5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1)	5.0(3)U4(1)	5.0(3)U3(1)	5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2)	5.0(3)U2(2c) 5.0(3)U2(2b) 5.0(3)U2(2a) 5.0(3)U2(2)	5.0(3) U2(1)	5.0(3)U1(2) 5.0(3)U1(2a)
QSFP								
Active copper splitter cable 7 m	QSFP-4x10G-AC7M ¹	X	—	—	—	—	—	—
Active copper splitter cable 10 m	QSFP-4x10G-AC10M ¹	X	—	—	—	—	—	—
Active copper QSFP transceiver module 7 m	QSFP-H40G-ACU7M ¹	X	—	—	—	—	—	—
Active copper QSFP transceiver module 10 m	QSFP-H40G-ACU10M ¹	X	—	—	—	—	—	—
40GBASE-CSR4 QSFP transceiver module with MPO connector 300 m	QSFP-40G-CSR4 ¹	X	X	—	—	—	—	—
40GBASE-CSR4 QSFP transceiver module with MPO connector 300 m (using fiber splitter cables)	QSFP-40G-CSR4 ¹	X	X	—	—	—	—	—
40GBASE-SR4 QSFP transceiver module with MPO connector 100 m	QSFP-40G-SR4 ¹	X	X	X	X	X	X	X
40GBASE-SR4 QSFP transceiver module with MPO connector 100 m (using fiber splitter cables)	QSFP-40G-SR4 ¹	X	X	X	X	X	X	X
40GBASE-CR4 passive copper cable, 1 m	QSFP-H40G-CU1M	X	X	X	X	X	X	X
40GBASE-CR4 passive copper cable, 3 m	QSFP-H40G-CU3M	X	X	X	X	X	X	X

Table 5 Transceivers Supported by Cisco NX-OS Release 5.x Software (continued)

Transceivers	Part Number	Supported Cisco NX-OS Release							
		5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1)	5.0(3)U4(1)	5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1)	5.0(3)U2(2c) 5.0(3)U2(2b) 5.0(3)U2(2a) 5.0(3)U2(2)	5.0(3) U2(1)	5.0(3)U1(2) 5.0(3)U1(2a)	5.0(3)U1(1a) 5.0(3)U1(1b) 5.0(3)U1(1d)	
40GBASE-CR4 passive copper cable, 5 m	QSFP-H40G-CU5M	X	X	X	X	X	X	X	
QSFP to 4xSFP10G passive copper splitter cable, 1 m	QSFP-4SFP10G-CU1M	X	X	X	X	X	X	X	
QSFP to 4xSFP10G passive copper splitter cable, 3 m	QSFP-4SFP10G-CU3M	X	X	X	X	X	X	X	
QSFP to 4xSFP10G passive copper splitter cable, 5 m	QSFP-4SFP10G-CU5M	X	X	X	X	X	X	X	
Revision 2 copper splitter cables 3 m	QSFP-4SFP10G-CU3 (Rev. 2)	X	—	—	—	—	—	—	
Revision 2 copper splitter cables 5 m	QSFP-4SFP10G-CU5 (Rev. 2)	X	—	—	—	—	—	—	
10-Gigabit									
10GBASE-SR SFP+ module (multimode fiber [MMF])	SFP-10G-SR	X	X	X	X	X	X	X	
10GBASE-LR SFP+ module (single-mode fiber [SMF])	SFP-10G-LR	X	X	X	X	X	X	X	
10GBASE-ER SFP+ module (single-mode fiber [SMF])	SFP-10G-ER	X	X	X	X	X	X	X	
10GBASE-ZR SFP+ module (single-mode fiber [SMF]) ²	SFP-10G-ZR ²	X	X	X	—	—	—	—	

Table 5 Transceivers Supported by Cisco NX-OS Release 5.x Software (continued)

Transceivers	Part Number	Supported Cisco NX-OS Release						
		5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1)	5.0(3)U4(1)	5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1)	5.0(3)U2(2c) 5.0(3)U2(2b) 5.0(3)U2(2a) 5.0(3)U2(2)	5.0(3)U2(1)	5.0(3)U1(2) 5.0(3)U1(2a)	5.0(3)U1(1a) 5.0(3)U1(1b) 5.0(3)U1(1d)
10GBASE-DWDM SFP+ module (single-mode fiber [SMF]) ²	10-2767-01 ²	X	X	X	—	—	—	—
10GBASE-CU SFP+ cable 1 m (Twinax cable)	SFP-H10GB-CU1M	X	X	X	X	X	X	X
10GBASE-CU SFP+ cable 3 m (Twinax cable)	SFP-H10GB-CU3M	X	X	X	X	X	X	X
10GBASE-CU SFP+ cable 5 m (Twinax cable)	SFP-H10GB-CU5M	X	X	X	X	X	X	X
10GBASE-CU SFP+ cable 2 m (Twinax cable) ³	SFP-H10GB-CU2M ³	X	X	—	—	—	—	—
10GBASE-CU SFP+ cable 2.5 m (Twinax cable) ³	SFP-H10GB-CU2-5M ³	X	X	—	—	—	—	—
Active optical cable 1 m	SFP-10G-AOC1M ⁴	X	—	—	—	—	—	—
Active optical cable 3 m	SFP-10G-AOC3M ⁴	X	—	—	—	—	—	—
Active optical cable 5 m	SFP-10G-AOC5M ⁴	X	—	—	—	—	—	—
Active optical cable 7 m	SFP-10G-AOC7M ⁴	X	—	—	—	—	—	—
1-Gigabit Ethernet								
1000BASE-T SFP ⁴	GLC-T ⁴	X	X	X	X	X	X	X
Gigabit Ethernet SFP, LC connector SX transceiver (MMF)	GLC-SX-MM ³	X	X	X	X	X	X	X

Table 5 Transceivers Supported by Cisco NX-OS Release 5.x Software (continued)

Transceivers	Part Number	Supported Cisco NX-OS Release						
		5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1)	5.0(3)U4(1)	5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1)	5.0(3)U2(2c) 5.0(3)U2(2b) 5.0(3)U2(2a) 5.0(3)U2(2)	5.0(3) U2(1)	5.0(3)U1(2) 5.0(3)U1(2a)	5.0(3)U1(1a) 5.0(3)U1(1b) 5.0(3)U1(1d)
Gigabit Ethernet SFP, LC connector SX transceiver (MMF)	GLC-SX-MMD ⁵	X	X	—	—	—	—	—
Gigabit Ethernet SFP, LC connector LX/LH transceiver (SMF)	GLC-LH-SM ⁴	X	X	X	X	X	X	X
1000BASE-LX/LH SFP transceiver module for MMF and SMF	GLC-LH-SMD ⁴	X	—	—	—	—	—	—
1000Base-BX fiber transceiver	GLC-BX-U ⁴	X	—	—	—	—	—	—
1000Base-BX fiber transceiver	GLC-BX-D ⁴	X	—	—	—	—	—	—
1000BASE-T SFP transceiver module with extended operating temperature range	SFP-GE-T ⁴	X	—	—	—	—	—	—
100-Mbps Ethernet								
100BASE-FX SFP module for Gigabit Ethernet ports GLC-GE-100FX ⁵	10-2019-02 ⁵ GLC-GE-100FX	X	X	X	X	X	X	X

1. Supported on the Cisco Nexus 3016, Cisco Nexus 3064-X, Cisco Nexus 3064-TQ, Cisco Nexus 3064, and Cisco Nexus 3064-E switches.
2. Supported on the Cisco Nexus 3064-E and Cisco Nexus 3064-X switches.
3. Supported on the Cisco Nexus 3048, Cisco Nexus 3064-X, Cisco Nexus 3064, and Cisco Nexus 3064-E switches.
4. Supported on the Cisco Nexus 3048, Cisco Nexus 3064-E, and Cisco Nexus 3064-X switches.
5. Supported on the Cisco Nexus 3064, Cisco Nexus 3064-E, and Cisco Nexus 3064-X switches. For the GLC-GE-100FX, only part number 10-2019-02 is supported.

Twinax Cable Support on Cisco Nexus 3000 Switches

Starting with Cisco Release NX-OS 5.0(3)U1(1), the following algorithm is used to detect copper SFP+ twinax, QSFP+ twinax, and QSFP+ splitter cables on Cisco Nexus 3000 Series switches.

If the attached interconnect (transceiver) is a copper SFP+ twinax or QSFP+ twinax cable:

- Verify the transceiver SPROM to match the Cisco magic code.
- If the check succeeds, bring up the interface. Otherwise, print the following warning message appears stating that a non-Cisco transceiver is attached and that you should try to bring up the port.

```
2009 Oct 9 01:46:42 switch %ETHPORT-3-IF_NON-CISCO_TRANSCEIVER: Non-Cisco transceiver
on interface Ethernet1/18 is detected.
```

If the attached transceiver is a QSFP+ splitter cable, then no special check is performed. The Cisco NX-OS software tries to bring up the port.

The following disclaimer applies to non-Cisco manufactured and non-Cisco certified QSFP copper splitter cables:

If a customer has a valid support contract for Cisco Nexus switches, Cisco TAC will support twinax cables that are a part of the compatibility matrix for the respective switches. However, if the twinax cables are not purchased through Cisco, a customer cannot return these cables through an RMA to Cisco for replacement.

If a twinax cable that is not part of the compatibility matrix is connected into a system, Cisco TAC will still debug the problem, provided the customer has a valid support contract on the switches. However TAC may ask the customer to replace the cables with Cisco qualified cables if there is a situation that points to the cables possibly being faulty or direct the customer to the cable provider for support. Cisco TAC cannot issue an RMA against uncertified cables for replacement.

Cisco QSFP 40-Gbps Bidirectional Short-Reach Transceiver

The Cisco QSFP 40-Gbps Bidirectional (BiDi) transceiver is a short-reach pluggable optical transceiver with a duplex LC connector for 40-GbE short-reach data communications and interconnect applications by using multimode fiber (MMF). The Cisco QSFP 40-Gbps BiDi transceiver offers a solution that uses existing duplex MMF infrastructure for 40-GbE connectivity. With the Cisco QSFP 40-Gbps BiDi transceiver, customers can upgrade their network from 10-GbE to 40-GbE without incurring any fiber infrastructure upgrade cost. The Cisco QSFP 40-Gbps BiDi transceiver can enable 40-GbE connectivity in a range of up to 100 meters over OM3 fiber, which meets most data center reach requirements. It complies with the Multiple Source Agreement (MSA) QSFP specification and enables customers to use it on all Cisco QSFP 40-Gbps platforms and achieve high density in a 40-GbE network. It can be used in data centers, high-performance computing (HPC) networks, enterprise and distribution layers, and service provider transport applications.

New and Changed Features

This section describes the new features introduced in Cisco NX-OS Release 6.0(2)U3(4). This section includes the following topics:

- [New Supported Hardware, page 19](#)
- [New Software Features, page 20](#)

New Supported Hardware

Cisco NX-OS Release 6.0(2)U3(4) does not include new hardware.

New Software Features

All Cisco Nexus 3000 Series switches are supported by Cisco NX-OS Release 6.0(2)U3(4). Cisco NX-OS interoperates with any networking operating system, including Cisco IOS software, that conforms to the networking standards listed in the product data sheet.

Cisco NX-OS Release 6.0(2)U3(4) does not include new software features.

Upgrade and Downgrade Guidelines

Ensure that you use the **install all** command to upgrade the switch software from one Cisco NX-OS release to another.

Upgrade Path to Release 6.0(2)U3(4)

Cisco Nexus 3000 Series switches that use software versions older than Cisco NX-OS Release 5.0(3)U5(1) need to be updated to Cisco NX-OS Release 5.0(3)U5(1) before they are upgraded to Cisco NX-OS Release 6.0(2).

Cisco NX-OS Release 5.0(3)U3(1) does not support a software upgrade from Cisco NX-OS Release 5.0(3)U2(2c). If you want to upgrade through this path, see [CSCty75328](#) for details about how to work around this issue.



Note

It is recommended that you upgrade to Cisco NX-OS Release 6.0(2)U3(4) by using Cisco NX-OS install procedures.

In Cisco NX-OS Release 5.0(3)U3(1), support for IPv6 has been added in Control Plane Policing (CoPP). To enable redirection of IPv6 control packets to the CPU, you must configure IPv6 CoPP on the system. Entering the **write erase** command on a device that runs Release 5.0(3)U3(1) automatically applies CoPP on the device and ensures that all IPv4 and IPv6-related CoPP configuration is set up correctly.

If you upgrade from a Cisco NX-OS release that does not support the CoPP feature to a release that does support the CoPP feature, you must run the setup utility after the upgrade to enable CoPP on the device.

If you upgrade from Cisco NX-OS Release 5.0(3)U2(2), which supports the CoPP feature, to Cisco NX-OS Release 5.0(3)U3(1), which adds CoPP classes for IPv6 support, you must run the setup script to enable the IPv6 CoPP feature on the device.

In Cisco NX-OS Release 6.0(2)U2(2), the default interface name in LLDP MIB is in short form. To make it long form, you must set **lldp portid-subtype** to 1. In Cisco NX-OS Release 6.0(2)U2(3), this behavior was reversed. The default interface name in LLDP MIB is now in long form. To make it short form, you must set **lldp portid-subtype** to 0.

If you have set **lldp port-subtype** to 1 and you are upgrading to Cisco NX-OS Release 6.0(2)U2(4), ensure that you set **lldp port-subtype** to 0.

Limitations

The following are the known limitations for Cisco NX-OS Release 6.0(2)U3(4):

- The **lldp tlv-set vlan** command must be run on Layer 2 ports only. If you run this command on Layer 3 ports, this configuration will be ignored while determining the mgmt IP address for LLDP mgmt TLV. However, the configuration will not be removed. When the port layer mode is changed to Layer 2 again, this configuration will be considered again (See [CSCuo03279](#)).
- During congestion, when traffic for priority levels 1 and 2 takes up all the available port bandwidth, all priority level 3 traffic is dropped even though the priority level 3 queue is configured with a shaper that has minimum guarantee.

To provide the priority level 3 queue with some bandwidth, apply max shaper values, which are less than the total port bandwidth on priority level 1 and priority level 2 queues. (See [CSCum99198](#))

- When configuring breakout or breakin on a range of ports, the following behavior is always observed (See [CSCun44231](#)):
 - Breakout or breakin takes 2-3 minutes if it is done on all QSFP ports simultaneously using the interface range command.

This does not have a workaround.

- Running the **speed 40000** command on an interface range of ports to breakin to 40G mode displays an error message:

```
switch(config)# interface Ethernet 1/49-54
switch(config-if-range)# speed 40000
ERROR: Ethernet1/49-13, Ethernet1/50-14, Ethernet1/51-15, Ethernet1/52-16,
Ethernet1/53-17, Ethernet1/54-18: Configuration does not match the port capability
```

Interface ranges such as **interface ethernet1/49-54** are not supported on QSFP ports with breakout mode. It will behave inconsistently if used. This is applicable for Cisco Nexus 3132, 3172PQ and 3172TQ switches.

However, interface range can be used as follows:

When in 40G mode,

```
switch(config)# int e1/49,e1/50,e1/51,e1/52,e1/53,e1/54
switch(config-if-range)
```

When in 10G mode,

```
switch(config)#
switch(config)# int eth1/49/1-4,eth1/50/1-4
```

- On Nexus 3172, whenever you change the portmode from 72x10G to 48x10G+breakout6x40G mode, all QSFP ports get converted to 4x10G breakout mode automatically (See [CSCun46788](#)).
- To get back to the 40G breakin mode, run the **speed 40000** command on the QSFP ports.
- Flows are created for VLANs that do not exist on the OVA via the controller. The OVA accepts these flows instead of rejecting them (See [CSCul69881](#)).
- OSPF over vPC and BFD with OSPF are supported on Cisco Nexus 3000 and 3100 Series switches. However, BFD with OSPF over vPC peer links is not currently supported (See [CSCtu87075](#)).
- MPLS stripping is not supported on Cisco NX-OS Release 6.0(2)U3(4).
- In Cisco NX-OS Release 6.0(2)U3(4), Cisco Nexus 3100 Series switches do not support PTP.
- Link Level Flow Control (LLFC) is not supported on Cisco Nexus 3000 series and Cisco Nexus 3100 series switches.

Caveats

The open and resolved bugs for this release are accessible through the [Cisco Bug Search Tool](#). This web-based tool provides you with access to the Cisco bug tracking system, which maintains information about bugs and vulnerabilities in this product and other Cisco hardware and software products.



Note You must have a Cisco.com account to log in and access the Cisco Bug Search Tool. If you do not have one, you can [register for an account](#).

For more information about the Cisco Bug Search Tool, see the [Bug Search Tool Help & FAQ](#).

This section includes the following topics:

- [Resolved Bugs in this Release, page 22](#)
- [Open Bugs for this Release, page 23](#)
- [Known Behaviors for this Release, page 23](#)

Resolved Bugs in this Release

[Table 6](#) lists descriptions of resolved bugs in Cisco NX-OS Release 6.0(2)U3(4). You can use the record ID to search the [Cisco Bug Search Tool](#) for details about the bug.

Table 6 Cisco NX-OS Release 6.0(2)U3(4) – Resolved Bugs

Record Number	Resolved Bug Headline
CSCun87600	On vPC failover on access, traffic disruption for approx 17 sec is seen.
CSCur04934	Product evaluation for CVE-2014-6271 and CVE-2014-7169.
CSCur02329	Routes are not learned through EIGRP in QSP.
CSCup68908	Need an option to limit backoff time for DHCP client retries.
CSCuq56034	IPFIB crash due to segmentation fault.
CSCuq43652	PPM crash while loading ACL.
CSCuo95375	Downgrade from Cisco NX-OS Release 6.0(2)U3(1) to Cisco NX-OS Release 6.0(2)U1(x) leads to ipqosmgr hap reset while bootup.
CSCuq14486	Cisco NX-OS Release 6.0(2)U3(3): Volatile database usage high, IPFIB crash.
CSCuq21902	Hardware l3lif gets exhausted on creating or deleting SVI multiple times.
CSCuq37330	Cisco Nexus 3172T: Wrong LED mapping for QSFP ports.
CSCuq43419	ACL group for v6 multicast packets is getting disabled after upgrade.
CSCuq52249	Applying a v6 ACL on to an SVI inbound shows an error that the TCAM is full.
CSCuq52769	Multicast queue-limit programmed in hardware for queue 1 only.
CSCup40763	Cisco Nexus 3000 Series switches not updating the ARP table from GARP request or reply.
CSCup45866	Persistent high rate of HW errors can trigger plog_sup process crash.
CSCup80823	SVI not responding to ARP request after reload.
CSCun37796	Cisco Nexus 3000 vPC: LACP timed out or failed on Hot-Standby Link.

Record Number	Resolved Bug Headline
CSCuo74028	Cisco Nexus 3000 returning invalid VLAN index value.
CSCuo88390	Cisco Nexus 3000 bcm_usd crash after parity error.
CSCup53845	SER: detection plog not generated for L3_DEF_IP table.
CSCup71579	Setup script fails with TCAM Region full error.
CSCuq53453	VRF route leak does not route packets on the leaked routes.
CSCuq53478	Cisco Nexus 3000: POAP Needs Script_Timeout longer than 3600 seconds.
CSCuq63323	copy bootflash:xxx run fails for BGP configurations.
CSCuq29719	Cisco Nexus 3000: Cosmetic CLI issue when Configuring PFC on port-channels.
CSCuq86552	The ip source interface icmp-errors command no longer functions.
CSCuo39282	QOS classification requires the set qos-group command to remark DSCP.

Open Bugs for this Release

Table 7 lists descriptions of open bugs in Cisco NX-OS Release 6.0(2)U3(4). You can use the record ID to search the [Cisco Bug Search Tool](#) for details about the bug.

Table 7 Cisco NX-OS Release 6.0(2)U3(4) – Open Bugs

Record Number	Open Bug Headline
CSCuo98834	VTY ACLs are not shown in startup after upgrade from Cisco NX-OS Release 6.0(2)U1(x) to Cisco NX-OS Release 6.0(2)U3(1).
CSCun19114	Port channel members flapping on peer reload in VPC on Cisco Nexus 3000 Series switches.
CSCun98182	Overwrite should not happen when mode OpenFlow or tap is given to interface.
CSCun74653	RIP neighbor is coming up even after shut on RIP process after system reboot.
CSCuj10855	show tunnel int # is not showing in/out tunnel traffic statistics.
CSCuo64647	Input type queuing policy errors out on configuration replay from file.

Known Behaviors for this Release

Large core files are split into 3 or more files. For example:

- 1405964207_0x101_fwm_log.3679.tar.gzaa
- 1405964207_0x101_fwm_log.3679.tar.gzab
- 1405964207_0x101_fwm_log.3679.tar.gzac

To decode the multiple core files, first club the files to a single file as demonstrated below:

```
$ cat 1405964207_0x101_fwm_log.3679.tar.gz* > 1405964207_0x101_fwm_log.3679.tar.gz
```

MIB Support

The Cisco Management Information Base (MIB) list includes Cisco proprietary MIBs and many other Internet Engineering Task Force (IETF) standard MIBs. These standard MIBs are defined in Requests for Comments (RFCs). To find specific MIB information, you must examine the Cisco proprietary MIB structure and related IETF-standard MIBs supported by the Cisco Nexus 3000 Series switch. The MIB Support List is available at the following FTP sites:

<ftp://ftp.cisco.com/pub/mibs/supportlists/nexus3000/Nexus3000MIBSupportList.html>

Related Documentation

Documentation for the Cisco Nexus 3000 Series Switch is available at the following URL:

http://www.cisco.com/en/US/products/ps11541/tsd_products_support_series_home.html

The documentation set is divided into the following categories:

Release Notes

The release notes are available at the following URL:

http://www.cisco.com/en/US/products/ps11541/prod_release_notes_list.html

Installation and Upgrade Guides

The installation and upgrade guides are available at the following URL:

http://www.cisco.com/en/US/products/ps11541/prod_installation_guides_list.html

Command References

The command references are available at the following URL:

http://www.cisco.com/en/US/products/ps11541/prod_command_reference_list.html

Technical References

The technical references are available at the following URL:

http://www.cisco.com/en/US/products/ps11541/prod_technical_reference_list.html

Configuration Guides

The configuration guides are available at the following URL:

http://www.cisco.com/en/US/products/ps11541/products_installation_and_configuration_guides_list.html

Error and System Messages

The system message reference guide is available at the following URL:

http://www.cisco.com/en/US/products/ps11541/products_system_message_guides_list.html

Documentation Feedback

To provide technical feedback on this document, or to report an error or omission, please send your comments to nexus3k-docfeedback@cisco.com. We appreciate your feedback.

Obtaining Documentation and Submitting a Service Request

For information on obtaining documentation, submitting a service request, and gathering additional information, see the monthly *What's New in Cisco Product Documentation*, which also lists all new and revised Cisco technical documentation, at:

<http://www.cisco.com/en/US/docs/general/whatsnew/whatsnew.html>

Subscribe to the *What's New in Cisco Product Documentation* as a Really Simple Syndication (RSS) feed and set content to be delivered directly to your desktop using a reader application. The RSS feeds are a free service and Cisco currently supports RSS version 2.0.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: www.cisco.com/go/trademarks. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)

© 2014 Cisco Systems, Inc. All rights reserved.

