

Network Access Server Identifier

- Information About Network Access Server Identifier, on page 1
- Creating a NAS ID Policy(GUI), on page 2
- Creating a NAS ID Policy, on page 2
- Attaching a Policy to a Tag (GUI), on page 3
- Attaching a Policy to a Tag (CLI), on page 3
- Verifying the NAS ID Configuration, on page 4

Information About Network Access Server Identifier

Network access server identifier (NAS-ID) is used to notify the source of a RADIUS access request, which enables the RADIUS server to choose a policy for that request. You can configure one on each WLAN profile, VLAN interface, or access point group. The NAS-ID is sent to the RADIUS server by the controller through an authentication request to classify users to different groups. This enables the RADIUS server to send a customized authentication response.



Note The acct-session-id is sent with the RADIUS access request only when accounting is enabled on the policy profile.

If you configure a NAS-ID for an AP group, it overrides the NAS-ID that is configured for a WLAN profile or the VLAN interface. Similarly, if you configure a NAS-ID for a WLAN profile, it overrides the NAS-ID that is configured for the VLAN interface.

Starting with Cisco IOS XE Cupertino 17.7.1, a new string named custom-string (custom string) is added.

The following options can be configured for a NAS ID:

- sys-name (System Name)
- sys-ip (System IP Address)
- sys-mac (System MAC Address)
- ap-ip (AP's IP address)
- ap-name (AP's Name)
- ap-mac (AP's MAC Address)

- ap-eth-mac (AP's Ethernet MAC Address)
- ap-policy-tag (AP's policy tag name)
- ap-site-tag (AP's site tag name)
- ssid (SSID Name)
- ap-location (AP's Location)
- custom-string (custom string)

Creating a NAS ID Policy(GUI)

Procedure

Step 1	Choose Configuration > Security > Wireless AAA Policy.		
Step 2	On the Wireless AAA Policy page, click the name of the Policy or click Add to create a new one.		
Step 3	3 In the Add/Edit Wireless AAA Policy window that is displayed, enter the name of the policy in the Police Name field.		
Step 4	Choose from one of the NAS ID options from the Option 1 drop-down list.		
Step 5	Choose from one of the NAS ID options from the Option 2 drop-down list.		
Step 6	Choose from one of the NAS ID options from the Option 3 drop-down list.		
Step 7	Save the configuration.		

Creating a NAS ID Policy

Follow the procedure given below to create NAS ID policy:

Before you begin

- NAS ID can be a combination of multiple NAS ID options; the maximum options are limited to 3.
- The maximum length of the NAS ID attribute is 253. Before adding a new attribute, the attribute buffer is checked, and if there is no sufficient space, the new attribute is ignored.
- By default, a wireless aaa policy (default-aaa-policy) is created with the default configuration (sys-name). You can update this policy with various NAS ID options. However, the default-aaa-policy cannot be deleted.
- If a NAS ID is not configured, the default sys-name is considered as the NAS ID for all wireless-specific RADIUS packets (authentication and accounting) from the controller.
- Starting with Cisco IOS XE Cupertino 17.7.1, you can configure a custom string with various combinations of option1, option2 and option3 (nas-id option3 custom-string *custom-string*) as NAS ID in RADIUS packets.

	Command or Action	Purpose
Step 1	configure terminal	Enters global configuration mode.
	Example:	
	Device# configure terminal	
Step 2	wireless aaa policy policy-name	Configures a new AAA policy.
	Example:	
	Device(config)# wireless aaa policy test	
Step 3	nas-id option1 sys-name	Configures NAS ID for option1.
	Example:	
	Device(config-aaa-policy)# nas-id option1 sys-name	
Step 4	nas-id option2 sys-ip	Configures NAS ID for option2.
	Example:	
	Device(config-aaa-policy)# nas-id option2 sys-ip	
Step 5	nas-id option3 sys-mac	Configures NAS ID for option3.
	Example:	
	Device(config-aaa-policy)# nas-id option3 sys-mac	

Procedure

Attaching a Policy to a Tag (GUI)

Procedure

Step 1	Choose Configuration > Tags & Profiles > Tags page, click Policy tab.
Step 2	Click Add to view the Add Policy Tag window.
Step 3	Enter a name and description for the policy tag.
Step 4	Click Add to map WLAN profile and Policy profile.
Step 5	Choose the WLAN Profile to map with the appropriate Policy Profile, and click the tick icon.
Step 6	Click Save & Apply to Device.

Attaching a Policy to a Tag (CLI)

Follow the procedure given below to attach a NAS ID policy to a tag:

	Command or Action	Purpose	
Step 1	configure terminal	Enters global configuration mode.	
	Example:		
	Device# configure terminal		
Step 2	wireless profile policy policy-name	Configures a WLAN policy profile.	
	Example:		
	<pre>Device(config)# wireless profile policy test1</pre>		
Step 3	aaa-policy aaa-policy-name	Configures a AAA policy profile.	
	Example:		
	Device(config-wireless-policy)# aaa-policy policy-aaa		
Step 4	exit	Returns to global configuration mode.	
	Example:		
	Device(config-wireless-policy)# exit		
Step 5	wireless tag policy policy-tag	Configures a wireless policy tag.	
	Example:		
	Device(config)# wireless tag policy policy-tag1		
Step 6	wlan wlan1 policy policy-name	Maps a WLAN profile to a policy profile.	
	Example: Device(config)# wlan wlan1 policy test1	Note You can also use the ap-tag option to configure a NAS ID for an AP group, which will override the NAS ID that is configured for a WLAN profile or the VLAN interface.	

Procedure

Verifying the NAS ID Configuration

Use the following **show** command to verify the NAS ID configuration:

Device# show wireless profile policy detailed test1

Policy Profile Name	:	test1
Description	:	
Status	:	ENABLED
VLAN	:	1
Client count	:	0
:		
:		
AAA Policy Params		
AAA Override	:	DISABLED

NAC AAA Policy name : DISABLED : test