

# Configuración de IPSec entre un switch gateway de acceso Catalyst 4224 y un router Cisco IOS

## Contenido

[Introducción](#)

[Prerequisites](#)

[Requirements](#)

[Componentes Utilizados](#)

[Convenciones](#)

[Configurar](#)

[Diagrama de la red](#)

[Configuraciones](#)

[Verificación](#)

[Troubleshoot](#)

[Comandos para resolución de problemas](#)

[Depuraciones de ejemplo](#)

[Información Relacionada](#)

## [Introducción](#)

Este documento ilustra la configuración de ejemplo de IPSec entre un Cisco Catalyst 4224 Access Gateway Switch y un Cisco Router que ejecuta Cisco IOS® Software. El cifrado se realiza entre la VLAN1 del gateway de acceso (donde se aplica el mapa criptográfico) y la interfaz FastEthernet0/1 del router.

## [Prerequisites](#)

## [Requirements](#)

No hay requisitos previos específicos para este documento.

## [Componentes Utilizados](#)

La información que contiene este documento se basa en las siguientes versiones de software y hardware.

- Versión 12.1(1)14 del software del IOS de Cisco
- Software IOS c4224 12.2(2)YC1

La información que se presenta en este documento se originó a partir de dispositivos dentro de un ambiente de laboratorio específico. All of the devices used in this document started with a cleared (default) configuration. Si la red está funcionando, asegúrese de haber comprendido el impacto

que puede tener un comando antes de ejecutarlo.

## Convenciones

Para obtener más información sobre las convenciones del documento, consulte [Convenciones de Consejos Técnicos de Cisco](#).

## Configurar

En esta sección encontrará la información para configurar las funciones descritas en este documento.

**Nota:** Para encontrar información adicional sobre los comandos usados en este documento, utilice la [Command Lookup Tool](#) (sólo clientes registrados) .

## Diagrama de la red

En este documento, se utiliza esta configuración de red:



## Configuraciones

En este documento, se utilizan estas configuraciones:

- [Switch de gateway de acceso Catalyst 4224](#)
- [Router del Cisco IOS](#)

### Switch de gateway de acceso Catalyst 4224

```
 triana#show version
Cisco Internetwork Operating System Software
IOS (tm) c4224 Software (c4224-IK903SX3-M), Version
12.2(2)YC1,
EARLY DEPLOYMENT RELEASE SOFTWARE (fc2)

26 FastEthernet/IEEE 802.3 interface(s)
2 Serial(sync/async) network interface(s)
2 Channelized E1/PRI port(s)
1 Virtual Private Network (VPN) Module(s)
!--- Access gateway has onboard encryption service
adapter. 8 Voice FXS interface(s) 256K bytes of non-
volatile configuration memory. 31744K bytes of processor
board System flash (Read/Write) Configuration register
is 0x2102 triana#show run
Building configuration...
```

```
Current configuration : 5111 bytes
!
! Last configuration change at 13:56:01 UTC Wed May 29
2002
! NVRAM config last updated at 13:56:03 UTC Wed May 29
2002
!
version 12.2
service timestamps debug datetime msec
service timestamps log datetime msec
no service password-encryption
!
hostname triana
!
no logging buffered
enable password ww
!
memory-size iomem 25
!--- Create the VLANS as required. vlan 1
  name default
vlan 3
  name VLAN0003
!--- Create the VLANS as required. vlan 2
  name data
vlan 999
  name VLAN0999
!
ip subnet-zero
no ip domain-lookup
!
ip audit notify log
ip audit po max-events 100
ip ssh time-out 120
ip ssh authentication-retries 3
isdn switch-type primary-net5
voicecard mode toll-by-pass
!
!
!
!
!
!
!
ccm-manager mgcp
!
!--- Define Phase 1 policy. crypto isakmp policy 10
  authentication pre-share
  crypto isakmp key yoursecretkey address 209.165.201.6
!
!
!--- Define Phase 2 policy. crypto ipsec transform-set
  basic esp-des esp-md5-hmac
crypto mib ipsec flowmib history tunnel size 200
crypto mib ipsec flowmib history failure size 200
!
!--- Define Phase 2 policy (continued). !--- Define the
encryption peer and crypto map parameters. crypto map
mymap 10 ipsec-isakmp
  set peer 209.165.201.6
  set transform-set basic
  match address cryptoacl
!
!
no spanning-tree optimize bpdu transmission
```

```
no spanning-tree vlan 1
no spanning-tree vlan 2
no spanning-tree vlan 3
!
controller E1 2/0
!
controller E1 2/1
!
translation-rule 1
  Rule 0 ^... 1
!
translation-rule 2
  Rule 0 ^10.. 0
  Rule 1 ^11.. 1
  Rule 2 ^12.. 2
  Rule 3 ^13.. 3
  Rule 4 ^14.. 4
  Rule 5 ^15.. 5
  Rule 6 ^16.. 6
  Rule 7 ^17.. 7
  Rule 8 ^18.. 8
  Rule 9 ^19.. 9
!
translation-rule 6
  Rule 0 ^112. 119
!
translation-rule 7
  Rule 0 ^1212 1196
!
translation-rule 3
  Rule 0 ^. 0
!
translation-rule 9
  Rule 0 ^. 9
!
translation-rule 99
  Rule 0 ^90.. 0
  Rule 1 ^91.. 1
  Rule 2 ^92.. 2
  Rule 3 ^93.. 3
  Rule 4 ^94.. 4
  Rule 5 ^95.. 5
  Rule 6 ^96.. 6
  Rule 7 ^97.. 7
  Rule 8 ^98.. 8
  Rule 9 ^99.. 9
!
translation-rule 999
  Rule 0 ^2186 1196
!
translation-rule 1122
  Rule 0 ^1122 528001
  Rule 1 ^1121 519352
!
translation-rule 20
  Rule 0 ^000 500
!
!
!
interface Loopback0
  no ip address
!
interface FastEthernet0/0
  no ip address
```

```
duplex auto
speed auto
!
interface Serial1/0
no ip address
no fair-queue
!
interface Serial1/1
no ip address
!
interface FastEthernet5/0
no ip address
duplex auto
speed auto
!
interface FastEthernet5/1
no ip address
shutdown
duplex auto
speed auto
switchport voice vlan 3
spanning-tree portfast
!
!--- For the lab setup, a host is connected on this
port. interface FastEthernet5/2
no ip address
duplex auto
speed auto
!--- Place the port in VLAN 2. switchport access vlan 2
spanning-tree portfast
!
interface FastEthernet5/3
no ip address
shutdown
duplex auto
speed auto
switchport access vlan 999
spanning-tree portfast
!
interface FastEthernet5/4
no ip address
duplex auto
speed auto
switchport access vlan 2
switchport voice vlan 3
spanning-tree portfast
!
interface FastEthernet5/5
no ip address
duplex auto
speed auto
!
interface FastEthernet5/6
no ip address
duplex auto
speed auto
!
interface FastEthernet5/7
no ip address
duplex auto
speed auto
!
interface FastEthernet5/8
no ip address
```

```
duplex auto
speed auto
!
interface FastEthernet5/9
no ip address
duplex auto
speed auto
!
interface FastEthernet5/10
no ip address
duplex auto
speed auto
switchport trunk allowed vlan 1-3
switchport mode trunk
!--- By default, the port belongs to VLAN 1. interface
FastEthernet5/11
no ip address
duplex auto
speed auto
!
interface FastEthernet5/12
no ip address
duplex auto
speed auto
!
interface FastEthernet5/13
no ip address
duplex auto
speed auto
!
interface FastEthernet5/14
no ip address
duplex auto
speed auto
!
interface FastEthernet5/15
no ip address
duplex auto
speed auto
!
interface FastEthernet5/16
no ip address
duplex auto
speed auto
!
interface FastEthernet5/17
no ip address
duplex auto
speed auto
!
interface FastEthernet5/18
no ip address
duplex auto
speed auto
!
interface FastEthernet5/19
no ip address
duplex auto
speed auto
!
interface FastEthernet5/20
no ip address
duplex auto
speed auto
```

```
!  
interface FastEthernet5/21  
  no ip address  
  duplex auto  
  speed auto  
!  
interface FastEthernet5/22  
  no ip address  
  duplex auto  
  speed auto  
!  
interface FastEthernet5/23  
  no ip address  
  duplex auto  
  speed auto  
!  
interface FastEthernet5/24  
  no ip address  
  duplex auto  
  speed auto  
!  
!--- Define an IP address and apply crypto map to enable  
!--- IPsec processing on this interface. interface Vlan  
1  
  ip address 209.165.201.5 255.255.255.224  
  crypto map mymap  
!  
!--- Define an IP address for VLAN 2. interface Vlan 2  
  ip address 192.168.10.1 255.255.255.0  
!  
ip classless  
ip route 10.48.66.0 255.255.254.0 209.165.201.6  
no ip http server  
!  
!  
ip access-list extended cryptoacl  
  remark This is crypto ACL  
  permit ip 192.168.10.0 0.0.0.255 10.48.66.0 0.0.1.255  
call rsvp-sync  
!  
voice-port 4/0  
  output attenuation 0  
!  
voice-port 4/1  
  output attenuation 0  
!  
voice-port 4/2  
  output attenuation 0  
!  
voice-port 4/3  
  output attenuation 0  
!  
voice-port 4/4  
  output attenuation 0  
!  
voice-port 4/5  
  output attenuation 0  
!  
voice-port 4/6  
  output attenuation 0  
!  
voice-port 4/7  
  output attenuation 0  
!
```

```
mgcp
no mgcp timer receive-rtcp
!
mgcp profile default
!
dial-peer cor custom
!
!
!
dial-peer voice 1 voip
!
dial-peer voice 2 pots
shutdown
!
!
line con 0
exec-timeout 0 0
length 0
line vty 0 4
password ww
login
!
end

 triana#
```

## Router del Cisco IOS

```
brussels#show run
Building configuration...

Current configuration : 1538 bytes
!
! Last configuration change at 17:16:19 UTC Wed May 29
2002
! NVRAM config last updated at 13:58:44 UTC Wed May 29
2002
!
version 12.1
no service single-slot-reload-enable
service timestamps debug uptime
service timestamps log uptime
no service password-encryption
!
hostname brussels
!
enable secret 5 $1$/vuT$081TvZgSFJ0xq5uTFc94u.
!
!
!
!
!
!
ip subnet-zero
no ip domain-lookup
!
ip cef
ip audit notify log
ip audit po max-events 100
!
!
!--- Define Phase 1 policy. crypto isakmp policy 10
authentication pre-share
```



```

crypto isakmp key yoursecretkey address 209.165.201.5
!
!
!--- Define the encryption policy for this setup. crypto
ipsec transform-set basic esp-des esp-md5-hmac
!
!--- Define a static crypto map entry for the remote PIX
!--- with mode ipsec-isakmp. !--- This indicates that
Internet Key Exchange (IKE) !--- is used to establish
the IPSec !--- security associations for protecting the
traffic !--- specified by this crypto map entry. crypto
map vpnmap 10 ipsec-isakmp
  set peer 209.165.201.5
  set transform-set basic
  match address cryptoacl
!
!
!
!
!
!
interface FastEthernet0/0
  ip address 10.48.66.34 255.255.254.0
  no ip mroute-cache
  duplex auto
  speed auto
!
interface Serial0/0
  no ip address
  shutdown
!
!--- Enable crypto processing on the interface !---
where traffic leaves the network. interface
FastEthernet0/1
  ip address 209.165.201.6 255.255.255.224
  no ip mroute-cache
  duplex auto
  speed auto
  crypto map vpnmap
!
interface Serial0/1
  no ip address
  shutdown
!
interface Group-Async1
  no ip address
  encapsulation ppp
  async mode dedicated
  ppp authentication pap
  group-range 33 40
!
ip classless
ip route 192.168.10.0 255.255.255.0 209.165.201.5
ip http server
!
!
!--- This access list defines interesting traffic for
IPSec. ip access-list extended cryptoacl
  permit ip 10.48.66.0 0.0.1.255 192.168.10.0 0.0.0.255
!
!
line con 0
  exec-timeout 0 0
  length 0

```

```
line 33 40
  modem InOut
line aux 0
line vty 0 4
  login local
!
end
```

## Verificación

En esta sección encontrará información que puede utilizar para confirmar que su configuración esté funcionando correctamente. La verificación de la operación IPsec se realiza con comandos **debug**. Se intenta realizar un ping extendido desde el router a un host detrás del gateway de acceso.

La herramienta [Output Interpreter](#) (sólo para clientes registrados) permite utilizar algunos comandos "show" y ver un análisis del resultado de estos comandos.

- **show debug**—Muestra la configuración de depuración actual.
- **show crypto isakmp sa** : muestra todas las asociaciones de seguridad actuales IKE (SA) en un par.
- **show crypto ipsec sa** — Muestra la configuración actual utilizada por las SA actuales

## Troubleshoot

En esta sección encontrará información que puede utilizar para solucionar problemas de configuración.

### Comandos para resolución de problemas

**Nota:** Antes de ejecutar comandos **debug**, consulte [Información Importante sobre Comandos Debug](#).

- **debug crypto ipsec** — Muestra eventos de IPsec.
- **debug crypto isakmp** — Muestra mensajes acerca de eventos IKE.
- **debug crypto engine** — Muestra información del motor de criptografía.

### Depuraciones de ejemplo

Esta sección proporciona un ejemplo de salida de depuración para el gateway de acceso y el router.

- [Switch de gateway de acceso Catalyst 4224](#)
- [Router del Cisco IOS](#)

### Switch de gateway de acceso Catalyst 4224

```
 triana#debug crypto ipsec
Crypto IPSEC debugging is on
```

```
triana#debug crypto isakmp
Crypto ISAKMP debugging is on
triana#debug crypto engine
Crypto Engine debugging is on
triana#show debug
```

Cryptographic Subsystem:

```
Crypto ISAKMP debugging is on
Crypto Engine debugging is on
Crypto IPSEC debugging is on
```

triana#

```
May 29 18:01:57.746: ISAKMP (0:0): received packet from 209.165.201.6 (N) NEW SA
```

```
May 29 18:01:57.746: ISAKMP: local port 500, remote port 500
```

```
May 29 18:01:57.746: ISAKMP (0:1): Input = IKE_MESG_FROM_PEER, IKE_MM_EXCH
```

```
Old State = IKE_READY New State = IKE_R_MM1
```

```
May 29 18:01:57.746: ISAKMP (0:1): processing SA payload. message ID = 0
```

```
May 29 18:01:57.746: ISAKMP (0:1): found peer pre-shared key
```

```
matching 209.165.201.6
```

```
!--- 4224 access gateway checks the attributes for Internet Security !--- Association & Key
Management Protocol (ISAKMP) negotiation !--- against the policy it has in its local
configuration.
```

```
May 29 18:01:57.746: ISAKMP (0:1): Checking ISAKMP transform 1 against priority
```

```
10 policy May 29 18:01:57.746: ISAKMP: encryption DES-CBC May 29 18:01:57.746: ISAKMP: hash SHA
```

```
May 29 18:01:57.746: ISAKMP: default group 1 May 29 18:01:57.746: ISAKMP: auth pre-share !---
```

```
The received attributes are acceptable !--- against the configured set of attributes.
```

```
May 29 18:01:57.746: ISAKMP (0:1): atts are acceptable. Next payload is 0 May 29 18:01:57.746:
```

```
CryptoEngine0: generate alg parameter May 29 18:01:57.746: CryptoEngine0:
```

```
CRYPTO_ISA_DH_CREATE(hw)(ipsec) May 29 18:01:57.898: CRYPTO_ENGINE: Dh phase 1 status: 0 May 29
```

```
18:01:57.898: ISAKMP (0:1): Input = IKE_MESG_INTERNAL, IKE_PROCESS_MAIN_MODE Old State =
```

```
IKE_R_MM1 New State = IKE_R_MM1 May 29 18:01:57.898: ISAKMP (0:1): SA is doing pre-shared key
```

```
authentication using id type ID_IPV4_ADDR May 29 18:01:57.898: ISAKMP (0:1): sending packet to
```

```
209.165.201.6 (R) MM_SA_SETUP May 29 18:01:57.898: ISAKMP (0:1): Input = IKE_MESG_INTERNAL,
```

```
IKE_PROCESS_COMPLETE Old State = IKE_R_MM1 New State = IKE_R_MM2 May 29 18:01:58.094: ISAKMP
```

```
(0:1): received packet from 209.165.201.6 (R) MM_SA_SETUP May 29 18:01:58.094: ISAKMP (0:1):
```

```
Input = IKE_MESG_FROM_PEER, IKE_MM_EXCH Old State = IKE_R_MM2 New State = IKE_R_MM3 May 29
```

```
18:01:58.098: ISAKMP (0:1): processing KE payload. message ID = 0 May 29 18:01:58.098:
```

```
CryptoEngine0: generate alg parameter May 29 18:01:58.098: CryptoEngine0:
```

```
CRYPTO_ISA_DH_SHARE_SECRET(hw)(ipsec) May 29 18:01:58.246: ISAKMP (0:1): processing NONCE
```

```
payload. message ID = 0 May 29 18:01:58.246: ISAKMP (0:1): found peer pre-shared key matching
```

```
209.165.201.6 May 29 18:01:58.250: CryptoEngine0: create ISAKMP SKEYID for conn id 1 May 29
```

```
18:01:58.250: CryptoEngine0: CRYPTO_ISA_SA_CREATE(hw)(ipsec) May 29 18:01:58.250: ISAKMP (0:1):
```

```
SKEYID state generated
```

```
May 29 18:01:58.250: ISAKMP (0:1): processing vendor id payload
```

```
May 29 18:01:58.250: ISAKMP (0:1): speaking to another IOS box!
```

```
May 29 18:01:58.250: ISAKMP (0:1): Input = IKE_MESG_INTERNAL, IKE_PROCESS_MAIN_MODE
```

```
Old State = IKE_R_MM3 New State = IKE_R_MM3
```

```
May 29 18:01:58.250: ISAKMP (0:1): sending packet to 209.165.201.6 (R) MM_KEY_EXCH
```

```
May 29 18:01:58.250: ISAKMP (0:1): Input = IKE_MESG_INTERNAL, IKE_PROCESS_COMPLETE
```

```
Old State = IKE_R_MM3 New State = IKE_R_MM4
```

```
May 29 18:01:58.490: ISAKMP (0:1): received packet from 209.165.201.6
```

```
(R) MM_KEY_EXCH
```

```
May 29 18:01:58.490: CryptoEngine0: CRYPTO_ISA_IKE_DECRYPT(hw)(ipsec)
```

```
May 29 18:01:58.490: ISAKMP (0:1): Input = IKE_MESG_FROM_PEER, IKE_MM_EXCH
```

```
Old State = IKE_R_MM4 New State = IKE_R_MM5
```

```
May 29 18:01:58.490: ISAKMP (0:1): processing ID payload. message ID = 0
```

```
May 29 18:01:58.490: ISAKMP (0:1): processing HASH payload. message ID = 0
```

```
May 29 18:01:58.490: CryptoEngine0: generate hmac context for conn id 1
```

```
May 29 18:01:58.490: CryptoEngine0: CRYPTO_ISA_IKE_HMAC(hw)(ipsec)
```

```
May 29 18:01:58.490: ISAKMP (0:1): SA has been authenticated with 209.165.201.6
```

```
!--- Phase 1 authentication is successful and the SA is authenticated. May 29 18:01:58.494:
```

```
ISAKMP (0:1): Input = IKE_MESG_INTERNAL, IKE_PROCESS_MAIN_MODE Old State = IKE_R_MM5 New State =
```

```
IKE_R_MM5 May 29 18:01:58.494: ISAKMP (1): ID payload next-payload : 8 type : 1 protocol : 17
```

port : 500 length : 8 May 29 18:01:58.494: ISAKMP (1): Total payload length: 12 May 29  
18:01:58.494: CryptoEngine0: generate hmac context for conn id 1 May 29 18:01:58.494:  
CryptoEngine0: CRYPTO\_ISA\_IKE\_HMAC(hw)(ipsec) May 29 18:01:58.494: CryptoEngine0: clear dh  
number for conn id 1 May 29 18:01:58.494: CryptoEngine0: CRYPTO\_ISA\_DH\_DELETE(hw)(ipsec) May 29  
18:01:58.494: CryptoEngine0: CRYPTO\_ISA\_IKE\_ENCRYPT(hw)(ipsec) May 29 18:01:58.494: ISAKMP  
(0:1): sending packet to 209.165.201.6 (R) QM\_IDLE May 29 18:01:58.498: ISAKMP (0:1): Input =  
IKE\_MSG\_INTERNAL, IKE\_PROCESS\_COMPLETE Old State = IKE\_R\_MM5 New State = IKE\_PI\_COMPLETE May 29  
18:01:58.518: ISAKMP (0:1): received packet from 209.165.201.6 (R) QM\_IDLE May 29 18:01:58.518:  
CryptoEngine0: CRYPTO\_ISA\_IKE\_DECRYPT(hw)(ipsec) May 29 18:01:58.518: CryptoEngine0: generate  
hmac context for conn id 1 May 29 18:01:58.518: CryptoEngine0: CRYPTO\_ISA\_IKE\_HMAC(hw)(ipsec)  
May 29 18:01:58.522: ISAKMP (0:1): processing HASH payload. message ID = -1809462101 May 29  
18:01:58.522: ISAKMP (0:1): processing SA payload. message ID = -1809462101 May 29 18:01:58.522:  
ISAKMP (0:1): Checking IPsec proposal 1 May 29 18:01:58.522: ISAKMP: transform 1, ESP\_DES May 29  
18:01:58.522: ISAKMP: attributes in transform: May 29 18:01:58.522: ISAKMP: encaps is 1 May 29  
18:01:58.522: ISAKMP: SA life type in seconds May 29 18:01:58.522: ISAKMP: SA life duration  
(basic) of 3600 May 29 18:01:58.522: ISAKMP: SA life type in kilobytes May 29 18:01:58.522:  
ISAKMP: SA life duration (VPI) of 0x0 0x46 0x50 0x0 May 29 18:01:58.522: ISAKMP: authenticator  
is HMAC-MD5 May 29 18:01:58.522: validate proposal 0 **May 29 18:01:58.522: ISAKMP (0:1): atts are  
acceptable.**  
May 29 18:01:58.522: IPSEC(validate\_proposal\_request): proposal part #1,  
*!--- After the attributes are negotiated, !--- IKE asks IPsec to validate the proposal.* (key  
eng. msg.) dest= 209.165.201.5, src= 209.165.201.6, dest\_proxy= 192.168.10.0/255.255.255.0/0/0  
(type=4), src\_proxy= 10.48.66.0/255.255.254.0/0/0 (type=4), protocol= ESP, transform= esp-des  
esp-md5-hmac , lifedur= 0s and 0kb, spi= 0x0(0), conn\_id= 0, keysize= 0, flags= 0x4 *!--- spi is  
still zero because SAs have not been set.* May 29 18:01:58.522: validate proposal request 0 May  
29 18:01:58.522: ISAKMP (0:1): processing NONCE payload. message ID = -1809462101 May 29  
18:01:58.522: ISAKMP (0:1): processing ID payload. message ID = -1809462101 May 29 18:01:58.522:  
ISAKMP (1): ID\_IPV4\_ADDR\_SUBNET src 10.48.66.0/255.255.254.0 prot 0 port 0 May 29 18:01:58.522:  
ISAKMP (0:1): processing ID payload. message ID = -1809462101 May 29 18:01:58.522: ISAKMP (1):  
ID\_IPV4\_ADDR\_SUBNET dst 192.168.10.0/255.255.255.0 prot 0 port 0 May 29 18:01:58.522: ISAKMP  
(0:1): asking for 1 spis from ipsec May 29 18:01:58.522: ISAKMP (0:1): Node -1809462101, Input =  
IKE\_MSG\_FROM\_PEER, IKE\_QM\_EXCH Old State = IKE\_QM\_READY New State = IKE\_QM\_SPI\_STARVE May 29  
18:01:58.526: IPSEC(key\_engine): got a queue event... May 29 18:01:58.526: IPSEC(spi\_response):  
getting spi 3384026087 for SA from 209.165.201.6 to 209.165.201.5 for prot 3 May 29  
18:01:58.526: ISAKMP: received ke message (2/1) May 29 18:01:58.774: CryptoEngine0: generate  
hmac context for conn id 1 May 29 18:01:58.774: CryptoEngine0: CRYPTO\_ISA\_IKE\_HMAC(hw)(ipsec)  
May 29 18:01:58.774: CryptoEngine0: CRYPTO\_ISA\_IKE\_ENCRYPT(hw)(ipsec) May 29 18:01:58.774:  
ISAKMP (0:1): sending packet to 209.165.201.6 (R) QM\_IDLE May 29 18:01:58.774: ISAKMP (0:1):  
Node -1809462101, Input = IKE\_MSG\_FROM\_IPSEC, IKE\_SPI\_REPLY Old State = IKE\_QM\_SPI\_STARVE New  
State = IKE\_QM\_R\_QM2 May 29 18:01:58.830: ISAKMP (0:1): received packet from 209.165.201.6 (R)  
QM\_IDLE May 29 18:01:58.830: CryptoEngine0: CRYPTO\_ISA\_IKE\_DECRYPT(hw)(ipsec) May 29  
18:01:58.834: CryptoEngine0: generate hmac context for conn id 1 May 29 18:01:58.834:  
CryptoEngine0: CRYPTO\_ISA\_IKE\_HMAC(hw)(ipsec) May 29 18:01:58.834: ipsec allocate flow 0 May 29  
18:01:58.834: ipsec allocate flow 0 May 29 18:01:58.834: CryptoEngine0:  
CRYPTO\_ISA\_IPSEC\_KEY\_CREATE(hw)(ipsec) May 29 18:01:58.834: CryptoEngine0:  
CRYPTO\_ISA\_IPSEC\_KEY\_CREATE(hw)(ipsec) **May 29 18:01:58.838: ISAKMP (0:1): Creating IPsec SAs**  
May 29 18:01:58.838: inbound SA from 209.165.201.6 to 209.165.201.5  
(proxy 10.48.66.0 to 192.168.10.0)  
May 29 18:01:58.838: has spi 0xC9B423E7 and conn\_id 50 and flags 4  
May 29 18:01:58.838: lifetime of 3600 seconds  
May 29 18:01:58.838: lifetime of 4608000 kilobytes  
May 29 18:01:58.838: outbound SA from 209.165.201.5 to 209.165.201.6  
(proxy 192.168.10.0 to 10.48.66.0)  
May 29 18:01:58.838: has spi 561973207 and conn\_id 51 and flags 4  
May 29 18:01:58.838: lifetime of 3600 seconds  
May 29 18:01:58.838: lifetime of 4608000 kilobytes  
May 29 18:01:58.838: ISAKMP (0:1): deleting node -1809462101 error FALSE reason  
"quick mode done (await()"  
May 29 18:01:58.838: ISAKMP (0:1): Node -1809462101, Input = IKE\_MSG\_FROM\_PEER,  
IKE\_QM\_EXCH  
Old State = IKE\_QM\_R\_QM2 New State = IKE\_QM\_PHASE2\_COMPLETE  
May 29 18:01:58.838: IPSEC(key\_engine): got a queue event...  
May 29 18:01:58.838: IPSEC(initialize\_sas): ,

```
(key eng. msg.) dest= 209.165.201.5, src= 209.165.201.6,
dest_proxy= 192.168.10.0/255.255.255.0/0/0 (type=4),
src_proxy= 10.48.66.0/255.255.254.0/0/0 (type=4),
protocol= ESP, transform= esp-des esp-md5-hmac ,
lifedur= 3600s and 4608000kb,
spi= 0xC9B423E7(3384026087), conn_id= 50, keysize= 0, flags= 0x4
```

```
!--- IPsec SAs are now initialized and encrypted !--- communication can now take place. May 29
18:01:58.838: IPSEC(initialize_sas): , (key eng. msg.) src= 209.165.201.5, dest= 209.165.201.6,
src_proxy= 192.168.10.0/255.255.255.0/0/0 (type=4), dest_proxy= 10.48.66.0/255.255.254.0/0/0
(type=4), protocol= ESP, transform= esp-des esp-md5-hmac , lifedur= 3600s and 4608000kb, spi=
0x217F07D7(561973207), conn_id= 51, keysize= 0, flags= 0x4 !--- IPsec SAs are now initialized
and encrypted !--- communication can now take place. May 29 18:01:58.838: IPSEC(create_sa): sa
created, (sa) sa_dest= 209.165.201.5, sa_prot= 50, sa_spi= 0xC9B423E7(3384026087), sa_trans=
esp-des esp-md5-hmac , sa_conn_id= 50 May 29 18:01:58.838: IPSEC(create_sa): sa created, (sa)
sa_dest= 209.165.201.6, sa_prot= 50, sa_spi= 0x217F07D7(561973207), sa_trans= esp-des esp-md5-
hmac , sa_conn_id= 51 !--- Observe that two IPsec SAs are created. !--- Recollect that IPsec SAs
are bidirectional. triana# triana# triana# triana#show crypto isakmp sa
```

dst	src	state	conn-id	slot
209.165.201.5	209.165.201.6	QM_IDLE	1	0

```
triana#show crypto ipsec sa
```

#### interface: Vlan 1

```
Crypto map tag: mymap, local addr. 209.165.201.5
```

```
local ident (addr/mask/prot/port): (192.168.10.0/255.255.255.0/0/0)
remote ident (addr/mask/prot/port): (10.48.66.0/255.255.254.0/0/0)
current_peer: 209.165.201.6
```

```
PERMIT, flags={origin_is_acl,}
```

```
#pkts encaps: 4, #pkts encrypt: 4, #pkts digest 4
```

```
#pkts decaps: 4, #pkts decrypt: 4, #pkts verify 4
```

```
#pkts compressed: 0, #pkts decompressed: 0
```

```
#pkts not compressed: 0, #pkts compr. failed: 0, #pkts decompress failed: 0
```

```
#send errors 0, #recv errors 0
```

```
local crypto endpt.: 209.165.201.5, remote crypto endpt.: 209.165.201.6
```

```
path mtu 1500, media mtu 1500
```

```
current outbound spi: 217F07D7
```

```
inbound esp sas:
```

```
spi: 0xC9B423E7(3384026087)
```

```
transform: esp-des esp-md5-hmac ,
```

```
in use settings ={Tunnel, }
```

```
slot: 0, conn id: 50, flow_id: 1, crypto map: mymap
```

```
sa timing: remaining key lifetime (k/sec): (4607998/3536)
```

```
IV size: 8 bytes
```

```
replay detection support: Y
```

```
inbound ah sas:
```

```
inbound pcg sas:
```

```
outbound esp sas:
```

```
spi: 0x217F07D7(561973207)
```

```
transform: esp-des esp-md5-hmac ,
```

```
in use settings ={Tunnel, }
```

```
slot: 0, conn id: 51, flow_id: 2, crypto map: mymap
```

```
sa timing: remaining key lifetime (k/sec): (4607999/3536)
```

```
IV size: 8 bytes
```

```
replay detection support: Y
```

```
outbound ah sas:
```

```
outbound pcg sas:
```

triana#

## Router del Cisco IOS

brussels#**show debug**

Cryptographic Subsystem:

Crypto ISAKMP debugging is on

Crypto Engine debugging is on

Crypto IPSEC debugging is on

brussels#p

Protocol [ip]:

Target IP address: 192.168.10.5

Repeat count [5]:

Datagram size [100]:

Timeout in seconds [2]:

Extended commands [n]: y

Source address or interface: fastethernet0/0

Type of service [0]:

Set DF bit in IP header? [no]:

Validate reply data? [no]:

Data pattern [0xABCD]:

Loose, Strict, Record, Timestamp, Verbose[none]:

Sweep range of sizes [n]:

Type escape sequence to abort.

Sending 5, 100-byte ICMP Echos to 192.168.10.5, timeout is 2 seconds:

```
May 29 18:01:54.285: IPSEC(sa_request): ,
  (key eng. msg.) src= 209.165.201.6, dest= 209.165.201.5,
  src_proxy= 10.48.66.0/255.255.254.0/0/0 (type=4),
  dest_proxy= 192.168.10.0/255.255.255.0/0/0 (type=4),
  protocol= ESP, transform= esp-des esp-md5-hmac ,
  lifedur= 3600s and 4608000kb,
  spi= 0x217F07D7(561973207), conn_id= 0, keysize= 0, flags= 0x4004
May 29 18:01:54.285: ISAKMP: received ke message (1/1)
May 29 18:01:54.285: ISAKMP: local port 500, remote port 500
May 29 18:01:54.289: ISAKMP (0:1): beginning Main Mode exchange
May 29 18:01:54.289: ISAKMP (1): sending packet to 209.165.201.5 (I) MM_NO_STATE
May 29 18:01:54.461: ISAKMP (1): received packet from 209.165.201.5 (I) MM_NO_STATE
May 29 18:01:54.461: ISAKMP (0:1): processing SA payload. message ID = 0
May 29 18:01:54.461: ISAKMP (0:1): Checking ISAKMP transform 1
  against priority 10 policy
May 29 18:01:54.465: ISAKMP:      encryption DES-CBC
May 29 18:01:54.465: ISAKMP:      hash SHA
May 29 18:01:54.465: ISAKMP:      default group 1
May 29 18:01:54.465: ISAKMP:      auth pre-share
May 29 18:01:54.465: ISAKMP (0:1): atts are acceptable. Next payload is 0
May 29 18:01:54.465: CryptoEngine0: generate alg parameter
May 29 18:01:54.637: CRYPTO_ENGINE: Dh phase 1 status: 0
May 29 18:01:54.637: CRYPTO_ENGINE: Dh phase 1 status: 0
May 29 18:01:54.637: ISAKMP (0:1): SA is doing pre-shared key authentication
May 29 18:01:54.637: ISAKMP (1): SA is doing pre-shared key authentication using
  id type ID_IPV4_ADDR
May 29 18:01:54.641: ISAKMP (1): sending packet to 209.165.201.5 (I) MM_SA_SETUP
May 29 18:01:54.805: ISAKMP (1): received packet from 209.165.201.5 (I) MM_SA_SETUP
May 29 18:01:54.805: ISAKMP (0:1): processing KE payload. message ID = 0
May 29 18:01:54.805: CryptoEngine0: generate alg parameter
May 29 18:01:55.021: ISAKMP (0:1): processing NONCE payload. messa!!!!
Success rate is 80 percent (4/5), round-trip min/avg/max = 20/21/24 ms
brussels#ge ID = 0
May 29 18:01:55.021: CryptoEngine0: create ISAKMP SKEYID for conn id 1
May 29 18:01:55.025: ISAKMP (0:1): SKEYID state generated
```

May 29 18:01:55.029: ISAKMP (0:1): processing vendor id payload  
May 29 18:01:55.029: ISAKMP (0:1): speaking to another IOS box!  
May 29 18:01:55.029: ISAKMP (1): ID payload  
    next-payload : 8  
    type : 1  
    protocol : 17  
    port : 500  
    length : 8  
May 29 18:01:55.029: ISAKMP (1): Total payload length: 12  
May 29 18:01:55.029: CryptoEngine0: generate hmac context for conn id 1  
May 29 18:01:55.033: ISAKMP (1): sending packet to 209.165.201.5 (I) MM\_KEY\_EXCH  
May 29 18:01:55.049: ISAKMP (1): received packet from 209.165.201.5 (I) MM\_KEY\_EXCH  
May 29 18:01:55.053: ISAKMP (0:1): processing ID payload. message ID = 0  
May 29 18:01:55.053: ISAKMP (0:1): processing HASH payload. message ID = 0  
May 29 18:01:55.053: CryptoEngine0: generate hmac context for conn id 1  
May 29 18:01:55.057: ISAKMP (0:1): SA has been authenticated with 209.165.201.5  
*!--- Phase 1 is completed and Phase 2 starts now.* May 29 18:01:55.057: ISAKMP (0:1): beginning Quick Mode exchange, M-ID of -1809462101 May 29 18:01:55.061: CryptoEngine0: generate hmac context for conn id 1 May 29 18:01:55.065: ISAKMP (1): sending packet to 209.165.201.5 (I) QM\_IDLE May 29 18:01:55.065: CryptoEngine0: clear dh number for conn id 1 May 29 18:01:55.337: ISAKMP (1): received packet from 209.165.201.5 (I) QM\_IDLE May 29 18:01:55.341: CryptoEngine0: generate hmac context for conn id 1 May 29 18:01:55.345: ISAKMP (0:1): processing SA payload. message ID = -1809462101 May 29 18:01:55.345: ISAKMP (0:1): Checking IPsec proposal 1 May 29 18:01:55.345: ISAKMP: transform 1, ESP\_DES May 29 18:01:55.345: ISAKMP: attributes in transform: May 29 18:01:55.345: ISAKMP: encaps is 1 May 29 18:01:55.345: ISAKMP: SA life type in seconds May 29 18:01:55.345: ISAKMP: SA life duration (basic) of 3600 May 29 18:01:55.345: ISAKMP: SA life type in kilobytes May 29 18:01:55.345: ISAKMP: SA life duration (VPI) of 0x0 0x46 0x50 0x0 May 29 18:01:55.349: ISAKMP: authenticator is HMAC-MD5 May 29 18:01:55.349: validate proposal 0  
**May 29 18:01:55.349: ISAKMP (0:1): atts are acceptable.**  
May 29 18:01:55.349: IPSEC(validate\_proposal\_request): proposal part #1,  
*!--- After negotiating the attributes, IKE asks IPsec to !--- validate the proposal.* (key eng. msg.) dest= 209.165.201.5, src= 209.165.201.6, dest\_proxy= 192.168.10.0/255.255.255.0/0/0 (type=4), src\_proxy= 10.48.66.0/255.255.254.0/0/0 (type=4), protocol= ESP, transform= esp-des esp-md5-hmac , lifedur= 0s and 0kb, spi= 0x0(0), conn\_id= 0, keysize= 0, flags= 0x4 *!--- spi is still zero because SAs have not been set.* May 29 18:01:55.353: validate proposal request 0 May 29 18:01:55.357: ISAKMP (0:1): processing NONCE payload. message ID = -1809462101 May 29 18:01:55.357: ISAKMP (0:1): processing ID payload. message ID = -1809462101 May 29 18:01:55.357: ISAKMP (0:1): processing ID payload. message ID = -1809462101 May 29 18:01:55.357: CryptoEngine0: generate hmac context for conn id 1 May 29 18:01:55.361: ipsec allocate flow 0 May 29 18:01:55.361: ipsec allocate flow 0 **May 29 18:01:55.369: ISAKMP (0:1): Creating IPsec SAs**  
May 29 18:01:55.369: inbound SA from 209.165.201.5 to 209.165.201.6 (proxy 192.168.10.0 to 10.48.66.0)  
May 29 18:01:55.369: has spi 561973207 and conn\_id 2000 and flags 4  
May 29 18:01:55.373: lifetime of 3600 seconds  
May 29 18:01:55.373: lifetime of 4608000 kilobytes  
May 29 18:01:55.373: outbound SA from 209.165.201.6 to 209.165.201.5 (proxy 10.48.66.0 to 192.168.10.0)  
May 29 18:01:55.373: has spi -910941209 and conn\_id 2001 and flags 4  
May 29 18:01:55.373: lifetime of 3600 seconds  
May 29 18:01:55.373: lifetime of 4608000 kilobytes  
May 29 18:01:55.377: ISAKMP (1): sending packet to 209.165.201.5 (I) QM\_IDLE  
May 29 18:01:55.377: ISAKMP (0:1): deleting node -1809462101 error FALSE reason ""  
May 29 18:01:55.381: IPSEC(key\_engine): got a queue event...  
May 29 18:01:55.381: IPSEC(initialize\_sas): ,  
    (key eng. msg.) dest= 209.165.201.6, src= 209.165.201.5,  
    dest\_proxy= 10.48.66.0/255.255.254.0/0/0 (type=4),  
    src\_proxy= 192.168.10.0/255.255.255.0/0/0 (type=4),  
    protocol= ESP, transform= esp-des esp-md5-hmac ,  
    lifedur= 3600s and 4608000kb,  
    spi= 0x217F07D7(561973207), conn\_id= 2000, keysize= 0, flags= 0x4  
*!--- IPsec SAs are now initialized and encrypted !--- communication can now take place.* May 29 18:01:55.381: IPSEC(initialize\_sas): , (key eng. msg.)src= 209.165.201.6, dest= 209.165.201.5, src\_proxy= 10.48.66.0/255.255.254.0/0/0 (type=4), dest\_proxy= 192.168.10.0/255.255.255.0/0/0 (type=4), protocol= ESP, transform= esp-des esp-md5-hmac , lifedur= 3600s and 4608000kb, spi=

```
0xC9B423E7(3384026087), conn_id= 2001, keysize= 0, flags= 0x4 !--- IPSec SAs are now initialized
and encrypted !--- communication can now take place. May 29 18:01:55.385: IPSEC(create_sa): sa
created, (sa) sa_dest= 209.165.201.6, sa_prot= 50, sa_spi= 0x217F07D7(561973207), sa_trans= esp-
des esp-md5-hmac , sa_conn_id= 2000 May 29 18:01:55.385: IPSEC(create_sa): sa created, (sa)
sa_dest= 209.165.201.5, sa_prot= 50, sa_spi= 0xC9B423E7(3384026087), sa_trans= esp-des esp-md5-
hmac , sa_conn_id= 2001 !--- Observe that two IPSec SAs are created. !--- Recollect that IPSec
SAs are bidirectional. brussels# brussels#show crypto isakmp sa
      dst          src          state          conn-id  slot
209.165.201.5    209.165.201.6    QM_IDLE              1        0
```

```
brussels#show crypto ipsec sa
```

```
interface: FastEthernet0/1
```

```
  Crypto map tag: vpnmap, local addr. 209.165.201.6
```

```
local ident (addr/mask/prot/port): (10.48.66.0/255.255.254.0/0/0)
remote ident (addr/mask/prot/port): (192.168.10.0/255.255.255.0/0/0)
current_peer: 209.165.201.5
  PERMIT, flags={origin_is_acl,}
#pkts encaps: 4, #pkts encrypt: 4, #pkts digest 4
#pkts decaps: 4, #pkts decrypt: 4, #pkts verify 4
#pkts compressed: 0, #pkts decompressed: 0
#pkts not compressed: 0, #pkts compr. failed: 0, #pkts decompress failed: 0
#send errors 1, #recv errors 0
```

```
local crypto endpt.: 209.165.201.6, remote crypto endpt.: 209.165.201.5
path mtu 1500, media mtu 1500
current outbound spi: C9B423E7
```

```
inbound esp sas:
```

```
spi: 0x217F07D7(561973207)
  transform: esp-des esp-md5-hmac ,
  in use settings = {Tunnel, }
  slot: 0, conn id: 2000, flow_id: 1, crypto map: vpnmap
  sa timing: remaining key lifetime (k/sec): (4607998/3560)
  IV size: 8 bytes
  replay detection support: Y
```

```
inbound ah sas:
```

```
inbound pcp sas:
```

```
outbound esp sas:
```

```
spi: 0xC9B423E7(3384026087)
  transform: esp-des esp-md5-hmac ,
  in use settings = {Tunnel, }
  slot: 0, conn id: 2001, flow_id: 2, crypto map: vpnmap
  sa timing: remaining key lifetime (k/sec): (4607999/3560)
  IV size: 8 bytes
  replay detection support: Y
```

```
outbound ah sas:
```

```
outbound pcp sas:
```

```
brussels#
```

## [Información Relacionada](#)

- [Página de soporte de IPSec](#)
- [Introducción a IPSec](#)



- [Soporte Técnico - Cisco Systems](#)