

Risolvere i problemi relativi all'errore: Impossibile recuperare i dati della licenza in Unity Connection Speechview

Sommario

[Introduzione](#)

[Prerequisiti](#)

[Requisiti](#)

[Componenti usati](#)

[Analisi log](#)

[Soluzione](#)

Introduzione

Questo documento descrive le azioni da eseguire quando Cisco Unity Connection (CUC) versione 12.5(1) sull'interfaccia utente grafica (GUI) visualizza il messaggio di errore: **Impossibile recuperare i dati della licenza. Per ulteriori informazioni, vedere i registri diagnostici di CuSImSvr** all'indirizzo enable/register the Speechview service.

Prerequisiti

Requisiti

Cisco raccomanda la conoscenza dei seguenti argomenti:

- Cisco Unity Connection.
- Funzione Cisco Speechview.

Componenti usati

Il documento può essere consultato per tutte le versioni software o hardware.

Le informazioni discusse in questo documento fanno riferimento a dispositivi usati in uno specifico ambiente di emulazione. Su tutti i dispositivi menzionati nel documento la configurazione è stata ripristinata ai valori predefiniti. Se la rete è operativa, valutare attentamente eventuali conseguenze derivanti dall'uso dei comandi.

Analisi log

Quando viene visualizzato il messaggio di errore, è necessario raccogliere i log di **CuSImSvr** (Connection Smart License Manager Server in RTMT) per analizzare ulteriormente il problema.

Il processo ha inizio:

```
19:19:03.395 |8060,,,CuSlmSvr,3,18-08-2020 INFO [SLM-12]
com.cisco.unity.slm.common.SmartLicenseUtility#isSttEnabled - STT Enabled Status :1
19:19:03.395 |8060,,,CuSlmSvr,3,18-08-2020 DEBUG [SLM-12]
com.cisco.unity.slm.dal.DbCrudOperationsImpl#get - Exceute Query : select sttdataacquired from
vw_elmlicensestatus
19:19:03.395 |8060,,,CuSlmSvr,3,18-08-2020 DEBUG [SLM-12]
com.cisco.unity.slm.dal.DbHelper#getDbConnection - Getting DB connection for executing query
19:19:03.396 |8060,,,CuSlmSvr,3,18-08-2020 DEBUG [SLM-12]
com.cisco.unity.slm.dal.DbHelper#executeQuery - Query executed succesfully
19:19:03.396 |8060,,,CuSlmSvr,3,18-08-2020 DEBUG [SLM-12]
com.cisco.unity.slm.dal.DbHelper#closeResources - closeResources Statement : DbHelper
19:19:03.396 |8060,,,CuSlmSvr,3,18-08-2020 INFO [SLM-12]
com.cisco.unity.slm.common.SmartLicenseUtility#isSttDataAcquired - STTDataAquired Status :0
19:19:03.396 |8060,,,CuSlmSvr,3,18-08-2020 DEBUG [SLM-12]
com.cisco.unity.slm.dal.DbCrudOperationsImpl#get - Exceute Query : select count from
UnityDirDb:vw_LicenseStatusCount where tagname='LicSTTProSubscribersMax'
19:19:03.397 |8060,,,CuSlmSvr,3,18-08-2020 DEBUG [SLM-12]
com.cisco.unity.slm.dal.DbHelper#getDbConnection - Getting DB connection for executing query
19:19:03.402 |8060,,,CuSlmSvr,3,18-08-2020 DEBUG [SLM-12]
com.cisco.unity.slm.dal.DbHelper#executeQuery - Query executed succesfully
19:19:03.402 |8060,,,CuSlmSvr,3,18-08-2020 DEBUG [SLM-12]
com.cisco.unity.slm.dal.DbHelper#closeResources - closeResources Statement : DbHelper
19:19:03.402 |8060,,,CuSlmSvr,3,18-08-2020 DEBUG [SLM-12]
com.cisco.unity.slm.core.SmartLicenseManager#fetchThirdPartyKeys - Values of parameter passed in
requestThirdPartyKeys method :: isLive :: true isComplianceRequired :: true
thirdPartyKeysParamArr [ThirdPartyKeysParam [id=2017844434, keyId=0, name=VOUCHER_CODE,
value=regid.2017-04.com.cisco.CUC_SpeechView,12.0_946cef06-3332-4037-9bd3-e4705c2c7ebb,
routing=NUANCE, action=GENERATE]]
19:19:03.403 |8060,,,CuSlmSvr,4,18-08-2020 DEBUG [SLM-12]
com.cisco.nesla.plugin.DefaultCrypto#parseCertificate - getSubjectDN().getName: CN=Cisco Unity
Connection,2.5.4.5=#132434643437646630342d616538392d346466362d626331352d643137633161336631353366
,O=Cisco
19:19:03.403 |8060,,,CuSlmSvr,4,18-08-2020 DEBUG [SLM-12]
com.cisco.nesla.plugin.DefaultCrypto#parseCertificate - getSubjectDN().toString: CN=Cisco Unity
Connection, SERIALNUMBER=4d47df04-ae89-4df6-bc15-d17c1a3f153f, O=Cisco
19:19:03.403 |8060,,,CuSlmSvr,3,18-08-2020 DEBUG [SLM-12]
com.cisco.unity.slm.crypto.CustomCrypto#extractSubjectAlternativeNames - Entered
extractSubjectAlternativeNames(null)
19:19:03.403 |8060,,,CuSlmSvr,3,18-08-2020 DEBUG [SLM-12]
com.cisco.unity.slm.crypto.CustomCrypto#getSUDIList - Collection<List<?>> is null, exiting -
extractSubjectAlternativeNames
19:19:03.403 |8060,,,CuSlmSvr,3,18-08-2020 DEBUG [SLM-12]
com.cisco.unity.slm.crypto.CustomCrypto#extractSubjectAlternativeNames - returning sudiList :
[], exiting extractSubjectAlternativeNames(Collection<List<?>>)
19:19:03.403 |8060,,,CuSlmSvr,3,18-08-2020 DEBUG [SLM-12]
com.cisco.unity.slm.crypto.CustomCrypto#extractCertificateType - Entered
extractCertificateType(subjectDnName = CN=Cisco Unity Connection, SERIALNUMBER=4d47df04-ae89-
4df6-bc15-d17c1a3f153f, O=Cisco)
19:19:03.403 |8060,,,CuSlmSvr,3,18-08-2020 INFO [SLM-12]
com.cisco.unity.slm.crypto.CustomCrypto#extractCertificateType - Matched subjectDnName -
CN=Cisco Unity Connection, SERIALNUMBER=4d47df04-ae89-4df6-bc15-d17c1a3f153f, O=Cisco,
pattern1=CN=.*SERIALNUMBER.*, match1=true, pattern2=O=.*SERIALNUMBER=.*CN=.*, match2=false,
returning certificate = ID_CERT
19:19:03.404 |8060,,,CuSlmSvr,4,18-08-2020 DEBUG [SLM-12]
com.cisco.nesla.plugin.DefaultCrypto#parseCertificate - getSubjectDN().getName: CN=MMI
Signer,O=Cisco
19:19:03.404 |8060,,,CuSlmSvr,4,18-08-2020 DEBUG [SLM-12]
com.cisco.nesla.plugin.DefaultCrypto#parseCertificate - getSubjectDN().toString: CN=MMI Signer,
O=Cisco
```

Il server richiede il valore VOUCHER_CODE:

```
19:19:03.417 |8060,,CuSlmSvr,4,18-08-2020 DEBUG [SLM-12]
com.cisco.nesla.agent.impl.MessageComposer#composeTPK - composedMesg: {"signature":{"type":"SHA-256","value":"Pf9PO06+YzchhKnZ3Q0SMamccnS/FPcoRSTdhJNyJkr0EHeDm3bU3FzUqneuKZuw4vfP3nsGP0OzwcY8tzOszcoK3JJDpi5y4wPm2IijLwGZSx0eQVatt7kXxbZ5PU25y4ZKY/egd1hANOn3E71cLAXAgmgNR5A2exxrgkLt5pHolmAVTSaDGag0+YqKRXxOTTyJPs1pmeIj6z7ELwWlwBD4QQANYdFj+leHChq9figxcE1ftcXHn1dy2nWl9musbfZu9B+Vb/32kusoRq/uEuxn2YbBQ3wsjq5yLQM8iDNzF7vzcZC1JsgyO3qn3jxzRYPrfhThr2LY6WgCRcJ37g=="}, "credential":null, "request":{"header":{"version":"1.1","locale":"en_US.UTF-8"},"sudi":{"suvi":null,"uuid":"0cd5739043bf4318aae467eacec7dbb9"},"host_identifier":null,"mac_address":null,"udi_pid":"Cisco Unity Connection"},"udi_serial_number":"0cd5739043bf4318aae467eacec","udi_vid":null},"timestamp":0,"nonce":"7648446339161391345","request_type":"THIRD_PARTY_KEY","agent_actions":null,"connect_info":null,"product_instance_identifier":"4d47df04-ae89-4df6-bc15-d17c1a3f153f","id_cert_serial_number":"16451298","signing_cert_serial_number":"3"},"nonce":"7648446339161391345","request_data":{"sudi":{"suvi":null,"uuid":"0cd5739043bf4318aae467eacec7dbb9"},"host_identifier":null,"mac_address":null,"udi_pid":"Cisco Unity Connection"},"udi_serial_number":"0cd5739043bf4318aae467eacec","udi_vid":null},"timestamp":1597792743402,"nonce":"7648446339161391345","live":true,"data":[{"id":"2017844434","name":"VOUCHER_CODE","value":"regid.2017-04.com.cisco.CUC_SpeechView,12.0_946cef06-3332-4037-9bd3-e4705c2c7ebb"},"routing":"NUANCE","action":"GENERATE","key_id":0}],"product_instance_identifier":"4d47df04-ae89-4df6-bc15-d17c1a3f153f","compliance_required":true}}}
```

Il messaggio viene inviato al modulo CSM con la richiesta di recupero delle chiavi.

```
19:19:03.417 |8060,,CuSlmSvr,4,18-08-2020 DEBUG [SLM-12]
com.cisco.nesla.plugin.EmbeddedGCHCommunication#sendSCHMessage - in sendMessage(),
resetProfileHttpAddr to: https://tools.cisco.com/its/service/oddce/services/DDCEService
19:19:03.417 |8060,,CuSlmSvr,4,18-08-2020 DEBUG [SLM-12]
com.cisco.nesla.plugin.EmbeddedGCHCommunication#sendSCHMessage - EmbeddedGCHCommunication
[callHomeProps={devUrl=https://tools.cisco.com/its/service/oddce/services/DDCEService},
url=https://tools.cisco.com/its/service/oddce/services/DDCEService,
transportMode=TransportCallHome, parentFactory=com.cisco.nesla.agent.SmartAgentFactory@158cfc5,
gchClient=com.callhome.service.CallHome@cb4b0, SA_PROFILE=null, dualUrl=null]
19:19:03.417 |8060,,CuSlmSvr,4,18-08-2020 DEBUG [SLM-12]
com.cisco.nesla.plugin.EmbeddedGCHCommunication#sendSCHMessage - effective Authenticator URL:
https://tools.cisco.com/its/service/oddce/services/DDCEService
19:19:03.417 |8060,,CuSlmSvr,6,18-08-2020 INFO [SLM-12]
com.callhome.module.config_manager.ProfileManager#resetProfileHttpAddr - reset http url Cisco-
TAC-1 for profile https://tools.cisco.com/its/service/oddce/services/DDCEService
19:19:03.418 |8060,,CuSlmSvr,6,18-08-2020 DEBUG [SLM-12]
com.callhome.module.message_processor.BaseMessage#setInternalReqData - Set request data:
Session_To = http://tools.cisco.com/neddce/services/DDCEService
19:19:03.422 |8060,,CuSlmSvr,6,18-08-2020 DEBUG [SLM-12]
com.callhome.module.message_processor.BaseMessage#setInternalReqData - Set request data:
Attachment_Data = {"signature":{"type":"SHA-256","value":"Pf9PO06+YzchhKnZ3Q0SMamccnS/FPcoRSTdhJNyJkr0EHeDm3bU3FzUqneuKZuw4vfP3nsGP0OzwcY8tzOszcoK3JJDpi5y4wPm2IijLwGZSx0eQVatt7kXxbZ5PU25y4ZKY/egd1hANOn3E71cLAXAgmgNR5A2exxrgkLt5pHolmAVTSaDGag0+YqKRXxOTTyJPs1pmeIj6z7ELwWlwBD4QQANYdFj+leHChq9figxcE1ftcXHn1dy2nWl9musbfZu9B+Vb/32kusoRq/uEuxn2YbBQ3wsjq5yLQM8iDNzF7vzcZC1JsgyO3qn3jxzRYPrfhThr2LY6WgCRcJ37g=="}, "credential":null, "request":{"header":{"version":"1.1","locale":"en_US.UTF-8"},"sudi":{"suvi":null,"uuid":"0cd5739043bf4318aae467eacec7dbb9"},"host_identifier":null,"mac_address":null,"udi_pid":"Cisco Unity Connection"},"udi_serial_number":"0cd5739043bf4318aae467eacec","udi_vid":null},"timestamp":0,"nonce":"7648446339161391345","request_type":"THIRD_PARTY_KEY","agent_actions":null,"connect_info":null,"product_instance_identifier":"4d47df04-ae89-4df6-bc15-d17c1a3f153f","id_cert_serial_number":"16451298","signing_cert_serial_number":"3"},"nonce":"7648446339161391345","request_data":{"sudi":{"suvi":null,"uuid":"0cd5739043bf4318aae467eacec7dbb9"},"host_identifier":null,"mac_address":null,"udi_pid":"Cisco Unity Connection"},"udi_serial_number":"0cd5739043bf4318aae467eacec","udi_vid":null},"timestamp":1597792743402,"nonce":"7648446339161391345","live":true,
```

```
\\\"data\\\": [{\\\"id\\\": 2017844434, \\\"name\\\": \\\"VOUCHER_CODE\\\", \\\"value\\\": \\\"regid.2017-04.com.cisco.CUC_SpeechView,12.0_946cef06-3332-4037-9bd3-e4705c2c7ebb\\\", \\\"routing\\\": \\\"NUANCE\\\", \\\"action\\\": \\\"GENERATE\\\", \\\"key_id\\\": 0}], \\\"product_instance_identifier\\\": \\\"4d47df04-ae89-4df6-bc15-d17c1a3f153f\\\", \\\"compliance_required\\\": true} \\\"}]
19:19:03.422 |8060,,,CuSlmSvr,6,18-08-2020 INFO [SLM-12]
com.callhome.module.data.statistics.StatisticsMgr#updateSLStatistics - update Smart Lincense Statistics Data
19:19:03.429 |8060,,,CuSlmSvr,6,18-08-2020 INFO [SLM-12]
com.callhome.module.message_processor.BaseMessage#makeAmlBlockAttachment - create attachment for smart_licensing_data with type inline
```

La risposta viene quindi elaborata

```
19:19:04.741 |8060,,,CuSlmSvr,6,18-08-2020 DEBUG [SLM-12]
com.callhome.module.message_processor.BaseMessage#processResponseMessage - Process response message
```

L'errore viene visualizzato

```
19:19:04.789 |8060,,,CuSlmSvr,3,18-08-2020 ERROR [SLM-12]
com.cisco.unity.slm.rpc.server.SlmRpcHandler#fetchThirdPartyKeys - Exception occurred while fetching Third party key from Nesla - LicenseResponse status code: FAILED, message: Product Instance is not consuming this tag :

19:19:04.789
|8060,,,CuSlmSvr,3,com.cisco.nesla.agent.impl.AsyncResponseProcessor.processTPK(AsyncResponseProcessor.java:676)
19:19:04.789
|8060,,,CuSlmSvr,3,com.cisco.nesla.agent.impl.AsyncRequestProcessor.sendTPK(AsyncRequestProcessor.java:427)
19:19:04.789
|8060,,,CuSlmSvr,3,com.cisco.nesla.agent.impl.SmartAgentImpl.requestThirdPartyKeys(SmartAgentImpl.java:1221)
19:19:04.789
|8060,,,CuSlmSvr,3,com.cisco.unity.slm.core.SmartLicenseManager.fetchThirdPartyKeys(SmartLicenseManager.java:1206)
19:19:04.789
|8060,,,CuSlmSvr,3,com.cisco.unity.slm.rpc.server.SlmRpcHandler.fetchThirdPartyKeys(SlmRpcHandler.java:882)
19:19:04.789 |8060,,,CuSlmSvr,3,sun.reflect.NativeMethodAccessorImpl.invoke0(Native Method)
19:19:04.790
|8060,,,CuSlmSvr,3,sun.reflect.NativeMethodAccessorImpl.invoke(NativeMethodAccessorImpl.java:57)
19:19:04.790
|8060,,,CuSlmSvr,3,sun.reflect.DelegatingMethodAccessorImpl.invoke(DelegatingMethodAccessorImpl.java:43)
19:19:04.790 |8060,,,CuSlmSvr,3,java.lang.reflect.Method.invoke(Method.java:606)
19:19:04.790
|8060,,,CuSlmSvr,3,com.retrogui.dualrpc.common.RpcWorker.processRpcCallMessage(RpcWorker.java:231)
19:19:04.790 |8060,,,CuSlmSvr,3,com.retrogui.dualrpc.common.RpcWorker.run(RpcWorker.java:75)
19:19:04.790 |8060,,,CuSlmSvr,3,18-08-2020 DEBUG [SLM-12]
com.retrogui.dualrpc.common.RpcWorker#processRpcCallMessage - 29341551:Outbound message id=s79970-1597791156498-12 contains the rpc results for originating message id=c2383379-1597792743384-1

19:19:04.790 |8056,,,CuSlmSvr,3,18-08-2020 DEBUG
[com.retrogui.messageserver.common.OutboundMessageHandler:hashCode=564416:sessionId=29341551]
com.retrogui.messageserver.common.OutboundMessageHandler#run - 29341551:Outgoing message size. Message id=s79970-1597791156498-12, size=684 bytes
```

La richiesta non riuscita è visibile

```
19:10:22.430 |2334,,,CuSlmSvr,3,18-08-2020 DEBUG [SLM-11]
com.cisco.unity.slm.core.SmartLicenseManager#requestLicenses - License Usage corresponding to
CUC_SpeechView is 0
19:10:22.430 |2334,,,CuSlmSvr,4,18-08-2020 DEBUG [SLM-11]
com.cisco.nesla.agent.impl.SmartAgentImpl#requestEntitlement - enter requestEntitlement()
19:10:22.430 |2334,,,CuSlmSvr,4,18-08-2020 DEBUG [SLM-11]
com.cisco.nesla.agent.impl.SmartAgentImpl#requestEntitlement - entitlementTag: regid.2017-
04.com.cisco.CUC_SpeechView,12.0_946cef06-3332-4037-9bd3-e4705c2c7ebb
19:10:22.430 |2334,,,CuSlmSvr,4,18-08-2020 DEBUG [SLM-11]
com.cisco.nesla.agent.impl.SmartAgentImpl#requestEntitlement - count: 0
19:10:22.430 |2334,,,CuSlmSvr,4,18-08-2020 DEBUG [SLM-11]
com.cisco.nesla.agent.impl.SmartAgentImpl#releaseEntitlement - enter releaseEntitlement()
19:10:22.430 |2334,,,CuSlmSvr,4,18-08-2020 DEBUG [SLM-11]
com.cisco.nesla.agent.impl.SmartAgentImpl#releaseEntitlement - entitlementTag: regid.2017-
04.com.cisco.CUC_SpeechView,12.0_946cef06-3332-4037-9bd3-e4705c2c7ebb
19:10:22.430 |2334,,,CuSlmSvr,4,18-08-2020 DEBUG [SLM-11]
com.cisco.nesla.agent.impl.AsyncRequestProcessor#sendAUTH - queue auth message, status: true
19:10:22.430 |2334,,,CuSlmSvr,4,18-08-2020 DEBUG [SLM-11]
com.cisco.nesla.agent.impl.SmartAgentImpl#releaseEntitlement - exit requestEntitlement()
```

Soluzione

In genere, è possibile superare l'errore **Impossibile recuperare i dati della licenza** emettendo un nuovo token per il server CUC nel satellite e registrando nuovamente l'intero server.

Quindi, tentare i passi successivi e provare più avanti:

Abilitare la **trascrizione SpeechView dei messaggi vocali nella classe di servizio**: I membri della classe di servizio possono visualizzare le trascrizioni dei messaggi vocali utilizzando un client IMAP configurato per accedere ai messaggi utente.

Procedura:

Passaggio 1. In Amministrazione di Cisco Unity Connection, espandere **Class of Service** e selezionare **Class of Service**.

Passaggio 2. Nella pagina Cerca classe di servizio, selezionare la **classe di servizio** in cui si desidera abilitare la trascrizione SpeechView o crearne una nuova selezionando **Aggiungi nuovo**.

Passaggio 3. Nella pagina **Modifica classe di servizio**, in **Funzionalità di gestione licenze**, selezionare **Usa servizio di trascrizione SpeechView standard** per abilitare la trascrizione standard. Analogamente, è possibile selezionare l'opzione **Usa servizio di trascrizione SpeechView Pro** per abilitare la trascrizione professionale.

Passaggio 4. Selezionare le opzioni applicabili nella sezione servizio di trascrizione e selezionare **Salva**. Per informazioni su ogni campo, vedere **Guida > Questa pagina**.

Il messaggio di errore rilevato deve scomparire dopo l'esecuzione dei passaggi precedenti ed è possibile continuare con la registrazione del servizio Speechview.