

Installatie van telefoon met landinstellingen op IP-telefoon 7841

Inhoud

[Inleiding](#)

[Voorwaarden](#)

[Vereisten](#)

[Gebruikte componenten](#)

[Achtergrondinformatie](#)

[Configureren](#)

[Configuraties](#)

[Verifiëren](#)

[Problemen oplossen](#)

Inleiding

Dit document beschrijft hoe u aan een lokale telefoon een 7841 Series IP-telefoon kunt installeren.

Voorwaarden

Vereisten

Er zijn geen specifieke vereisten van toepassing op dit document.

Gebruikte componenten

De informatie in dit document is gebaseerd op de volgende software- en hardware-versies:

- Cisco Unified Communications Manager 12.x
- Cisco IP-telefoon 7841

De informatie in dit document is gebaseerd op de apparaten in een specifieke laboratoriumomgeving. Alle apparaten die in dit document worden beschreven, hadden een opgeschoonde (standaard)configuratie. Als uw netwerk levend is, zorg er dan voor dat u de mogelijke impact van om het even welke opdracht begrijpt.

Achtergrondinformatie

Cisco Unified Communications Manager (CUCM) biedt ondersteuning voor systeemgedefinieerde localisatie voor 12 talen inclusief Engels en 16 landen met inbegrip van de Verenigde Staten. Netwerklocaties geven landspecifieke tonen en -mazen aan; de gebruikerslocales specificeren de taal die voor tekstdisplays moet worden gebruikt .

Configureren

Configuraties

Dit is de procedure om een harde fabrieksreset van de telefoon uit te voeren:

Stap 1. Download het lokale toetsenbord van de Cisco website.

Downloads Home / Collaboration Endpoints / IP Phones / IP Phone 7800 Series / IP Phone 7841 / Unified Communications Manager Endpoints Locale Installer- 12.1(1.1000)

IP Phone 7841
Release 12.1(1.1000)
Notifications
Related Links and Documentation
- No related links or documentation -

File Information	Release Date	Size	
Cisco Unified Communications Locale Installer 12.1.1.1000 Arabic (United Arab Emirates) for Cisco Unified IP Phones FW 12.1(1) po-locale-ar_AE-k3-12.1.1.1000-1.cop.sgn	27-MAR-2018	2.89 MB	↓ 🛒 📄
Cisco Unified Communications Locale Installer 12.1.1.1000 Arabic (Bahrain) for Cisco Unified IP Phones FW 12.1(1) po-locale-ar_BH-k3-12.1.1.1000-1.cop.sgn	27-MAR-2018	2.88 MB	↓ 🛒 📄
Cisco Unified Communications Locale Installer 12.1.1.1000 Arabic (Algeria) for Cisco Unified IP Phones	27-MAR-2018	2.88 MB	↓ 🛒 📄

Stap 2. Navigeer naar OS-beheer > Software-upgrades > Installatie/upgrade.

Cisco Unified Operating System Administration
For Cisco Unified Communications Solutions

Show Settings Security Software Upgrades Services Help

Install/Upgrade
TFTP File Management
Install/Upgrade
Customized Logon Message
Branding

WARNING: It is recommended to perform a successful backup. Please verify backup configuration.

Cisco Unified Operating System Administration
System version: 12.0.0.99834-4
VMware Installation: 2 vCPU Intel(R) Xeon(R) CPU ES-2697A v4 @ 2.60GHz, disk 1: 110Gbytes, 8192Mbytes RAM, ERROR: UNSUPPORTED: Partitions unaligned
WARNING: DNS unreachable

User admin last logged in to this cluster on Friday, June 29, 2018 3:39:36 PM IST, to node 10.106.111.182, from 10.196.121.10 using HTTPS
User admin failed to log in 1 times!
Most recent failure Sunday, July 1, 2018 5:26:34 PM IST, to 10.106.111.182, from 10.65.43.63 using HTTPS

Copyright © 1999 - 2017 Cisco Systems, Inc.
All rights reserved.

This product contains cryptographic features and is subject to United States and local country laws governing import, export, transfer and use. Delivery of Cisco cryptographic products does not imply that exporters, distributors and users are responsible for compliance with U.S. and local country laws. By using this product you agree to comply with applicable laws and regulations. If you are unable to comply with applicable laws and regulations, you may not use this product.

A summary of U.S. laws governing Cisco cryptographic products may be found at our [Export Compliance Product Report](#) web site.

For information about Cisco Unified Communications Manager please visit our [Unified Communications System Documentation](#) web site.

For Cisco Technical Support please visit our [Technical Support](#) web site.

Stap 3. Zoals in de afbeelding wordt getoond, voert u de aanmeldingsgegevens voor de SFTP-server in.



Cisco Unified Operating System Administration


For Cisco Unified Communications Solutions

Show ▾ Settings ▾ Security ▾ Software Upgrades ▾ Services ▾ Help ▾

Software Installation/Upgrade


 Cancel  Next

- Status

 Status: Ready

- Software Location

Source*	<input type="text" value="Remote Filesystem"/>
Directory*	<input type="text" value="/"/>
Server*	<input type="text" value="192.168.0.5"/>
User Name*	<input type="text" value="cisco"/>
User Password*	<input type="password" value="*****"/>
Transfer Protocol*	<input type="text" value="SFTP"/>
SMTP Server	<input type="text"/>
Email Destination	<input type="text"/>

 *- indicates required item.

Stap 4. Selecteer het lokale toetsenbord in het uitrolmenu **Opties/upgrades** en klik op **Volgende**, zoals in de afbeelding. De lokale installatie start.

Cisco Unified Operating System Administration
For Cisco Unified Communications Solutions

Show ▾ Settings ▾ Security ▾ Software Upgrades ▾ Services ▾ Help ▾

Software Installation/Upgrade

Cancel Next

Status
Status: Ready

Software Location
Options/Upgrades* po-locale-ca_ES-k3-12.1.1.1000-1.cop.sgn

Invalid Upgrades

Option Names	
web.xml	Name does not match any filter pattern.
New	Name does not match any filter pattern.

Cancel Next

*- indicates required item.

5. Klik op **Volgende**, zoals in de afbeelding, nadat de **checksum details** is geverifieerd.

Cisco Unified Operating System Administration
For Cisco Unified Communications Solutions

Show ▾ Settings ▾ Security ▾ Software Upgrades ▾ Services ▾ Help ▾

Software Installation/Upgrade

Cancel Next

Status

Warning: To ensure the integrity of the installation file, please verify the MD5 hash value against the Cisco Systems web site

Warning: To ensure the integrity of the installation file, please verify the SHAS12 value against the Cisco Systems web site

Warning: You may need to stop some services before you install a locale. You may then restart those services after you complete the locale installation. Refer to your product-specific online help for locale installation details.

File Checksum Details

File	po-locale-ca_ES-k3-12.1.1.1000-1.cop.sgn
MD5 Hash Value	85:25:ce:23:15:64:f2:ed:25:59:f7:a0:38:d7:d6:4e
SHAS12 Value	

Cancel Next

*- indicates required item.

Stap 6. De installatie van het lokale toetsenbord is geslaagd

Cisco Unified Operating System Administration
For Cisco Unified Communications Solutions

Show Settings Security Software Upgrades Services Help

Software Installation/Upgrade

Install Another

Installation Status

File po-locale-ca_ES-k3-12.1.1.1000-1.cop.sgn
 Start Time Mon Jul 02 13:19:26 IST 2018
 Status Complete

Installation Log

```

[18/07/02_13:19:57] locale_install.sh: Publisher: Starting installdb...
/bin/su -l informix -s /bin/sh -c
"source /usr/local/cm/db/dblenv.bash /usr/local/cm ;
source /usr/local/cm/db/informix/local/ids.env ;
nice /usr/local/cm/bin/installdb -x /usr/local/cm/db/xml/xml"
    
```

Install Another

i *- indicates required item.

Stap 7. Reset de Cisco TFTP-service op alle knooppunten die deze draaien terwijl u naar **Service Page > Gereedschappen > Functieservices controleren**. Selecteer Cisco TFTP-service daar en klik op **opnieuw opstarten**, zoals in de afbeelding.

Cisco Unified Serviceability
For Cisco Unified Communications Solutions

Alarm Trace Tools Snmp CallHome Help

Control Center - Feature Services

Start Stop Restart Refresh Page

Status:
Ready

Select Server
Server* 10.106.111.182--CUCM Voice/Video Go

Performance and Monitoring Services

Service Name	Status:
Cisco Serviceability Reporter	Started
Cisco CallManager SNMP Service	Started

Directory Services

Service Name	Status:
Cisco DirSync	Started

CM Services

Service Name	Status:
Cisco CallManager	Started
Cisco Unified Mobile Voice Access Service	Started
Cisco IP Voice Media Streaming App	Started
Cisco CTIManager	Started
Cisco Extension Mobility	Started
Cisco DHCP Monitor Service	Started
Cisco Intercluster Lookup Service	Started
Cisco Location Bandwidth Manager	Started
Cisco Directory Number Alias Sync	Started
Cisco Directory Number Alias Lookup	Started
Cisco Dialed Number Analyzer Server	Started
Cisco Dialed Number Analyzer	Started
Cisco Tftp	Started

Stap 8. Navigeer aan de telefoon.

System ▾ Call Routing ▾ Media Resources ▾ Advanced Features ▾ Device ▾ Application ▾ User Management ▾ Bulk Administration ▾ Help ▾

Find and List Phones Related Links: [Actively Logged In Device Report](#)

+ Add New Select All Clear All Delete Selected Reset Selected Apply Config to Selected

Status
1 records found

Query Information
Searching on a directory number may show the same device name multiple times depending on the number of lines configured per device.

Phone (1 - 1 of 1) Rows per Page 50 ▾

Find Phone where: Directory Number ▾ begins with ▾ 1006

Select item or enter search text ▾

<input type="checkbox"/>	Device Name(s) (1)	Description	Device Pool	Extension	Partition	Device Protocol	Status	IPv4 Address	Copy	Super Copy
<input type="checkbox"/>	SEP5C5015458F33(1)	Auto 1006	Default	1006		SIP	Registered with 10.106.113.72	10.106.113.89	<input type="button" value="Copy"/>	<input type="button" value="Super Copy"/>

Stap 9. Onder **Gebruiker Locale** selecteert u het lokale toetsenbord dat u zожuist hebt gedownload.

MAC Address* 5C5015458F33

Description Auto 1006

Device Pool* Default [View Details](#)

Common Device Configuration < None > [View Details](#)

Phone Button Template* SEP5C5015458F33-SIP-Individual Template

Softkey Template < None >

Common Phone Profile* Standard Common Phone Profile [View Details](#)

Calling Search Space < None >

AAR Calling Search Space < None >

Media Resource Group List < None >

User Hold MOH Audio Source < None >

Network Hold MOH Audio Source < None >

Location* Hub_None

AAR Group < None >

User Locale < None >

Network Locale < None >

Built In Bridge* English, United States


Privacy* **Català, Reino de España**

English(British), United Kingdom

Stap 10. Opslaan, configuratie toepassen en de telefoon resetten.

Verifiëren

Als het lokale toetsenbord met succes is geïnstalleerd, kunt u de software in de moedertaal zien zoals in de afbeelding:



Problemen oplossen

Er is momenteel geen specifieke troubleshooting-informatie beschikbaar voor deze configuratie.