

Configurar a interceptação TCP nos roteadores Cisco IOS?/IOS-XE

Contents

[Introduction](#)
[Prerequisites](#)
[Requirements](#)
[Componentes Utilizados](#)
[Problema](#)
[Para roteadores ISR G1](#)
[Para roteadores ISR G2](#)
[Para roteadores ISR G3](#)
[Para roteadores ASR1k](#)
[Solução](#)
[Verificar](#)
[Troubleshoot](#)
[Informações Relacionadas](#)

Introduction

Este documento descreve os requisitos para ativar o recurso de interceptação do Cisco Transmission Control Protocol (TCP) em roteadores Cisco IOS®/IOS-XE. A interceptação TCP é necessária para proteger os servidores TCP de ataques de inundação de sincronização TCP (SYN), um tipo de ataque de negação de serviço.

Prerequisites

Requirements

Não existem requisitos específicos para este documento.

Componentes Utilizados

Este documento não se restringe a versões de software e hardware específicas.

The information in this document was created from the devices in a specific lab environment. All of the devices used in this document started with a cleared (default) configuration. Se a rede estiver ativa, certifique-se de que você entenda o impacto potencial de qualquer comando.

Problema

Você não pode configurar 'ip tcp intercept' nos roteadores ISR G1/G2/G3 e ASR1k. Você pode ver os registros aqui:

• Para roteadores ISR G1

```
Router#show ver
```

```
Cisco IOS® Software, 2800 Software (C2800NM-IPBASEK9-M), Version 15.1(4)M12a, RELEASE SOFTWARE  
(fc1)  
Router uptime is 14 minutes  
System returned to ROM by reload at 07:45:56 UTC Tue Nov 1 2016  
System image file is "flash:c2800nm-ipbasek9-mz.151-4.M12a(1).bin"
```

```
Last reload type: Normal Reload
```

```
<omitted>
```

```
Cisco 2811 (revision 1.0) with 512000K/12288K bytes of memory.  
Processor board ID FHK1404F3U8  
2 FastEthernet interfaces  
1 Channelized E1/PRI port  
DRAM configuration is 64 bits wide with parity enabled.  
239K bytes of non-volatile configuration memory.  
250368K bytes of ATA CompactFlash (Read/Write)
```

```
License Info:
```

```
License UDI:
```

```
-----  
Device# PID SN  
-----  
*0 CISCO2811 FHK1404F3U8
```

```
Configuration register is 0x2102
```

```
Router# config t
```

```
Enter configuration commands, one per line. End with CNTL/Z.
```

```
Router(config)#ip tcp ?  
RST-count Configure RST throttle count  
async-mobility Configure async-mobility  
chunk-size TCP chunk size  
ecn Enable Explicit Congestion Notification  
mss TCP initial maximum segment size  
path-mtu-discovery Enable path-MTU discovery on new TCP connections  
queuemax Maximum queue of outgoing TCP packets  
selective-ack Enable TCP selective-ACK  
synwait-time Set time to wait on new TCP connections  
timestamp Enable TCP timestamp option  
window-size TCP window size
```

• Para roteadores ISR G2

```

Router#show ver

Cisco IOS® Software, C1900 Software (C1900-UNIVERSALK9-M), Version 15.4(3)M4, RELEASE SOFTWARE
(fcl)

<omitted>

Router uptime is 1 minute
System returned to ROM by reload at 10:28:40 UTC Mon Oct 31 2016
System image file is "flash:c1900-universalk9-mz.SPA.154-3.M4.bin"
Last reload type: Normal Reload
Last reload reason: Reload Command

<omitted>

Cisco CISCO1941/K9 (revision 1.0) with 2543552K/77824K bytes of memory.
Processor board ID FHK141571QW
4 FastEthernet interfaces

<omitted>

```

Technology Package License Information for Module:'c1900'

Technology	Technology-package Current	Type	Technology-package Next reboot
ipbase	ipbasek9	Permanent	ipbasek9
security	securityk9	RightToUse	securityk9
data	None	None	None
NtwkEss	None	None	None

Configuration register is 0x2102

```

Router# config t

Enter configuration commands, one per line. End with CNTL/Z.

Router(config)#ip tcp ?
  RST-count          Configure RST throttle count
  async-mobility     Configure async-mobility
  chunk-size         TCP chunk size
  ecn                Enable Explicit Congestion Notification
  keepalive          Configure TCP Keepalive parameters
  mss                TCP initial maximum segment size
  path-mtu-discovery Enable path-MTU discovery on new TCP connections
  queuemax           Maximum queue of outgoing TCP packets
  selective-ack      Enable TCP selective-ACK
  synwait-time       Set time to wait on new TCP connections
  timestamp          Enable TCP timestamp option
  window-size         TCP window size

```

• Para roteadores ISR G3

```

Router#sh ver

Cisco IOS® XE Software, Version 03.15.02.S - Standard Support Release
Cisco IOS® Software, ISR Software (X86_64_LINUX_IOS® D-UNIVERSALK9-M), Version 15.5(2)S2,
RELEASE SOFTWARE (fcl)
Technical Support: http://www.cisco.com/techsupport

```

Copyright (c) 1986-2015 by Cisco Systems, Inc.
Compiled Fri 16-Oct-15 18:00 by mcpre

<omitted>

Router uptime is 7 minutes
Uptime for this control processor is 8 minutes
System returned to ROM by reload
System image file is "bootflash:isr4300-universalk9.03.15.02.S.155-2.S2-std.SPA.bin"
Last reload reason: Reload Command

<omitted>

Technology Package License Information:

Technology	Technology-package Current	Type	Technology-package Next reboot
appx	None	None	None
uc	uck9	Permanent	uck9
security	securityk9	EvalRightToUse	securityk9
ipbase	ipbasek9	Permanent	ipbasek9

cisco ISR4331/K9 (1RU) processor with 1665776K/6147K bytes of memory.
Processor board ID FDO2012A0AT
3 Gigabit Ethernet interfaces
32768K bytes of non-volatile configuration memory.
4194304K bytes of physical memory.
3223551K bytes of flash memory at bootflash:.

Configuration register is 0x2102

Router# config t

Enter configuration commands, one per line. End with CNTL/Z.

Router(config)#ip tcp ?
RST-count Configure RST throttle count
async-mobility Configure async-mobility
chunk-size TCP chunk size
ecn Enable Explicit Congestion Notification
keepalive Configure TCP Keepalive parameters
mss TCP initial maximum segment size
path-mtu-discovery Enable path-MTU discovery on new TCP connections
queuemax Maximum queue of outgoing TCP packets
selective-ack Enable TCP selective-ACK
synwait-time Set time to wait on new TCP connections
timestamp Enable TCP timestamp option
window-size TCP window size

• Para roteadores ASR1k

Router#show version

Cisco IOS® XE Software, Version 03.16.01a.S - Extended Support Release
Cisco IOS® Software, ASR1000 Software (X86_64_LINUX_IOSD-UNIVERSAL-M), Version 15.5(3)S1a,

```
RELEASE SOFTWARE (fc1)
Technical Support: http://www.cisco.com/techsupport
Copyright (c) 1986-2015 by Cisco Systems, Inc.
Compiled Wed 04-Nov-15 13:57 by mcpre

<omitted>

Router uptime is 1 minute
Uptime for this control processor is 2 minutes
System returned to ROM by reload
System image file is "bootflash:asr1001x-universal.03.16.01a.S.155-3.S1a-ext.SPA.bin"
Last reload reason: PowerOn
```

```
License Level: ipbase
License Type: Permanent
Next reload license Level: ipbase
```

```
cisco ASR1001-X (1NG) processor (revision 1NG) with 3753592K/6147K bytes of memory.
Processor board ID FXS1925Q33T
6 Gigabit Ethernet interfaces
2 Ten Gigabit Ethernet interfaces
32768K bytes of non-volatile configuration memory.
8388608K bytes of physical memory.
6684671K bytes of eUSB flash at bootflash:
```

```
Configuration register is 0x2102
Router#config t
Enter configuration commands, one per line. End with CNTL/Z.
```

```
Router(config)#ip tcp ?
  RST-count          Configure RST throttle count
  async-mobility     Configure async-mobility
  chunk-size         TCP chunk size
  ecn                Enable Explicit Congestion Notification
  keepalive          Configure TCP Keepalive parameters
  mss                TCP initial maximum segment size
  path-mtu-discovery Enable path-MTU discovery on new TCP connections
  queuemax           Maximum queue of outgoing TCP packets
  selective-ack      Enable TCP selective-ACK
  synwait-time       Set time to wait on new TCP connections
  timestamp          Enable TCP timestamp option
  window-size         TCP window size
```

Solução

Para habilitar o recurso Interceptação TCP, você precisaria:

- Mínimo de recursos **entbase** definidos nos roteadores ISR G1
- **Appxk9/Datak9** em roteadores das séries ISRG2 e G3
- Licença mínima de **advipservices** no roteador ASR1k series

Depois de habilitar a licença necessária na plataforma, você poderá configurar o mesmo:

```
Router(config)#ip tcp ?
  RST-count          Configure RST throttle count
  async-mobility     Configure async-mobility
  chunk-size         TCP chunk size
  ecn                Enable Explicit Congestion Notification
  intercept          Enable TCP intercepting
  keepalive          Configure TCP Keepalive parameters
```

mss	TCP initial maximum segment size
path-mtu-discovery	Enable path-MTU discovery on new TCP connections
queuemax	Maximum queue of outgoing TCP packets
selective-ack	Enable TCP selective-ACK
synwait-time	Set time to wait on new TCP connections
timestamp	Enable TCP timestamp option
window-size	TCP window size

Verificar

No momento, não há procedimento de verificação disponível para esta configuração.

Troubleshoot

Atualmente, não existem informações disponíveis específicas sobre Troubleshooting para esta configuração.

Informações Relacionadas

- http://www.cisco.com/c/en/us/td/docs/ios/12_2/security/configuration/guide/fsecur_c/scfdenl.html
- [Suporte Técnico e Documentação - Cisco Systems](#)