



QoS: Service Groups Configuration Guide, Cisco IOS XE Everest 16.6

Americas Headquarters

Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134-1706
USA
<http://www.cisco.com>
Tel: 408 526-4000
800 553-NETS (6387)
Fax: 408 527-0883

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NON-INFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <http://www.cisco.com/go/trademarks>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)

© 2014–2017 Cisco Systems, Inc. All rights reserved.



CONTENTS

CHAPTER 1

Read Me First 1

CHAPTER 2

Service Groups 3

- Finding Feature Information 3
- Restrictions for Service Groups 3
- Information About Service Groups 4
 - Service Instances and Service Groups 4
- How to Configure Service Groups 5
 - Creating a Service Group 5
 - Adding or Deleting Service Group Members 6
 - Deleting a Service Group 8
 - Verifying the Service Group Configuration 9
 - Adding or Deleting a Subinterface from a Service Group 11
 - Verifying the Subinterface Configuration 13
- Configuration Examples for Service Groups 15
 - Example Creating a Service Group 15
 - Example Adding Service Instance Members to a Service Group 15
 - Example Adding Subinterfaces to a Service Group 15
 - Example Deleting Service Instance Members from a Service Group 15
 - Example Deleting Subinterfaces from a Service Group 16
 - Example Deleting a Service Group 16
 - Example Verifying the Service Group Configuration 16
- How to Configure Service-group Support on Aggregate Port-channel 17
 - Adding Service Instance Members to a Service Group 17
 - Deleting Service Instance Members from a Service Group 19
- Configuration Examples for Service-group on Aggregate Port-channel 20
 - Example: Adding Service Instance Members to a Service Group 20
 - Example: Deleting Service Instance Members to a Service Group 20

[Service Groups](#) 20

[Additional References](#) 21

[Feature Information for Service Groups](#) 22



Read Me First

Important Information about Cisco IOS XE 16

Effective Cisco IOS XE Release 3.7.0E (for Catalyst Switching) and Cisco IOS XE Release 3.17S (for Access and Edge Routing) the two releases evolve (merge) into a single version of converged release—the Cisco IOS XE 16—providing one release covering the extensive range of access and edge products in the Switching and Routing portfolio.

Feature Information

Use [Cisco Feature Navigator](#) to find information about feature support, platform support, and Cisco software image support. An account on Cisco.com is not required.

Related References

- [Cisco IOS Command References, All Releases](#)

Obtaining Documentation and Submitting a Service Request

For information on obtaining documentation, using the Cisco Bug Search Tool (BST), submitting a service request, and gathering additional information, see [What's New in Cisco Product Documentation](#).

To receive new and revised Cisco technical content directly to your desktop, you can subscribe to the [What's New in Cisco Product Documentation RSS feed](#). RSS feeds are a free service.



CHAPTER 2

Service Groups

This feature provides the ability to apply an aggregate QoS service policy across multiple VLAN subinterfaces or service instances that are on the same physical interface. The Service Group feature allows network administrators to create service groups, add members (such as service instances) to those service groups, and apply service policies to the groups. The service policies contain the aggregate features (such as traffic policing and queueing) that can be applied to the groups. These service policies are in compliance with the Service-Level Agreement (SLA) negotiated between the service provider and the subscribers.

- [Finding Feature Information, page 3](#)
- [Restrictions for Service Groups, page 3](#)
- [Information About Service Groups, page 4](#)
- [How to Configure Service Groups, page 5](#)
- [Configuration Examples for Service Groups, page 15](#)
- [How to Configure Service-group Support on Aggregate Port-channel, page 17](#)
- [Configuration Examples for Service-group on Aggregate Port-channel, page 20](#)
- [Service Groups, page 20](#)

Finding Feature Information

Your software release may not support all the features documented in this module. For the latest caveats and feature information, see [Bug Search Tool](#) and the release notes for your platform and software release. To find information about the features documented in this module, and to see a list of the releases in which each feature is supported, see the feature information table.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to www.cisco.com/go/cfn. An account on Cisco.com is not required.

Restrictions for Service Groups

- Only EFP service instances, routed sub-interfaces and aggregate port-channel sub-interfaces can be added as members of service groups.

Each service instance or sub-interface can belong to only one service group at time.

- The service group must exist before any member can join the group.
- All members of a service group must reside on the same physical interface or same aggregate port-channel interface.
- Sub-interfaces or service instances that are members of a service group cannot have a QoS policy applied to the interfaces, even if the service group does not have a QoS policy applied.
- MPOL is not supported on aggregate port-channel when policy is applied on aggregated port-channel main interface, port-channel sub-interface cannot be attached by any policy, or be configured as a member of a service-group.
- Sub-interface belongs to service group and sub-interface applied with service-policy cannot be configured on the same aggregate port-channel simultaneously.
- Each sub-interface belongs to only one service group at a time.
- Interfaces that are a member of a service group cannot have a QoS policy applied.
- A batch configuration including both "define service-group" and "add sub-interface to service-group" may result in membership error, and vice versa in the unconfiguration.

So it is recommended to define the service-group before adding subinterfaces or service instances to it, and removing them from the service-group before deleting the service-group or deleting the subinterfaces or service instances.

Information About Service Groups

Service Instances and Service Groups

A service instance is a configuration object (container) that holds all management and control plane attributes and parameters that apply to that service instance on a per-port basis. Different service instances that correspond to the same Ethernet Virtual Connection (EVC) must share the same name. Service instances are associated with a global EVC object through their shared name.

The Service Groups feature allows you to create service groups and apply aggregate features to those service groups. Service groups are created with input and output policies. Members join these groups by configuring the group ID in their configuration.

Make note of the following actions when enabling the service group feature:

- A service group must be created before a QoS policy can be configured on the service group.
- A service group sub-interface or service instance must be created before it can be bound to its group interface.

When disabling the service group feature:

- A service group sub-interface or service instance must be unbound from the service group interface before the service member interface is deleted.
- A service group sub-interface or service instance unbound from the service group interface before the service group interface is deleted.

- A QoS policy must be removed from the service group interface before the service group interface is deleted.

How to Configure Service Groups

Creating a Service Group

Before You Begin

In this procedure, you need to specify the name of a QoS policy to be attached to the service group. The QoS policy must already exist.

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **service-group** *service-group-identifier*
4. **description** *descriptive-text*
5. **service-policy** {**input** | **output**} *policy-map-name*
6. **end**

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. • Enter your password if prompted.
Step 2	configure terminal Example: Device# configure terminal	Enters global configuration mode.
Step 3	service-group <i>service-group-identifier</i> Example: Device(config)# service-group 20	Creates a service group and enters service-group configuration mode. • Enter the service group number. The number of service groups that can be created varies by Device.
Step 4	description <i>descriptive-text</i>	(Optional) Creates a description of the service group.

	Command or Action	Purpose
	<p>Example:</p> <pre>Device(config-service-group)# description subscriber account number 105AB1</pre>	<ul style="list-style-type: none"> Enter a description (for example, additional information about the group) of the service group. Descriptions can be a maximum of 240 characters.
Step 5	<p>service-policy {input output} <i>policy-map-name</i></p> <p>Example:</p> <pre>Device(config-service-group)# service-policy input policyl</pre>	<p>(Optional) Attaches a policy map to the service group, in either the ingress (input) or egress (output) direction.</p> <ul style="list-style-type: none"> Enter either the input or output keyword and the name of the previously created policy map.
Step 6	<p>end</p> <p>Example:</p> <pre>Device(config-service-group)# end</pre>	<p>(Optional) Returns to privileged EXEC mode.</p>

Adding or Deleting Service Group Members



Note The following restrictions apply to service group members:

- A member can join only one service group at a time.
- All members of a service group must reside on the same physical interface.
- Service instances cannot join the same group from multiple interfaces. Group members must come from the same interface, as shown in the sample configuration below:

```
interface GigabitEthernet 2/0/0
service instance 1 ethernet
group 32
service instance 2 ethernet
group 32
interface GigabitEthernet 2/0/0.2
encapsulation dot1q 2
group 37
interface GigabitEthernet 2/0/1
service instance 1 ethernet
group 32 |<--Disallowed because this group has members in g2/0/0 already |
>
```

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **interface** *type number*
4. **service instance** *service-instance-number* **ethernet**
5. **group** *service-group-identifier*
6. **no group** *service-group-identifier*
7. **exit**
8. **end**

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	configure terminal Example: Device# configure terminal	Enters global configuration mode.
Step 3	interface <i>type number</i> Example: Device(config)# interface GigabitEthernet 0/1/0	Configures an interface and enters interface configuration mode.
Step 4	service instance <i>service-instance-number</i> ethernet Example: Device(config-if)# service instance 200 ethernet	Specifies the service instance to be added or deleted from a service group and enters service configuration mode.
Step 5	group <i>service-group-identifier</i> Example: Device(config-if-srv)# group 20	Number of the service group specified by the member will be added.
Step 6	no group <i>service-group-identifier</i> Example: Device(config-if-srv)# no group 20	(Optional) Number of the service group specified by the member will be added.

	Command or Action	Purpose
Step 7	exit Example: Device(config-if-srv)# exit	(Optional) Returns to interface configuration mode.
Step 8	end Example: Device(config-if-srv)# end	(Optional) Returns to privileged EXEC mode.

Deleting a Service Group

Before You Begin

- A service member interface must be unbound from the service group interface before the service group interface is deleted.
- A QoS policy must be removed from the service group interface before the service group interface is deleted.

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **no service-group** *service-group-identifier*
4. **end**

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	configure terminal Example: Device# configure terminal	Enters global configuration mode.

	Command or Action	Purpose
Step 3	no service-group <i>service-group-identifier</i> Example: Device(config)# no service-group 20	Deletes a service group and deletes all members from the service group. <ul style="list-style-type: none"> • Enter the service group number to be deleted. Note When you delete a service group, all members of the service group are automatically removed from the service group.
Step 4	end Example: Device(config)# end	(Optional) Exits global configuration mode.

Verifying the Service Group Configuration

SUMMARY STEPS

1. enable
2. show running-config service-group
3. show service-group {*service-group-identifier* | all}
4. show service-group interface *type number*
5. show service-group stats
6. show service-group state
7. show service-group traffic-stats
8. show policy-map interface *type number* service group {*service-group-identifier*}
9. show policy-map target service-group {*service-group-identifier*}
10. show ethernet service instance [detail]
11. clear service-group traffic-stats
12. debug service-group {all | error | feature | group | interface | ipc | member | qos | stats}

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.

	Command or Action	Purpose
Step 2	show running-config service-group Example: Device# show running-config service-group	(Optional) Displays the running service-group configuration.
Step 3	show service-group { <i>service-group-identifier</i> all } Example: Device# show service-group all	(Optional) Displays service-group configuration information for one or all service groups.
Step 4	show service-group interface <i>type number</i> Example: Device# show service-group interface gigabitethernet 3/1	(Optional) Displays service-group membership information by interface. <ul style="list-style-type: none"> • Enter the interface type and number.
Step 5	show service-group stats Example: Device# show service-group stats	(Optional) Displays service-group statistical information.
Step 6	show service-group state Example: Device# show service-group state	(Optional) Displays state information about service groups.
Step 7	show service-group traffic-stats Example: Device# show service-group traffic-stats	(Optional) Displays traffic statistics for all the members of a service group. <ul style="list-style-type: none"> • The information displayed is the combined total of the traffic statistics for all members.
Step 8	show policy-map interface <i>type number</i> service group { <i>service-group-identifier</i> } Example: Device# show policy-map interface gigabitEthernet 9/5 service group	(Optional) Displays policy-map information for service groups. <ul style="list-style-type: none"> • Enter the interface type and number.
Step 9	show policy-map target service-group { <i>service-group-identifier</i> } Example: Device# show policy-map target service-group 1	(Optional) Displays policy-map information for service groups that have members attached to the specified interface. <ul style="list-style-type: none"> • Enter the service group identifier.

	Command or Action	Purpose
Step 10	show ethernet service instance [detail] Example: Device# show ethernet service instance detail	(Optional) Displays information about the service instances. Note To display the service group number, use the detail keyword.
Step 11	clear service-group traffic-stats Example: Device# clear service-group traffic-stats	(Optional) Clears the traffic statistics for the service group. Note Clearing the traffic statistics for the service group does not clear the traffic statistics for the group members. To clear the traffic statistics for group members, use the clear ethernet service instance command. For more information about the clear ethernet service instance command, see the Cisco IOS Carrier Ethernet Command Reference .
Step 12	debug service-group {all error feature group interface ipc member qos stats} Example: Device# debug service-group qos	(Optional) Debugs service-group events and errors.

Adding or Deleting a Subinterface from a Service Group



Note

If a subinterface is already a member of a group, you cannot add it to another group. To move a subinterface, first delete it from the current group, then add it to the new group.

>

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **interface** *type number*
4. **group** *service-group-identifier*
5. **no group** *service-group-identifier*
6. **exit**
7. **end**

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	configure terminal Example: Device# configure terminal	Enters global configuration mode.
Step 3	interface <i>type number</i> Example: Device(config)# interface GigabitEthernet 1/1/0.30 Device(config)# interface range GigabitEthernet 1/1/0.30 - GigabitEthernet 1/1/0.36	Configures a subinterface and enters subinterface configuration mode. <ul style="list-style-type: none"> • Enter the interface type and the subinterface number. or Configures a range of subinterfaces and enters subinterface configuration mode. <ul style="list-style-type: none"> • Enter the interface types and the subinterface numbers.
Step 4	group <i>service-group-identifier</i> Example: Device(config-subif)# group 20	Number of the service group to which the subinterfaces will be added. <ul style="list-style-type: none"> • Enter the service group number.
Step 5	no group <i>service-group-identifier</i> Example: Device(config-subif)# no group 30	(Optional) Number of the service group from which the subinterfaces will be deleted. <ul style="list-style-type: none"> • Enter the service group number.
Step 6	exit Example: Device(config-subif)# exit	(Optional) Returns to interface configuration mode.
Step 7	end Example: Device(config-subif)# end	(Optional) Returns to privileged EXEC mode.

Verifying the Subinterface Configuration

SUMMARY STEPS

1. `enable`
2. `show running-config service-group`
3. `show service-group {service-group-identifier | all}`
4. `show service-group interface type number`
5. `show policy-map target service-group service-group-identifier`
6. `show service-group stats`
7. `show service-group state`
8. `show service-group traffic-stats`
9. `clear service-group traffic-stats`
10. `debug service-group {all | error | feature | group | interface | ipc | member | qos | stats}`

DETAILED STEPS

	Command or Action	Purpose
Step 1	<p><code>enable</code></p> <p>Example:</p> <pre>Device> enable</pre>	<p>Enables privileged EXEC mode.</p> <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	<p><code>show running-config service-group</code></p> <p>Example:</p> <pre>Device# show running-config service-group</pre>	(Optional) Displays the running service-group configuration.
Step 3	<p><code>show service-group {service-group-identifier all}</code></p> <p>Example:</p> <pre>Device# show service-group all</pre>	(Optional) Displays service-group configuration information for one or all service groups.
Step 4	<p><code>show service-group interface type number</code></p> <p>Example:</p> <pre>Device# show service-group interface gigabitethernet 3/1</pre>	<p>(Optional) Displays service-group membership information by interface.</p> <ul style="list-style-type: none"> • Enter the interface type and number.
Step 5	<p><code>show policy-map target service-group service-group-identifier</code></p>	(Optional) Displays the policy-map information for all service groups or the specified service group.

	Command or Action	Purpose
	<p>Example:</p> <pre>Device# show policy-map target service-group 1</pre>	<ul style="list-style-type: none"> • Enter the target and service group.
Step 6	<p>show service-group stats</p> <p>Example:</p> <pre>Device# show service-group stats</pre>	(Optional) Displays service-group statistical information.
Step 7	<p>show service-group state</p> <p>Example:</p> <pre>Device# show service-group state</pre>	(Optional) Displays state information about service groups.
Step 8	<p>show service-group traffic-stats</p> <p>Example:</p> <pre>Device# show service-group traffic-stats</pre>	<p>(Optional) Displays the traffic statistics for all the members of a service group.</p> <ul style="list-style-type: none"> • The information displayed is the combined total of the traffic statistics for all members.
Step 9	<p>clear service-group traffic-stats</p> <p>Example:</p> <pre>Device# clear service-group traffic-stats</pre>	<p>(Optional) Clears the traffic statistics for the service group.</p> <p>Note Clearing the traffic statistics for the service group does not clear the traffic statistics for the group members. To clear the traffic statistics for group members, use the clear ethernet service instance command. For more information about the clear ethernet service instance command, see the <i>Cisco IOS Carrier Ethernet Command Reference</i>.</p>
Step 10	<p>debug service-group {all error feature group interface ipc member qos stats}</p> <p>Example:</p> <pre>Device# debug service-group qos</pre>	(Optional) Debugs service-group events and errors.

Configuration Examples for Service Groups

Example Creating a Service Group

In the following example, service group 20 has been created:

```
Device> enable
Device# configure terminal
Device(config)# service-group 20
Device(config-service-group)# description account number 105AB1
Device(config-service-group)# service-policy input policy1
Device(config-service-group)# end
```

Example Adding Service Instance Members to a Service Group

In the following example, service instance 200 will be added to service group 20:

```
Device> enable

Device# configure terminal

Device(config)# interface GigabitEthernet 1/0

Device(config-if)# service instance 200 ethernet

Device(config-if-srv)# group 20

Device(config-if-srv)# end
```

Example Adding Subinterfaces to a Service Group

In the following example, subinterface g3/7.12 will be added to service group 10:

```
Device> enable

Device# configure terminal

Device(config)# interface GigabitEthernet 3/7.12

Device(config-subif)# group 10

Device(config-subif)# end
```

Example Deleting Service Instance Members from a Service Group

In the following example, service instance 300 will be deleted from service group 30 on a port channel:

```
Device> enable
Device# configure terminal
Device(config)# interface GigabitEthernet 1/0.56 or
Device(config-if)# service instance 300 ethernet
```

```
Device(config-if-srv)# no group 30
Device(config-if-srv)# end
```

Example Deleting Subinterfaces from a Service Group

In the following example, subinterface g3/7.12 will be deleted from service group 10:

```
Device> enable
Device# configure terminal
Device(config)# interface g3/7.12
Device(config-subif)# no group 10
Device(config-subif)# end
```

Example Deleting a Service Group

In the following example, service group 20 will be deleted:

```
Device> enable
Device# configure terminal
Device(config)# no service-group 20
Device(config)# end
```

Example Verifying the Service Group Configuration

This section contains sample output from the **show policy-map target service-group** command. The **show policy-map target service-group** command displays policy-map information for service groups.



Note

This command is one of several that you can use to verify the service-group configuration. For additional commands that can be used, see *Verifying the Service Group Configuration*.

In the following example, service group 1 is specified. Service group 1 contains two policy maps (service policies), policy1 and policy2. Traffic policing is enabled in the EVC policy map. Traffic queuing is enabled in the ISG policy map.

```
Device# show policy-map target service-group 1

GigabitEthernet9/5: Service Group 1

Service-policy input: policy1

Class-map: class-default (match-any)
  0 packets, 0 bytes
  5 minute offered rate 0000 bps, drop rate 0000 bps
Match: any
police:
  cir 200000 bps, bc 6250 bytes
  conformed 0 packets, 0 bytes; actions:
    transmit
  exceeded 0 packets, 0 bytes; actions:
    drop
  conformed 0000 bps, exceed 0000 bps
```

```

Service-policy output: policy2

Counters last updated 00:00:34 ago
Class-map: class-default (match-any)
  0 packets, 0 bytes
  5 minute offered rate 0000 bps, drop rate 0000 bps
Match: any
Queueing
queue limit 131072 packets
(queue depth/total drops/no-buffer drops) 0/0/0
(pkts output/bytes output) 0/0
bandwidth remaining ratio 2

```

How to Configure Service-group Support on Aggregate Port-channel

Adding Service Instance Members to a Service Group

SUMMARY STEPS

1. enable
2. configure terminal
3. service-group *service-group-identifier*
4. service-policy {input | output} *policy-map-name*
5. platform qos port-channel-aggregate *port-channel-number*
6. interface port-channel *port-channel-number*
7. interface *interface*
8. channel-group *number*
9. interface port-channel *port-channel-number.subinterface-number*
10. encapsulation dot1Q *vlan-id* second-dot1q *vlan-id*
11. group *service-group-identifier*
12. end

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. Enter your password if prompted.
Step 2	configure terminal Example: Device# configure terminal	Enters global configuration mode.
Step 3	service-group <i>service-group-identifier</i>	Adds a service group and all members to the service group.

	Command or Action	Purpose
	Example: Device(config)# service-group 10	
Step 4	service-policy {input output} policy-map-name Example: Device(config-service-group)# service-policy input policy1 Device(config-service-group)# service-policy output policy2	(Optional) Attaches a policy map to the service group, in either the ingress (input) or egress (output) direction. <ul style="list-style-type: none"> • Enter either the input or output keyword and the name of the previously created policy map.
Step 5	platform qos port-channel-aggregate port-channel-number Example: Device(config)# platform qos port-channel-aggregate 1	Enables aggregate mode for a port-channel interface. <p>Note It must be configured before a port-channel is created. Enable aggregate mode before a port-channel interface is attached by policy, or subinterfaces of the port-channel to be added to a service-group.</p>
Step 6	interface port-channel port-channel-number Example: Device(config)# interface port-channel 1	Enters interface configuration mode to configure a specific port channel.
Step 7	interface interface Example: Device(config)# interface g0/0/0	Configures physical interface as a member link of the port-channel.
Step 8	channel-group number Example: Device(config)# channel-group 1	Adds the physical interface to the port-channel 1 as a member link.
Step 9	interface port-channel port-channel-number.subinterface-number Example: Device(config)# interface port-channel 1.10	Enters interface configuration mode to configure a specific port channel subinterface.
Step 10	encapsulation dot1Q vlan-id second-dot1q vlan-id Example: Device(config-subif)# encapsulation dot1Q 10 second-dot1q 11	Defines the matching criteria to map Q-in-Q ingress frames on the port-channel subinterface. <p>Note Configuring second-dot1q is optional.</p>
Step 11	group service-group-identifier Example: Device(config-subif)# group 10	Adds the port-channel sub interface to the specified service-group.

	Command or Action	Purpose
Step 12	end Example: Device(config-subif)# end	Returns to privileged EXEC mode.

Deleting Service Instance Members from a Service Group

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **interface port-channel** *port-channel-number.subinterface-number*
4. **no group** *service-group-identifier*
5. **no service-group** *service-group-identifier*
6. **end**

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. Enter your password if prompted.
Step 2	configure terminal Example: Device# configure terminal	Enters global configuration mode.
Step 3	interface port-channel <i>port-channel-number.subinterface-number</i> Example: Device(config)# interface port-channel 1.10	Enters interface configuration mode to configure a specific port channel subinterface.
Step 4	no group <i>service-group-identifier</i> Example: Device(config-subif)# no group 10	Removes the port-channel sub-interface from the service group specified by the number.
Step 5	no service-group <i>service-group-identifier</i>	Deletes a service group.

	Command or Action	Purpose
	Example: Device(config-subif)# no service-group 10	Note All members should be removed from the service group first.
Step 6	end Example: Device(config)# end	Returns to privileged EXEC mode.

Configuration Examples for Service-group on Aggregate Port-channel

Example: Adding Service Instance Members to a Service Group

```

Device> enable
Device# configure terminal
Device(config)# service-group 10
Device(config-service-group)# service-policy input policy1
Device(config-service-group)# service-policy output policy2
Device(config)# platform qos port-channel-aggregate 1
Device(config)# interface port-channel 1
Device(config)# interface g0/0/0
Device(config-if)# channel-group 1
Device(config)# interface port-channel 1.10
Device(config-subif)# encapsulation dot1q 10 second-dot1q 11
Device(config-subif)# group 10
Device(config-subif)# end

```

Example: Deleting Service Instance Members to a Service Group

```

Device> enable
Device# configure terminal
Device(config)# interface port-channel 1.10
Device(config-subif)# no group 10
Device(config-subif)# no service-group 10
Device(config)# end

```

Service Groups

This feature provides the ability to apply an aggregate QoS service policy across multiple VLAN subinterfaces or service instances that are on the same physical interface. The Service Group feature allows network administrators to create service groups, add members (such as service instances) to those service groups, and apply service policies to the groups. The service policies contain the aggregate features (such as traffic policing

and queueing) that can be applied to the groups. These service policies are in compliance with the Service-Level Agreement (SLA) negotiated between the service provider and the subscribers.

Additional References

Related Documents

Related Topic	Document Title
QoS commands: complete command syntax, command modes, command history, defaults, usage guidelines, and examples.	<i>Cisco IOS Quality of Service Solutions Command Reference</i>
Debug commands: complete command syntax, command modes, command history, defaults, usage guidelines, and examples.	<i>Cisco IOS Debug Command Reference</i>
MQC, policy maps	"Applying QoS Features Using the MQC" module
Service instance configuration information and concepts	<i>Cisco IOS Carrier Ethernet Configuration Guide</i>
Service instance commands	<i>Cisco IOS Carrier Ethernet Command Reference</i>

Standards

Standard	Title
No new or modified standards are supported by this feature, and support for existing standards has not been modified by this feature.	--

MIBs

MIB	MIBs Link
No new or modified MIBs are supported by this feature, and support for existing MIBs has not been modified by this feature.	To locate and download MIBs for selected platforms, Cisco IOS releases, and feature sets, use Cisco MIB Locator found at the following URL: http://www.cisco.com/go/mibs

RFCs

RFC	Title
No new or modified RFCs are supported by this feature, and support for existing RFCs has not been modified by this feature.	--

Technical Assistance

Description	Link
The Cisco Support and Documentation website provides online resources to download documentation, software, and tools. Use these resources to install and configure the software and to troubleshoot and resolve technical issues with Cisco products and technologies. Access to most tools on the Cisco Support and Documentation website requires a Cisco.com user ID and password.	http://www.cisco.com/cisco/web/support/index.html

Feature Information for Service Groups

The following table provides release information about the feature or features described in this module. This table lists only the software release that introduced support for a given feature in a given software release train. Unless noted otherwise, subsequent releases of that software release train also support that feature.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to www.cisco.com/go/cfn. An account on Cisco.com is not required.

Table 1: Feature Information for Service Groups

Feature Name	Releases	Feature Information
Service Groups	Cisco IOS XE Release 3.15S	<p>The Service Groups feature provides the ability to apply an aggregate QoS service policy across multiple VLAN subinterfaces or service instances that are on the same physical interface.</p> <p>In Cisco IOS Release XE Release 3.15S, this feature was supported on Cisco ASR 1000 Series Aggregation Services Routers, Cisco ISR 4000 Series Integrated Services Routers, and Cisco CSR 1000V Cloud Services Routers.</p>

Feature Name	Releases	Feature Information
Service-group on Aggregate Port-channel Subinterface	Cisco IOS XE Denali 16.3.1.	The Service-group on Aggregate Port-channel Subinterface feature allows network administrators to add aggregate port-channel subinterface to the service groups, In Cisco IOS XE Release 16.3, this feature was implemented on the Cisco ASR 1000 Series Aggregation Services Routers.

