

Cisco نم CGR2010 ذفانم عجرم

تايوتحمل

[قمدقمل](#)

[قضاارتفال ذفانم](#)

[يسكعل ذفانم تامدخ لودج](#)

قمدقمل

تاقيبطتل قصنم لمعتسي Cisco CGR2010 نأ انيم UDP و TCP ل ا قيثو اذه فصبي
تنرتنل تالاصتاو.

قضاارتفال ذفانم

: اضاارتفانكمي انيم اذه Cisco CGR2010 قىلتي

```
Router#show control-plane host open-ports
Active internet connections (servers and established)
Prot Local Address Foreign Address Service State
tcp *:23 *:0 Telnet LISTEN
```

Router#

CGR 2010: لوحمل ايف اوتفم 22 ذفانم نوكي، هومل ايف SSH لوكوتورب نيكمت ل ايف

```
Router#show control-plane host open-ports
Active internet connections (servers and established)
Prot Local Address Foreign Address Service State
tcp *:22 *:0 SSH-Server LISTEN
tcp *:23 *:0 Telnet LISTEN
```

هومل ايف انيكمت متي تل ذفانم ن ققحتل NMAP مدختسأ

```
C:\Program Files (x86)\Nmap>nmap -sS -p1-10000 10.31.126.137
Starting Nmap 7.70 ( https://nmap.org ) at 2018-12-06 20:05 Central Standard Time (Mexico)
Nmap scan report for 10.31.126.137
Host is up (0.0054s latency).
Not shown: 9998 closed ports
PORT STATE SERVICE
22/tcp open ssh
23/tcp open telnet
```

Nmap done: 1 IP address (1 host up) scanned in 14.23 seconds

C:\Program Files (x86)\Nmap>

و 6003 و 4003 و 2003 ذفانملا هجوملا حت في ، CGR2010 ىلع لوحملل ةيطمن ةدحو تيبثت دنع
9003. ةلواطلا ىلع ةرظان قلا.

```
C:\Program Files (x86)\Nmap>nmap -ss -p1-10000 10.31.126.137
Starting Nmap 7.70 ( https://nmap.org ) at 2018-12-06 20:22 Central Standard Time (Mexico)
Nmap scan report for 10.31.126.137
Host is up (0.0067s latency).
Not shown: 9994 closed ports
PORT STATE SERVICE
22/tcp open  ssh
23/tcp open  telnet
2003/tcp open  finger
4003/tcp open  pxc-splr-ft
6003/tcp open  X11:3
9003/tcp open  unknown

Nmap done: 1 IP address (1 host up) scanned in 12.54 seconds
```

```
C:\Program Files (x86)\Nmap>
```

يسكعلا ذفنملا تامدخ لودج

ةمدخلا مسا	زوجحملا ذفنملا قاطن
ي داعلا Telnet جمانرب	2000-2xxx
مخال TCP لوكوتورب	4000-4xxx زارطلا
ل Telnet ل ئانثلا عضولا	6xxx ىل 6000 نم
سكع Xremote	9xxx ىل 9000 نم

رم اوألا هذه في كولسلا اذه لوانت متي:

<https://bst.cloudapps.cisco.com/bugsearch/bug/CSCsh95539>

ةمچرتل هذه لوج

ةللأل تاي نقتل نمة ومة مادختساب دن تسمل اذة Cisco تمةرت
ملاعلاء انء مء مء نمة دختسمل معد و تمة مء دقتل ةر شبل او
امك ةق قء نوك ت نل ةللأل ةمچرت لصف أن ةظحال مء ءرء. ةصاأل مء تءل ب
Cisco ةللخت. فرتمة مچرت مء دقء ةللأل ةل فارتحال ةمچرتل عم لاعل او
ىل إأمءءاد ءوچرلاب ةصوء و تامةرتل هذه ةقء نء اهءل وئس م Cisco
Systems (رفوتم طبارل) ةلصلأل ةزىل ءنل اءل دن تسمل