



Configuration Group Workflows

- [Use the Configuration Group Workflows, on page 1](#)
- [Run the Create Configuration Group Workflow, on page 2](#)
- [Run the Rapid Site Configuration Group Workflow, on page 3](#)
- [Run the Custom Configuration Group Workflow, on page 3](#)

Use the Configuration Group Workflows

Before You Begin

Ensure that the IP address of the Cisco SD-WAN Validator is specified.

1. From the Cisco SD-WAN Manager menu, choose **Administration** > **Settings** > **Validator**.
2. Enter the IP address of the Cisco SD-WAN Validator.

Ensure that granular RBAC for each feature profile is specified by expanding it. With the set permissions to the usergroup, ensure that you are able to access required feature profiles from Cisco IOS XE Catalyst SD-WAN Release 17.12.1a, choose **Configuration** > **Configuration Groups** in the Cisco SD-WAN Manager menu.

In Cisco IOS XE Catalyst SD-WAN Release 17.11.1a and earlier, choose **Configuration** > **Templates** > **Configuration Groups**.

1. From the Cisco SD-WAN Manager menu, choose **Administration** > **Manage Users** > **User Groups**.
2. Click **Add User Group**.
3. Enter **User Group Name**.
4. Select the **Read** or **Write** check box against feature that you want to assign to a user group.
5. Click **Save**.



Note To create Service, System and Transport feature profiles using configuration groups, you need to provide read and write permissions on the following features to access each configuration group.

- **Feature Profile > System**
- **Feature Profile > System > AAA**
- **Feature Profile > System > BFD**
- **Feature Profile > System > Banner**
- **Feature Profile > System > Basic**
- **Feature Profile > System > Logging**
- **Feature Profile > System > NTP**
- **Feature Profile > System > OMP**
- **Feature Profile > System > SNMP**
- **Feature Profile > Service**
- **Feature Profile > Service > BFD**
- **Feature Profile > Service > LAN/VPN**
- **Feature Profile > Service > LAN/VPN/Interface/Ethernet**
- **Feature Profile > Service > Routing/BGP**
- **Feature Profile > Service > Routing/OSPF**
- **Feature Profile > Service > Routing/DHCP**
- **Feature Profile > Service > Routing/Multicast**
- **Feature Profile > Transport**
- **Feature Profile > Transport > Routing/BGP**
- **Feature Profile > Transport > WAN/VPN**
- **Feature Profile > Transport > WAN/VPN/Interface/Ethernet**

For more details on adding user groups, see [Create User Groups](#).

Run the Create Configuration Group Workflow

Minimum releases: Cisco IOS XE Catalyst SD-WAN Release 17.9.1a, Cisco vManage Release 20.9.1

From the Cisco SD-WAN Manager menu, choose **Workflows > Create Configuration Group**. Alternatively, do the following:

1. From the Cisco SD-WAN Manager menu, choose **Workflows > Workflow Library**.

2. On the **Workflow Library** page, in the **Library** section, click **Create Configuration Group**.
Alternatively, from Cisco IOS XE Catalyst SD-WAN Release 17.12.1a, choose **Configuration > Configuration Groups** in the Cisco SD-WAN Manager menu, and click **Add Configuration Group**.
In Cisco IOS XE Catalyst SD-WAN Release 17.11.1a and earlier, choose **Configuration > Templates > Configuration Groups**.

The workflow creates a configuration group, which includes various feature profiles.

Run the Rapid Site Configuration Group Workflow



Note This workflow is available only in Cisco vManage Release 20.8.x.

1. From the Cisco SD-WAN Manager menu, choose **Workflows > Workflow Library**.
2. On the **Workflow Library** page, start a new workflow or resume an existing workflow:
 - a. Start a new workflow: In the **Library** section, click **Create Configuration Group**. Alternatively, From Cisco IOS XE Catalyst SD-WAN Release 17.12.1a, choose **Configuration > Configuration Groups** in the Cisco SD-WAN Manager menu, and click **Add Configuration Group**.
In Cisco IOS XE Catalyst SD-WAN Release 17.11.1a and earlier, choose **Configuration > Templates > Configuration Groups**.
 - b. Resume an in-progress workflow: In the **In-progress** section, click **Rapid Site Configuration Group**.

The workflow generates the following components:

- A configuration group
- Four feature profiles: System profile, transport and management profile, service profile, and CLI profile (optional)

Run the Custom Configuration Group Workflow



Note This workflow is available only in Cisco vManage Release 20.8.x.

1. From the Cisco SD-WAN Manager menu, choose **Workflows > Workflow Library**.
2. On the **Workflow Library** page, start a new workflow or resume an existing workflow:
 - a. Start a new workflow: In the **Library** section, click **Create Configuration Group**. Alternatively, From Cisco IOS XE Catalyst SD-WAN Release 17.12.1a, choose **Configuration > Configuration Groups** in the Cisco SD-WAN Manager menu, and click **Add Configuration Group**.
In Cisco IOS XE Catalyst SD-WAN Release 17.11.1a and earlier, choose **Configuration > Templates > Configuration Groups**.

- b. Resume an in-progress workflow: In the **In-progress** section, click **Custom Configuration Group**.

The workflow generates the following components:

- A configuration group
- Three feature profiles: System profile, transport and management profile, and service profile