



Policy Manager Faults

First Published: July 23, 2014
Last Updated: July 23, 2014

fltFirmwareDownloadPolicyError

Fault Code: F10000242

Message

[type] Download Policy Configuration Error. Check scheduler Name, Username, Password and HTTP URL

Explanation

This fault typically occurs when the download configuration is not correct

Recommended Action

If you see this fault, take the following actions:

-
- Step 1** Review the fault and the error message on the FSM tab.
 - Step 2** Check scheduler Name, Username, Password and HTTP URL in download configuration
 - Step 3** If the above actions did not resolve the issue, create a **show tech-support** file and contact Cisco TAC.

Fault Details

Severity: minor
Cause: configuration-error
mibFaultCode: 10000242
mibFaultName: fltFirmwareDownloadPolicyError
moClass: firmware:DownloadPolicy
Type: management
Auto Cleared: true
Affected MO: domaingroup-[name]/dl-policy-[type]

fltCommSvcEpCommSvcNotDeployed

Fault Code: F10000339

Message

Communication Service configuration can't be deployed. Error: [configStatusMessage]

Explanation

This fault typically occurs because Cisco UCS Manager has detected an invalid communication policy configuration.

Recommended Action

If you see this fault, take the following actions:

-
- Step 1** Verify that ports configured across all communication services is unique.

Fault Details

```
Severity: major
Cause: comm-svc-config-error
mibFaultCode: 10000339
mibFaultName: fltCommSvcEpCommSvcNotDeployed
moClass: comm:SvcEp
Type: comm-svc-not-deployed
Auto Cleared: true
Affected MO: compute/sys-[id]/svc-ext
Affected MO: sys/svc-ext
```

fltPkiTPStatus

Fault Code: F10000591

Message

[name] Trustpoint's cert-chain is invalid, reason: [certStatus].

Explanation

This fault occurs when certificate status of TrustPoint has become invalid.

Recommended Action

None set.

Fault Details

```
Severity: major
Cause: invalid-trustpoint-cert-chain
mibFaultCode: 10000591
mibFaultName: fltPkiTPStatus
moClass: pki:TP
Type: security
Auto Cleared: true
Affected MO: domaingroup-[name]/tp-[name]
Affected MO: org-[name]/deviceprofile-[name]/pki-ext/tp-[name]
Affected MO: sys/pki-ext/tp-[name]
```

fltPkiKeyRingStatus

Fault Code: F10000592

Message

[name] Keyring's certificate is invalid, reason: [certStatus].

Explanation

This fault occurs when certificate status of Keyring has become invalid.

Recommended Action

None set.

Fault Details

Severity: major
Cause: invalid-keyring-certificate
mibFaultCode: 10000592
mibFaultName: fltPkiKeyRingStatus
moClass: pki:KeyRing
Type: security
Auto Cleared: true
Affected MO: org-[name]/deviceprofile-[name]/pki-ext/keyring-[name]
Affected MO: sys/pki-ext/keyring-[name]