

Balanceo de Carga y Failover L2TP

Contenido

[Introducción](#)

[Prerequisites](#)

[Requirements](#)

[Componentes Utilizados](#)

[Convenciones](#)

[Balanceo de Carga LNS](#)

[Failover LNS](#)

[Balanceo de Carga y Failover LNS](#)

[Prueba de laboratorio](#)

[Balanceo de Carga de LNS con Pares de Valor/Atributo Específicos del Proveedor de Cisco](#)

[LAC - Configuración](#)

[LNS - Configuración](#)

[Depuraciones tomadas de LAC](#)

[Conmutación por error de LNS con atributos/pares de valor específicos del proveedor de Cisco](#)

[Equilibrio de carga y conmutación por fallas de LNS con atributos/pares de valor específicos del proveedor de Cisco](#)

[Información Relacionada](#)

Introducción

Este documento explica las capacidades de un concentrador de acceso L2TP (LAC) que realiza funciones de equilibrio de carga y conmutación por fallo en varios servidores de red L2TP (LNS).

Prerequisites

Requirements

No hay requisitos específicos para este documento.

Componentes Utilizados

Este documento no tiene restricciones específicas en cuanto a versiones de software y de hardware.

Convenciones

Consulte [Convenciones de Consejos Técnicos Cisco para obtener más información sobre las convenciones del documento.](#)

Balanceo de Carga LNS

Al utilizar RADIUS para proporcionar información de túnel de red de acceso telefónico privada virtual (VPDN) a un LAC, es posible reenviar usuarios del mismo servicio de identificación de número marcado (DNIS) o dominio a varios LNS. Se trata de un requisito cuando los túneles y sesiones entrantes deben compartirse entre varios LNS para ayudar en la distribución de la carga y ofrecer niveles más altos de redundancia. Para habilitar la función de balanceo de carga, las direcciones IP para cada LNS disponible como punto final del túnel deben entregarse en el par de atributo/valor específico del proveedor (VSA) de Cisco.

```
Cisco:Avpair = "vpdn:ip-addresses=10.51.6.82,10.51.6.59"
```

El "," se utiliza como delimitador para indicar que hay varios puntos finales disponibles para el LAC (también puede utilizar un espacio como delimitador para indicar la prioridad igual de los puntos finales del túnel). El LAC selecciona qué punto final usar en función de la selección aleatoria de la primera dirección IP no activa entregada. Si está ocupado (el LAC no puede conectarse a la dirección IP), se selecciona la siguiente dirección IP. Si no hay direcciones IP no activas disponibles, la siguiente selección se basa en una dirección IP que está en 'estado de túnel abierto' y, por último, en una dirección IP que está 'pendiente del estado de túnel'.

Failover LNS

El software Cisco IOS® permite un máximo de seis niveles de prioridad al utilizar varios LNS. Al utilizar el '/' como delimitador, puede asignar diferentes grupos de prioridad a los LNS que se descargan en el LAC. Esto permite que ciertos LNS funcionen como el LNS primario y otros como respaldo. Como antes, los puntos finales del túnel se entregan en el par de atributos/valores de VSA de Cisco.

```
Cisco:Avpair = "vpdn:ip-addresses=10.51.6.82/10.51.6.59"
```

El delimitador '/' indica que 10.51.6.82 está en el Grupo de Prioridad 1 y 10.51.6.59 está en el Grupo de Prioridad 2.

Balanceo de Carga y Failover LNS

Es posible utilizar el balanceo de carga y la conmutación por fallas en el mismo perfil. Esto se logra mediante el par de atributos/valores de VSA de Cisco "vpdn:ip-address", como se muestra aquí:

```
Cisco:Avpair = "vpdn:ip-addresses=  
1.1.1.1,2.2.2.2/3.3.3.3,4.4.4.4/5.5.5.5,6.6.6.6"
```

Esto se interpreta como:

- los extremos de túnel 1.1.1.1 y 2.2.2.2 se encuentran en el grupo de prioridad 1
- los extremos de túnel 3.3.3.3 y 4.4.4.4 se encuentran en el grupo de prioridad 2
- los extremos de túnel 5.5.5.5 y 6.6.6.6 se encuentran en el grupo de prioridad 3

La función de balanceo de carga se realiza en Grupo de prioridad 1: no activo/no ocupado, abierto, pendiente. Si no hay ninguno disponible en este nivel de prioridad, vaya al siguiente nivel de prioridad y continúe con la lógica de selección.

Prueba de laboratorio

Las pruebas de esta sección muestran tres escenarios diferentes para el uso de las funciones de balanceo de carga y conmutación por fallas:

- Equilibrio de carga LNS con pares de atributos/valores específicos del proveedor de Cisco
- Conmutación por fallas LNS con pares de atributos/valores específicos del proveedor de Cisco
- Equilibrio de carga LNS y failover usando pares de atributos/valores específicos del proveedor de Cisco

Balanceo de Carga de LNS con Pares de Valor/Atributo Específicos del Proveedor de Cisco

Perfil RADIUS

Perfiles de usuario y túnel RADIUS en el servidor Merit RADIUS 3.6B:

```
2500-1 Password = "cisco"  
Service-Type = Framed,  
Framed-Protocol = PPP,  
Framed-IP-Address = 255.255.255.255
```

```
dnis:614629 Password = "cisco"  
Service-Type = Outbound,  
Cisco:Avpair = "vpdn:tunnel-type=l2tp",  
Cisco:Avpair = "vpdn:tunnel-id=hgw",  
Cisco:Avpair = "vpdn:ip-addresses=10.51.6.82,10.51.6.59",  
Cisco:Avpair = "vpdn:l2tp-tunnel-password=hello"
```

LAC - Configuración

```
aaa new-model  
!--- Enables Authentication, Authorization and Accounting functionality. aaa group server radius  
NSA_LAB server 10.51.6.3 auth-port 1645 acct-port 0 non-standard ! aaa authentication login  
default local aaa authentication ppp default local group NSA_LAB aaa authentication ppp DIAL  
group NSA_LAB local aaa authorization network default group NSA_LAB local aaa authorization  
network DIAL group NSA_LAB local !--- Authentication and Authorization will be implemented !---  
in sequence by the methods configured. vpdn enable !--- Enables the VPDN feature. no vpdn  
logging vpdn search-order dnis !--- Once LCP state is open, the dialed number is checked !--- to  
see if the remote is a VPDN user. interface Serial0:15 no ip address encapsulation ppp no  
logging event link-status dialer rotary-group 1 dialer-group 1 autodetect encapsulation ppp v120  
no snmp trap link-status isdn switch-type primary-net5 isdn incoming-voice modem compress stac !  
interface Dialer1 ip unnumbered Loopback0 encapsulation ppp no ip mroute-cache dialer-group 1  
autodetect encapsulation ppp v120 !--- Allows the encapsulation type to be dynamically set if  
the call !--- type is not identified in the ISDN Q.931 Lower Layer Compatibility. peer default  
ip address pool default compress stac ppp authentication chap pap DIAL ppp authorization DIAL !--  
-- The list-name DIAL is configured, that PPP Authentication and !--- Authorization will use.  
ppp chap hostname 5300-1 !--- The name 5300-1 is used for all CHAP challenge and response on !--  
- this interface. ppp multilink ! radius-server host 10.51.6.3 auth-port 1645 acct-port 1646  
non-standard !--- 'non-standard' indicates that the RADIUS Server will use !--- non standard  
RADIUS attributes.
```

LNS - Configuración

aaa new-model

!--- Enables Authentication, Authorization and Accounting functionality. aaa authentication login default local aaa authentication enable default group radius enable aaa authentication ppp default local aaa authentication ppp vpdn group radius none aaa authorization network default local none aaa authorization network vpdn group radius local *!--- Authentication and Authorization will be implemented !--- in sequence by the methods configured.* vpdn enable *!--- Enables the VPDN feature.* vpdn-group 1 accept-dialin protocol l2tp virtual-template 1 local name l2tp-gw l2tp tunnel password 7 1211001B1E04 *!--- The LNS will accept connections from the LAC using L2TP !--- using All Virtual-Access Interfaces that are created will be cloned from !--- Virtual-Template 1. The name 'l2tp-gw' is used to identify the password, !--- that will authenticate the tunnel, is encrypted.* interface Ethernet5/0 ip address 10.51.6.59 255.255.252.0 ! interface Virtual-Templatel ip unnumbered Ethernet5/0 no ip route-cache cef peer default ip address pool default ppp authentication chap vpdn ppp authorization vpdn ! radius-server host 10.51.6.3 auth-port 1645 acct-port 1646 non-standard *!--- 'non-standard' identifies the RADIUS Server will be !--- using nonstandard RADIUS attributes.*

Depuraciones tomadas de LAC

```
Jan 1 00:32:54.847: %LINK-3-UPDOWN: Interface Serial0:0, changed state to up
Jan 1 00:32:55.027: Se0:0 PPP: Treating connection as a callin
Jan 1 00:32:55.027: Se0:0 PPP: Phase is ESTABLISHING, Passive Open
Jan 1 00:32:55.027: Se0:0 CHAP: Using alternate hostname 5300-1
Jan 1 00:32:55.027: Se0:0 LCP: State is Listen
Jan 1 00:32:55.027: Se0:0 LCP: I CONFREQ [Listen] id 112 len 10
- snip -
Jan 1 00:32:55.063: Se0:0 LCP: State is Open
Jan 1 00:32:55.063: Se0:0 PPP: Phase is AUTHENTICATING, by this end
Jan 1 00:32:55.063: Se0:0 CHAP: Using alternate hostname 5300-1
Jan 1 00:32:55.063: Se0:0 CHAP: O CHALLENGE id 14 len 27 from "5300-1"
Jan 1 00:32:55.083: Se0:0 CHAP: I RESPONSE id 14 len 27 from "2500-1"
Jan 1 00:32:55.083: Se0:0 PPP: Phase is FORWARDING
Jan 1 00:32:55.083: Se0:0 VPDN: Got DNIS string 614629
Jan 1 00:32:55.083: Se0:0 VPDN: Looking for tunnel -- dnis:614629 --
Jan 1 00:32:55.083: Serial0:0 AAA/AUTHOR/VPDN (480033158):
Port='Serial0:0' list='default' service=NET
Jan 1 00:32:55.083: AAA/AUTHOR/VPDN: Serial0:0 (480033158) user='dnis:614629'
Jan 1 00:32:55.087: Serial0:0 AAA/AUTHOR/VPDN (480033158): send AV service=ppp
Jan 1 00:32:55.087: Serial0:0 AAA/AUTHOR/VPDN (480033158): send AV protocol=vpdn
Jan 1 00:32:55.087: Serial0:0 AAA/AUTHOR/VPDN (480033158): found list "default"
Jan 1 00:32:55.087: Serial0:0 AAA/AUTHOR/VPDN (480033158): Method=NSA_LAB (radius)
Jan 1 00:32:55.087: RADIUS: Initial Transmit Serial0:0 id 50 10.51.6.3:1645,
Access-Request, len 100
Jan 1 00:32:55.087: Attribute 4 6 0A330644
Jan 1 00:32:55.087: Attribute 5 6 00000000
Jan 1 00:32:55.087: Attribute 26 17 00000009020B5365
Jan 1 00:32:55.087: Attribute 61 6 00000002
Jan 1 00:32:55.087: Attribute 1 13 646E6973
Jan 1 00:32:55.087: Attribute 30 8 36313436
Jan 1 00:32:55.087: Attribute 2 18 F0AF3BC4
Jan 1 00:32:55.087: Attribute 6 6 00000005
Jan 1 00:32:55.091: RADIUS: Received from id 50 10.51.6.3:1645,
Access-Accept, len 167
Jan 1 00:32:55.091: Attribute 6 6 00000005
Jan 1 00:32:55.091: Attribute 26 29 0000000901177670
Jan 1 00:32:55.091: Attribute 26 26 0000000901147670
Jan 1 00:32:55.091: Attribute 26 47 0000000901297670
Jan 1 00:32:55.091: Attribute 26 39 0000000901217670
!--- LAC receives a call, negotiates PPP, LCP is declared Open, !--- the dialed number is queried to ascertain if this is a VPDN customer. !--- VPDN attempts to find an existing tunnel for the user, queries RADIUS for !--- the tunnel information. Jan 1 00:32:55.091: RADIUS: saved authorization data for user 61F40024 at 61F9813C Jan 1 00:32:55.091: RADIUS: cisco AVPair
```

"vpdn:tunnel-type=l2tp" Jan 1 00:32:55.091: RADIUS: cisco AVPair "vpdn:tunnel-id=hgw" Jan 1 00:32:55.091: RADIUS: cisco AVPair "vpdn:ip-addresses=10.51.6.82,10.51.6.59" Jan 1 00:32:55.095: RADIUS: cisco AVPair "vpdn:l2tp-tunnel-password=hello" Jan 1 00:32:55.095: AAA/AUTHOR (480033158): Post authorization status = PASS_ADD Jan 1 00:32:55.095: AAA/AUTHOR/VPDN: Processing AV service=ppp Jan 1 00:32:55.095: AAA/AUTHOR/VPDN: Processing AV protocol=vpdn Jan 1 00:32:55.095: AAA/AUTHOR/VPDN: Processing AV tunnel-type=l2tp Jan 1 00:32:55.095: AAA/AUTHOR/VPDN: Processing AV tunnel-id=hgw **Jan 1 00:32:55.095: AAA/AUTHOR/VPDN: Processing AV ip-addresses= 10.51.6.82,10.51.6.59**

Jan 1 00:32:55.095: AAA/AUTHOR/VPDN: Processing AV l2tp-tunnel-password=hello
Jan 1 00:32:55.095: Se0:0 VPDN/RPMS/: Got tunnel info for dnis:614629
Jan 1 00:32:55.095: Se0:0 VPDN/RPMS/: LAC hgw
Jan 1 00:32:55.095: Se0:0 VPDN/RPMS/: l2tp-busy-disconnect yes
Jan 1 00:32:55.095: Se0:0 VPDN/RPMS/: l2tp-tunnel-password xxxxxx
Jan 1 00:32:55.095: Se0:0 VPDN/RPMS/: 2 IP addresses
Jan 1 00:32:55.095: Se0:0 VPDN/RPMS/: IP 10.51.6.82 Priority 1
Jan 1 00:32:55.095: Se0:0 VPDN/RPMS/: IP 10.51.6.59 Priority 1
Jan 1 00:32:55.095: Se0:0 VPDN/: curlvl 1 Address 0: 10.51.6.82, priority 1
Jan 1 00:32:55.095: Se0:0 VPDN/: Select non-active address 10.51.6.82, priority 1
!--- The tunnel information is downloaded, using Cisco VSA. Two LNS IP !--- Addresses are used with a ',' as the delimiter, indicating that both !--- have equal priority. In this case 10.51.6.82 is selected as the tunnel !--- endpoint. Jan 1 00:32:55.095: Se0:0 VPDN: Find LNS process created Jan 1 00:32:55.095: Tnl 49467 L2TP: SM State idle Jan 1 00:32:55.095: Tnl 49467 L2TP: O SCCRQ Jan 1 00:32:55.099: Tnl 49467 L2TP: Tunnel state change from idle to wait-ctl-reply Jan 1 00:32:55.099: Tnl 49467 L2TP: SM State wait-ctl-reply **Jan 1 00:32:55.099: Se0:0 VPDN: Forward to address 10.51.6.82**

Jan 1 00:32:55.099: Se0:0 VPDN: Pending
Jan 1 00:32:55.099: Se0:0 VPDN: Process created
Jan 1 00:32:55.191: Tnl 49467 L2TP: I SCCRP from l2tp-gw
Jan 1 00:32:55.191: Tnl 49467 L2TP: Got a challenge from remote peer, l2tp-gw
Jan 1 00:32:55.191: Tnl 49467 L2TP: Got a response from remote peer, l2tp-gw
Jan 1 00:32:55.191: Tnl 49467 L2TP: Tunnel Authentication success
Jan 1 00:32:55.191: Tnl 49467 L2TP: Tunnel state change from wait-ctl-reply to established

Jan 1 00:32:55.191: Tnl 49467 L2TP: O SCCCN to l2tp-gw tnlid 62193
Jan 1 00:32:55.195: Tnl 49467 L2TP: SM State established
Jan 1 00:32:55.195: Tnl/Cl 49467/16 L2TP: Session FS enabled
Jan 1 00:32:55.195: Tnl/Cl 49467/16 L2TP: Session state change from idle to wait-for-tunnel
Jan 1 00:32:55.195: Se0:0 Tnl/Cl 49467/16 L2TP: Create session
Jan 1 00:32:55.195: Tnl 49467 L2TP: SM State established
Jan 1 00:32:55.195: Se0:0 Tnl/Cl 49467/16 L2TP: O ICRQ to l2tp-gw 62193/0
Jan 1 00:32:55.195: Se0:0 Tnl/Cl 49467/16 L2TP: Session state change from wait-for-tunnel to wait-reply
Jan 1 00:32:55.195: Se0:0 VPDN: 2500-1 is forwarded
Jan 1 00:32:55.327: Se0:0 Tnl/Cl 49467/16 L2TP: O ICCN to l2tp-gw 62193/17
Jan 1 00:32:55.327: Se0:0 Tnl/Cl 49467/16 L2TP: Session state change from wait-reply to established

Jan 1 00:32:56.195: %LINEPROTO-5-UPDOWN: Line protocol on Interface Serial0:0, changed state to up
Jan 1 00:33:00.851: %ISDN-6-CONNECT:Interface Serial0:0 is now connected to 2500-1
Jan 1 00:33:06.111: %ISDN-6-CONNECT:
Interface Serial0:1 is now connected to N/A N/A
!--- Second call is received by the LAC, !--- the dialed number is a VPDN customer. Jan 1 00:33:35.027: As1 LCP: I CONFREQ [Closed] id 1 len 23 - snip - **Jan 1 00:33:39.275: As1 LCP: State is Open**

Jan 1 00:33:39.275: As1 PPP: Phase is AUTHENTICATING, by this end
Jan 1 00:33:39.275: As1 CHAP: Using alternate hostname 5300-1
Jan 1 00:33:39.275: As1 CHAP: O CHALLENGE id 2 len 27 from "5300-1"
Jan 1 00:33:39.383: As1 CHAP: I RESPONSE id 2 len 25 from "paul"
Jan 1 00:33:39.383: As1 PPP: Phase is FORWARDING
Jan 1 00:33:39.383: As1 VPDN: Got DNIS string 614629
Jan 1 00:33:39.383: As1 VPDN: Looking for tunnel -- dnis:614629 --
Jan 1 00:33:39.387: Async1 AAA/AUTHOR/VPDN (3019717950):

```
Port='Async1' list='default' service=NET
Jan 1 00:33:39.387: AAA/AUTHOR/VPDN: Async1 (3019717950) user='dnis:614629'
Jan 1 00:33:39.387: Async1 AAA/AUTHOR/VPDN (3019717950): send AV service=ppp
Jan 1 00:33:39.387: Async1 AAA/AUTHOR/VPDN (3019717950): send AV protocol=vpdn
Jan 1 00:33:39.387: Async1 AAA/AUTHOR/VPDN (3019717950): found list "default"
Jan 1 00:33:39.387: Async1 AAA/AUTHOR/VPDN (3019717950): Method=NSA_LAB (radius)
Jan 1 00:33:39.387: RADIUS: Initial Transmit Async1 id 52 10.51.6.3:1645,
Access-Request, len 97
Jan 1 00:33:39.387: Attribute 4 6 0A330644
Jan 1 00:33:39.387: Attribute 5 6 00000001
Jan 1 00:33:39.387: Attribute 26 14 0000000902084173
Jan 1 00:33:39.387: Attribute 61 6 00000000
Jan 1 00:33:39.387: Attribute 1 13 646E6973
Jan 1 00:33:39.387: Attribute 30 8 36313436
Jan 1 00:33:39.387: Attribute 2 18 E9164E4C
Jan 1 00:33:39.387: Attribute 6 6 00000005
Jan 1 00:33:39.391: RADIUS: Received from id 52 10.51.6.3:1645,
Access-Accept, len 167
Jan 1 00:33:39.391: Attribute 6 6 00000005
Jan 1 00:33:39.391: Attribute 26 29 0000000901177670
Jan 1 00:33:39.391: Attribute 26 26 0000000901147670
Jan 1 00:33:39.391: Attribute 26 47 0000000901297670
Jan 1 00:33:39.391: Attribute 26 39 0000000901217670
Jan 1 00:33:39.391: RADIUS: saved authorization data for user
621904CC at 61FAB9EC
Jan 1 00:33:39.391: RADIUS: cisco AVPair "vpdn:tunnel-type=l2tp"
Jan 1 00:33:39.391: RADIUS: cisco AVPair "vpdn:tunnel-id=hgw"
Jan 1 00:33:39.391: RADIUS: cisco AVPair "vpdn:ip-addresses=10.51.6.82,10.51.6.59"
Jan 1 00:33:39.391: RADIUS: cisco AVPair "vpdn:l2tp-tunnel-password=hello"
Jan 1 00:33:39.395: AAA/AUTHOR (3019717950): Post authorization status = PASS_ADD
Jan 1 00:33:39.395: AAA/AUTHOR/VPDN: Processing AV service=ppp
Jan 1 00:33:39.395: AAA/AUTHOR/VPDN: Processing AV protocol=vpdn
Jan 1 00:33:39.395: AAA/AUTHOR/VPDN: Processing AV tunnel-type=l2tp
Jan 1 00:33:39.395: AAA/AUTHOR/VPDN: Processing AV tunnel-id=hgw
Jan 1 00:33:39.395: AAA/AUTHOR/VPDN:
Processing AV ip-addresses=10.51.6.82,10.51.6.59
Jan 1 00:33:39.395: AAA/AUTHOR/VPDN:
Processing AV l2tp-tunnel-password=hello
Jan 1 00:33:39.395: As1 VPDN/RPMS/: Got tunnel info for dnis:614629
Jan 1 00:33:39.395: As1 VPDN/RPMS/: LAC hgw
Jan 1 00:33:39.395: As1 VPDN/RPMS/: l2tp-busy-disconnect yes
Jan 1 00:33:39.395: As1 VPDN/RPMS/: l2tp-tunnel-password xxxxxx
Jan 1 00:33:39.395: As1 VPDN/RPMS/: 2 IP addresses
Jan 1 00:33:39.395: As1 VPDN/RPMS/: IP 10.51.6.82 Priority 1
Jan 1 00:33:39.395: As1 VPDN/RPMS/: IP 10.51.6.59 Priority 1
Jan 1 00:33:39.395: As1 VPDN/: curlvl 1 Address 1: 10.51.6.59, priority 1
Jan 1 00:33:39.395: As1 VPDN/: Select non-active address 10.51.6.59, priority 1
!--- The second non-active endpoint is selected 10.51.6.59 !--- and the control connection is
established. Jan 1 00:33:39.395: As1 VPDN: Find LNS process created Jan 1 00:33:39.395: Tnl
20770 L2TP: SM State idle Jan 1 00:33:39.395: Tnl 20770 L2TP: O SCCRQ Jan 1 00:33:39.399: Tnl
20770 L2TP: Tunnel state change from idle to wait-ctl-reply Jan 1 00:33:39.399: Tnl 20770 L2TP:
SM State wait-ctl-reply Jan 1 00:33:39.399: As1 VPDN: Forward to address 10.51.6.59
Jan 1 00:33:39.399: As1 VPDN: Pending
Jan 1 00:33:39.399: As1 VPDN: Process created
Jan 1 00:33:39.399: Tnl 20770 L2TP: I SCCRP from l2tp-gw
Jan 1 00:33:39.399: Tnl 20770 L2TP: Got a challenge from remote peer, l2tp-gw
Jan 1 00:33:39.399: Tnl 20770 L2TP: Got a response from remote peer, l2tp-gw
Jan 1 00:33:39.399: Tnl 20770 L2TP: Tunnel Authentication success
Jan 1 00:33:39.399: Tnl 20770 L2TP: Tunnel state change from
wait-ctl-reply to established
Jan 1 00:33:39.403: Tnl 20770 L2TP: O SCCCN to l2tp-gw tnlid 42921
Jan 1 00:33:39.403: Tnl 20770 L2TP: SM State established
Jan 1 00:33:39.403: As1 VPDN: Forwarding...
Jan 1 00:33:39.403: Tnl/C1 20770/17 L2TP: Session FS enabled
```

Jan 1 00:33:39.403: Tnl/Cl 20770/17 L2TP: Session state change from
idle to wait-for-tunnel
Jan 1 00:33:39.403: As1 Tnl/Cl 20770/17 L2TP: Create session
Jan 1 00:33:39.403: Tnl 20770 L2TP: SM State established
Jan 1 00:33:39.403: As1 Tnl/Cl 20770/17 L2TP: O ICRQ to l2tp-gw 42921/0
Jan 1 00:33:39.403: As1 Tnl/Cl 20770/17 L2TP: Session state change from
wait-for-tunnel to wait-reply
Jan 1 00:33:39.403: As1 VPDN: paul is forwarded
Jan 1 00:33:39.407: As1 Tnl/Cl 20770/17 L2TP: O ICCN to l2tp-gw 42921/16
**Jan 1 00:33:39.407: As1 Tnl/Cl 20770/17 L2TP: Session state change from
wait-reply to established**

