

Hardware cliente del Easy VPN Remote IOS a un ejemplo de configuración del Easy VPN Server PIX

Contenido

[Introducción](#)

[prerrequisitos](#)

[Requisitos](#)

[Componentes Utilizados](#)

[Convenciones](#)

[Configurar](#)

[Diagrama de la red](#)

[Configuraciones](#)

[Verificación](#)

[Easy VPN Server PIX](#)

[Cliente del hardware remoto del Cisco IOS Easy VPN](#)

[Troubleshooting](#)

[Easy VPN Server PIX](#)

[Cliente del hardware remoto del Cisco IOS Easy VPN](#)

[Información Relacionada](#)

[Introducción](#)

Este documento proporciona una configuración de muestra para el IPsec entre el hardware cliente del Easy VPN Remote de Cisco IOS® y el Easy VPN Server PIX.

Nota: La característica del Easy VPN Remote también se refiere como el hardware cliente y cliente EzVPN.

Refiera al [EzVPN con el NEM en el router IOS con el ejemplo de configuración concentrador VPN 3000](#) para la información sobre cómo configurar a un router del Cisco IOS como un EzVPN en el [Modo de ampliación de la red \(NEM\)](#) para conectar con un Cisco VPN 3000 Concentrator.

Refiera al [PIX/ASA 7.x y posterior: VPN fácil con el Túnel dividido ASA 5500 como el servidor y Cisco 871 como el ejemplo de la configuración VNP remota sencilla](#) para la información sobre cómo configurar el IPsec entre un PIX/ASA 7.x de Cisco y un Cisco 871 Router que usa el VPN fácil.

Refiera al [router IOS: VPN fácil \(EzVPN\) con el ejemplo de configuración del Modo de ampliación de la red \(NEM\)](#) para la información sobre cómo configurar un Cisco 7200 Router como EzVPN y al Cisco 871 Router como el cliente del Easy VPN Remote.

prerrequisitos

Requisitos

Asegúrese de cumplir estos requisitos antes de intentar esta configuración:

- Asegúrese de que su Cisco IOS y soportes del hardware que el Easy VPN Remote ofrece. Refiera al [Software Advisor \(clientes registrados solamente\)](#).
- Asegúrese de que su Easy VPN Server sea un firewall PIX que ejecuta la versión de software PIX 6.2 o más adelante.
- Asegúrese de que usted tenga una licencia 3DES instalada en su PIX. Refiera a la [actualización la clave de activación](#).

Componentes Utilizados

La información que contiene este documento se basa en las siguientes versiones de software y hardware.

- El cliente del hardware remoto del Cisco IOS Easy VPN es un 831 Router que funciona con el Cisco IOS Software Release 12.3(8)T.
- El Easy VPN Server es un PIX 525 que funciona con la versión de software PIX 6.3(3).

La información que contiene este documento se creó a partir de los dispositivos en un ambiente de laboratorio específico. Todos los dispositivos que se utilizan en este documento se pusieron en funcionamiento con una configuración verificada (predeterminada). Si la red está funcionando, asegúrese de haber comprendido el impacto que puede tener cualquier comando.

Convenciones

Consulte [Convenciones de Consejos TécnicosCisco](#) para obtener más información sobre las convenciones del documento.


Configurar

En esta sección encontrará la información para configurar las funciones descritas en este documento.

Nota: Utilice la herramienta [Command Lookup Tool \(clientes registrados solamente\)](#) para obtener más información sobre los comandos utilizados en esta sección.

Diagrama de la red

En este documento, se utiliza esta configuración de red:



Configuraciones

En este documento, se utilizan estas configuraciones:

- [Easy VPN Server PIX](#)
- [Cliente del hardware remoto del Cisco IOS Easy VPN](#)

Easy VPN Server PIX

```

pix525#show running-config
: Saved
:
PIX Version 6.3(3)
interface ethernet0 auto
interface ethernet1 auto
interface ethernet2 auto shutdown
interface ethernet3 auto shutdown
interface ethernet4 auto shutdown
interface ethernet5 auto shutdown
interface ethernet6 auto shutdown
nameif ethernet0 outside security0
nameif ethernet1 inside security100
nameif ethernet2 intf2 security4
nameif ethernet3 intf3 security6
nameif ethernet4 intf4 security8
nameif ethernet5 intf5 security10
nameif ethernet6 intf6 security12
enable password 8Ry2YjIyt7RRXU24 encrypted
passwd 2KFQnbNIdI.2KYOU encrypted
hostname pix525
fixup protocol dns maximum-length 512
fixup protocol ftp 21
fixup protocol h323 h225 1720
fixup protocol h323 ras 1718-1719
fixup protocol http 80
fixup protocol rsh 514
fixup protocol rtsp 554
fixup protocol sip 5060
fixup protocol sip udp 5060
fixup protocol skinny 2000
fixup protocol smtp 25
fixup protocol sqlnet 1521
fixup protocol tftp 69
names

!--- Specify the access list to bypass !--- Network
Address Translation (NAT) for VPN traffic. access-list
nonat permit ip 172.16.1.0 255.255.255.0 192.168.1.0
255.255.255.0 !--- Specify the split tunneling access
list. access-list 110 permit ip 172.16.1.0 255.255.255.0
192.168.1.0 255.255.255.0 pager lines 24 mtu outside
1500 mtu inside 1500 mtu intf2 1500 mtu intf3 1500 mtu

```

```

intf4 1500 mtu intf5 1500 mtu intf6 1500 ip address
outside 10.66.79.72 255.255.255.224 ip address inside
172.16.1.254 255.255.255.0 no ip address intf2 no ip
address intf3 no ip address intf4 no ip address intf5 no
ip address intf6 ip audit info action alarm ip audit
attack action alarm no failover failover timeout 0:00:00
failover poll 15 no failover ip address outside no
failover ip address inside no failover ip address intf2
no failover ip address intf3 no failover ip address
intf4 no failover ip address intf5 no failover ip
address intf6 pdm history enable arp timeout 14400 !---
Configure NAT/Port Address Translation (PAT) !--- for
non-encrypted traffic, as well as NAT for IPSec traffic.
global (outside) 1 interface nat (inside) 0 access-list
nonat nat (inside) 1 172.16.1.0 255.255.255.0 0 0 route
outside 0.0.0.0 0.0.0.0 10.66.79.65 1 timeout xlate
3:00:00 timeout conn 1:00:00 half-closed 0:10:00 udp
0:02:00 rpc 0:10:00 h225 1:00:00 timeout h323 0:05:00
mgcp 0:05:00 sip 0:30:00 sip_media 0:02:00 timeout uauth
0:05:00 absolute aaa-server TACACS+ protocol tacacs+
aaa-server RADIUS protocol radius aaa-server LOCAL
protocol local no snmp-server location no snmp-server
contact snmp-server community public no snmp-server
enable traps floodguard enable sysopt connection permit-
ipsec !--- Configure IPSec transform set and dynamic
crypto map. crypto ipsec transform-set tripledes esp-
3des esp-sha-hmac crypto dynamic-map dynmap 10 set
transform-set tripledes crypto map mymap 10 ipsec-isakmp
dynamic dynmap !--- Apply crypto map to the outside
interface. crypto map mymap interface outside !---
Configure Phase 1 Internet Security Association !--- and
Key Management Protocol (ISAKMP) parameters. isakmp
enable outside isakmp identity address isakmp policy 10
authentication pre-share isakmp policy 10 encryption
3des isakmp policy 10 hash sha isakmp policy 10 group 2
isakmp policy 10 lifetime 86400 !--- Configure VPN Group
parameters that are sent down to the client. vpngroup
vpn-hw-client-group dns-server 172.16.1.1 vpngroup vpn-
hw-client-group wins-server 172.16.1.1 vpngroup vpn-hw-
client-group default-domain cisco.com vpngroup vpn-hw-
client-group split-tunnel 110 vpngroup vpn-hw-client-
group idle-time 1800 vpngroup vpn-hw-client-group
password ***** telnet timeout 5 ssh timeout 5 console
timeout 0 terminal width 80
Cryptochecksum:700fe4d4e7fcdc6750953e64046930c0 : end

```

Cliente del hardware remoto del Cisco IOS Easy VPN

```

831#show running-config
831#show run
Building configuration...

Current configuration : 1226 bytes
!
version 12.3
no service pad
service timestamps debug datetime msec
service timestamps log datetime msec
no service password-encryption
!
hostname 831
!
boot-start-marker

```

```
boot-end-marker
!
!
no aaa new-model
ip subnet-zero
!
!
!
!
ip name-server 172.16.1.1
ip ips po max-events 100
no ftp-server write-enable
!
!
!
!
!
!
!
!
!
!
!
crypto ipsec client ezvpn vpn-hw-client
connect auto
group vpn-hw-client-group key password
mode network-extension
peer 10.66.79.72
!
!
!
!
interface Ethernet0
 ip address 192.168.1.254 255.255.255.0
 crypto ipsec client ezvpn vpn-hw-client inside
!
interface Ethernet1
 ip address 10.66.79.126 255.255.255.224
 duplex auto
 crypto ipsec client ezvpn vpn-hw-client
!
interface FastEthernet1
 no ip address
 duplex auto
 speed auto
!
interface FastEthernet2
 no ip address
 duplex auto
 speed auto
!
interface FastEthernet3
 no ip address
 duplex auto
 speed auto
!
interface FastEthernet4
 no ip address
 duplex auto
 speed auto
!
ip classless
ip route 0.0.0.0 0.0.0.0 10.66.79.97
!
ip http server
no ip http secure-server
```

```

!
!
no cdp run
!
control-plane
!
!
line con 0
  no modem enable
  transport preferred all
  transport output all
line aux 0
line vty 0 4
!
scheduler max-task-time 5000
end

```

Verificación

Utilice estas secciones para confirmar que su configuración trabaja correctamente.

- [Easy VPN Server PIX](#)
- [Cliente del hardware remoto del Cisco IOS Easy VPN](#)

Easy VPN Server PIX

[La herramienta Output Interpreter Tool \(clientes registrados solamente\)](#) (OIT) soporta ciertos comandos show. Utilice la OIT para ver un análisis del resultado del comando show.

- **muestre isakmp crypto sa** — Visualiza todas las asociaciones de seguridad actuales del Internet Key Exchange (IKE) (SA) en un par.

```

pix525(config)#show crypto isakmp sa
Total      : 1
Embryonic  : 0

```

dst	src	state	pending	created
10.66.79.72	10.66.79.126	QM_IDLE	0	1

- **show crypto ipsec sa** — Muestra los IPsec SA construidos entre pares.

```

pix525(config)#show crypto ipsec sa

```

```

!--- This command is issued after a ping !--- is attempted from the PC behind the !--- Easy
VPN Client to the PC !--- behind the server. interface: outside Crypto map tag: mymap, local
addr. 10.66.79.72 local ident (addr/mask/prot/port): (172.16.1.0/255.255.255.0/0/0) remote
ident (addr/mask/prot/port): (192.168.1.0/255.255.255.0/0/0) current_peer: 10.66.79.126:500
dynamic allocated peer ip: 0.0.0.0 PERMIT, flags={} #pkts encaps: 5, #pkts encrypt: 5, #pkts
digest 5 #pkts decaps: 5, #pkts decrypt: 5, #pkts verify 5 #pkts compressed: 0, #pkts
decompressed: 0 #pkts not compressed: 0, #pkts compr. failed: 0, #pkts decompress failed: 0
#send errors 0, #rcv errors 0 !--- ping packets !--- are successfully exchanged between the
!--- Easy VPN Remote Hardware Client !--- and the Easy VPN Server. local crypto endpt.:
10.66.79.72, remote crypto endpt.: 10.66.79.126 path mtu 1500, ipsec overhead 56, media mtu
1500 current outbound spi: 13f1aa83 inbound esp sas: spi: 0xf4dd4178(4108140920) transform:
esp-3des esp-sha-hmac , in use settings = {Tunnel, } slot: 0, conn id: 1, crypto map: mymap
sa timing: remaining key lifetime (k/sec): (4607999/28567) IV size: 8 bytes replay detection
support: Y inbound ah sas: inbound pcp sas: outbound esp sas: spi: 0x13f1aa83(334604931)
transform: esp-3des esp-sha-hmac , in use settings = {Tunnel, } slot: 0, conn id: 2, crypto
map: mymap sa timing: remaining key lifetime (k/sec): (4607999/28567) IV size: 8 bytes
replay detection support: Y outbound ah sas: outbound pcp sas:

```

[Cliente del hardware remoto del Cisco IOS Easy VPN](#)

[La herramienta Output Interpreter Tool \(clientes registrados solamente\)](#) (OIT) soporta ciertos comandos show. Utilice la OIT para ver un análisis del resultado del comando show.

- **show crypto isakmp sa** — Muestra todas las asociaciones actuales de seguridad (SA) IKE de un par.

```
831#show crypto isakmp sa
dst          src          state         conn-id slot
10.66.79.72  10.66.79.126 QM_IDLE      1      0
```

- **show crypto ipsec sa** — Muestra los IPsec SA construidos entre pares.

```
831#show crypto ipsec sa
```

```
!--- This command is issued after a ping !--- is attempted from the PC behind the !--- Easy VPN Client to the PC !--- behind the server. interface: Ethernet1 Crypto map tag: Ethernet1-head-0, local addr. 10.66.79.126 protected vrf: local ident (addr/mask/prot/port): (192.168.1.0/255.255.255.0/0/0) remote ident (addr/mask/prot/port): (172.16.1.0/255.255.255.0/0/0) current_peer: 10.66.79.72:500 PERMIT, flags={origin_is_acl,} #pkts encaps: 5, #pkts encrypt: 5, #pkts digest: 5 #pkts decaps: 5, #pkts decrypt: 5, #pkts verify: 5 #pkts compressed: 0, #pkts decompressed: 0 #pkts not compressed: 0, #pkts compr. failed: 0 #pkts not decompressed: 0, #pkts decompress failed: 0 #send errors 0, #recv errors 0 !--- ping packets !--- are successfully exchanged between !--- the Easy VPN Remote Hardware Client !--- and the Easy VPN Server. local crypto endpt.: 10.66.79.126, remote crypto endpt.: 10.66.79.72 path mtu 1500, media mtu 1500 current outbound spi: F4DD4178 inbound esp sas: spi: 0x13F1AA83(334604931) transform: esp-3des esp-sha-hmac , in use settings = {Tunnel, } slot: 0, conn id: 20, flow_id: 1, crypto map: Ethernet1-head-0 crypto engine type: Hardware, engine_id: 2 sa timing: remaining key lifetime (k/sec): (4444258/28648) ike_cookies: A12E6D0D 2C8D9B92 41AB02FB A00A5B03 IV size: 8 bytes replay detection support: Y inbound ah sas: inbound pcp sas: outbound esp sas: spi: 0xF4DD4178(4108140920) transform: esp-3des esp-sha-hmac , in use settings = {Tunnel, } slot: 0, conn id: 21, flow_id: 2, crypto map: Ethernet1-head-0 crypto engine type: Hardware, engine_id: 2 sa timing: remaining key lifetime (k/sec): (4444258/28647) ike_cookies: A12E6D0D 2C8D9B92 41AB02FB A00A5B03 IV size: 8 bytes replay detection support: Y outbound ah sas: outbound pcp sas:
```

- **EzVPN de la demostración crypto ipsec client** — Información de la configuración del dispositivo del cliente VPN o del Easy VPN Remote de las visualizaciones.

```
831#show crypto ipsec client ezvpn
Easy VPN Remote Phase: 2
```

```
Tunnel name : vpn-hw-client
Inside interface list: Ethernet0,
Outside interface: Ethernet1
Current State: IPSEC_ACTIVE
Last Event: SOCKET_UP
DNS Primary: 172.16.1.1
DNS Secondary: 172.16.1.1
NBMS/WINS Primary: 172.16.1.1
NBMS/WINS Secondary: 172.16.1.1
Default Domain: cisco.com
Split Tunnel List: 1
    Address      : 172.16.1.0
    Mask         : 255.255.255.0
    Protocol     : 0x0
    Source Port  : 0
    Dest Port    : 0
```

[Troubleshooting](#)

Estas secciones proporcionan la información que usted puede utilizar para resolver problemas su

configuración.

- [Easy VPN Server PIX](#)
- [Cliente del hardware remoto del Cisco IOS Easy VPN](#)

Si usted ha configurado el hardware cliente y el Easy VPN Server del Easy VPN Remote como descrito en este documento y usted todavía experimente los problemas, recolecte la **salida de los debugs de** cada dispositivo y la salida de los **comandos show** para el análisis por el Centro de Asistencia Técnica de Cisco (TAC).

Refiera al [Troubleshooting de IP Security - Entendiendo y con los comandos debug y resolver problemas el PIX de pasar el tráfico de datos en un túnel de IPSec establecido](#) para más información sobre el troubleshooting.

[Easy VPN Server PIX](#)

[La herramienta Output Interpreter Tool \(clientes registrados solamente\)](#) (OIT) soporta ciertos comandos show. Utilice la OIT para ver un análisis del resultado del comando show.

Nota: Consulte [Información Importante sobre Comandos de Debug](#) antes de usar un **comando debug**.

- `debug crypto ipsec` — Muestra los IPSec Negotiations de la Fase 2.
- `debug crypto isakmp` — Muestra las negociaciones ISAKMP para la fase 1.

La salida de muestra se muestra aquí:

```
pix525(config)#  
!--- As soon as the crypto ipsec client ezvpn vpn-hw-client command !--- is issued on the  
outside interface of the Cisco IOS Easy VPN Remote !--- Hardware Client, the server receives an  
IKE negotiation request.
```

```
crypto_isakmp_process_block:src:10.66.79.126, dest:10.66.79.72 spt:500 dpt:500  
OAK_AG exchange  
ISAKMP (0): processing SA payload. message ID = 0
```

```
ISAKMP (0): Checking ISAKMP transform 1 against priority 10 policy  
ISAKMP:      encryption 3DES-CBC  
ISAKMP:      hash SHA  
ISAKMP:      default group 2  
ISAKMP:      extended auth pre-share (init)  
ISAKMP:      life type in seconds  
ISAKMP:      life duration (VPI) of  0x0 0x20 0xc4 0x9b  
ISAKMP (0): atts are not acceptable. Next payload is 3  
ISAKMP (0): Checking ISAKMP transform 2 against priority 10 policy  
ISAKMP:      encryption 3DES-CBC  
ISAKMP:      hash MD5  
ISAKMP:      default group 2  
ISAKMP:      extended auth pre-share (init)  
ISAKMP:      life type in seconds  
ISAKMP:      life duration (VPI) of  0x0 0x20 0xc4 0x9b  
ISAKMP (0): atts are not acceptable. Next payload is 3  
ISAKMP (0): Checking ISAKMP transform 3 against priority 10 policy  
ISAKMP:      encryption DES-CBC  
ISAKMP:      hash SHA  
ISAKMP:      default group 2  
ISAKMP:      extended auth pre-share (init)
```



```
ISAKMP:      life type in seconds
ISAKMP:      life duration (VPI) of  0x0 0x20 0xc4 0x9b
ISAKMP (0):  atts are not acceptable. Next payload is 3
ISAKMP (0):  Checking ISAKMP transform 4 against priority 10 policy
ISAKMP:      encryption DES-CBC
ISAKMP:      hash MD5
ISAKMP:      default group 2
ISAKMP:      extended auth pre-share (init)
ISAKMP:      life type in seconds
ISAKMP:      life duration (VPI) of  0x0 0x20 0xc4 0x9b
ISAKMP (0):  atts are not acceptable. Next payload is 3
ISAKMP (0):  Checking ISAKMP transform 5 against priority 10 policy
ISAKMP:      encryption 3DES-CBC
ISAKMP:      hash SHA
ISAKMP:      default group 2
ISAKMP:      auth pre-share
ISAKMP:      life type in seconds
ISAKMP:      life duration (VPI) of  0x0 0x20 0xc4 0x9b
ISAKMP (0):  atts are acceptable. Next payload is 3
ISAKMP (0):  processing vendor id payload

ISAKMP (0:0): vendor ID is NAT-T
ISAKMP (0):  processing vendor id payload

ISAKMP (0:0): vendor ID is NAT-T
ISAKMP (0):  processing KE payload. message ID = 0

ISAKMP (0):  processing NONCE payload. message ID = 0

ISAKMP (0):  processing ID payload. message ID = 0
ISAKMP (0):  processing vendor id payload

ISAKMP (0):  remote peer supports dead peer detection

ISAKMP (0):  processing vendor id payload

ISAKMP (0):  received xauth v6 vendor id

ISAKMP (0):  processing vendor id payload

ISAKMP (0):  claimed IOS but failed authentication

ISAKMP (0):  processing vendor id payload

ISAKMP (0):  speaking to a Unity client

ISAKMP (0):  ID payload
      next-payload : 10
      type          : 1
      protocol      : 17
      port          : 500
      length        : 8
ISAKMP (0):  Total payload length: 12
return status is IKMP_NO_ERROR
crypto_isakmp_process_block:src:10.66.79.126, dest:10.66.79.72 spt:500 dpt:500
OAK_AG exchange
ISAKMP (0):  processing HASH payload. message ID = 0
ISAKMP (0):  processing NOTIFY payload 24578 protocol 1
      spi 0, message ID = 0
ISAKMP (0):  processing notify INITIAL_CONTACTIPSEC(key_engine): got a queue event...
IPSEC(key_engine_delete_sas): rec'd delete notify from ISAKMP
IPSEC(key_engine_delete_sas): delete all SAs shared with      10.66.79.126

ISAKMP (0):  SA has been authenticated
```

```

ISAKMP: Created a peer struct for 10.66.79.126, peer port 62465
return status is IKMP_NO_ERROR
ISAKMP (0): sending phase 1 RESPONDER_LIFETIME notify
ISAKMP (0): sending NOTIFY message 24576 protocol 1
VPN Peer: ISAKMP: Added new peer: ip:10.66.79.126/500 Total VPN Peers:1
VPN Peer: ISAKMP: Peer ip:10.66.79.126/500 Ref cnt incremented to:1 Total
VPN Peers:1
ISAKMP: peer is a remote access client
crypto_isakmp_process_block:src:10.66.79.126, dest:10.66.79.72 spt:500 dpt:500
ISAKMP_TRANSACTION exchange
ISAKMP (0:0): processing transaction payload from 10.66.79.126.
message ID = 63324444
ISAKMP: Config payload CFG_REQUEST
ISAKMP (0:0): checking request:
ISAKMP: attribute      IP4_DNS (3)
ISAKMP: attribute      IP4_DNS (3)
ISAKMP: attribute      IP4_NBNS (4)
ISAKMP: attribute      IP4_NBNS (4)
ISAKMP: attribute      ALT_SPLIT_INCLUDE (28676)
ISAKMP: attribute      ALT_SPLITDNS_NAME (28675)
ISAKMP: attribute      ALT_DEF_DOMAIN (28674)
ISAKMP: attribute      UNKNOWN (28673)
Unsupported Attr: 28673
ISAKMP: attribute      UNKNOWN (28678)
Unsupported Attr: 28678
ISAKMP: attribute      ALT_PFS (28679)
ISAKMP: attribute      ALT_BACKUP_SERVERS (28681)
ISAKMP: attribute      APPLICATION_VERSION (7)
ISAKMP (0:0): responding to peer config from 10.66.79.126. ID = 2563858956
return status is IKMP_NO_ERROR
crypto_isakmp_process_block:src:10.66.79.126, dest:10.66.79.72 spt:500 dpt:500
OAK_QM exchange
oakley_process_quick_mode:
OAK_QM_IDLE
ISAKMP (0): processing SA payload. message ID = 3238088328

ISAKMP : Checking IPsec proposal 1

ISAKMP: transform 1, ESP_3DES
ISAKMP:  attributes in transform:
ISAKMP:  encaps is 1
ISAKMP:  SA life type in seconds
ISAKMP:  SA life duration (VPI) of  0x0 0x20 0xc4 0x9b
ISAKMP:  SA life type in kilobytes
ISAKMP:  SA life duration (VPI) of  0x0
crypto_isakmp_process_block:src:10.66.79.126, dest:10.66.79.72 spt:500 dpt:500
OAK_QM exchange
ISADB: reaper checking SA 0x3c6420c, conn_id = 0

```

[Cliente del hardware remoto del Cisco IOS Easy VPN](#)

[La herramienta Output Interpreter Tool \(clientes registrados solamente\)](#) (OIT) soporta ciertos comandos show. Utilice la OIT para ver un análisis del resultado del comando show.

Nota: Consulte [Información Importante sobre Comandos de Debug](#) antes de usar un **comando debug**.

- debug crypto ipsec — Muestra los IPsec Negotiations de la Fase 2.
- debug crypto isakmp — Muestra las negociaciones ISAKMP para la fase 1.

La salida de muestra se muestra aquí:

831(config)#int eth 1

831(config-if)#crypto ipsec client ezvpn vpn-hw-client

```
*Mar 1 01:42:18.739: ISAKMP: callback: no SA found for 0.0.0.0/0.0.0.0 [vrf 0]
*Mar 1 01:42:18.739: %CRYPTO-6-ISAKMP_ON_OFF: ISAKMP is ON
*Mar 1 01:42:18.743: ISAKMP: Looking for a matching key for 10.66.79.72 in default
*Mar 1 01:42:18.743: ISAKMP: received ke message (1/1)
*Mar 1 01:42:18.743: ISAKMP:(0:0:N/A:0): SA request profile is (NULL)
*Mar 1 01:42:18.743: ISAKMP: Created a peer struct for 10.66.79.72, peer port 500
*Mar 1 01:42:18.743: ISAKMP: Locking peer struct 0x81F05E5C, IKE refcount
  1 for isakmp_initiator
*Mar 1 01:42:18.747: ISAKMP:(0:0:N/A:0):Setting client config settings 81C8F564
*Mar 1 01:42:18.747: ISAKMP: local port 500, remote port 500
*Mar 1 01:42:18.747: insert sa successfully sa = 81C8EEB8
*Mar 1 01:42:18.747: ISAKMP:(0:0:N/A:0): client mode configured.
*Mar 1 01:42:18.751: ISAKMP:(0:0:N/A:0): constructed NAT-T vendor-03 ID
*Mar 1 01:42:18.751: ISAKMP:(0:0:N/A:0): constructed NAT-T vendor-02 ID
*Mar 1 01:42:19.203: ISAKMP:(0:1:HW:2):SA is doing pre-shared key authentication
  plus XAUTH using id type ID_KEY_ID
*Mar 1 01:42:19.203: ISAKMP (0:268435457): ID payload
  next-payload : 13
  type          : 11
  group id      : vpn-hw-client-group
  protocol      : 17
  port          : 0
  length        : 27
*Mar 1 01:42:19.203: ISAKMP:(0:1:HW:2):Total payload length: 27
*Mar 1 01:42:19.207: ISAKMP:(0:1:HW:2):Input = IKE_MESG_FROM_IPSEC, IKE_SA_REQ_AM
*Mar 1 01:42:19.207: ISAKMP:(0:1:HW:2):Old State = IKE_READY New State = IKE_I_AM1

*Mar 1 01:42:19.207: ISAKMP:(0:1:HW:2): beginning Aggressive Mode exchange
*Mar 1 01:42:19.207: ISAKMP:(0:1:HW:2): sending packet to 10.66.79.72
  my_port 500 peer_port 500 (I) AG_INIT_EXCH
*Mar 1 01:42:19.267: ISAKMP (0:268435457): received packet from 10.66.79.72
  dport 500 sport 500 Global (I) AG_INIT_EXCH
*Mar 1 01:42:19.271: ISAKMP:(0:1:HW:2): processing SA payload. message ID = 0
*Mar 1 01:42:19.271: ISAKMP:(0:1:HW:2): processing ID payload. message ID = 0
*Mar 1 01:42:19.271: ISAKMP (0:268435457): ID payload
  next-payload : 10
  type          : 1
  address       : 10.66.79.72
  protocol      : 17
  port          : 500
  length        : 12
*Mar 1 01:42:19.271: ISAKMP:(0:1:HW:2): processing vendor id payload
*Mar 1 01:42:19.271: ISAKMP:(0:1:HW:2): vendor ID seems Unity/DPD but major
  215 mismatch
*Mar 1 01:42:19.275: ISAKMP:(0:1:HW:2): vendor ID is XAUTH
*Mar 1 01:42:19.275: ISAKMP:(0:1:HW:2): processing vendor id payload
*Mar 1 01:42:19.275: ISAKMP:(0:1:HW:2): vendor ID is DPD
*Mar 1 01:42:19.275: ISAKMP:(0:1:HW:2): processing vendor id payload
*Mar 1 01:42:19.275: ISAKMP:(0:1:HW:2): vendor ID is Unity
*Mar 1 01:42:19.275: ISAKMP:(0:1:HW:2): local preshared key found
*Mar 1 01:42:19.275: ISAKMP : Scanning profiles for xauth ...
*Mar 1 01:42:19.279: ISAKMP:(0:1:HW:2): Authentication by xauth preshared
*Mar 1 01:42:19.279: ISAKMP:(0:1:HW:2):Checking ISAKMP transform 1 against
  priority 65527 policy
*Mar 1 01:42:19.279: ISAKMP:      encryption 3DES-CBC
*Mar 1 01:42:19.279: ISAKMP:      hash SHA
*Mar 1 01:42:19.279: ISAKMP:      default group 2
*Mar 1 01:42:19.279: ISAKMP:      auth pre-share
*Mar 1 01:42:19.279: ISAKMP:      life type in seconds
*Mar 1 01:42:19.279: ISAKMP:      life duration (VPI) of 0x0 0x20 0xC4 0x9B
```

```
*Mar 1 01:42:19.279: ISAKMP:(0:1:HW:2):Authentication method offered does
not match policy!
*Mar 1 01:42:19.283: ISAKMP:(0:1:HW:2):atts are not acceptable.
Next payload is 0
*Mar 1 01:42:19.283: ISAKMP:(0:1:HW:2):Checking ISAKMP transform 1
against priority 65528 policy
*Mar 1 01:42:19.283: ISAKMP: encryption 3DES-CBC
*Mar 1 01:42:19.283: ISAKMP: hash SHA
*Mar 1 01:42:19.283: ISAKMP: default group 2
*Mar 1 01:42:19.283: ISAKMP: auth pre-share
*Mar 1 01:42:19.283: ISAKMP: life type in seconds
*Mar 1 01:42:19.283: ISAKMP: life duration (VPI) of 0x0 0x20 0xC4 0x9B
*Mar 1 01:42:19.283: ISAKMP:(0:1:HW:2):Hash algorithm offered does not
match policy!
*Mar 1 01:42:19.283: ISAKMP:(0:1:HW:2):atts are not acceptable. Next
payload is 0
*Mar 1 01:42:19.287: ISAKMP:(0:1:HW:2):Checking ISAKMP transform 1
against priority 65529 policy
*Mar 1 01:42:19.287: ISAKMP: encryption 3DES-CBC
*Mar 1 01:42:19.287: ISAKMP: hash SHA
*Mar 1 01:42:19.287: ISAKMP: default group 2
*Mar 1 01:42:19.287: ISAKMP: auth pre-share
*Mar 1 01:42:19.287: ISAKMP: life type in seconds
*Mar 1 01:42:19.287: ISAKMP: life duration (VPI) of 0x0 0x20 0xC4 0x9B
*Mar 1 01:42:19.287: ISAKMP:(0:1:HW:2):Encryption algorithm offered does
not match policy!
*Mar 1 01:42:19.287: ISAKMP:(0:1:HW:2):atts are not acceptable.
Next payload is 0
*Mar 1 01:42:19.291: ISAKMP:(0:1:HW:2):Checking ISAKMP transform
1 against priority 65530 policy
*Mar 1 01:42:19.291: ISAKMP: encryption 3DES-CBC
*Mar 1 01:42:19.291: ISAKMP: hash SHA
*Mar 1 01:42:19.291: ISAKMP: default group 2
*Mar 1 01:42:19.291: ISAKMP: auth pre-share
*Mar 1 01:42:19.291: ISAKMP: life type in seconds
*Mar 1 01:42:19.291: ISAKMP: life duration (VPI) of 0x0 0x20 0xC4 0x9B
*Mar 1 01:42:19.291: ISAKMP:(0:1:HW:2):Encryption algorithm offered
does not match policy!
*Mar 1 01:42:19.291: ISAKMP:(0:1:HW:2):atts are not acceptable. Next
payload is 0
*Mar 1 01:42:19.295: ISAKMP:(0:1:HW:2):Checking ISAKMP transform 1
against priority 65531 policy
*Mar 1 01:42:19.295: ISAKMP: encryption 3DES-CBC
*Mar 1 01:42:19.295: ISAKMP: hash SHA
*Mar 1 01:42:19.295: ISAKMP: default group 2
*Mar 1 01:42:19.295: ISAKMP: auth pre-share
*Mar 1 01:42:19.295: ISAKMP: life type in seconds
*Mar 1 01:42:19.295: ISAKMP: life duration (VPI) of 0x0 0x20 0xC4 0x9B
*Mar 1 01:42:19.295: ISAKMP:(0:1:HW:2):atts are acceptable. Next payload is 0
*Mar 1 01:42:19.295: ISAKMP:(0:1:HW:2): processing KE payload. message ID = 0
*Mar 1 01:42:19.747: ISAKMP:(0:1:HW:2): processing NONCE payload. message ID = 0
*Mar 1 01:42:19.747: ISAKMP:(0:1:HW:2):SKEYID state generated
*Mar 1 01:42:19.747: ISAKMP:(0:1:HW:2): processing HASH payload. message ID = 0
*Mar 1 01:42:19.751: ISAKMP:(0:1:HW:2):SA authentication status:
authenticated
*Mar 1 01:42:19.751: ISAKMP:(0:1:HW:2):SA has been authenticated with 10.66.79.72
*Mar 1 01:42:19.751: ISAKMP: Trying to insert a peer
10.66.79.126/10.66.79.72/500/, and inserted successfully.
*Mar 1 01:42:19.751: ISAKMP:(0:1:HW:2):Send initial contact
*Mar 1 01:42:19.759: ISAKMP:(0:1:HW:2): sending packet to 10.66.79.72
my_port 500 peer_port 500 (I) AG_INIT_EXCH
*Mar 1 01:42:19.759: ISAKMP:(0:1:HW:2):Input = IKE_MESG_FROM_PEER, IKE_AM_EXCH
*Mar 1 01:42:19.759: ISAKMP:(0:1:HW:2):Old State = IKE_I_AM1
New State = IKE_P1_COMPLETE
```

```
*Mar 1 01:42:19.763: ISAKMP:(0:1:HW:2):Need config/address
*Mar 1 01:42:19.763: ISAKMP:(0:1:HW:2):Need config/address
*Mar 1 01:42:19.763: ISAKMP: set new node -1731108340 to CONF_ADDR
*Mar 1 01:42:19.763: ISAKMP: Sending APPLICATION_VERSION string:
Cisco IOS Software, C831 Software (C831-K9O3SY6-M), Version 12.3(8)T,
RELEASE SOFTWARE (fc2)
Technical Support: http://www.cisco.com/techsupport
Copyright (c) 1986-2004 by Cisco Systems, Inc.
Compiled Fri 14-May-04 01:40 by eaarmas
*Mar 1 01:42:19.775: ISAKMP:(0:1:HW:2): initiating peer config to
10.66.79.72. ID = -1731108340
*Mar 1 01:42:19.775: ISAKMP:(0:1:HW:2): sending packet to 10.66.79.72
my_port 500 peer_port 500 (I) CONF_ADDR
*Mar 1 01:42:19.775: ISAKMP:(0:1:HW:2):Input = IKE_MSG_INTERNAL,
IKE_PHASE1_COMPLETE
*Mar 1 01:42:19.775: ISAKMP:(0:1:HW:2):Old State = IKE_P1_COMPLETE
New State = IKE_CONFIG_MODE_REQ_SENT
*Mar 1 01:42:19.775: ISAKMP (0:268435457): received packet from 10.66.79.72
dport 500 sport 500 Global (I) CONF_ADDR
*Mar 1 01:42:19.779: ISAKMP: set new node -531260300 to CONF_ADDR
*Mar 1 01:42:19.783: ISAKMP:(0:1:HW:2): processing HASH payload.
message ID = -531260300
*Mar 1 01:42:19.783: ISAKMP:(0:1:HW:2): processing NOTIFY
RESPONDER_LIFETIME protocol 1
spi 0, message ID = -531260300, sa = 81C8EEB8
*Mar 1 01:42:19.783: ISAKMP:(0:1:HW:2):SA authentication status:
authenticated
*Mar 1 01:42:19.787: ISAKMP:(0:1:HW:2): processing responder lifetime
*Mar 1 01:42:19.787: ISAKMP:(0:1:HW:2): start processing isakmp
responder lifetime
*Mar 1 01:42:19.787: ISAKMP:(0:1:HW:2): restart ike sa timer to 86400 secs
*Mar 1 01:42:19.787: ISAKMP:(0:1:HW:2):deleting node -531260300 error
FALSE reason "Informational (in) state 1"
*Mar 1 01:42:19.787: ISAKMP:(0:1:HW:2):Input = IKE_MSG_FROM_PEER,
IKE_INFO_NOTIFY
*Mar 1 01:42:19.787: ISAKMP:(0:1:HW:2):Old State = IKE_CONFIG_MODE_REQ_SENT
New State = IKE_CONFIG_MODE_REQ_SENT
*Mar 1 01:42:19.791: ISAKMP (0:268435457): received packet from 10.66.79.72
dport 500 sport 500 Global (I) CONF_ADDR
*Mar 1 01:42:19.795: ISAKMP:(0:1:HW:2):processing transaction payload from
10.66.79.72. message ID = -1731108340
*Mar 1 01:42:19.795: ISAKMP: Config payload REPLY
*Mar 1 01:42:19.799: ISAKMP(0:268435457) process config reply
*Mar 1 01:42:19.799: ISAKMP:(0:1:HW:2):deleting node -1731108340 error
FALSE reason "Transaction mode done"
*Mar 1 01:42:19.799: ISAKMP:(0:1:HW:2):Input = IKE_MSG_FROM_PEER,
IKE_CFG_REPLY
*Mar 1 01:42:19.799: ISAKMP:(0:1:HW:2):Old State = IKE_CONFIG_MODE_REQ_SENT
New State = IKE_P1_COMPLETE
*Mar 1 01:42:19.807: ISAKMP:(0:1:HW:2):Input = IKE_MSG_INTERNAL,
IKE_PHASE1_COMPLETE
*Mar 1 01:42:19.807: ISAKMP:(0:1:HW:2):Old State = IKE_P1_COMPLETE
New State = IKE_P1_COMPLETE
*Mar 1 01:42:19.815: IPSEC(sa_request): ,
(key eng. msg.) OUTBOUND local= 10.66.79.126, remote= 10.66.79.72,
local_proxy= 192.168.1.0/255.255.255.0/0/0 (type=4),
remote_proxy= 172.16.1.0/255.255.255.0/0/0 (type=4),
protocol= ESP, transform= esp-3des esp-sha-hmac (Tunnel),
lifedur= 2147483s and 4608000kb,
```

```

spi= 0x13F1AA83(334604931), conn_id= 0, keysize= 0, flags= 0x400A
*Mar 1 01:42:19.815: IPSEC(sa_request): ,
(key eng. msg.) OUTBOUND local= 10.66.79.126, remote= 10.66.79.72,
local_proxy= 192.168.1.0/255.255.255.0/0/0 (type=4),
remote_proxy= 172.16.1.0/255.255.255.0/0/0 (type=4),
protocol= ESP, transform= esp-3des esp-md5-hmac (Tunnel),
lifedur= 2147483s and 4608000kb,
spi= 0xAD8C95C7(2911671751), conn_id= 0, keysize= 0, flags= 0x400A
*Mar 1 01:42:19.819: IPSEC(sa_request): ,
(key eng. msg.) OUTBOUND local= 10.66.79.126, remote= 10.66.79.72,
local_proxy= 192.168.1.0/255.255.255.0/0/0 (type=4),
remote_proxy= 172.16.1.0/255.255.255.0/0/0 (type=4),
protocol= ESP, transform= esp-des esp-sha-hmac (Tunnel),
lifedur= 2147483s and 4608000kb,
spi= 0x7B5EBFA(129362938), conn_id= 0, keysize= 0, flags= 0x400A
*Mar 1 01:42:19.819: IPSEC(sa_request): ,
(key eng. msg.) OUTBOUND local= 10.66.79.126, remote= 10.66.79.72,
local_proxy= 192.168.1.0/255.255.255.0/0/0 (type=4),
remote_proxy= 172.16.1.0/255.255.255.0/0/0 (type=4),
protocol= ESP, transform= esp-des esp-md5-hmac (Tunnel),
lifedur= 2147483s and 4608000kb,
spi= 0x702568AE(1881499822), conn_id= 0, keysize= 0, flags= 0x400A
*Mar 1 01:42:19.823: ISAKMP: received ke message (1/4)
*Mar 1 01:42:19.823: ISAKMP: set new node 0 to QM_IDLE
*Mar 1 01:42:19.823: ISAKMP:(0:1:HW:2): sitting IDLE. Starting QM
immediately (QM_IDLE )
*Mar 1 01:42:19.823: ISAKMP:(0:1:HW:2):beginning Quick Mode exchange,
M-ID of -1056878968
*Mar 1 01:42:19.835: ISAKMP:(0:1:HW:2): sending packet to 10.66.79.72
my_port 500 peer_port 500 (I) QM_IDLE
*Mar 1 01:42:19.835: ISAKMP:(0:1:HW:2):Node -1056878968, Input =
IKE_MSG_INTERNAL, IKE_INIT_QM
*Mar 1 01:42:19.843: ISAKMP:(0:1:HW:2):Old State = IKE_QM_READY
New State = IKE_QM_I_QM1
*Mar 1 01:42:19.859: ISAKMP (0:268435457): received packet from
10.66.79.72 dport 500 sport 500 Global (I) QM_IDLE
*Mar 1 01:42:19.863: ISAKMP:(0:1:HW:2): processing HASH payload.
message ID = -1056878968
*Mar 1 01:42:19.863: ISAKMP:(0:1:HW:2): processing SA payload.
message ID = -1056878968
*Mar 1 01:42:19.863: ISAKMP:(0:1:HW:2):Checking IPsec proposal 1
*Mar 1 01:42:19.863: ISAKMP: transform 1, ESP_3DES
*Mar 1 01:42:19.863: ISAKMP: attributes in transform:
*Mar 1 01:42:19.863: ISAKMP: encaps is 1 (Tunnel)
*Mar 1 01:42:19.867: ISAKMP: SA life type in seconds
*Mar 1 01:42:19.867: ISAKMP: SA life duration (VPI) of 0x0 0x20 0xC4 0x9B
*Mar 1 01:42:19.867: ISAKMP: SA life type in kilobytes
*Mar 1 01:42:19.867: ISAKMP: SA life duration (VPI) of 0x0 0x46 0x50 0x0
*Mar 1 01:42:19.867: ISAKMP: authenticator is HMAC-SHA
*Mar 1 01:42:19.867: ISAKMP:(0:1:HW:2):atts are acceptable.
*Mar 1 01:42:19.871: IPSEC(validate_proposal_request): proposal part #1,
(key eng. msg.) INBOUND local= 10.66.79.126, remote= 10.66.79.72,
local_proxy= 192.168.1.0/255.255.255.0/0/0 (type=4),
remote_proxy= 172.16.1.0/255.255.255.0/0/0 (type=4),
protocol= ESP, transform= esp-3des esp-sha-hmac (Tunnel),
lifedur= 0s and 0kb,
spi= 0x0(0), conn_id= 0, keysize= 0, flags= 0x2
*Mar 1 01:42:19.871: Crypto mapdb : proxy_match
src addr : 192.168.1.0
dst addr : 172.16.1.0
protocol : 0
src port : 0
dst port : 0
*Mar 1 01:42:19.871: ISAKMP:(0:1:HW:2): processing NONCE payload.

```

```
message ID = -1056878968
*Mar 1 01:42:19.875: ISAKMP:(0:1:HW:2): processing ID payload.
message ID = -1056878968
*Mar 1 01:42:19.875: ISAKMP:(0:1:HW:2): processing ID payload.
message ID = -1056878968
*Mar 1 01:42:19.875: ISAKMP:(0:1:HW:2): processing NOTIFY
RESPONDER_LIFETIME protocol 3
spi 4108140920, message ID = -1056878968, sa = 81C8EEB8
*Mar 1 01:42:19.875: ISAKMP:(0:1:HW:2):SA authentication status:
authenticated
*Mar 1 01:42:19.875: ISAKMP:(0:1:HW:2): processing responder lifetime
*Mar 1 01:42:19.875: ISAKMP (268435457): responder lifetime of 28800s
*Mar 1 01:42:19.879: IPsec: Flow_switching Allocated flow for flow_id 268435457
*Mar 1 01:42:19.879: IPsec: Flow_switching Allocated flow for flow_id 268435458
*Mar 1 01:42:19.887: %CRYPTO-5-SESSION_STATUS: Crypto tunnel is UP .
Peer 10.66.79.72:500 Id: 10.66.79.72
*Mar 1 01:42:19.887: ISAKMP: Locking peer struct 0x81F05E5C, IPSEC
refcount 1 for for stuff_ke
*Mar 1 01:42:19.887: ISAKMP:(0:1:HW:2): Creating IPsec SAs
*Mar 1 01:42:19.895: inbound SA from 10.66.79.72 to 10.66.79.126
(f/i) 0/ 0
(proxy 172.16.1.0 to 192.168.1.0)
*Mar 1 01:42:19.895: has spi 0x13F1AA83 and conn_id 20 and flags 2
*Mar 1 01:42:19.895: lifetime of 28790 seconds
*Mar 1 01:42:19.895: lifetime of 4608000 kilobytes
*Mar 1 01:42:19.895: has client flags 0x0
*Mar 1 01:42:19.895: outbound SA from 10.66.79.126 to 10.66.79.72
(f/i) 0/0
(proxy 192.168.1.0 to 172.16.1.0)
*Mar 1 01:42:19.895: has spi -186826376 and conn_id 21 and flags A
*Mar 1 01:42:19.895: lifetime of 28790 seconds
*Mar 1 01:42:19.895: lifetime of 4608000 kilobytes
*Mar 1 01:42:19.895: has client flags 0x0
*Mar 1 01:42:19.899: IPSEC(key_engine): got a queue event with 2 kei messages
*Mar 1 01:42:19.899: IPSEC(initialize_sas): ,
(key eng. msg.) INBOUND local= 10.66.79.126, remote= 10.66.79.72,
local_proxy= 192.168.1.0/255.255.255.0/0/0 (type=4),
remote_proxy= 172.16.1.0/255.255.255.0/0/0 (type=4),
protocol= ESP, transform= esp-3des esp-sha-hmac (Tunnel),
lifedur= 28790s and 4608000kb,
spi= 0x13F1AA83(334604931), conn_id= 268435476, keysize= 0, flags= 0x2
*Mar 1 01:42:19.899: IPSEC(initialize_sas): ,
(key eng. msg.) OUTBOUND local= 10.66.79.126, remote= 10.66.79.72,
local_proxy= 192.168.1.0/255.255.255.0/0/0 (type=4),
remote_proxy= 172.16.1.0/255.255.255.0/0/0 (type=4),
protocol= ESP, transform= esp-3des esp-sha-hmac (Tunnel),
lifedur= 28790s and 4608000kb,
spi= 0xF4DD4178(4108140920), conn_id= 268435477, keysize= 0, flags= 0xA
*Mar 1 01:42:19.903: Crypto mapdb : proxy_match
src addr : 192.168.1.0
dst addr : 172.16.1.0
protocol : 0
src port : 0
dst port : 0
*Mar 1 01:42:19.903: IPSEC(crypto_ipsec_sa_find_ident_head):
reconnecting with the same proxies and 10.66.79.72
*Mar 1 01:42:19.903: IPSEC(policy_db_add_ident): src 192.168.1.0,
dest 172.16.1.0, dest_port 0
*Mar 1 01:42:19.907: IPSEC(create_sa): sa created,
(sa) sa_dest= 10.66.79.126, sa_prot= 50,
sa_spi= 0x13F1AA83(334604931),
sa_trans= esp-3des esp-sha-hmac , sa_conn_id= 268435476
*Mar 1 01:42:19.907: IPSEC(create_sa): sa created,
```

```

(sa) sa_dest= 10.66.79.72, sa_prot= 50,
    sa_spi= 0xF4DD4178(4108140920),
    sa_trans= esp-3des esp-sha-hmac , sa_conn_id= 268435477
*Mar 1 01:42:19.911: ISAKMP:(0:1:HW:2): sending packet to
10.66.79.72 my_port 500 peer_port 500 (I) QM_IDLE
*Mar 1 01:42:19.911: ISAKMP:(0:1:HW:2):deleting node -1056878968
error FALSE reason "No Error"
*Mar 1 01:42:19.911: ISAKMP:(0:1:HW:2):Node -1056878968, Input =
IKE_MSG_FROM_PEER, IKE_QM_EXCH
*Mar 1 01:42:19.911: ISAKMP:(0:1:HW:2):Old State = IKE_QM_I_QM1
New State = IKE_QM_PHASE2_COMPLETE
*Mar 1 01:43:09.787: ISAKMP:(0:1:HW:2):purging node -531260300
*Mar 1 01:43:09.799: ISAKMP:(0:1:HW:2):purging node -1731108340
*Mar 1 01:43:09.911: ISAKMP:(0:1:HW:2):purging node -1056878968

```

- **debug vpnclient** — Visualiza las negociaciones específicas al cliente VPN.

La salida de muestra se muestra aquí:

```

831(config)#int eth 1
831(config-if)#crypto ipsec client ezvpn vpn-hw-client
*Mar 1 01:49:26.543: %CRYPTO-6-ISAKMP_ON_OFF: ISAKMP is ON
*Mar 1 01:49:26.547: EZVPN(vpn-hw-client): Current State: IDLE
*Mar 1 01:49:26.547: EZVPN(vpn-hw-client): Event: VALID_CONFIG_ENTERED
*Mar 1 01:49:26.547: EZVPN(vpn-hw-client): ezvpn_check_tunnel_interface_state
*Mar 1 01:49:26.547: EZVPN(vpn-hw-client): New State: VALID_CFG
*Mar 1 01:49:26.547: EZVPN(vpn-hw-client): Current State: VALID_CFG
*Mar 1 01:49:26.547: EZVPN(vpn-hw-client): Event: VALID_CONFIG_ENTERED
*Mar 1 01:49:26.547: EZVPN(vpn-hw-client): No state change
*Mar 1 01:49:26.547: EZVPN(vpn-hw-client): Current State: VALID_CFG
*Mar 1 01:49:26.551: EZVPN(vpn-hw-client): Event: TUNNEL_INTERFACE_UP
*Mar 1 01:49:26.551: EZVPN(vpn-hw-client): ezvpn_check_tunnel_interface_address
*Mar 1 01:49:26.551: EZVPN(vpn-hw-client): New State: TUNNEL_INT_UP
*Mar 1 01:49:26.551: EZVPN(vpn-hw-client): Current State: TUNNEL_INT_UP
*Mar 1 01:49:26.551: EZVPN(vpn-hw-client): Event: TUNNEL_HAS_PUBLIC_IP_ADD
*Mar 1 01:49:26.551: EZVPN(vpn-hw-client): New State: CONNECT_REQUIRED
*Mar 1 01:49:26.551: EZVPN(vpn-hw-client): Current State: CONNECT_REQUIRED
*Mar 1 01:49:26.551: EZVPN(vpn-hw-client): Event: CONNECT
*Mar 1 01:49:26.555: EZVPN(vpn-hw-client): ezvpn_connect_request
*Mar 1 01:49:26.555: EZVPN(vpn-hw-client): New State: READY
*Mar 1 01:49:27.535: EZVPN(vpn-hw-client): Current State: READY
*Mar 1 01:49:27.535: EZVPN(vpn-hw-client): Event: CONN_UP
*Mar 1 01:49:27.535: EZVPN(vpn-hw-client): ezvpn_conn_up A12E6D0D D9C3B1AE
41AB02FB 62DD1B01
*Mar 1 01:49:27.539: EZVPN(vpn-hw-client): No state change
*Mar 1 01:49:27.563: EZVPN(vpn-hw-client): Current State: READY
*Mar 1 01:49:27.563: EZVPN(vpn-hw-client): Event: MODE_CONFIG_REPLY
*Mar 1 01:49:27.563: EZVPN(vpn-hw-client): ezvpn_mode_config
*Mar 1 01:49:27.563: EZVPN(vpn-hw-client): ezvpn_parse_mode_config_msg
*Mar 1 01:49:27.563: EZVPN: Attributes sent in message:
*Mar 1 01:49:27.563:           DNS Primary: 172.16.1.1
*Mar 1 01:49:27.567:           DNS Secondary: 172.16.1.1
*Mar 1 01:49:27.567:           NBMS/WINS Primary: 172.16.1.1
*Mar 1 01:49:27.567:           NBMS/WINS Secondary: 172.16.1.1
*Mar 1 01:49:27.567:           Split Tunnel List: 1
*Mar 1 01:49:27.567:           Address      : 172.16.1.0
*Mar 1 01:49:27.567:           Mask          : 255.255.255.0
*Mar 1 01:49:27.567:           Protocol     : 0x0
*Mar 1 01:49:27.567:           Source Port: 0
*Mar 1 01:49:27.567:           Dest Port  : 0
*Mar 1 01:49:27.567:           Default Domain: cisco.com
*Mar 1 01:49:27.567: EZVPN: Unknown/Unsupported Attr: PFS (0x7007)
*Mar 1 01:49:27.571: EZVPN(vpn-hw-client): ezvpn_nat_config

```



```
*Mar 1 01:49:27.571: EZVPN: close old connection, len 0
*Mar 1 01:49:27.575: EZVPN(vpn-hw-client): New State: SS_OPEN
*Mar 1 01:49:27.587: EZVPN(vpn-hw-client): Current State: SS_OPEN
*Mar 1 01:49:27.587: EZVPN(vpn-hw-client): Event: SOCKET_READY
*Mar 1 01:49:27.587: EZVPN(vpn-hw-client): No state change
*Mar 1 01:49:27.619: %CRYPTO-5-SESSION_STATUS: Crypto tunnel is UP .
Peer 10.66.79.72:500      Id: 10.66.79.72
*Mar 1 01:49:27.623: EZVPN(vpn-hw-client): Current State: SS_OPEN
*Mar 1 01:49:27.623: EZVPN(vpn-hw-client): Event: MTU_CHANGED
*Mar 1 01:49:27.623: EZVPN(vpn-hw-client): No state change
*Mar 1 01:49:27.627: EZVPN(vpn-hw-client): Current State: SS_OPEN
*Mar 1 01:49:27.627: EZVPN(vpn-hw-client): Event: SOCKET_UP
*Mar 1 01:49:27.631: ezvpn_socket_up
*Mar 1 01:49:27.631: EZVPN(vpn-hw-client): New State: IPSEC_ACTIVE
```

[Información Relacionada](#)

- [Página de soporte de la serie PIX 500](#)
- [Documentación para Firewall PIX](#)
- [Referencias de Comando PIX](#)
- [Página de Soporte de IPsec Negotiation/IKE Protocols](#)