

TechNote de dépannage du redémarrage des serveurs UCS série C

Contenu

[Introduction](#)

[Conditions préalables](#)

[Conditions requises](#)

[Components Used](#)

[Sortie attendue pour différentes conditions de redémarrage](#)

[Redémarrer à partir du système d'exploitation \(vSphere 5.0\)](#)

[Cycle d'alimentation à partir de l'interface utilisateur CIMC](#)

[Désactiver l'interface utilisateur CIMC](#)

[Mise sous tension de l'interface utilisateur CIMC](#)

[Bouton d'alimentation à l'avant du serveur \(OFF\)](#)

[Bouton d'alimentation à l'avant du serveur \(ON\)](#)

Introduction

Ce document fournit la sortie de `/var/log/messages` (également trouvée dans le journal de consignation des défaillances embarquées (OBFL)) pour un C210-M2 qui représente la sortie attendue lors de différentes conditions de redémarrage. Lorsque vous dépannez des problèmes de démarrage du serveur Cisco Unified Computing System (UCS) série C, vous pouvez commencer par les journaux `/var/log/messages` et OBFL. Ces journaux se trouvent dans les fichiers de support technique. L'idée est que vous pouvez faire correspondre la sortie d'un message de support technique particulier avec la sortie de ce document afin de confirmer ce qui a déclenché le redémarrage.

Conditions préalables

Conditions requises

Cisco vous recommande de prendre connaissance des rubriques suivantes :

- VMware vSphere 5.0
- Cisco Integrated Management Controller (CIMC)

Components Used

Ce document n'est pas limité à des versions de matériel et de logiciel spécifiques.

The information in this document was created from the devices in a specific lab environment. All of the devices used in this document started with a cleared (default) configuration. If your network is live, make sure that you understand the potential impact of any command.

Sortie attendue pour différentes conditions de redémarrage

Redémarrer à partir du système d'exploitation (vSphere 5.0)

```
5:2012 May 11 13:49:38:BMC:kernel:--<5>LPC Reset ISR -> ResetState: 1
7:2012 May 11 13:49:38:BMC:kernel:--<7>[peci_init_hardware]:490:peci:
  unregistered IRQ: [13]
7:2012 May 11 13:49:38:BMC:kernel:--<7>[block_transfer_deallocate_entire_list]:
  1141:block_transfer_deallocate_entire_list
7:2012 May 11 13:49:38:BMC:kernel:--<7>[block_transfer_deallocate_entire_list]:
  1185:block_transfer_deallocate_entire_list : Dumped: 0x0002 files.
5:2012 May 11 13:49:38:BMC:BIOSReader:391: BIOSReader.c:555:File Close :
  /var/nuova/BIOS/BiosTech_1.txt
5:2012 May 11 13:49:38:BMC:BIOSReader:391: BIOSReader.c:555:File Close :
  /var/nuova/BIOS/BiosTech_4.txt
5:2012 May 11 13:49:38:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]:
  2125:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
  HostBTDescr = 126 : FName = BiosTech_1.txt
5:2012 May 11 13:49:38:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]:
  2125:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
  HostBTDescr = 125 : FName = BiosTech_4.txt
5:2012 May 11 13:49:38:BMC:kernel:--<5>LPC Reset ISR -> ResetState: 0
7:2012 May 11 13:49:38:BMC:kernel:--<7>[peci_init_hardware]:472:peci:
  registered IRQ: [13]
5:2012 May 11 13:49:38:BMC:kernel:--<5>[lpc_reset_handler_Port80_Capture_setup]:
  630:BIOS_POST_CMPLT De-asserted --> BIOS is running
7:2012 May 11 13:49:38:BMC:kernel:--<7>[block_transfer_deallocate_entire_list]:
  1141:block_transfer_deallocate_entire_list
7:2012 May 11 13:49:38:BMC:kernel:--<7>[block_transfer_deallocate_entire_list]:
  1185:block_transfer_deallocate_entire_list : Dumped: 0x0000 files.
6:2012 May 11 13:49:38:BMC:avct_server:--: rvas_wait_for_changes failed
4:2012 May 11 13:49:38:BMC:avct_server:--: No Video Source Detected!
5:2012 May 11 13:49:39:BMC:bioscom:--: lv_mode_dimm_support.c:126:
  [lpc_reset_seen]LPC Reset Count is Different [0x28:0x29]
  Asserted LPC Reset Seen
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1388:audit from:kcs
  Fn:0x4 Cmd:0x28 Resp:0x0
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1415:audit data&colon; 0x9 0x80
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1388:audit from:kcs
  Fn:0x4 Cmd:0x28 Resp:0x0
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1415:audit data&colon; 0xa 0x80
5:2012 May 11 13:49:39:BMC:bioscom:--: lv_mode_dimm_support.c:197:
  [transition_function]Starting Transition to
  [High Voltage Mode] from [Unknown Mode]
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1388:audit from:kcs
  Fn:0x4 Cmd:0x28 Resp:0x0
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1415:audit data&colon; 0x9 0x80
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1388:audit from:kcs
  Fn:0x4 Cmd:0x28 Resp:0x0
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1415:audit data&colon; 0xa 0x80
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1388:audit from:kcs
  Fn:0x4 Cmd:0x26 Resp:0x0
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1415:audit data&colon;
  0x9 0x36 0x92 0x92 0x89 0x9f 0x9f 0xa8
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1388:audit from:kcs
  Fn:0x4 Cmd:0x26 Resp:0x0
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1415:audit data&colon;
  0xa 0x36 0x92 0x92 0x89 0x9f 0x9f 0xa8
5:2012 May 11 13:49:39:BMC:bioscom:--: lv_mode_dimm_support.c:217:
  [transition_function]Transition to [High Voltage Mode] Success
```

```

5:2012 May 11 13:49:39:BMC:IPMI:591: VirtualSEL.c:224:SEL Evt[04 00]<
    04 00 02 F3 18 AD 4F 20 00 04 25 53 08 00 FF FF >
5:2012 May 11 13:49:39:BMC:BIOSReader:391: BIOSReader.c:227:File Open :
    BiosTech_3.txt
5:2012 May 11 13:49:39:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]:
    2063:block_transfer_fetch_host_request_for_app: BT_OPEN:
    HostDescriptor = 131 : Filename = BiosTech_3.txt
7:2012 May 11 13:49:39:BMC:kernel:--<7>[mailbox_isr]:276:
    Mailbox[0] Bit Change w/NULL Handler (01 - 10)!
7:2012 May 11 13:49:39:BMC:kernel:--<7>[mailbox_isr]:276:
    Mailbox[0] Bit Change w/NULL Handler (01 - 20)!
7:2012 May 11 13:49:39:BMC:kernel:--<7>[mailbox_isr]:276:
    Mailbox[0] Bit Change w/NULL Handler (01 - 40)!
5:2012 May 11 13:49:39:BMC:kernel:--<5>LPC Reset ISR -> ResetState: 1
7:2012 May 11 13:49:39:BMC:kernel:--<7>[peci_init_hardware]:490:peci:
    unregistered IRQ: [13]
7:2012 May 11 13:49:39:BMC:kernel:--<7>[block_transfer_deallocate_entire_list]:
    1141:block_transfer_deallocate_entire_list
7:2012 May 11 13:49:39:BMC:kernel:--<7>[block_transfer_deallocate_entire_list]:
    1185:block_transfer_deallocate_entire_list : Dumped: 0x0001 files.
5:2012 May 11 13:49:39:BMC:kernel:--<5>LPC Reset ISR -> ResetState: 0
7:2012 May 11 13:49:39:BMC:kernel:--<7>[peci_init_hardware]:472:peci:
    registered IRQ: [13]

```

Remarques :

- Seul le démarrage du système d'exploitation n'affiche pas la sortie « do_power ». Vous pouvez utiliser ce fait afin de déterminer rapidement si le serveur a démarré sur le système d'exploitation.
- Seul le démarrage du système d'exploitation imprime les transitions [High Voltage Mode].

Cycle d'alimentation à partir de l'interface utilisateur CIMC

```

5:2012 May 11 13:50:22:BMC:IPMI:585: Bridge.c:1388:audit from:kcs
    Fn:0x0 Cmd:0x2 Resp:0x0
5:2012 May 11 13:50:22:BMC:IPMI:585: Bridge.c:1415:audit data&colon; 0x2
7:2012 May 11 13:50:22:BMC:kernel:--<7>[do_power_off]:188:do_power_off
5:2012 May 11 13:50:22:BMC:kernel:--<5>[do_power_off]:190:Power Driver:
    Power Off Logic @ 181790792
6:2012 May 11 13:50:22:BMC:kernel:--<6>[press_button]:105:Power Driver:
    Press Power Button @ 181790793
5:2012 May 11 13:50:22:BMC:AUDIT:--: Server power state modify (op:power-cycle)
5:2012 May 11 13:50:26:BMC:kernel:--<5>LPC Reset ISR -> ResetState: 1
7:2012 May 11 13:50:26:BMC:kernel:--<7>[peci_init_hardware]:490:peci:
    unregistered IRQ: [13]
7:2012 May 11 13:50:26:BMC:kernel:--<7>[block_transfer_deallocate_entire_list]:
    1141:block_transfer_deallocate_entire_list
7:2012 May 11 13:50:26:BMC:kernel:--<7>[block_transfer_deallocate_entire_list]:
    1185:block_transfer_deallocate_entire_list : Dumped: 0x0001 files.
7:2012 May 11 13:50:26:BMC:kernel:--<7>USB FS: VDD Power WAKEUP- Power Good = OFF
7:2012 May 11 13:50:26:BMC:kernel:--<7>kbd_complete: -108, 0/8
7:2012 May 11 13:50:26:BMC:kernel:--<7>mouse_complete: -108, 0/6
7:2012 May 11 13:50:26:BMC:kernel:--<7>USB HS: VDD Power WAKEUP- Power Good = OFF
7:2012 May 11 13:50:26:BMC:kernel:--<7>bulk_out_complete: -108, 0/31, LUN[0][2]
7:2012 May 11 13:50:26:BMC:kernel:--<7>handle_exception: Handling
    MSD_STATE_DISCONNECT for interface[0]
7:2012 May 11 13:50:26:BMC:kernel:--<7>do_set_interface(): reset_interface
7:2012 May 11 13:50:26:BMC:kernel:--<7>handle_exception:
    Handling MSD_STATE_DISCONNECT for interface[1]
5:2012 May 11 13:50:26:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]:
    2125:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :

```

```
HostBTDescr = 132 : FName = BiosTech_4.txt
6:2012 May 11 13:50:26:BMC:kernel:--:<6>kbdmouse_write:
    kbd write aborted for device reset.
6:2012 May 11 13:50:26:BMC:kernel:--:<6>kbdmouse_write:
    mouse write aborted for device reset.
6:2012 May 11 13:50:26:BMC:avct_server:--: rvas_wait_for_changes failed
5:2012 May 11 13:50:26:BMC:BIOSReader:391:
    BIOSReader.c:555:File Close : /var/nuova/BIOS/BiosTech_4.txt
```

Désactiver l'interface utilisateur CIMC

```
5:2012 May 11 13:58:57:BMC:IPMI:585: Bridge.c:1388:audit from:kcs
    Fn:0x0 Cmd:0x2 Resp:0x0
7:2012 May 11 13:58:57:BMC:kernel:--:<7>[do_power_off]:188:do_power_off
5:2012 May 11 13:58:57:BMC:kernel:--:<5>[do_power_off]:190:Power Driver:
    Power Off Logic @ 182297296
6:2012 May 11 13:58:57:BMC:kernel:--:<6>[press_button]:105:Power Driver:
    Press Power Button @ 182297296
5:2012 May 11 13:58:57:BMC:IPMI:585: Bridge.c:1415:audit data&colon; 0x0
5:2012 May 11 13:58:57:BMC:AUDIT:--: Server power state modify (op:power-off)
5:2012 May 11 13:59:01:BMC:kernel:--:<5>LPC Reset ISR -> ResetState: 1
7:2012 May 11 13:59:01:BMC:kernel:--:<7>[peci_init_hardware]:490:peci:
    unregistered IRQ: [13]
7:2012 May 11 13:59:01:BMC:kernel:--:<7>[block_transfer_deallocate_entire_list]:
    1141:block_transfer_deallocate_entire_list
7:2012 May 11 13:59:01:BMC:kernel:--:<7>[block_transfer_deallocate_entire_list]:
    1185:block_transfer_deallocate_entire_list : Dumped: 0x0002 files.
7:2012 May 11 13:59:01:BMC:kernel:--:<7>USB FS: VDD Power WAKEUP- Power Good = OFF
7:2012 May 11 13:59:01:BMC:kernel:--:<7>USB HS: VDD Power WAKEUP- Power Good = OFF
7:2012 May 11 13:59:01:BMC:kernel:--:<7>bulk_out_complete: -108, 0/31, LUN[0][2]
7:2012 May 11 13:59:01:BMC:kernel:--:<7>handle_exception: Handling
    MSD_STATE_DISCONNECT for interface[0]
7:2012 May 11 13:59:01:BMC:kernel:--:<7>do_set_interface(): reset_interface
7:2012 May 11 13:59:01:BMC:kernel:--:<7>handle_exception: Handling
    MSD_STATE_DISCONNECT for interface[1]
5:2012 May 11 13:59:01:BMC:kernel:--:<5>[block_transfer_fetch_host_request_for_app]:
    2125:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
    HostBTDescr = 143 : FName = BiosTech_3.txt
5:2012 May 11 13:59:01:BMC:kernel:--:<5>[block_transfer_fetch_host_request_for_app]:
    2125:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
    HostBTDescr = 142 : FName = BiosTech_2.txt
6:2012 May 11 13:59:01:BMC:avct_server:--: rvas_wait_for_changes failed
5:2012 May 11 13:59:01:BMC:BIOSReader:391: BIOSReader.c:555:File Close :
    /var/nuova/BIOS/BiosTech_3.txt
5:2012 May 11 13:59:01:BMC:BIOSReader:391: BIOSReader.c:555:File Close :
    /var/nuova/BIOS/BiosTech_2.txt
```

Mise sous tension de l'interface utilisateur CIMC

```
5:2012 May 11 13:59:13:BMC:IPMI:585: Bridge.c:1388:audit from:
    kcs Fn:0x0 Cmd:0x2 Resp:0x0
5:2012 May 11 13:59:13:BMC:IPMI:585: Bridge.c:1415:audit data&colon; 0x1
7:2012 May 11 13:59:13:BMC:kernel:--:<7>[do_power_on]:226:do_power_on
5:2012 May 11 13:59:13:BMC:kernel:--:<5>[do_power_on]:231:Power Driver:
    Power On Logic Pulse for 250ms @ 182313079
6:2012 May 11 13:59:13:BMC:kernel:--:<6>[press_button]:105:Power Driver:
    Press Power Button @ 182313079
5:2012 May 11 13:59:13:BMC:AUDIT:--: Server power state modify (op:power-on)
6:2012 May 11 13:59:13:BMC:kernel:--:<6>[release_button]:115:Power Driver:
    Release Power Button @ 182313330
7:2012 May 11 13:59:13:BMC:kernel:--:<7>USB FS: VDD Power WAKEUP-
```

```

Power Good = ON
6:2012 May 11 13:59:13:BMC:kernel:--:<6>se_pilot2_udc_usb_turnon:
Passed USB1.1 register test (0)
7:2012 May 11 13:59:13:BMC:kernel:--:<7>USB HS: VDD Power WAKEUP-
Power Good = ON
6:2012 May 11 13:59:13:BMC:kernel:--:<6>se_pilot2_udc_usb_turnon:
Passed USB2.0 register test (11)
5:2012 May 11 13:59:13:BMC:kernel:--:<5>LPC Reset ISR -> ResetState: 0
7:2012 May 11 13:59:13:BMC:kernel:--:<7>[peci_init_hardware]:472:peci:
registered IRQ: [13]
5:2012 May 11 13:59:13:BMC:kernel:--:<5>[lpc_reset_handler_Port80_Capture_setup]:
630:BIOS_POST_CMPLT De-asserted --> BIOS is running
7:2012 May 11 13:59:13:BMC:kernel:--:<7>[block_transfer_deallocate_entire_list]:
1141:block_transfer_deallocate_entire_list
7:2012 May 11 13:59:13:BMC:kernel:--:<7>[block_transfer_deallocate_entire_list]:
1185:block_transfer_deallocate_entire_list : Dumped: 0x0000 files.
5:2012 May 11 13:59:13:BMC:IPMI:587: Pilot2SrvPower.c:394:
Blade Power Changed To: [ ON ]
5:2012 May 11 13:59:13:BMC:kernel:--:<5>[do_power_on]:
251:Power Driver: Power On Logic Done @ 182313832
5:2012 May 11 13:59:13:BMC:IPMI:590: Pilot2SrvPower.c:
188:Pilot2SrvPowerOn
5:2012 May 11 13:59:14:BMC:IPMI:591: VirtualSEL.c:224:
SEL Evt[25 00]< 25 00 02 32 1B AD 4F 20 00 04 25 52 08 01 FF FF >
5:2012 May 11 13:59:14:BMC:IPMI:591: VirtualSEL.c:224:
SEL Evt[26 00]< 26 00 02 32 1B AD 4F 20 00 04 25 53 08 00 FF FF >
5:2012 May 11 13:59:14:BMC:IPMI:591: VirtualSEL.c:224:
SEL Evt[27 00]< 27 00 02 32 1B AD 4F 20 00 04 08 62 0B 00 FF FF >
5:2012 May 11 13:59:14:BMC:kernel:--:<5>[block_transfer_fetch_host_request_for_app]:
2063:block_transfer_fetch_host_request_for_app: BT_OPEN:
HostDescriptor = 148 : Filename = BiosTech_1.txt
5:2012 May 11 13:59:14:BMC:BIOSReader:391: BIOSReader.c:227:
File Open : BiosTech_1.txt
7:2012 May 11 13:59:14:BMC:kernel:--:<7>[mailbox_isr]:276:
Mailbox[0] Bit Change w/NULL Handler (01 - 10)!
7:2012 May 11 13:59:14:BMC:kernel:--:<7>[mailbox_isr]:276:
Mailbox[0] Bit Change w/NULL Handler (01 - 20)!
7:2012 May 11 13:59:14:BMC:kernel:--:<7>[mailbox_isr]:276:
Mailbox[0] Bit Change w/NULL Handler (01 - 40)!
5:2012 May 11 13:59:14:BMC:kernel:--:<5>LPC Reset ISR -> ResetState: 1
7:2012 May 11 13:59:14:BMC:kernel:--:<7>[peci_init_hardware]:490:peci:
unregistered IRQ: [13]
7:2012 May 11 13:59:14:BMC:kernel:--:<7>[block_transfer_deallocate_entire_list]:
1141:block_transfer_deallocate_entire_list
7:2012 May 11 13:59:14:BMC:kernel:--:<7>[block_transfer_deallocate_entire_list]:
1185:block_transfer_deallocate_entire_list : Dumped: 0x0001 files.
6:2012 May 11 13:59:14:BMC:avct_server:--: Clear RVAS regs
5:2012 May 11 13:59:14:BMC:kernel:--:<5>LPC Reset ISR -> ResetState: 0

```

Bouton d'alimentation à l'avant du serveur (OFF)

```

6:2012 May 11 14:01:51:BMC:storage:--: SLOT-5:
Time established as 05/11/12 14:01:27; (75 seconds since power on)
6:2012 May 11 14:01:51:BMC:avct_server:--:
rvas_wait_for_changes failed
5:2012 May 11 14:01:51:BMC:kernel:--:<5>LPC Reset ISR -> ResetState: 1
7:2012 May 11 14:01:51:BMC:kernel:--:<7>[peci_init_hardware]:490:peci:
unregistered IRQ: [13]
7:2012 May 11 14:01:51:BMC:kernel:--:<7>[block_transfer_deallocate_entire_list]:
1141:block_transfer_deallocate_entire_list
7:2012 May 11 14:01:51:BMC:kernel:--:<7>[block_transfer_deallocate_entire_list]:
1185:block_transfer_deallocate_entire_list : Dumped: 0x0002 files.

```

```

7:2012 May 11 14:01:51:BMC:kernel:-:<7>USB FS: VDD Power WAKEUP- Power Good = OFF
7:2012 May 11 14:01:51:BMC:kernel:-:<7>USB HS: VDD Power WAKEUP- Power Good = OFF
7:2012 May 11 14:01:51:BMC:kernel:-:<7>bulk_out_complete: -108, 0/31, LUN[0][0]
7:2012 May 11 14:01:51:BMC:kernel:-:<7>handle_exception: Handling
MSD_STATE_DISCONNECT for interface[0]
7:2012 May 11 14:01:51:BMC:kernel:-:<7>do_set_interface(): reset_interface
7:2012 May 11 14:01:51:BMC:kernel:-:<7>handle_exception: Handling
MSD_STATE_DISCONNECT for interface[1]
5:2012 May 11 14:01:51:BMC:BIOSReader:391: BIOSReader.c:555:File Close :
/var/nuova/BIOS/BiosTech_3.txt
5:2012 May 11 14:01:51:BMC:BIOSReader:391: BIOSReader.c:555:File Close :
/var/nuova/BIOS/BiosTech_2.txt
5:2012 May 11 14:01:51:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]:
2125:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 150 : FName = BiosTech_3.txt
5:2012 May 11 14:01:51:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]:
2125:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 149 : FName = BiosTech_2.txt
5:2012 May 11 14:01:51:BMC:IPMI:593: Pilot2SrvPower.c:394:
Blade Power Changed To: [ OFF ]
5:2012 May 11 14:01:51:BMC:IPMI:591: VirtualSEL.c:224:SEL Evt[33 00]<
33 00 02 CF 1B AD 4F 20 00 04 25 52 08 00 FF FF >
6:2012 May 11 14:01:51:BMC:IPMI:583: mcddI2CDrv.c:860:PI2CPerformOP:
ioctl to driver failed to read Bus[f4].Dev[5e]! ErrorStatus[32]
6:2012 May 11 14:01:52:BMC:IPMI:583: mcddI2CDrv.c:860:PI2CPerformOP:
ioctl to driver failed to read Bus[f4].Dev[5e]! ErrorStatus[32]
4:2012 May 11 14:01:52:BMC:avct_server:-: No Video Source Detected!
6:2012 May 11 14:01:52:BMC:avct_server:-: Video Source Detected!
5:2012 May 11 14:01:52:BMC:IPMI:591: VirtualSEL.c:224:
SEL Evt[34 00]< 34 00 02 D0 1B AD 4F 20 00 04 25 53 08 01 FF FF >
5:2012 May 11 14:01:52:BMC:bioscom:-: lv_mode_dimm_support.c:126:
[lpc_reset_seen]LPC Reset Count is Different [0x30:0x31]
Asserted LPC Reset Seen

```

Bouton d'alimentation à l'avant du serveur (ON)

```

5:2012 May 11 14:01:58:BMC:IPMI:591: VirtualSEL.c:224:
SEL Evt[35 00]< 35 00 02 D6 1B AD 4F 20 00 04 08 62 0B 00 FF FF >
7:2012 May 11 14:01:58:BMC:kernel:-:<7>USB FS: VDD Power WAKEUP-
Power Good = ON
6:2012 May 11 14:01:58:BMC:kernel:-:<6>se_pilot2_udc_usb_turnon:
Passed USB1.1 register test (0)
7:2012 May 11 14:01:58:BMC:kernel:-:<7>USB HS: VDD Power WAKEUP-
Power Good = ON
6:2012 May 11 14:01:58:BMC:kernel:-:<6>se_pilot2_udc_usb_turnon:
Passed USB2.0 register test (11)
5:2012 May 11 14:01:58:BMC:kernel:-:<5>LPC Reset ISR -> ResetState: 0
7:2012 May 11 14:01:58:BMC:kernel:-:<7>[peci_init_hardware]:472:peci:
registered IRQ: [13]
5:2012 May 11 14:01:58:BMC:kernel:-:<5>[lpc_reset_handler_Port80_Capture_setup]:
630:BIOS_POST_CMPLT De-asserted --> BIOS is running
7:2012 May 11 14:01:58:BMC:kernel:-:<7>[block_transfer_deallocate_entire_list]:
1141:block_transfer_deallocate_entire_list
7:2012 May 11 14:01:58:BMC:kernel:-:<7>[block_transfer_deallocate_entire_list]:
1185:block_transfer_deallocate_entire_list : Dumped: 0x0000 files.
5:2012 May 11 14:01:59:BMC:IPMI:587: Pilot2SrvPower.c:394:
Blade Power Changed To: [ ON ]
5:2012 May 11 14:01:59:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]:
2063:block_transfer_fetch_host_request_for_app: BT_OPEN:
HostDescriptor = 155 : Filename = BiosTech_1.txt
5:2012 May 11 14:01:59:BMC:BIOSReader:391: BIOSReader.c:227:File Open :
BiosTech_1.txt

```

5:2012 May 11 14:01:59:BMC:kernel:-:<5>LPC Reset ISR -> ResetState: 1
7:2012 May 11 14:01:59:BMC:kernel:-:<7>[peci_init_hardware]:490:peci:
unregistered IRQ: [13]
7:2012 May 11 14:01:59:BMC:kernel:-:<7>[block_transfer_deallocate_entire_list]:
1141:block_transfer_deallocate_entire_list
7:2012 May 11 14:01:59:BMC:kernel:-:<7>[block_transfer_deallocate_entire_list]:
1185:block_transfer_deallocate_entire_list : Dumped: 0x0001 files.
5:2012 May 11 14:01:59:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]:
2125:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 155 : FName = BiosTech_1.txt
5:2012 May 11 14:01:59:BMC:BIOSReader:391: BIOSReader.c:555:File Close :
/var/nuova/BIOS/BiosTech_1.txt
5:2012 May 11 14:01:59:BMC:kernel:-:<5>LPC Reset ISR -> ResetState: 0
7:2012 May 11 14:01:59:BMC:kernel:-:<7>[peci_init_hardware]:472:peci:
registered IRQ: [13]
5:2012 May 11 14:01:59:BMC:kernel:-:<5>[lpc_reset_handler_Port80_Capture_setup]:
630:BIOS_POST_CMPLT De-asserted --> BIOS is running
7:2012 May 11 14:01:59:BMC:kernel:-:<7>[block_transfer_deallocate_entire_list]:
1141:block_transfer_deallocate_entire_list
7:2012 May 11 14:01:59:BMC:kernel:-:<7>[block_transfer_deallocate_entire_list]:
1185:block_transfer_deallocate_entire_list : Dumped: 0x0000 files.
6:2012 May 11 14:01:59:BMC:avct_server:-: Clear RVAS regs
5:2012 May 11 14:01:59:BMC:IPMI:591: VirtualSEL.c:224:SEL Evt[36 00]<
36 00 02 D7 1B AD 4F 20 00 04 25 52 08 01 FF FF >
6:2012 May 11 14:02:00:BMC:avct_server:-: Set TSTMUL reg to 0x00100000
5:2012 May 11 14:02:00:BMC:IPMI:591: VirtualSEL.c:224:SEL Evt[37 00]<
37 00 02 D8 1B AD 4F 20 00 04 25 53 08 00 FF FF >
6:2012 May 11 14:02:00:BMC:avct_server:-: Detected VGA Text Mode: 80 x 25 chars
6:2012 May 11 14:02:00:BMC:avct_server:-: Current Graphics Core Settings are:
6:2012 May 11 14:02:00:BMC:avct_server:-: 720 x 400, 4 bits per pixel, 640 pitch,
in VGA mode
6:2012 May 11 14:02:00:BMC:avct_server:-: Video Signal detected: 720 x 400,
color depth is: 4 bits
6:2012 May 11 14:02:00:BMC:avct_server:-: VGA Text mode
6:2012 May 11 14:02:00:BMC:avct_server:-: Change Detected before TFE start
5:2012 May 11 14:02:00:BMC:bioscom:-: lv_mode_dimm_support.c:126:
[lpc_reset_seen]LPC Reset Count is Different [0x31:0x32]
Asserted LPC Reset Seen