

EzVPN 機能を備えた Cisco IOS ルータに接続する Cisco VPN 3002 ハードウェア クライアント の Network Extension モードでの設定

内容

[概要](#)

[前提条件](#)

[要件](#)

[使用するコンポーネント](#)

[表記法](#)

[設定](#)

[ネットワーク図](#)

[Cisco VPN 3002 Hardware Client の設定](#)

[確認](#)

[トラブルシュート](#)

[トラブルシューティングの手順](#)

[トラブルシューティングのためのコマンド](#)

[Cisco VPN 3002 Hardware Client のデバッグ](#)

[関連情報](#)

概要

このドキュメントでは、Cisco IOS ソフトウェア リリース 12.2(8)T と Easy VPN (EzVPN) サーバ機能を使用して、Network Extension Mode で Cisco IOS® ルータへ接続する Cisco VPN 3002 Hardware Client の設定を説明します。これにより、Cisco IOS では VPN クライアント、PIX、および Cisco IOS EzVPN クライアントなどの EzVPN クライアントからの VPN トンネルを終端できるようになります。VPN クライアントがヘッドエンド デバイスに接続する場合は、少なくとも 5 つの security association (SA; セキュリティ アソシエーション) (1 つの Internet Key Exchange (IKE; インターネット キー エクスチェンジ) と 4 つの IPSec) が存在します。これは、VPN クライアントがヘッドエンドへ接続する際に、コンセントレータのパブリック インターフェイスの IP アドレスが含まれた 2 つの IPSec SA がヘッドエンドの IP アドレスへ常にネゴシエーションされるためです。このトンネルは、GUI または Command Line Interface (CLI; コマンドライン インターフェイス) のどちらかを介してヘッドエンドから VPN クライアントへ接続するために、管理目的で使用されます。これは自動的に実行されます。他の 2 つは、VPN クライアントと Cisco IOS ルータの背後のネットワーク間のデータ トランザクション用です。

VPN サーバが PIX 6.x の場合の同様のシナリオについては、『[PIX 6.x への VPN 3002 Hardware Client の設定](#)』を参照してください。

VPN サーバが Cisco VPN 3000 シリーズ コンセントレータの場合の同様のシナリオについては、『[Network Extension Mode での VPN 3002 Hardware Client と VPN 3000 コンセントレータとの接続の設定](#)』を参照してください。

前提条件

要件

このドキュメントに特有の要件はありません。

使用するコンポーネント

このドキュメントの情報は、次のソフトウェアとハードウェアのバージョンに基づいています。

- Cisco VPN 3002 ハードウェア クライアント
- Cisco IOS ソフトウェア リリース 12.2(8)T 以降

このドキュメントの情報は、特定のラボ環境にあるデバイスに基づいて作成されました。このドキュメントで使用するすべてのデバイスは、初期（デフォルト）設定の状態から起動しています。対象のネットワークが実稼働中である場合には、どのようなコマンドについても、その潜在的な影響について確実に理解しておく必要があります。

表記法

ドキュメント表記の詳細は、『[シスコ テクニカル ティップスの表記法](#)』を参照してください。


設定

このセクションでは、このドキュメントで説明する機能を設定するために必要な情報を提供しています。

注：このドキュメントで使用されているコマンドの詳細を調べるには、[Command Lookup Tool](#)（[登録ユーザ専用](#)）を使用してください。

ネットワーク図

このドキュメントでは、次のネットワーク セットアップを使用します。



このドキュメントでは次の設定を使用します。

- [Cisco IOS ルータ](#)
- [Cisco VPN 3002 ハードウェア クライアント](#)

Cisco IOS ルータ

```
akim#show running
Current configuration : 1449 bytes
!
version 12.2
service config
service timestamps debug uptime
service timestamps log uptime
no service password-encryption
!
hostname akim
!
!--- Enable Authentication, Authorizing and Accounting
(AAA) !--- for user authentication and group
authorization. aaa new-model
!--- To enable X-Auth for user authentication, !---
enable the AAA commands. aaa authentication login
userauthen local
!--- To enable group authorization, !--- enable the AAA
commands. aaa authorization network groupauthor local
aaa session-id common
!
!--- Define the username and password to be used for X-
Auth. username fadi password 0 cisco memory-size iomem
10 ip subnet-zero ! ! ! !--- Create an Internet Security
Association and !--- Key Management Protocol (ISAKMP)
policy for Phase 1 negotiations. crypto isakmp policy 3
    encr 3des
    authentication pre-share
    group 2
!
!--- Create a group with the pre-shared key for IKE
authentication. crypto isakmp client configuration group
fadigroup
    key cisco123
!
!
!--- Create the Phase 2 policy for actual data
encryption. crypto ipsec transform-set myset esp-3des
esp-sha-hmac
!
!--- Create a dynamic map and !--- apply the transform
set that was created earlier. crypto dynamic-map dynmap
10
    set transform-set myset
!
!--- Create the actual crypto map, !--- and apply the
AAA lists that were created earlier. !--- These commands
associate the AAA commands to the crypto map. crypto map
clientmap client authentication list userauthen
crypto map clientmap isakmp authorization list
groupauthor
crypto map clientmap 10 ipsec-isakmp dynamic dynmap
!
!
!
!
!
!
fax interface-type fax-mail
mta receive maximum-recipients 0
```

```
!
!
!
!--- Apply the crypto map on the interface where !---
traffic leaves the router. interface FastEthernet0/0
 ip address 209.165.202.129 255.255.255.224
duplex auto
speed auto
crypto map clientmap
!
interface Serial0/0
 no ip address
 shutdown
 no fair-queue
 clockrate 2000000
!
interface FastEthernet0/1
 ip address 10.48.220.1 255.255.254.0
duplex auto
speed auto
!
interface Serial0/1
 no ip address
 shutdown
 clockrate 2000000
!
ip classless
ip route 0.0.0.0 0.0.0.0 209.165.202.130
ip http server
ip pim bidir-enable
!
!
!
!
call rsvp-sync
!
!
mgcp profile default
!
dial-peer cor custom
!
!
!
!
line con 0
 exec-timeout 0 0
line aux 0
line vty 0 4
!
!
end
```

Cisco VPN 3002 Hardware Client の設定

VPN クライアントを設定するには、次の手順を実行します。

1. Configuration > Interfaces の順に選択して、IP アドレスを確認します。

This section lets you configure the VPN 3002 Hardware Client's network interfaces.

In the table below, or in the picture, select and click the interface you want to configure:

Interface	Status	IP Address	Subnet Mask	MAC Address	Default Gateway
Ethernet 1 (Private)	UP	10.48.66.185	255.255.254.0	00.05.31.98.00.0A	
Ethernet 2 (Public)	UP	209.165.200.225	255.255.255.224	00.05.31.98.00.0B	209.165.200.226
DNS Server(s)	DNS Server Not Configured				
DNS Domain Name					



2. Configuration > Quick > Time and Date > Time の順に選択し、時刻の設定と確認を行います

Configuration | Quick | Time and Date

- [Time](#)
- [Upload Config](#)
- [Private Intf](#)
- [Public Intf](#)
- [IPSec](#)
- [PAT](#)

Set the time on your device. The correct time is very important, so that logging entries are accurate.

The current time on this device is Thursday, 30 May 2002 16:17:11.

New Time : : May / / (GMT+01:00) Paris

Enable DST Support

Click to go back without saving changes
 Click to save changes and continue

[Back](#) [Continue](#)

3. Configuration > Quick > Private Interface > Private Intf の順に選択し、内部ホスト上で固定 IP アドレスを設定します (DHCP 不可)。
4. 「Do you want to configure the IP address of the Private Interface?」には No を選択します。
5. 「Do you want to use the DHCP server on Interface 1 to provide addresses for the local LAN?」には No, do not use the DHCP server to provide addresses を選択します。



You are modifying the interface you are using to connect to this device. If you make any changes, you will be logged out of the device and must log back in.

IP Address 10.48.66.185 / 255.255.254.0

DHCP Server Enabled (10.48.66.58 - 10.48.66.184)

Do you want to configure the IP address of the Private Interface?

Yes

No

Do you want to use the DHCP server on Interface 1 to provide addresses for the local LAN?

Yes, and configure the DHCP server parameters.

Yes, but leave the DHCP server parameters as is.

No, do not use the DHCP server to provide addresses.

Click to go back without making any changes

Click to make changes and continue

Back

Continue

6. Configuration > Quick > Public Interface > Public Intf の順に選択して、固定 IP アドレスを用意してある場合は IP アドレスを指定します。
7. Public Interface ウィンドウで **Specify an IP address** を選択し、適切な IP アドレス、サブネットマスク、およびデフォルトゲートウェイを入力します。

Configuration | Quick | Public Interface**Time****Upload Config****Private Intf ✓****Public Intf****IPSec****System Name (a.k.a. hostname) may be required to be set if you use DHCP to obtain an address.****System Name** **How do you want to configure the IP address of the Public Interface?**

- Obtain an IP address from a DHCP server
- Use PPPoE to connect to a public network

PPPoE User Name **PPPoE Password** **Verify PPPoE Password**

- Specify an IP address

IP Address **Subnet Mask** **Default Gateway**

↙ Click to go back without saving any changes

↙ Click to save changes and continue

Back**Continue**

8. リモート VPN ピア（ルータのパブリック IP アドレス）を設定します。これを実行するには、Configuration > Quick > IPSec の順に選択し、Group Name に fadigroup、Group Password に cisco123、User Name に fadi、User Password に cisco を入力します。

Remote Server Enter remote server address/host name.**IPSec over TCP** Check to enable IPSec over TCP.**IPSec over TCP Port** Enter IPSec over TCP port (1 - 65535).**Use Certificate** Click to use the installed certificate.

Certificate Transmission	<input type="radio"/> Entire certificate chain	Choose how to send the digital certificate to the server.
	<input checked="" type="radio"/> Identity certificate only	

	Name	Password	Verify
Group	<input type="text" value="fadigroup"/>	<input type="password"/>	<input type="password"/>
User	<input type="text" value="fadi"/>	<input type="password"/>	<input type="password"/>

9. Configuration > Quick > PAT の順に選択し、PAT ウィンドウで No, use Network Extension mode を選択して Network Extension Mode を設定します。

Configuration | Quick | PAT

[Time](#) [Upload Config](#) [Private Intf ✓](#) [Public Intf ✓](#)

Do you want to use PAT on the IP Sec tunnel to the VPN Concentrator?

Yes

No, use Network Extension mode

 Click to go back without making any changes

 Click to make changes and continue

[Back](#) [Continue](#)

10. Configuration > Quick > DNS の順に選択し、ISP の DNS サーバとドメイン名を入力して DNS を設定します。

Configuration | Quick | DNS

[Time](#) [Upload Config](#) [Private Intf ✓](#) [Public Intf ✓](#)

Configure the ISP's DNS server IP address. Enter 0.0.0.0 to not use DNS.

DNS Server

Domain

 Click to go back without making any changes

 Click to make changes and continue

[Back](#) [Continue](#)

11. Configuration > Quick > Static Routes の順に選択し、Add をクリックして静态ルートをルーティング テーブルに追加し、VPN クライアントのデフォルト ゲートウェイを設定します。

This section lets you configure static routes for IP routing.

Static Routes	Actions
Default-> 209.165.200.226	<input type="button" value="Add"/> a route to the routing table. <input type="button" value="Delete"/> a route from the routing table. <input type="button" value="Back"/> to the previous section. <input type="button" value="Continue"/> to the next section

確認

ここでは、設定が正しく機能していることを確認するために使用する情報を示します。

[アウトプット インタープリタツール（登録ユーザ専用）（OIT）は、特定の show コマンドをサポートします。](#) OIT を使用して、show コマンドの出力の分析を表示します。

関連する [show コマンドについて](#)は、『IP Security のトラブルシューティング - debug コマンドの理解と使用』を参照してください。

トラブルシュート

ここでは、設定のトラブルシューティングに使用できる情報を示します。

注：Cisco VPN 3002クライアントでPAT Enabledが使用されている場合、リロードによって既存のユーザ名とパスワードが削除されます。クライアントには新しいユーザ名とパスワードを設定する必要があります。

注：PAT Disabled (NEM)が使用されている場合、ヘッドエンドがユーザ名とパスワードを保存するように設定されていれば、リロードでユーザ名とパスワードが保持されます。

トラブルシューティングの手順

この設定に関するトラブルシューティング情報を次に示します。このほかのトラブルシューティングについては、『[IP Security のトラブルシューティング - debug コマンドの理解と使用](#)』を参照してください。設定をトラブルシューティングするには、次の手順を実行します。

1. Phase 1 と Phase 2 の SA の確立を確認します。「[トラブルシューティングのためのコマンド](#)」セクションの debug ベースラインを使用します。
2. SA が表示されたら、保護されたネットワーク間にトラフィックを送信して、接続をテストします。

トラブルシューティングのためのコマンド

[アウトプット インタープリタツール（登録ユーザ専用）（OIT）は、特定の show コマンドをサポートします。](#) OIT を使用して、show コマンドの出力の分析を表示します。

注 : [debug](#) コマンドを使用する前に、『[debug コマンドの重要な情報](#)』を参照してください。

- **debug crypto ipsec** : IPsec イベントを表示します。
- **debug crypto isakmp** : IKE イベントに関するメッセージを表示します。
- **debug crypto engine** : 暗号化と復号化を行う暗号化エンジンに関するデバッグ メッセージを表示します。

```
!--- Cisco IOS has received a request for new SA from the VPN Client. 03:36:19: ISAKMP (0:0): received packet from 209.165.200.225 (N) NEW SA 03:36:19: ISAKMP: local port 500, remote port 500 03:36:19: ISAKMP (0:1): (Re)Setting client xauth list userauthen and state 03:36:19: ISAKMP: Locking CONFIG struct 0x631B752C from crypto_ikmp_config_initialize_sa, count 1 03:36:19: ISAKMP (0:1): processing SA payload. message ID = 0 03:36:19: ISAKMP (0:1): processing ID payload. message ID = 0 03:36:19: ISAKMP (0:1): processing vendor id payload 03:36:19: ISAKMP (0:1): vendor ID seems Unity/DPD but bad major 03:36:19: ISAKMP (0:1): vendor ID is XAUTH 03:36:19: ISAKMP (0:1): processing vendor id payload 03:36:19: ISAKMP (0:1): vendor ID is Unity !--- Cisco IOS checks the incoming ISAKMP proposal with the policy !--- defined in Cisco IOS. 03:36:19: ISAKMP (0:1): Checking ISAKMP transform 1 against priority 3 policy 03:36:19: ISAKMP: default group 2 03:36:19: ISAKMP: encryption 3DES-CBC 03:36:19: ISAKMP: hash SHA 03:36:19: ISAKMP: auth XAUTHInitPreShared 03:36:19: ISAKMP: life type in seconds 03:36:19: ISAKMP: life duration (VPI) of 0x7F 0xFF 0xFF 0x00 03:36:19: ISAKMP (0:1): atts are acceptable. Next payload is 3 03:36:19: CryptoEngine0: generate alg parameter 03:36:19: CRYPTO_ENGINE: Dh phase 1 status: 0 03:36:19: CRYPTO_ENGINE: Dh phase 1 status: 0 03:36:19: ISAKMP (0:1): processing KE payload. message ID = 0 03:36:19: CryptoEngine0: generate alg parameter 03:36:19: ISAKMP (0:1): processing NONCE payload. message ID = 0 03:36:19: ISAKMP (0:1): processing vendor id payload 03:36:19: ISAKMP (0:1): vendor ID seems Unity/DPD but bad major 03:36:19: ISAKMP (0:1): vendor ID is XAUTH 03:36:19: ISAKMP (0:1): processing vendor id payload 03:36:19: ISAKMP (0:1): vendor ID is Unity 03:36:19: ISAKMP (0:1): Input = IKE_MESG_FROM_PEER, IKE_AM_EXCH Old State = IKE_READY New State = IKE_R_AM_AAA_AWAIT 03:36:19: ISAKMP: got callback 1 03:36:19: CryptoEngine0: create ISAKMP SKEYID for conn id 1 03:36:19: ISAKMP (0:1): SKEYID state generated 03:36:19: ISAKMP (0:1): SA is doing pre-shared key authentication plus XAUTH using id type ID_IPV4_ADDR 03:36:19: ISAKMP (1): ID payload next-payload : 10 type : 1 protocol : 17 port : 500 length : 8 03:36:19: ISAKMP (1): Total payload length: 12 03:36:19: CryptoEngine0: generate hmac context for conn id 1 03:36:19: ISAKMP (0:1): sending packet to 209.165.200.225 (R) AG_INIT_EXCH 03:36:19: ISAKMP (0:1): Input = IKE_MESG_FROM_AAA, PRESHARED_KEY_REPLY Old State = IKE_R_AM_AAA_AWAIT New State = IKE_R_AM2 03:36:27: ISAKMP (0:1): received packet from 209.165.200.225 (R) AG_INIT_EXCH 03:36:28: ISAKMP (0:1): sending packet to 209.165.200.225 (R) AG_INIT_EXCH 03:36:28: ISAKMP (0:1): received packet from 209.165.200.225 (R) AG_INIT_EXCH 03:36:28: ISAKMP (0:1): processing HASH payload. message ID = 0 03:36:28: CryptoEngine0: generate hmac context for conn id 1 03:36:28: ISAKMP (0:1): processing NOTIFY INITIAL_CONTACT protocol 1 spi 0, message ID = 0, sa = 63393F7C 03:36:28: ISAKMP (0:1): Process initial contact, bring down existing phase 1 and 2 SA's 03:36:28: ISAKMP (0:1): returning IP addr to the address pool 03:36:28: ISAKMP (0:1): peer does not do paranoid keepalives. 03:36:28: ISAKMP (0:1): processing vendor id payload 03:36:28: ISAKMP (0:1): vendor ID is DPD !--- Phase 1 is now complete and ISAKMP SA is negotiated. 03:36:28: ISAKMP (0:1): SA has been authenticated with 209.165.200.225 03:36:28: CryptoEngine0: clear dh number for conn id 1 03:36:28: CryptoEngine0: generate hmac context for conn id 1 03:36:28: ISAKMP (0:1): sending packet to 209.165.200.225 (R) QM_IDLE 03:36:28: ISAKMP (0:1): purging node -2033367886 03:36:28: ISAKMP: Sending phase 1 responder lifetime 86400 03:36:28: ISAKMP (0:1): Input = IKE_MESG_FROM_PEER, IKE_AM_EXCH Old State = IKE_R_AM2 New State = IKE_P1_COMPLETE 03:36:28: IPSEC(key_engine): got a queue event... 03:36:28: IPSEC(key_engine_delete_sas): rec'd delete notify from ISAKMP 03:36:28: IPSEC(key_engine_delete_sas): delete all SAs shared with 209.165.200.225 !--- Proceed to the Extended Authentication. !--- Remember that XAUTH is done before Phase 2 and after Phase 1. 03:36:28: ISAKMP (0:1): Need XAUTH 03:36:28: ISAKMP (0:1): Input = IKE_MESG_INTERNAL, IKE_PHASE1_COMPLETE Old State = IKE_P1_COMPLETE New State = IKE_XAUTH_AAA_START_LOGIN_AWAIT 03:36:28: ISAKMP: got callback 1 03:36:28: ISAKMP/xauth: request attribute XAUTH_TYPE_V2 03:36:28: ISAKMP/xauth: request attribute XAUTH_MESSAGE_V2 03:36:28: ISAKMP/xauth: request
```

attribute XAUTH_USER_NAME_V2 03:36:28: ISAKMP/xauth: request attribute XAUTH_USER_PASSWORD_V2
03:36:28: CryptoEngine0: generate hmac context for conn id 1 03:36:28: ISAKMP (0:1): initiating peer config to 209.165.200.225. ID = 1189186805 03:36:28: ISAKMP (0:1): sending packet to 209.165.200.225 (R) CONF_XAUTH 03:36:28: ISAKMP (0:1): Input = IKE_MESG_FROM_AAA, IKE_AAA_START_LOGIN Old State = IKE_XAUTH_AAA_START_LOGIN_AWAIT New State = IKE_XAUTH_REQ_SENT 03:36:28: ISAKMP (0:1): received packet from 209.165.200.225 (R) CONF_XAUTH 03:36:28: ISAKMP (0:1): processing transaction payload from 209.165.200.225. message ID = 1189186805 03:36:28: CryptoEngine0: generate hmac context for conn id 1 03:36:28: ISAKMP: Config payload REPLY 03:36:28: ISAKMP/xauth: reply attribute XAUTH_USER_NAME_V2 03:36:28: ISAKMP/xauth: reply attribute XAUTH_USER_PASSWORD_V2 03:36:28: ISAKMP (0:1): deleting node 1189186805 error FALSE reason "done with xauth request/reply exchange" 03:36:28: ISAKMP (0:1): Input = IKE_MESG_FROM_PEER, IKE_CFG_REPLY Old State = IKE_XAUTH_REQ_SENT New State = IKE_XAUTH_AAA_CONT_LOGIN_AWAIT 03:36:28: ISAKMP: got callback 1 03:36:28: CryptoEngine0: generate hmac context for conn id 1 03:36:28: ISAKMP (0:1): initiating peer config to 209.165.200.225. ID = 1490194005 03:36:28: ISAKMP (0:1): sending packet to 209.165.200.225 (R) CONF_XAUTH 03:36:28: ISAKMP (0:1): Input = IKE_MESG_FROM_AAA, IKE_AAA_CONT_LOGIN Old State = IKE_XAUTH_AAA_CONT_LOGIN_AWAIT New State = IKE_XAUTH_SET_SENT 03:36:28: ISAKMP (0:1): received packet from 209.165.200.225 (R) CONF_XAUTH 03:36:28: ISAKMP (0:1): processing transaction payload from 209.165.200.225. message ID = 1490194005 03:36:28: CryptoEngine0: generate hmac context for conn id 1 03:36:28: ISAKMP: Config payload ACK 03:36:28: ISAKMP (0:1): XAUTH ACK Processed 03:36:28: ISAKMP (0:1): deleting node 1490194005 error FALSE reason "done with transaction" 03:36:28: ISAKMP (0:1): Input = IKE_MESG_FROM_PEER, IKE_CFG_ACK Old State = IKE_XAUTH_SET_SENT New State = IKE_P1_COMPLETE 03:36:28: ISAKMP (0:1): received packet from 209.165.200.225 (R) QM_IDLE 03:36:28: ISAKMP (0:1): processing transaction payload from 209.165.200.225. message ID = 113305927 03:36:28: CryptoEngine0: generate hmac context for conn id 1 03:36:28: ISAKMP: Config payload REQUEST 03:36:28: ISAKMP (0:1): checking request: 03:36:28: ISAKMP: IP4_DNS 03:36:28: ISAKMP: IP4_DNS 03:36:28: ISAKMP: IP4_NBNS 03:36:28: ISAKMP: IP4_NBNS 03:36:28: ISAKMP: SPLIT_INCLUDE 03:36:28: ISAKMP: DEFAULT_DOMAIN 03:36:28: ISAKMP: UNKNOWN Unknown Attr: 0x7005 03:36:28: ISAKMP: UNKNOWN Unknown Attr: 0x7007 03:36:28: ISAKMP: UNKNOWN Unknown Attr: 0x7800 03:36:28: ISAKMP: UNKNOWN Unknown Attr: 0x7801 03:36:28: ISAKMP: UNKNOWN Unknown Attr: 0x7802 03:36:28: ISAKMP: UNKNOWN Unknown Attr: 0x7803 03:36:28: ISAKMP: UNKNOWN Unknown Attr: 0x7804 03:36:28: ISAKMP: UNKNOWN Unknown Attr: 0x7805 03:36:28: ISAKMP: UNKNOWN Unknown Attr: 0x7806 03:36:28: ISAKMP: UNKNOWN Unknown Attr: 0x7009 03:36:28: ISAKMP: APPLICATION_VERSION 03:36:28: ISAKMP (0:1): Input = IKE_MESG_FROM_PEER, IKE_CFG_REQUEST Old State = IKE_P1_COMPLETE New State = IKE_CONFIG_AUTHOR_AAA_AWAIT 03:36:28: ISAKMP (0:1): Unknown Input: state = IKE_CONFIG_AUTHOR_AAA_AWAIT, major, minor = IKE_MESG_INTERNAL, IKE_PHASE1_COMPLETE 03:36:28: ISAKMP: got callback 1 03:36:28: ISAKMP (0:1): Config attributes requested but config attributes not in crypto map. Sending empty reply. 03:36:28: ISAKMP (0:1): attributes sent in message: 03:36:28: ISAKMP: Unknown Attr: UNKNOWN (0x7005) 03:36:28: ISAKMP: Unknown Attr: UNKNOWN (0x7007) 03:36:28: ISAKMP: Unknown Attr: UNKNOWN (0x7800) 03:36:28: ISAKMP: Unknown Attr: UNKNOWN (0x7801) 03:36:28: ISAKMP: Unknown Attr: UNKNOWN (0x7802) 03:36:28: ISAKMP: Unknown Attr: UNKNOWN (0x7803) 03:36:28: ISAKMP: Unknown Attr: UNKNOWN (0x7804) 03:36:28: ISAKMP: Unknown Attr: UNKNOWN (0x7805) 03:36:28: ISAKMP: Unknown Attr: UNKNOWN (0x7806) 03:36:28: ISAKMP: Unknown Attr: UNKNOWN (0x7009) 03:36:28: ISAKMP: Sending APPLICATION_VERSION string: Cisco Internetwork Operating System Software IOS (tm) 3600 Software (C3640-JK9S-M), Version 12.2(8)T1, RELEASE SOFTWARE (fc2) TAC Support: http://www.cisco.com/tac Copyright (c) 1986-2002 by cisco Systems, Inc. Compiled Sun 31-Mar-02 03:30 by ccai 03:36:28: CryptoEngine0: generate hmac context for conn id 1 03:36:28: ISAKMP (0:1): responding to peer config from 209.165.200.225. ID = 113305927 03:36:28: ISAKMP (0:1): sending packet to 209.165.200.225 (R) CONF_ADDR 03:36:28: ISAKMP (0:1): deleting node 113305927 error FALSE reason "" 03:36:28: ISAKMP (0:1): Input = IKE_MESG_FROM_AAA, IKE_AAA_GROUP_ATTR Old State = IKE_CONFIG_AUTHOR_AAA_AWAIT New State = IKE_P1_COMPLETE 03:36:28: ISAKMP (0:1): received packet from 209.165.200.225 (R) QM_IDLE 03:36:28: CryptoEngine0: generate hmac context for conn id 1 03:36:28: ISAKMP (0:1): processing HASH payload. message ID = 1022849755 03:36:28: ISAKMP (0:1): processing SA payload. message ID = 1022849755 !--- ISAKMP now verifies the IPSec proposal !--- to see if it is acceptable. 03:36:28: ISAKMP (0:1): Checking IPSec proposal 1 03:36:28: ISAKMP: transform 1, ESP_3DES 03:36:28: ISAKMP: attributes in transform: 03:36:28: ISAKMP: SA life type in seconds 03:36:28: ISAKMP: SA life duration (VPI) of 0x7F 0xFF 0xFF 0xFF 03:36:28: ISAKMP: encaps is 1 03:36:28: ISAKMP: authenticator is HMAC-SHA 03:36:28: validate proposal 0 03:36:28: ISAKMP (0:1): atts are acceptable. !--- As the attributes are acceptable, ISAKMP asks !--- IPSec to validate the proposal. 03:36:28: IPSEC(validate_proposal_request): proposal part #1, (key eng. msg.) INBOUND local= 209.165.202.129, remote= 209.165.200.225, local_proxy= 209.165.202.129/255.255.255/0/0 (type=1), remote_proxy= 209.165.200.225/255.255.255/0/0 (type=1), protocol= ESP, transform= esp-3des esp-sha-hmac , lifedur= 0s and 0kb, spi= 0x0(0),

```

conn_id= 0, keysize= 0, flags= 0x4 03:36:28: validate proposal request 0 03:36:28: ISAKMP (0:1):
processing NONCE payload. message ID = 1022849755 03:36:28: ISAKMP (0:1): processing ID payload.
message ID = 1022849755 03:36:28: ISAKMP (0:1): processing ID payload. message ID = 1022849755
03:36:28: ISAKMP (0:1): asking for 1 spis from ipsec 03:36:28: ISAKMP (0:1): Node 1022849755,
Input = IKE_MESG_FROM_PEER, IKE_QM_EXCH Old State = IKE_QM_READY New State = IKE_QM_SPI_STARVE
03:36:28: IPSEC(key_engine): got a queue event... 03:36:28: IPSEC(spi_response): getting spi
1910172102 for SA from 209.165.202.129 to 209.165.200.225 for prot 3 03:36:28: ISAKMP: received
ke message (2/1) 03:36:28: CryptoEngine0: generate hmac context for conn id 1 03:36:28: ISAKMP
(0:1): sending packet to 209.165.200.225 (R) QM_IDLE 03:36:28: ISAKMP (0:1): Node 1022849755,
Input = IKE_MESG_FROM_IPSEC, IKE_SPI_REPLY Old State = IKE_QM_SPI_STARVE New State =
IKE_QM_R_QM2 03:36:28: ISAKMP (0:1): received packet from 209.165.200.225 (R) QM_IDLE 03:36:28:
CryptoEngine0: generate hmac context for conn id 1 03:36:28: ipsec allocate flow 0 03:36:28:
ipsec allocate flow 0 !--- After IPsec validates the proposal, !--- IPsec proceeds to create the
IPsec SAs. 03:36:28: ISAKMP (0:1): Creating IPsec SAs 03:36:28: inbound SA from 209.165.200.225
to 209.165.202.129 (proxy 209.165.200.225 to 209.165.202.129) 03:36:28: has spi 0x71DAE9C6 and
conn_id 2000 and flags 4 03:36:28: lifetime of 2147483647 seconds 03:36:28: outbound SA from
209.165.202.129 to 209.165.200.225 (proxy 209.165.202.129 to 209.165.200.225) 03:36:28: has spi
101033821 and conn_id 2001 and flags C 03:36:28: lifetime of 2147483647 seconds 03:36:28: ISAKMP
(0:1): deleting node 1022849755 error FALSE reason "quick mode done (await())" 03:36:28: ISAKMP
(0:1): Node 1022849755, Input = IKE_MESG_FROM_PEER, IKE_QM_EXCH Old State = IKE_QM_R_QM2 New
State = IKE_QM_PHASE2_COMPLETE 03:36:28: IPSEC(key_engine): got a queue event... 03:36:28:
IPSEC(initialize_sas): , (key eng. msg.) INBOUND local= 209.165.202.129, remote=
209.165.200.225, !--- This is the management tunnel. local_proxy= 209.165.202.129/0.0.0.0/0/0
(type=1),
remote_proxy= 209.165.200.225/0.0.0.0/0/0 (type=1),
protocol= ESP, transform= esp-3des esp-sha-hmac ,
lifedur= 2147483647s and 0kb,
spi= 0x71DAE9C6(1910172102), conn_id= 2000, keysize= 0, flags= 0x4
03:36:28: IPSEC(initialize_sas): ,
(key eng. msg.) OUTBOUND local= 209.165.202.129, remote= 209.165.200.225,
local_proxy= 209.165.202.129/0.0.0.0/0/0 (type=1),
remote_proxy= 209.165.200.225/0.0.0.0/0/0 (type=1),
protocol= ESP, transform= esp-3des esp-sha-hmac,
lifedur= 2147483647s and 0kb,
spi= 0x605A75D(101033821), conn_id= 2001, keysize= 0, flags= 0xC
03:36:28: IPSEC(create_sa): sa created,
(sa) sa_dest= 209.165.202.129, sa_prot= 50,
sa_spi= 0x71DAE9C6(1910172102),
sa_trans= esp-3des esp-sha-hmac , sa_conn_id= 2000
03:36:28: IPSEC(create_sa): sa created,
(sa) sa_dest= 209.165.200.225, sa_prot= 50,
sa_spi= 0x605A75D(101033821),
sa_trans= esp-3des esp-sha-hmac , sa_conn_id= 2001
03:36:28: ISAKMP: received ke message (4/1)
03:36:28: ISAKMP: Locking CONFIG struct 0x631B752C for
crypto_ikmp_config_handle_kei_mess, count 2
03:36:32: ISAKMP (0:1): received packet from 209.165.200.225 (R) QM_IDLE
03:36:32: CryptoEngine0: generate hmac context for conn id 1
03:36:32: ISAKMP (0:1): processing HASH payload. message ID = 852253052
03:36:32: ISAKMP (0:1): processing SA payload. message ID = 852253052
03:36:32: ISAKMP (0:1): Checking IPsec proposal 1
03:36:32: ISAKMP: transform 1, ESP_3DES
03:36:32: ISAKMP: attributes in transform:
03:36:32: ISAKMP:     SA life type in seconds
03:36:32: ISAKMP:     SA life duration (VPI) of 0x7F 0xFF 0xFF 0xFF
03:36:32: ISAKMP:     encaps is 1
03:36:32: ISAKMP:     authenticator is HMAC-SHA
03:36:32: validate proposal 0
03:36:32: ISAKMP (0:1): atts are acceptable.
03:36:32: IPSEC(validate_proposal_request): proposal part #1,
(key eng. msg.) INBOUND local= 209.165.202.129, remote= 209.165.200.225,
local_proxy= 0.0.0.0/0.0.0.0/0/0 (type=4),
remote_proxy= 10.48.66.0/255.255.254.0/0/0 (type=4),
protocol= ESP, transform= esp-3des esp-sha-hmac ,

```

```

lifedur= 0s and 0kb,
spi= 0x0(0), conn_id= 0, keysize= 0, flags= 0x4
03:36:32: validate proposal request 0
03:36:32: ISAKMP (0:1): processing NONCE payload. message ID = 852253052
03:36:32: ISAKMP (0:1): processing ID payload. message ID = 852253052
03:36:32: ISAKMP (0:1): processing ID payload. message ID = 852253052
03:36:32: ISAKMP (0:1): asking for 1 spis from ipsec
03:36:32: ISAKMP (0:1): Node 852253052, Input = IKE_MESG_FROM_PEER, IKE_QM_EXCH
Old State = IKE_QM_READY New State = IKE_QM_SPI_STARVE
03:36:32: IPSEC(key_engine): got a queue event...
03:36:32: IPSEC(spi_response): getting spi 3997625134 for SA
    from 209.165.202.129 to 209.165.200.225 for prot 3
03:36:32: ISAKMP: received ke message (2/1)
03:36:32: CryptoEngine0: generate hmac context for conn id 1
03:36:32: ISAKMP (0:1): sending packet to 209.165.200.225 (R) QM_IDLE
03:36:32: ISAKMP (0:1): Node 852253052, Input = IKE_MESG_FROM_IPSEC, IKE_SPI_REPLY
Old State = IKE_QM_SPI_STARVE New State = IKE_QM_R_QM2
03:36:32: ISAKMP (0:1): received packet from 209.165.200.225 (R) QM_IDLE
03:36:32: CryptoEngine0: generate hmac context for conn id 1
03:36:32: ipsec allocate flow 0
03:36:32: ipsec allocate flow 0
03:36:32: ISAKMP (0:1): Creating IPSec SAs
03:36:32:     inbound SA from 209.165.200.225 to 209.165.202.129
        (proxy 10.48.66.0 to 0.0.0.0)
03:36:32:         has spi 0xEE46EB2E and conn_id 2002 and flags 4
03:36:32:             lifetime of 2147483647 seconds
03:36:32:         outbound SA from 209.165.202.129 to 209.165.200.225
        (proxy 0.0.0.0 to 10.48.66.0)
03:36:32:             has spi 674305339 and conn_id 2003 and flags C
03:36:32:                 lifetime of 2147483647 seconds
03:36:32: ISAKMP (0:1): deleting node 852253052 error FALSE reason "quick mode done (await())"
03:36:32: ISAKMP (0:1): Node 852253052, Input = IKE_MESG_FROM_PEER, IKE_QM_EXCH
Old State = IKE_QM_R_QM2 New State = IKE_QM_PHASE2_COMPLETE
03:36:32: IPSEC(key_engine): got a queue event...
    --- IPSec now initializes the SAs as these are !--- stored in the SA Database. 03:36:32:
IPSEC(initialize_sas): , (key eng. msg.) INBOUND local= 209.165.202.129, remote=
209.165.200.225, !--- This SA is for the actual data traffic between the !--- networks behind
the VPN Client and the Cisco IOS router. local_proxy= 0.0.0.0/0.0.0.0/0/0 (type=4),
remote_proxy= 10.48.66.0/255.255.254.0/0/0 (type=4),
protocol= ESP, transform= esp-3des esp-sha-hmac ,
lifedur= 2147483647s and 0kb,
spi= 0xEE46EB2E(3997625134), conn_id= 2002, keysize= 0, flags= 0x4
03:36:32: IPSEC(initialize_sas): ,
(key eng. msg.) OUTBOUND local= 209.165.202.129, remote= 209.165.200.225,
local_proxy= 0.0.0.0/0.0.0.0/0/0 (type=4),
remote_proxy= 10.48.66.0/255.255.254.0/0/0 (type=4),
protocol= ESP, transform= esp-3des esp-sha-hmac ,
lifedur= 2147483647s and 0kb,
spi= 0x2831153B(674305339), conn_id= 2003, keysize= 0, flags= 0xC
03:36:32: IPSEC(create_sa): sa created,
(sa) sa_dest= 209.165.202.129, sa_prot= 50,
sa_spi= 0xEE46EB2E(3997625134),
sa_trans= esp-3des esp-sha-hmac , sa_conn_id= 2002
03:36:32: IPSEC(create_sa): sa created,
(sa) sa_dest= 209.165.200.225, sa_prot= 50,
sa_spi= 0x2831153B(674305339),
sa_trans= esp-3des esp-sha-hmac , sa_conn_id= 2003
03:36:32: ISAKMP: received ke message (4/1)
03:36:32: ISAKMP: Locking CONFIG struct 0x631B752C for
crypto_ikmp_config_handle_kei_mess, count 3

```

Cisco VPN 3002 Hardware Client のデバッグ

VPN Client GUI から、Configuration > System > Events > Classes の順に選択して、IKE、IKEDBG、IPSEC、および IPSECDDBG をレベル 13 で SYSLOG に対して有効にします。テストを完了したら、デバッグを無効にすることに注意してください。

Cisco VPN 3002 Hardware Client のデバッグ

```
297 06/03/2002 11:02:30.100 SEV=7 IPSECDDBG/14 RPT=3
!---- The VPN Client attempts to connect to the headend.
!---- In this case, it is Cisco IOS. Sending KEY_ACQUIRE
to IKE for src 209.165.200.225, dst 209.165.202.129 298
06/03/2002 11:02:30.100 SEV=8 IKEDBG/0 RPT=108 pitcher:
received a key acquire message! 299 06/03/2002
11:02:30.100 SEV=4 IKE/41 RPT=135 209.165.202.129 IKE
Initiator: New Phase 1, Intf 2, IKE Peer 209.165.202.129
local Proxy Address 209.165.200.225, remote Proxy
Address 209.165.202.129, SA (ESP-3DES-MD5) 302
06/03/2002 11:02:30.100 SEV=9 IKEDBG/0 RPT=109
209.165.202.129 constructing ISA_SA for isakmp 303
06/03/2002 11:02:30.230 SEV=9 IKEDBG/0 RPT=110
209.165.202.129 constructing ke payload 304 06/03/2002
11:02:30.230 SEV=9 IKEDBG/1 RPT=30 209.165.202.129
constructing nonce payload 305 06/03/2002 11:02:30.230
SEV=9 IKEDBG/1 RPT=31 209.165.202.129 constructing ID
306 06/03/2002 11:02:30.230 SEV=9 IKEDBG/46 RPT=4
209.165.202.129 constructing xauth V6 VID payload 307
06/03/2002 11:02:30.230 SEV=9 IKEDBG/46 RPT=5
209.165.202.129 constructing VID payload 308 06/03/2002
11:02:30.230 SEV=9 IKEDBG/48 RPT=2 209.165.202.129 Send
Cisco Unity client VID 309 06/03/2002 11:02:30.230 SEV=8
IKEDBG/0 RPT=111 209.165.202.129 SENDING Message
(msgid=0) with payloads : HDR + SA (1) + KE (4) + NONCE
(10) + ID (5) + VENDOR (13) + VENDOR (13) + NONE (0)
... total length : 541 312 06/03/2002 11:02:30.520 SEV=8
IKEDBG/0 RPT=112 209.165.202.129 RECEIVED Message
(msgid=0) with payloads : HDR + SA (1) + VENDOR (13) +
VENDOR (13) + VENDOR (13) + VENDOR (13) + KE (4) + ID
(5) + NONCE (10) + HASH (8) + NONE (0) ... total length
: 348 315 06/03/2002 11:02:30.530 SEV=8 IKEDBG/0 RPT=113
209.165.202.129 RECEIVED Message (msgid=0) with payloads
: HDR + SA (1) + VENDOR (13) + VENDOR (13) + VENDOR (13)
+ VENDOR (13) + KE (4) + ID (5) + NONCE (10) + HASH (8)
+ NONE (0) ... total length : 348 318 06/03/2002
11:02:30.530 SEV=9 IKEDBG/0 RPT=114 209.165.202.129
processing SA payload 319 06/03/2002 11:02:30.530 SEV=7
IKEDBG/0 RPT=115 209.165.202.129 Oakley proposal is
acceptable 320 06/03/2002 11:02:30.530 SEV=9 IKEDBG/47
RPT=5 209.165.202.129 processing VID payload 321
06/03/2002 11:02:30.530 SEV=9 IKEDBG/49 RPT=4
209.165.202.129 Received Cisco Unity client VID 322
06/03/2002 11:02:30.530 SEV=9 IKEDBG/47 RPT=6
209.165.202.129 processing VID payload 323 06/03/2002
11:02:30.530 SEV=9 IKEDBG/49 RPT=5 209.165.202.129
Received DPD VID 324 06/03/2002 11:02:30.530 SEV=9
IKEDBG/47 RPT=7 209.165.202.129 processing VID payload
325 06/03/2002 11:02:30.530 SEV=9 IKEDBG/38 RPT=2
209.165.202.129 Processing IOS/PIX Vendor ID payload
(version: 1.0.0, capabilities: 0000007f) 326 06/03/2002
11:02:30.530 SEV=9 IKEDBG/47 RPT=8 209.165.202.129
processing VID payload 327 06/03/2002 11:02:30.530 SEV=9
IKEDBG/49 RPT=6 209.165.202.129 !---- The VPN Client
understands that it needs !--- to go through Extended
authentication to !--- bring the tunnel up. Received
```

```
xauth V6 VID 328 06/03/2002 11:02:30.530 SEV=9 IKEDBG/0
RPT=116 209.165.202.129 processing ke payload 329
06/03/2002 11:02:30.530 SEV=9 IKEDBG/0 RPT=117
209.165.202.129 processing ISA_KE 330 06/03/2002
11:02:30.530 SEV=9 IKEDBG/1 RPT=32 209.165.202.129
Processing ID 331 06/03/2002 11:02:30.530 SEV=9 IKEDBG/1
RPT=33 209.165.202.129 processing nonce payload 332
06/03/2002 11:02:30.660 SEV=9 IKEDBG/0 RPT=118
209.165.202.129 Generating keys for Initiator... 333
06/03/2002 11:02:30.670 SEV=9 IKEDBG/0 RPT=119
209.165.202.129 Group [209.165.202.129] processing hash
334 06/03/2002 11:02:30.670 SEV=9 IKEDBG/0 RPT=120
209.165.202.129 Group [209.165.202.129] computing hash
335 06/03/2002 11:02:30.680 SEV=9 IKEDBG/0 RPT=121 Group
[209.165.202.129] construct hash payload 336 06/03/2002
11:02:30.680 SEV=9 IKEDBG/0 RPT=122 209.165.202.129
Group [209.165.202.129] computing hash 337 06/03/2002
11:02:30.680 SEV=9 IKEDBG/46 RPT=6 209.165.202.129 Group
[209.165.202.129] constructing dpd vid payload 338
06/03/2002 11:02:30.680 SEV=8 IKEDBG/0 RPT=123
209.165.202.129 SENDING Message (msgid=0) with payloads
: HDR + HASH (8) + NOTIFY (11) + VENDOR (13) + NONE (0)
... total length : 100 340 06/03/2002 11:02:30.690 SEV=8
IKEDBG/0 RPT=124 209.165.202.129 RECEIVED Message
(msgid=71c8c9fd) with payloads : HDR + HASH (8) + NOTIFY
(11) + NONE (0) ... total length : 92 342 06/03/2002
11:02:30.690 SEV=9 IKEDBG/0 RPT=125 209.165.202.129
Group [209.165.202.129] processing hash 343 06/03/2002
11:02:30.690 SEV=9 IKEDBG/0 RPT=126 209.165.202.129
Group [209.165.202.129] Processing Notify payload 344
06/03/2002 11:02:30.690 SEV=5 IKE/73 RPT=19
209.165.202.129 Group [209.165.202.129] !--- As IOS has
a default IKE time of 1 day (86400) seconds !--- and
forces the VPN Client to accept this value. !--- This is
because Cisco IOS responds and the VPN Client initiates.
Responder forcing change of IKE rekeying duration from
2147483647 to 86400 seconds 347 06/03/2002 11:02:30.690
SEV=6 IKE/0 RPT=2 AM AM:843f96f6 received unexpected
event EV_RESET_LIFETIME in state AM_RSND_LST_ MSG 349
06/03/2002 11:02:30.700 SEV=8 IKEDBG/0 RPT=127
209.165.202.129 RECEIVED Message (msgid=ecb5af46) with
payloads : HDR + HASH (8) + ATTR (14) + NONE (0) ...
total length : 86 351 06/03/2002 11:02:30.700 SEV=9
IKEDBG/1 RPT=34 process_attr(): Enter! 352 06/03/2002
11:02:30.700 SEV=9 IKEDBG/1 RPT=35 Processing cfg
Request attributes 353 06/03/2002 11:02:30.700 SEV=9
IKEDBG/1 RPT=36 Received Xauth Type in request! 354
06/03/2002 11:02:30.700 SEV=9 IKEDBG/1 RPT=37 Received
Xauth Message! 355 06/03/2002 11:02:30.700 SEV=9
IKEDBG/1 RPT=38 Received Xauth Username request! 356
06/03/2002 11:02:30.700 SEV=9 IKEDBG/1 RPT=39 Received
Xauth Password request! 357 06/03/2002 11:02:30.700
SEV=9 IKEDBG/0 RPT=128 209.165.202.129 Group
[209.165.202.129] constructing blank hash 358 06/03/2002
11:02:30.700 SEV=9 IKEDBG/0 RPT=129 209.165.202.129
Group [209.165.202.129] constructing qm hash 359
06/03/2002 11:02:30.700 SEV=8 IKEDBG/0 RPT=130
209.165.202.129 SENDING Message (msgid=ecb5af46) with
payloads : HDR + HASH (8) + ATTR (14) + NONE (0) ...
total length : 77 361 06/03/2002 11:02:30.710 SEV=8
IKEDBG/0 RPT=131 209.165.202.129 RECEIVED Message
(msgid=ad808e58) with payloads : HDR + HASH (8) + ATTR
(14) + NONE (0) ... total length : 64 363 06/03/2002
11:02:30.710 SEV=9 IKEDBG/1 RPT=40 process_attr():
```

```
Enter! 364 06/03/2002 11:02:30.710 SEV=9 IKEDBG/1 RPT=41
Processing cfg Request attributes 365 06/03/2002
11:02:30.710 SEV=9 IKEDBG/1 RPT=42 Received Xauth Status
Set! 366 06/03/2002 11:02:30.710 SEV=9 IKEDBG/0 RPT=132
209.165.202.129 Group [209.165.202.129] constructing
blank hash 367 06/03/2002 11:02:30.710 SEV=9 IKEDBG/0
RPT=133 209.165.202.129 Group [209.165.202.129]
constructing qm hash 368 06/03/2002 11:02:30.710 SEV=8
IKEDBG/0 RPT=134 209.165.202.129 SENDING Message
(msgid=ad808e58) with payloads : HDR + HASH (8) + ATTR
(14) + NONE (0) ... total length : 60 370 06/03/2002
11:02:30.720 SEV=9 IKEDBG/0 RPT=135 209.165.202.129
Group [209.165.202.129] constructing blank hash 371
06/03/2002 11:02:30.720 SEV=9 IKEDBG/0 RPT=136
209.165.202.129 Group [209.165.202.129] constructing qm
hash 372 06/03/2002 11:02:30.720 SEV=8 IKEDBG/0 RPT=137
209.165.202.129 SENDING Message (msgid=30ce63a8) with
payloads : HDR + HASH (8) + ATTR (14) + NONE (0) ...
total length : 231 374 06/03/2002 11:02:30.740 SEV=8
IKEDBG/0 RPT=138 209.165.202.129 RECEIVED Message
(msgid=30ce63a8) with payloads : HDR + HASH (8) + ATTR
(14) + NONE (0) ... total length : 313 376 06/03/2002
11:02:30.740 SEV=9 IKEDBG/1 RPT=43 process_attr():
Enter! 377 06/03/2002 11:02:30.740 SEV=9 IKEDBG/1 RPT=44
Processing MODE_CFG Reply attributes !--- The VPN Client
processes the mode !--- configuration reply attributes
sent by Cisco IOS. 378 06/03/2002 11:02:30.740 SEV=6
IKE/130 RPT=2 209.165.202.129 Group [209.165.202.129]
Received unsupported transaction mode attribute: 7 379
06/03/2002 11:02:30.740 SEV=5 IKE/115 RPT=7
209.165.202.129 Group [209.165.202.129] Client rejected
NAT enabled IPSec request, falling back to standard
IPSec 381 06/03/2002 11:02:30.740 SEV=3 AUTH/24 RPT=7
Tunnel to headend device 209.165.202.129 connected 382
06/03/2002 11:02:30.740 SEV=9 IKEDBG/0 RPT=139
209.165.202.129 Group [209.165.202.129] Oakley begin
quick mode 383 06/03/2002 11:02:30.740 SEV=4 IKE/119
RPT=7 209.165.202.129 Group [209.165.202.129] !--- Phase
1 is complete. 384 06/03/2002 11:02:30.740 SEV=6 IKE/121
RPT=2 209.165.202.129 Keep-alive type for this
connection: DPD 385 06/03/2002 11:02:30.740 SEV=7
IKEDBG/0 RPT=140 209.165.202.129 Group [209.165.202.129]
Starting phase 1 rekey timer: 73440000 (ms) 386
06/03/2002 11:02:30.740 SEV=9 IPSECDBG/6 RPT=15 IPSEC
key message parse - msgtype 6, len 200, vers 1, pid
00000000, seq 13, err 0, type 2, mode 0, state 32, label
0, pad 0, spi 00000000, encrKeyLen 0, hashKey Len 0,
ivlen 0, alg 0, hmacAlg 0, lifetype 0, lifetime1 662488,
lifetime2 0, dsI d 300 390 06/03/2002 11:02:30.740 SEV=9
IPSECDBG/1 RPT=47 Processing KEY_GETSPI msg! 391
06/03/2002 11:02:30.740 SEV=7 IPSECDBG/13 RPT=3 Reserved
SPI 1608220759 392 06/03/2002 11:02:30.740 SEV=8
IKEDBG/6 RPT=3 IKE got SPI from key engine: SPI =
0x5fdb8057 393 06/03/2002 11:02:30.750 SEV=9 IKEDBG/0
RPT=141 209.165.202.129 Group [209.165.202.129] oakley
constucting quick mode 394 06/03/2002 11:02:30.750 SEV=9
IKEDBG/0 RPT=142 209.165.202.129 Group [209.165.202.129]
constructing blank hash 395 06/03/2002 11:02:30.750
SEV=9 IKEDBG/0 RPT=143 209.165.202.129 Group
[209.165.202.129] constructing ISA_SA for ipsec 396
06/03/2002 11:02:30.750 SEV=9 IKEDBG/1 RPT=45
209.165.202.129 Group [209.165.202.129] constructing
ipsec nonce payload 397 06/03/2002 11:02:30.750 SEV=9
IKEDBG/1 RPT=46 209.165.202.129 Group [209.165.202.129]
```

```
constructing proxy ID 398 06/03/2002 11:02:30.750 SEV=7
IKEDBG/0 RPT=144 209.165.202.129 Group [209.165.202.129]
Transmitting Proxy Id: !--- This is the SA for
management between !--- the VPN Client and Cisco IOS.
Local host: 209.165.200.225 Protocol 0 Port 0
Remote host: 209.165.202.129 Protocol 0 Port 0
402 06/03/2002 11:02:30.750 SEV=9 IKEDBG/0 RPT=145
209.165.202.129
Group [209.165.202.129]
constructing qm hash
403 06/03/2002 11:02:30.750 SEV=8 IKEDBG/0 RPT=146
209.165.202.129
SENDING Message (msgid=e429a70e) with payloads :
HDR + HASH (8) + SA (1) + NONCE (10) + ID (5) + ID (5) +
NONE (0) ... total leng
th : 292
406 06/03/2002 11:02:31.010 SEV=8 IKEDBG/0 RPT=147
209.165.202.129
RECEIVED Message (msgid=e429a70e) with payloads :
HDR + HASH (8) + SA (1) + NONCE (10) + ID (5) + ID (5) +
NOTIFY (11) + NONE (0)
... total length : 192
409 06/03/2002 11:02:31.010 SEV=9 IKEDBG/0 RPT=148
209.165.202.129
Group [209.165.202.129]
processing hash
410 06/03/2002 11:02:31.010 SEV=9 IKEDBG/0 RPT=149
209.165.202.129
Group [209.165.202.129]
processing SA payload
411 06/03/2002 11:02:31.020 SEV=9 IKEDBG/1 RPT=47
209.165.202.129
Group [209.165.202.129]
processing nonce payload
412 06/03/2002 11:02:31.020 SEV=9 IKEDBG/1 RPT=48
209.165.202.129
Group [209.165.202.129]
Processing ID
413 06/03/2002 11:02:31.020 SEV=9 IKEDBG/1 RPT=49
209.165.202.129
Group [209.165.202.129]
Processing ID
414 06/03/2002 11:02:31.020 SEV=9 IKEDBG/0 RPT=150
209.165.202.129
Group [209.165.202.129]
Processing Notify payload
415 06/03/2002 11:02:31.020 SEV=5 IKE/73 RPT=20
209.165.202.129
Group [209.165.202.129]
Responder forcing change of IPsec rekeying duration from
2147483647 to 3600 seco
nds
418 06/03/2002 11:02:31.020 SEV=9 IKEDBG/0 RPT=151
209.165.202.129
Group [209.165.202.129]
loading all IPSEC SAs
419 06/03/2002 11:02:31.020 SEV=9 IKEDBG/1 RPT=50
209.165.202.129
Group [209.165.202.129]
Generating Quick Mode Key!
420 06/03/2002 11:02:31.020 SEV=9 IKEDBG/1 RPT=51
209.165.202.129
Group [209.165.202.129]
Generating Quick Mode Key!
```

```
421 06/03/2002 11:02:31.020 SEV=7 IKEDBG/0 RPT=152
209.165.202.129
Group [209.165.202.129]
Loading host:
Dst: 209.165.202.129
Src: 209.165.200.225
423 06/03/2002 11:02:31.020 SEV=4 IKE/49 RPT=13
209.165.202.129
Group [209.165.202.129]
Security negotiation complete for peer (209.165.202.129)
Initiator, Inbound SPI = 0x5fdb8057, Outbound SPI =
0xa088f2dc
426 06/03/2002 11:02:31.020 SEV=9 IKEDBG/0 RPT=153
209.165.202.129
Group [209.165.202.129]
oakley constructing final quick mode
427 06/03/2002 11:02:31.030 SEV=8 IKEDBG/0 RPT=154
209.165.202.129
SENDING Message (msgid=e429a70e) with payloads :
HDR + HASH (8) + NONE (0) ... total length : 76
429 06/03/2002 11:02:31.030 SEV=9 IPSECDBG/6 RPT=16
IPSEC key message parse - msgtype 1, len 612, vers 1,
pid 00000000, seq 0, err 0
, type 2, mode 1, state 64, label 0, pad 0, spi
a088f2dc, encrKeyLen 24, hashKey
Len 20, ivlen 8, alg 2, hmacAlg 4, lifetype 0, lifetime1
662488, lifetime2 0, ds
Id -378167296
433 06/03/2002 11:02:31.030 SEV=9 IPSECDBG/1 RPT=48
Processing KEY_ADD msg!
434 06/03/2002 11:02:31.030 SEV=9 IPSECDBG/1 RPT=49
key_msghdr2secassoc(): Enter
435 06/03/2002 11:02:31.030 SEV=7 IPSECDBG/1 RPT=50
No USER filter configured
436 06/03/2002 11:02:31.030 SEV=9 IPSECDBG/1 RPT=51
KeyProcessAdd: Enter
437 06/03/2002 11:02:31.030 SEV=8 IPSECDBG/1 RPT=52
KeyProcessAdd: Adding outbound SA
438 06/03/2002 11:02:31.030 SEV=8 IPSECDBG/1 RPT=53
KeyProcessAdd: src 209.165.200.225 mask 0.0.0.0, dst
209.165.202.129 mask 0.0.0.
0
440 06/03/2002 11:02:31.030 SEV=8 IPSECDBG/1 RPT=54
KeyProcessAdd: FilterIpsecAddIKEsa success
441 06/03/2002 11:02:31.030 SEV=9 IPSECDBG/6 RPT=17
IPSEC key message parse - msgtype 3, len 332, vers 1,
pid 00000000, seq 0, err 0
, type 2, mode 1, state 32, label 0, pad 0, spi
5fdb8057, encrKeyLen 24, hashKey
Len 20, ivlen 8, alg 2, hmacAlg 4, lifetype 0, lifetime1
662488, lifetime2 0, ds
Id -378167296
445 06/03/2002 11:02:31.030 SEV=9 IPSECDBG/1 RPT=55
Processing KEY_UPDATE msg!
446 06/03/2002 11:02:31.030 SEV=9 IPSECDBG/1 RPT=56
Update inbound SA addresses
447 06/03/2002 11:02:31.030 SEV=9 IPSECDBG/1 RPT=57
key_msghdr2secassoc(): Enter
448 06/03/2002 11:02:31.030 SEV=7 IPSECDBG/1 RPT=58
No USER filter configured
449 06/03/2002 11:02:31.030 SEV=9 IPSECDBG/1 RPT=59
KeyProcessUpdate: Enter
450 06/03/2002 11:02:31.030 SEV=8 IPSECDBG/1 RPT=60
KeyProcessUpdate: success
```

```

451 06/03/2002 11:02:31.030 SEV=8 IKEDBG/7 RPT=3
IKE got a KEY_ADD msg for SA: SPI = 0xa088f2dc
452 06/03/2002 11:02:31.030 SEV=8 IKEDBG/0 RPT=155
pitcher: rcv KEY_UPDATE, spi 0x5fdb8057
453 06/03/2002 11:02:31.040 SEV=4 IKE/120 RPT=13
209.165.202.129
Group [209.165.202.129]
PHASE 2 COMPLETED (msgid=e429a70e)
!--- This line indicates that SA establishment !--- for management between the VPN Client and Cisco IOS is complete. 454 06/03/2002 11:02:35.040 SEV=7 IPSECDBG/10 RPT=4 IPSEC ipsec_output() can call key_acquire()
because 4 seconds have elapsed since last IKE negotiation began (src 0x0a3042b9, dst 0x00a66e24) 456 06/03/2002 11:02:35.040 SEV=7 IPSECDBG/14 RPT=4 Sending KEY_ACQUIRE to IKE for src 10.48.66.185, dst 0.0.0.0 457 06/03/2002 11:02:35.040 SEV=8 IKEDBG/0 RPT=156 pitcher: received a key acquire message! 458 06/03/2002 11:02:35.040 SEV=4 IKE/41 RPT=136 IKE Initiator: New Phase 2, Intf 2, IKE Peer 209.165.202.129 local Proxy Address 10.48.66.0, remote Proxy Address 0.0.0.0, SA (ESP-3DES-MD5) 460 06/03/2002 11:02:35.040 SEV=9 IKEDBG/0 RPT=157 209.165.202.129 Group [209.165.202.129] Oakley begin quick mode 461 06/03/2002 11:02:35.040 SEV=9 IPSECDBG/6 RPT=18 IPSEC key message parse -
msgtype 6, len 200, vers 1, pid 00000000, seq 14, err 0,
type 2, mode 0, state 32, label 0, pad 0, spi 00000000,
encrKeyLen 0, hashKey Len 0, ivlen 0, alg 0, hmacAlg 0,
lifetype 0, lifetime1 662488, lifetime2 0, dsI d 300 465 06/03/2002 11:02:35.040 SEV=9 IPSECDBG/1 RPT=61 Processing KEY_GETSPI msg! 466 06/03/2002 11:02:35.040 SEV=7 IPSECDBG/13 RPT=4 Reserved SPI 1819592269 467 06/03/2002 11:02:35.040 SEV=8 IKEDBG/6 RPT=4 IKE got SPI from key engine: SPI = 0x6c74c64d 468 06/03/2002 11:02:35.040 SEV=9 IKEDBG/0 RPT=158 209.165.202.129 Group [209.165.202.129] oakley constucting quick mode 469 06/03/2002 11:02:35.040 SEV=9 IKEDBG/0 RPT=159 209.165.202.129 Group [209.165.202.129] constructing blank hash 470 06/03/2002 11:02:35.040 SEV=9 IKEDBG/0 RPT=160 209.165.202.129 Group [209.165.202.129] constructing ISA_SA for ipsec 471 06/03/2002 11:02:35.040 SEV=9 IKEDBG/1 RPT=52 209.165.202.129 Group [209.165.202.129] constructing ipsec nonce payload 472 06/03/2002 11:02:35.040 SEV=9 IKEDBG/1 RPT=53 209.165.202.129 Group [209.165.202.129] constructing proxy ID 473 06/03/2002 11:02:35.040 SEV=7 IKEDBG/0 RPT=161 209.165.202.129 Group [209.165.202.129] Transmitting Proxy Id: Local subnet: 10.48.66.0 mask 255.255.254.0 Protocol 0 Port 0
Remote subnet: 0.0.0.0 Mask 0.0.0.0 Protocol 0 Port 0
!--- This line indicates the SA for the traffic between the networks behind the VPN Client and Cisco IOS.
477 06/03/2002 11:02:35.040 SEV=9 IKEDBG/0 RPT=162 209.165.202.129 Group [209.165.202.129] constructing qm hash 478 06/03/2002 11:02:35.040 SEV=8 IKEDBG/0 RPT=163 209.165.202.129 SENDING Message (msgid=a809c6b4) with payloads : HDR + HASH (8) + SA (1) + NONCE (10) + ID (5) + ID (5) + NONE (0) ... total leng th : 300 481 06/03/2002 11:02:35.310 SEV=8 IKEDBG/0 RPT=164 209.165.202.129 RECEIVED Message (msgid=a809c6b4) with payloads : HDR + HASH (8) + SA (1) + NONCE (10) + ID (5) + ID (5) + NOTIFY (11) + NONE (0) ... total length : 200 484 06/03/2002 11:02:35.310 SEV=9 IKEDBG/0 RPT=165

```

```
209.165.202.129 Group [209.165.202.129] processing hash  
485 06/03/2002 11:02:35.310 SEV=9 IKEDBG/0 RPT=166  
209.165.202.129 Group [209.165.202.129] processing SA  
payload 486 06/03/2002 11:02:35.310 SEV=9 IKEDBG/1  
RPT=54 209.165.202.129 Group [209.165.202.129]  
processing nonce payload 487 06/03/2002 11:02:35.310  
SEV=9 IKEDBG/1 RPT=55 209.165.202.129 Group  
[209.165.202.129] Processing ID 488 06/03/2002  
11:02:35.310 SEV=9 IKEDBG/1 RPT=56 209.165.202.129 Group  
[209.165.202.129] Processing ID 489 06/03/2002  
11:02:35.310 SEV=9 IKEDBG/0 RPT=167 209.165.202.129  
Group [209.165.202.129] Processing Notify payload 490  
06/03/2002 11:02:35.310 SEV=5 IKE/73 RPT=21  
209.165.202.129 Group [209.165.202.129] Responder  
forcing change of IPSec rekeying duration from  
2147483647 to 3600 seco nds 493 06/03/2002 11:02:35.310  
SEV=9 IKEDBG/0 RPT=168 209.165.202.129 Group  
[209.165.202.129] loading all IPSEC SAs 494 06/03/2002  
11:02:35.310 SEV=9 IKEDBG/1 RPT=57 209.165.202.129 Group  
[209.165.202.129] Generating Quick Mode Key! 495  
06/03/2002 11:02:35.320 SEV=9 IKEDBG/1 RPT=58  
209.165.202.129 Group [209.165.202.129] Generating Quick  
Mode Key! 496 06/03/2002 11:02:35.320 SEV=7 IKEDBG/0  
RPT=169 209.165.202.129 Group [209.165.202.129] Loading  
subnet: Dst: 0.0.0.0 mask: 0.0.0.0 Src: 10.48.66.0 mask:  
255.255.254.0 499 06/03/2002 11:02:35.320 SEV=4 IKE/49  
RPT=14 209.165.202.129 Group [209.165.202.129] Security  
negotiation complete for peer (209.165.202.129)  
Initiator, Inbound SPI = 0x6c74c64d, Outbound SPI =  
0x8e34d356 502 06/03/2002 11:02:35.320 SEV=9 IKEDBG/0  
RPT=170 209.165.202.129 Group [209.165.202.129] oakley  
constructing final quick mode 503 06/03/2002  
11:02:35.320 SEV=8 IKEDBG/0 RPT=171 209.165.202.129  
SENDING Message (msgid=a809c6b4) with payloads : HDR +  
HASH (8) + NONE (0) ... total length : 76 505 06/03/2002  
11:02:35.320 SEV=9 IPSECDBG/6 RPT=19 IPSEC key message  
parse - msgtype 1, len 612, vers 1, pid 00000000, seq 0,  
err 0 , type 2, mode 1, state 64, label 0, pad 0, spi  
8e34d356, encrKeyLen 24, hashKey Len 20, ivlen 8, alg 2,  
hmacAlg 4, lifetype 0, lifetime1 662488, lifetime2 0, ds  
Id -378167296 509 06/03/2002 11:02:35.330 SEV=9  
IPSECDBG/1 RPT=62 Processing KEY_ADD msg! 510 06/03/2002  
11:02:35.330 SEV=9 IPSECDBG/1 RPT=63  
key_msghdr2secassoc(): Enter 511 06/03/2002 11:02:35.330  
SEV=7 IPSECDBG/1 RPT=64 No USER filter configured 512  
06/03/2002 11:02:35.330 SEV=9 IPSECDBG/1 RPT=65  
KeyProcessAdd: Enter 513 06/03/2002 11:02:35.330 SEV=8  
IPSECDBG/1 RPT=66 KeyProcessAdd: Adding outbound SA 514  
06/03/2002 11:02:35.330 SEV=8 IPSECDBG/1 RPT=67  
KeyProcessAdd: src 10.48.66.0 mask 0.0.1.255, dst  
0.0.0.0 mask 255.255.255.255 515 06/03/2002 11:02:35.330  
SEV=8 IPSECDBG/1 RPT=68 KeyProcessAdd:  
FilterIpsecAddIkeSa success 516 06/03/2002 11:02:35.330  
SEV=9 IPSECDBG/6 RPT=20 IPSEC key message parse -  
msgtype 3, len 332, vers 1, pid 00000000, seq 0, err 0 ,  
type 2, mode 1, state 32, label 0, pad 0, spi 6c74c64d,  
encrKeyLen 24, hashKey Len 20, ivlen 8, alg 2, hmacAlg  
4, lifetype 0, lifetime1 662488, lifetime2 0, ds Id -  
378167296 520 06/03/2002 11:02:35.330 SEV=9 IPSECDBG/1  
RPT=69 Processing KEY_UPDATE msg! 521 06/03/2002  
11:02:35.330 SEV=9 IPSECDBG/1 RPT=70 Update inbound SA  
addresses 522 06/03/2002 11:02:35.330 SEV=9 IPSECDBG/1  
RPT=71 key_msghdr2secassoc(): Enter 523 06/03/2002  
11:02:35.330 SEV=7 IPSECDBG/1 RPT=72 No USER filter
```

```
configured 524 06/03/2002 11:02:35.330 SEV=9 IPSECDBG/1
RPT=73 KeyProcessUpdate: Enter 525 06/03/2002
11:02:35.330 SEV=8 IPSECDBG/1 RPT=74 KeyProcessUpdate:
success 526 06/03/2002 11:02:35.330 SEV=8 IKEDBG/7 RPT=4
IKE got a KEY_ADD msg for SA: SPI = 0x8e34d356 527
06/03/2002 11:02:35.330 SEV=8 IKEDBG/0 RPT=172 pitcher:
rcv KEY_UPDATE, spi 0x6c74c64d 528 06/03/2002
11:02:35.330 SEV=4 IKE/120 RPT=14 209.165.202.129 Group
[209.165.202.129] PHASE 2 COMPLETED (msgid=a809c6b4) !--
- This line indicates that SA establishment !--- for
networks between the VPN Client and Cisco IOS is
complete.
```

関連情報

- [Cisco VPN 3000 コンセントレータのサポート](#)
- [Cisco VPN 3002 Hardware Client のサポート](#)
- [IPSec ネゴシエーション/IKE プロトコルのサポート](#)
- [テクニカル サポートとドキュメント – Cisco Systems](#)