

ASR 5000 シリーズで最初のトリガー後にアラームの現在の障害発生率を確認する方法

内容

[質問](#)

[応答 \(Answer \)](#)

[関連するシスコ サポート コミュニティ ディスカッション](#)

質問

最初のトリガーの後に、アラームの現在の障害率を随時判別する方法。初期故障率は見つけやすいかもしれませんが、現在の故障率は数時間後に見つかるでしょうか。

応答 (Answer)

最初のSNMPトラップ、ログ、およびアラームは、監視対象しきい値の初期障害レートを追跡しますが、現在の障害レートを取得する方法が明らかでない場合があります。「show threshold」の下部にあるコマンドは、最後のポーリング間隔における現在の失敗率に関するすべてのアラームのステータスを報告します。

```
[local]PDSN> show threshold
Friday June 12 04:39:32 UTC 2015
```

Outstanding alarms:

```
      Threshold Name:    aaa-acct-failure-rate
      Alarm Source:      System
Last Measured: 77% Raise Time: 2015-Jun-11+22:15:05
```

```
[local]PDSN> show thresh
Friday June 12 05:34:04 UTC 2015
```

Outstanding alarms:

```
      Threshold Name:    aaa-acct-failure-rate
Alarm Source: System Last Measured: 65%
      Raise Time:        2015-Jun-11+22:15:05
```

```
[local]PDSN> show thresh
Friday June 12 06:06:07 UTC 2015
```

Outstanding alarms:

```
      Threshold Name:    aaa-acct-failure-rate
      Alarm Source:      System
Last Measured: 61%
      Raise Time:        2015-Jun-11+22:15:05
```

```
[local]PDSN> show alarm outstanding verbose
Friday June 12 04:41:28 UTC 2015
```

Severity Object Timestamp Alarm ID

Alarm Details

Minor Chassis Thursday **June 11 22:15:05** U 5770524519230406656

<28:**aaa-acct-failure-rate**> has reached or exceeded the configured threshold <25%>, the measured value is <32%>. It is detected at <System>.

2015-Jun-11+**22:15:05**.418 [alarmctrl 65201 info] [8/0/5185 <evlogd:0> alarmctrl.c:192] [software internal system critical-info syslog] **Alarm condition:** id 5015057a08690000 (Minor): <28:**aaa-acct-failure-rate**> has reached or exceeded the configured threshold <25%>, the measured value is <32%>. It is detected at <System>.

Thu Jun 11 **22:15:05** 2015 Internal trap notification 222 (**ThreshAAAacctFailRate**) threshold 25% measured value 32%

2015-Jun-12+**07:15:05**.210 [alarmctrl 65200 info] [8/0/5185 <evlogd:0> alarmctrl.c:285] [software internal system critical-info syslog] **Alarm cleared:** id 5015057a08690000: <28:**aaa-acct-failure-rate**> has reached or exceeded the configured threshold <25%>, the measured value is <32%>. It is detected at <System>.

Fri Jun 12 07:15:05 2015 Internal trap notification 223 (**ThreshClearAAAacctFailRate**) threshold 20%**measured value 0%**

[local]PDSN> show threshold Friday June 12 13:45:26 UTC 2015

...

No outstanding alarm