



重大度別メッセージ リスト

この付録には、次の項があります。

- [アラートメッセージ、重大度 1 \(P.A-2\)](#)
- [クリティカルメッセージ、重大度 2 \(P.A-4\)](#)
- [エラーメッセージ、重大度 3 \(P.A-6\)](#)
- [警告メッセージ、重大度 4 \(P.A-13\)](#)
- [通知メッセージ、重大度 5 \(P.A-18\)](#)
- [情報メッセージ、重大度 6 \(P.A-23\)](#)
- [デバッグメッセージ、重大度 7 \(P.A-31\)](#)



(注)

Cisco ASA は、重大度 0 (緊急) メッセージは syslog に送信しません。この重大度 0 メッセージは UNIX のパニック メッセージと同様に、システムが不安定であることを示します。

アラートメッセージ、重大度 1

次のメッセージが重大度 1（アラート）で表示されます。

- %PIX|ASA-1-101001: (Primary) Failover cable OK.
- %PIX|ASA-1-101002: (Primary) Bad failover cable.
- %PIX|ASA-1-101003: (Primary) Failover cable not connected (this unit).
- %PIX|ASA-1-101004: (Primary) Failover cable not connected (other unit).
- %PIX|ASA-1-101005: (Primary) Error reading failover cable status.
- %PIX|ASA-1-102001: (Primary) Power failure/System reload other side.
- %PIX|ASA-1-103001: (Primary) No response from other firewall (reason code = code).
- %PIX|ASA-1-103002: (Primary) Other firewall network interface interface_number OK.
- %PIX|ASA-1-103003: (Primary) Other firewall network interface interface_number failed.
- %PIX|ASA-1-103004: (Primary) Other firewall reports this firewall failed.
- %PIX|ASA-1-103005: (Primary) Other firewall reporting failure.
- %PIX|ASA-1-104001: (Primary) Switching to ACTIVE (cause: string).
- %PIX|ASA-1-104002: (Primary) Switching to STNDBY (cause: string).
- %PIX|ASA-1-104003: (Primary) Switching to FAILED.
- %PIX|ASA-1-104004: (Primary) Switching to OK.
- %PIX|ASA-1-105001: (Primary) Disabling failover.
- %PIX|ASA-1-105002: (Primary) Enabling failover.
- %PIX|ASA-1-105003: (Primary) Monitoring on interface interface_name waiting
- %PIX|ASA-1-105004: (Primary) Monitoring on interface interface_name normal
- %PIX|ASA-1-105005: (Primary) Lost Failover communications with mate on interface interface_name.
- %PIX|ASA-1-105006: (Primary) Link status 'Up' on interface interface_name.
- %PIX|ASA-1-105007: (Primary) Link status 'Down' on interface interface_name.
- %PIX|ASA-1-105008: (Primary) Testing interface interface_name.
- %PIX|ASA-1-105009: (Primary) Testing on interface interface_name {Passed|Failed}.
- %PIX|ASA-1-105011: (Primary) Failover cable communication failure
- %PIX|ASA-1-105020: (Primary) Incomplete/slow config replication
- %PIX|ASA-1-105021: (failover_unit) Standby unit failed to sync due to a locked context_name config. Lock held by lock_owner_name
- %PIX|ASA-1-105031: Failover LAN interface is up
- %PIX|ASA-1-105032: LAN Failover interface is down
- %PIX|ASA-1-105034: Receive a LAN_FAILOVER_UP message from peer.
- %PIX|ASA-1-105035: Receive a LAN failover interface down msg from peer.
- %PIX|ASA-1-105036: dropped a LAN Failover command message.
- %PIX|ASA-1-105037: The primary and standby units are switching back and forth as the active unit.
- %PIX|ASA-1-105038: (Primary) Interface count mismatch
- %PIX|ASA-1-105039: (Primary) Unable to verify the Interface count with mate. Failover may be disabled in mate.
- %PIX|ASA-1-105040: (Primary) Mate failover version is not compatible.
- %PIX|ASA-1-105042: (Primary) Failover interface OK
- %PIX|ASA-1-105043: (Primary) Failover interface failed
- %PIX|ASA-1-105044: (Primary) Mate operational mode mode is not compatible with my mode mode.

- %PIX|ASA-1-105045: (Primary) Mate license (number contexts) is not compatible with my license (number contexts).
- %PIX|ASA-1-105046 (Primary|Secondary) Mate has a different chassis
- %PIX|ASA-1-105047: Mate has a io_card_name1 card in slot slot_number which is different from my io_card_name2
- %PIX|ASA-1-106021: Deny protocol reverse path check from source_address to dest_address on interface interface_name
- %PIX|ASA-1-106022: Deny protocol connection spoof from source_address to dest_address on interface interface_name
- %PIX|ASA-1-106101 The number of ACL log deny-flows has reached limit (number).
- %PIX|ASA-1-107001: RIP auth failed from IP_address: version=number, type=string, mode=string, sequence=number on interface interface_name
- %PIX|ASA-1-107002: RIP pkt failed from IP_address: version=number on interface interface_name
- %ASA-1-114001: Failed to initialize 4GE SSM I/O card (error error_string).
- %ASA-1-114002: Failed to initialize SFP in 4GE SSM I/O card (error error_string).
- %ASA-1-114003: Failed to run cached commands in 4GE SSM I/O card (error error_string).
- %PIX|ASA-1-111111 error_message
- %PIX|ASA-1-415004:internal_sig_id Content type not found - action mime_type from source_address to dest_address
- %PIX|ASA-1-709003: (Primary) Beginning configuration replication: Sending to mate.
- %PIX|ASA-1-709004: (Primary) End Configuration Replication (ACT)
- %PIX|ASA-1-709005: (Primary) Beginning configuration replication: Receiving from mate.
- %PIX|ASA-1-709006: (Primary) End Configuration Replication (STB)

クリティカル メッセージ、重大度 2

次のメッセージが重大度 2（クリティカル）で表示されます。

- %PIX|ASA-2-106001: Inbound TCP connection denied from IP_address/port to IP_address/port flags tcp_flags on interface interface_name
- %PIX|ASA-2-106002: protocol Connection denied by outbound list acl_ID src inside_address dest outside_address
- %PIX|ASA-2-106006: Deny inbound UDP from outside_address/outside_port to inside_address/inside_port on interface interface_name.
- %PIX|ASA-2-106007: Deny inbound UDP from outside_address/outside_port to inside_address/inside_port due to DNS {Response|Query}.
- %PIX|ASA-2-106013: Dropping echo request from IP_address to PAT address IP_address
- %PIX|ASA-2-106016: Deny IP spoof from (IP_address) to IP_address on interface interface_name.
- %PIX|ASA-2-106017: Deny IP due to Land Attack from IP_address to IP_address
- %PIX|ASA-2-106018: ICMP packet type ICMP_type denied by outbound list acl_ID src inside_address dest outside_address
- %PIX|ASA-2-106020: Deny IP teardrop fragment (size = number, offset = number) from IP_address to IP_address
- %PIX|ASA-2-106024: Access rules memory exhausted
- %PIX|ASA-2-108002: SMTP replaced string: out source_address in inside_address data: string
- %PIX|ASA-2-108003: Terminating ESMTP/SMTP connection; malicious pattern detected in the mail address from source_interface:source_address/source_port to dest_interface:dest_address/dset_port. Data:string
- %PIX|ASA-2-109011: Authen Session Start: user 'user', sid number
- %PIX|ASA-3-109032: Unable to install ACL access_list, downloaded for user username; Error in ACE: ace.
- %PIX|ASA-2-112001: (string:dec) Clear complete.
- %PIX|ASA-3-113020: Kerberos error : Clock skew with server ip_address greater than 300 seconds
- %ASA-3-114006: Failed to get port statistics in 4GE SSM I/O card (error error_string).
- %ASA-3-114007: Failed to get current msr in 4GE SSM I/O card (error error_string).
- %ASA-3-114008: Failed to enable port after link is up in 4GE SSM I/O card due to either I2C serial bus access error or switch access error.
- %ASA-3-114009: Failed to set multicast address in 4GE SSM I/O card (error error_string).
- %ASA-3-114010: Failed to set multicast hardware address in 4GE SSM I/O card (error error_string).
- %ASA-3-114011: Failed to delete multicast address in 4GE SSM I/O card (error error_string).
- %ASA-3-114012: Failed to delete multicast hardware address in 4GE SSM I/O card (error error_string).
- %ASA-3-114013: Failed to set mac address table in 4GE SSM I/O card (error error_string).
- %ASA-3-114014: Failed to set mac address in 4GE SSM I/O card (error error_string).
- %ASA-3-114015: Failed to set mode in 4GE SSM I/O card (error error_string).
- %ASA-3-114016: Failed to set multicast mode in 4GE SSM I/O card (error error_string).
- %ASA-3-114017: Failed to get link status in 4GE SSM I/O card (error error_string).
- %ASA-3-114018: Failed to set port speed in 4GE SSM I/O card (error error_string).
- %ASA-3-114019: Failed to set media type in 4GE SSM I/O card (error error_string).
- %ASA-3-114020: Port link speed is unknown in 4GE SSM I/O card.
- %PIX|ASA-2-201003: Embryonic limit exceeded nconns/elimit for outside_address/outside_port (global_address) inside_address/inside_port on interface interface_name

- %PIX|ASA-2-214001: Terminating manager session from IP_address on interface interface_name. Reason: incoming encrypted data (number bytes) longer than number bytes
- %PIX|ASA-2-215001:Bad route_compress() call, sdb= number
- %PIX|ASA-2-217001: No memory for string in string
- %PIX|ASA-2-304007: URL Server IP_address not responding, ENTERING ALLOW mode.
- %PIX|ASA-2-304008: LEAVING ALLOW mode, URL Server is up.
- %ASA-3-323004: Module in slot slotnum failed to write software vnewver (currently vver), reason. Hw-module reset is required before further use.
- %ASA-3-323005: Module in slot slotnum can not be powered on completely
- %ASA-3-420001 : IPS card not up and fail-close mode used, dropping ICMP packet ifc_in:SIP to ifc_out:DIP (typeICMP_TYPE, code ICMP_CODE)"
- %PIX|ASA-3-702307: IPSEC: An direction tunnel_type SA (SPI=spi) between local_IP and remote_IP (username) is rekeying due to data rollover.
- %PIX|ASA-2-709007: Configuration replication failed for command command
- %PIX|ASA-2-713078: Temp buffer for building mode config attributes exceeded: bufsize available_size, used value
- %PIX|ASA-2-713176: Device_type memory resources are critical, IKE key acquire message on interface interface_number, for Peer IP_address ignored
- %PIX|ASA-3-713230 Internal Error, ike_lock trying to lock bit that is already locked for type type
- %PIX|ASA-3-713231 Internal Error, ike_lock trying to unlock bit that is not locked for type type
- %PIX|ASA-3-713232 SA lock refCnt = value, bitmask = hexvalue, p1_decrypt_cb = value, qm_decrypt_cb = value, qm_hash_cb = value, qm_spi_ok_cb = value, qm_dh_cb = value, qm_secret_key_cb = value, qm_encrypt_cb = value
- %PIX|ASA-3-713238: Invalid source proxy address: 0.0.0.0! Check private address on remote client
- %PIX|ASA-3-713902 Descriptive_event_string
- %PIX|ASA-2-717008: Insufficient memory to process_requiring_memory.
- %PIX|ASA-2-717011: Unexpected event event event_ID
- %PIX|ASA-3-717021 Certificate data could not be verified. Locate Reason: reason_string serial number: serial number, subject name: subject name, key length key length bits.
- %PIX|ASA-3-717023 SSL failed to set device certificate for trustpoint trustpoint name. Reason: reason_string.
- %PIX|ASA-3-717027 Certificate chain failed validation. reason_string.

エラーメッセージ、重大度 3

次のメッセージが重大度 3（エラー）で表示されます。

- %PIX|ASA-3-105010: (Primary) Failover message block alloc failed
- %PIX|ASA-3-106010: Deny inbound protocol src interface_name:dest_address/dest_port dst interface_name:source_address/source_port
- %PIX|ASA-3-106011: Deny inbound (No xlate) string
- %PIX|ASA-3-106014: Deny inbound icmp src interface_name: IP_address dst interface_name: IP_address (type dec, code dec)
- %PIX|ASA-3-109010: Auth from inside_address/inside_port to outside_address/outside_port failed (too many pending auths) on interface interface_name.
- %PIX|ASA-3-109013: User must authenticate before using this service
- %PIX|ASA-3-109016: Can't find authorization ACL acl_ID for user 'user'
- %PIX|ASA-3-109018: Downloaded ACL acl_ID is empty
- %PIX|ASA-3-109019: Downloaded ACL acl_ID has parsing error; ACE string
- %PIX|ASA-3-109020: Downloaded ACL has config error; ACE
- %PIX|ASA-3-109023: User from source_address/source_port to dest_address/dest_port on interface outside_interface must authenticate before using this service.
- %PIX|ASA-3-109026: [aaa protocol] Invalid reply digest received; shared server key may be mismatched.
- %PIX|ASA-3-113001: Unable to open AAA session. Session limit [limit] reached.
- %PIX|ASA-3-113018: User: user, Unsupported downloaded ACL Entry: ACL_entry, Action: action
- %PIX|ASA-3-201002: Too many TCP connections on {static|xlate} global_address! econns nconns
- %PIX|ASA-3-201004: Too many UDP connections on {static|xlate} global_address! udp connections limit
- %PIX|ASA-3-201005: FTP data connection failed for IP_address IP_address
- %PIX|ASA-3-201006: RCMD backconnection failed for IP_address/port
- %PIX|ASA-3-201008: The Cisco ASA is disallowing new connections.
- %PIX|ASA-3-201009: TCP connection limit of number for host IP_address on interface_name exceeded
- %PIX|ASA-3-201010: Embryonic connection limit exceeded econns/limit for dir packet from source_address/source_port to dest_address/dest_port on interface interface_name
- %PIX|ASA-3-202001: Out of address translation slots!
- %PIX|ASA-3-202005: Non-embryonic in embryonic list outside_address/outside_port inside_address/inside_port
- %PIX|ASA-3-202011: Connection limit exceeded econns/limit for dir packet from source_address/source_port to dest_address/dest_port on interface interface_name
- %PIX|ASA-3-208005: (function:line_num) clear command return code
- %PIX|ASA-3-210001: LU sw_module_name error = number
- %PIX|ASA-3-210002: LU allocate block (bytes) failed.
- %PIX|ASA-3-210003: Unknown LU Object number
- %PIX|ASA-3-210005: LU allocate connection failed
- %PIX|ASA-3-210006: LU look NAT for IP_address failed
- %PIX|ASA-3-210007: LU allocate xlate failed
- %PIX|ASA-3-210008: LU no xlate for inside_address/inside_port outside_address/outside_port
- %PIX|ASA-3-210010: LU make UDP connection for outside_address:outside_port inside_address:inside_port failed
- %PIX|ASA-3-210020: LU PAT port port reserve failed

- %PIX|ASA-3-210021: LU create static xlate global_address ifc interface_name failed
- %PIX|ASA-3-211001: Memory allocation Error
- %PIX|ASA-3-211003: CPU utilization for number seconds = percent
- %PIX|ASA-3-212001: Unable to open SNMP channel (UDP port port) on interface interface_number, error code = code
- %PIX|ASA-3-212002: Unable to open SNMP trap channel (UDP port port) on interface interface_number, error code = code
- %PIX|ASA-3-212003: Unable to receive an SNMP request on interface interface_number, error code = code, will try again.
- %PIX|ASA-3-212004: Unable to send an SNMP response to IP Address IP_address Port port interface interface_number, error code = code
- %PIX|ASA-3-212005: incoming SNMP request (number bytes) on interface interface_name exceeds data buffer size, discarding this SNMP request.
- %PIX|ASA-3-212006: Dropping SNMP request from source_address/source_port to interface_name:dest_address/dest_port because: reason.
- %PIX|ASA-3-213001: PPTP control daemon socket io string, errno = number.
- %PIX|ASA-3-213002: PPTP tunnel hashtable insert failed, peer = IP_address.
- %PIX|ASA-3-213003: PPP virtual interface interface_number isn't opened.
- %PIX|ASA-3-213004: PPP virtual interface interface_number client ip allocation failed.
- %PIX|ASA-3-302019: H.323 library_name ASN Library failed to initialize, error code number
- %PIX|ASA-3-302302: ACL = deny; no sa created
- %PIX|ASA-3-304003: URL Server IP_address timed out URL url
- %PIX|ASA-3-304006: URL Server IP_address not responding
- %PIX|ASA-3-305005: No translation group found for protocol src interface_name:dest_address/dest_port dst interface_name:source_address/source_port
- %PIX|ASA-3-305006: {outbound static|identity|portmap|regular) translation creation failed for protocol src interface_name:source_address/source_port dst interface_name:dest_address/dest_port
- %PIX|ASA-3-305008: Free unallocated global IP address.
- %PIX|ASA-3-313001: Denied ICMP type=number, code=code from IP_address on interface interface_name
- %PIX|ASA-3-315004: Fail to establish SSH session because RSA host key retrieval failed.
- %PIX|ASA-3-316001: Denied new tunnel to IP_address. VPN peer limit (platform_vpn_peer_limit) exceeded
- %PIX|ASA-3-317001: No memory available for limit_slow
- %PIX|ASA-3-317002: Bad path index of number for IP_address, number max
- %PIX|ASA-3-317003: IP routing table creation failure - reason
- %PIX|ASA-3-317004: IP routing table limit warning
- %PIX|ASA-3-317005: IP routing table limit exceeded - reason, IP_address netmask
- %PIX|ASA-3-318001: Internal error: reason
- %PIX|ASA-3-318002: Flagged as being an ABR without a backbone area
- %PIX|ASA-3-318003: Reached unknown state in neighbor state machine
- %PIX|ASA-3-318004: area string lsid IP_address mask netmask adv IP_address type number
- %PIX|ASA-3-318005: lsid ip_address adv IP_address type number gateway gateway_address metric number network IP_address mask netmask protocol hex attr hex net-metric number
- %PIX|ASA-3-318006: if interface_name if_state number
- %PIX|ASA-3-318007: OSPF is enabled on interface_name during idb initialization

- %PIX|ASA-3-318008: OSPF process number is changing router-id. Reconfigure virtual link neighbors with our new router-id
- %PIX|ASA-3-319001: Acknowledge for arp update for IP address dest_address not received (number).
- %PIX|ASA-3-319002: Acknowledge for route update for IP address dest_address not received (number).
- %PIX|ASA-3-319003: Arp update for IP address address to NPn failed.
- %PIX|ASA-3-319004: Route update for IP address dest_address failed (number).
- %PIX|ASA-3-320001: The subject name of the peer cert is not allowed for connection
- %PIX|ASA-3-322001: Deny MAC address MAC_address, possible spoof attempt on interface interface
- %PIX|ASA-3-322002: ARP inspection check failed for arp {request|response} received from host MAC_address on interface interface. This host is advertising MAC Address MAC_address_1 for IP Address IP_address, which is {statically|dynamically} bound to MAC Address MAC_address_2.
- %PIX|ASA-3-322003: ARP inspection check failed for arp {request|response} received from host MAC_address on interface interface. This host is advertising MAC Address MAC_address_1 for IP Address IP_address, which is not bound to any MAC Address.
- %PIX|ASA-3-324000: Drop GTPv version message msg_type from source_interface:source_address/source_port to dest_interface:dest_address/dest_port Reason: reason
- %PIX|ASA-3-324001: GTPv0 packet parsing error from source_interface:source_address/source_port to dest_interface:dest_address/dest_port, TID: tid_value, Reason: reason
- %PIX|ASA-3-324002: No PDP[MCB] exists to process GTPv0 msg_type from source_interface:source_address/source_port to dest_interface:dest_address/dest_port, TID: tid_value
- %PIX|ASA-3-324003: No matching request to process GTPv version msg_type from source_interface:source_address/source_port to source_interface:dest_address/dest_port
- %PIX|ASA-3-324004: GTP packet with version%d from source_interface:source_address/source_port to dest_interface:dest_address/dest_port is not supported
- %PIX|ASA-3-324005: Unable to create tunnel from source_interface:source_address/source_port to dest_interface:dest_address/dest_port
- %PIX|ASA-3-324006: GSN IP_address tunnel limit tunnel_limit exceeded, PDP Context TID tid failed
- %PIX|ASA-3-324007: Unable to create GTP connection for response from source_interface:source_address/0 to dest_interface:dest_address/dest_port
- %PIX|ASA-3-325001: Router ipv6_address on interface has conflicting ND (Neighbor Discovery) settings
- %PIX|ASA-3-326001: Unexpected error in the timer library: error_message
- %PIX|ASA-3-326002: Error in error_message : error_message
- %PIX|ASA-3-326004: An internal error occurred while processing a packet queue
- %PIX|ASA-3-326005: Mrib notification failed for (IP_address, IP_address)
- %PIX|ASA-3-326006: Entry-creation failed for (IP_address, IP_address)
- %PIX|ASA-3-326007: Entry-update failed for (IP_address, IP_address)
- %PIX|ASA-3-326008: MRIB registration failed
- %PIX|ASA-3-326009: MRIB connection-open failed
- %PIX|ASA-3-326010: MRIB unbind failed
- %PIX|ASA-3-326011: MRIB table deletion failed
- %PIX|ASA-3-326012: Initialization of string functionality failed
- %PIX|ASA-3-326013: Internal error: string in string line %d (%s)
- %PIX|ASA-3-326014: Initialization failed: error_message error_message
- %PIX|ASA-3-326015: Communication error: error_message error_message
- %PIX|ASA-3-326016: Failed to set un-numbered interface for interface_name (string)
- %PIX|ASA-3-326017: Interface Manager error - string in string : string

- %PIX|ASA-3-326019: string in string : string
- %PIX|ASA-3-326020: List error in string : string
- %PIX|ASA-3-326021: Error in string : string
- %PIX|ASA-3-326022: Error in string : string
- %PIX|ASA-3-326023: string - IP_address : string
- %PIX|ASA-3-326024: An internal error occurred while processing a packet queue.
- %PIX|ASA-3-326025: string
- %PIX|ASA-3-326026: Server unexpected error: error_message
- %PIX|ASA-3-326027: Corrupted update: error_message
- %PIX|ASA-3-326028: Asynchronous error: error_message
- %PIXPIX|ASA-3-403501: PPPoE - Bad host-unique in PADO - packet dropped. Intf:interface_name AC:ac_name
- %PIXPIX|ASA-3-403502: PPPoE - Bad host-unique in PADS - dropping packet. Intf:interface_name AC:ac_name
- %PIXPIX|ASA-3-403503: PPPoE:PPP link down:reason
- %PIXPIX|ASA-3-403504: PPPoE:No 'vpdn group' for PPPoE is created
- %PIX|ASA-3-404102: ISAKMP: Exceeded embryonic limit
- %PIX|ASA-3-407002: Embryonic limit nconns/limit through connections exceeded.outside_address/outside_port to global_address (inside_address)/inside_port on interface interface_name
- %PIX|ASA-3-414001: Failed to save logging buffer using file name filename to FTP server ftp_server_address on interface interface_name: [fail_reason]
- %PIX|ASA-3-414002: Failed to save logging buffer to flash:/syslog directory using file name: filename: [fail_reason]
- %PIX|ASA-3-610001: NTP daemon interface interface_name: Packet denied from IP_address
- %PIX|ASA-3-610002: NTP daemon interface interface_name: Authentication failed for packet from IP_address
- %PIX|ASA-3-611313: VPNClient: Backup Server List Error: reason
- %PIX|ASA-3-713008: Key ID in ID payload too big for pre-shared IKE tunnel
- %PIX|ASA-3-713008: Key ID in ID payload too big for pre-shared IKE tunnel
- %PIX|ASA-3-713009: OU in DN in ID payload too big for Certs IKE tunnel
- %PIX|ASA-3-713012: Unknown protocol (protocol). Not adding SA w/spi=SPI value
- %PIX|ASA-3-713014: Unknown Domain of Interpretation (DOI): DOI value
- %PIX|ASA-3-713016: Unknown identification type, Phase 1 or 2, Type ID_Type
- %PIX|ASA-3-713017: Identification type not supported, Phase 1 or 2, Type ID_Type
- %PIX|ASA-3-713018: Unknown ID type during find of group name for certs, Type ID_Type
- %PIX|ASA-3-713020: No Group found by matching OU(s) from ID payload: OU_value
- %PIX|ASA-3-713022: No Group found matching peer_ID or IP_address for Pre-shared key peer IP_address
- %PIX|ASA-3-713032: Received invalid local Proxy Range IP_address - IP_address
- %PIX|ASA-3-713033: Received invalid remote Proxy Range IP_address - IP_address
- %PIX|ASA-3-713042: IKE Initiator unable to find policy: Intf interface_number, Src: source_address, Dst: dest_address
- %PIX|ASA-3-713043: Cookie/peer address IP_address session already in progress
- %PIX|ASA-3-713047: Unsupported Oakley group: Group Diffie-Hellman group
- %PIX|ASA-3-713048: Error processing payload: Payload ID: id

- %PIX|ASA-3-713051: Terminating connection attempt: IPSEC not permitted for group (group_name)
- %PIX|ASA-3-713056: Tunnel rejected: SA (SA_name) not found for group (group_name)!
- %PIX|ASA-3-713059: Tunnel Rejected: User (user) matched with group name, group-lock check failed.
- %PIX|ASA-3-713060: Tunnel Rejected: User (user) not member of group (group_name), group-lock check failed.
- %PIX|ASA-3-713061: Tunnel rejected: Crypto Map Policy not found for Src:source_address, Dst: dest_address!
- %PIX|ASA-3-713062: IKE Peer address same as our interface address IP_address
- %PIX|ASA-3-713063: IKE Peer address not configured for destination IP_address
- %PIX|ASA-3-713065: IKE Remote Peer did not negotiate the following: proposal attribute
- %PIX|ASA-3-713072: Password for user (user) too long, truncating to number characters
- %PIX|ASA-3-713081: Unsupported certificate encoding type encoding_type
- %PIX|ASA-3-713082: Failed to retrieve identity certificate
- %PIX|ASA-3-713083: Invalid certificate handle
- %PIX|ASA-3-713084: Received invalid phase 1 port value (port) in ID payload
- %PIX|ASA-3-713085: Received invalid phase 1 protocol (protocol) in ID payload
- %PIX|ASA-3-713086: Received unexpected Certificate payload Possible invalid Auth Method (Auth method (auth numerical value))
- %PIX|ASA-3-713088: Set Cert filehandle failure: no IPsec SA in group group_name
- %PIX|ASA-3-713098: Aborting: No identity cert specified in IPsec SA (SA_name)!
- %PIX|ASA-3-713102: Phase 1 ID Data length number too long - reject tunnel!
- %PIX|ASA-3-713105: Zero length data in ID payload received during phase 1 or 2 processing
- %PIX|ASA-3-713107: IP_Address request attempt failed!
- %PIX|ASA-3-713109: Unable to process the received peer certificate
- %PIX|ASA-3-713112: Failed to process CONNECTED notify (SPI SPI_value)!
- %PIX|ASA-3-713116: Terminating connection attempt: L2TP-over-IPSEC attempted by group (group_name) but L2TP disabled
- %PIX|ASA-3-713118: Detected invalid Diffie-Hellman group_descriptor group_number, in IKE area
- %PIX|ASA-3-713119: PHASE 1 COMPLETED
- %PIX|ASA-3-713122: Keep-alives configured keepalive_type but peer IP_address support keep-alives (type = keepalive_type)
- %PIX|ASA-3-713123: IKE lost contact with remote peer, deleting connection (keepalive type: keepalive_type)
- %PIX|ASA-3-713124: Received DPD sequence number rcv_sequence_# in DPD Action, description expected seq #
- %PIX|ASA-3-713127: Xauth required but selected Proposal does not support xauth, Check priorities of ike xauth proposals in ike proposal list
- %PIX|ASA-3-713128: Connection attempt to VCIPIP redirected to VCA peer IP_address via load balancing
- %PIX|ASA-3-713129: Received unexpected Transaction Exchange payload type: payload_id
- %PIX|ASA-3-713132: Cannot obtain an IP_address for remote peer
- %PIX|ASA-3-713133: Mismatch: Overriding phase 2 DH Group(DH group DH group_id) with phase 1 group(DH group DH group_number)
- %PIX|ASA-3-713134: Mismatch: P1 Authentication algorithm in the crypto map entry different from negotiated algorithm for the L2L connection

- %PIX|ASA-3-713138: Group group_name not found and BASE GROUP default preshared key not configured
- %PIX|ASA-3-713140: Split Tunneling Policy requires network list but none configured
- %PIX|ASA-3-713141: Client-reported firewall does not match configured firewall: action tunnel. Received -- Vendor: vendor(id), Product product(id), Caps: capability_value. Expected -- Vendor: vendor(id), Product: product(id), Caps: capability_value
- %PIX|ASA-3-713142: Client did not report firewall in use, but there is a configured firewall: action tunnel. Expected -- Vendor: vendor(id), Product product(id), Caps: capability_value
- %PIX|ASA-3-713146: Could not add route for Hardware Client in network extension mode, address: IP_address, mask: netmask
- %PIX|ASA-3-713149: Hardware client security attribute attribute_name was enabled but not requested.
- %PIX|ASA-3-713152: Unable to obtain any rules from filter ACL_tag to send to client for CPP, terminating connection.
- %PIX|ASA-3-713159: TCP Connection to Firewall Server has been lost, restricted tunnels are now allowed full network access
- %PIX|ASA-3-713161: Remote user (session Id - id) network access has been restricted by the Firewall Server
- %PIX|ASA-3-713162: Remote user (session Id - id) has been rejected by the Firewall Server
- %PIX|ASA-3-713163: Remote user (session Id - id) has been terminated by the Firewall Server
- %PIX|ASA-3-713165: Client IKE Auth mode differs from the group's configured Auth mode
- %PIX|ASA-3-713166: Headend security gateway has failed our user authentication attempt - check configured username and password
- %PIX|ASA-3-713167: Remote peer has failed user authentication - check configured username and password
- %PIX|ASA-3-713168: Re-auth enabled, but tunnel must be authenticated interactively!
- %PIX|ASA-3-713174: Hardware Client connection rejected! Network Extension Mode is not allowed for this group!
- %PIX|ASA-3-713182: IKE could not recognize the version of the client! IPSec Fragmentation Policy will be ignored for this connection!
- %PIX|ASA-3-713185: Error: Username too long - connection aborted
- %PIX|ASA-3-713186: Invalid secondary domain name list received from the authentication server. List Received: list_text Character index (value) is illegal
- %PIX|ASA-3-713189: Attempted to assign network or broadcast IP_address, removing (IP_address) from pool.
- %PIX|ASA-3-713193: Received packet with missing payload, Expected payload: payload_id
- %PIX|ASA-3-713194: IKE|IPSec Delete With Reason message: termination_reason
- %PIX|ASA-3-713195: Tunnel rejected: Originate-Only: Cannot accept incoming tunnel yet!
- %PIX|ASA-3-713198: User Authorization failed: user User authorization failed.
- %PIX|ASA-3-713203: IKE Receiver: Error reading from socket.
- %PIX|ASA-3-713205: Could not add static route for client address: IP_address
- %PIX|ASA-3-713206: Tunnel Rejected: Conflicting protocols specified by tunnel-group and group-policy
- %PIX|ASA-3-713208: Cannot create dynamic rule for Backup L2L entry rule rule_id
- %PIX|ASA-3-713209: Cannot delete dynamic rule for Backup L2L entry rule id
- %PIX|ASA-3-713210: Cannot create dynamic map for Backup L2L entry rule_id
- %PIX|ASA-3-713212: Could not add route for L2L peer coming in on a dynamic map. address: IP_address, mask: netmask

- %PIX|ASA-3-713214: Could not delete route for L2L peer that came in on a dynamic map. address: IP_address, mask: netmask
- %PIX|ASA-3-713217: Skipping unrecognized rule: action: action client type: client_type client version: client_version
- %PIX|ASA-3-713218: Tunnel Rejected: Client Type or Version not allowed.
- %PIX|ASA-3-713226: Connection failed with peer IP_address, no trust-point defined in tunnel-group tunnel_group
- %PIX|ASA-3-717001: Querying keypair failed.
- %PIX|ASA-3-717002: Certificate enrollment failed for trustpoint trustpoint_name. Reason: reason_string.
- %PIX|ASA-3-717009: Certificate validation failed. Reason: reason_string.
- %PIX|ASA-3-717010: CRL polling failed for trustpoint trustpoint_name.
- %PIX|ASA-3-717012: Failed to refresh CRL cache entry from the server for trustpoint trustpoint_name at time_of_failure
- %PIX|ASA-3-717015: CRL received from issuer is too large to process (CRL size = crl_size, maximum CRL size = max_crl_size)
- %PIX|ASA-3-717017: Failed to query CA certificate for trustpoint trustpoint_name from enrollment_url
- %PIX|ASA-3-717018: CRL received from issuer has too many entries to process (number of entries = number_of_entries, maximum number allowed = max_allowed)
- %PIX|ASA-3-717019: Failed to insert CRL for trustpoint trustpoint_name. Reason: failure_reason.

警告メッセージ、重大度 4

次のメッセージが重大度 4（警告）で表示されます。

- %PIX|ASA-4-106023: Deny protocol src [interface_name:source_address/source_port] dst interface_name:dest_address/dest_port [type {string}, code {code}] by access_group acl_ID
- %PIX|ASA-4-106027:Failed to determine the security context for the packet:vlan source Vlan#:ethertype src sourceMAC dst destMAC
- %PIX|ASA-4-109017: User at IP_address exceeded auth proxy connection limit (max)
- %PIX|ASA-4-109022: exceeded HTTPS proxy process limit
- %PIX|ASA-4-109027: [aaa protocol] Unable to decipher response message Server = server_IP_address, User = user
- %PIX|ASA-4-109028: aaa bypassed for same-security traffic from ingress_ interface:source_address/source_port to egress_interface:dest_address/dest_port
- %PIX|ASA-4-109030: Autodetect ACL convert wildcard did not convert ACL access_list source | dest netmask netmask.
- %PIX|ASA-4-109031: NT Domain Authentication Failed: rejecting guest login for username.
- %PIX|ASA-4-209003: Fragment database limit of number exceeded: src = source_address, dest = dest_address, proto = protocol, id = number
- %PIX|ASA-4-209004: Invalid IP fragment, size = bytes exceeds maximum size = bytes: src = source_address, dest = dest_address, proto = protocol, id = number
- %PIX|ASA-4-209005: Discard IP fragment set with more than number elements: src = Too many elements are in a fragment set.
- %PIX|ASA-4-308002: static global_address inside_address netmask netmask overlapped with global_address inside_address
- %PIX|ASA-4-313003: Invalid destination for ICMP error
- %PIX|ASA-4-313004:Denied ICMP type=icmp_type, from source_address on interface interface_name to dest_address:no matching session
- %PIX|ASA-4-325002: Duplicate address ipv6_address/MAC_address on interface
- %PIX|ASA-4-4000nn: IPS:number string from IP_address to IP_address on interface interface_name
- %PIX|ASA-4-401001: Shuns cleared
- %PIX|ASA-4-401002: Shun added: IP_address IP_address port port
- %PIX|ASA-4-401003: Shun deleted: IP_address
- %PIX|ASA-4-401004: Shunned packet: IP_address ==> IP_address on interface interface_name
- %PIX|ASA-4-401005: Shun add failed: unable to allocate resources for IP_address IP_address port port
- %PIX|ASA-4-402101: decaps: rec'd IPSEC packet has invalid spi for destaddr=dest_address, prot=protocol, spi=number
- %PIX|ASA-4-402102: decapsulate: packet missing {AH|ESP}, destadr=dest_address, actual prot=protocol
- %PIX|ASA-4-402103: identity doesn't match negotiated identity (ip) dest_address= dest_address, src_addr= source_address, prot= protocol, (ident) local=inside_address, remote=remote_address, local_proxy=IP_address/IP_address/port/port, remote_proxy=IP_address/IP_address/port/port
- %PIX|ASA-4-402106: Rec'd packet not an IPSEC packet (ip) dest_address= dest_address, src_addr= source_address, prot= protocol
- %PIX|ASA-4-402114: IPSEC: Received an protocol packet (SPI=spi, sequence number= seq_num) from remote_IP to local_IP with an invalid SPI.
- %PIX|ASA-4-402115: IPSEC: Received a packet from remote_IP to local_IP containing act_prot data instead of exp_prot data.

- %PIX|ASA-4-402116: IPSEC: Received an protocol packet (SPI=spi, sequence number= seq_num) from remote_IP (username) to local_IP . The decapsulated inner packet doesn't match the negotiated policy in the SA. The packet specifies its destination as pkt_daddr , its source as pkt_saddr , and its protocol as pkt_prot . The SA specifies its local proxy as id_daddr /id_dmask /id_dprot /id_dport and its remote proxy as id_saddr /id_smask /id_sprot /id_sport .
- %PIX|ASA-4-402117: IPSEC: Received a non-IPSec (protocol) packet from remote_IP to local_IP.
- %PIX|ASA-4-402118: IPSEC: Received an protocol packet (SPI=spi, sequence number seq_num) from remote_IP (username) to local_IP containing an illegal IP fragment of length frag_len with offset frag_offset.
- %PIX|ASA-4-402119: IPSEC: Received an protocol packet (SPI=spi, sequence number= seq_num) from remote_IP (username) to local_IP that failed anti-replay checking.
- %PIX|ASA-4-402120: IPSEC: Received an protocol packet (SPI=spi, sequence number= seq_num) from remote_IP (username) to local_IP that failed authentication.
- %PIX|ASA-4-402121: IPSEC: Received an protocol packet (SPI=spi, sequence number= seq_num) from remote_IP (username) to local_IP that was dropped by IPSec (drop_reason).
- %PIX|ASA-4-402122: IPSEC: Received a cleartext packet from src_addr to dest_addr that was to be encapsulated in IPSec that was dropped by IPSec (drop_reason).
- %PIX|ASA-4-402123: CRYPTO: The accel_type hardware accelerator encountered an error (code= error_string) while executing crypto command command .
- %PIX|ASA-4-403101: PPTP session state not established, but received an XGRE packet, tunnel_id=number, session_id=number
- %PIXPIX|ASA-4-403102: PPP virtual interface interface_name rcvd pkt with invalid protocol: protocol, reason: reason.
- %PIXPIX|ASA-4-403103: PPP virtual interface max connections reached.
- %PIXPIX|ASA-4-403104: PPP virtual interface interface_name requires mschap for MPPE.
- %PIXPIX|ASA-4-403106: PPP virtual interface interface_name requires RADIUS for MPPE.
- %PIXPIX|ASA-4-403107: PPP virtual interface interface_name missing aaa server group info
- %PIXPIX|ASA-4-403108: PPP virtual interface interface_name missing client ip address option
- %PIXPIX|ASA-4-403109: Rec'd packet not an PPTP packet. (ip) dest_address= dest_address, src_addr= source_address, data: string.
- %PIXPIX|ASA-4-403110: PPP virtual interface interface_name, user: user missing MPPE key from aaa server.
- %PIXPIX|ASA-4-403505: PPPoE:PPP - Unable to set default route to IP_address at interface_name
- %PIXPIX|ASA-4-403506: PPPoE:failed to assign PPP IP_address netmask netmask at interface_name
- %PIX|ASA-4-404101: ISAKMP: Failed to allocate address for client from pool string
- %PIX|ASA-4-405001: Received ARP {request | response} collision from IP_address/MAC_address on interface interface_name
- %PIX|ASA-4-405002: Received mac mismatch collision from IP_address/MAC_address for authenticated host
- %PIX|ASA-4-405101: Unable to Pre-allocate H225 Call Signalling Connection for foreign_address outside_address[/outside_port] to local_address inside_address[/inside_port]
- %PIX|ASA-4-405102: Unable to Pre-allocate H245 Connection for foreign_address outside_address[/outside_port] to local_address inside_address[/inside_port]
- %PIX|ASA-4-405103: H225 message from source_address/source_port to dest_address/dest_port contains bad protocol discriminator hex
- %PIX|ASA-4-405104: H225 message received from outside_address/outside_port to inside_address/inside_port before SETUP
- %PIX|ASA-4-405105: H323 RAS message AdmissionConfirm received from source_address/source_port to dest_address/dest_port without an AdmissionRequest

- %PIX|ASA-4-405201: ILS ILS_message_type from inside_interface:source_IP_address to outside_interface:/destination_IP_address has wrong embedded address embedded_IP_address
- %PIX|ASA-4-406001: FTP port command low port: IP_address/port to IP_address on interface interface_name
- %PIX|ASA-4-406002: FTP port command different address: IP_address(IP_address) to IP_address on interface interface_name
- %PIX|ASA-4-407001: Deny traffic for local-host interface_name:inside_address, license limit of number exceeded
- %PIX|ASA-4-407003: Established limit for RPC services exceeded number
- %PIX|ASA-4-408001: IP route counter negative - reason, IP_address Attempt: number
- %PIX|ASA-4-408002: ospf process id route type update address1 netmask1 [distance1/metric1] via source IP:interface1 address2 netmask2 [distance2/metric2] interface2
- %PIX|ASA-4-409001: Database scanner: external LSA IP_address netmask is lost, reinstalls
- %PIX|ASA-4-409002: db_free: external LSA IP_address netmask
- %PIX|ASA-4-409003: Received invalid packet: reason from IP_address, interface_name
- %PIX|ASA-4-409004: Received reason from unknown neighbor IP_address
- %PIX|ASA-4-409005: Invalid length number in OSPF packet from IP_address (ID IP_address), interface_name
- %PIX|ASA-4-409006: Invalid lsa: reason Type number, LSID IP_address from IP_address, IP_address, interface_name
- %PIX|ASA-4-409007: Found LSA with the same host bit set but using different mask LSA ID IP_address netmask New: Destination IP_address netmask
- %PIX|ASA-4-409008: Found generating default LSA with non-zero mask LSA type : number Mask: netmask metric : number area : string
- %PIX|ASA-4-409009: OSPF process number cannot start. There must be at least one up IP interface, for OSPF to use as router ID
- %PIX|ASA-4-409010: Virtual link information found in non-backbone area: string
- %PIX|ASA-4-409011: OSPF detected duplicate router-id IP_address from IP_address on interface interface_name
- %PIX|ASA-4-409012: Detected router with duplicate router ID IP_address in area string
- %PIX|ASA-4-409013: Detected router with duplicate router ID IP_address in Type-4 LSA advertised by IP_address
- %PIX|ASA-4-409023: Attempting AAA Fallback method method_name for request_type request for user user :Auth-server group server_tag unreachable
- %PIX|ASA-4-410001: UDP DNS request from source_interface:source_address/source_port to dest_interface:dest_address/dest_port; (label length | domain-name length) 52 bytes exceeds remaining packet length of 44 bytes.
- %PIX|ASA-4-411001:Line protocol on interface interface_name changed state to up
- %PIX|ASA-4-411002:Line protocol on interface interface_name changed state to down
- %PIX|ASA-4-411003: Configuration status on interface interface_name changed state to downup
- %PIX|ASA-4-411004: Configuration status on interface interface_name changed state to up
- %PIX|ASA-4-412001:MAC MAC_address moved from interface_1 to interface_2
- %PIX|ASA-4-412002:Detected bridge table full while inserting MAC MAC_address on interface interface. Number of entries = num
- %PIX|ASA-4-415012:internal_sig_id HTTP Deobfuscation signature detected - action HTTP deobfuscation detected IPS evasion technique from source_address to source_address
- %PIX|ASA-4-415014:internal_sig_id Maximum of 10 unanswered HTTP requests exceeded from source_address to dest_address

- %PIX|ASA-4-416001: Dropped UDP SNMP packet from source_interface :source_IP/source_port to dest_interface:dest_address/dest_port; version (prot_version) is not allowed through the firewall
- %PIX|ASA-4-417001: Unexpected event received: number
- %PIX|ASA-4-417004: Filter violation error: conn number (string:string) in string
- %PIX|ASA-4-417006: No memory for string) in string. Handling: string
- %PIX|ASA-4-418001: Through-the-device packet to/from management-only network is denied: protocol_string from interface_name IP_address (port) to interface_name IP_address (port)
- %PIX|ASA-4-419001: Dropping TCP packet from src_ifc:src_IP/src_port to dest_ifc:dest_IP/dest_port, reason: MSS exceeded, MSS size, data size
- %ASA-3-420001 : IPS card not up and fail-close mode used, dropping ICMP packet ifc_in:SIP to ifc_out:DIP (typeICMP_TYPE, code ICMP_CODE)"
- %ASA-4-420002 : IPS requested to drop ICMP packets ifc_in:SIP to ifc_out:DIP (typeICMP_TYPE, code ICMP_CODE)"
- %ASA-4-420003 : IPS requested to reset TCP connection from ifc_in:SIP/SPORT to ifc_out:DIP/DPORT"
- %PIX|ASA-4-500004: Invalid transport field for protocol=protocol, from source_address/source_port to dest_address/dest_port
- %PIX|ASA-4-612002: Auto Update failed:filename, version:number, reason:reason
- %PIX|ASA-4-612003:Auto Update failed to contact:url, reason:reason
- %PIX|ASA-4-620002: Unsupported CTIQBE version: hex: from interface_name:IP_address/port to interface_name:IP_address/port
- %PIX|ASA-4-713154: DNS lookup for peer_description Server [server_name] failed!
- %PIX|ASA-4-713157: Timed out on initial contact to server [server_name or IP_address] Tunnel could not be established.
- %PIX|ASA-4-713903:Descriptive_event_string.
- %PIX|ASA-4-717026 Name lookup failed for hostname hostname during PKI operation.
- %PIX|ASA-4-717031 Failed to find a suitable trustpoint for the issuer: issuer Reason: reason_string
- %ASA-4-720001: (VPN-unit) Failed to initialize with Chunk Manager.
- %ASA-4-720007: (VPN-unit) Failed to allocate chunk from Chunk Manager.
- %ASA-4-720008: (VPN-unit) Failed to register to High Availability Framework.
- %ASA-4-720009: (VPN-unit) Failed to create version control block.
- %ASA-4-720011: (VPN-unit) Failed to allocate memory
- %ASA-4-720013: (VPN-unit) Failed to insert certificate in trust point trustpoint_name
- %ASA-4-720022: (VPN-unit) Cannot find trust point trustpoint
- %ASA-4-720033: (VPN-unit) Failed to queue add to message queue.
- %ASA-4-720038: (VPN-unit) Corrupted message from active unit.
- %ASA-4-720043: (VPN-unit) Failed to send type message id to standby unit
- %ASA-4-720044: (VPN-unit) Failed to receive message from active unit
- %ASA-4-720047: (VPN-unit) Failed to sync SDI node secret file for server IP_address on the standby unit.
- %ASA-4-720051: (VPN-unit) Failed to add new SDI node secret file for server id on the standby unit.
- %ASA-4-720052: (VPN-unit) Failed to delete SDI node secret file for server id on the standby unit.
- %ASA-4-720053: (VPN-unit) Failed to add cTCP IKE rule during bulk sync, peer=IP_address, port=port
- %ASA-4-720054: (VPN-unit) Failed to add new cTCP record, peer=IP_address, port=port.
- %ASA-4-720055: (VPN-unit) VPN Stateful failover can only be run in single/non-transparent mode.

- %ASA-4-720064: (VPN-unit) Failed to update cTCP database record for peer=IP_address, port=port during bulk sync.
- %ASA-4-720065: (VPN-unit) Failed to add new cTCP IKE rule, peer=peer, port=port.
- %ASA-4-720066: (VPN-unit) Failed to activate IKE database.
- %ASA-4-720067: (VPN-unit) Failed to deactivate IKE database.
- %ASA-4-720068: (VPN-unit) Failed to parse peer message.
- %ASA-4-720069: (VPN-unit) Failed to activate cTCP database.
- %ASA-4-720070: (VPN-unit) Failed to deactivate cTCP database.
- %ASA-4-720072: (VPN-unit) Cannot find trust point tp
- %ASA4-720073: (VPN-unit) Fail to insert certificate in trust point trustpoint on the standby unit.

通知メッセージ、重大度 5

次のメッセージが重大度 5（通知）で表示されます。

- %PIX|ASA-5-109012: Authen Session End: user 'user', sid number, elapsed number seconds
- %PIX|ASA-5-109029: Parsing downloaded ACL: string
- %PIX|ASA-5-111002: Begin configuration: IP_address reading from device
- %PIX|ASA-5-111003: IP_address Erase configuration
- %PIX|ASA-5-111004: IP_address end configuration: {FAILED|OK}
- %PIX|ASA-5-111005: IP_address end configuration: OK
- %PIX|ASA-5-111007: Begin configuration: IP_address reading from device.
- %PIX|ASA-5-111008: User user executed the command string
- %PIX|ASA-5-199001: Reload command executed from telnet (remote IP_address).
- %PIX|ASA-5-199006: Orderly reload started at when by whom. Reload reason: reason
- %PIX|ASA-5-1999007: IP detected an attached application using port port while removing context
- %PIX|ASA-5-1999008: Protocol detected an attached application using local port local_port and destination port dest_port
- %PIX|ASA-5-303004: FTP cmd_string command unsupported - failed strict inspection, terminating connection from source_interface:source_address/source_port to dest_interface:dest_address/dest_interface
- %PIX|ASA-5-304001: user source_address Accessed {JAVA URL|URL} dest_address: url.
- %PIX|ASA-5-304002: Access denied URL chars SRC IP_address DEST IP_address: chars
- %PIX|ASA-5-321001: Resource var1 limit of var2 reached.
- %PIX|ASA-5-321002: Resource var1 rate limit of var2 reached.
- %PIX|ASA-5-415001: internal_sig_id HTTP Tunnel detected - action tunnel_type from source_address to dest_address
- %PIX|ASA-5-415002: internal_sig_id HTTP Instant Messenger detected - action instant_messenger_type from source_address to dest_address
- %PIX|ASA-5-415003: internal_sig_id HTTP Peer-to-Peer detected - action peer_to_peer_type from source_address to dest_address
- %PIX|ASA-5-415005: Internal_Sig_Id Content type does not match specified type - Action Content Verification Failed from source_address to Dst_IP_Address
- %PIX|ASA-5-415007: internal_sig_id HTTP Extension method illegal - action 'method_name' from source_address to dest_address
- %PIX|ASA-5-415008: internal_sig_id HTTP RFC method illegal - action 'method_name' from source_address to dest_address
- %PIX|ASA-5-415010: internal_sig_id HTTP protocol violation detected - action HTTP Protocol not detected from source_address to dest_address
- %PIX|ASA-5-415013: internal_sig_id HTTP Transfer encoding violation detected - action Xfer_encode Transfer encoding not allowed from source_address to dest_address
- %PIX|ASA-5-500001: ActiveX content modified src IP_address dest IP_address on interface interface_name.
- %PIX|ASA-5-500002: Java content modified src IP_address dest IP_address on interface interface_name.
- %PIX|ASA-5-500003: Bad TCP hdr length (hdrlen=bytes, pktlen=bytes) from source_address/source_port to dest_address/dest_port, flags: tcp_flags, on interface interface_name
- %ASA-5-505001: Module in slot slotnum is shutting down. Please wait...
- %ASA-5-505002: Module in slot slotnum is reloading. Please wait...
- %ASA-5-505003: Module in slot slotnum is resetting. Please wait...

- %ASA-5-505004: Module in slot slotnum shutdown is complete.
- %ASA-5-505005: Module in slot slotnum is initializing control communication. Please wait...
- %ASA-5-505006: Module in slot slotnum is Up.
- %ASA-5-505007: Module in slot slotnum is recovering. Please wait...
- %ASA-5-505008: Module in slot slotnum software is being updated to vnewver (currently vver)
- %ASA-5-505009: Module in slot slotnum software was updated to vnewver (previously vver)
- %ASA-5-506001: event_source_string event_string
- %PIX|ASA-5-501101: User transitioning priv level
- %PIX|ASA-5-502101: New user added to local dbase: Uname: user Priv: privilege_level Encpass: string
- %PIX|ASA-5-502102: User deleted from local dbase: Uname: user Priv: privilege_level Encpass: string
- %PIXPIX|ASA-5-502103: User priv level changed: Uname: user From: privilege_level To: privilege_level
- %PIXPIX|ASA-5-502111: New group policy added: name: policy_name Type: policy_type
- %PIXPIX|ASA-5-502112: Group policy deleted: name: policy_name Type: policy_type
- %PIXPIX|ASA-5-503001: Process number, Nbr IP_address on interface_name from string to string, reason
- %PIXPIX|ASA-5-504001: Security context context_name was added to the system
- %PIXPIX|ASA-5-504002: Security context context_name was removed from the system
- %PIXPIX|ASA-5-507001: Terminating TCP-Proxy connection from interface_inside:source_address/source_port to interface_outside:dest_address/dest_port - reassembly limit of limit bytes exceeded
- %PIX|ASA-5-611103: User logged out: Uname: user
- %PIX|ASA-5-611104: Serial console idle timeout exceeded
- %PIX|ASA-5-612001: Auto Update succeeded:filename, version:number
- %PIX|ASA-5-713006: Failed to obtain state for message Id message_number, Peer Address: IP_address
- %PIX|ASA-5-713010: IKE area: failed to find centry for message Id message_number
- %PIX|ASA-5-713041: IKE Initiator: new or rekey Phase 1 or 2, Intf interface_number, IKE Peer IP_address local Proxy Address IP_address, remote Proxy Address IP_address, Crypto map (crypto map tag)
- %PIX|ASA-5-713049: Security negotiation complete for tunnel_type type (group_name) Initiator/Responder, Inbound SPI = SPI, Outbound SPI = SPI
- %PIX|ASA-5-713050: Connection terminated for peer IP_address. Reason: termination reason Remote Proxy IP_address, Local Proxy IP_address
- %PIX|ASA-5-713068: Received non-routine Notify message: notify_type (notify_value)
- %PIX|ASA-5-713073: Responder forcing change of Phase 1/Phase 2 rekeying duration from larger_value to smaller_value seconds
- %PIX|ASA-5-713074: Responder forcing change of IPSec rekeying duration from larger_value to smaller_value Kbs
- %PIX|ASA-5-713075: Overriding Initiator's IPSec rekeying duration from larger_value to smaller_value seconds
- %PIX|ASA-5-713076: Overriding Initiator's IPSec rekeying duration from larger_value to smaller_value Kbs
- %PIX|ASA-5-713092: Failure during phase 1 rekeying attempt due to collision
- %PIX|ASA-5-713115: Client rejected NAT enabled IPSec request, falling back to standard IPSec
- %PIX|ASA-5-713120: PHASE 2 COMPLETED (msgid=msg_id)
- %PIX|ASA-5-713130: Received unsupported transaction mode attribute: attribute id

- %PIX|ASA-5-713131: Received unknown transaction mode attribute: attribute_id
- %PIX|ASA-5-713135: message received, redirecting tunnel to IP_address.
- %PIX|ASA-5-713136: IKE session establishment timed out [IKE_state_name], aborting!
- %PIX|ASA-5-713137: Reaper overriding refCnt [ref_count] and tunnelCnt [tunnel_count] -- deleting SA!
- %PIX|ASA-5-713139: group_name not found, using BASE GROUP default preshared key
- %PIX|ASA-5-713144: Ignoring received malformed firewall record; reason - error_reason TLV type attribute_value correction
- %PIX|ASA-5-713148: Terminating tunnel to Hardware Client in network extension mode, unable to delete static route for address: IP_address, mask: netmask
- %PIX|ASA-5-713155: DNS lookup for Primary VPN Server [server_name] successfully resolved after a previous failure. Resetting any Backup Server init.
- %PIX|ASA-5-713156: Initializing Backup Server [server_name or IP_address]
- %PIX|ASA-5-713158: Client rejected NAT enabled IPSec Over UDP request, falling back to IPSec Over TCP
- %PIX|ASA-5-713178: IKE Initiator received a packet from its peer without a Responder cookie
- %PIX|ASA-5-713179: IKE AM Initiator received a packet from its peer without a payload_type payload
- %PIX|ASA-5-713196: Remote L2L Peer IP_address initiated a tunnel with same outer and inner addresses.Peer could be Originate Only - Possible misconfiguration!
- %PIX|ASA-5-713197: The configured Confidence Interval of number seconds is invalid for this tunnel_type connection. Enforcing the second default.
- %PIX|ASA-5-713199: Reaper corrected an SA that has not decremented the concurrent IKE negotiations counter (counter_value)!
- %PIX|ASA-5-713216: Rule: action Client type : version Client: type version is/is not allowed
- %PIX|ASA5-713229: Auto Update - Notification to client client_ip of update string: message_string.%PIX|ASA-5-109029: Parsing downloaded ACL: string
- %PIX|ASA-5-713237: ACL update (access_list) received during re-key re-authentication will not be applied to the tunnel.
- %PIX|ASA-5-713904:Descriptive_event_string.
- %PIX|ASA-5-717013: Removing a cached CRL to accommodate an incoming CRL. Issuer: issuer
- %PIX|ASA-5-717014: Unable to cache a CRL received from CDP due to size limitations (CRL size = size, available cache space = space)
- %PIX|ASA-5-718002: Create peer IP_address failure, already at maximum of number_of_peers
- %PIX|ASA-5-718005: Fail to send to IP_address, port port
- %PIX|ASA-5-718006: Invalid load balancing state transition [cur=state_number][event=event_number]
- %PIX|ASA-5-718007: Socket open failure failure_code
- %PIX|ASA-5-718008: Socket bind failure failure_code
- %PIX|ASA-5-718009: Send HELLO response failure to IP_address
- %PIX|ASA-5-718010: Sent HELLO response to IP_address
- %PIX|ASA-5-718011: Send HELLO request failure to IP_address
- %PIX|ASA-5-718012: Sent HELLO request to IP_address
- %PIX|ASA-5-718014: Master peer IP_address is not answering HELLO
- %PIX|ASA-5-718015: Received HELLO request from IP_address
- %PIX|ASA-5-718016: Received HELLO response from IP_address
- %PIX|ASA-5-718024: Send CFG UPDATE failure to IP_address
- %PIX|ASA-5-718028: Send OOS indicator failure to IP_address
- %PIX|ASA-5-718048: Create of secure tunnel failure for peer IP_address

- %PIX|ASA-5-718050: Delete of secure tunnel failure for peer IP_address
- %PIX|ASA-5-718052: Received GRAT-ARP from duplicate master MAC_address
- %PIX|ASA-5-718053: Detected duplicate master, mastership stolen MAC_address
- %PIX|ASA-5-718054: Detected duplicate master MAC_address and going to SLAVE
- %PIX|ASA-5-718055: Detected duplicate master MAC_address and staying MASTER
- %PIX|ASA-7-718056: Deleted Master peer, IP IP_address
- %PIX|ASA-5-718057: Queue send failure from ISR, msg type failure_code
- %PIX|ASA-5-718060: Inbound socket select fail: context=context_ID.
- %PIX|ASA-5-718061: Inbound socket read fail: context=context_ID.
- %PIX|ASA-5-718062: Inbound thread is awake (context=context_ID).
- %PIX|ASA-5-718063: Interface interface_name is down.
- %PIX|ASA-5-718064: Admin. interface interface_name is down.
- %PIX|ASA-5-718065: Cannot continue to run (public=up/down, private=up/down, enable=LB_state, master=IP_address, session=Enable/Disable).
- %PIX|ASA-5-718066: Cannot add secondary address to interface interface_name, ip IP_address.
- %PIX|ASA-5-718067: Cannot delete secondary address to interface interface_name, ip IP_address.
- %PIX|ASA-5-718068: Start VPN Load Balancing in context context_ID.
- %PIX|ASA-5-718069: Stop VPN Load Balancing in context context_ID.
- %PIX|ASA-5-718070: Reset VPN Load Balancing in context context_ID.
- %PIX|ASA-5-718071: Terminate VPN Load Balancing in context context_ID.
- %PIX|ASA-5-718072: Becoming master of Load Balancing in context context_ID.
- %PIX|ASA-5-718073: Becoming slave of Load Balancing in context context_ID.
- %PIX|ASA-5-718074: Fail to create access list for peer context_ID.
- %PIX|ASA-5-718075: Peer IP_address access list not set.
- %PIX|ASA-5-718076: Fail to create tunnel group for peer IP_address.
- %PIX|ASA-5-718077: Fail to delete tunnel group for peer IP_address.
- %PIX|ASA-5-718078: Fail to create crypto map for peer IP_address.
- %PIX|ASA-5-718079: Fail to delete crypto map for peer IP_address.
- %PIX|ASA-5-718080: Fail to create crypto policy for peer IP_address.
- %PIX|ASA-5-718081: Fail to delete crypto policy for peer IP_address.
- %PIX|ASA-5-718084: Public/cluster IP not on the same subnet: public IP_address, mask netmask, cluster IP_address
- %PIX|ASA-5-718085: Interface interface_name has no IP address defined.
- %PIX|ASA-5-718086: Fail to install LB NP rules: type rule_type, dst interface_name, port port.
- %PIX|ASA-5-718087: Fail to delete LB NP rules: type rule_type, rule rule_ID.
- %ASA-5-719014: Email Proxy is changing listen port from old_port to new_port for mail protocol protocol.
- %ASA-5-720016: (VPN-unit) Failed to initialize default timer #index.
- %ASA-5-720017: (VPN-unit) Failed to update LB runtime data
- %ASA-5-720018: (VPN-unit) Failed to get a buffer from the underlying core high availability subsystem. Error code code.
- %ASA-5-720019: (VPN-unit) Failed to update cTCP statistics.
- %ASA-5-720020: (VPN-unit) Failed to send type timer message.
- %ASA-5-720021: (VPN-unit) HA non-block send failed for peer msg message_number. HA error code.

- %PIX|ASA-5-718031: Received OOS obituary for IP_address
- %PIX|ASA-5-718032: Received OOS indicator from IP_address
- %PIX|ASA-5-718033: Send TOPOLOGY indicator failure to IP_address
- %PIX|ASA-5-718042: Unable to ARP for IP_address
- %PIX|ASA-5-718043: Updating/removing duplicate peer entry IP_address
- %PIX|ASA-5-718044: Deleted peer IP_address
- %PIX|ASA-5-718045: Created peer IP_address
- %ASA-5-720035: (VPN-unit) Fail to look up CTCP flow handle
- %ASA-5-720036: (VPN-unit) Failed to process state update message from the active peer.
- %ASA-5-720071: (VPN-unit) Failed to update cTCP dynamic data.

情報メッセージ、重大度 6

次のメッセージが重大度 6（情報）で表示されます。

- %PIX|ASA-6-106012: Deny IP from IP_address to IP_address, IP options hex.
- %PIX|ASA-6-106015: Deny TCP (no connection) from IP_address/port to IP_address/port flags tcp_flags on interface interface_name.
- %PIX|ASA-6-106025: Failed to determine the security context for the packet:sourceVlan:source_address dest_address source_port dest_port protocol
- %PIX|ASA-6-106026: Failed to determine the security context for the packet:sourceVlan:source_address dest_address source_port dest_port protocol
- %PIX|ASA-6-109001: Auth start for user user from inside_address/inside_port to outside_address/outside_port
- %PIX|ASA-6-109002: Auth from inside_address/inside_port to outside_address/outside_port failed (server IP_address failed) on interface interface_name.
- %PIX|ASA-6-109003: Auth from inside_address to outside_address/outside_port failed (all servers failed) on interface interface_name.
- %PIX|ASA-6-109005: Authentication succeeded for user user from inside_address/inside_port to outside_address/outside_port on interface interface_name.
- %PIX|ASA-6-109006: Authentication failed for user user from inside_address/inside_port to outside_address/outside_port on interface interface_name.
- %PIX|ASA-6-109007: Authorization permitted for user user from inside_address/inside_port to outside_address/outside_port on interface interface_name.
- %PIX|ASA-6-109008: Authorization denied for user user from outside_address/outside_port to inside_address/ inside_port on interface interface_name.
- %PIX|ASA-6-109024: Authorization denied from source_address/source_port to dest_address/dest_port (not authenticated) on interface interface_name using protocol
- %PIX|ASA-6-109025: Authorization denied (acl=acl_ID) for user 'user' from source_address/source_port to dest_address/dest_port on interface interface_name using protocol
- %PIX|ASA-6-110001: No route to dest_address from source_address
- %PIX|ASA-6-113003: AAA group policy for user user is being set to policy_name.
- %PIX|ASA-6-113004: AAA user aaa_type Successful: server = server_IP_address, User = user
- %PIX|ASA-6-113005: AAA user authentication Rejected: reason = string: server = server_IP_address, User = user
- %PIX|ASA-6-113006: User user locked out on exceeding number successive failed authentication attempts
- %PIX|ASA-6-113007: User user unlocked by administrator
- %PIX|ASA-6-113008: AAA transaction status ACCEPT: user = user
- %PIX|ASA-6-113009: AAA retrieved default group policy policy for user user
- %PIX|ASA-6-113010: AAA challenge received for user user from server server_IP_address
- %PIX|ASA-6-113011: AAA retrieved user specific group policy policy for user user
- %PIX|ASA-6-113012: AAA user authentication Successful: local database : user = user
- %PIX|ASA-6-113013: AAA unable to complete the request Error: reason = reason: user = user
- %PIX|ASA-6-113014: AAA authentication server not accessible: server = server_IP_address: user = user
- %PIX|ASA-6-113015: AAA user authentication Rejected: reason = reason : local database: user = user
- %PIX|ASA-6-113016: AAA credentials rejected: reason = reason: server = server_IP_address: user = user
- %PIX|ASA-6-113017: AAA credentials rejected: reason = reason: local database: user = user\
- %ASA-6-114004: 4GE SSM I/O Initialization start.

- %ASA-6-114005: 4GE SSM I/O Initialization end.
- %PIX|ASA-6-199002: startup completed. Beginning operation.
- %PIX|ASA-6-199003: Reducing link MTU dec.
- %PIX|ASA-6-199005: Startup begin
- %PIX|ASA-6-210022: LU missed number updates
- %PIX|ASA-6-302003: Built H245 connection for foreign_address outside_address/outside_port local_address inside_address/inside_port
- %PIX|ASA-6-302004: Pre-allocate H323 UDP backconnection for foreign_address outside_address/outside_port to local_address inside_address/inside_port
- %PIX|ASA-6-302009: Rebuilt TCP connection number for foreign_address outside_address/outside_port global_address global_address/global_port local_address inside_address/inside_port
- %PIX|ASA-6-302010: connections in use, connections most used
- %PIX|ASA-6-302012: Pre-allocate H225 Call Signalling Connection for faddr IP_address/port to laddr IP_address
- %PIX|ASA-6-302013: Built {inbound|outbound} TCP connection_id for interface:real-address/real-port (mapped-address/mapped-port) to interface:real-address/real-port (mapped-address/mapped-port) [(user)]
- %PIX|ASA-6-302014: Teardown TCP connection id for interface:real-address/real-port to interface:real-address/real-port duration hh:mm:ss bytes bytes [reason] [(user)]
- %PIX|ASA-6-302015: Built {inbound|outbound} UDP connection number for interface_name:real_address/real_port (mapped_address/mapped_port) to interface_name:real_address/real_port (mapped_address/mapped_port) [(user)]
- %PIX|ASA-6-302016: Teardown UDP connection number for interface:real-address/real-port to interface:real-address/real-port duration hh:mm:ss bytes bytes [(user)]
- %PIX|ASA-6-302017: Built {inbound|outbound} GRE connection id from interface:real_address (translated_address) to interface:real_address/real_cid (translated_address/translated_cid)[(user)]
- %PIX|ASA-6-302018: Teardown GRE connection id from interface:real_address (translated_address) to interface:real_address/real_cid (translated_address/translated_cid) duration hh:mm:ss bytes bytes [(user)]
- %PIX|ASA-6-302020: Built {in | out}bound ICMP connection for faddr {faddr | icmp_seq_num} gaddr {gaddr | cmp_type} laddr laddr
- %PIX|ASA-6-302021: Teardown ICMP connection for faddr {faddr | icmp_seq_num} gaddr {gaddr | cmp_type} laddr laddr
- %PIX|ASA-6-303002: source_address {Stored|Retrieved} dest_address: mapped_address
- %PIX|ASA-6-303003: FTP cmd_name command denied - failed strict inspection, terminating connection from source_interface:source_address/source_port to dest_interface:dest_address/dest_port
- %PIX|ASA-6-304004: URL Server IP_address request failed URL url
- %PIX|ASA-6-305007: addrpool_free(): Orphan IP IP_address on interface interface_number
- %PIX|ASA-6-305009: Built {dynamic|static} translation from interface_name [(acl-name)]:real_address to interface_name:mapped_address
- %PIX|ASA-6-305010: Teardown {dynamic|static} translation from interface_name:real_address to interface_name:mapped_address duration time
- %PIX|ASA-6-305011: Built {dynamic|static} {TCP|UDP|ICMP} translation from interface_name:real_address/real_port to interface_name:mapped_address/mapped_port
- %PIX|ASA-6-305012: Teardown {dynamic|static} {TCP|UDP|ICMP} translation from interface_name [(acl-name)]:real_address/{real_port|real_ICMP_ID} to interface_name:mapped_address/{mapped_port|mapped_ICMP_ID} duration time
- %PIX|ASA-6-308001: console enable password incorrect for number tries (from IP_address)
- %PIX|ASA-6-311001: LU loading standby start
- %PIX|ASA-6-311002: LU loading standby end

- %PIX|ASA-6-311003: LU rcv thread up
- %PIX|ASA-6-311004: LU xmit thread up
- %PIX|ASA-6-312001: RIP hdr failed from IP_address: cmd=string, version=number domain=string on interface interface_name
- %PIX|ASA-6-314001: Pre-allocate RTSP UDP backconnection for foreign_address outside_address/outside_port to local_address inside_address/inside_port
- %PIX|ASA-6-315011: SSH session from IP_address on interface interface_name for user user disconnected by SSH server, reason: reason
- %PIX|ASA-6-321003: Resource var1 log level of var2 reached.
- %PIX|ASA-6-321004: Resource var1 rate log level of var2 reached
- %PIXPIX|ASA-6-403500: PPPoE - Service name 'any' not received in PADO. Intf:interface_name AC:ac_name.
- %PIX|ASA-6-415011:internal_sig_id HTTP URL Length exceeded. Received size byte URL - action URI length exceeded from source_address to dest_address
- %PIXPIX|ASA-6-602101: PMTU-D packet number bytes greater than effective mtu number dest_addr=dest_address, src_addr=source_address, prot=protocol
- %PIX|ASA-6-602103: IPSEC: Received an ICMP Destination Unreachable from src_addr with suggested PMTU of rcvd_mtu; PMTU updated for SA with peer peer_addr, SPI spi, tunnel name username, old PMTU old_mtu, new PMTU new_mtu.%PIX|ASA-7-703001: H.225 message received from interface_name:IP_address/port to interface_name:IP_address/port is using an unsupported version number
- %PIX|ASA-6-602104: IPSEC: Received an ICMP Destination Unreachable from src_addr, PMTU is unchanged because suggested PMTU of rcvd_mtu is equal to or greater than the current PMTU of curr_mtu, for SA with peer peer_addr, SPI spi, tunnel name username.
- %PIX|ASA-6-602201: ISAKMP Phase 1 SA created (local IP_address/port (initiator|responder), remote IP_address/port, authentication=auth_type, encryption=encl_alg, hash=hash_alg, group=DH_grp, lifetime=seconds)
- %PIX|ASA-6-602202: ISAKMP session connected (local IP_address (initiator|responder), remote IP_address)
- %PIXPIX|ASA-6-602203: ISAKMP session disconnected (local IP_address (initiator|responder), remote IP_address)
- %PIX|ASA-6-602303: IPSEC: An direction tunnel_type SA (SPI=spi) between local_IP and remote_IP (username) has been created.
- %PIX|ASA-6-603101: PPTP received out of seq or duplicate pkt, tnl_id=number, sess_id=number, seq=number.
- %PIX|ASA-6-603102: PPP virtual interface interface_name - user: user aaa authentication started.
- %PIX|ASA-6-603103: PPP virtual interface interface_name - user: user aaa authentication status
- %PIX|ASA-6-603104: PPTP Tunnel created, tunnel_id is number, remote_peer_ip is remote_address, ppp_virtual_interface_id is number, client_dynamic_ip is IP_address, username is user, MPPE_key_strength is string
- %PIX|ASA-6-603105: PPTP Tunnel deleted, tunnel_id = number, remote_peer_ip= remote_address
- %PIX|ASA-6-603106: L2TP Tunnel created, tunnel_id is number, remote_peer_ip is remote_address, ppp_virtual_interface_id is number, client_dynamic_ip is IP_address, username is user
- %PIX|ASA-6-603107: L2TP Tunnel deleted, tunnel_id = number, remote_peer_ip = remote_address
- %PIX|ASA-6-603108: Built PPTP Tunnel at interface_name, tunnel-id = number, remote-peer = IP_address, virtual-interface = number, client-dynamic-ip = IP_address, username = user, MPPE-key-strength = number
- %PIX|ASA-6-603109: Teardown PPPOE Tunnel at interface_name, tunnel-id = number, remote-peer = IP_address

- %PIX|ASA-6-604101: DHCP client interface interface_name: Allocated ip = IP_address, mask = netmask, gw = gateway_address
- %PIX|ASA-6-604102: DHCP client interface interface_name: address released
- %PIX|ASA-6-604103: DHCP daemon interface interface_name: address granted MAC_address (IP_address)
- %PIX|ASA-6-604104: DHCP daemon interface interface_name: address released
- %PIX|ASA-6-605004: Login denied from source-address/source-port to interface:destination/service for user "username"
- %PIX|ASA-6-605005: Login permitted from source-address/source-port to interface:destination/service for user "username"
- %PIX|ASA-6-606001: ASDM session number number from IP_address started
- %PIX|ASA-6-606002: ASDM session number number from IP_address ended
- %PIX|ASA-6-606003: ASDM logging session number id from IP_address started id session ID assigned
- %PIX|ASA-6-606004: ASDM logging session number id from IP_address ended
- %PIX|ASA-6-607001: Pre-allocate SIP connection_type secondary channel for interface_name:IP_address/port to interface_name:IP_address from string message
- %PIX|ASA-6-608001: Pre-allocate Skinny connection_type secondary channel for interface_name:IP_address to interface_name:IP_address/port from string message
- %PIX|ASA-6-609001: Built local-host interface_name:IP_address
- %PIX|ASA-6-609002: Teardown local-host interface_name:IP_address duration time
- %PIX|ASA-6-610101: Authorization failed: Cmd: command Cmdtype: command_modifier
- %PIX|ASA-6-611101: User authentication succeeded: Uname: user
- %PIX|ASA-6-611102: User authentication failed: Uname: user
- %PIX|ASA-6-611301: VPNClient: NAT configured for Client Mode with no split tunneling: NAT address: mapped_address
- %PIX|ASA-6-611302: VPNClient: NAT exemption configured for Network Extension Mode with no split tunneling
- %PIX|ASA-6-611303: VPNClient: NAT configured for Client Mode with split tunneling: NAT address: mapped_address Split Tunnel Networks: IP_address/netmask IP_address/netmask ...
- %PIX|ASA-6-611304: VPNClient: NAT exemption configured for Network Extension Mode with split tunneling: Split Tunnel Networks: IP_address/netmask IP_address/netmask ...
- %PIX|ASA-6-611305: VPNClient: DHCP Policy installed: Primary DNS: IP_address Secondary DNS: IP_address Primary WINS: IP_address Secondary WINS: IP_address
- %PIX|ASA-6-611306: VPNClient: Perfect Forward Secrecy Policy installed
- %PIX|ASA-6-611307: VPNClient: Head end : IP_address
- %PIX|ASA-6-611308: VPNClient: Split DNS Policy installed: List of domains: string string ...
- %PIX|ASA-6-611309: VPNClient: Disconnecting from head end and uninstalling previously downloaded policy: Head End: IP_address
- %PIX|ASA-6-611310: VNPClient: XAUTH Succeeded: Peer: IP_address
- %PIX|ASA-6-611311: VNPClient: XAUTH Failed: Peer: IP_address
- %PIX|ASA-6-611312: VPNClient: Backup Server List: reason
- %PIX|ASA-6-611314: VPNClient: Load Balancing Cluster with Virtual IP: IP_address has redirected the to server IP_address
- %PIX|ASA-6-611315: VPNClient: Disconnecting from Load Balancing Cluster member IP_address
- %PIX|ASA-6-611316: VPNClient: Secure Unit Authentication Enabled
- %PIX|ASA-6-611317: VPNClient: Secure Unit Authentication Disabled

- %PIX|ASA-6-611318: VPNClient: User Authentication Enabled: Auth Server IP: IP_address Auth Server Port: port Idle Timeout: time
- %PIX|ASA-6-611319: VPNClient: User Authentication Disabled
- %PIX|ASA-6-611320: VPNClient: Device Pass Thru Enabled
- %PIX|ASA-6-611321: VPNClient: Device Pass Thru Disabled
- %PIX|ASA-6-611322: VPNClient: Extended XAUTH conversation initiated when SUA disabled
- %PIX|ASA-6-611323: VPNClient: Duplicate split nw entry
- %PIX|ASA-6-613001: Checksum Failure in database in area string Link State Id IP_address Old Checksum number New Checksum number
- %PIX|ASA-6-613002: interface interface_name has zero bandwidth
- %PIX|ASA-6-613003: IP_address netmask changed from area string to area string
- %PIX|ASA-6-614001: Split DNS: request patched from server: IP_address to server: IP_address
- %PIX|ASA-6-614002: Split DNS: reply from server:IP_address reverse patched back to original server:IP_address
- %PIX|ASA-6-615001: vlan number not available for firewall interface
- %PIX|ASA-6-615002: vlan number available for firewall interface
- %PIX|ASA-6-616001:Pre-allocate MGCP data_channel connection for inside_interface:inside_address to outside_interface:outside_address/port from message_type message
- %PIX|ASA-6-617001: GTPv version msg_type from source_interface:source_address/source_port not accepted by source_interface:dest_address/dest_port
- %PIX|ASA-6-617002: Removing v1 PDP Context with TID tid from GGSN IP_address and SGSN IP_address, Reason: reason or Removing v1 primary|secondary PDP Context with TID tid from GGSN IP_address and SGSN IP_address, Reason: reason
- %PIX|ASA-6-617003: GTP Tunnel created from source_interface:source_address/source_port to source_interface:dest_address/dest_port
- %PIX|ASA-6-617004: GTP connection created for response from source_interface:source_address/0 to source_interface:dest_address/dest_port
- %PIX|ASA-6-620001: Pre-allocate CTIQBE {RTP | RTCP} secondary channel for interface_name:outside_address[/outside_port] to interface_name:inside_address[/inside_port] from CTIQBE_message_name message
- %PIX|ASA-6-621001: Interface interface_name does not support multicast, not enabled
- %PIX|ASA-6-621002: Interface interface_name does not support multicast, not enabled
- %PIX|ASA-6-621003: The event queue size has exceeded number
- %PIX|ASA-6-621006: Mrib disconnected, (IP_address,IP_address) event cancelled
- %PIX|ASA-6-621007: Bad register from interface_name:IP_address to IP_address for (IP_address, IP_address)
- %PIX|ASA-6-713145: Detected Hardware Client in network extension mode, adding static route for address: IP_address, mask: netmask
- %PIX|ASA-6-713147: Terminating tunnel to Hardware Client in network extension mode, deleting static route for address: IP_address, mask: netmask
- %PIX|ASA-6-713172: Automatic NAT Detection Status: Remote end is|is not behind a NAT device This end is|is not behind a NAT device
- %PIX|ASA-6-713177: Received remote Proxy Host FQDN in ID Payload: Host Name: host_name Address IP_address, Protocol protocol, Port port
- %PIX|ASA-6-713184: Client Type: Client_type Client Application Version: Application_version_string
- %PIX|ASA-6-713211: Adding static route for L2L peer coming in on a dynamic map. address: IP_address, mask: netmask

- %PIX|ASA-6-713213: Deleting static route for L2L peer that came in on a dynamic map. address: IP_address, mask: netmask
- %PIX|ASA-6-713215: No match against Client Type and Version rules. Client: type version is/is not allowed by default
- %PIX|ASA-6-713219: Queueing KEY-ACQUIRE messages to be processed when P1 SA is complete.
- %PIX|ASA-6-713220: De-queueing KEY-ACQUIRE messages that were left pending.
- %PIX|ASA-6-713228: Assigned private IP address assigned_private_IP%PIX|ASA-7-713235: Attempt to send an IKE packet from standby unit. Dropping the packet!
- %ASA-6-716001: Group group User user WebVPN session started.
- %ASA-6-716002: Group group User user WebVPN session terminated: reason.
- %ASA-6-716003: Group group User user WebVPN access GRANTED:: url
- %ASA-6-716004: Group group User user WebVPN access DENIED to specified location: url
- %ASA-6-716005: Group group User user WebVPN ACL Parse Error: reason
- %ASA-6-716006: Group name User user WebVPN session terminated. Idle timeout.
- %ASA-6-716009: Group group User user WebVPN session not allowed. WebVPN ACL parse error.
- %PIX|ASA-6-717003: Certificate received from Certificate Authority for trustpoint trustpoint_name.
- %ASA-6-716038: Authentication: successful, group = name user = user, Session Type: WebVPN
- %ASA-6-716039: Authentication: rejected, group = name user = user, Session Type: WebVPN
- %ASA-6-716040: Reboot pending, new sessions disabled. Denied user login.
- %ASA-6-716041: access-list acl_ID action url url hit_cnt count
- %ASA-6-716042: access-list acl_ID action tcp source_interface/source_address (source_port) -> dest_interface/dest_address(dest_port) hit-cnt count
- %PIX|ASA-6-717004: PKCS #12 export failed for trustpoint trustpoint_name.
- %PIX|ASA-6-717005: PKCS #12 export succeeded for trustpoint trustpoint_name.
- %PIX|ASA-6-717006: PKCS #12 import failed for trustpoint trustpoint_name.
- %PIX|ASA-6-717007: PKCS #12 import succeeded for trustpoint trustpoint_name.
- %PIX|ASA-6-717016: Removing expired CRL from the CRL cache. Issuer: issuer
- %PIX|ASA-6-717022 Certificate was successfully validated. certificate identifiers
- %PIX|ASA-6-717028 Certificate chain was successfully validated additional info.
- %PIX|ASA-6-718003: Got unknown peer message message_number from IP_address, local version version_number, remote version version_number
- %PIX|ASA-6-718004: Got unknown internal message message_number
- %PIX|ASA-6-718013: Peer IP_address is not answering HELLO
- %PIX|ASA-6-718027: Received unexpected KEEPALIVE request from IP_address
- %PIX|ASA-6-718030: Received planned OOS from IP_address
- %PIX|ASA-6-718037: Master processed number_of_timeouts timeouts
- %PIX|ASA-6-718038: Slave processed number_of_timeouts timeouts
- %PIX|ASA-6-718039: Process dead peer IP_address
- %PIX|ASA-6-718040: Timed-out exchange ID exchange_ID not found
- %PIX|ASA-6-718051: Deleted secure tunnel to peer IP_address
- %ASA-6-719001: Email Proxy session could not be established: session limit of maximum_sessions has been reached.
- %ASA-6-719003: Email Proxy session pointer resources have been freed for source_address.
- %ASA-6-719004: Email Proxy session pointer has been successfully established for source_address.
- %ASA-6-719010: protocol Email Proxy feature is disabled on interface interface_name.

- %ASA-6-719011: Protocol Email Proxy feature is enabled on interface interface_name.
- %ASA-6-719012: Email Proxy server listening on port port for mail protocol protocol.
- %ASA-6-719013: Email Proxy server closing port port for mail protocol protocol.
- %ASA-6-719017: WebVPN user: vpnuser invalid dynamic ACL.
- %ASA-6-719018: WebVPN user: vpnuser ACL ID acl_ID not found
- %ASA-6-719019: WebVPN user: vpnuser authorization failed.
- %ASA-6-719020: WebVPN user vpnuser authorization completed successfully.
- %ASA-6-719021: WebVPN user: vpnuser is not checked against ACL.
- %ASA-6-719022: WebVPN user vpnuser has been authenticated.
- %ASA-6-719023: WebVPN user vpnuser has not been successfully authenticated. Access denied.
- %ASA-6-719024: Email Proxy piggyback auth fail: session = pointer user=vpnuser addr=source_address
- %ASA-6-719025: Email Proxy DNS name resolution failed for hostname.
- %ASA-6-719026: Email Proxy DNS name hostname resolved to IP_address.
- %ASA-6-720002: (VPN-unit) Starting VPN Stateful Failover Subsystem...
- %ASA-6-720003: (VPN-unit) Initialization of VPN Stateful Failover Component completed successfully
- %ASA-6-720004: (VPN-unit) VPN failover main thread started.
- %ASA-6-720005: (VPN-unit) VPN failover timer thread started.
- %ASA-6-720006: (VPN-unit) VPN failover sync thread started.
- %ASA-6-720010: (VPN-unit) VPN failover client is being disabled
- %ASA-6-720012: (VPN-unit) Failed to update IPSec failover runtime data on the standby unit.
- %ASA-6-720014: (VPN-unit) Phase 2 connection entry (msg_id=message_number, my cookie=mine, his cookie=his) contains no SA list.
- %ASA-6-720015: (VPN-unit) Cannot found Phase 1 SA for Phase 2 connection entry (msg_id=message_number,my cookie=mine, his cookie=his).
- %ASA-6-720023: (VPN-unit) HA status callback: Peer is not present.
- %ASA-6-720024: (VPN-unit) HA status callback: Control channel is status.
- %ASA-6-720025: (VPN-unit) HA status callback: Data channel is status.
- %ASA-6-720026: (VPN-unit) HA status callback: Current progression is being aborted.
- %ASA-6-720027: (VPN-unit) HA status callback: My state state.
- %ASA-6-720028: (VPN-unit) HA status callback: Peer state state.
- %ASA-6-720029: (VPN-unit) HA status callback: Start VPN bulk sync state.
- %ASA-6-720030: (VPN-unit) HA status callback: Stop bulk sync state.
- %ASA-6-720032: (VPN-unit) HA status callback: id=ID, seq=sequence_#, grp=group, event=event, op=operand, my=my_state, peer=peer_state.
- %ASA-6-720037: (VPN-unit) HA progression callback: id=id,seq=sequence_number,grp=group,event=event,op=operand, my=my_state,peer=peer_state.
- %ASA-6-720039: (VPN-unit) VPN failover client is transitioning to active state
- %ASA-6-720040: (VPN-unit) VPN failover client is transitioning to standby state.
- %ASA-6-720045: (VPN-unit) Start bulk syncing of state information on standby unit.
- %ASA-6-720046: (VPN-unit) End bulk syncing of state information on standby unit
- %ASA-6-720056: (VPN-unit) VPN Stateful failover Message Thread is being disabled.
- %ASA-6-720057: (VPN-unit) VPN Stateful failover Message Thread is enabled.
- %ASA-6-720058: (VPN-unit) VPN Stateful failover Timer Thread is disabled.
- %ASA-6-720059: (VPN-unit) VPN Stateful failover Timer Thread is enabled.

- %ASA-6-720060: (VPN-unit) VPN Stateful failover Sync Thread is disabled.
- %ASA-6-720061: (VPN-unit) VPN Stateful failover Sync Thread is enabled.
- %ASA-6-720062: (VPN-unit) Active unit started bulk sync of state information to standby unit.
- %ASA-6-720063: (VPN-unit) Active unit completed bulk sync of state information to standby.

デバッグメッセージ、重大度 7

次のメッセージが重大度 7（デバッグ）で表示されます。

- %PIX|ASA-7-109014: uauth_lookup_net fail for uauth_in()
- %PIX|ASA-7-109021: Uauth null proxy error
- %PIX|ASA-7-111009: User user executed cmd:string
- %PIX|ASA-7-199009: ICMP detected an attached application while removing a context
- %PIX|ASA-7-304005: URL Server IP_address request pending URL url
- %PIX|ASA-7-304009: Ran out of buffer blocks specified by url-block command
- %PIX|ASA-7-701001: alloc_user() out of Tcp_user objects
- %PIX|ASA-7-701002: alloc_user() out of Tcp_proxy objects
- %PIX|ASA-7-702201: ISAKMP Phase 1 delete received (local IP_address (initiator|responder), remote IP_address)
- %PIX|ASA-7-702202: ISAKMP Phase 1 delete sent (local IP_address (initiator|responder), remote IP_address)
- %PIX|ASA-7-702203: ISAKMP DPD timed out (local IP_address (initiator|responder), remote IP_address)
- %PIX|ASA-7-702204: ISAKMP Phase 1 retransmission (local IP_address (initiator|responder), remote IP_address)
- %PIX|ASA-7-702205: ISAKMP Phase 2 retransmission (local IP_address (initiator|responder), remote IP_address)
- %PIX|ASA-7-702206: ISAKMP malformed payload received (local IP_address (initiator|responder), remote IP_address)
- %PIX|ASA-7-702207: ISAKMP duplicate packet detected (local IP_address (initiator|responder), remote IP_address)
- %PIX|ASA-7-702208: ISAKMP Phase 1 exchange started (local IP_address (initiator|responder), remote IP_address)
- %PIX|ASA-7-702209: ISAKMP Phase 2 exchange started (local IP_address (initiator|responder), remote IP_address)
- %PIX|ASA-7-702210: ISAKMP Phase 1 exchange completed(local IP_address (initiator|responder), remote IP_address)
- %PIX|ASA-7-702211: ISAKMP Phase 2 exchange completed(local IP_address (initiator|responder), remote IP_address)
- %PIX|ASA-7-702212: ISAKMP Phase 1 initiating rekey (local IP_address (initiator|responder), remote IP_address)
- %PIX|ASA-7-703001: H.225 message received from interface_name:IP_address/port to interface_name:IP_address/port is using an unsupported version number
- %PIX|ASA-7-703002: Received H.225 Release Complete with newConnectionNeeded for interface_name:IP_address to interface_name:IP_address/port
- %PIX|ASA-7-709001: FO replication failed: cmd=command returned=code
- %PIX|ASA-7-709002: FO unreplicable: cmd=command
- %PIX|ASA-7-710001: TCP access requested from source_address/source_port to interface_name:dest_address/service
- %PIX|ASA-7-710002: {TCP|UDP} access permitted from source_address/source_port to interface_name:dest_address/service
- %PIX|ASA-7-710004: TCP connection limit exceeded from source_address/source_port to interface_name:dest_address/service

- %PIX|ASA-7-710005: {TCP|UDP} request discarded from source_address/source_port to interface_name:dest_address/service
- %PIX|ASA-7-710006: protocol request discarded from source_address to interface_name:dest_address
- %PIX|ASA-7-711001: debug_trace_msg
- %PIX|ASA-7-711002: Task ran for elapsed_time msec, process = process_name
- %PIX|ASA-7-713024: Received local Proxy Host data in ID Payload: Address IP_address, Protocol protocol, Port port
- %PIX|ASA-7-713025: Received remote Proxy Host data in ID Payload: Address IP_address, Protocol protocol, Port port
- %PIX|ASA-7-713026: Transmitted local Proxy Host data in ID Payload: Address IP_address, Protocol protocol, Port port
- %PIX|ASA-7-713027: Transmitted remote Proxy Host data in ID Payload: Address IP_address, Protocol protocol, Port port
- %PIX|ASA-7-713028: Received local Proxy Range data in ID Payload: Addresses IP_address - IP_address, Protocol protocol, Port port
- %PIX|ASA-7-713029: Received remote Proxy Range data in ID Payload: Addresses IP_address - IP_address, Protocol protocol, Port port
- %PIX|ASA-7-713030: Transmitted local Proxy Range data in ID Payload: Addresses IP_address - IP_address, Protocol protocol, Port port
- %PIX|ASA-7-713031: Transmitted remote Proxy Range data in ID Payload: Addresses IP_address - IP_address, Protocol protocol, Port port
- %PIX|ASA-7-713034: Received local IP Proxy Subnet data in ID Payload: Address IP_address, Mask netmask, Protocol protocol, Port port
- %PIX|ASA-7-713035: Received remote IP Proxy Subnet data in ID Payload: Address IP_address, Mask netmask, Protocol protocol, Port port
- %PIX|ASA-7-713036: Transmitted local IP Proxy Subnet data in ID Payload: Address IP_address, Mask netmask, Protocol protocol, Port port
- %PIX|ASA-7-713037: Transmitted remote IP Proxy Subnet data in ID Payload: Address IP_address, Mask netmask, Protocol protocol, Port port
- %PIX|ASA-7-713039: Send failure: Bytes (number), Peer: IP_address
- %PIX|ASA-7-713040: Could not find connection entry and can not encrypt: msgid message_number
- %PIX|ASA-7-713052: User (user) authenticated.
- %PIX|ASA-7-713066: IKE Remote Peer configured for SA: SA_name
- %PIX|ASA-7-713094: Cert validation failure: handle invalid for Main/Aggressive Mode Initiator/Responder!
- %PIX|ASA-7-713099: Tunnel Rejected: Received NONCE length number is out of range!
- %PIX|ASA-7-713103: Invalid (NULL) secret key detected while computing hash
- %PIX|ASA-7-713104: Attempt to get Phase 1 ID data failed while hash computation
- %PIX|ASA-7-713113: Deleting IKE SA with associated IPSec connection entries. IKE peer: IP_address, SA address: internal_SA_address, tunnel count: count
- %PIX|ASA-7-713114: Connection entry (conn entry internal address) points to IKE SA (SA_internal_address) for peer IP_address, but cookies don't match
- %PIX|ASA-7-713117: Received Invalid SPI notify (SPI SPI_Value)!
- %PIX|ASA-7-713121: Keep-alive type for this connection: keepalive_type
- %PIX|ASA-7-713143: Processing firewall record. Vendor: vendor(id), Product: product(id), Caps: capability_value, Version Number: version_number, Version String: version_text
- %PIX|ASA-7-713160: Remote user (session Id - id) has been granted access by the Firewall Server
- %PIX|ASA-7-713164: The Firewall Server has requested a list of active user sessions

- %PIX|ASA-7-713169: IKE Received delete for rekeyed SA IKE peer: IP_address, SA address: internal_SA_address, tunnelCnt: tunnel_count
- %PIX|ASA-7-713170: IKE Received delete for rekeyed centry IKE peer: IP_address, centry address: internal_address, msgid: id
- %PIX|ASA-7-713171: NAT-Traversal sending NAT-Original-Address payload
- %PIX|ASA-7-713187: Tunnel Rejected: IKE peer does not match remote peer as defined in L2L policy IKE peer address: IP_address, Remote peer address: IP_address
- %PIX|ASA-7-713190: Got bad refCnt (ref_count_value) assigning IP_address (IP_address)
- %PIX|ASA-7-713204: Adding static route for client address: IP_address
- %PIX|ASA-7-713221: Static Crypto Map check, checking map = crypto_map_tag, seq = seq_number...
- %PIX|ASA-7-713222: Static Crypto Map check, map = crypto_map_tag, seq = seq_number, ACL does not match proxy IDs src:source_address dst:dest_address
- %PIX|ASA-7-713223: Static Crypto Map check, map = crypto_map_tag, seq = seq_number, no ACL configured
- %PIX|ASA-7-713224: Static Crypto Map Check by-passed: Crypto map entry incomplete!
- %PIX|ASA-7-713225: [IKEv1], Static Crypto Map check, map map_name, seq = sequence_number is a successful match
- %PIX|ASA-7-713236: IKE_DECODE tx/rx Message (msgid=msgid) with payloads :payload1 (payload1_len) + payload2 (payload2_len)...total length : tlen
- %PIX|ASA-7-713900:Descriptive_event_string.
- %PIX|ASA-7-713901:Descriptive_event_string.
- %PIX|ASA-7-713905:Descriptive_event_string.
- %PIX|ASA-7-713906: debug_message
- %PIX|ASA-7-714001: Description of event or packet
- %PIX|ASA-7-714002: IKE Initiator starting QM: msg id = message_number
- %PIX|ASA-7-714003: IKE Responder starting QM: msg id = message_number
- %PIX|ASA-7-714004: IKE Initiator sending 1st QM pkt: msg id = message_number
- %PIX|ASA-7-714005: IKE Responder sending 2nd QM pkt: msg id = message_number
- %PIX|ASA-7-714006: IKE Initiator sending 3rd QM pkt: msg id = message_number
- %PIX|ASA-7-714007: IKE Initiator sending Initial Contact
- %PIX|ASA-7-714011: Description of received ID values
- %PIX|ASA-7-715001: Descriptive statement
- %PIX|ASA-7-715004: subroutine name() Q Send failure: RetCode (return_code)
- %PIX|ASA-7-715005: subroutine name() Bad message code: Code (message_code)
- %PIX|ASA-7-715006: IKE got SPI from key engine: SPI = SPI_value
- %PIX|ASA-7-715007: IKE got a KEY_ADD msg for SA: SPI = SPI_value
- %PIX|ASA-7-715008: Could not delete SA SA_address, refCnt = number, caller = calling_subroutine_address
- %PIX|ASA-7-715009: IKE Deleting SA: Remote Proxy IP_address, Local Proxy IP_address
- %PIX|ASA-7-715013: Tunnel negotiation in progress for destination IP_address, discarding data
- %PIX|ASA-7-715019: IKEGetUserAttributes: Attribute name = name
- %PIX|ASA-7-715020: construct_cfg_set: Attribute name = name
- %PIX|ASA-7-715040: Deleting active auth handle during SA deletion: handle = internal_authentication_handle
- %PIX|ASA-7-715041: Received keep-alive of type keepalive_type, not the negotiated type
- %PIX|ASA-7-715042: IKE received response of type failure_type to a request from the IP_address utility

- %PIX|ASA-7-715044: Ignoring Keepalive payload from vendor not support KeepAlive capability
- %PIX|ASA-7-715045: ERROR: malformed Keepalive payload
- %PIX|ASA-7-715046: constructing payload_description payload
- %PIX|ASA-7-715047: processing payload_description payload
- %PIX|ASA-7-715048: Send VID_type VID
- %PIX|ASA-7-715049: Received VID_type VID
- %PIX|ASA-7-715050: Claims to be IOS but failed authentication
- %PIX|ASA-7-715051: Received unexpected TLV type TLV_type while processing FWTYPE ModeCfg Reply
- %PIX|ASA-7-715052: Old P1 SA is being deleted but new SA is DEAD, cannot transition centres
- %PIX|ASA-7-715053: MODE_CFG: Received request for attribute_info!
- %PIX|ASA-7-715054: MODE_CFG: Received attribute_name reply: value
- %PIX|ASA-7-715055: Send attribute_name
- %PIX|ASA-7-715056: Client is configured for TCP_transparency
- %PIX|ASA-7-715057: Auto-detected a NAT device with NAT-Traversal. Ignoring IPSec-over-UDP configuration.
- %PIX|ASA-7-715058: NAT-Discovery payloads missing. Aborting NAT-Traversal.
- %PIX|ASA-7-715059: Proposing/Selecting only UDP-Encapsulated-Tunnel and UDP-Encapsulated-Transport modes defined by NAT-Traversal
- %PIX|ASA-7-715060: Dropped received IKE fragment. Reason: reason
- %PIX|ASA-7-715061: Rcv'd fragment from a new fragmentation set. Deleting any old fragments.
- %PIX|ASA-7-715062: Error assembling fragments! Fragment numbers are non-continuous.
- %PIX|ASA-7-715063: Successfully assembled an encrypted pkt from rcv'd fragments!
- %PIX|ASA-7-715064 -- IKE Peer included IKE fragmentation capability flags: Main Mode: true/false Aggressive Mode: true/false
- %PIX|ASA-7-715065: IKE state_machine subtype FSM error history (struct data_structure_address) state, event: state/event pairs
- %PIX|ASA-7-715066: Can't load an IPSec SA! The corresponding IKE SA contains an invalid logical ID.
- %PIX|ASA-7-715067: QM IsRekeyed: existing sa from different peer, rejecting new sa
- %PIX|ASA-7-715067: QM IsRekeyed: existing sa from different peer, rejecting new sa
- %PIX|ASA-7-715068: QM IsRekeyed: duplicate sa found by address, deleting old sa
- %PIX|ASA-7-715069: Invalid ESP SPI size of SPI_size
- %PIX|ASA-7-715070: Invalid IPComp SPI size of SPI_size
- %PIX|ASA-7-715071: AH proposal not supported
- %PIX|ASA-7-715072: Received proposal with unknown protocol ID protocol_ID
- %PIX|ASA-7-715074: Could not retrieve authentication attributes for peer IP_address
- %PIX|ASA-7-715075: Group = group_name, Username = client, IP = IP_address Received keep-alive of type message_type (seq number number)
- %PIX|ASA-7-715076: Computing hash for ISAKMP
- %PIX|ASA-7-715077: Pitcher: msg string, spi spi
- %ASA-7-716008: WebVPN ACL: action
- %ASA-7-716010: Group group User user Browse network.
- %ASA-7-716011: Group group User user Browse domain domain.
- %ASA-7-716012: Group group User user Browse directory directory.
- %ASA-7-716013: Group group User user Close file filename.

- %ASA-7-716014: Group group User user View file filename.
- %ASA-7-716015: Group group User user Remove file filename.
- %ASA-7-716016: Group group User user Rename file old_filename to new_filename.
- %ASA-7-716017: Group group User user Modify file filename.
- %ASA-7-716018: Group group User user Create file filename.
- %ASA-7-716019: Group group User user Create directory directory.
- %ASA-7-716020: Group group User user Remove directory directory.
- %ASA-7-716021: File access DENIED, filename.
- %PIX|ASA-7-717024 Checking CRL from trustpoint: trustpoint name for purpose
- %PIX|ASA-7-717025 Validating certificate chain containing number of certs certificate(s).
- %PIX|ASA-7-717029 Identified client certificate within certificate chain. serial number: serial_number, subject name: subject_name.
- %PIX|ASA-7-717030 Found a suitable trustpoint trustpoint name to validate certificate.
- %PIX|ASA-7-713233: (VPN-unit) Remote network (remote network) validated for network extension mode.
- %PIX|ASA-7-713234: (VPN-unit) Remote network (remote network) from network extension mode client mismatches AAA configuration (aaa network).
- %PIX|ASA-7-718001: Internal interprocess communication queue send failure: code error_code
- %PIX|ASA-7-718017: Got timeout for unknown peer IP_address msg type message_type
- %PIX|ASA-7-718018: Send KEEPALIVE request failure to IP_address
- %PIX|ASA-7-718019: Sent KEEPALIVE request to IP_address
- %PIX|ASA-7-718020: Send KEEPALIVE response failure to IP_address
- %PIX|ASA-7-718021: Sent KEEPALIVE response to IP_address
- %PIX|ASA-7-718022: Received KEEPALIVE request from IP_address
- %PIX|ASA-7-718023: Received KEEPALIVE response from IP_address
- %PIX|ASA-7-718025: Sent CFG UPDATE to IP_address
- %PIX|ASA-7-718026: Received CFG UPDATE from IP_address
- %PIX|ASA-7-718034: Sent TOPOLOGY indicator to IP_address
- %PIX|ASA-7-718035: Received TOPOLOGY indicator from IP_address
- %PIX|ASA-7-718036: Process timeout for req-type type_value, exid exchange_ID, peer IP_address
- %PIX|ASA-7-718041: Timeout [msgType=type] processed with no callback
- %PIX|ASA-7-718046: Create group policy policy_name
- %PIX|ASA-7-718047: Fail to create group policy policy_name
- %PIX|ASA-7-718049: Created secure tunnel to peer IP_address
- %PIX|ASA-7-718058: State machine return code: action_routine, return_code
- %PIX|ASA-7-718059: State machine function trace: state=state_name, event=event_name, func=action_routine
- %PIX|ASA-7-718088: Possible VPN LB misconfiguration. Offending device MAC MAC_address.
- %PIX|ASA-7-718029: Sent OOS indicator to IP_address
- %ASA-7-720031: (VPN-unit) HA status callback: Invalid event received. event=event_ID.
- %ASA-7-720034: (VPN-unit) Invalid type (type) for message handler.
- %ASA-7-720041: (VPN-unit) Sending type message id to standby unit
- %ASA-7-720042: (VPN-unit) Receiving type message id from active unit
- %ASA-7-720048: (VPN-unit) FSM action trace begin: state=state, last event=event, func=function.

■ デバッグメッセージ、重大度 7

- %ASA-7-720049: (VPN-unit) FSM action trace end: state=state, last event=event, return=return, func=function.
- %ASA-7-720050: (VPN-unit) Failed to remove timer. ID = id.