

RIP 커피그레이션을 사용하는 GRE 터널의 라우터 간 IPSec(RSA 키) 예

목차

[소개](#)
[사전 요구 사항](#)
[요구 사항](#)
[사용되는 구성 요소](#)
[표기 규칙](#)
[구성](#)
[네트워크 다이어그램](#)
[구성](#)
[다음을 확인합니다.](#)
[문제 해결](#)
[트러블슈팅 절차](#)
[문제 해결 명령](#)
[관련 정보](#)

소개

이 문서에서는 RSA 키가 있는 라우터에 대한 샘플 커피그레이션을 제공합니다. 두 라우터 모두 RSA 키와 RIP(Routing Information Protocol)가 포함된 IPSec/GRE(Generic Routing Encapsulation) 터널에 대해 구성됩니다.

사전 요구 사항

요구 사항

이 문서에 대한 특정 요건이 없습니다.

사용되는 구성 요소

이 문서의 정보는 다음 소프트웨어 및 하드웨어 버전을 기반으로 합니다.

- Cisco IOS® 소프트웨어 릴리스 12.2를 실행하는 Cisco 라우터

이 문서의 정보는 특정 랩 환경의 디바이스를 토대로 작성되었습니다. 이 문서에 사용된 모든 디바이스는 초기화된(기본) 커피그레이션으로 시작되었습니다. 현재 네트워크가 작동 중인 경우, 모든 명령어의 잠재적인 영향을 미리 숙지하시기 바랍니다.

표기 규칙

문서 표기 규칙에 대한 자세한 내용은 [Cisco 기술 팁 표기 규칙을 참조하십시오.](#)

구성

이 섹션에는 이 문서에서 설명하는 기능을 구성하기 위한 정보가 표시됩니다.

참고: 이 문서에 사용된 명령에 대한 추가 정보를 찾으려면 [명령 조회 도구\(등록된 고객만 해당\)](#)를 사용합니다.

네트워크 다이어그램

이 문서에서는 다음 네트워크 설정을 사용합니다.



구성

이 문서에서는 다음 구성을 사용합니다.

- [라우터 101용 암호화 컨피그레이션](#)
- [라우터 101](#)
- [라우터 102의 암호화 구성](#)
- [라우터 102](#)

라우터 101용 암호화 컨피그레이션

```
101(config)#crypto isakmp enable
101(config)#crypto isakmp identity hostname
101(config)#crypto isakmp policy 1
101(config-isakmp)#authentication rsa-encr
101(config)#access-list 101 permit gre host 20.1.1.1
host 20.1.1.2
101(config)#crypto ipsec transform-set test esp-des esp-
sha-hmac
101(cfg-crypto-trans)#mode transport
101(config)#crypto map test 10 ip
101(config)#crypto map test 10 ipsec-is
% NOTE: This new crypto map will remain disabled until a
peer
        and a valid access list have been configured.
101(config-crypto-map)#set transform-set test
101(config-crypto-map)#match address 101
101(config-crypto-map)#set peer 20.1.1.2
101(config-crypto-map)#
101(config)#access-list 101 permit gre host 20.1.1.1
host 20.1.1.2
```

```
101(config)#interface Tunnel0
101(config-if)#crypto map test

101(config)#interface ethernet 1/0
101(config-if)#crypto map test
```

라우터 101

```
Building configuration...

Current configuration : 1486 bytes
!
version 12.2
service timestamps debug datetime msec
service timestamps log datetime msec
no service password-encryption
!
hostname 101
!
!
clock timezone PST -8
ip subnet-zero
ip domain name cisco.com
ip host 102.cisco.com 20.1.1.2
!
ip audit notify log
ip audit po max-events 100
!
crypto isakmp policy 1
 authentication rsa-encr
crypto isakmp identity hostname
crypto isakmp keepalive 20 5
!
!
crypto ipsec transform-set test esp-des esp-sha-hmac
 mode transport
!
crypto map test 10 ipsec-isakmp
 set peer 20.1.1.2
 set transform-set test
 match address 101
!
!
crypto key pubkey-chain rsa
 named-key 102.cisco.com
 key-string
 305C300D 06092A86 4886F70D 01010105 00034B00 30480241
00DB4FEB EF0C0D3D
 72FC5BD3 29C8E94B 726161BC F1AF337C E5F2D11D FBFC2245
95EA2AB7 9D09156C
 08A5A7CD 36E43D94 F1E3C978 37A79379 384D2A72 CE575E91
3F020301 0001
 quit
!
!
!
interface Loopback1
 ip address 192.168.1.1 255.255.255.0
!
interface Tunnel0
 ip address 10.10.10.1 255.255.255.252
 ip mtu 1420
 tunnel source Ethernet1/0
```

```

tunnel destination 20.1.1.2
crypto map test
!
interface Ethernet0/0
 ip address 1.1.1.1 255.255.255.0
!
interface Ethernet1/0
 ip address 20.1.1.1 255.255.255.0
crypto map test
!
interface Serial2/0
 no ip address
 shutdown
!
interface Serial3/0
 no ip address
 shutdown
!
router rip
 version 2
 passive-interface Ethernet1/0
 network 10.0.0.0
 network 192.168.1.0
!
ip classless
no ip http server
!
!
access-list 101 permit gre host 20.1.1.1 host 20.1.1.2
!
!
line con 0
line aux 0
line vty 0 4
 login
!
end

101#

```

라우터 102의 암호화 구성

```

102(config)#crypto isakmp enable
102(config)#crypto isakmp identity hostname
102(config)#crypto isakmp policy 1
102(config-isakmp)#authentication rsa-encr
102(config)#access-list 101 permit gre host 20.1.1.2
host 20.1.1.1
102(config)#crypto ipsec transform-set test esp-des esp-
sha-hmac
102(crypto-trans)#mode transport
102(config)#crypto map test 10 ip
102(config)#crypto map test 10 ipsec-is
% NOTE: This new crypto map will remain disabled until a
peer
      and a valid access list have been configured.
102(config-crypto-map)#set transform-set test
102(config-crypto-map)#match address 101
102(config-crypto-map)#set peer 20.1.1.1
102(config-crypto-map)#

```

```
102(config)#interface Tunnel0
102(config-if)#crypto map test

102(config)#interface ethernet 1/0
102(config-if)#crypto map test
```

라우터 102

```
102#write terminal
Building configuration...

Current configuration : 1484 bytes
!
version 12.2
service timestamps debug datetime msec
service timestamps log datetime msec
no service password-encryption
!
hostname 102
!
!
clock timezone PST -8
ip subnet-zero
ip domain name cisco.com
ip host 101.cisco.com 20.1.1.1
!
ip audit notify log
ip audit po max-events 100
!
crypto isakmp policy 1
 authentication rsa-encr
crypto isakmp identity hostname
crypto isakmp keepalive 20 5
!
!
crypto ipsec transform-set test esp-des esp-sha-hmac
 mode transport
!
crypto map test 10 ipsec-isakmp
 set peer 20.1.1.1
 set transform-set test
 match address 101
!
!
crypto key pubkey-chain rsa
 named-key 101.cisco.com
 address 20.1.1.1
 key-string
 305C300D 06092A86 4886F70D 01010105 00034B00 30480241
00A7D24F E6E15787
 5EE1434A A76A3DC1 ADE96A4D C6B4D0F3 A7DDAD10 446EF83A
89D1115F 0C517118
 ECAF418E F4C84823 2A017B97 F85690EF EBCF3414 AB3E81F6
A5020301 0001
 quit
!
!
!
interface Loopback1
 ip address 172.16.1.1 255.255.255.0
!
interface Tunnel0
 ip address 10.10.10.2 255.255.255.252
```

```

ip mtu 1420
tunnel source Ethernet0/0
tunnel destination 20.1.1.1
crypto map test
!
interface Ethernet0/0
 ip address 20.1.1.2 255.255.255.0
 crypto map test
!
interface Ethernet1/0
 no ip address
!
interface Serial2/0
 no ip address
 shutdown
!
interface Serial3/0
 no ip address
 shutdown
!
router rip
 version 2
 passive-interface Ethernet0/0
 network 10.0.0.0
 network 172.16.0.0
!
ip classless
no ip http server
!
!
access-list 101 permit gre host 20.1.1.2 host 20.1.1.1
!
!
line con 0
line aux 0
line vty 0 4
 login
!
end

102#

```

다음을 확인합니다.

이 섹션에서는 컨피그레이션이 제대로 작동하는지 확인하는 데 사용할 수 있는 정보를 제공합니다.

일부 **show** 명령은 [출력 인터프리터 터미널에서 지원되는데\(등록된 고객만\)](#), 이 터미널을 사용하면 **show** 명령 출력의 분석 결과를 볼 수 있습니다.

- **show crypto isakmp sa detail** - 피어의 현재 모든 IKE(Internet Key Exchange) 보안 연결(SA)을 표시합니다.
- **show crypto ipsec sa** - 현재 SA에서 사용하는 설정을 표시합니다.
- **show crypto engine connections active**—암호화 엔진에 대한 컨피그레이션 정보의 요약을 표시합니다.
- **show ip route** - 라우팅 테이블의 현재 상태를 표시합니다.

라우터 101 명령 출력

```

101#show crypto isakmp sa detail
*Dec 28 21:15:19.371: ISAKMP (0:14): purging node 543282640
Codes: C - IKE configuration mode, D - Dead Peer Detection
      K - Keepalives, N - NAT-traversal
      X - IKE Extended Authentication
      psk - Preshared key, rsig - RSA signature
      renc - RSA encryption

Conn id Local           Remote           Encr Hash Auth DH Lifetime Capabilities
14     20.1.1.1         20.1.1.2       des  sha  rsig 1  23:59:06 D

```

```
101#show crypto ipsec sa
```

```

interface: Ethernet1/0
  Crypto map tag: test, local addr. 20.1.1.1

  local ident (addr/mask/prot/port): (20.1.1.1/255.255.255.255/47/0)
  remote ident (addr/mask/prot/port): (20.1.1.2/255.255.255.255/47/0)
  current_peer: 20.1.1.2:500
    PERMIT, flags={origin_is_acl,}
    #pkts encaps: 0, #pkts encrypt: 0, #pkts digest 0
    #pkts decaps: 0, #pkts decrypt: 0, #pkts verify 0
    #pkts compressed: 0, #pkts decompressed: 0
    #pkts not compressed: 0, #pkts compr. failed: 0
    #pkts not decompressed: 0, #pkts decompress failed: 0
    #send errors 1, #recv errors 0

  local crypto endpt.: 20.1.1.1, remote crypto endpt.: 20.1.1.2
  path mtu 1420, media mtu 1420
  current outbound spi: 7FB7A347

  inbound esp sas:
    spi: 0x7221D7D2(1914820562)
      transform: esp-des esp-sha-hmac ,
      in use settings ={Transport, }
      slot: 0, conn id: 2000, flow_id: 1, crypto map: test
      sa timing: remaining key lifetime (k/sec): (4468975/3586)
      IV size: 8 bytes
      replay detection support: Y

  inbound ah sas:

  inbound pcp sas:

  outbound esp sas:
    spi: 0x7FB7A347(2142741319)
      transform: esp-des esp-sha-hmac ,
      in use settings ={Transport, }
      slot: 0, conn id: 2001, flow_id: 2, crypto map: test
      sa timing: remaining key lifetime (k/sec): (4468975/3586)
      IV size: 8 bytes
      replay detection support: Y

  outbound ah sas:

  outbound pcp sas:

interface: Tunnel0

```

```
Crypto map tag: test, local addr. 20.1.1.1
```

```
local ident (addr/mask/prot/port): (20.1.1.1/255.255.255.255/47/0)
remote ident (addr/mask/prot/port): (20.1.1.2/255.255.255.255/47/0)
current_peer: 20.1.1.2:500
```

```
    PERMIT, flags={origin_is_acl,}
#pkts encaps: 0, #pkts encrypt: 0, #pkts digest 0
#pkts decaps: 0, #pkts decrypt: 0, #pkts verify 0
#pkts compressed: 0, #pkts decompressed: 0
#pkts not compressed: 0, #pkts compr. failed: 0
#pkts not decompressed: 0, #pkts decompress failed: 0
#send errors 1, #recv errors 0
```

```
local crypto endpt.: 20.1.1.1, remote crypto endpt.: 20.1.1.2
path mtu 1420, media mtu 1420
current outbound spi: 7FB7A347
```

```
inbound esp sas:
spi: 0x7221D7D2(1914820562)
    transform: esp-des esp-sha-hmac ,
    in use settings ={Transport, }
    slot: 0, conn id: 2000, flow_id: 1, crypto map: test
    sa timing: remaining key lifetime (k/sec): (4468975/3585)
    IV size: 8 bytes
    replay detection support: Y
```

```
inbound ah sas:
```

```
inbound pcp sas:
```

```
outbound esp sas:
spi: 0x7FB7A347(2142741319)
    transform: esp-des esp-sha-hmac ,
    in use settings ={Transport, }
    slot: 0, conn id: 2001, flow_id: 2, crypto map: test
    sa timing: remaining key lifetime (k/sec): (4468975/3584)
    IV size: 8 bytes
    replay detection support: Y
```

```
outbound ah sas:
```

```
outbound pcp sas:
```

```
101#show crypto engine connections active
```

ID	Interface	IP-Address	State	Algorithm	Encrypt	Decrypt
14	Ethernet1/0	20.1.1.1	set	HMAC_SHA+DES_56_CB	0	0
2000	Ethernet1/0	20.1.1.1	set	HMAC_SHA+DES_56_CB	0	6
2001	Ethernet1/0	20.1.1.1	set	HMAC_SHA+DES_56_CB	5	0

```
101#show ip route
```

```
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
      D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
      N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
      E1 - OSPF external type 1, E2 - OSPF external type 2
      i - IS-IS, L1 - IS-IS level-1, L2 - IS-IS level-2, ia - IS-IS inter area
      * - candidate default, U - per-user static route, o - ODR
      P - periodic downloaded static route
```

```
Gateway of last resort is not set
```

```

20.0.0.0/24 is subnetted, 1 subnets
C      20.1.1.0 is directly connected, Ethernet1/0
R  172.16.0.0/16 [120/1] via 10.10.10.2, 00:00:08, Tunnel0
  10.0.0.0/30 is subnetted, 1 subnets
C      10.10.10.0 is directly connected, Tunnel0
C  192.168.1.0/24 is directly connected, Loopback1
101#

```

라우터 102 명령 출력

```

102#show crypto isakmp sa detail
Codes: C - IKE configuration mode, D - Dead Peer Detection
      K - Keepalives, N - NAT-traversal
      X - IKE Extended Authentication
      psk - Preshared key, rsig - RSA signature
      renc - RSA encryption

Conn id Local           Remote          Encr Hash Auth DH Lifetime Capabilities
15      20.1.1.2        20.1.1.1       des  sha  rsig 1  23:58:44 D

```

```
102#show crypto ipsec sa
```

interface: Ethernet0/0

```

Crypto map tag: test, local addr. 20.1.1.2

local ident (addr/mask/prot/port): (20.1.1.2/255.255.255.255/47/0)
remote ident (addr/mask/prot/port): (20.1.1.1/255.255.255.255/47/0)
current_peer: 20.1.1.1:500
  PERMIT, flags={origin_is_acl,}
#pkts encaps: 4, #pkts encrypt: 4, #pkts digest 4
#pkts decaps: 3, #pkts decrypt: 3, #pkts verify 3
#pkts compressed: 0, #pkts decompressed: 0
#pkts not compressed: 0, #pkts compr. failed: 0
#pkts not decompressed: 0, #pkts decompress failed: 0
#send errors 0, #recv errors 0

local crypto endpt.: 20.1.1.2, remote crypto endpt.: 20.1.1.1
path mtu 1420, media mtu 1420
current outbound spi: 92F52EF2

```

```

inbound esp sas:
spi: 0x1D25013E(488964414)
  transform: esp-des esp-sha-hmac ,
  in use settings ={Transport, }
  slot: 0, conn id: 2000, flow_id: 1, crypto map: test
  sa timing: remaining key lifetime (k/sec): (4596388/3494)
  IV size: 8 bytes
  replay detection support: Y

```

```
inbound ah sas:
```

```
inbound pcp sas:
```

```

outbound esp sas:
spi: 0x92F52EF2(2465541874)
  transform: esp-des esp-sha-hmac ,
  in use settings ={Transport, }
  slot: 0, conn id: 2001, flow_id: 2, crypto map: test
  sa timing: remaining key lifetime (k/sec): (4596388/3494)
  IV size: 8 bytes
  replay detection support: Y

```

```

outbound ah sas:

outbound pcp sas:

interface: Tunnel0
  Crypto map tag: test, local addr. 20.1.1.2

  local ident (addr/mask/prot/port): (20.1.1.2/255.255.255.255/47/0)
  remote ident (addr/mask/prot/port): (20.1.1.1/255.255.255.255/47/0)
  current_peer: 20.1.1.1:500
    PERMIT, flags={origin_is_acl,}

  #pkts encaps: 4, #pkts encrypt: 4, #pkts digest 4
  #pkts decaps: 3, #pkts decrypt: 3, #pkts verify 3
  #pkts compressed: 0, #pkts decompressed: 0
  #pkts not compressed: 0, #pkts compr. failed: 0
  #pkts not decompressed: 0, #pkts decompress failed: 0
  #send errors 0, #recv errors 0

  local crypto endpt.: 20.1.1.2, remote crypto endpt.: 20.1.1.1
  path mtu 1420, media mtu 1420
  current outbound spi: 92F52EF2

  inbound esp sas:
    spi: 0x1D25013E(488964414)
      transform: esp-des esp-sha-hmac ,
      in use settings ={Transport, }
      slot: 0, conn id: 2000, flow_id: 1, crypto map: test
      sa timing: remaining key lifetime (k/sec): (4596388/3493)
      IV size: 8 bytes
      replay detection support: Y

  inbound ah sas:

  inbound pcp sas:

  outbound esp sas:
    spi: 0x92F52EF2(2465541874)
      transform: esp-des esp-sha-hmac ,
      in use settings ={Transport, }
      slot: 0, conn id: 2001, flow_id: 2, crypto map: test
      sa timing: remaining key lifetime (k/sec): (4596388/3493)
      IV size: 8 bytes
      replay detection support: Y

  outbound ah sas:

  outbound pcp sas:

```

102#**show crypto engine connections active**

ID	Interface	IP-Address	State	Algorithm	Encrypt	Decrypt
15	Ethernet0/0	20.1.1.2	set	HMAC_SHA+DES_56_CB	0	0
2000	Ethernet0/0	20.1.1.2	set	HMAC_SHA+DES_56_CB	0	3
2001	Ethernet0/0	20.1.1.2	set	HMAC_SHA+DES_56_CB	4	0

102#

102#**show ip route**

Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
 D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area

N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, L1 - IS-IS level-1, L2 - IS-IS level-2, ia - IS-IS inter area
* - candidate default, U - per-user static route, o - ODR
P - periodic downloaded static route

Gateway of last resort is not set

```
20.0.0.0/24 is subnetted, 1 subnets
C      20.1.1.0 is directly connected, Ethernet0/0
172.16.0.0/24 is subnetted, 1 subnets
C      172.16.1.0 is directly connected, Loopback1
10.0.0.0/30 is subnetted, 1 subnets
C      10.10.10.0 is directly connected, Tunnel0
R  192.168.1.0/24 [120/1] via 10.10.10.1, 00:00:08, Tunnel0
```

문제 해결

이 섹션에서는 컨피그레이션 문제를 해결하는 데 사용할 수 있는 정보를 제공합니다. 문제 해결에 대한 자세한 내용은 [IP 보안 문제 해결 - 디버그 명령 이해 및 사용을 참조하십시오.](#)

트러블슈팅 절차

컨피그레이션 문제를 해결하려면 다음 지침을 따르십시오.

1. 라우터 101에서 RSA 키를 생성합니다.

```
101#show crypto key mypubkey rsa
101#
101#
101#conf t
101(config)#ip domain-name cisco.com
101(config)#crypto key generate rsa ?
    general-keys  Generate a general purpose RSA key pair for signing and
                   encryption
    usage-keys    Generate separate RSA key pairs for signing and encryption

101(config)#crypto key generate rsa
The name for the keys will be: 101.cisco.com
Choose the size of the key modulus in the range of 360 to 2048 for your
General Purpose Keys. Choosing a key modulus greater than 512 may take
a few minutes.

How many bits in the modulus [512]:
% Generating 512 bit RSA keys ...[OK]

101#show crypto key mypubkey rsa
% Key pair was generated at: 12:02:08 PST Dec 28 2002
Key name: 101.cisco.com
Usage: General Purpose Key
Key Data:
305C300D 06092A86 4886F70D 01010105 00034B00 30480241 00A7D24F E6E15787
5EE1434A A76A3DC1 ADE96A4D C6B4D0F3 A7DDAD10 446EF83A 89D1115F 0C517118
ECAF418E F4C84823 2A017B97 F85690EF EBCF3414 AB3E81F6 A5020301 0001
% Key pair was generated at: 12:02:12 PST Dec 28 2002
Key name: 101.cisco.com.server
Usage: Encryption Key
Key Data:
307C300D 06092A86 4886F70D 01010105 00036B00 30680261 00B2092A 86483641
EB09900B BA0CD88A BE915C5E 05C1496B 70093D8B BC277A88 0E256BBE 4DB7EF92
8FE93C61 710309A3 451DAB72 93F35CD0 1CAD15AC B904B2B4 73B7A9F5 65A79E66
```

```
8D145427 F06DD89C 862B88BB 4C671508 AB3443BB 6270388C A7020301 0001  
101#
```

2. 라우터 102에서 RSA 키를 생성합니다.

```
102#configure terminal  
Enter configuration commands, one per line. End with CNTL/Z.  
102(config)#ip domain-name cisco.com  
102(config)#crypto key gen rsa  
The name for the keys will be: 102.cisco.com  
Choose the size of the key modulus in the range of 360 to 2048 for your  
General Purpose Keys. Choosing a key modulus greater than 512 may take  
a few minutes.  
  
How many bits in the modulus [512]:  
% Generating 512 bit RSA keys ...[OK]
```

```
102#show crypto key mypubkey rsa  
% Key pair was generated at: 12:03:45 PST Dec 28 2002  
Key name: 102.cisco.com  
Usage: General Purpose Key  
Key Data:  
305C300D 06092A86 4886F70D 01010105 00034B00 30480241 00DB4FEB EF0C0D3D  
72FC5BD3 29C8E94B 726161BC F1AF337C E5F2D11D FBFC2245 95EA2AB7 9D09156C  
08A5A7CD 36E43D94 F1E3C978 37A79379 384D2A72 CE575E91 3F020301 0001  
% Key pair was generated at: 12:03:48 PST Dec 28 2002  
Key name: 102.cisco.com.server  
Usage: Encryption Key  
Key Data:  
307C300D 06092A86 4886F70D 01010105 00036B00 30680261 00BFD36E A1642BFC  
77C88F89 8A260840 213E122E E1AF1E24 AF39B984 DACA06BC C303AD77 95BB6B6C  
89CC6D13 B16CC4E3 45C101E4 61A13924 5559891A AB59B40D 826A5066 231B48D6  
AEB2B367 94F6C492 016F8778 74B368A2 BFD1424D 79C63C94 5F020301 0001  
102#
```

3. 호스트 이름을 확인합니다.

```
102(config)#ip host 101.cisco.com 20.1.1.1
```

4. 라우터 101에서 범용 키를 교환합니다.

```
101(config)#crypto key pubkey-chain rsa  
101(config-pubkey-chain)#named-key 102.cisco.com  
% Named public key resolved to ip address: 20.1.1.2  
101(config-pubkey-key)#key-string ?  
Enter a public key as a hexadecimal number ....
```

```
101(config-pubkey)##$6F70D 01010105 00034B00 30480241 00DB4FEB EF0C0D3D  
101(config-pubkey)##$26161BC F1AF337C E5F2D11D FBFC2245 95EA2AB7 9D09156C  
101(config-pubkey)##$1E3C978 37A79379 384D2A72 CE575E91 3F020301 0001  
101(config-pubkey)##quit  
101(config-pubkey-key)#exit
```

5. 라우터 102에서 범용 키를 교환합니다.

```
102(config)#crypto key pubkey-chain rsa  
102(config-pubkey-chain)#named-key 101.cisco.com  
% Named public key resolved to ip address: 20.1.1.1  
102(config-pubkey-key)#key-string  
Enter a public key as a hexadecimal number ....  
  
102(config-pubkey)##$6F70D 01010105 00034B00 30480241 00A7D24F E6E15787  
102(config-pubkey)##$DE96A4D C6B4D0F3 A7DDAD10 446EF83A 89D1115F 0C517118  
102(config-pubkey)##$A017B97 F85690EF EBCF3414 AB3E81F6 A5020301 0001  
102(config-pubkey)##quit  
102(config-pubkey-key)#exit
```

```
102(config-pubkey-chain)#exit  
102(config)#exit
```

문제 해결 명령

일부 **show** 명령은 출력 인터프리터 터미널에서 지원되는데(등록된 고객만), 이 터미널을 사용하면 show 명령 출력의 분석 결과를 볼 수 있습니다.

참고: debug 명령을 실행하기 전에 [디버그 명령에 대한 중요 정보를 참조하십시오.](#)

라우터 101 디버그:

```
101#  
101#  
101#  
101#  
*Dec 28 21:14:27.011: IPSEC(sa_request): ,  
  (key eng. msg.) OUTBOUND local= 20.1.1.1, remote= 20.1.1.2,  
  local_proxy= 20.1.1.1/255.255.255.255/47/0 (type=1),  
  remote_proxy= 20.1.1.2/255.255.255.255/47/0 (type=1),  
  protocol= ESP, transform= esp-des esp-sha-hmac ,  
  lifedur= 3600s and 4608000kb,  
  spi= 0xA12DDC39(2704137273), conn_id= 0, keysize= 0, flags= 0x400C  
*Dec 28 21:14:27.051: ISAKMP: received ke message (1/1)  
*Dec 28 21:14:27.051: ISAKMP: local port 500, remote port 500  
*Dec 28 21:14:27.099: ISAKMP: set new node 0 to QM_IDLE  
*Dec 28 21:14:27.099: ISAKMP (0:14): constructed NAT-T vendor-03 ID  
*Dec 28 21:14:27.099: ISAKMP (0:14): constructed NAT-T vendor-02 ID  
*Dec 28 21:14:27.099: ISAKMP (0:14): Input = IKE_MESG_FROM_IPSEC, IKE_SA_REQ_MM  
*Dec 28 21:14:27.099: ISAKMP (0:14): Old State = IKE_READY New State = IKE_I_MM1  
  
*Dec 28 21:14:27.099: ISAKMP (0:14): beginning Main Mode exchange  
*Dec 28 21:14:27.099: ISAKMP (0:14): sending packet to 20.1.1.2 my_port  
  500 peer_port 500 (I) MM_NO_STATE  
*Dec 28 21:14:27.343: ISAKMP (0:14): received packet from 20.1.1.2 dport  
  500 sport 500 (I) MM_NO_STATE  
*Dec 28 21:14:27.343: ISAKMP (0:14): Input = IKE_MESG_FROM_PEER, IKE_MM_EXCH  
*Dec 28 21:14:27.343: ISAKMP (0:14): Old State = IKE_I_MM1 New State = IKE_I_MM2  
  
*Dec 28 21:14:27.411: ISAKMP (0:14): processing SA payload. message ID = 0  
*Dec 28 21:14:27.411: ISAKMP (0:14): processing vendor id payload  
*Dec 28 21:14:27.411: ISAKMP (0:14): vendor ID seems Unity/DPD but bad major  
*Dec 28 21:14:27.411: ISAKMP (0:14): vendor ID is NAT-T  
*Dec 28 21:14:27.411: ISAKMP (0:14): Checking ISAKMP transform 1 against priority 1 policy  
*Dec 28 21:14:27.411: ISAKMP:      encryption DES-CBC  
*Dec 28 21:14:27.411: ISAKMP:      hash SHA  
*Dec 28 21:14:27.411: ISAKMP:      default group 1  
*Dec 28 21:14:27.411: ISAKMP:      auth RSA sig  
*Dec 28 21:14:27.411: ISAKMP:      life type in seconds  
*Dec 28 21:14:27.411: ISAKMP:      life duration (VPI) of 0x0 0x1 0x51 0x80  
*Dec 28 21:14:27.411: ISAKMP (0:14): Authentication method offered does not  
  match policy!  
*Dec 28 21:14:27.411: ISAKMP (0:14): atts are not acceptable. Next payload is 0  
*Dec 28 21:14:27.411: ISAKMP (0:14): Checking ISAKMP transform 1 against  
  priority 65535 policy  
*Dec 28 21:14:27.411: ISAKMP:      encryption DES-CBC  
*Dec 28 21:14:27.411: ISAKMP:      hash SHA  
*Dec 28 21:14:27.411: ISAKMP:      default group 1  
*Dec 28 21:14:27.411: ISAKMP:      auth RSA sig  
*Dec 28 21:14:27.411: ISAKMP:      life type in seconds
```

```

*Dec 28 21:14:27.411: ISAKMP:      life duration (VPI) of 0x0 0x1 0x51 0x80
*Dec 28 21:14:27.411: ISAKMP (0:14): atts are acceptable. Next payload is 0
*Dec 28 21:14:27.411: ISAKMP (0:14): processing vendor id payload
*Dec 28 21:14:27.411: ISAKMP (0:14): vendor ID seems Unity/DPD but bad major
*Dec 28 21:14:27.411: ISAKMP (0:14): vendor ID is NAT-T
*Dec 28 21:14:27.411: ISAKMP (0:14): Input = IKE_MESG_INTERNAL,
    IKE_PROCESS_MAIN_MODE
*Dec 28 21:14:27.411: ISAKMP (0:14): Old State = IKE_I_MM2
    New State = IKE_I_MM2

*Dec 28 21:14:27.503: ISAKMP (0:14): constructed HIS NAT-D
*Dec 28 21:14:27.503: ISAKMP (0:14): constructed MINE NAT-D
*Dec 28 21:14:27.503: ISAKMP (0:14): sending packet to 20.1.1.2 my_port
    500 peer_port 500 (I) MM_SA_SETUP
*Dec 28 21:14:27.503: ISAKMP (0:14): Input = IKE_MESG_INTERNAL,
    IKE_PROCESS_COMPLETE
*Dec 28 21:14:27.503: ISAKMP (0:14): Old State = IKE_I_MM2  New State = IKE_I_MM3

*Dec 28 21:14:27.763: ISAKMP (0:14): received packet from 20.1.1.2 dport
    500 sport 500 (I) MM_SA_SETUP
*Dec 28 21:14:27.763: ISAKMP (0:14): Input = IKE_MESG_FROM_PEER, IKE_MM_EXCH
*Dec 28 21:14:27.763: ISAKMP (0:14): Old State = IKE_I_MM3  New State = IKE_I_MM4

*Dec 28 21:14:27.811: ISAKMP (0:14): processing KE payload. message ID = 0
*Dec 28 21:14:27.811: ISAKMP (0:14): processing NONCE payload. message ID = 0
*Dec 28 21:14:27.811: ISAKMP (0:14): SKEYID state generated
*Dec 28 21:14:27.811: ISAKMP (0:14): processing vendor id payload
*Dec 28 21:14:27.811: ISAKMP (0:14): vendor ID is Unity
*Dec 28 21:14:27.811: ISAKMP (0:14): vendor ID is NAT-T
*Dec 28 21:14:27.811: ISAKMP (0:14): processing vendor id payload
*Dec 28 21:14:27.811: ISAKMP (0:14): vendor ID is DPD
*Dec 28 21:14:27.811: ISAKMP (0:14): vendor ID is NAT-T
*Dec 28 21:14:27.811: ISAKMP (0:14): processing vendor id payload
*Dec 28 21:14:27.811: ISAKMP (0:14): speaking to another IOS box!
*Dec 28 21:14:27.811: ISAKMP:received payload type 17
*Dec 28 21:14:27.811: ISAKMP (0:14): Detected NAT-D payload
*Dec 28 21:14:27.811: ISAKMP (0:14): NAT match MINE hash
*Dec 28 21:14:27.811: ISAKMP:received payload type 17
*Dec 28 21:14:27.811: ISAKMP (0:14): Detected NAT-D payload
*Dec 28 21:14:27.811: ISAKMP (0:14): NAT match HIS hash
*Dec 28 21:14:27.811: ISAKMP (0:14): Input = IKE_MESG_INTERNAL,
    IKE_PROCESS_MAIN_MODE
*Dec 28 21:14:27.811: ISAKMP (0:14): Old State = IKE_I_MM4
    New State = IKE_I_MM4

*Dec 28 21:14:27.903: ISAKMP (0:14): Send initial contact
*Dec 28 21:14:27.903: ISAKMP (0:14): SA is doing RSA signature
    authentication using id type ID_FQDN
*Dec 28 21:14:27.903: ISAKMP (14): ID payload
    next-payload : 9
    type : 2
    FQDN name : 101.cisco.com
    protocol : 17
    port : 0
    length : 17
*Dec 28 21:14:27.903: ISAKMP (14): Total payload length: 21
*Dec 28 21:14:27.903: ISAKMP (0:14): using the default keypair to sign
*Dec 28 21:14:28.003: ISAKMP (0:14): sending packet to 20.1.1.2
    my_port 500 peer_port 500 (I) MM_KEY_EXCH
*Dec 28 21:14:28.003: ISAKMP (0:14): Input = IKE_MESG_INTERNAL,
    IKE_PROCESS_COMPLETE
*Dec 28 21:14:28.003: ISAKMP (0:14): Old State = IKE_I_MM4  New State = IKE_I_MM5

*Dec 28 21:14:28.435: ISAKMP (0:14): received packet from 20.1.1.2 dport

```

```
500 sport 500 (I) MM_KEY_EXCH
*Dec 28 21:14:28.435: ISAKMP (0:14): Input = IKE_MESG_FROM_PEER, IKE_MM_EXCH
*Dec 28 21:14:28.435: ISAKMP (0:14): Old State = IKE_I_MM5 New State = IKE_I_MM6

*Dec 28 21:14:28.435: ISAKMP (0:14): received packet from 20.1.1.2 dport
500 sport 500 (I) MM_KEY_EXCH
*Dec 28 21:14:28.435: ISAKMP: set new node 226463539 to QM_IDLE
*Dec 28 21:14:28.435: ISAKMP (0:14): Unknown Input: state = IKE_I_MM6,
major, minor = IKE_MESG_FROM_PEER, IKE_INFO_DELETE

*Dec 28 21:14:28.435: %CRYPTO-6-IKMP_MODE_FAILURE: Processing of
Informational mode failed with peer at 20.1.1.2
*Dec 28 21:14:28.503: ISAKMP (0:14): processing ID payload. message ID = 0
*Dec 28 21:14:28.503: ISAKMP (14): Process ID payload
    type      : 2
    FQDN name : 102.cisco.com
    protocol   : 17
    port       : 0
    length     : 13
*Dec 28 21:14:28.503: ISAKMP (0:14): processing SIG payload. message ID = 0
*Dec 28 21:14:28.503: ISAKMP (14): sa->peer.name = , sa->peer_id.id.id_fqdn.fqdn =
102.cisco.com
*Dec 28 21:14:28.551: ISAKMP (0:14): SA has been authenticated with 20.1.1.2
*Dec 28 21:14:28.551: ISAKMP (0:14): IKE_DPD is enabled, initializing timers
*Dec 28 21:14:28.551: ISAKMP: Locking peer struct 0x18E6620, IKE refcount 2
for from crypto_ikmp_dpd_ike_init
*Dec 28 21:14:28.551: ISAKMP (0:14): Input = IKE_MESG_INTERNAL,
IKE_PROCESS_MAIN_MODE
*Dec 28 21:14:28.551: ISAKMP (0:14): Old State = IKE_I_MM6 New State = IKE_I_MM6

*Dec 28 21:14:28.551: ISAKMP (0:14): received packet from 20.1.1.2 dport 500 sport
500 (I) MM_KEY_EXCH
*Dec 28 21:14:28.551: ISAKMP: set new node 2089493550 to QM_IDLE
*Dec 28 21:14:28.551: ISAKMP (0:14): Unknown Input: state = IKE_I_MM6, major,
minor = IKE_MESG_FROM_PEER, IKE_INFO_DELETE

*Dec 28 21:14:28.611: ISAKMP (0:14): Input = IKE_MESG_INTERNAL,
IKE_PROCESS_COMPLETE
*Dec 28 21:14:28.611: ISAKMP (0:14): Old State = IKE_I_MM6
New State = IKE_P1_COMPLETE

*Dec 28 21:14:28.651: ISAKMP (0:14): beginning Quick Mode exchange,
M-ID of 543282640
*Dec 28 21:14:28.683: ISAKMP (0:14): sending packet to 20.1.1.2
my_port 500 peer_port 500 (I) QM_IDLE
*Dec 28 21:14:28.683: ISAKMP (0:14): Node 543282640, Input = IKE_MESG_INTERNAL,
IKE_INIT_QM
*Dec 28 21:14:28.683: ISAKMP (0:14): Old State = IKE_QM_READY
New State = IKE_QM_I_QM1
*Dec 28 21:14:28.683: ISAKMP (0:14): Input = IKE_MESG_INTERNAL,
IKE_PHASE1_COMPLETE
*Dec 28 21:14:28.683: ISAKMP (0:14): Old State = IKE_P1_COMPLETE
New State = IKE_P1_COMPLETE

*Dec 28 21:14:29.303: ISAKMP (0:14): received packet from 20.1.1.2
dport 500 sport 500 (I) QM_IDLE
*Dec 28 21:14:29.303: ISAKMP (0:14): processing HASH payload. message
ID = 543282640
*Dec 28 21:14:29.303: ISAKMP (0:14): processing SA payload. message
ID = 543282640
*Dec 28 21:14:29.303: ISAKMP (0:14): Checking IPSec proposal 1
*Dec 28 21:14:29.303: ISAKMP: transform 1, ESP_DES
*Dec 28 21:14:29.303: ISAKMP: attributes in transform:
*Dec 28 21:14:29.303: ISAKMP: encaps is 2
```

```

*Dec 28 21:14:29.303: ISAKMP:      SA life type in seconds
*Dec 28 21:14:29.303: ISAKMP:      SA life duration (basic) of 3600
*Dec 28 21:14:29.303: ISAKMP:      SA life type in kilobytes
*Dec 28 21:14:29.303: ISAKMP:      SA life duration (VPI) of 0x0 0x46 0x50 0x0
*Dec 28 21:14:29.303: ISAKMP:      authenticator is HMAC-SHA
*Dec 28 21:14:29.303: ISAKMP (0:14): atts are acceptable.
*Dec 28 21:14:29.303: IPSEC(validate_proposal_request): proposal part #1,
(key eng. msg.) INBOUND local= 20.1.1.1, remote= 20.1.1.2,
    local_proxy= 20.1.1.1/255.255.255.255/47/0 (type=1),
    remote_proxy= 20.1.1.2/255.255.255.255/47/0 (type=1),
    protocol= ESP, transform= esp-des esp-sha-hmac ,
    lifedur= 0s and 0kb,
    spi= 0x0(0), conn_id= 0, keysize= 0, flags= 0x4
*Dec 28 21:14:29.303: ISAKMP (0:14): processing NONCE payload.
message ID = 543282640
*Dec 28 21:14:29.303: ISAKMP (0:14): processing ID payload. message ID = 543282640
*Dec 28 21:14:29.303: ISAKMP (0:14): processing ID payload. message ID = 543282640
*Dec 28 21:14:29.351: ISAKMP: Locking peer struct 0x18E6620, IPSEC refcount 1
for for stuff_ke
*Dec 28 21:14:29.351: ISAKMP (0:14): Creating IPSec SAs
*Dec 28 21:14:29.351:           inbound SA from 20.1.1.2 to 20.1.1.1
    (proxy 20.1.1.2 to 20.1.1.1)
*Dec 28 21:14:29.351:           has spi 0xA12DDC39 and conn_id 2000 and flags 4
*Dec 28 21:14:29.351:           lifetime of 3600 seconds
*Dec 28 21:14:29.351:           lifetime of 4608000 kilobytes
*Dec 28 21:14:29.351:           has client flags 0x0
*Dec 28 21:14:29.351:           outbound SA from 20.1.1.1
    to 20.1.1.2 (proxy 20.1.1.1           to 20.1.1.2)
*Dec 28 21:14:29.351:           has spi -437189881 and conn_id 2001 and flags C
*Dec 28 21:14:29.351:           lifetime of 3600 seconds
*Dec 28 21:14:29.351:           lifetime of 4608000 kilobytes
*Dec 28 21:14:29.351:           has client flags 0x0
*Dec 28 21:14:29.351: ISAKMP (0:14): sending packet to 20.1.1.2 my_port
500 peer_port 500 (I) QM_IDLE
*Dec 28 21:14:29.351: ISAKMP (0:14): deleting node 543282640 error
    FALSE reason ""
*Dec 28 21:14:29.351: ISAKMP (0:14): Node 543282640, Input = IKE_MESG_FROM_PEER,
    IKE_QM_EXCH
*Dec 28 21:14:29.351: ISAKMP (0:14): Old State = IKE_QM_I_QM1
    New State = IKE_QM_PHASE2_COMPLETE
*Dec 28 21:14:29.371: IPSEC(key_engine): got a queue event...
*Dec 28 21:14:29.371: IPSEC(initialize_sas): ,
(key eng. msg.) INBOUND local= 20.1.1.1, remote= 20.1.1.2,
    local_proxy= 20.1.1.1/0.0.0.0/47/0 (type=1),
    remote_proxy= 20.1.1.2/0.0.0.0/47/0 (type=1),
    protocol= ESP, transform= esp-des esp-sha-hmac ,
    lifedur= 3600s and 4608000kb,
    spi= 0xA12DDC39(2704137273), conn_id= 2000, keysize= 0, flags= 0x4
*Dec 28 21:14:29.371: IPSEC(initialize_sas): ,
(key eng. msg.) OUTBOUND local= 20.1.1.1, remote= 20.1.1.2,
    local_proxy= 20.1.1.1/0.0.0.0/47/0 (type=1),
    remote_proxy= 20.1.1.2/0.0.0.0/47/0 (type=1),
    protocol= ESP, transform= esp-des esp-sha-hmac ,
    lifedur= 3600s and 4608000kb,
    spi= 0xE5F10307(3857777415), conn_id= 2001, keysize= 0, flags= 0xC
*Dec 28 21:14:29.371: IPSEC(add_mtree): src 20.1.1.1, dest 20.1.1.2, dest_port 0

*Dec 28 21:14:29.371: IPSEC(create_sa): sa created,
(sa) sa_dest= 20.1.1.1, sa_prot= 50,
    sa_spi= 0xA12DDC39(2704137273),
    sa_trans= esp-des esp-sha-hmac , sa_conn_id= 2000
*Dec 28 21:14:29.371: IPSEC(create_sa): sa created,
(sa) sa_dest= 20.1.1.2, sa_prot= 50,
    sa_spi= 0xE5F10307(3857777415),

```

```
sa_trans= esp-des esp-sha-hmac , sa_conn_id= 2001
```

라우터 102 디버그:

```
102#  
*Dec 28 21:18:12.111: ISAKMP (0:0): received packet from 20.1.1.1  
dport 500 sport 500 (N) NEW SA  
*Dec 28 21:18:12.111: ISAKMP: local port 500, remote port 500  
*Dec 28 21:18:12.147: ISAKMP (0:15): Input = IKE_MESG_FROM_PEER, IKE_MM_EXCH  
*Dec 28 21:18:12.147: ISAKMP (0:15): Old State = IKE_READY New State = IKE_R_MM1  
  
*Dec 28 21:18:12.187: ISAKMP (0:15): processing SA payload. message ID = 0  
*Dec 28 21:18:12.187: ISAKMP (0:15): processing vendor id payload  
*Dec 28 21:18:12.187: ISAKMP (0:15): vendor ID seems Unity/DPD but bad major  
*Dec 28 21:18:12.187: ISAKMP (0:15): vendor ID is NAT-T  
*Dec 28 21:18:12.187: ISAKMP (0:15): processing vendor id payload  
*Dec 28 21:18:12.187: ISAKMP (0:15): vendor ID seems Unity/DPD but bad major  
*Dec 28 21:18:12.187: ISAKMP (0:15): vendor ID is NAT-T  
*Dec 28 21:18:12.187: ISAKMP (0:15): Checking ISAKMP transform 1 against  
priority 1 policy  
*Dec 28 21:18:12.187: ISAKMP: encryption DES-CBC  
*Dec 28 21:18:12.187: ISAKMP: hash SHA  
*Dec 28 21:18:12.187: ISAKMP: default group 1  
*Dec 28 21:18:12.187: ISAKMP: auth RSA sig  
*Dec 28 21:18:12.187: ISAKMP: life type in seconds  
*Dec 28 21:18:12.187: ISAKMP: life duration (VPI) of 0x0 0x1 0x51 0x80  
*Dec 28 21:18:12.187: ISAKMP (0:15): Authentication method offered does not  
match policy!  
*Dec 28 21:18:12.187: ISAKMP (0:15): atts are not acceptable. Next payload is 0  
*Dec 28 21:18:12.187: ISAKMP (0:15): Checking ISAKMP transform 1 against  
priority 65535 policy  
*Dec 28 21:18:12.187: ISAKMP: encryption DES-CBC  
*Dec 28 21:18:12.187: ISAKMP: hash SHA  
*Dec 28 21:18:12.187: ISAKMP: default group 1  
*Dec 28 21:18:12.187: ISAKMP: auth RSA sig  
*Dec 28 21:18:12.187: ISAKMP: life type in seconds  
*Dec 28 21:18:12.187: ISAKMP: life duration (VPI) of 0x0 0x1 0x51 0x80  
*Dec 28 21:18:12.187: ISAKMP (0:15): atts are acceptable. Next payload is 0  
*Dec 28 21:18:12.187: ISAKMP (0:15): processing vendor id payload  
*Dec 28 21:18:12.187: ISAKMP (0:15): vendor ID seems Unity/DPD but bad major  
*Dec 28 21:18:12.187: ISAKMP (0:15): vendor ID is NAT-T  
*Dec 28 21:18:12.187: ISAKMP (0:15): processing vendor id payload  
*Dec 28 21:18:12.187: ISAKMP (0:15): vendor ID seems Unity/DPD but bad major  
*Dec 28 21:18:12.187: ISAKMP (0:15): vendor ID is NAT-T  
*Dec 28 21:18:12.187: ISAKMP (0:15): Input = IKE_MESG_INTERNAL,  
IKE_PROCESS_MAIN_MODE  
*Dec 28 21:18:12.187: ISAKMP (0:15): Old State = IKE_R_MM1 New State = IKE_R_MM1  
  
*Dec 28 21:18:12.255: ISAKMP (0:15): constructed NAT-T vendor-03 ID  
*Dec 28 21:18:12.255: ISAKMP (0:15): sending packet to 20.1.1.1 my_port  
500 peer_port 500 (R) MM_SA_SETUP  
*Dec 28 21:18:12.255: ISAKMP (0:15): Input = IKE_MESG_INTERNAL,  
IKE_PROCESS_COMPLETE  
*Dec 28 21:18:12.255: ISAKMP (0:15): Old State = IKE_R_MM1 New State = IKE_R_MM2  
  
*Dec 28 21:18:12.563: ISAKMP (0:15): received packet from 20.1.1.1 dport  
500 sport 500 (R) MM_SA_SETUP  
*Dec 28 21:18:12.563: ISAKMP (0:15): Input = IKE_MESG_FROM_PEER, IKE_MM_EXCH  
*Dec 28 21:18:12.563: ISAKMP (0:15): Old State = IKE_R_MM2 New State = IKE_R_MM3  
  
*Dec 28 21:18:12.619: ISAKMP (0:15): processing KE payload. message ID = 0  
*Dec 28 21:18:12.619: ISAKMP (0:15): processing NONCE payload. message ID = 0  
*Dec 28 21:18:12.695: ISAKMP (0:15): SKEYID state generated
```

```

*Dec 28 21:18:12.695: ISAKMP (0:15): processing vendor id payload
*Dec 28 21:18:12.695: ISAKMP (0:15): vendor ID is Unity
*Dec 28 21:18:12.695: ISAKMP (0:15): vendor ID is NAT-T
*Dec 28 21:18:12.695: ISAKMP (0:15): processing vendor id payload
*Dec 28 21:18:12.695: ISAKMP (0:15): vendor ID is DPD
*Dec 28 21:18:12.695: ISAKMP (0:15): vendor ID is NAT-T
*Dec 28 21:18:12.695: ISAKMP (0:15): processing vendor id payload
*Dec 28 21:18:12.695: ISAKMP (0:15): speaking to another IOS box!
*Dec 28 21:18:12.695: ISAKMP:received payload type 17
*Dec 28 21:18:12.695: ISAKMP (0:15): Detected NAT-D payload
*Dec 28 21:18:12.695: ISAKMP (0:15): NAT match MINE hash
*Dec 28 21:18:12.695: ISAKMP:received payload type 17
*Dec 28 21:18:12.695: ISAKMP (0:15): Detected NAT-D payload
*Dec 28 21:18:12.695: ISAKMP (0:15): NAT match HIS hash
*Dec 28 21:18:12.695: ISAKMP (0:15): Input = IKE_MESG_INTERNAL,
IKE_PROCESS_MAIN_MODE
*Dec 28 21:18:12.695: ISAKMP (0:15): Old State = IKE_R_MM3
New State = IKE_R_MM3

*Dec 28 21:18:12.735: ISAKMP (0:15): constructed HIS NAT-D
*Dec 28 21:18:12.735: ISAKMP (0:15): constructed MINE NAT-D
*Dec 28 21:18:12.735: ISAKMP (0:15): sending packet to 20.1.1.1
my_port 500 peer_port 500 (R)
MM_KEY_EXCH *Dec 28 21:18:12.735: ISAKMP (0:15): Input = IKE_MESG_INTERNAL,
IKE_PROCESS_COMPLETE
*Dec 28 21:18:12.735: ISAKMP (0:15): Old State = IKE_R_MM3 New State = IKE_R_MM4

*Dec 28 21:18:13.395: ISAKMP (0:15): received packet from 20.1.1.1 dport
500 sport 500 (R) MM_KEY_EXCH
*Dec 28 21:18:13.395: ISAKMP (0:15): Input = IKE_MESG_FROM_PEER, IKE_MM_EXCH
*Dec 28 21:18:13.395: ISAKMP (0:15): Old State = IKE_R_MM4 New State = IKE_R_MM5

*Dec 28 21:18:13.435: ISAKMP (0:15): processing ID payload. message ID = 0
*Dec 28 21:18:13.435: ISAKMP (15): Process ID payload
    type      : 2
    FQDN name : 101.cisco.com
    protocol   : 17
    port       : 0
    length     : 13
*Dec 28 21:18:13.435: ISAKMP (0:15): processing SIG payload. message ID = 0
*Dec 28 21:18:13.435: ISAKMP (15): sa->peer.name = ,
sa->peer_id.id.id_fqdn = 101.cisco.com
*Dec 28 21:18:13.567: ISAKMP:received payload type 14
*Dec 28 21:18:13.567: ISAKMP (0:15): processing NOTIFY INITIAL_CONTACT protocol 1
    spi 0, message ID = 0, sa = 1AD8D08
*Dec 28 21:18:13.567: ISAKMP (0:15): Process initial contact,
bring down existing phase 1 and 2 SA's with local 20.1.1.2 remote 20.1.1.1
remote port 500
*Dec 28 21:18:13.587: ISAKMP (0:15): SA has been authenticated with 20.1.1.1
*Dec 28 21:18:13.587: ISAKMP (0:15): IKE_DPD is enabled, initializing timers
*Dec 28 21:18:13.587: ISAKMP: Locking peer struct 0x18EA370, IKE refcount 2
for from crypto_ikmp_dpd_ike_init
*Dec 28 21:18:13.587: ISAKMP (0:15): Input = IKE_MESG_INTERNAL,
IKE_PROCESS_MAIN_MODE
*Dec 28 21:18:13.587: ISAKMP (0:15): Old State = IKE_R_MM5 New State = IKE_R_MM5

*Dec 28 21:18:13.599: IPSEC(key_engine): got a queue event...
*Dec 28 21:18:13.627: ISAKMP (0:15): SA is doing RSA signature authentication
using id type ID_FQDN
*Dec 28 21:18:13.627: ISAKMP (15): ID payload
    next-payload : 9
    type        : 2
    FQDN name   : 102.cisco.com
    protocol    : 17

```

```

port          : 0
length        : 17
*Dec 28 21:18:13.627: ISAKMP (15): Total payload length: 21
*Dec 28 21:18:13.627: ISAKMP (0:15): using the default keypair to sign
*Dec 28 21:18:13.731: ISAKMP (0:15): sending packet to 20.1.1.1 my_port
500 peer_port 500 (R) MM_KEY_EXCH
*Dec 28 21:18:13.731: ISAKMP (0:15): Input = IKE_MESG_INTERNAL,
IKE_PROCESS_COMPLETE
*Dec 28 21:18:13.731: ISAKMP (0:15): Old State = IKE_R_MM5
New State = IKE_P1_COMPLETE

*Dec 28 21:18:13.779: ISAKMP (0:15): Input = IKE_MESG_INTERNAL,
IKE_PHASE1_COMPLETE
*Dec 28 21:18:13.779: ISAKMP (0:15): Old State = IKE_P1_COMPLETE
New State = IKE_P1_COMPLETE

*Dec 28 21:18:14.215: ISAKMP (0:15): received packet from 20.1.1.1
dport 500 sport 500 (R) QM_IDLE
*Dec 28 21:18:14.215: ISAKMP: set new node 1098460553 to QM_IDLE
*Dec 28 21:18:14.215: ISAKMP (0:15): processing HASH payload.
message ID = 1098460553
*Dec 28 21:18:14.215: ISAKMP (0:15): processing SA payload.
message ID = 1098460553
*Dec 28 21:18:14.215: ISAKMP (0:15): Checking IPSec proposal 1
*Dec 28 21:18:14.215: ISAKMP: transform 1, ESP DES
*Dec 28 21:18:14.215: ISAKMP: attributes in transform:
*Dec 28 21:18:14.215: ISAKMP:      encaps is 2
*Dec 28 21:18:14.215: ISAKMP:      SA life type in seconds
*Dec 28 21:18:14.215: ISAKMP:      SA life duration (basic) of 3600
*Dec 28 21:18:14.215: ISAKMP:      SA life type in kilobytes
*Dec 28 21:18:14.215: ISAKMP:      SA life duration (VPI) of 0x0 0x46 0x50 0x0
*Dec 28 21:18:14.215: ISAKMP:      authenticator is HMAC-SHA
*Dec 28 21:18:14.215: ISAKMP (0:15): atts are acceptable.
*Dec 28 21:18:14.215: IPSEC(validate_proposal_request): proposal part #1,
(key eng. msg.) INBOUND local= 20.1.1.2, remote= 20.1.1.1,
local_proxy= 20.1.1.2/255.255.255.255/47/0 (type=1),
remote_proxy= 20.1.1.1/255.255.255.255/47/0 (type=1),
protocol= ESP, transform= esp-des esp-sha-hmac ,
lifedur= 0s and 0kb,
spi= 0x0(0), conn_id= 0, keysize= 0, flags= 0x4
*Dec 28 21:18:14.215: ISAKMP (0:15): processing NONCE payload.
message ID = 1098460553
*Dec 28 21:18:14.215: ISAKMP (0:15): processing ID payload.
message ID = 1098460553
*Dec 28 21:18:14.215: ISAKMP (0:15): processing ID payload.
message ID = 1098460553
*Dec 28 21:18:14.215: ISAKMP (0:15): asking for 1 spis from ipsec
*Dec 28 21:18:14.215: ISAKMP (0:15): Node 1098460553, Input = IKE_MESG_FROM_PEER,
IKE_QM_EXCH
*Dec 28 21:18:14.215: ISAKMP (0:15): Old State = IKE_QM_READY
New State = IKE_QM_SPI_STARVE
*Dec 28 21:18:14.235: IPSEC(key_engine): got a queue event...
*Dec 28 21:18:14.235: IPSEC(spi_response): getting spi 488964414 for SA
from 20.1.1.2      to 20.1.1.1      for prot 3
*Dec 28 21:18:14.267: ISAKMP: received ke message (2/1)
*Dec 28 21:18:14.547: ISAKMP (0:15): sending packet to 20.1.1.1 my_port
500 peer_port 500 (R) QM_IDLE

*Dec 28 21:18:14.547: ISAKMP (0:15): Node 1098460553, Input = IKE_MESG_FROM_IPSEC,
IKE_SPI_REPLY
*Dec 28 21:18:14.547: ISAKMP (0:15): Old State = IKE_QM_SPI_STARVE
New State = IKE_QM_R_QM2
*Dec 28 21:18:14.707: ISAKMP (0:15): received packet from 20.1.1.1
dport 500 sport 500 (R) QM_IDLE

```

```

*Dec 28 21:18:14.747: ISAKMP: Locking peer struct 0x18EA370, IPSEC
  refcount 1 for for stuff_ke
*Dec 28 21:18:14.747: ISAKMP (0:15): Creating IPSec SAs
*Dec 28 21:18:14.747:           inbound SA from 20.1.1.1 to 20.1.1.2
  (proxy 20.1.1.1 to 20.1.1.2)
*Dec 28 21:18:14.747:           has spi 0x1D25013E and conn_id 2000 and flags 4
*Dec 28 21:18:14.747:           lifetime of 3600 seconds
*Dec 28 21:18:14.747:           lifetime of 4608000 kilobytes
*Dec 28 21:18:14.747:           has client flags 0x0
*Dec 28 21:18:14.747:           outbound SA from 20.1.1.2           to 20.1.1.1
  (proxy 20.1.1.2           to 20.1.1.1      )
*Dec 28 21:18:14.747:           has spi -1829425422 and conn_id 2001 and flags C
*Dec 28 21:18:14.747:           lifetime of 3600 seconds
*Dec 28 21:18:14.747:           lifetime of 4608000 kilobytes
*Dec 28 21:18:14.747:           has client flags 0x0
*Dec 28 21:18:14.747: ISAKMP (0:15): deleting node 1098460553 error FALSE
  reason "quick mode done (await())"
*Dec 28 21:18:14.747: ISAKMP (0:15): Node 1098460553, Input = IKE_MESG_FROM_PEER,
  IKE_QM_EXCH
*Dec 28 21:18:14.747: ISAKMP (0:15): Old State = IKE_QM_R_QM2
  New State = IKE_QM_PHASE2_COMPLETE
*Dec 28 21:18:14.767: IPSEC(key_engine): got a queue event...
*Dec 28 21:18:14.767: IPSEC(initialize_sas): ,
  (key eng. msg.) INBOUND local= 20.1.1.2, remote= 20.1.1.1,
  local_proxy= 20.1.1.2/0.0.0.0/47/0 (type=1),
  remote_proxy= 20.1.1.1/0.0.0.0/47/0 (type=1),
  protocol= ESP, transform= esp-des esp-sha-hmac ,
  lifedur= 3600s and 4608000kb,
  spi= 0x1D25013E(488964414), conn_id= 2000, keysize= 0, flags= 0x4
*Dec 28 21:18:14.767: IPSEC(initialize_sas): ,
  (key eng. msg.) OUTBOUND local= 20.1.1.2, remote= 20.1.1.1,
  local_proxy= 20.1.1.2/0.0.0.0/47/0 (type=1),
  remote_proxy= 20.1.1.1/0.0.0.0/47/0 (type=1),
  protocol= ESP, transform= esp-des esp-sha-hmac ,
  lifedur= 3600s and 4608000kb,
  spi= 0x92F52EF2(2465541874), conn_id= 2001, keysize= 0, flags= 0xC
*Dec 28 21:18:14.767: IPSEC(add mtree): src 20.1.1.2, dest 20.1.1.1, dest_port 0

*Dec 28 21:18:14.767: IPSEC(create_sa): sa created,
  (sa) sa_dest= 20.1.1.2, sa_prot= 50,
  sa_spi= 0x1D25013E(488964414),
  sa_trans= esp-des esp-sha-hmac , sa_conn_id= 2000
*Dec 28 21:18:14.767: IPSEC(create_sa): sa created,
  (sa) sa_dest= 20.1.1.1, sa_prot= 50,
  sa_spi= 0x92F52EF2(2465541874),
  sa_trans= esp-des esp-sha-hmac , sa_conn_id= 2001

```

관련 정보

- [IPSec 지원 페이지](#)
- [Technical Support - Cisco Systems](#)