

Multicast voor routing - MSDP en PIM doorlopen

Inhoud

[Inleiding](#)

[Topologie](#)

[regelvlak](#)

[Bron-registratie \(stappen 1-3\)](#)

[Groep ontvangers \(stappen 4 - 11\)](#)

[R4 PIM RP Prunes off \(S,G\) Stap 12](#)

[Samenvatting](#)

[Gerelateerde informatie](#)

Inleiding

Dit document beschrijft de werking van Protocol Independent Multicast (PIM) en Multicast Source Discovery Protocol (MSDP) met het gebruik van een eenvoudige multicast topologie. Dit is handig om de controle-vlakte bediening en sequentie van gebeurtenissen van wanneer een bron wordt geregistreerd tot wanneer de ontvanger multicast pakketten begint te ontvangen.

Opmerking: Op apparaten die in dit document worden gebruikt, wordt Cisco IOS® versie 15.3M in een labomgeving uitgevoerd.

Topologie

Autonoom systeem AS65000 links bevat de multicast bron. R1 treedt op als First Hop Router (FHR) en zal de bron (10.1.1.1) registreren met het PIM Rendezvous Point (PIM RP) R3. R7 en R3 zijn iBGP burenen, en R3-R4 en R7-R6 zijn eBGP burenen. R7 en R6 zijn ingesteld als het voorkeurspad tussen de twee autonome systemen. In AS6499 heeft R5 een lokaal aangesloten ontvanger. R5 is ingesteld om R4 te gebruiken als PIM RP.

regelvlak

De video laat zien welke berichten worden verstuurd en wanneer. Bekijk deze video en de muziekopname voor gedetailleerde beschrijvingen bij elke stap.

Bron-registratie (stappen 1-3)

De bron begint met het verzenden van multicast gegevens naar 239.1.1.1. Na het ontvangen van deze gegevens neemt R1 (die de PIM Aangewezen Router (DR) voor het segment is) het multicastpakket in en bouwt een PIM registratiebericht.

Het registratiebericht is een eenvoudig PIM-pakket dat van R1 naar R3 wordt verzonden om de PIM RP van de bron te informeren.

```
R1#
*May 21 14:54:08.461: PIM(0): Check RP 10.10.10.10 into the (*, 239.1.1.1) entry
*May 21 14:54:08.461: PIM(0): Building Triggered (*,G) Join / (S,G,RP-bit) Prune message
for 239.1.1.1
*May 21 14:54:08.461: PIM(0): Adding register encap tunnel (Tunnel0) as forwarding
interface of (10.1.1.1, 239.1.1.1).
```

Nu, de PIM RP, R3 ontvangt het register bericht en reageert met register-stop. R3 stuurt ook een MSDP SA-bericht naar R4 via MSDP. De "A"-vlag op de route betekent dat hij kandidaat is voor MSDP-advertenties. De markering "P" geeft aan dat de markering is gesnoeid omdat u geen ontvanger of vertrekinterface voor de groep hebt.

```
R3#
*May 21 14:54:08.459: PIM(0): Received v2 Register on Ethernet1/0 from 10.0.12.1
*May 21 14:54:08.459:           for 10.1.1.1, group 239.1.1.1
*May 21 14:54:08.459: PIM(0): Check RP 10.10.10.10 into the (*, 239.1.1.1) entry
*May 21 14:54:08.459: PIM(0): Adding register decap tunnel (Tunnel1) as accepting
interface of (*, 239.1.1.1).
*May 21 14:54:08.459: PIM(0): Adding register decap tunnel (Tunnel1) as accepting
interface of (10.1.1.1, 239.1.1.1).
*May 21 14:54:08.459: PIM(0): Send v2 Register-Stop to 10.0.12.1 for 10.1.1.1,
group 239.1.1.1
```

```
R3#show ip mroute 239.1.1.1
IP Multicast Routing Table
Flags: D - Dense, S - Sparse, B - Bidir Group, s - SSM Group, C - Connected,
       L - Local, P - Pruned, R - RP-bit set, F - Register flag,
       T - SPT-bit set, J - Join SPT, M - MSDP created entry, E - Extranet,
       X - Proxy Join Timer Running, A - Candidate for MSDP Advertisement,
       U - URD, I - Received Source Specific Host Report,
       Z - Multicast Tunnel, z - MDT-data group sender,
       Y - Joined MDT-data group, y - Sending to MDT-data group,
       G - Received BGP C-Mroute, g - Sent BGP C-Mroute,
       Q - Received BGP S-A Route, q - Sent BGP S-A Route,
       V - RD & Vector, v - Vector
Outgoing interface flags: H - Hardware switched, A - Assert winner
Timers: Uptime/Expires
Interface state: Interface, Next-Hop or VCD, State/Mode

(*, 239.1.1.1), 00:00:33/stopped, RP 10.10.10.10, flags: SP
Incoming interface: Null, RPF nbr 0.0.0.0
Outgoing interface list: Null

(10.1.1.1, 239.1.1.1), 00:00:33/00:02:26, flags: PA
Incoming interface: Ethernet1/0, RPF nbr 10.0.37.7
Outgoing interface list: Null
```

```
R3#show ip msdp sa-cache
MSDP Source-Active Cache - 0 entries
R3#
*May 21 14:54:58.511: MSDP(0): (10.1.1.1/32, 239.1.1.1)
```

Hier ontvangt R1 het registratiepunt van R3.

```
*May 21 14:54:08.461: PIM(0): Received v2 Register-Stop on Ethernet0/0 from 10.10.10.10
*May 21 14:54:08.461: PIM(0):           for source 10.1.1.1, group 239.1.1.1
```

```
*May 21 14:54:08.461: PIM(0): Removing register encap tunnel (Tunnel0) as forwarding interface of (10.1.1.1, 239.1.1.1).
```

```
*May 21 14:54:08.461: PIM(0): Clear Registering flag to 10.10.10.10 for (10.1.1.1/32, 239.1.1.1)
```

Op R4 kan je zien dat er geen routestaat is, maar je hebt wel een MSDP SA.

```
R4#show ip mroute
```

```
*May 21 14:54:58.591: MSDP(0): (10.1.1.1/32, 239.1.1.1), accepted
```

```
R4#show ip mroute
```

```
IP Multicast Routing Table
```

```
Flags: D - Dense, S - Sparse, B - Bidir Group, s - SSM Group, C - Connected,
```

```
    L - Local, P - Pruned, R - RP-bit set, F - Register flag,
```

```
    T - SPT-bit set, J - Join SPT, M - MSDP created entry, E - Extranet,
```

```
    X - Proxy Join Timer Running, A - Candidate for MSDP Advertisement,
```

```
    U - URD, I - Received Source Specific Host Report,
```

```
    Z - Multicast Tunnel, z - MDT-data group sender,
```

```
    Y - Joined MDT-data group, y - Sending to MDT-data group,
```

```
    G - Received BGP C-Mroute, g - Sent BGP C-Mroute,
```

```
    Q - Received BGP S-A Route, q - Sent BGP S-A Route,
```

```
    V - RD & Vector, v - Vector
```

```
Outgoing interface flags: H - Hardware switched, A - Assert winner
```

```
Timers: Uptime/Expires
```

```
Interface state: Interface, Next-Hop or VCD, State/Mode
```

```
(* , 224.0.1.40), 00:35:32/00:02:31, RP 10.20.20.20, flags: SJCL
```

```
Incoming interface: Null, RPF nbr 0.0.0.0
```

```
Outgoing interface list:
```

```
    Ethernet1/0, Forward/Sparse, 00:23:16/00:02:36
```

```
    Loopback0, Forward/Sparse, 00:35:31/00:02:31
```

```
R4#show ip msdp sa-cache
```

```
MSDP Source-Active Cache - 1 entries
```

```
(10.1.1.1, 239.1.1.1), RP 10.10.10.10, BGP/AS 65000, 00:01:00/00:05:49, Peer 10.33.33.33
```

Groep ontvangers (stappen 4 - 11)

R5 ontvangt een IGMP treedt op op zijn interface en bouwt een PIM aan pakket (*,G sluit zich aan). De deelnemers worden naar R6 gestuurd.

```
R5#conf t
```

```
Enter configuration commands, one per line. End with CNTL/Z.
```

```
R5(config)#int e0/1
```

```
R5(config-if)#ip igmp join-group 239.1.1.1
```

```
R5(config-if)#
```

```
*May 21 14:56:43.234: PIM(0): Check RP 10.20.20.20 into the (*, 239.1.1.1) entry
```

```
*May 21 14:56:43.234: PIM(0): Building Triggered (*,G) Join / (S,G,RP-bit) Prune message for 239.1.1.1
```

```
*May 21 14:56:43.234: PIM(0): Building Triggered (*,G) Join / (S,G,RP-bit) Prune message for 239.1.1.1
```

```
*May 21 14:56:43.234: PIM(0): Insert (*,239.1.1.1) join in nbr 10.0.56.6's queue
```

```
*May 21 14:56:43.246: PIM(0): Building Join/Prune packet for nbr 10.0.56.6
```

```
*May 21 14:56:43.246: PIM(0): Adding v2 (10.20.20.20/32, 239.1.1.1), WC-bit, RPT-bit, S-bit Join
```

```
*May 21 14:56:43.246: PIM(0): Send v2 join/prune to 10.0.56.6 (Ethernet0/0)
```

R6 ontvangt de (*,G) PIM-verbinding van R5 en stuurt (*,G) mee naar R4 PIM RP.

R6#
*May 21 14:56:43.248: PIM(0): Received v2 Join/Prune on Ethernet2/0 from 10.0.56.5, to us
May 21 14:56:43.248: PIM(0): Join-list: (, 239.1.1.1), RPT-bit set, WC-bit set, S-bit set
May 21 14:56:43.248: PIM(0): Check RP 10.20.20.20 into the (, 239.1.1.1) entry
May 21 14:56:43.248: PIM(0): Building Triggered (,G) Join / (S,G,RP-bit) Prune message for 239.1.1.1
May 21 14:56:43.248: PIM(0): Add Ethernet2/0/10.0.56.5 to (, 239.1.1.1), Forward state, by PIM *G Join
May 21 14:56:43.248: PIM(0): Building Triggered (,G) Join / (S,G,RP-bit) Prune message for 239.1.1.1
May 21 14:56:43.248: PIM(0): Insert (,239.1.1.1) join in nbr 10.0.46.4's queue
*May 21 14:56:43.248: PIM(0): Building Join/Prune packet for nbr 10.0.46.4
*May 21 14:56:43.248: PIM(0): Adding v2 (10.20.20.20/32, 239.1.1.1), WC-bit, RPT-bit, S-bit Join
*May 21 14:56:43.248: PIM(0): Send v2 join/prune to 10.0.46.4 (Ethernet1/0)
R4 PIM RP ontvangt de (*,G) aansluiting bij R6. Het stuurt vervolgens een (S,G) aansluiting bij de bron 10.1.1.1, die teruggaat naar R6.

R4#
*May 21 14:56:43.331: PIM(0): Received v2 Join/Prune on Ethernet1/0 from 10.0.46.6, to us
May 21 14:56:43.331: PIM(0): Join-list: (, 239.1.1.1), RPT-bit set, WC-bit set, S-bit set
May 21 14:56:43.331: PIM(0): Check RP 10.20.20.20 into the (, 239.1.1.1) entry
May 21 14:56:43.331: PIM(0): Adding register decap tunnel (Tunnel1) as accepting interface of (, 239.1.1.1).
May 21 14:56:43.331: PIM(0): Add Ethernet1/0/10.0.46.6 to (, 239.1.1.1), Forward state, by PIM *G Join
*May 21 14:56:43.331: PIM(0): Adding register decap tunnel (Tunnel1) as accepting interface of (10.1.1.1, 239.1.1.1).
*May 21 14:56:43.331: PIM(0): Insert (10.1.1.1,239.1.1.1) join in nbr 10.0.46.6's queue
R4#
*May 21 14:56:43.331: PIM(0): Building Join/Prune packet for nbr 10.0.46.6
*May 21 14:56:43.331: PIM(0): Adding v2 (10.1.1.1/32, 239.1.1.1), S-bit Join
*May 21 14:56:43.331: PIM(0): Send v2 join/prune to 10.0.46.6 (Ethernet1/0)

R6 ontvangt de (S,G) toetreedt van R4 en stuurt vervolgens een (S,G) aansluiting bij R7 in AS65000. Wanneer het (S,G) lid wordt ontvangen van R4, stuurt R6 een duim (SGR) naar R4 (STAP 9). Dit gebeurt om dubbele pakketten bij R4 te voorkomen.

*May 21 14:56:43.248: PIM(0): Received v2 Join/Prune on Ethernet1/0 from 10.0.46.4, to us
*May 21 14:56:43.248: PIM(0): Join-list: (10.1.1.1/32, 239.1.1.1), S-bit set
*May 21 14:56:43.248: PIM(0): Add Ethernet1/0/10.0.46.4 to (10.1.1.1, 239.1.1.1), Forward state, by PIM SG Join
*May 21 14:56:43.248: PIM(0): Insert (10.1.1.1,239.1.1.1) join in nbr 10.0.67.7's queue
R6#
*May 21 14:56:43.248: PIM(0): Building Join/Prune packet for nbr 10.0.67.7
*May 21 14:56:43.248: PIM(0): Adding v2 (10.1.1.1/32, 239.1.1.1), S-bit Join
*May 21 14:56:43.248: PIM(0): Send v2 join/prune to 10.0.67.7 (Ethernet0/0)
R6#
*May 21 14:56:44.476: PIM(0): Insert (10.1.1.1,239.1.1.1) sgr prune in nbr 10.0.46.4's queue
*May 21 14:56:44.476: PIM(0): Building Join/Prune packet for nbr 10.0.46.4
*May 21 14:56:44.476: PIM(0): Adding v2 (10.1.1.1/32, 239.1.1.1), RPT-bit, S-bit Prune
*May 21 14:56:44.476: PIM(0): Send v2 join/prune to 10.0.46.4 (Ethernet1/0)

R7 ontvangt de (S,G) toetreedt van R6 en stuurt vervolgens (S,G) toe aan R2 volgend op de route

naar de bron.

```
R7#
*May 21 14:56:43.241: PIM(0): Received v2 Join/Prune on Ethernet0/0 from 10.0.67.6,
to us
*May 21 14:56:43.241: PIM(0): Join-list: (10.1.1.1/32, 239.1.1.1), S-bit set
*May 21 14:56:43.241: PIM(0): Check RP 10.10.10.10 into the (*, 239.1.1.1) entry
*May 21 14:56:43.241: PIM(0): Building Triggered (*,G) Join / (S,G,RP-bit) Prune message
for 239.1.1.1
*May 21 14:56:43.241: PIM(0): Add Ethernet0/0/10.0.67.6 to (10.1.1.1, 239.1.1.1),
Forward state, by PIM SG Join
*May 21 14:56:43.241: PIM(0): Insert (10.1.1.1,239.1.1.1) join in nbr 10.0.27.2's queue
*May 21 14:56:43.241: PIM(0): Building Join/Prune packet for nbr 10.0.27.2
R7#
*May 21 14:56:43.241: PIM(0): Adding v2 (10.1.1.1/32, 239.1.1.1), S-bit Join
*May 21 14:56:43.241: PIM(0): Send v2 join/prune to 10.0.27.2 (Ethernet2/0)
```

```
R7#show ip mroute
IP Multicast Routing Table
Flags: D - Dense, S - Sparse, B - Bidir Group, s - SSM Group, C - Connected,
L - Local, P - Pruned, R - RP-bit set, F - Register flag,
T - SPT-bit set, J - Join SPT, M - MSDP created entry, E - Extranet,
X - Proxy Join Timer Running, A - Candidate for MSDP Advertisement,
U - URD, I - Received Source Specific Host Report,
Z - Multicast Tunnel, z - MDT-data group sender,
Y - Joined MDT-data group, y - Sending to MDT-data group,
G - Received BGP C-Mroute, g - Sent BGP C-Mroute,
Q - Received BGP S-A Route, q - Sent BGP S-A Route,
V - RD & Vector, v - Vector
Outgoing interface flags: H - Hardware switched, A - Assert winner
Timers: Uptime/Expires
Interface state: Interface, Next-Hop or VCD, State/Mode

(*, 239.1.1.1), 00:03:33/stopped, RP 10.10.10.10, flags: SP
Incoming interface: Ethernet1/0, RPF nbr 10.0.37.3
Outgoing interface list: Null
```

```
(10.1.1.1, 239.1.1.1), 00:03:33/00:02:56, flags: T
Incoming interface: Ethernet2/0, RPF nbr 10.0.27.2
Outgoing interface list:
Ethernet0/0, Forward/Sparse, 00:03:33/00:02:53
```

R2 ontvangt de (S,G) toetreedt van R7 en stuurt vervolgens (S,G) toe aan R1 volgend op de route naar de bron

```
R2#
*May 21 14:56:43.253: PIM(0): Received v2 Join/Prune on Ethernet1/0 from 10.0.27.7,
to us
*May 21 14:56:43.253: PIM(0): Join-list: (10.1.1.1/32, 239.1.1.1), S-bit set
*May 21 14:56:43.253: PIM(0): Check RP 10.10.10.10 into the (*, 239.1.1.1) entry
*May 21 14:56:43.253: PIM(0): Building Triggered (*,G) Join / (S,G,RP-bit) Prune
message for 239.1.1.1
*May 21 14:56:43.253: PIM(0): Add Ethernet1/0/10.0.27.7 to (10.1.1.1, 239.1.1.1),
Forward state, by PIM SG Join
*May 21 14:56:43.253: PIM(0): Insert (10.1.1.1,239.1.1.1) join in nbr 10.0.12.1's queue
*May 21 14:56:43.253: PIM(0): Building Join/Prune packet for nbr 10.0.12.1
R2#
*May 21 14:56:43.253: PIM(0): Adding v2 (10.1.1.1/32, 239.1.1.1), S-bit Join
*May 21 14:56:43.253: PIM(0): Send v2 join/prune to 10.0.12.1 (Ethernet0/0)
```

```
R2#show ip mroute
```

IP Multicast Routing Table

Flags: D - Dense, S - Sparse, B - Bidir Group, s - SSM Group, C - Connected,
L - Local, P - Pruned, R - RP-bit set, F - Register flag,
T - SPT-bit set, J - Join SPT, M - MSDP created entry, E - Extranet,
X - Proxy Join Timer Running, A - Candidate for MSDP Advertisement,
U - URD, I - Received Source Specific Host Report,
Z - Multicast Tunnel, z - MDT-data group sender,
Y - Joined MDT-data group, y - Sending to MDT-data group,
G - Received BGP C-Mroute, g - Sent BGP C-Mroute,
Q - Received BGP S-A Route, q - Sent BGP S-A Route,
V - RD & Vector, v - Vector

Outgoing interface flags: H - Hardware switched, A - Assert winner

Timers: Uptime/Expires

Interface state: Interface, Next-Hop or VCD, State/Mode

(* , 239.1.1.1), 00:01:27/stopped, RP 10.10.10.10, flags: SP

Incoming interface: Ethernet1/0, RPF nbr 10.0.27.7

Outgoing interface list: Null

(10.1.1.1, 239.1.1.1), 00:01:27/00:01:32, flags: T

Incoming interface: Ethernet0/0, RPF nbr 10.0.12.1

Outgoing interface list:

Ethernet1/0, Forward/Sparse, 00:01:27/00:03:01

R1 ontvangt het (S,G) lid van R2 en voegt de interface toe aan de vertrekkende interfacelijst

*May 21 14:56:43.261: PIM(0): Received v2 Join/Prune on Ethernet0/0 from 10.0.12.2,
to us

*May 21 14:56:43.261: PIM(0): Join-list: (10.1.1.1/32, 239.1.1.1), S-bit set

*May 21 14:56:43.261: PIM(0): Add Ethernet0/0/10.0.12.2 to (10.1.1.1, 239.1.1.1),

Forward state, by PIM SG Join

R1#show ip mroute

IP Multicast Routing Table

Flags: D - Dense, S - Sparse, B - Bidir Group, s - SSM Group, C - Connected,
L - Local, P - Pruned, R - RP-bit set, F - Register flag,
T - SPT-bit set, J - Join SPT, M - MSDP created entry, E - Extranet,
X - Proxy Join Timer Running, A - Candidate for MSDP Advertisement,
U - URD, I - Received Source Specific Host Report,
Z - Multicast Tunnel, z - MDT-data group sender,
Y - Joined MDT-data group, y - Sending to MDT-data group,
G - Received BGP C-Mroute, g - Sent BGP C-Mroute,
Q - Received BGP S-A Route, q - Sent BGP S-A Route,
V - RD & Vector, v - Vector

Outgoing interface flags: H - Hardware switched, A - Assert winner

Timers: Uptime/Expires

Interface state: Interface, Next-Hop or VCD, State/Mode

(* , 239.1.1.1), 00:03:25/stopped, RP 10.10.10.10, flags: SPF

Incoming interface: Ethernet0/0, RPF nbr 10.0.12.2

Outgoing interface list: Null

(10.1.1.1, 239.1.1.1), 00:03:25/00:03:24, flags: FT

Incoming interface: Ethernet0/1, RPF nbr 0.0.0.0

Outgoing interface list:

Ethernet0/0, Forward/Sparse, 00:00:50/00:02:39

Op dit punt stroomt de data van de bron tot de ontvanger. Na ontvangst van een gegevenspakket zal R5 van de (*,G) boom overschakelen naar de (S,G) boom.

R5#

*May 21 14:56:44.494: PIM(0): Insert (10.1.1.1,239.1.1.1) join in nbr 10.0.56.6's queue

```
*May 21 14:56:44.498: PIM(0): Building Join/Prune packet for nbr 10.0.56.6
*May 21 14:56:44.498: PIM(0): Adding v2 (10.1.1.1/32, 239.1.1.1), S-bit Join
*May 21 14:56:44.498: PIM(0): Send v2 join/prune to 10.0.56.6 (Ethernet0/0)
```

```
R5#show ip mroute
```

```
IP Multicast Routing Table
```

```
Flags: D - Dense, S - Sparse, B - Bidir Group, s - SSM Group, C - Connected,
       L - Local, P - Pruned, R - RP-bit set, F - Register flag,
       T - SPT-bit set, J - Join SPT, M - MSDP created entry, E - Extranet,
       X - Proxy Join Timer Running, A - Candidate for MSDP Advertisement,
       U - URD, I - Received Source Specific Host Report,
       Z - Multicast Tunnel, z - MDT-data group sender,
       Y - Joined MDT-data group, y - Sending to MDT-data group,
       G - Received BGP C-Mroute, g - Sent BGP C-Mroute,
       Q - Received BGP S-A Route, q - Sent BGP S-A Route,
       V - RD & Vector, v - Vector
```

```
Outgoing interface flags: H - Hardware switched, A - Assert winner
```

```
Timers: Uptime/Expires
```

```
Interface state: Interface, Next-Hop or VCD, State/Mode
```

```
(* , 239.1.1.1), 00:02:47/00:00:14, RP 10.20.20.20, flags: SJCL
```

```
Incoming interface: Ethernet0/0, RPF nbr 10.0.56.6
```

```
Outgoing interface list:
```

```
Ethernet0/1, Forward/Sparse, 00:02:47/00:02:14
```

```
(10.1.1.1, 239.1.1.1), 00:02:45/00:00:14, flags: LJT
```

```
Incoming interface: Ethernet0/0, RPF nbr 10.0.56.6
```

```
Outgoing interface list:
```

```
Ethernet0/1, Forward/Sparse, 00:02:45/00:02:14
```

R6 ontvangt de (S,G) verbinding van R5 en stuurt de gegevenspakketten van E2/0 naar R5 door.

```
R6#
```

```
*May 21 14:56:44.496: PIM(0): Received v2 Join/Prune on Ethernet2/0 from 10.0.56.5,
to us
```

```
*May 21 14:56:44.496: PIM(0): Join-list: (10.1.1.1/32, 239.1.1.1), S-bit set
```

```
*May 21 14:56:44.496: PIM(0): Update Ethernet2/0/10.0.56.5 to (10.1.1.1, 239.1.1.1),
Forward state, by PIM SG Join
```

```
*May 21 14:56:49.056: PIM(0): Received v2 Join/Prune on Ethernet1/0 from 10.0.46.4,
to us
```

```
*May 21 14:56:49.056: PIM(0): Prune-list: (10.1.1.1/32, 239.1.1.1)
```

```
*May 21 14:56:49.056: PIM(0): Prune Ethernet1/0/239.1.1.1 from (10.1.1.1/32, 239.1.1.1)
- deleted
```

```
R6#show ip mroute
```

```
IP Multicast Routing Table
```

```
Flags: D - Dense, S - Sparse, B - Bidir Group, s - SSM Group, C - Connected,
       L - Local, P - Pruned, R - RP-bit set, F - Register flag,
       T - SPT-bit set, J - Join SPT, M - MSDP created entry, E - Extranet,
       X - Proxy Join Timer Running, A - Candidate for MSDP Advertisement,
       U - URD, I - Received Source Specific Host Report,
       Z - Multicast Tunnel, z - MDT-data group sender,
       Y - Joined MDT-data group, y - Sending to MDT-data group,
       G - Received BGP C-Mroute, g - Sent BGP C-Mroute,
       Q - Received BGP S-A Route, q - Sent BGP S-A Route,
       V - RD & Vector, v - Vector
```

```
Outgoing interface flags: H - Hardware switched, A - Assert winner
```

```
Timers: Uptime/Expires
```

```
Interface state: Interface, Next-Hop or VCD, State/Mode
```

```
(* , 239.1.1.1), 00:03:43/00:02:42, RP 10.20.20.20, flags: S
```

```
Incoming interface: Ethernet1/0, RPF nbr 10.0.46.4
```

```
Outgoing interface list:
  Ethernet2/0, Forward/Sparse, 00:03:43/00:02:42
(10.1.1.1, 239.1.1.1), 00:03:43/00:02:46, flags: T
Incoming interface: Ethernet0/0, RPF nbr 10.0.67.7
Outgoing interface list:
  Ethernet2/0, Forward/Sparse, 00:03:43/00:02:44
```

R4 PIM RP Prunes off (S,G) Stap 12

Ten slotte stuurt R4 PIM een duun (S,G) naar R6. Merk op dat de "M" vlag op de route aanwezig is (MSDP Created entry).

```
R4#
*May 21 14:56:44.559: PIM(0): Received v2 Join/Prune on Ethernet1/0 from 10.0.46.6,
to us
*May 21 14:56:44.559: PIM(0): Prune-list: (10.1.1.1/32, 239.1.1.1) RPT-bit set
*May 21 14:56:44.579: PIM(0): Removing register decap tunnel (Tunnel1) as accepting
interface of (10.1.1.1, 239.1.1.1).
*May 21 14:56:44.579: PIM(0): Installing Ethernet1/0 as accepting interface for
(10.1.1.1, 239.1.1.1).

*May 21 14:56:46.107: MSDP(0): (10.1.1.1/32, 239.1.1.1), accepted

*May 21 14:56:49.139: PIM(0): Insert (10.1.1.1,239.1.1.1) prune in nbr 10.0.46.6's queue
*May 21 14:56:49.139: PIM(0): Building Join/Prune packet for nbr 10.0.46.6
*May 21 14:56:49.139: PIM(0): Adding v2 (10.1.1.1/32, 239.1.1.1), S-bit Prune
*May 21 14:56:49.139: PIM(0): Send v2 join/prune to 10.0.46.6 (Ethernet1/0)
```

```
R4#show ip mroute
IP Multicast Routing Table
Flags: D - Dense, S - Sparse, B - Bidir Group, s - SSM Group, C - Connected,
  L - Local, P - Pruned, R - RP-bit set, F - Register flag,
  T - SPT-bit set, J - Join SPT, M - MSDP created entry, E - Extranet,
  X - Proxy Join Timer Running, A - Candidate for MSDP Advertisement,
  U - URD, I - Received Source Specific Host Report,
  Z - Multicast Tunnel, z - MDT-data group sender,
  Y - Joined MDT-data group, y - Sending to MDT-data group,
  G - Received BGP C-Mroute, g - Sent BGP C-Mroute,
  Q - Received BGP S-A Route, q - Sent BGP S-A Route,
  V - RD & Vector, v - Vector
```

```
Outgoing interface flags: H - Hardware switched, A - Assert winner
Timers: Uptime/Expires
Interface state: Interface, Next-Hop or VCD, State/Mode
```

```
(* , 239.1.1.1), 00:02:15/00:03:12, RP 10.20.20.20, flags: S
Incoming interface: Null, RPF nbr 0.0.0.0
Outgoing interface list:
  Ethernet1/0, Forward/Sparse, 00:02:15/00:03:12
```

```
(10.1.1.1, 239.1.1.1), 00:02:15/00:02:46, flags: PMT
Incoming interface: Ethernet1/0, RPF nbr 10.0.46.6
Outgoing interface list: Null
```

Hier wordt de uitgaande interface (OIF) E1/0 tot R4 van R6 verwijderd.

```
R6#
*May 21 14:56:49.056: PIM(0): Received v2 Join/Prune on Ethernet1/0 from 10.0.46.4, to us
*May 21 14:56:49.056: PIM(0): Prune-list: (10.1.1.1/32, 239.1.1.1)
*May 21 14:56:49.056: PIM(0): Prune Ethernet1/0/239.1.1.1 from (10.1.1.1/32, 239.1.1.1)
- deleted
```


Samenvatting

MSDP biedt een methode voor het onderling verbinden van verschillende PIM-domeinen die elk hun eigen RP gebruiken. Het wordt ook vaak gebruikt voor de uitvoering van "Anycast RP", die niet in dit document is opgenomen. MSDP en PIM werken samen om een ontvanger in één domein in staat te stellen om verkeer van een bron in een ander domein te ontvangen. MSDP SA-berichten maken het mogelijk dat de andere RP's over bronnen in een ander PIM-domein leren, terwijl PIM wordt gebruikt om de multicast-boom te bouwen.

Raadpleeg voor meer informatie over de protocolbewerkingen de RFC's die in de corresponderende informatie zijn vermeld.

Gerelateerde informatie

- PIM RFC

<https://tools.ietf.org/html/rfc4601>

- MSDP RFC

<https://tools.ietf.org/html/rfc3618>