

ASA/PIX 7.x及更高版本 : LAN到LAN和EasyVPN IPSec隧道终止在同样接口配置示例

目录

[简介](#)
[先决条件](#)
[要求](#)
[使用的组件](#)
[规则](#)
[配置](#)
[网络图](#)
[配置](#)
[验证](#)
[故障排除](#)
[故障排除命令](#)
[相关信息](#)

[简介](#)

本文提供了一个示例配置，以介绍如何使 HUB ASA 在相同接口上接受站点到站点隧道和 Easy VPN IPSec 连接。Cisco ASA 5520 和 Cisco 自适应安全设备 (ASA) 5505 之间的 IPsec 使用带有网络扩展模式 (NEM) 的 Easy VPN。

[先决条件](#)

[要求](#)

本文档没有任何特定的要求。

[使用的组件](#)

本文档中的信息基于以下软件和硬件版本：

- 运行 7.x 版本及更高版本的 ASA 5500 系列 (集线器) **注意**：HUB ASA 配置也可与运行 7.x 及更高版本的 PIX 安全设备 515、515E、525 和 535 一起使用
- 运行 7.x 版本及更高版本的 Easy VPN ASA 5505
- 运行 7.x 版本及更高版本的 PIX 安全工具 515、515E、525 和 535

本文档中的信息都是基于特定实验室环境中的设备编写的。本文档中使用的所有设备最初均采用原始 (默认) 配置。如果您使用的是真实网络，请确保您已经了解所有命令的潜在影响。

规则

有关文档约定的更多信息，请参考 [Cisco 技术提示约定](#)。


配置

本部分提供了可用于配置本文所述功能的信息。

注意：要获取有关本部分中所使用命令的更多信息，可使用[命令查找工具](#)（仅限[已注册客户](#)）。

网络图

本文档使用以下网络设置：



注意：此配置中使用的IP编址方案在Internet上不可合法路由。这些地址是在实验室环境中使用的[RFC 1918 地址](#)。

配置

本文档使用以下配置：

- [HUB ASA](#)
- [Easy VPN 客户机 ASA 5505](#)
- [PIX](#)

HUB ASA
ASA Version 8.0(2) ! hostname ciscoasa enable password 8Ry2YjIyt7RRXU24 encrypted names !

```
interface Ethernet0/0
nameif outside
security-level 0
ip address 10.1.1.1 255.255.255.0
!
interface Ethernet0/1
nameif inside
security-level 100
ip address 192.168.2.1 255.255.255.0
!
!--- Output Suppressed. !--- Access-list for interesting
traffic (Site to Site) to be !--- encrypted between hub
ASA and spoke (PIX) networks. access-list
outside_cryptomap_20 extended permit ip 192.168.2.0
255.255.255.0 192.168.1.0 255.255.255.0 !--- Access-list
for interesting traffic to be !--- encrypted between hub
ASA and spoke easy vpn client ASA networks. access-list
ezvpn1 extended permit ip 192.168.2.0 255.255.255.0
192.168.3.0 255.255.255.0 !--- Access-list for traffic
to bypass the network address !--- translation (NAT)
process. access-list nonat extended permit ip
192.168.2.0 255.255.255.0 192.168.1.0 255.255.255.0
access-list nonat extended permit ip 192.168.2.0
255.255.255.0 192.168.3.0 255.255.255.0 !--- Output
Suppressed. !--- Specify the NAT configuration. !--- NAT
0 prevents NAT for the ACL defined in this
configuration. !--- The nat 1 command specifies NAT for
all other traffic. nat-control global (outside) 1
interface nat (inside) 0 access-list nonat nat (inside)
1 0.0.0.0 0.0.0.0 route outside 0.0.0.0 0.0.0.0 10.1.1.2
1 !--- Output Suppressed. !--- Configuration of IPsec
Phase 2 crypto ipsec transform-set myset esp-3des esp-
sha-hmac !--- IPsec configuration for the dynamic LAN-
to-LAN tunnel crypto dynamic-map ezvpn 30 set transform-
set myset !--- IPsec configuration for the static LAN-
to-LAN tunnel crypto map outside_map 20 match address
outside_cryptomap_20 crypto map outside_map 20 set peer
172.16.1.1 crypto map outside_map 20 set transform-set
myset !--- IPsec configuration that binds dynamic map to
crypto map crypto map outside_map 65535 ipsec-isakmp
dynamic ezvpn !--- Crypto map applied to the outside
interface of the ASA crypto map outside_map interface
outside isakmp enable outside !--- PHASE 1 CONFIGURATION
---! !--- This configuration uses isakmp policy 1. !---
These configuration commands !--- define the Phase 1
policies that are used. crypto isakmp policy 10
authentication pre-share encryption 3des hash sha group
2 lifetime 86400 !--- Output Suppressed. !--- This
defines the group policy you use with Easy VPN. !---
Specify the networks that can pass through !--- the
tunnel and that you want to !--- use network extension
mode. group-policy tunnel internal group-policy tunnel
attributes nem enable !--- The username and password
associated with !--- this VPN connection are defined
here. You !--- can also use AAA for this function.
username cisco password fflIRPGpDSOJh9YLq encrypted
tunnel-group 172.16.1.1 type ipsec-l2l tunnel-group
172.16.1.1 ipsec-attributes pre-shared-key * !--- The
tunnel-group commands bind the configurations !--- !
defined in this configuration to the tunnel that is !--- !
used for Easy VPN. This tunnel name is the one !--- !
specified on the remote side. tunnel-group mytunnel type
remote-access tunnel-group mytunnel general-attributes
default-group-policy tunnel !--- Defines the pre-shared
```

```
key used for !--- IKE authentication for the dynamic
tunnel. tunnel-group mytunnel ipsec-attributes pre-
shared-key * prompt hostname context
Cryptochecksum:e148bf43d04906f5db41fc6f90c52d34 : end
```

Easy VPN 客户机 - ASA 5505

```
ASA Version 7.2(2)
!
hostname ciscoasa
domain-name default.domain.invalid
enable password 8Ry2YjIyt7RRXU24 encrypted
names
!
interface Vlan1
 nameif outside
 security-level 0
 ip address 172.16.2.2 255.255.255.0
!
interface Vlan2
 nameif inside
 security-level 100
 ip address 192.168.3.1 255.255.255.0
!
interface Ethernet0/0
!
interface Ethernet0/1
 shutdown
!
interface Ethernet0/2
!
interface Ethernet0/3
!
interface Ethernet0/4
 switchport access vlan 2

!--- Output Suppressed. ! route outside 0.0.0.0 0.0.0.0
172.16.2.1 1 !--- Output Suppressed. !--- Easy VPN
Client Configuration ---! !--- Specify the IP address of
the VPN server. vpnclient server 10.1.1.1 !--- This
example uses network extension mode. vpnclient mode
network-extension-mode !--- Specify the group name and
the pre-shared key. vpnclient vpnngroup mytunnel password
***** !--- Specify the authentication username and
password. vpnclient username cisco password ***** !--
- In order to enable the device as hardware vpnclient,
use this command. vpnclient enable ! !--- Output
Suppressed.
Cryptochecksum:0458ce7a08e6b7f9417b17bc254eb4e2 : end
```

PIX

```
PIX Version 8.0(2)
!
hostname pixfirewall
enable password 8Ry2YjIyt7RRXU24 encrypted
names
!
interface Ethernet0
 nameif outside
 security-level 0
 ip address 172.16.1.1 255.255.255.0
!
```

```

interface Ethernet1
nameif inside
security-level 100
ip address 192.168.1.2 255.255.255.0
!
passwd 2KFQnbNIdI.2KYOU encrypted
ftp mode passive
!--- This access list (inside_nat0_outbound) is used
with the nat zero command. !--- This prevents traffic
which matches the access list from undergoing !--- 
network address translation (NAT). access-list
inside_nat0_outbound extended permit ip 192.168.1.0
255.255.255.0 192.168.2.0 255.255.255.0 !--- The traffic
specified by this ACL is !--- traffic that is to be
encrypted and !--- sent across the VPN tunnel. This ACL
is intentionally !--- the same as
(inside_nat0_outbound). !--- Two separate access lists
must always be used in this configuration. access-list
outside_cryptomap_20 extended permit ip 192.168.1.0
255.255.255.0 192.168.2.0 255.255.255.0 !--- NAT 0
prevents NAT for networks specified in the ACL
inside_nat0_outbound. nat (inside) 0 access-list
inside_nat0_outbound !--- Output Suppressed. route
outside 0.0.0.0 0.0.0.0 172.16.1.2 1 !--- Output
Suppressed. !--- PHASE 2 CONFIGURATION ---! !--- The
encryption types for Phase 2 are defined here. !--- 
Define the transform set for Phase 2. crypto ipsec
transform-set myset esp-3des esp-sha-hmac !--- Define
which traffic can be sent to the IPsec peer. crypto map
outside_map 20 match address outside_cryptomap_20 !--- 
Sets the IPsec peer. crypto map outside_map 20 set peer
10.1.1.1 !--- Sets the IPsec transform set "myset" !--- 
to be used with the crypto map entry "outside_map".
crypto map outside_map 20 set transform-set myset !--- 
Specifies the interface to be used with !--- the
settings defined in this configuration. crypto map
outside_map interface outside !--- PHASE 1 CONFIGURATION
---! !--- This configuration uses isakmp policy 10. !--- 
Policy 65535 is included in the config by default. !--- 
The configuration commands here define the Phase !--- 1
policy parameters that are used. crypto isakmp enable
outside crypto isakmp policy 10 authentication pre-share
encryption 3des hash sha group 2 lifetime 86400 crypto
isakmp policy 65535 authentication pre-share encryption
3des hash sha group 2 lifetime 86400 !--- Output
Suppressed. !--- In order to create and manage the
database of connection-specific records !--- for ipsec-
121-IPsec (LAN-to-LAN) tunnels, use the tunnel-group !-- 
- command in global configuration mode. !--- For L2L
connections the name of the tunnel group MUST be the IP
!--- address of the IPsec peer. tunnel-group 10.1.1.1
type ipsec-121 !--- Enter the pre-shared-key in order to
configure the authentication method. tunnel-group
10.1.1.1 ipsec-attributes pre-shared-key * prompt
hostname context
Cryptochecksum:4a2c70f2102113315de795f13f25c2aa : end

```

验证

本部分提供了可用于确认您的配置是否正常运行的信息。

[命令输出解释程序 \(仅限注册用户\) \(OIT\)](#) 支持某些 show 命令。使用 OIT 可查看对 show 命令输出的分析。

- **show crypto isakmp sa** - 显示对等体上的所有当前 IKE 安全关联 (SA)。
- **show crypto ipsec sa** — 显示所有当前 SA。

本部分显示用于以下配置的示例验证配置：

- [HUB ASA](#)
- [Easy VPN 客户机 ASA 5505](#)
- [PIX](#)

HUB ASA

```
ciscoasa #show crypto isakmp sa

Active SA: 2
Rekey SA: 0 (A tunnel will report 1 Active and 1
Rekey SA during rekey)
Total IKE SA: 2
!--- Dynamic LAN-to-LAN tunnel establishment 1 IKE Peer:
172.16.2.2 Type : user Role : responder Rekey : no State
: AM_ACTIVE !--- Static LAN-to-LAN tunnel establishment
2 IKE Peer: 172.16.1.1 Type : L2L Role : initiator Rekey
: no State : MM_ACTIVE ciscoasa #show crypto ipsec sa
ciscoasa(config)#sh crypto ipsec sa
interface: outside
  Crypto map tag: outside_map, seq num: 20, local
addr: 10.1.1.1

    access-list outside_cryptomap_20 permit ip
192.168.2.0 255.255.255.0
192.168.1.0 255.255.255.0
      local ident (addr/mask/prot/port):
(192.168.2.0/255.255.255.0/0/0)
      remote ident (addr/mask/prot/port):
(192.168.1.0/255.255.255.0/0/0)
      current_peer: 172.16.1.1

      #pkts encaps: 4, #pkts encrypt: 4, #pkts digest: 4
      #pkts decaps: 4, #pkts decrypt: 4, #pkts verify: 4
      #pkts compressed: 0, #pkts decompressed: 0
      #pkts not compressed: 4, #pkts comp failed: 0,
#pkts decomp failed: 0
      #pre-frag successes: 0, #pre-frag failures: 0,
#fragments created: 0
      #PMTUs sent: 0, #PMTUs rcvd: 0, #decapsulated frgs
needing reassembly: 0
      #send errors: 0, #recv errors: 0

      local crypto endpt.: 10.1.1.1, remote crypto
endpt.: 172.16.1.1

      path mtu 1500, ipsec overhead 58, media mtu 1500
      current outbound spi: E4312E13

      inbound esp sas:
        spi: 0x9ABAC3DD (2595931101)
          transform: esp-3des esp-sha-hmac none
          in use settings ={L2L, Tunnel, }
```

```
slot: 0, conn_id: 741376, crypto-map:  
outside_map  
    sa timing: remaining key lifetime (kB/sec):  
(4274999/28783)  
        IV size: 8 bytes  
        replay detection support: Y  
outbound esp sas:  
    spi: 0xE4312E13 (3828428307)  
        transform: esp-3des esp-sha-hmac none  
        in use settings ={L2L, Tunnel, }  
        slot: 0, conn_id: 741376, crypto-map:  
outside_map  
    sa timing: remaining key lifetime (kB/sec):  
(4274999/28783)  
        IV size: 8 bytes  
        replay detection support: Y  
  
Crypto map tag: ezvpn, seq num: 30, local addr:  
10.1.1.1  
  
    local ident (addr/mask/prot/port):  
(10.1.1.1/255.255.255.255/0/0)  
        remote ident (addr/mask/prot/port):  
(172.16.2.2/255.255.255.255/0/0)  
            current_peer: 172.16.2.2, username: cisco  
            dynamic allocated peer ip: 0.0.0.0  
  
            #pkts encaps: 0, #pkts encrypt: 0, #pkts digest: 0  
            #pkts decaps: 0, #pkts decrypt: 0, #pkts verify: 0  
            #pkts compressed: 0, #pkts decompressed: 0  
            #pkts not compressed: 0, #pkts comp failed: 0,  
#pkts decomp failed: 0  
            #pre-frag successes: 0, #pre-frag failures: 0,  
#fragments created: 0  
            #PMTUs sent: 0, #PMTUs rcvd: 0, #decapsulated frgs  
needing reassembly: 0  
            #send errors: 0, #recv errors: 0  
  
    local crypto endpt.: 10.1.1.1, remote crypto  
endpt.: 172.16.2.2  
  
    path mtu 1500, ipsec overhead 58, media mtu 1500  
    current outbound spi: 2647B59C  
  
inbound esp sas:  
    spi: 0x21685AF8 (560487160)  
        transform: esp-3des esp-sha-hmac none  
        in use settings ={RA, Tunnel, }  
        slot: 0, conn_id: 737280, crypto-map: ezvpn  
        sa timing: remaining key lifetime (sec): 28146  
        IV size: 8 bytes  
        replay detection support: Y  
outbound esp sas:  
    spi: 0x2647B59C (642233756)  
        transform: esp-3des esp-sha-hmac none  
        in use settings ={RA, Tunnel, }  
        slot: 0, conn_id: 737280, crypto-map: ezvpn  
        sa timing: remaining key lifetime (sec): 28146  
        IV size: 8 bytes  
        replay detection support: Y  
  
Crypto map tag: ezvpn, seq num: 30, local addr:  
10.1.1.1
```

```
local ident (addr/mask/prot/port):
(0.0.0.0/0.0.0.0/0/0)
    remote ident (addr/mask/prot/port):
(192.168.3.0/255.255.255.0/0/0)
        current_peer: 172.16.2.2, username: cisco
        dynamic allocated peer ip: 0.0.0.0

        #pkts encaps: 5, #pkts encrypt: 5, #pkts digest: 5
        #pkts decaps: 5, #pkts decrypt: 5, #pkts verify: 5
        #pkts compressed: 0, #pkts decompressed: 0
        #pkts not compressed: 5, #pkts comp failed: 0,
#pkts decomp failed: 0
        #pre-frag successes: 0, #pre-frag failures: 0,
#fragments created: 0
        #PMTUs sent: 0, #PMTUs rcvd: 0, #decapsulated frgs
needing reassembly: 0
        #send errors: 0, #recv errors: 0

    local crypto endpt.: 10.1.1.1, remote crypto
endpt.: 172.16.2.2

    path mtu 1500, ipsec overhead 58, media mtu 1500
    current outbound spi: 07997B21

    inbound esp sas:
        spi: 0xB5B6013D (3048603965)
            transform: esp-3des esp-sha-hmac none
            in use settings ={RA, Tunnel, }
            slot: 0, conn_id: 737280, crypto-map: ezvpn
            sa timing: remaining key lifetime (sec): 28145
            IV size: 8 bytes
            replay detection support: Y
    outbound esp sas:
        spi: 0x07997B21 (127499041)
            transform: esp-3des esp-sha-hmac none
            in use settings ={RA, Tunnel, }
            slot: 0, conn_id: 737280, crypto-map: ezvpn
            sa timing: remaining key lifetime (sec): 28145
            IV size: 8 bytes
            replay detection support: Y

    Crypto map tag: ezvpn, seq num: 30, local addr:
10.1.1.1

        local ident (addr/mask/prot/port):
(0.0.0.0/0.0.0.0/0/0)
        remote ident (addr/mask/prot/port):
(172.16.2.2/255.255.255.255/0/0)
        current_peer: 172.16.2.2, username: cisco
        dynamic allocated peer ip: 0.0.0.0

        #pkts encaps: 0, #pkts encrypt: 0, #pkts digest: 0
        #pkts decaps: 0, #pkts decrypt: 0, #pkts verify: 0
        #pkts compressed: 0, #pkts decompressed: 0
        #pkts not compressed: 0, #pkts comp failed: 0,
#pkts decomp failed: 0
        #pre-frag successes: 0, #pre-frag failures: 0,
#fragments created: 0
        #PMTUs sent: 0, #PMTUs rcvd: 0, #decapsulated frgs
needing reassembly: 0
        #send errors: 0, #recv errors: 0

    local crypto endpt.: 10.1.1.1, remote crypto
endpt.: 172.16.2.2
```

```

path mtu 1500, ipsec overhead 58, media mtu 1500
current outbound spi: 0F0B1A75

inbound esp sas:
    spi: 0x68B0EA75 (1756424821)
        transform: esp-3des esp-sha-hmac none
        in use settings ={RA, Tunnel, }
        slot: 0, conn_id: 737280, crypto-map: ezvpn
        sa timing: remaining key lifetime (sec): 28143
        IV size: 8 bytes
        replay detection support: Y
outbound esp sas:
    spi: 0x0F0B1A75 (252385909)
        transform: esp-3des esp-sha-hmac none
        in use settings ={RA, Tunnel, }
        slot: 0, conn_id: 737280, crypto-map: ezvpn
        sa timing: remaining key lifetime (sec): 28143
        IV size: 8 bytes
        replay detection support: Y

```

Easy VPN 客户机 ASA 5505

```

ciscoasa(config)# sh crypto isakmp sa

Active SA: 1
    Rekey SA: 0 (A tunnel will report 1 Active and 1
Rekey SA during rekey)
Total IKE SA: 1

1  IKE Peer: 10.1.1.1
    Type      : user          Role      : initiator
    Rekey     : no           State    : AM_ACTIVE

ciscoasa(config)# sh crypto ipsec sa
interface: outside
    Crypto map tag: _vpnc_cm, seq num: 10, local addr:
172.16.2.2

        access-list _vpnc_acl permit ip host 172.16.2.2
host 10.1.1.1
        local ident (addr/mask/prot/port):
(172.16.2.2/255.255.255.255/0/0)
        remote ident (addr/mask/prot/port):
(10.1.1.1/255.255.255.255/0/0)
        current_peer: 10.1.1.1, username: 10.1.1.1
        dynamic allocated peer ip: 0.0.0.0

        #pkts encaps: 0, #pkts encrypt: 0, #pkts digest: 0
        #pkts decaps: 0, #pkts decrypt: 0, #pkts verify: 0
        #pkts compressed: 0, #pkts decompressed: 0
        #pkts not compressed: 0, #pkts comp failed: 0,
#pkts decomp failed: 0
        #pre-frag successes: 0, #pre-frag failures: 0,
#fragments created: 0
        #PMTUs sent: 0, #PMTUs rcvd: 0, #decapsulated frgs
needing reassembly: 0
        #send errors: 0, #recv errors: 0

```

```
local crypto endpt.: 172.16.2.2, remote crypto
endpt.: 10.1.1.1

path mtu 1500, ipsec overhead 58, media mtu 1500
current outbound spi: 21685AF8

inbound esp sas:
spi: 0x2647B59C (642233756)
    transform: esp-3des esp-sha-hmac none
    in use settings ={RA, Tunnel, }
    slot: 0, conn_id: 178, crypto-map: _vpnc_cm
    sa timing: remaining key lifetime (sec): 28298
    IV size: 8 bytes
    replay detection support: Y
outbound esp sas:
spi: 0x21685AF8 (560487160)
    transform: esp-3des esp-sha-hmac none
    in use settings ={RA, Tunnel, }
    slot: 0, conn_id: 178, crypto-map: _vpnc_cm
    sa timing: remaining key lifetime (sec): 28298
    IV size: 8 bytes
    replay detection support: Y

Crypto map tag: _vpnc_cm, seq num: 10, local addr:
172.16.2.2

access-list _vpnc_acl permit ip host 172.16.2.2
any
    local ident (addr/mask/prot/port):
(172.16.2.2/255.255.255.255/0/0)
    remote ident (addr/mask/prot/port):
(0.0.0.0/0.0.0.0/0/0)
    current_peer: 10.1.1.1, username: 10.1.1.1
    dynamic allocated peer ip: 0.0.0.0

#pkts encaps: 0, #pkts encrypt: 0, #pkts digest: 0
#pkts decaps: 0, #pkts decrypt: 0, #pkts verify: 0
#pkts compressed: 0, #pkts decompressed: 0
#pkts not compressed: 0, #pkts comp failed: 0,
#pkts decomp failed: 0
#pre-frag successes: 0, #pre-frag failures: 0,
#fragments created: 0
#PMTUs sent: 0, #PMTUs rcvd: 0, #decapsulated frgs
needing reassembly: 0
#send errors: 0, #recv errors: 0

local crypto endpt.: 172.16.2.2, remote crypto
endpt.: 10.1.1.1

path mtu 1500, ipsec overhead 58, media mtu 1500
current outbound spi: 68B0EA75

inbound esp sas:
spi: 0x0FB1A75 (252385909)
    transform: esp-3des esp-sha-hmac none
    in use settings ={RA, Tunnel, }
    slot: 0, conn_id: 178, crypto-map: _vpnc_cm
    sa timing: remaining key lifetime (sec): 28298
    IV size: 8 bytes
    replay detection support: Y
outbound esp sas:
spi: 0x68B0EA75 (1756424821)
    transform: esp-3des esp-sha-hmac none
    in use settings ={RA, Tunnel, }
```

```

slot: 0, conn_id: 178, crypto-map: _vpnc_cm
sa timing: remaining key lifetime (sec): 28298
IV size: 8 bytes
replay detection support: Y

Crypto map tag: _vpnc_cm, seq num: 10, local addr:
172.16.2.2

access-list _vpnc_acl permit ip 192.168.3.0
255.255.255.0 any
    local ident (addr/mask/prot/port):
(192.168.3.0/255.255.255.0/0/0)
    remote ident (addr/mask/prot/port):
(0.0.0.0/0.0.0.0/0/0)
    current_peer: 10.1.1.1, username: 10.1.1.1
    dynamic allocated peer ip: 0.0.0.0

#pkts encaps: 5, #pkts encrypt: 5, #pkts digest: 5
#pkts decaps: 5, #pkts decrypt: 5, #pkts verify: 5
#pkts compressed: 0, #pkts decompressed: 0
#pkts not compressed: 0, #pkts comp failed: 0,
#pkts decomp failed: 0
    #pre-frag successes: 0, #pre-frag failures: 0,
#fragments created: 0
    #PMTUs sent: 0, #PMTUs rcvd: 0, #decapsulated frgs
needing reassembly: 0
    #send errors: 0, #recv errors: 0

    local crypto endpt.: 172.16.2.2, remote crypto
endpt.: 10.1.1.1

path mtu 1500, ipsec overhead 58, media mtu 1500
current outbound spi: B5B6013D

inbound esp sas:
    spi: 0x07997B21 (127499041)
        transform: esp-3des esp-sha-hmac none
        in use settings ={RA, Tunnel, }
        slot: 0, conn_id: 178, crypto-map: _vpnc_cm
        sa timing: remaining key lifetime (sec): 28294
        IV size: 8 bytes
        replay detection support: Y
outbound esp sas:
    spi: 0xB5B6013D (3048603965)
        transform: esp-3des esp-sha-hmac none
        in use settings ={RA, Tunnel, }
        slot: 0, conn_id: 178, crypto-map: _vpnc_cm
        sa timing: remaining key lifetime (sec): 28294
        IV size: 8 bytes
        replay detection support: Y

```

PIX

```

pixfirewall(config)# sh crypto isakmp sa

Active SA: 1
    Rekey SA: 0 (A tunnel will report 1 Active and 1
Rekey SA during rekey)
Total IKE SA: 1

1  IKE Peer: 10.1.1.1
    Type      : L2L           Role     : responder
    Rekey    : no            State   : MM_ACTIVE

```

```
pixfirewall(config)# sh crypto ipsec sa
interface: outside
  Crypto map tag: outside_map, seq num: 20, local
  addr: 172.16.1.1

    access-list outside_cryptomap_20 permit ip
 192.168.1.0 255.255.255.0
  192.168.2.0 255.255.255.0
    local ident (addr/mask/prot/port):
  (192.168.1.0/255.255.255.0/0/0)
    remote ident (addr/mask/prot/port):
  (192.168.2.0/255.255.255.0/0/0)
      current_peer: 10.1.1.1

    #pkts encaps: 4, #pkts encrypt: 4, #pkts digest: 4
    #pkts decaps: 4, #pkts decrypt: 4, #pkts verify: 4
    #pkts compressed: 0, #pkts decompressed: 0
    #pkts not compressed: 0, #pkts comp failed: 0,
#pkts decomp failed: 0
    #pre-frag successes: 0, #pre-frag failures: 0,
#fragments created: 0
    #PMTUs sent: 0, #PMTUs rcvd: 0, #decapsulated frgs
needing reassembly: 0
    #send errors: 0, #recv errors: 0

      local crypto endpt.: 172.16.1.1, remote crypto
endpt.: 10.1.1.1

      path mtu 1500, ipsec overhead 58, media mtu 1500
      current outbound spi: 9ABAC3DD

      inbound esp sas:
        spi: 0xE4312E13 (3828428307)
          transform: esp-3des esp-sha-hmac none
          in use settings ={L2L, Tunnel, }
          slot: 0, conn_id: 12288, crypto-map:
outside_map
          sa timing: remaining key lifetime (kB/sec):
(3824999/28628)
          IV size: 8 bytes
          replay detection support: Y
      outbound esp sas:
        spi: 0x9ABAC3DD (2595931101)
          transform: esp-3des esp-sha-hmac none
          in use settings ={L2L, Tunnel, }
          slot: 0, conn_id: 12288, crypto-map:
outside_map
          sa timing: remaining key lifetime (kB/sec):
(3824999/28628)
          IV size: 8 bytes
          replay detection support: Y
```

故障排除

本部分提供了可用于对配置进行故障排除的信息。

故障排除命令

[命令输出解释程序工具](#) (仅限注册用户) 支持某些 show 命令，使用此工具可以查看对 show 命令输出的分析。

注意：在发出debug命令之前，请参阅有关Debug命令的重要信息。

在配置模式下发出 PIX 命令：

- clear crypto isakmp sa — 清除第 1 阶段 SA
- clear crypto ipsec sa — 清除第 2 阶段 SA

用于 VPN 隧道的 debug 命令：

- debug crypto isakmp sa — 调试 ISAKMP SA 协商
- debug crypto ipsec sa — 调试 IPSec SA 协商

[相关信息](#)

- [Cisco PIX 500 系列安全设备 - 简介](#)
- [最常见的L2L和远程访问IPSec VPN故障排除解决方案](#)
- [Cisco ASA 5500 系列自适应安全设备 - 产品支持](#)
- [IPsec 协商/IKE 协议](#)
- [技术支持和文档 - Cisco Systems](#)