



思科 ISE 系统日志

首次发布日期: 2019 年 2 月 18 日

上次修改日期: 2019 年 11 月 6 日

Americas Headquarters

Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134-1706
USA
<http://www.cisco.com>
Tel: 408 526-4000
800 553-NETS (6387)
Fax: 408 527-0883

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NON-INFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

All printed copies and duplicate soft copies of this document are considered uncontrolled. See the current online version for the latest version.

Cisco has more than 200 offices worldwide. Addresses and phone numbers are listed on the Cisco website at www.cisco.com/go/offices.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <https://www.cisco.com/c/en/us/about/legal/trademarks.html>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

© 2019 Cisco Systems, Inc. 保留所有权利。



第 1 章

思科 ISE 系统日志简介

- [思科 ISE 消息目录](#)，第 1 页
- [本地存储系统日志消息格式](#)，第 1 页
- [远程系统日志消息格式](#)，第 3 页

思科 ISE 消息目录

思科身份识别服务引擎 (ISE) 提供用于审核、故障管理和故障排除的日志记录机制。日志记录机制可以帮助您识别所部署的服务中的故障情况并有效地对相应问题进行故障排除。它还以一致的方式从监控和故障排除主要节点提供日志记录输出。

在思科 ISE 中，系统在称为日志记录目标的位置收集系统日志。目标是指收集和存储日志的服务器的 IP 地址。您可以在本地生成和存储日志，也可以使用 FTP 工具将日志传输至外部服务器。

可以使用思科 ISE 控制板的“消息目录” (Message Catalog) 页面查看所有可能的日志消息和说明。依次选择管理 (Administration) > 系统 (System) > 日志记录 (Logging) > 消息目录 (Message Catalog)。

系统将显示“日志消息目录” (Log Message Catalog) 页面，您可以在此查看所有显示在日志文件中可能的日志消息。此页面中可用的数据仅用于显示。如果使用的是思科 ISE 2.3 及更高版本，请选择导出 (Export) 以 CSV 文件形式导出所有系统日志消息。

本地存储系统日志消息格式

思科 ISE 日志消息以如下系统日志消息格式发送至本地存储：

```
timestamp sequence_num msg_ode msg_sev msg_class msg_text attr =value
```

字段	说明
<i>timestamp</i>	<p>依据源思科 ISE 节点的本地时钟的消息生成的日期，格式如下：</p> <p><i>YYYY-MM-DD hh:mm:ss:xxx +/-zh:zm</i>。</p> <p>可能的值包括：</p> <ul style="list-style-type: none"> • <i>YYYY</i> = 年份的数字表示。 • <i>MM</i> = 月份的数值表示。对于单个数的月份（1 月至 9 月），此数值前加零。 • <i>DD</i> = 每月的日期数字表示。对于单个数的日期（每月 1 号至 9 号），此数值前加零。 • <i>hh</i> = 一天的整点 - 此值范围为 00 至 23。 • <i>mm</i> = 整点后面的分钟数 - 此值范围为 00 至 59。 • <i>ss</i> = 分钟数后的秒数 - 此值范围为 00 至 59。 • <i>xxx</i> = 秒数后面的毫秒数 - 此值范围为 000 至 999。 • <i>+/-zh:zm</i> = 与思科 ISE 服务器时区的时区偏移，其中 <i>zh</i> 是偏移小时数，<i>zm</i> 是偏移小时的分钟数，所有时区偏移值前面都有一个正号或负号，表示偏移的方向。例如，+02:00 表示某个思科 ISE 节点上在时间戳指示的时间生成的消息比思科 ISE 服务器时区早两个小时。
<i>sequence_num</i>	<p>每条消息的全局计数器。如果一条消息发送至本地存储库，下一条消息发送至系统日志服务器目标，则该计数器数值增加 2。可能的值为 000000001 至 999999999。</p>
<i>msg_ode</i>	<p>日志记录类别中定义的消息代码。</p>
<i>msg_sev</i>	<p>日志消息的消息严重性级别。请查看 Administration > System > Logging > Logging Categories。</p>
<i>msg_class</i>	<p>消息类，是具有相同上下文的一系列消息的标识。</p>
<i>msg_text</i>	<p>英文说明性文本消息。</p>

字段	说明
<i>attr=value</i>	<p>属性 - 值对的集合，提供关于所记录事件的详细信息。每对之间用逗号 (,) 隔开。</p> <p>属性名称如思科 ISE 字典所定义。</p> <p>Response direction AttributesSet 的值与一个名称为 Response 的属性放在一起并用花括号 “{}” 括起来。此外，Response 内的属性-值对用分号分隔。</p> <p>例如，Response={RadiusPacketType=AccessAccept; AuthenticationResult=UnknownUser; cisco-av-pair=sga:security-group-tag=0000-00;}</p>

远程系统日志消息格式

思科 ISE 日志消息采用此系统日志消息信头格式发送到远程系统日志服务器，此格式位于本地存储库系统日志消息格式之前：

pri_num Mmm DD hh:mm:ss xx:xx:xx:xx/host_name cat_name msg_id total_seg seg_num

字段	说明
<i>pri_num</i>	<p>消息的优先级值；消息的易度值和严重性值的组合。优先级值 = (易度值*8) + 严重性值。请参阅适用于您的版本的相关《思科 ISE 管理员指南》，以设置消息代码的安全级别。</p> <p>设备代码的有效选项包括：</p> <ul style="list-style-type: none"> • LOCAL0 (代码 = 16) • LOCAL1 (代码 = 17) • LOCAL2 (代码 = 18) • LOCAL3 (代码 = 19) • LOCAL4 (代码 = 20) • LOCAL5 (代码 = 21) • LOCAL6 (代码 = 22; 默认值) • LOCAL7 (代码 = 23)

字段	说明
<i>time</i>	<p>基于原始思科 ISE 服务器本地时钟的消息生成日期，格式为 Mmm DD hh:mm:ss。</p> <p>可能的值包括：</p> <ul style="list-style-type: none"> • Mmm = 月份表示 - Jan、Feb、Mar、Apr、May、Jun、Jul、Aug、Sep、Oct、Nov、Dec。 • DD=每月的日期数字表示。对于一位数的日期（1 至 9），数字前面留有一个空格。 • hh = 一天的整点 - 此值范围为 00 至 23。 • mm = 整点后面的分钟数 - 此值范围为 00 至 59。 • ss = 分钟数后的秒数 - 此值范围为 00 至 59。 <p>某些设备会发送以 <i>-/+hhmm</i> 格式指定时区的消息，其中 <i>-</i> 和 <i>+</i> 用于标识思科 ISE 服务器时区的方向偏移量，<i>hh</i> 是偏移小时数，<i>mm</i> 是偏移小时的分钟数。例如，<i>+02:00</i> 表示某个思科 ISE 节点上在时间戳指示的时间生成的消息比思科 ISE 服务器时区早两个小时。</p>
<i>xx:xx:xx:xx/host_name</i>	原始思科 ISE 节点的 IP 地址或主机名。
<i>cat_name</i>	CSCOxxx 字符串之后的日志记录类别名称。
<i>msg_id</i>	唯一消息 ID；1 至 4294967295。消息 ID 随着每个新消息递增 1。每次重新启动应用时，消息 ID 会从 1 重新开始。
<i>total_seg</i>	<p>日志消息中的分段总数。长消息划分为多个分段。</p> <p>注释 <i>total_seg</i> 取决于远程日志记录目标页面中的 Maximum Length 设置。请参阅“远程日志记录目标设置”。</p>
<i>seg_num</i>	消息中的分段的序列号。使用此号码可确定正在查看的消息的分段。

日志消息数据或负载与本地存储系统日志消息格式相同。远程系统日志服务器目标使用设备代码名称进行标识，范围为 LOCAL0 到 LOCAL7（LOCAL6 是默认日志记录位置）。您分配给远程系统日志服务器的日志消息被发送至 Linux 系统日志的默认位置 (*/var/log/messages*)，但是您可以在服务器上配置不同位置。



第 2 章

思科 ISE 系统日志列表

- 思科 ISE 系统日志列表，第 6 页
- AD 连接器，第 6 页
- 管理和操作审核，第 25 页
- 管理员身份验证和授权，第 190 页
- 身份验证流程诊断，第 194 页
- 分布式管理，第 214 页
- 外部 MDM，第 231 页
- 失败尝试，第 233 页
- 访客，第 244 页
- 身份存储库诊断，第 252 页
- 内部 MDM，第 381 页
- 内部操作诊断，第 391 页
- 许可，第 434 页
- MDM 诊断，第 445 页
- 我的设备，第 452 页
- 通过身份验证，第 456 页
- 被动 ID，第 460 页
- 策略诊断，第 489 页
- 终端安全评估和客户端调配审核，第 504 页
- 终端安全评估和客户端调配诊断，第 510 页
- Profiler，第 512 页
- RADIUS 记账，第 516 页
- RADIUS 诊断，第 519 页
- 系统统计项，第 718 页
- TACACS 计费，第 719 页
- TACACS 诊断，第 721 页
- 以威胁防护为中心的 NAC，第 738 页

思科 ISE 系统日志列表

以下各部分包括生成的系统日志、每个系统日志的含义以及本地和远程日志记录目标中的消息格式的全面列表。

AD 连接器

- 消息代码: 25000

严重性: 信息 (INFO)

消息文本: ISE 服务器密码更新成功 (ISE server password update succeeded)

消息说明: ISE 服务器密码更新成功

本地目标消息格式: <timestamp> <seq_num> 25000 INFO AD-Connector: ISE server password update succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25000 INFO AD-Connector: ISE server password update succeeded, <log details>

- 消息代码: 25001

严重性: 错误 (ERROR)

消息文本: AD: ISE 帐户密码更新失败。(AD: ISE account password update failed.)

消息说明: ISE 服务器未能更新其 AD 计算机帐户密码。

本地目标消息格式: <timestamp> <seq_num> 25001 ERROR AD-Connector: AD: ISE account password update failed., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25001 ERROR AD-Connector: AD: ISE account password update failed., <log details>

- 消息代码: 25002

严重性: 信息 (INFO)

消息文本: ISE 服务器 TGT 刷新成功 (ISE server TGT refresh succeeded)

消息说明: ISE 服务器 TGT 刷新成功

本地目标消息格式: <timestamp> <seq_num> 25002 INFO AD-Connector: ISE server TGT refresh succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25002 INFO AD-Connector: ISE server TGT refresh succeeded, <log details>

- 消息代码: 25003
 - 严重性: 错误 (ERROR)
 - 消息文本: AD: 计算机 TGT 刷新失败。(AD: Machine TGT refresh failed.)
 - 消息说明: ISE 服务器 TGT (票证授予票证) 刷新失败; 它用于 AD 连接和服务。
 - 本地目标消息格式: <timestamp> <seq_num> 25003 ERROR AD-Connector: AD: Machine TGT refresh failed., <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 25003 ERROR AD-Connector: AD: Machine TGT refresh failed., <log details>

- 消息代码: 25004
 - 严重性: 信息 (INFO)
 - 消息文本: AD 连接器已启动 (AD Connector started)
 - 消息说明: AD 连接器已启动
 - 本地目标消息格式: <timestamp> <seq_num> 25004 INFO AD-Connector: AD Connector started, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 25004 INFO AD-Connector: AD Connector started, <log details>

- 消息代码: 25005
 - 严重性: 信息 (INFO)
 - 消息文本: AD 连接器已停止 (AD Connector stopped)
 - 消息说明: AD 连接器已停止
 - 本地目标消息格式: <timestamp> <seq_num> 25005 INFO AD-Connector: AD Connector stopped, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 25005 INFO AD-Connector: AD Connector stopped, <log details>

- 消息代码: 25006
 - 严重性: 警告 (WARN)
 - 消息文本: AD 连接器必须重新启动。(AD Connector had to be restarted.)
 - 消息说明: AD 连接器意外停止运行, 必须自动重启。
 - 本地目标消息格式: <timestamp> <seq_num> 25006 WARN AD-Connector: AD Connector had to be restarted., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 25006 WARN AD-Connector: AD Connector
had to be restarted., <log details>

- 消息代码: 25007

严重性: 信息 (INFO)

消息文本: 加入点连接器已启动 (Join point connector started)

消息说明: 加入点连接器已启动

本地目标消息格式: <timestamp> <seq_num> 25007 INFO AD-Connector: Join point connector started,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 25007 INFO AD-Connector: Join point
connector started, <log details>

- 消息代码: 25008

严重性: 信息 (INFO)

消息文本: 加入点连接器已停止 (Join point connector stopped)

消息说明: 加入点连接器已停止

本地目标消息格式: <timestamp> <seq_num> 25008 INFO AD-Connector: Join point connector
stopped, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 25008 INFO AD-Connector: Join point
connector stopped, <log details>

- 消息代码: 25009

严重性: 信息 (INFO)

消息文本: 已成功发现受信任域 (Trusted domains discovery succeeded)

消息说明: 已成功发现受信任域

本地目标消息格式: <timestamp> <seq_num> 25009 INFO AD-Connector: Trusted domains discovery
succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 25009 INFO AD-Connector: Trusted domains
discovery succeeded, <log details>

- 消息代码: 25010

严重性: 错误 (ERROR)

消息文本: 未能发现受信任域 (Trusted domains discovery failed)

消息说明: 未能发现受信任域

本地目标消息格式: <timestamp> <seq_num> 25010 ERROR AD-Connector: Trusted domains discovery failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25010 ERROR AD-Connector: Trusted domains discovery failed, <log details>

- 消息代码: 25011

严重性: 信息 (INFO)

消息文本: 加入域成功 (Domain join succeeded)

消息说明: 加入域成功

本地目标消息格式: <timestamp> <seq_num> 25011 INFO AD-Connector: Domain join succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25011 INFO AD-Connector: Domain join succeeded, <log details>

- 消息代码: 25012

严重性: 警告 (WARN)

消息文本: 加入域失败 (Domain join failed)

消息说明: 加入域失败

本地目标消息格式: <timestamp> <seq_num> 25012 WARN AD-Connector: Domain join failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25012 WARN AD-Connector: Domain join failed, <log details>

- 消息代码: 25013

严重性: 信息 (INFO)

消息文本: 离开域成功 (Domain leave succeeded)

消息说明: 离开域成功

本地目标消息格式: <timestamp> <seq_num> 25013 INFO AD-Connector: Domain leave succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25013 INFO AD-Connector: Domain leave succeeded, <log details>

- 消息代码: 25014

严重性: 警告 (WARN)

消息文本: 离开域失败 (Domain leave failed)

消息说明: 离开域失败

本地目标消息格式: <timestamp> <seq_num> 25014 WARN AD-Connector: Domain leave failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25014 WARN AD-Connector: Domain leave failed, <log details>

- 消息代码: 25015

严重性: 信息 (INFO)

消息文本: DNS SRV 查询成功 (DNS SRV query succeeded)

消息说明: DNS SRV 查询成功

本地目标消息格式: <timestamp> <seq_num> 25015 INFO AD-Connector: DNS SRV query succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25015 INFO AD-Connector: DNS SRV query succeeded, <log details>

- 消息代码: 25016

严重性: 错误 (ERROR)

消息文本: DNS SRV 查询失败 (DNS SRV query failed)

消息说明: DNS SRV 查询失败

本地目标消息格式: <timestamp> <seq_num> 25016 ERROR AD-Connector: DNS SRV query failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25016 ERROR AD-Connector: DNS SRV query failed, <log details>

- 消息代码: 25017

严重性: 信息 (INFO)

消息文本: DC 发现成功 (DC discovery succeeded)

消息说明: DC 发现成功

本地目标消息格式: <timestamp> <seq_num> 25017 INFO AD-Connector: DC discovery succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25017 INFO AD-Connector: DC discovery succeeded, <log details>

- 消息代码: 25018

严重性: 错误 (ERROR)

消息文本: DC 发现失败 (DC discovery failed)

消息说明: DC 发现失败

本地目标消息格式: <timestamp> <seq_num> 25018 ERROR AD-Connector: DC discovery failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 25018 ERROR AD-Connector: DC discovery failed, <log details>

- 消息代码: 25019

严重性: 信息 (INFO)

消息文本: KDC 发现成功 (KDC discovery succeeded)

消息说明: KDC 发现成功

本地目标消息格式: <timestamp> <seq_num> 25019 INFO AD-Connector: KDC discovery succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 25019 INFO AD-Connector: KDC discovery succeeded, <log details>

- 消息代码: 25020

严重性: 错误 (ERROR)

消息文本: KDC 发现失败 (KDC discovery failed)

消息说明: KDC 发现失败

本地目标消息格式: <timestamp> <seq_num> 25020 ERROR AD-Connector: KDC discovery failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 25020 ERROR AD-Connector: KDC discovery failed, <log details>

- 消息代码: 25021

严重性: 信息 (INFO)

消息文本: GC 发现成功 (GC discovery succeeded)

消息说明: GC 发现成功

本地目标消息格式: <timestamp> <seq_num> 25021 INFO AD-Connector: GC discovery succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 25021 INFO AD-Connector: GC discovery succeeded, <log details>

- 消息代码: 25022

严重性: 错误 (ERROR)

消息文本: GC 发现失败 (GC discovery failed)

消息说明: GC 发现失败

本地目标消息格式: <timestamp> <seq_num> 25022 ERROR AD-Connector: GC discovery failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25022 ERROR AD-Connector: GC discovery failed, <log details>

- 消息代码: 25023

严重性: 信息 (INFO)

消息文本: LDAP 连接到域控制器成功 (LDAP connect to domain controller succeeded)

消息说明: LDAP 连接到域控制器成功

本地目标消息格式: <timestamp> <seq_num> 25023 INFO AD-Connector: LDAP connect to domain controller succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25023 INFO AD-Connector: LDAP connect to domain controller succeeded, <log details>

- 消息代码: 25024

严重性: 错误 (ERROR)

消息文本: LDAP 连接到域控制器失败 (LDAP connect to domain controller failed)

消息说明: LDAP 连接到域控制器失败

本地目标消息格式: <timestamp> <seq_num> 25024 ERROR AD-Connector: LDAP connect to domain controller failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25024 ERROR AD-Connector: LDAP connect to domain controller failed, <log details>

- 消息代码: 25025

严重性: 信息 (INFO)

消息文本: LDAP 连接到全局目录成功 (LDAP connect to global catalog succeeded)

消息说明: LDAP 连接到域控制器成功

本地目标消息格式: <timestamp> <seq_num> 25025 INFO AD-Connector: LDAP connect to global catalog succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25025 INFO AD-Connector: LDAP connect to global catalog succeeded, <log details>

- 消息代码: 25026
 - 严重性: 错误 (ERROR)
 - 消息文本: LDAP 连接到全局目录失败 (LDAP connect to global catalog failed)
 - 消息说明: LDAP 连接到域控制器失败
 - 本地目标消息格式: <timestamp> <seq_num> 25026 ERROR AD-Connector: LDAP connect to global catalog failed, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25026 ERROR AD-Connector: LDAP connect to global catalog failed, <log details>

- 消息代码: 25027
 - 严重性: 信息 (INFO)
 - 消息文本: RPC 连接到域控制器成功 (RPC connect to domain controller succeeded)
 - 消息说明: RPC 连接到域控制器成功
 - 本地目标消息格式: <timestamp> <seq_num> 25027 INFO AD-Connector: RPC connect to domain controller succeeded, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25027 INFO AD-Connector: RPC connect to domain controller succeeded, <log details>

- 消息代码: 25028
 - 严重性: 错误 (ERROR)
 - 消息文本: RPC 连接到域控制器失败 (RPC connect to domain controller failed)
 - 消息说明: RPC 连接到域控制器失败
 - 本地目标消息格式: <timestamp> <seq_num> 25028 ERROR AD-Connector: RPC connect to domain controller failed, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25028 ERROR AD-Connector: RPC connect to domain controller failed, <log details>

- 消息代码: 25029
 - 严重性: 信息 (INFO)
 - 消息文本: KDC 连接到域控制器成功 (KDC connect to domain controller succeeded)
 - 消息说明: KDC 连接到域控制器成功
 - 本地目标消息格式: <timestamp> <seq_num> 25029 INFO AD-Connector: KDC connect to domain controller succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 25029 INFO AD-Connector: KDC connect
to domain controller succeeded, <log details>

- 消息代码: 25030

严重性: 错误 (ERROR)

消息文本: KDC 连接到域控制器失败 (KDC connect to domain controller failed)

消息说明: KDC 连接到域控制器失败

本地目标消息格式: <timestamp> <seq_num> 25030 ERROR AD-Connector: KDC connect to domain
controller failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 25030 ERROR AD-Connector: KDC connect
to domain controller failed, <log details>

- 消息代码: 25031

严重性: 错误 (ERROR)

消息文本: AD 提供程序无法启动 (AD Provider failed to start)

消息说明: AD 提供程序无法启动

本地目标消息格式: <timestamp> <seq_num> 25031 ERROR AD-Connector: AD Provider failed to
start, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 25031 ERROR AD-Connector: AD Provider
failed to start, <log details>

- 消息代码: 25032

严重性: 信息 (INFO)

消息文本: 发现了受信任域 (Trusted domain discovered)

消息说明: 发现了受信任域

本地目标消息格式: <timestamp> <seq_num> 25032 INFO AD-Connector: Trusted domain discovered,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 25032 INFO AD-Connector: Trusted domain
discovered, <log details>

- 消息代码: 25033

严重性: 信息 (INFO)

消息文本: DNS A/AAAA 查询成功 (DNS A/AAAA query succeeded)

消息说明: DNS A/AAAA 查询成功

本地目标消息格式: <timestamp> <seq_num> 25033 INFO AD-Connector: DNS A/AAAA query succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25033 INFO AD-Connector: DNS A/AAAA query succeeded, <log details>

- 消息代码: 25034

严重性: 错误 (ERROR)

消息文本: DNS A/AAAA 查询失败 (DNS A/AAAA query failed)

消息说明: DNS A/AAAA 查询失败

本地目标消息格式: <timestamp> <seq_num> 25034 ERROR AD-Connector: DNS A/AAAA query failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25034 ERROR AD-Connector: DNS A/AAAA query failed, <log details>

- 消息代码: 25035

严重性: 信息 (INFO)

消息文本: 可写 DC 发现成功 (Writeable DC discovery succeeded)

消息说明: 可写 DC 发现成功

本地目标消息格式: <timestamp> <seq_num> 25035 INFO AD-Connector: Writeable DC discovery succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25035 INFO AD-Connector: Writeable DC discovery succeeded, <log details>

- 消息代码: 25036

严重性: 错误 (ERROR)

消息文本: 可写 DC 发现失败 (Writeable DC discovery failed)

消息说明: 可写 DC 发现失败

本地目标消息格式: <timestamp> <seq_num> 25036 ERROR AD-Connector: Writeable DC discovery failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25036 ERROR AD-Connector: Writeable DC discovery failed, <log details>

- 消息代码: 25037

严重性: 信息 (INFO)

消息文本: DC 记录已缓存 (DC record cached)

消息说明: DC 记录已缓存

本地目标消息格式: <timestamp> <seq_num> 25037 INFO AD-Connector: DC record cached, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25037 INFO AD-Connector: DC record cached, <log details>

- 消息代码: 25038

严重性: 信息 (INFO)

消息文本: GC 记录已缓存 (GC record cached)

消息说明: GC 记录已缓存

本地目标消息格式: <timestamp> <seq_num> 25038 INFO AD-Connector: GC record cached, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25038 INFO AD-Connector: GC record cached, <log details>

- 消息代码: 25039

严重性: 错误 (ERROR)

消息文本: LDAP SASL 绑定失败 (LDAP SASL bind failed)

消息说明: LDAP SASL 绑定失败

本地目标消息格式: <timestamp> <seq_num> 25039 ERROR AD-Connector: LDAP SASL bind failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25039 ERROR AD-Connector: LDAP SASL bind failed, <log details>

- 消息代码: 25040

严重性: 错误 (ERROR)

消息文本: RPC 安全信道建立失败 (RPC secure channel establishment failed)

消息说明: RPC 安全信道建立失败

本地目标消息格式: <timestamp> <seq_num> 25040 ERROR AD-Connector: RPC secure channel establishment failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25040 ERROR AD-Connector: RPC secure channel establishment failed, <log details>

- 消息代码: 25041

严重性: 信息 (INFO)

消息文本: 已发现 ISE 服务器站点 (ISE Server site discovered)

消息说明: 已发现 ISE 服务器站点

本地目标消息格式: <timestamp> <seq_num> 25041 INFO AD-Connector: ISE Server site discovered, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 25041 INFO AD-Connector: ISE Server site discovered, <log details>

- 消息代码: 25042

严重性: 警告 (WARN)

消息文本: ISE 服务器未分配到任何 AD 站点 (ISE Server is not assigned to any AD site)

消息说明: ISE 服务器未分配到任何 AD 站点

本地目标消息格式: <timestamp> <seq_num> 25042 WARN AD-Connector: ISE Server is not assigned to any AD site, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 25042 WARN AD-Connector: ISE Server is not assigned to any AD site, <log details>

- 消息代码: 25043

严重性: 警告 (WARN)

消息文本: 未在 ISE 服务器站点中找到域控制器 (No domain controller found in ISE Server site)

消息说明: 未在 ISE 服务器站点中找到域控制器

本地目标消息格式: <timestamp> <seq_num> 25043 WARN AD-Connector: No domain controller found in ISE Server site, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 25043 WARN AD-Connector: No domain controller found in ISE Server site, <log details>

- 消息代码: 25044

严重性: 错误 (ERROR)

消息文本: 与域的通信失败 (Communication to domain failed)

消息说明: 与域的通信失败

本地目标消息格式: <timestamp> <seq_num> 25044 ERROR AD-Connector: Communication to domain failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 25044 ERROR AD-Connector: Communication to domain failed, <log details>

- 消息代码: 25045

严重性: 错误 (ERROR)

消息文本: 配置的名称服务器已关闭 (Configured nameserver is down)

消息说明: 配置的名称服务器已关闭。因此, AD 操作将会失败。

本地目标消息格式: <timestamp> <seq_num> 25045 ERROR AD-Connector: Configured nameserver is down, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25045 ERROR AD-Connector: Configured nameserver is down, <log details>

- 消息代码: 25046

严重性: 错误 (ERROR)

消息文本: 所加入的域不可用 (Joined domain is unavailable)

消息说明: 所加入的域不可用, 无法用于身份验证、授权以及组和属性检索

本地目标消息格式: <timestamp> <seq_num> 25046 ERROR AD-Connector: Joined domain is unavailable, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25046 ERROR AD-Connector: Joined domain is unavailable, <log details>

- 消息代码: 25047

严重性: 错误 (ERROR)

消息文本: 身份验证域不可用 (Authentication domain is unavailable)

消息说明: 身份验证域不可用, 无法用于身份验证、授权以及组和属性检索

本地目标消息格式: <timestamp> <seq_num> 25047 ERROR AD-Connector: Authentication domain is unavailable, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25047 ERROR AD-Connector: Authentication domain is unavailable, <log details>

- 消息代码: 25048

严重性: 错误 (ERROR)

消息文本: Active-Directory 林不可用 (Active-Directory forest is unavailable)

消息说明: Active Directory 林 GC (全局目录) 不可用, 无法用于身份验证、授权以及组和属性检索

本地目标消息格式: <timestamp> <seq_num> 25048 ERROR AD-Connector: Active-Directory forest is unavailable, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 25048 ERROR AD-Connector:
Active-Directory forest is unavailable, <log details>

- 消息代码: 25049

严重性: 警告 (WARN)

消息文本: 找不到计算机帐户 (Machine account was not found)

消息说明: 在使用凭证离开期间未找到计算机帐户。

本地目标消息格式: <timestamp> <seq_num> 25049 WARN AD-Connector: Machine account was
not found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 25049 WARN AD-Connector: Machine
account was not found, <log details>

- 消息代码: 25050

严重性: 信息 (INFO)

消息文本: 计算机帐户已从 AD 中删除 (Machine account was deleted from AD)

消息说明: 计算机帐户已从 AD 中删除

本地目标消息格式: <timestamp> <seq_num> 25050 INFO AD-Connector: Machine account was
deleted from AD, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 25050 INFO AD-Connector: Machine account
was deleted from AD, <log details>

- 消息代码: 25051

严重性: 错误 (ERROR)

消息文本: 计算机帐户删除失败 (Machine account deletion was failed)

消息说明: 用户凭证权限不足以删除计算机帐户

本地目标消息格式: <timestamp> <seq_num> 25051 ERROR AD-Connector: Machine account deletion
was failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 25051 ERROR AD-Connector: Machine
account deletion was failed, <log details>

- 消息代码: 25052

严重性: 信息 (INFO)

消息文本: 已启动定期信任发现方法 (Periodic trusts discovery started)

消息说明: 已启动定期信任发现方法

本地目标消息格式: <timestamp> <seq_num> 25052 INFO AD-Connector: Periodic trusts discovery started, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25052 INFO AD-Connector: Periodic trusts discovery started, <log details>

- 消息代码: 25053

严重性: 信息 (INFO)

消息文本: 已检测到离线林 (Detected offline forest)

消息说明: 已检测到离线林

本地目标消息格式: <timestamp> <seq_num> 25053 INFO AD-Connector: Detected offline forest, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25053 INFO AD-Connector: Detected offline forest, <log details>

- 消息代码: 25054

严重性: 信息 (INFO)

消息文本: 通过发现删除了信任 (Trust removed by discovery)

消息说明: 通过发现删除了信任

本地目标消息格式: <timestamp> <seq_num> 25054 INFO AD-Connector: Trust removed by discovery, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25054 INFO AD-Connector: Trust removed by discovery, <log details>

- 消息代码: 25055

严重性: 信息 (INFO)

消息文本: DC 已添加到黑名单 (DC added to black list)

消息说明: 域控制器已添加至黑名单

本地目标消息格式: <timestamp> <seq_num> 25055 INFO AD-Connector: DC added to black list, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25055 INFO AD-Connector: DC added to black list, <log details>

- 消息代码: 25056

严重性: 信息 (INFO)

消息文本: 已从黑名单中删除 DC (DC removed from black list)

消息说明: 已从黑名单中删除域控制器

本地目标消息格式: <timestamp> <seq_num> 25056 INFO AD-Connector: DC removed from black list, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25056 INFO AD-Connector: DC removed from black list, <log details>

- 消息代码: 25057

严重性: 错误 (ERROR)

消息文本: ISE 计算机帐户没有获取组所需的权限。(The ISE machine account does not have the required privileges to fetch groups.)

消息说明: ISE 计算机帐户没有获取组所需的权限。

本地目标消息格式: <timestamp> <seq_num> 25057 ERROR AD-Connector: The ISE machine account does not have the required privileges to fetch groups., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25057 ERROR AD-Connector: The ISE machine account does not have the required privileges to fetch groups., <log details>

- 消息代码: 25058

严重性: 错误 (ERROR)

消息文本: ISE 未加入 Active Directory 域控制器 (ISE is not joined to an Active Directory Domain Controller)

消息说明: ISE 未加入 Active Directory 域控制器

本地目标消息格式: <timestamp> <seq_num> 25058 ERROR AD-Connector: ISE is not joined to an Active Directory Domain Controller, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 25058 ERROR AD-Connector: ISE is not joined to an Active Directory Domain Controller, <log details>

- 消息代码: 25100

严重性: 正在连接外部 REST ID 存储服务器

消息文本: ISE 将与外部 REST ID 存储服务器建立新连接 (ISE is going to establish a new connection to external REST ID store server)

消息说明: 调试 (DEBUG)

本地目标消息格式: <timestamp> <seq_num>25100 Connecting to external REST ID store server External-REST ISE is going to establish a new connection to external REST ID store server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>25100 Connecting to external REST ID store server External-REST ISE is going to establish a new connection to external REST ID store server, <log details>

- 消息代码: 25101

严重性: 成功连接到外部 REST ID 存储服务器

消息文本: ISE 成功连接到外部 REST ID 存储服务器 (ISE successfully connect to external REST ID store server)

消息说明: 调试 (DEBUG)

本地目标消息格式: <timestamp> <seq_num>25101 Successfully connected to external REST ID store server External-REST ISE successfully connect to external REST ID store server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>25101 Successfully connected to external REST ID store server External-REST ISE successfully connect to external REST ID store server, <log details>

- 消息代码: 25102

严重性: 连接外部 REST 数据库失败

消息文本: ISE 未能与外部 REST 数据库建立新连接 (ISE failed to establish a new connection to external REST database)

消息说明: 调试 (DEBUG)

本地目标消息格式: <timestamp> <seq_num>25102 Connection to external REST database failed External-REST ISE failed to establish a new connection to external REST database, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>25102 Connection to external REST database failed External-REST ISE failed to establish a new connection to external REST database, <log details>

- 消息代码: 25103

严重性: 在外部 REST ID 存储服务器中执行纯文本密码身份验证

消息文本: ISE 正在外部 REST ID 存储服务器上启动纯文本密码身份验证 (ISE is starting plain text password authentication against the external REST ID store server)

消息说明: 调试 (DEBUG)

本地目标消息格式: <timestamp> <seq_num>25103 Perform plain text password authentication in external REST ID store server External-REST ISE is starting plain text password authentication against the external REST ID store server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>25103 Perform plain text password authentication in external REST ID store server External-REST ISE is starting plain text password authentication against the external REST ID store server, <log details>

- 消息代码: 25104

严重性: 外部 REST ID 存储服务器中的纯文本密码身份验证成功

消息文本: 外部 REST ID 存储服务器中的纯文本密码身份验证成功 (Plain text password authentication in external REST ID store server succeeded)

消息说明: 调试 (DEBUG)

本地目标消息格式: <timestamp> <seq_num>25104 Plain text password authentication in external REST ID store server succeeded External-REST Plain text password authentication in external REST ID store server succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>25104 Plain text password authentication in external REST ID store server succeeded External-REST Plain text password authentication in external REST ID store server succeeded, <log details>

- 消息代码: 25105

严重性: 外部 REST ID 存储服务器中的纯文本密码身份验证失败

消息文本: 外部 REST ID 存储服务器中的纯文本密码身份验证失败 (Plain text password authentication in external REST ID store server failed)

消息说明: 调试 (DEBUG)

本地目标消息格式: <timestamp> <seq_num>25105 Plain text password authentication in external REST ID store server failed External-REST Plain text password authentication in external REST ID store server failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>25105 Plain text password authentication in external REST ID store server failed External-REST Plain text password authentication in external REST ID store server failed, <log details>

- 消息代码: 25106

严重性: REST ID 存储服务器指示纯文本密码身份验证失败

消息文本: REST ID 存储服务器指示纯文本密码身份验证失败 (REST ID store server indicated plain text password authentication failure)

消息说明: 调试 (DEBUG)

本地目标消息格式: <timestamp> <seq_num>25106 REST ID Store server indicated plain text password authentication failure External-REST REST ID store server indicated plain text password authentication failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>25106 REST ID Store server indicated plain text password authentication failure External-REST REST ID store server indicated plain text password authentication failure, <log details>

- 消息代码: 25107

严重性: REST ID 存储服务器响应组

消息文本: 在身份验证过程中, REST ID 存储服务器响应身份验证中的组 (REST ID store server respond with groups in authentication as part of authentication)

消息说明: 调试 (DEBUG)

本地目标消息格式: <timestamp> <seq_num>25107 REST ID store server respond with groups External-REST REST ID store server respond with groups in authentication as part of authentication, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>25107 REST ID store server respond with groups External-REST REST ID store server respond with groups in authentication as part of authentication, <log details>

- 消息代码: 25108

严重性: REST ID 存储服务器不包含任何用户组

消息文本: REST ID 存储服务器没有在身份验证响应中包含任何用户组 (REST ID store server does not include any user groups as part of authentication response)

消息说明: 调试 (DEBUG)

本地目标消息格式: <timestamp> <seq_num>25108 REST ID store server does not include any user groups External-REST REST ID store server does not include any user groups as part of authentication response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>25108 REST ID store server does not include any user groups External-REST REST ID store server does not include any user groups as part of authentication response, <log details>

- 消息代码: 25109

严重性: ISE 开始在会话缓存中设置用户组

消息文本: ISE 开始在会话缓存中设置用户组, 以便在后期的授权过程中使用 (ISE starts set user groups in session cache to be used later in authorization process)

消息说明: 调试 (DEBUG)

本地目标消息格式: <timestamp> <seq_num>25109 ISE starts set user groups in session cache External-REST ISE starts set user groups in session cache to be used later in authorization process, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>25109 ISE starts set user groups in session cache External-REST ISE starts set user groups in session cache to be used later in authorization process, <log details>

- 消息代码: 25110

严重性: 用户组已插入会话缓存

消息文本: ISE 成功为缓存中的当前会话设置用户组 (ISE succeed to set user groups for current session in cache)

消息说明: 调试 (DEBUG)

本地目标消息格式: <timestamp> <seq_num>25110 User groups inserted to session cache External-REST ISE succeed to set user groups for current session in cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num>25110 User groups inserted to session cache
External-REST ISE succeed to set user groups for current session in cache, <log details>

- 消息代码: 25111

严重性: 未能在会话缓存中设置用户组

消息文本: ISE 未能在会话缓存中设置用户组, 授权过程中不会使用这些组 (ISE failed to set user groups in session cache, groups will not be used in authorization process)

消息说明: 调试 (DEBUG)

本地目标消息格式: <timestamp> <seq_num>25111 Failed to set user groups in session cache
External-REST ISE failed to set user groups in session cache, groups will not be used in authorization process, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num>25111 Failed to set user groups in session cache
External-REST ISE failed to set user groups in session cache, groups will not be used in authorization process, <log details>

- 消息代码: 25112

严重性: REST 数据库指示纯文本密码身份验证失败

消息文本: REST 数据库指示纯文本密码身份验证失败 (REST database indicated plain text password authentication failure)

消息说明: 调试 (DEBUG)

本地目标消息格式: <timestamp> <seq_num>25112 REST database indicated plain text password authentication failure
External-REST REST database indicated plain text password authentication failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num>25112 REST database indicated plain text password authentication failure
External-REST REST database indicated plain text password authentication failure, <log details>

管理和操作审核

- 消息代码: 51000

严重性: 通知 (NOTICE)

消息文本: 管理员身份验证失败 (Administrator authentication failed)

消息说明: 管理员身份验证失败

本地目标消息格式: <timestamp> <seq_num> 51000 NOTICE Administrator-Login: Administrator authentication failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
 <msg_id> <total seg> <seg num><timestamp> <seq_num> 51000 NOTICE
 Administrator-Login: Administrator authentication failed, <log details>

- 消息代码: 51001

严重性: 通知 (NOTICE)

消息文本: 管理员身份验证成功 (Administrator authentication succeeded)

消息说明: 管理员身份验证成功

本地目标消息格式: <timestamp> <seq_num> 51001 NOTICE Administrator-Login: Administrator authentication succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
 <msg_id> <total seg> <seg num> <timestamp> <seq_num> 51001 NOTICE Administrator-Login:
 Administrator authentication succeeded, <log details>

- 消息代码: 51002

严重性: 通知 (NOTICE)

消息文本: 管理员已注销 (Administrator logged off)

消息说明: 管理员已注销

本地目标消息格式: <timestamp> <seq_num> 51002 NOTICE Administrator-Login: Administrator logged off, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
 <msg_id> <total seg> <seg num> <timestamp> <seq_num> 51002 NOTICE
 Administrator-Login: Administrator logged off, <log details>

- 消息代码: 51003

严重性: 通知 (NOTICE)

消息文本: 会话超时 (Session Timeout)

消息说明: 管理员出现会话超时

本地目标消息格式: <timestamp> <seq_num> 51003 NOTICE Administrator-Login: Session Timeout, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
 <msg_id> <total seg> <seg num> <timestamp> <seq_num> 51003 NOTICE Administrator-Login: Session
 Timeout, <log details>

- 消息代码: 51004

严重性: 通知 (NOTICE)

消息文本: 已拒绝来自未获授权客户端 IP 地址的管理员会话 (Rejected administrator session from unauthorized client IP address)

消息说明：已拒绝从未获授权客户端 IP 地址开始管理员会话的企图。请检查客户端的管理访问设置。

本地目标消息格式：<timestamp> <seq_num> 51004 NOTICE Administrator-Login: Rejected administrator session from unauthorized client IP address, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 51004 NOTICE Administrator-Login: Rejected administrator session from unauthorized client IP address, <log details>

- 消息代码：51005

严重性：通知 (NOTICE)

消息文本：管理员身份验证失败。(Administrator authentication failed.) 已禁用管理帐户

消息说明：管理员身份验证失败。已禁用管理帐户。

本地目标消息格式：<timestamp> <seq_num> 51005 NOTICE Administrator-Login: Administrator authentication failed. Administrator account is disabled, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 51005 NOTICE Administrator-Login: Administrator authentication failed. Administrator account is disabled, <log details>

- 消息代码：51006

严重性：通知 (NOTICE)

消息文本：管理员身份验证失败。(Administrator authentication failed.) 由于帐户处于不活动状态，已被禁用

消息说明：管理员身份验证失败。由于帐户处于不活动状态，已被禁用。

本地目标消息格式：<timestamp> <seq_num> 51006 NOTICE Administrator-Login: Administrator authentication failed. Account is disabled due to inactivity, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 51006 NOTICE Administrator-Login: Administrator authentication failed. Account is disabled due to inactivity, <log details>

- 消息代码：51007

严重性：通知 (NOTICE)

消息文本：身份验证失败。(Authentication failed.) 由于密码过期，帐户已被禁用

消息说明：身份验证失败。由于密码过期，帐户已被禁用

本地目标消息格式：<timestamp> <seq_num> 51007 NOTICE Administrator-Login: Authentication failed. Account is disabled due to password expiration, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 51007 NOTICE Administrator-Login: Authentication failed. Account is disabled due to password expiration, <log details>

- 消息代码: 51008

严重性: 通知 (NOTICE)

消息文本: 管理员身份验证失败。(Administrator authentication failed.) 由于身份验证尝试失败次数过多, 帐户已被禁用

消息说明: 管理员身份验证失败。由于身份验证尝试失败次数过多, 帐户已被禁用。

本地目标消息格式: <timestamp> <seq_num> 51008 NOTICE Administrator-Login: Administrator authentication failed. Account is disabled due to excessive failed authentication attempts, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 51008 NOTICE Administrator-Login: Administrator authentication failed. Account is disabled due to excessive failed authentication attempts, <log details>

- 消息代码: 51009

严重性: 通知 (NOTICE)

消息文本: 身份验证失败。(Authentication failed.) ISE 运行时间未运行

消息说明: 身份验证失败。ISE 运行时间未运行

本地目标消息格式: <timestamp> <seq_num> 51009 NOTICE Administrator-Login: Authentication failed. ISE Runtime is not running, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 51009 NOTICE Administrator-Login: Authentication failed. ISE Runtime is not running, <log details>

- 消息代码: 51020

严重性: 通知 (NOTICE)

消息文本: 管理员身份验证失败。(Administrator authentication failed.) 登录用户名不存在。

消息说明: 管理员身份验证失败。登录用户名不存在。

本地目标消息格式: <timestamp> <seq_num> 51020 NOTICE Administrator-Login: Administrator authentication failed. Login username does not exist., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 51020 NOTICE Administrator-Login: Administrator authentication failed. Login username does not exist., <log details>

- 消息代码: 51021

严重性: 通知 (NOTICE)

消息文本: 管理员身份验证失败。(Administrator authentication failed.) 密码错误。

消息说明: 管理员身份验证失败。密码错误。

本地目标消息格式: <timestamp> <seq_num> 51021 NOTICE Administrator-Login: Administrator authentication failed. Wrong password., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 51021 NOTICE Administrator-Login:
Administrator authentication failed. Wrong password., <log details>

- 消息代码: 51022

严重性: 通知 (NOTICE)

消息文本: 管理员身份验证失败。(Administrator authentication failed.) 系统错误

消息说明: 管理员身份验证失败。系统错误

本地目标消息格式: <timestamp> <seq_num> 51022 NOTICE Administrator-Login: Administrator
authentication failed. System Error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 51022 NOTICE Administrator-Login:
Administrator authentication failed. System Error, <log details>

- 消息代码: 51023

严重性: 通知 (NOTICE)

消息文本: 管理员帐户已解锁 (Administrator account is unlocked)

消息说明: 管理员帐户已解锁

本地目标消息格式: <timestamp> <seq_num> 51023 NOTICE Administrator-Login: Administrator
account is unlocked, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 51023 NOTICE Administrator-Login:
Administrator account is unlocked, <log details>

- 消息代码: 51100

严重性: 通知 (NOTICE)

消息文本: 密码更改成功 (Password changed successfully)

消息说明: 密码已成功更改

本地目标消息格式: <timestamp> <seq_num> 51100 NOTICE User change password: Password
changed successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 51100 NOTICE User change password:
Password changed successfully, <log details>

- 消息代码: 51101

严重性: 通知 (NOTICE)

消息文本: 新密码无效。(Invalid new password.) 密码太短

消息说明: 新密码无效。密码太短。

本地目标消息格式: <timestamp> <seq_num> 51101 NOTICE User change password: Invalid new password. Password is too short, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 51101 NOTICE User change password: Invalid new password. Password is too short, <log details>

- 消息代码: 51102

严重性: 通知 (NOTICE)

消息文本: 新密码无效。(Invalid new password.) 重复的字符过多

消息说明: 新密码无效。重复的字符过多。

本地目标消息格式: <timestamp> <seq_num> 51102 NOTICE User change password: Invalid new password. Too many repeating characters, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 51102 NOTICE User change password: Invalid new password. Too many repeating characters, <log details>

- 消息代码: 51103

严重性: 通知 (NOTICE)

消息文本: 新密码无效。(Invalid new password.) 缺少所需的字符类型

消息说明: 新密码无效。缺少所需的字符类型。

本地目标消息格式: <timestamp> <seq_num> 51103 NOTICE User change password: Invalid new password. Missing required character type, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 51103 NOTICE User change password: Invalid new password. Missing required character type, <log details>

- 消息代码: 51104

严重性: 通知 (NOTICE)

消息文本: 新密码无效。(Invalid new password.) 包含用户名

消息说明: 新密码无效。密码不能包含用户名。

本地目标消息格式: <timestamp> <seq_num> 51104 NOTICE User change password: Invalid new password. Contains username, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 51104 NOTICE User change password: Invalid new password. Contains username, <log details>

- 消息代码: 51105

严重性: 通知 (NOTICE)

消息文本: 新密码无效。(Invalid new password.) 包含保留字

消息说明：新密码无效。密码不能包含保留字。

本地目标消息格式：<timestamp> <seq_num> 51105 NOTICE User change password: Invalid new password. Contains reserved word, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 51105 NOTICE User change password: Invalid new password. Contains reserved word, <log details>

- 消息代码：51106

严重性：通知 (NOTICE)

消息文本：Web 服务的身份验证失败 (Authentication for web services failed)

消息说明：Web 服务的身份验证失败。

本地目标消息格式：<timestamp> <seq_num> 51106 NOTICE User change password: Authentication for web services failed, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 51106 NOTICE User change password: Authentication for web services failed, <log details>

- 消息代码：51107

严重性：通知 (NOTICE)

消息文本：新密码无效 (Invalid new password)

消息说明：新密码无效

本地目标消息格式：<timestamp> <seq_num> 51107 NOTICE User change password: Invalid new password, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 51107 NOTICE User change password: Invalid new password, <log details>

- 消息代码：51115

严重性：通知 (NOTICE)

消息文本：新密码无效。(The new password is invalid.) 此密码以前用过。

消息说明：新密码无效。此密码以前用过。

本地目标消息格式：<timestamp> <seq_num> 51115 NOTICE User change password: The new password is invalid. This password has been previously used., <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 51115 NOTICE User change password: The new password is invalid. This password has been previously used., <log details>

- 消息代码：51116

严重性：通知 (NOTICE)

消息文本: 新密码无效。(Invalid new password.) 密码不得包含字典单词或倒序使用其字符

消息说明: 新密码无效。密码不得包含字典单词或倒序使用其字符

本地目标消息格式: <timestamp> <seq_num> 51116 NOTICE User change password: Invalid new password. Password must not contain dictionary words or their characters in reverse order, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 51116 NOTICE User change password: Invalid new password. Password must not contain dictionary words or their characters in reverse order, <log details>

- 消息代码: 52000

严重性: 通知 (NOTICE)

消息文本: 已添加配置 (Added configuration)

消息说明: 已添加配置

本地目标消息格式: <timestamp> <seq_num> 52000 NOTICE Configuration-Changes: Added configuration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 52000 NOTICE Configuration-Changes: Added configuration, <log details>

- 消息代码: 52001

严重性: 通知 (NOTICE)

消息文本: 已更改配置 (Changed configuration)

消息说明: 已更改配置

本地目标消息格式: <timestamp> <seq_num> 52001 NOTICE Configuration-Changes: Changed configuration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 52001 NOTICE Configuration-Changes: Changed configuration, <log details>

- 消息代码: 52002

严重性: 通知 (NOTICE)

消息文本: 已删除配置 (Deleted configuration)

消息说明: 已删除配置

本地目标消息格式: <timestamp> <seq_num> 52002 NOTICE Configuration-Changes: Deleted configuration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 52002 NOTICE Configuration-Changes: Deleted configuration, <log details>

- 消息代码: 52003
严重性: 通知 (NOTICE)
消息文本: 注销节点 (Deregister Node)
消息说明: 部署中的一个 ISE 实例已被注销。
本地目标消息格式: <timestamp> <seq_num> 52003 NOTICE Distributed-Management: Deregister Node, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52003 NOTICE Distributed-Management: Deregister Node, <log details>
- 消息代码: 52004
严重性: 通知 (NOTICE)
消息文本: 注册节点 (Register Node)
消息说明: 已注册一个新的 ISE 实例, 并且它已加入部署。
本地目标消息格式: <timestamp> <seq_num> 52004 NOTICE Distributed-Management: Register Node, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52004 NOTICE Distributed-Management: Register Node, <log details>
- 消息代码: 52005
严重性: 通知 (NOTICE)
消息文本: 激活节点 (Activate Node)
消息说明: 已激活一个 ISE 实例, 以便从主节点接收更新。
本地目标消息格式: <timestamp> <seq_num> 52005 NOTICE Distributed-Management: Activate Node, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52005 NOTICE Distributed-Management: Activate Node, <log details>
- 消息代码: 52006
严重性: 通知 (NOTICE)
消息文本: 停用 ISE 节点 (Deactivate ISE Node)
消息说明: 一个 ISE 实例已停用, 不再从主节点接收更新。
本地目标消息格式: <timestamp> <seq_num> 52006 NOTICE Distributed-Management: Deactivate ISE Node, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 52006 NOTICE Distributed-Management:
Deactivate ISE Node, <log details>

- 消息代码: 52007

严重性: 通知 (NOTICE)

消息文本: 强制完全复制 (Force Full replication)

消息说明: 已为 ISE 实例发出强制完全复制命令。

本地目标消息格式: <timestamp> <seq_num> 52007 NOTICE Distributed-Management: Force Full
replication, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 52007 NOTICE Distributed-Management:
Force Full replication, <log details>

- 消息代码: 52008

严重性: 通知 (NOTICE)

消息文本: 更换注册处理程序 (Replacement Register Handler)

消息说明: 新的 ISE 实例已通过硬件更换加入部署。

本地目标消息格式: <timestamp> <seq_num> 52008 NOTICE Distributed-Management: Replacement
Register Handler, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 52008 NOTICE Distributed-Management:
Replacement Register Handler, <log details>

- 消息代码: 52009

严重性: 通知 (NOTICE)

消息文本: 升级节点 (Promote Node)

消息说明: 辅助节点已升级为部署的主节点。

本地目标消息格式: <timestamp> <seq_num> 52009 NOTICE Distributed-Management: Promote
Node, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 52009 NOTICE Distributed-Management:
Promote Node, <log details>

- 消息代码: 52010

严重性: 通知 (NOTICE)

消息文本: 升级节点处理程序 (Promote Node Handler)

消息说明: 辅助节点已升级为部署的主节点。

本地目标消息格式: <timestamp> <seq_num> 52010 NOTICE Distributed-Management: Promote Node Handler, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52010 NOTICE Distributed-Management: Promote Node Handler, <log details>

- 消息代码: 52011

严重性: 通知 (NOTICE)

消息文本: 本地模式 (Local Mode)

消息说明: ISE 实例已切换到本地模式运行, 不再从主节点接收更新。

本地目标消息格式: <timestamp> <seq_num> 52011 NOTICE Distributed-Management: Local Mode, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52011 NOTICE Distributed-Management: Local Mode, <log details>

- 消息代码: 52012

严重性: 通知 (NOTICE)

消息文本: 本地模式处理程序 (Local Mode Handler)

消息说明: ISE 实例已切换到本地模式运行, 不再从主节点接收更新。

本地目标消息格式: <timestamp> <seq_num> 52012 NOTICE Distributed-Management: Local Mode Handler, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52012 NOTICE Distributed-Management: Local Mode Handler, <log details>

- 消息代码: 52013

严重性: 通知 (NOTICE)

消息文本: 硬件更换 (Hardware Replacement)

消息说明: 新的 ISE 实例已通过硬件更换加入部署。

本地目标消息格式: <timestamp> <seq_num> 52013 NOTICE Distributed-Management: Hardware Replacement, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52013 NOTICE Distributed-Management: Hardware Replacement, <log details>

- 消息代码: 52014

严重性: 通知 (NOTICE)

消息文本: 注销处理程序 (Deregister Handler)

消息说明：部署中的一个 ISE 实例已被注销。

本地目标消息格式：<timestamp> <seq_num> 52014 NOTICE Distributed-Management: Deregister Handler, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52014 NOTICE Distributed-Management: Deregister Handler, <log details>

- 消息代码：52015

严重性：通知 (NOTICE)

消息文本：启用日志收集器目标 (Enable LogCollector Target)

消息说明：启用部署日志收集器目标。

本地目标消息格式：<timestamp> <seq_num> 52015 NOTICE Distributed-Management: Enable LogCollector Target, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52015 NOTICE Distributed-Management: Enable LogCollector Target, <log details>

- 消息代码：52016

严重性：通知 (NOTICE)

消息文本：选择日志收集器节点 (Select LogCollector Node)

消息说明：已选择部署的日志收集器节点。

本地目标消息格式：<timestamp> <seq_num> 52016 NOTICE Distributed-Management: Select LogCollector Node, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52016 NOTICE Distributed-Management: Select LogCollector Node, <log details>

- 消息代码：52017

严重性：通知 (NOTICE)

消息文本：应用软件更新 (Apply software update)

消息说明：对选定的 ISE 实例应用软件更新。

本地目标消息格式：<timestamp> <seq_num> 52017 NOTICE Distributed-Management: Apply software update, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52017 NOTICE Distributed-Management: Apply software update, <log details>

- 消息代码：52018

严重性：通知 (NOTICE)

消息文本: 正覆盖 ISE 实例日志类别 (Overriding an ISE Instances Log Categories)

消息说明: ISE 实例已覆盖其日志类别, 以允许在“全局日志类别”配置之外对它单独进行配置。

本地目标消息格式: <timestamp> <seq_num> 52018 NOTICE Distributed-Management: Overriding an ISE Instances Log Categories, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52018 NOTICE Distributed-Management: Overriding an ISE Instances Log Categories, <log details>

- 消息代码: 52019

严重性: 通知 (NOTICE)

消息文本: 正将 ISE 实例日志类别恢复为“全局” (Restoring an ISE Instances Log Categories to Global)

消息说明: ISE 实例已将其日志类别恢复为使用“全局日志类别”配置。

本地目标消息格式: <timestamp> <seq_num> 52019 NOTICE Distributed-Management: Restoring an ISE Instances Log Categories to Global, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52019 NOTICE Distributed-Management: Restoring an ISE Instances Log Categories to Global, <log details>

- 消息代码: 52020

严重性: 通知 (NOTICE)

消息文本: 完全复制 (Full Replication)

消息说明: 主节点请求完全复制

本地目标消息格式: <timestamp> <seq_num> 52020 NOTICE Distributed-Management: Full Replication, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52020 NOTICE Distributed-Management: Full Replication, <log details>

- 消息代码: 52021

严重性: 通知 (NOTICE)

消息文本: 完全复制请求 (Full replication request)

消息说明: 辅助节点请求完全复制

本地目标消息格式: <timestamp> <seq_num> 52021 NOTICE Distributed-Management: Full replication request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52021 NOTICE Distributed-Management: Full replication request, <log details>

- 消息代码: 52022
严重性: 通知 (NOTICE)
消息文本: 完全复制 (Full replication)
消息说明: 在主节点和辅助节点之间创建链接
本地目标消息格式: <timestamp> <seq_num> 52022 NOTICE Distributed-Management: Full replication, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52022 NOTICE Distributed-Management: Full replication, <log details>
- 消息代码: 52023
严重性: 通知 (NOTICE)
消息文本: 完全复制失败 (Full replication failed)
消息说明: 未能在主节点和辅助节点之间创建链接
本地目标消息格式: <timestamp> <seq_num> 52023 NOTICE Distributed-Management: Full replication failed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52023 NOTICE Distributed-Management: Full replication failed, <log details>
- 消息代码: 52024
严重性: 通知 (NOTICE)
消息文本: 完全复制 (Full replication)
消息说明: 正在节点上创建本地凭证文件
本地目标消息格式: <timestamp> <seq_num> 52024 NOTICE Distributed-Management: Full replication, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52024 NOTICE Distributed-Management: Full replication, <log details>
- 消息代码: 52025
严重性: 通知 (NOTICE)
消息文本: 完全复制 (Full replication)
消息说明: 正检索远程数据库密钥
本地目标消息格式: <timestamp> <seq_num> 52025 NOTICE Distributed-Management: Full replication, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 52025 NOTICE Distributed-Management:
Full replication, <log details>

- 消息代码: 52026

严重性: 通知 (NOTICE)

消息文本: 完全复制 (Full replication)

消息说明: 正通过安全的 Sybase 信道从主节点检索数据库

本地目标消息格式: <timestamp> <seq_num> 52026 NOTICE Distributed-Management: Full replication,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 52026 NOTICE Distributed-Management:
Full replication, <log details>

- 消息代码: 52027

严重性: 通知 (NOTICE)

消息文本: 完全复制 (Full replication)

消息说明: 正停止消息总线心跳信道

本地目标消息格式: <timestamp> <seq_num> 52027 NOTICE Distributed-Management: Full replication,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 52027 NOTICE Distributed-Management:
Full replication, <log details>

- 消息代码: 52028

严重性: 通知 (NOTICE)

消息文本: 完全复制 (Full replication)

消息说明: 正删除备份文件

本地目标消息格式: <timestamp> <seq_num> 52028 NOTICE Distributed-Management: Full replication,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 52028 NOTICE Distributed-Management:
Full replication, <log details>

- 消息代码: 52029

严重性: 通知 (NOTICE)

消息文本: 完全复制 (Full replication)

消息说明: 正运行清理脚本并重启 ISE 服务

本地目标消息格式: <timestamp> <seq_num> 52029 NOTICE Distributed-Management: Full replication, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52029 NOTICE Distributed-Management: Full replication, <log details>

- 消息代码: 52030

严重性: 通知 (NOTICE)

消息文本: 完全复制成功 (Full replication succeeded)

消息说明: 完全复制已成功完成

本地目标消息格式: <timestamp> <seq_num> 52030 NOTICE Distributed-Management: Full replication succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52030 NOTICE Distributed-Management: Full replication succeeded, <log details>

- 消息代码: 52031

严重性: 通知 (NOTICE)

消息文本: 完全复制失败 (Full replication failed)

消息说明: 未能完成完全复制

本地目标消息格式: <timestamp> <seq_num> 52031 NOTICE Distributed-Management: Full replication failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52031 NOTICE Distributed-Management: Full replication failed, <log details>

- 消息代码: 52032

严重性: 通知 (NOTICE)

消息文本: 注册请求 (Registration request)

消息说明: 一个 ISE 实例请求加入分布式环境

本地目标消息格式: <timestamp> <seq_num> 52032 NOTICE Distributed-Management: Registration request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52032 NOTICE Distributed-Management: Registration request, <log details>

- 消息代码: 52033

严重性: 通知 (NOTICE)

消息文本: 注册成功 (Registration succeeded)

消息说明: 注册主节点已成功完成

本地目标消息格式: <timestamp> <seq_num> 52033 NOTICE Distributed-Management: Registration succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 52033 NOTICE Distributed-Management: Registration succeeded, <log details>

- 消息代码: 52034

严重性: 通知 (NOTICE)

消息文本: 注册请求 (Registration request)

消息说明: 主实例已请求完全复制

本地目标消息格式: <timestamp> <seq_num> 52034 NOTICE Distributed-Management: Registration request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 52034 NOTICE Distributed-Management: Registration request, <log details>

- 消息代码: 52035

严重性: 通知 (NOTICE)

消息文本: 注册失败 (Registration failed)

消息说明: 未能执行主实例请求的完全复制

本地目标消息格式: <timestamp> <seq_num> 52035 NOTICE Distributed-Management: Registration failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 52035 NOTICE Distributed-Management: Registration failed, <log details>

- 消息代码: 52036

严重性: 通知 (NOTICE)

消息文本: 注册 (Registration)

消息说明: 正将 ISE 实例从主实例改为辅助实例

本地目标消息格式: <timestamp> <seq_num> 52036 NOTICE Distributed-Management: Registration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 52036 NOTICE Distributed-Management: Registration, <log details>

- 消息代码: 52037

严重性: 通知 (NOTICE)

消息文本: 注册 (Registration)

消息说明: 正在数据库中将主实例更新为辅助实例

本地目标消息格式: <timestamp> <seq_num> 52037 NOTICE Distributed-Management: Registration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 52037 NOTICE Distributed-Management: Registration, <log details>

- 消息代码: 52038

严重性: 通知 (NOTICE)

消息文本: 注册成功 (Registration succeeded)

消息说明: ISE 实例成功加入分布式 ISE 部署

本地目标消息格式: <timestamp> <seq_num> 52038 NOTICE Distributed-Management: Registration succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 52038 NOTICE Distributed-Management: Registration succeeded, <log details>

- 消息代码: 52039

严重性: 通知 (NOTICE)

消息文本: 注册失败 (Registration failed)

消息说明: ISE 实例无法加入分布式部署

本地目标消息格式: <timestamp> <seq_num> 52039 NOTICE Distributed-Management: Registration failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 52039 NOTICE Distributed-Management: Registration failed, <log details>

- 消息代码: 52040

严重性: 通知 (NOTICE)

消息文本: 升级请求 (Promotion request)

消息说明: 已发出升级辅助实例的请求

本地目标消息格式: <timestamp> <seq_num> 52040 NOTICE Distributed-Management: Promotion request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 52040 NOTICE Distributed-Management: Promotion request, <log details>

- 消息代码: 52041

严重性: 通知 (NOTICE)

消息文本: 升级请求 (Promotion request)

消息说明: 一个辅助实例请求升级为主实例

本地目标消息格式: <timestamp> <seq_num> 52041 NOTICE Distributed-Management: Promotion request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52041 NOTICE Distributed-Management: Promotion request, <log details>

- 消息代码: 52042

严重性: 通知 (NOTICE)

消息文本: 降级成功 (Demotion succeeded)

消息说明: 现有主实例降级已成功完成

本地目标消息格式: <timestamp> <seq_num> 52042 NOTICE Distributed-Management: Demotion succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52042 NOTICE Distributed-Management: Demotion succeeded, <log details>

- 消息代码: 52043

严重性: 通知 (NOTICE)

消息文本: 降级失败 (Demotion failed)

消息说明: 现有主实例降级失败

本地目标消息格式: <timestamp> <seq_num> 52043 NOTICE Distributed-Management: Demotion failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52043 NOTICE Distributed-Management: Demotion failed, <log details>

- 消息代码: 52044

严重性: 通知 (NOTICE)

消息文本: 升级 (Promotion)

消息说明: 全局部署 ID 已成功更新

本地目标消息格式: <timestamp> <seq_num> 52044 NOTICE Distributed-Management: Promotion, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52044 NOTICE Distributed-Management: Promotion, <log details>

- 消息代码: 52045
严重性: 通知 (NOTICE)
消息文本: 升级成功 (Promotion succeeded)
消息说明: 辅助实例升级已成功完成
本地目标消息格式: <timestamp> <seq_num> 52045 NOTICE Distributed-Management: Promotion succeeded, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52045 NOTICE Distributed-Management: Promotion succeeded, <log details>
- 消息代码: 52046
严重性: 通知 (NOTICE)
消息文本: 升级失败 (Promotion failed)
消息说明: 辅助实例升级失败
本地目标消息格式: <timestamp> <seq_num> 52046 NOTICE Distributed-Management: Promotion failed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52046 NOTICE Distributed-Management: Promotion failed, <log details>
- 消息代码: 52047
严重性: 通知 (NOTICE)
消息文本: 本地模式重新连接请求
消息说明: 本地模式下的 ISE 实例发出重新连接到部署的请求
本地目标消息格式: <timestamp> <seq_num> 52047 NOTICE Distributed-Management: Local mode reconnect request, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52047 NOTICE Distributed-Management: Local mode reconnect request, <log details>
- 消息代码: 52048
严重性: 通知 (NOTICE)
消息文本: 本地模式启动 (Local mode start)
消息说明: 本地模式下的 ISE 实例向主实例发出远程呼叫, 以重新连接到部署
本地目标消息格式: <timestamp> <seq_num> 52048 NOTICE Distributed-Management: Local mode start, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 52048 NOTICE Distributed-Management:
Local mode start, <log details>

- 消息代码: 52049

严重性: 通知 (NOTICE)

消息文本: 本地模式重新连接 (Local mode reconnect)

消息说明: 启动本地模式下的 ISE 实例的完全复制

本地目标消息格式: <timestamp> <seq_num> 52049 NOTICE Distributed-Management: Local mode
reconnect, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 52049 NOTICE Distributed-Management:
Local mode reconnect, <log details>

- 消息代码: 52050

严重性: 通知 (NOTICE)

消息文本: 本地模式重新连接 (Local mode reconnect)

消息说明: 正将 ISE 实例状态更改为辅助

本地目标消息格式: <timestamp> <seq_num> 52050 NOTICE Distributed-Management: Local mode
reconnect, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 52050 NOTICE Distributed-Management:
Local mode reconnect, <log details>

- 消息代码: 52051

严重性: 通知 (NOTICE)

消息文本: 本地模式重新连接 (Local mode reconnect)

消息说明: 正在数据库中将主实例状态更新为辅助

本地目标消息格式: <timestamp> <seq_num> 52051 NOTICE Distributed-Management: Local mode
reconnect, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 52051 NOTICE Distributed-Management:
Local mode reconnect, <log details>

- 消息代码: 52052

严重性: 通知 (NOTICE)

消息文本: 本地模式重新连接成功 (Local mode reconnect succeeded)

消息说明: 将本地模式实例重新连接到部署已成功完成

本地目标消息格式: <timestamp> <seq_num> 52052 NOTICE Distributed-Management: Local mode reconnect succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52052 NOTICE Distributed-Management: Local mode reconnect succeeded, <log details>

- 消息代码: 52053

严重性: 通知 (NOTICE)

消息文本: 本地模式重新连接失败 (Local mode reconnect failed)

消息说明: 将本地模式实例重新连接到部署失败

本地目标消息格式: <timestamp> <seq_num> 52053 NOTICE Distributed-Management: Local mode reconnect failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52053 NOTICE Distributed-Management: Local mode reconnect failed, <log details>

- 消息代码: 52054

严重性: 通知 (NOTICE)

消息文本: 本地模式请求 (Local mode request)

消息说明: 已发出本地模式请求

本地目标消息格式: <timestamp> <seq_num> 52054 NOTICE Distributed-Management: Local mode request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52054 NOTICE Distributed-Management: Local mode request, <log details>

- 消息代码: 52055

严重性: 通知 (NOTICE)

消息文本: 本地模式请求 (Local mode request)

消息说明: 辅助实例请求置于本地模式下

本地目标消息格式: <timestamp> <seq_num> 52055 NOTICE Distributed-Management: Local mode request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52055 NOTICE Distributed-Management: Local mode request, <log details>

- 消息代码: 52056

严重性: 通知 (NOTICE)

消息文本: 本地模式 (Local mode)

消息说明: 正将 ISE 实例状态更改为本地模式

本地目标消息格式: <timestamp> <seq_num> 52056 NOTICE Distributed-Management: Local mode, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52056 NOTICE Distributed-Management: Local mode, <log details>

- 消息代码: 52057

严重性: 通知 (NOTICE)

消息文本: 本地模式 (Local mode)

消息说明: 正在数据库中将实例状态更新为本地模式

本地目标消息格式: <timestamp> <seq_num> 52057 NOTICE Distributed-Management: Local mode, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52057 NOTICE Distributed-Management: Local mode, <log details>

- 消息代码: 52058

严重性: 通知 (NOTICE)

消息文本: 本地模式成功 (Local mode succeeded)

消息说明: 本地模式请求已成功完成

本地目标消息格式: <timestamp> <seq_num> 52058 NOTICE Distributed-Management: Local mode succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52058 NOTICE Distributed-Management: Local mode succeeded, <log details>

- 消息代码: 52059

严重性: 通知 (NOTICE)

消息文本: 本地模式失败 (Local mode failed)

消息说明: 本地模式请求失败

本地目标消息格式: <timestamp> <seq_num> 52059 NOTICE Distributed-Management: Local mode failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52059 NOTICE Distributed-Management: Local mode failed, <log details>

- 消息代码: 52060

严重性: 通知 (NOTICE)

消息文本: 注销请求 (Deregister request)

消息说明: 主节点请求从分布式部署中注销辅助节点

本地目标消息格式: <timestamp> <seq_num> 52060 NOTICE Distributed-Management: Deregister request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 52060 NOTICE Distributed-Management: Deregister request, <log details>

- 消息代码: 52061

严重性: 通知 (NOTICE)

消息文本: 注销请求 (Deregister request)

消息说明: 辅助节点请求从分布式部署中注销

本地目标消息格式: <timestamp> <seq_num> 52061 NOTICE Distributed-Management: Deregister request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 52061 NOTICE Distributed-Management: Deregister request, <log details>

- 消息代码: 52062

严重性: 通知 (NOTICE)

消息文本: 注销 (Deregister)

消息说明: 正删除辅助节点和主节点之间的连接

本地目标消息格式: <timestamp> <seq_num> 52062 NOTICE Distributed-Management: Deregister, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 52062 NOTICE Distributed-Management: Deregister, <log details>

- 消息代码: 52063

严重性: 通知 (NOTICE)

消息文本: 注销 (Deregister)

消息说明: 正在重启注册心跳信道

本地目标消息格式: <timestamp> <seq_num> 52063 NOTICE Distributed-Management: Deregister, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 52063 NOTICE Distributed-Management: Deregister, <log details>

- 消息代码: 52070

严重性: 通知 (NOTICE)

消息文本: 注销请求 (Deregister request)

消息说明: 辅助节点请求主节点自行注销

本地目标消息格式: <timestamp> <seq_num> 52070 NOTICE Distributed-Management: Deregister request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52070 NOTICE Distributed-Management: Deregister request, <log details>

- 消息代码: 52071

严重性: 通知 (NOTICE)

消息文本: 注销 (Deregister)

消息说明: 主节点已删除辅助证书信息

本地目标消息格式: <timestamp> <seq_num> 52071 NOTICE Distributed-Management: Deregister, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52071 NOTICE Distributed-Management: Deregister, <log details>

- 消息代码: 52072

严重性: 通知 (NOTICE)

消息文本: 注销成功 (Deregister succeeded)

消息说明: 注销已成功完成

本地目标消息格式: <timestamp> <seq_num> 52072 NOTICE Distributed-Management: Deregister succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52072 NOTICE Distributed-Management: Deregister succeeded, <log details>

- 消息代码: 52073

严重性: 通知 (NOTICE)

消息文本: 注销失败 (Deregister failed)

消息说明: 注销失败

本地目标消息格式: <timestamp> <seq_num> 52073 NOTICE Distributed-Management: Deregister failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52073 NOTICE Distributed-Management: Deregister failed, <log details>

- 消息代码: 52074
严重性: 通知 (NOTICE)
消息文本: 删除节点请求 (Delete node request)
消息说明: 处于非活动模式的 ISE 辅助实例请求从部署断开连接
本地目标消息格式: <timestamp> <seq_num> 52074 NOTICE Distributed-Management: Delete node request, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52074 NOTICE Distributed-Management: Delete node request, <log details>
- 消息代码: 52075
严重性: 通知 (NOTICE)
消息文本: 删除节点请求 (Delete node request)
消息说明: 处于非活动模式的 ISE 辅助实例请求从主实例断开连接
本地目标消息格式: <timestamp> <seq_num> 52075 NOTICE Distributed-Management: Delete node request, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52075 NOTICE Distributed-Management: Delete node request, <log details>
- 消息代码: 52076
严重性: 通知 (NOTICE)
消息文本: 删除节点请求 (Delete node request)
消息说明: ISE 主实例请求删除处于非活动模式的辅助实例
本地目标消息格式: <timestamp> <seq_num> 52076 NOTICE Distributed-Management: Delete node request, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52076 NOTICE Distributed-Management: Delete node request, <log details>
- 消息代码: 52077
严重性: 通知 (NOTICE)
消息文本: 删除节点 (Delete node)
消息说明: 处于非活动模式的 ISE 辅助实例已成功从部署断开连接
本地目标消息格式: <timestamp> <seq_num> 52077 NOTICE Distributed-Management: Delete node, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 52077 NOTICE Distributed-Management:
Delete node, <log details>

- 消息代码: 52078

严重性: 通知 (NOTICE)

消息文本: 删除节点失败 (Delete node failed)

消息说明: 无法从部署删除处于非活动模式的 ISE 辅助实例

本地目标消息格式: <timestamp> <seq_num> 52078 NOTICE Distributed-Management: Delete node
failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 52078 NOTICE Distributed-Management:
Delete node failed, <log details>

- 消息代码: 52079

严重性: 通知 (NOTICE)

消息文本: 删除节点成功 (Delete node succeeded)

消息说明: ISE 主实例已成功删除处于非活动模式的辅助实例

本地目标消息格式: <timestamp> <seq_num> 52079 NOTICE Distributed-Management: Delete node
succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 52079 NOTICE Distributed-Management:
Delete node succeeded, <log details>

- 消息代码: 52080

严重性: 通知 (NOTICE)

消息文本: 删除节点失败 (Delete node failed)

消息说明: 无法从主实例中删除处于非活动模式的 ISE 辅助实例

本地目标消息格式: <timestamp> <seq_num> 52080 NOTICE Distributed-Management: Delete node
failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 52080 NOTICE Distributed-Management:
Delete node failed, <log details>

- 消息代码: 52081

严重性: 通知 (NOTICE)

消息文本: 备份请求 (Backup request)

消息说明: 已请求立即备份辅助实例

本地目标消息格式: <timestamp> <seq_num> 52081 NOTICE DB-Management: Backup request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52081 NOTICE DB-Management: Backup request, <log details>

- 消息代码: 52082

严重性: 通知 (NOTICE)

消息文本: 备份失败 (Backup failed)

消息说明: 立即备份辅助实例失败

本地目标消息格式: <timestamp> <seq_num> 52082 NOTICE DB-Management: Backup failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52082 NOTICE DB-Management: Backup failed, <log details>

- 消息代码: 52083

严重性: 通知 (NOTICE)

消息文本: 备份请求 (Backup request)

消息说明: 已请求立即备份主实例

本地目标消息格式: <timestamp> <seq_num> 52083 NOTICE DB-Management: Backup request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52083 NOTICE DB-Management: Backup request, <log details>

- 消息代码: 52084

严重性: 通知 (NOTICE)

消息文本: 备份成功 (Backup succeeded)

消息说明: 立即备份主实例已成功完成

本地目标消息格式: <timestamp> <seq_num> 52084 NOTICE DB-Management: Backup succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52084 NOTICE DB-Management: Backup succeeded, <log details>

- 消息代码: 52085

严重性: 通知 (NOTICE)

消息文本: 备份失败 (Backup failed)

消息说明: 立即备份主实例失败

本地目标消息格式: <timestamp> <seq_num> 52085 NOTICE DB-Management: Backup failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52085 NOTICE DB-Management: Backup failed, <log details>

- 消息代码: 52086

严重性: 通知 (NOTICE)

消息文本: 软件更新请求 (Software update request)

消息说明: 已请求软件更新

本地目标消息格式: <timestamp> <seq_num> 52086 NOTICE Software-Management: Software update request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52086 NOTICE Software-Management: Software update request, <log details>

- 消息代码: 52088

严重性: 通知 (NOTICE)

消息文本: 软件更新 (Software update)

消息说明: 正在应用软件更新

本地目标消息格式: <timestamp> <seq_num> 52088 NOTICE Software-Management: Software update, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52088 NOTICE Software-Management: Software update, <log details>

- 消息代码: 52089

严重性: 通知 (NOTICE)

消息文本: 软件更新 (Software update)

消息说明: 软件更新要求在更新之前进行备份

本地目标消息格式: <timestamp> <seq_num> 52089 NOTICE Software-Management: Software update, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52089 NOTICE Software-Management: Software update, <log details>

- 消息代码: 52090

严重性: 通知 (NOTICE)

消息文本: 软件更新 (Software update)

消息说明: 软件更新正在从主实例下载更新捆绑包

本地目标消息格式: <timestamp> <seq_num> 52090 NOTICE Software-Management: Software update, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 52090 NOTICE Software-Management: Software update, <log details>

- 消息代码: 52091

严重性: 通知 (NOTICE)

消息文本: 软件更新失败 (Software update failed)

消息说明: 软件更新的更新捆绑包下载失败

本地目标消息格式: <timestamp> <seq_num> 52091 NOTICE Software-Management: Software update failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 52091 NOTICE Software-Management: Software update failed, <log details>

- 消息代码: 52092

严重性: 通知 (NOTICE)

消息文本: 软件更新成功 (Software update succeeded)

消息说明: 软件更新已成功完成

本地目标消息格式: <timestamp> <seq_num> 52092 NOTICE Software-Management: Software update succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 52092 NOTICE Software-Management: Software update succeeded, <log details>

- 消息代码: 52093

严重性: 通知 (NOTICE)

消息文本: 软件更新失败 (Software update failed)

消息说明: 软件更新失败

本地目标消息格式: <timestamp> <seq_num> 52093 NOTICE Software-Management: Software update failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 52093 NOTICE Software-Management: Software update failed, <log details>

- 消息代码: 52094

严重性: 通知 (NOTICE)

消息文本: 激活请求 (Activate request)

消息说明: 请求激活辅助实例

本地目标消息格式: <timestamp> <seq_num> 52094 NOTICE Distributed-Management: Activate request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52094 NOTICE Distributed-Management: Activate request, <log details>

- 消息代码: 52095

严重性: 通知 (NOTICE)

消息文本: 注册 (Register)

消息说明: 请求在部署中对辅助实例执行硬件更换

本地目标消息格式: <timestamp> <seq_num> 52095 NOTICE Distributed-Management: Register, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52095 NOTICE Distributed-Management: Register, <log details>

- 消息代码: 52096

严重性: 通知 (NOTICE)

消息文本: 激活 (Activate)

消息说明: 无法检索主实例信息

本地目标消息格式: <timestamp> <seq_num> 52096 NOTICE Distributed-Management: Activate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52096 NOTICE Distributed-Management: Activate, <log details>

- 消息代码: 52097

严重性: 通知 (NOTICE)

消息文本: 激活 (Activate)

消息说明: 请求辅助实例发起完全复制

本地目标消息格式: <timestamp> <seq_num> 52097 NOTICE Distributed-Management: Activate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52097 NOTICE Distributed-Management: Activate, <log details>

- 消息代码: 52098
严重性: 通知 (NOTICE)
消息文本: 激活 (Activate)
消息说明: 请求激活辅助实例已成功完成
本地目标消息格式: <timestamp> <seq_num> 52098 NOTICE Distributed-Management: Activate, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52098 NOTICE Distributed-Management: Activate, <log details>
- 消息代码: 52099
严重性: 通知 (NOTICE)
消息文本: 激活 (Activate)
消息说明: 请求激活辅助实例失败
本地目标消息格式: <timestamp> <seq_num> 52099 NOTICE Distributed-Management: Activate, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52099 NOTICE Distributed-Management: Activate, <log details>
- 消息代码: 52100
严重性: 通知 (NOTICE)
消息文本: 取消注册 (Deregister)
消息说明: 辅助实例上的检查状态进程检测到现在它已在主实例上取消注册。
本地目标消息格式: <timestamp> <seq_num> 52100 NOTICE Distributed-Management: Deregister, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52100 NOTICE Distributed-Management: Deregister, <log details>
- 消息代码: 52101
严重性: 通知 (NOTICE)
消息文本: 取消注册 (Deregister)
消息说明: 主实例上的检查状态进程检测到辅助实例已自行取消注册。
本地目标消息格式: <timestamp> <seq_num> 52101 NOTICE Distributed-Management: Deregister, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 52101 NOTICE Distributed-Management:
Deregister, <log details>

- 消息代码: 52102

严重性: 通知 (NOTICE)

消息文本: 计划备份 (SCHEDULED BACKUP)

消息说明: 在主实例上启动计划备份。

本地目标消息格式: <timestamp> <seq_num> 52102 NOTICE DB-Management: SCHEDULED
BACKUP, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 52102 NOTICE DB-Management:
SCHEDULED BACKUP, <log details>

- 消息代码: 52103

严重性: 通知 (NOTICE)

消息文本: 计划备份 (SCHEDULED BACKUP)

消息说明: 由于备份名称中存在无效字符, 因此计划备份无法启动。

本地目标消息格式: <timestamp> <seq_num> 52103 NOTICE DB-Management: SCHEDULED
BACKUP, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 52103 NOTICE DB-Management:
SCHEDULED BACKUP, <log details>

- 消息代码: 52104

严重性: 通知 (NOTICE)

消息文本: 计划备份 (SCHEDULED BACKUP)

消息说明: 由于存储库无效, 因此无法启动计划备份。

本地目标消息格式: <timestamp> <seq_num> 52104 NOTICE DB-Management: SCHEDULED
BACKUP, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 52104 NOTICE DB-Management:
SCHEDULED BACKUP, <log details>

- 消息代码: 52105

严重性: 通知 (NOTICE)

消息文本: 计划备份 (SCHEDULED BACKUP)

消息说明: 由于内部错误, 计划备份失败。

本地目标消息格式: <timestamp> <seq_num> 52105 NOTICE DB-Management: SCHEDULED BACKUP, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52105 NOTICE DB-Management: SCHEDULED BACKUP, <log details>

- 消息代码: 52106

严重性: 通知 (NOTICE)

消息文本: 计划备份 (SCHEDULED BACKUP)

消息说明: 计划备份已成功完成。

本地目标消息格式: <timestamp> <seq_num> 52106 NOTICE DB-Management: SCHEDULED BACKUP, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 52106 NOTICE DB-Management: SCHEDULED BACKUP, <log details>

- 消息代码: 57000

严重性: 通知 (NOTICE)

消息文本: 已删除滚动更新的本地日志文件 (Deleted rolled-over local log file(s))

消息说明: 已删除滚动更新的本地日志文件

本地目标消息格式: <timestamp> <seq_num> 57000 NOTICE Configuration-changes: Deleted rolled-over local log file(s), <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 57000 NOTICE Configuration-changes: Deleted rolled-over local log file(s), <log details>

- 消息代码: 58001

严重性: 通知 (NOTICE)

消息文本: ISE 进程已启动 (ISE process started)

消息说明: ISE 进程已启动

本地目标消息格式: <timestamp> <seq_num> 58001 NOTICE Process-Management: ISE process started, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58001 NOTICE Process-Management: ISE process started, <log details>

- 消息代码: 58002

严重性: 通知 (NOTICE)

消息文本: ISE 进程已停止 (ISE process stopped)

消息说明: ISE 进程已停止

本地目标消息格式: <timestamp> <seq_num> 58002 NOTICE Process-Management: ISE process stopped, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58002 NOTICE Process-Management: ISE process stopped, <log details>

- 消息代码: 58003

严重性: 通知 (NOTICE)

消息文本: ISE 进程已启动 (ISE processes started)

消息说明: 所有 ISE 进程已启动

本地目标消息格式: <timestamp> <seq_num> 58003 NOTICE Process-Management: ISE processes started, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58003 NOTICE Process-Management: ISE processes started, <log details>

- 消息代码: 58004

严重性: 通知 (NOTICE)

消息文本: ISE 进程已停止 (ISE processes stopped)

消息说明: 所有 ISE 进程已停止

本地目标消息格式: <timestamp> <seq_num> 58004 NOTICE Process-Management: ISE processes stopped, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58004 NOTICE Process-Management: ISE processes stopped, <log details>

- 消息代码: 58005

严重性: 通知 (NOTICE)

消息文本: 监视器服务已重启 ISE 进程 (ISE process was restarted by watchdog service)

消息说明: 监视器服务已重启 ISE 进程

本地目标消息格式: <timestamp> <seq_num> 58005 NOTICE Process-Management: ISE process was restarted by watchdog service, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58005 NOTICE Process-Management: ISE process was restarted by watchdog service, <log details>

- 消息代码: 58006

严重性: 通知 (NOTICE)

消息文本: 监视器配置已重新加载 (Watchdog configuration reloaded)

消息说明: 监视器配置已重新加载

本地目标消息格式: <timestamp> <seq_num> 58006 NOTICE Process-Management: Watchdog configuration reloaded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 58006 NOTICE Process-Management: Watchdog configuration reloaded, <log details>

- 消息代码: 58007

严重性: 通知 (NOTICE)

消息文本: ISE 进程报告启动/停止错误 (ISE process reported start/stop error)

消息说明: 一个 ISE 进程已报告启动或停止

本地目标消息格式: <timestamp> <seq_num> 58007 NOTICE Process-Management: ISE process reported start/stop error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 58007 NOTICE Process-Management: ISE process reported start/stop error, <log details>

- 消息代码: 58008

严重性: 通知 (NOTICE)

消息文本: CARS 备份完成 (CARS backup complete)

消息说明: CARS 备份已成功完成

本地目标消息格式: <timestamp> <seq_num> 58008 NOTICE DB-Management: CARS backup complete, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 58008 NOTICE DB-Management: CARS backup complete, <log details>

- 消息代码: 58009

严重性: 通知 (NOTICE)

消息文本: CARS 恢复完成 (CARS restore complete)

消息说明: CARS 恢复已成功完成

本地目标消息格式: <timestamp> <seq_num> 58009 NOTICE DB-Management: CARS restore complete, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 58009 NOTICE DB-Management: CARS restore complete, <log details>

- 消息代码: 58010

严重性: 通知 (NOTICE)

消息文本: ISE 数据库备份 (ISE database backup)

消息说明: ISE 数据库备份已成功完成

本地目标消息格式: <timestamp> <seq_num> 58010 NOTICE DB-Management: ISE database backup, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58010 NOTICE DB-Management: ISE database backup, <log details>

- 消息代码: 58011

严重性: 通知 (NOTICE)

消息文本: ISE 数据库恢复 (ISE database restore)

消息说明: ISE 数据库恢复已成功完成

本地目标消息格式: <timestamp> <seq_num> 58011 NOTICE DB-Management: ISE database restore, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58011 NOTICE DB-Management: ISE database restore, <log details>

- 消息代码: 58012

严重性: 通知 (NOTICE)

消息文本: 已收集 ISE 支持捆绑包 (ISE support bundle collected)

消息说明: 已收集 ISE 支持捆绑包

本地目标消息格式: <timestamp> <seq_num> 58012 NOTICE DB-Management: ISE support bundle collected, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58012 NOTICE DB-Management: ISE support bundle collected, <log details>

- 消息代码: 58013

严重性: 通知 (NOTICE)

消息文本: ISE 数据库重置 (ISE database reset)

消息说明: 已重置 ISE 数据库

本地目标消息格式: <timestamp> <seq_num> 58013 NOTICE DB-Management: ISE database reset, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58013 NOTICE DB-Management: ISE database reset, <log details>

- 消息代码: 58014
严重性: 通知 (NOTICE)
消息文本: ISE 核心文件已删除 (ISE core files deleted)
消息说明: 已删除 ISE 核心文件
本地目标消息格式: <timestamp> <seq_num> 58014 NOTICE File-Management: ISE core files deleted, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58014 NOTICE File-Management: ISE core files deleted, <log details>
- 消息代码: 58015
严重性: 通知 (NOTICE)
消息文本: ISE 日志文件已删除 (ISE log files deleted)
消息说明: 已删除 ISE 日志文件
本地目标消息格式: <timestamp> <seq_num> 58015 NOTICE File-Management: ISE log files deleted, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58015 NOTICE File-Management: ISE log files deleted, <log details>
- 消息代码: 58016
严重性: 通知 (NOTICE)
消息文本: ISE 升级 (ISE upgrade)
消息说明: ISE 升级已成功完成
本地目标消息格式: <timestamp> <seq_num> 58016 NOTICE Software-Management: ISE upgrade, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58016 NOTICE Software-Management: ISE upgrade, <log details>
- 消息代码: 58017
严重性: 通知 (NOTICE)
消息文本: ISE 补丁安装 (ISE patch install)
消息说明: ISE 补丁已成功安装
本地目标消息格式: <timestamp> <seq_num> 58017 NOTICE Software-Management: ISE patch install, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 58017 NOTICE Software-Management: ISE
patch install, <log details>

- 消息代码: 58018

严重性: 通知 (NOTICE)

消息文本: 已启用/禁用 ISE 迁移接口 (ISE migration interface enabled/disabled)

消息说明: 已启用或禁用 ISE 迁移接口

本地目标消息格式: <timestamp> <seq_num> 58018 NOTICE System-Management: ISE migration
interface enabled/disabled, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 58018 NOTICE System-Management: ISE
migration interface enabled/disabled, <log details>

- 消息代码: 58019

严重性: 通知 (NOTICE)

消息文本: 已重置 ISE 管理员密码 (ISE administrator password reset)

消息说明: 已重置 ISE 管理员密码

本地目标消息格式: <timestamp> <seq_num> 58019 NOTICE System-Management: ISE administrator
password reset, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 58019 NOTICE System-Management: ISE
administrator password reset, <log details>

- 消息代码: 58020

严重性: 通知 (NOTICE)

消息文本: 时钟已设置 (Clock set)

消息说明: 时钟已设置

本地目标消息格式: <timestamp> <seq_num> 58020 NOTICE System-Management: Clock set, <log
details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 58020 NOTICE System-Management: Clock
set, <log details>

- 消息代码: 58021

严重性: 通知 (NOTICE)

消息文本: 时区已设置 (Time zone set)

消息说明: 时区已设置

本地目标消息格式: <timestamp> <seq_num> 58021 NOTICE System-Management: Time zone set, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58021 NOTICE System-Management: Time zone set, <log details>

- 消息代码: 58022

严重性: 通知 (NOTICE)

消息文本: NTP 服务器已设置 (NTP Server set)

消息说明: NTP 服务器已设置

本地目标消息格式: <timestamp> <seq_num> 58022 NOTICE System-Management: NTP Server set, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58022 NOTICE System-Management: NTP Server set, <log details>

- 消息代码: 58023

严重性: 通知 (NOTICE)

消息文本: 主机名已设置 (Hostname set)

消息说明: 已设置主机名

本地目标消息格式: <timestamp> <seq_num> 58023 NOTICE System-Management: Hostname set, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58023 NOTICE System-Management: Hostname set, <log details>

- 消息代码: 58024

严重性: 通知 (NOTICE)

消息文本: IP 地址已设置 (IP address set)

消息说明: 已设置 IP 地址

本地目标消息格式: <timestamp> <seq_num> 58024 NOTICE System-Management: IP address set, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58024 NOTICE System-Management: IP address set, <log details>

- 消息代码: 58025

严重性: 通知 (NOTICE)

消息文本: IP 地址状态 (IP address state)

消息说明: IP 地址状态

本地目标消息格式: <timestamp> <seq_num> 58025 NOTICE System-Management: IP address state, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 58025 NOTICE System-Management: IP address state, <log details>

- 消息代码: 58026

严重性: 通知 (NOTICE)

消息文本: 默认网关已设置 (Default gateway set)

消息说明: 已设置默认网关

本地目标消息格式: <timestamp> <seq_num> 58026 NOTICE System-Management: Default gateway set, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 58026 NOTICE System-Management: Default gateway set, <log details>

- 消息代码: 58027

严重性: 通知 (NOTICE)

消息文本: 名称服务器已设置 (Name server set)

消息说明: 已设置名称服务器

本地目标消息格式: <timestamp> <seq_num> 58027 NOTICE System-Management: Name server set, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 58027 NOTICE System-Management: Name server set, <log details>

- 消息代码: 58028

严重性: 通知 (NOTICE)

消息文本: ADE OS Xfer 库错误 (ADE OS Xfer library error)

消息说明: ADE OS Xfer 库中出现错误

本地目标消息格式: <timestamp> <seq_num> 58028 NOTICE System-Management: ADE OS Xfer library error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 58028 NOTICE System-Management: ADE OS Xfer library error, <log details>

- 消息代码: 58029

严重性: 通知 (NOTICE)

消息文本: ADE OS 安装库错误 (ADE OS install library error)

消息说明: ADE OS 安装库中出现错误

本地目标消息格式: <timestamp> <seq_num> 58029 NOTICE System-Management: ADE OS install library error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58029 NOTICE System-Management: ADE OS install library error, <log details>

- 消息代码: 58030

严重性: 通知 (NOTICE)

消息文本: ISE 升级 - 方案更改 (ISE upgrade - schema change)

消息说明: ISE 方案升级完成

本地目标消息格式: <timestamp> <seq_num> 58030 NOTICE Software-Management: ISE upgrade - schema change, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58030 NOTICE Software-Management: ISE upgrade - schema change, <log details>

- 消息代码: 58031

严重性: 通知 (NOTICE)

消息文本: ISE 升级 - 词典 (ISE upgrade - dictionary)

消息说明: ISE 词典升级完成

本地目标消息格式: <timestamp> <seq_num> 58031 NOTICE Software-Management: ISE upgrade - dictionary, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58031 NOTICE Software-Management: ISE upgrade - dictionary, <log details>

- 消息代码: 58032

严重性: 通知 (NOTICE)

消息文本: ISE 升级 - 数据操作 (ISE upgrade - data manipulation)

消息说明: ISE 升级 - 数据操作阶段完成

本地目标消息格式: <timestamp> <seq_num> 58032 NOTICE Software-Management: ISE upgrade - data manipulation, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58032 NOTICE Software-Management: ISE upgrade - data manipulation, <log details>

- 消息代码: 58033

严重性: 通知 (NOTICE)

消息文本: ISE 升级 - AAC (ISE upgrade - AAC)

消息说明: ISE AAC 升级完成

本地目标消息格式: <timestamp> <seq_num> 58033 NOTICE Software-Management: ISE upgrade - AAC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58033 NOTICE Software-Management: ISE upgrade - AAC, <log details>

- 消息代码: 58034

严重性: 通知 (NOTICE)

消息文本: ISE 升级 - PKI (ISE upgrade - PKI)

消息说明: ISE PKI 升级完成

本地目标消息格式: <timestamp> <seq_num> 58034 NOTICE Software-Management: ISE upgrade - PKI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58034 NOTICE Software-Management: ISE upgrade - PKI, <log details>

- 消息代码: 58035

严重性: 通知 (NOTICE)

消息文本: ISE 升级 - MnT (ISE upgrade - MnT)

消息说明: MnT 升级完成

本地目标消息格式: <timestamp> <seq_num> 58035 NOTICE Software-Management: ISE upgrade - MnT, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58035 NOTICE Software-Management: ISE upgrade - MnT, <log details>

- 消息代码: 58036

严重性: 通知 (NOTICE)

消息文本: ISE 升级 (ISE upgrade)

消息说明: 已开始 ISE 升级

本地目标消息格式: <timestamp> <seq_num> 58036 NOTICE Software-Management: ISE upgrade, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58036 NOTICE Software-Management: ISE upgrade, <log details>

- 消息代码: 58037
严重性: 通知 (NOTICE)
消息文本: ISE 安装 (ISE install)
消息说明: 已开始 ISE 安装
本地目标消息格式: <timestamp> <seq_num> 58037 NOTICE Software-Management: ISE install, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58037 NOTICE Software-Management: ISE install, <log details>
- 消息代码: 58038
严重性: 通知 (NOTICE)
消息文本: 无法加入 AD (Failed to join to AD)
消息说明: AD 代理无法加入 AD 域
本地目标消息格式: <timestamp> <seq_num> 58038 NOTICE System-Management: Failed to join to AD, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58038 NOTICE System-Management: Failed to join to AD, <log details>
- 消息代码: 58039
严重性: 通知 (NOTICE)
消息文本: AD 加入 (AD join)
消息说明: AD 代理已加入 AD 域
本地目标消息格式: <timestamp> <seq_num> 58039 NOTICE System-Management: AD join, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58039 NOTICE System-Management: AD join, <log details>
- 消息代码: 58040
严重性: 通知 (NOTICE)
消息文本: AD 离开 (AD leave)
消息说明: AD 代理已离开 AD 域
本地目标消息格式: <timestamp> <seq_num> 58040 NOTICE System-Management: AD leave, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 58040 NOTICE System-Management: AD
leave, <log details>

- 消息代码: 58041

严重性: 通知 (NOTICE)

消息文本: 导入/导出过程已中止 (Import/export process aborted)

消息说明: 导入/导出过程已中止

本地目标消息格式: <timestamp> <seq_num> 58041 NOTICE System-Management: Import/export
process aborted, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 58041 NOTICE System-Management:
Import/export process aborted, <log details>

- 消息代码: 58042

严重性: 通知 (NOTICE)

消息文本: 导入/导出过程已开始 (Import/export process started)

消息说明: 导入/导出过程已开始

本地目标消息格式: <timestamp> <seq_num> 58042 NOTICE System-Management: Import/export
process started, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 58042 NOTICE System-Management:
Import/export process started, <log details>

- 消息代码: 58043

严重性: 通知 (NOTICE)

消息文本: 导入/导出过程完成 (Import/export process complete)

消息说明: 导入/导出过程完成

本地目标消息格式: <timestamp> <seq_num> 58043 NOTICE System-Management: Import/export
process complete, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 58043 NOTICE System-Management:
Import/export process complete, <log details>

- 消息代码: 58044

严重性: 通知 (NOTICE)

消息文本: 导入/导出过程中出错 (Error in import/export process)

消息说明: 导入/导出过程中出现错误

本地目标消息格式: <timestamp> <seq_num> 58044 NOTICE System-Management: Error in import/export process, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58044 NOTICE System-Management: Error in import/export process, <log details>

- 消息代码: 58045

严重性: 通知 (NOTICE)

消息文本: 只允许一个网络接口 (Only single network interface is allowed)

消息说明: 只允许一个网络接口

本地目标消息格式: <timestamp> <seq_num> 58045 NOTICE System-Management: Only single network interface is allowed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 58045 NOTICE System-Management: Only single network interface is allowed, <log details>

- 消息代码: 59000

严重性: 通知 (NOTICE)

消息文本: 收到撤销所有 PAC 的请求 (Received request to revoke all PACs)

消息说明: 管理员请求生成新的 EAP-FAST 种子密钥, 以撤销之前发布的所有与 EAP-FAST 相关的密钥和 PAC。

本地目标消息格式: <timestamp> <seq_num> 59000 NOTICE EAP-FAST: Received request to revoke all PACs, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59000 NOTICE EAP-FAST: Received request to revoke all PACs, <log details>

- 消息代码: 59001

严重性: 通知 (NOTICE)

消息文本: 已生成新的 EAP-FAST 种子密钥 (Generated new EAP-FAST seed key)

消息说明: 已成功生成新的 EAP-FAST 种子密钥。所有与 EAP-FAST 相关的密钥和 PAC 均将被撤销。

本地目标消息格式: <timestamp> <seq_num> 59001 NOTICE EAP-FAST: Generated new EAP-FAST seed key, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59001 NOTICE EAP-FAST: Generated new EAP-FAST seed key, <log details>

- 消息代码: 59002

严重性: 通知 (NOTICE)

消息文本: 已成功更新 EAP-FAST 种子密钥 (Successfully updated EAP-FAST seed key)

消息说明: 已成功更新 EAP-FAST 种子密钥, 该密钥将用于派生主密钥。已撤销之前生成的所有 EAP-FAST 密钥和 PAC。

本地目标消息格式: <timestamp> <seq_num> 59002 NOTICE EAP-FAST: Successfully updated EAP-FAST seed key, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59002 NOTICE EAP-FAST: Successfully updated EAP-FAST seed key, <log details>

- 消息代码: 59003

严重性: 通知 (NOTICE)

消息文本: 用户无权撤销所有 EAP-FAST PAC (User not authorized to revoke all EAP-FAST PACs)

消息说明: 用户未获得撤销所有 EAP-FAST PAC 的授权。

本地目标消息格式: <timestamp> <seq_num> 59003 NOTICE EAP-FAST: User not authorized to revoke all EAP-FAST PACs, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59003 NOTICE EAP-FAST: User not authorized to revoke all EAP-FAST PACs, <log details>

- 消息代码: 59004

严重性: 通知 (NOTICE)

消息文本: 尝试撤销 EAP-FAST 密钥和 PAC 期间超时 (Timed out during attempt to revoke EAP-FAST keys and PACs)

消息说明: 尝试撤销之前生成的 EAP-FAST 密钥和 PAC 时, ISE 运行时间超时。

本地目标消息格式: <timestamp> <seq_num> 59004 NOTICE EAP-FAST: Timed out during attempt to revoke EAP-FAST keys and PACs, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59004 NOTICE EAP-FAST: Timed out during attempt to revoke EAP-FAST keys and PACs, <log details>

- 消息代码: 59005

严重性: 通知 (NOTICE)

消息文本: 收到生成隧道 PAC 的请求 (Received request to generate Tunnel PAC)

消息说明: 管理员请求手动发布带外 EAP-FAST 隧道 PAC。

本地目标消息格式: <timestamp> <seq_num> 59005 NOTICE EAP-FAST: Received request to generate Tunnel PAC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 59005 NOTICE EAP-FAST: Received
request to generate Tunnel PAC, <log details>

- 消息代码: 59006

严重性: 通知 (NOTICE)

消息文本: 收到生成计算机 PAC 的请求 (Received request to generate Machine PAC)

消息说明: 管理员请求手动发布带外 EAP-FAST 计算机 PAC。

本地目标消息格式: <timestamp> <seq_num> 59006 NOTICE EAP-FAST: Received request to generate
Machine PAC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 59006 NOTICE EAP-FAST: Received
request to generate Machine PAC, <log details>

- 消息代码: 59007

严重性: 通知 (NOTICE)

消息文本: 无法生成 PAC (Failed to generate PAC)

消息说明: 尝试发布带外 EAP-FAST PAC 时遇到错误。

本地目标消息格式: <timestamp> <seq_num> 59007 NOTICE EAP-FAST: Failed to generate PAC,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 59007 NOTICE EAP-FAST: Failed to
generate PAC, <log details>

- 消息代码: 59008

严重性: 通知 (NOTICE)

消息文本: 已成功生成 PAC (Successfully generated PAC)

消息说明: 已成功手动发布带外 EAP-FAST PAC。

本地目标消息格式: <timestamp> <seq_num> 59008 NOTICE EAP-FAST: Successfully generated
PAC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 59008 NOTICE EAP-FAST: Successfully
generated PAC, <log details>

- 消息代码: 59009

严重性: 通知 (NOTICE)

消息文本: 收到生成 TrustSec PAC 的请求 (Received request to generate TrustSec PAC)

消息说明: 管理员请求手动发布带外 EAP-FAST TrustSec PAC。

本地目标消息格式: <timestamp> <seq_num> 59009 NOTICE SGA-PAC: Received request to generate TrustSec PAC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59009 NOTICE SGA-PAC: Received request to generate TrustSec PAC, <log details>

- 消息代码: 59010

严重性: 通知 (NOTICE)

消息文本: 无法生成 TrustSec PAC (Failed to generate TrustSec PAC)

消息说明: 尝试发布带外 EAP-FAST TrustSec PAC 时遇到错误。

本地目标消息格式: <timestamp> <seq_num> 59010 NOTICE SGA-PAC: Failed to generate TrustSec PAC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59010 NOTICE SGA-PAC: Failed to generate TrustSec PAC, <log details>

- 消息代码: 59011

严重性: 通知 (NOTICE)

消息文本: 已成功生成 TrustSec PAC (Successfully generated TrustSec PAC)

消息说明: 已成功手动发布带外 EAP-FAST TrustSec PAC。

本地目标消息格式: <timestamp> <seq_num> 59011 NOTICE SGA-PAC: Successfully generated TrustSec PAC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59011 NOTICE SGA-PAC: Successfully generated TrustSec PAC, <log details>

- 消息代码: 59050

严重性: 通知 (NOTICE)

消息文本: 收到撤销所有故障单的请求 (Received request to revoke all Tickets)

消息说明: 管理员请求生成新的 EAP-TLS 种子密钥, 以撤销之前发布的所有与 EAP-TLS 相关的密钥和故障单。

本地目标消息格式: <timestamp> <seq_num> 59050 NOTICE EAP-TLS: Received request to revoke all Tickets, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59050 NOTICE EAP-TLS: Received request to revoke all Tickets, <log details>

- 消息代码: 59051

严重性: 通知 (NOTICE)

消息文本: 已生成新的 EAP-TLS 种子密钥 (Generated new EAP-TLS seed key)

消息说明: 已成功生成新的 EAP-TLS 种子密钥。所有与 EAP-TLS 相关的密钥和故障单均将被撤销。

本地目标消息格式: <timestamp> <seq_num> 59051 NOTICE EAP-TLS: Generated new EAP-TLS seed key, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59051 NOTICE EAP-TLS: Generated new EAP-TLS seed key, <log details>

- 消息代码: 59052

严重性: 通知 (NOTICE)

消息文本: 已成功更新 EAP-TLS 种子密钥 (Successfully updated EAP-TLS seed key)

消息说明: 已成功更新 EAP-TLS 种子密钥, 该密钥将用于派生主密钥。已撤销之前生成的所有 EAP-TLS 密钥和故障单。

本地目标消息格式: <timestamp> <seq_num> 59052 NOTICE EAP-TLS: Successfully updated EAP-TLS seed key, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59052 NOTICE EAP-TLS: Successfully updated EAP-TLS seed key, <log details>

- 消息代码: 59100

严重性: 通知 (NOTICE)

消息文本: 删除本地存储日志 (Delete local store logs)

消息说明: 管理员请求删除本地存储日志

本地目标消息格式: <timestamp> <seq_num> 59100 NOTICE Log-Management: Delete local store logs, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59100 NOTICE Log-Management: Delete local store logs, <log details>

- 消息代码: 59101

严重性: 通知 (NOTICE)

消息文本: 删除本地存储日志 (Delete local store logs)

消息说明: 已成功删除本地存储日志文件

本地目标消息格式: <timestamp> <seq_num> 59101 NOTICE Log-Management: Delete local store logs, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59101 NOTICE Log-Management: Delete local store logs, <log details>

- 消息代码: 59102
严重性: 通知 (NOTICE)
消息文本: 删除本地存储日志 (Delete local store logs)
消息说明: 已成功删除本地存储日志文件
本地目标消息格式: <timestamp> <seq_num> 59102 NOTICE Log-Management: Delete local store logs, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59102 NOTICE Log-Management: Delete local store logs, <log details>
- 消息代码: 59103
严重性: 通知 (NOTICE)
消息文本: 删除本地存储日志 (Delete local store logs)
消息说明: 无法删除本地存储日志文件
本地目标消息格式: <timestamp> <seq_num> 59103 NOTICE Log-Management: Delete local store logs, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59103 NOTICE Log-Management: Delete local store logs, <log details>
- 消息代码: 59200
严重性: 通知 (NOTICE)
消息文本: 设置日志收集器 (Set log collector)
消息说明: 管理员请求设置日志收集器
本地目标消息格式: <timestamp> <seq_num> 59200 NOTICE Log-Management: Set log collector, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59200 NOTICE Log-Management: Set log collector, <log details>
- 消息代码: 59201
严重性: 通知 (NOTICE)
消息文本: 设置日志收集器 (Set log collector)
消息说明: 日志收集器设置成功
本地目标消息格式: <timestamp> <seq_num> 59201 NOTICE Log-Management: Set log collector, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 59201 NOTICE Log-Management: Set log collector, <log details>

- 消息代码: 59202

严重性: 通知 (NOTICE)

消息文本: 设置日志收集器 (Set log collector)

消息说明: 设置日志收集器时出错

本地目标消息格式: <timestamp> <seq_num> 59202 NOTICE Log-Management: Set log collector, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 59202 NOTICE Log-Management: Set log collector, <log details>

- 消息代码: 59203

严重性: 通知 (NOTICE)

消息文本: 恢复日志收集器 (Resume log collector)

消息说明: 管理员请求恢复日志收集器

本地目标消息格式: <timestamp> <seq_num> 59203 NOTICE Log-Management: Resume log collector, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 59203 NOTICE Log-Management: Resume log collector, <log details>

- 消息代码: 59204

严重性: 通知 (NOTICE)

消息文本: 恢复日志收集器 (Resume log collector)

消息说明: 日志收集器已恢复成功

本地目标消息格式: <timestamp> <seq_num> 59204 NOTICE Log-Management: Resume log collector, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 59204 NOTICE Log-Management: Resume log collector, <log details>

- 消息代码: 59205

严重性: 通知 (NOTICE)

消息文本: 恢复日志收集器 (Resume log collector)

消息说明: 恢复日志收集器时出错

本地目标消息格式: <timestamp> <seq_num> 59205 NOTICE Log-Management: Resume log collector, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59205 NOTICE Log-Management: Resume log collector, <log details>

- 消息代码: 59206

严重性: 通知 (NOTICE)

消息文本: 暂停日志收集器 (Suspend log collector)

消息说明: 管理员请求暂停日志收集器

本地目标消息格式: <timestamp> <seq_num> 59206 NOTICE Log-Management: Suspend log collector, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59206 NOTICE Log-Management: Suspend log collector, <log details>

- 消息代码: 59207

严重性: 通知 (NOTICE)

消息文本: 暂停日志收集器 (Suspend log collector)

消息说明: 日志收集器暂停成功

本地目标消息格式: <timestamp> <seq_num> 59207 NOTICE Log-Management: Suspend log collector, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59207 NOTICE Log-Management: Suspend log collector, <log details>

- 消息代码: 59208

严重性: 通知 (NOTICE)

消息文本: 暂停日志收集器 (Suspend log collector)

消息说明: 暂停日志收集器时出错

本地目标消息格式: <timestamp> <seq_num> 59208 NOTICE Log-Management: Suspend log collector, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59208 NOTICE Log-Management: Suspend log collector, <log details>

- 消息代码: 59250

严重性: 通知 (NOTICE)

消息文本: 管理员已从 CLI 重置访问设置 (Administrator reset the access setting from CLI)

消息说明：管理员已从 config-acs 外壳成功激活 access-setting 命令。有关详细信息，请参阅本消息中的命令行信息。

本地目标消息格式：<timestamp> <seq_num> 59250 NOTICE CLI: Administrator reset the access setting from CLI, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 59250 NOTICE CLI: Administrator reset the access setting from CLI, <log details>

- 消息代码：59251

严重性：通知 (NOTICE)

消息文本：管理员已从 CLI 激活/禁用 AD 调试级别 (Administrator activated/deactivated AD debug level from CLI)

消息说明：管理员已从 config-acs 外壳成功激活 debug-adclient 命令。有关详细信息，请参阅本消息中的命令行信息。

本地目标消息格式：<timestamp> <seq_num> 59251 NOTICE CLI: Administrator activated/deactivated AD debug level from CLI, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 59251 NOTICE CLI: Administrator activated/deactivated AD debug level from CLI, <log details>

- 消息代码：59252

严重性：通知 (NOTICE)

消息文本：管理员已从 CLI 更改组件调试日志级别 (Administrator changed component debug log level from CLI)

消息说明：管理员已从 config-acs 外壳成功激活 debug-log 命令。有关详细信息，请参阅本消息中的命令行信息。

本地目标消息格式：<timestamp> <seq_num> 59252 NOTICE CLI: Administrator changed component debug log level from CLI, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 59252 NOTICE CLI: Administrator changed component debug log level from CLI, <log details>

- 消息代码：59253

严重性：通知 (NOTICE)

消息文本：管理员已从 CLI 启动导出配置数据进程 (Administrator started export configuration data process from CLI)

消息说明：管理员已从 config-acs 外壳成功激活 export-data 命令。有关详细信息，请参阅本消息中的命令行信息。

本地目标消息格式：<timestamp> <seq_num> 59253 NOTICE CLI: Administrator started export configuration data process from CLI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 59253 NOTICE CLI: Administrator started
export configuration data process from CLI, <log details>

- 消息代码: 59254

严重性: 通知 (NOTICE)

消息文本: 管理员已从 CLI 启动导出配置数据进程 (Administrator started export configuration data
process from CLI)

消息说明: 管理员已从 config-acs 外壳成功激活 import-data 命令。有关详细信息, 请参阅本消
息中的命令行信息。

本地目标消息格式: <timestamp> <seq_num> 59254 NOTICE CLI: Administrator started export
configuration data process from CLI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 59254 NOTICE CLI: Administrator started
export configuration data process from CLI, <log details>

- 消息代码: 59255

严重性: 通知 (NOTICE)

消息文本: 管理员已从 CLI 中止导入/导出配置数据进程 (Administrator aborted import/export
configuration data process from CLI)

消息说明: 管理员已从 config-acs 外壳成功激活 import-export-abort 命令。有关详细信息, 请参
阅本消息中的命令行信息。

本地目标消息格式: <timestamp> <seq_num> 59255 NOTICE CLI: Administrator aborted import/export
configuration data process from CLI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 59255 NOTICE CLI: Administrator aborted
import/export configuration data process from CLI, <log details>

- 消息代码: 59256

严重性: 通知 (NOTICE)

消息文本: 管理员已从 CLI 启动复制进程 (Administrator started replication process from CLI)

消息说明: 管理员已从 config-acs 外壳成功激活复制命令。有关详细信息, 请参阅本消息中的命
令行信息。

本地目标消息格式: <timestamp> <seq_num> 59256 NOTICE CLI: Administrator started replication
process from CLI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 59256 NOTICE CLI: Administrator started
replication process from CLI, <log details>

- 消息代码: 59257

严重性: 通知 (NOTICE)

消息文本: 管理员已从 CLI 重置管理界面证书 (Administrator reset management interface certificate from CLI)

消息说明: 管理员已从 config-acs 外壳成功激活 reset-management-interface-certificate 命令。有关详细信息, 请参阅本消息中的命令行信息。

本地目标消息格式: <timestamp> <seq_num> 59257 NOTICE CLI: Administrator reset management interface certificate from CLI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59257 NOTICE CLI: Administrator reset management interface certificate from CLI, <log details>

- 消息代码: 59258

严重性: 通知 (NOTICE)

消息文本: 管理员已从 CLI 解密支持捆绑包 (Administrator decrypted support bundle from CLI)

消息说明: 管理员已从 config-acs 外壳成功激活 decrypt-support-bundle 命令。有关详细信息, 请参阅本消息中的命令行信息

本地目标消息格式: <timestamp> <seq_num> 59258 NOTICE CLI: Administrator decrypted support bundle from CLI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59258 NOTICE CLI: Administrator decrypted support bundle from CLI, <log details>

- 消息代码: 59259

严重性: 警告 (WARN)

消息文本: 复制失败 (Replication failed)

消息说明: 复制失败, 并将停止应用新的配置更改

本地目标消息格式: <timestamp> <seq_num> 59259 WARN Replication: Replication failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 59259 WARN Replication: Replication failed, <log details>

- 消息代码: 60000

严重性: 通知 (NOTICE)

消息文本: 在节点上成功完成了补丁安装 (Patch installation completed successfully on the node)

消息说明: 在节点上成功完成了补丁安装

本地目标消息格式: <timestamp> <seq_num> 60000 NOTICE Software-Management: Patch installation completed successfully on the node, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60000 NOTICE Software-Management:
Patch installation completed successfully on the node, <log details>

- 消息代码: 60001

严重性: 通知 (NOTICE)

消息文本: 节点上的补丁安装失败 (Patch installation failed on the node)

消息说明: 节点上的补丁安装失败

本地目标消息格式: <timestamp> <seq_num> 60001 NOTICE Software-Management: Patch installation
failed on the node, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60001 NOTICE Software-Management:
Patch installation failed on the node, <log details>

- 消息代码: 60002

严重性: 通知 (NOTICE)

消息文本: 在节点上成功完成了补丁回滚 (Patch rollback completed successfully on the node)

消息说明: 在节点上成功完成了补丁回滚

本地目标消息格式: <timestamp> <seq_num> 60002 NOTICE Software-Management: Patch rollback
completed successfully on the node, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60002 NOTICE Software-Management:
Patch rollback completed successfully on the node, <log details>

- 消息代码: 60003

严重性: 通知 (NOTICE)

消息文本: 节点上的补丁回滚失败 (Patch rollback failed on the node)

消息说明: 节点上的补丁回滚失败

本地目标消息格式: <timestamp> <seq_num> 60003 NOTICE Software-Management: Patch rollback
failed on the node, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60003 NOTICE Software-Management:
Patch rollback failed on the node, <log details>

- 消息代码: 60050

严重性: 通知 (NOTICE)

消息文本: 已成功将节点添加到部署中 (Node added to deployment successfully)

消息说明: 已成功将节点添加到部署中

本地目标消息格式: <timestamp> <seq_num> 60050 NOTICE Distributed-Management: Node added to deployment successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60050 NOTICE Distributed-Management: Node added to deployment successfully, <log details>

- 消息代码: 60051

严重性: 通知 (NOTICE)

消息文本: 无法将节点添加到部署中 (Failed to add node to deployment)

消息说明: 无法将节点添加到部署中

本地目标消息格式: <timestamp> <seq_num> 60051 NOTICE Distributed-Management: Failed to add node to deployment, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60051 NOTICE Distributed-Management: Failed to add node to deployment, <log details>

- 消息代码: 60052

严重性: 通知 (NOTICE)

消息文本: 已从部署中删除节点 (Node removed from deployment)

消息说明: 已从部署中删除节点

本地目标消息格式: <timestamp> <seq_num> 60052 NOTICE Distributed-Management: Node removed from deployment, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60052 NOTICE Distributed-Management: Node removed from deployment, <log details>

- 消息代码: 60053

严重性: 通知 (NOTICE)

消息文本: 从部署中删除节点失败 (Failed to remove node from deployment)

消息说明: 从部署中删除节点失败

本地目标消息格式: <timestamp> <seq_num> 60053 NOTICE Distributed-Management: Failed to remove node from deployment, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60053 NOTICE Distributed-Management: Failed to remove node from deployment, <log details>

- 消息代码: 60054

严重性: 通知 (NOTICE)

消息文本: 节点成功更新 (Node updated successfully)

消息说明: 节点成功更新

本地目标消息格式: <timestamp> <seq_num> 60054 NOTICE Distributed-Management: Node updated successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60054 NOTICE Distributed-Management: Node updated successfully, <log details>

- 消息代码: 60055

严重性: 通知 (NOTICE)

消息文本: 未能更新节点 (Failed to update node)

消息说明: 未能更新节点

本地目标消息格式: <timestamp> <seq_num> 60055 NOTICE Distributed-Management: Failed to update node, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60055 NOTICE Distributed-Management: Failed to update node, <log details>

- 消息代码: 60056

严重性: 通知 (NOTICE)

消息文本: 节点组的运行时间状态已更改 (The runtime status of the node group has changed)

消息说明: 集群状态有更改

本地目标消息格式: <timestamp> <seq_num> 60056 NOTICE PSN-Heartbeat: The runtime status of the node group has changed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60056 NOTICE PSN-Heartbeat: The runtime status of the node group has changed, <log details>

- 消息代码: 60057

严重性: 通知 (NOTICE)

消息文本: PSN 节点关闭 (A PSN node went down)

消息说明: 节点组中的一个 PSN 节点已关闭

本地目标消息格式: <timestamp> <seq_num> 60057 NOTICE PSN-Heartbeat: A PSN node went down, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60057 NOTICE PSN-Heartbeat: A PSN node went down, <log details>

- 消息代码: 60058

严重性: 通知 (NOTICE)

消息文本: 心跳系统的初始状态 (The initial status of the heartbeat system)

消息说明: 心跳系统的初始状态

本地目标消息格式: <timestamp> <seq_num> 60058 NOTICE PSN-Heartbeat: The initial status of the heartbeat system, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60058 NOTICE PSN-Heartbeat: The initial status of the heartbeat system, <log details>

- 消息代码: 60059

严重性: 通知 (NOTICE)

消息文本: 节点已成功注册到 MnT (Node has successfully registered with MnT)

消息说明: 节点已成功注册到 MnT

本地目标消息格式: <timestamp> <seq_num> 60059 NOTICE PSN-Heartbeat: Node has successfully registered with MnT, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60059 NOTICE PSN-Heartbeat: Node has successfully registered with MnT, <log details>

- 消息代码: 60060

严重性: 通知 (NOTICE)

消息文本: 管理员已为所有策略服务节点调用 OCSP 清除缓存操作 (Administrator invoked OCSP Clear Cache operation for all Policy Service nodes)

消息说明: ISE 管理员已为所有策略服务节点调用 OCSP 清除缓存操作

本地目标消息格式: <timestamp> <seq_num> 60060 NOTICE OCSP: Administrator invoked OCSP Clear Cache operation for all Policy Service nodes, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60060 NOTICE OCSP: Administrator invoked OCSP Clear Cache operation for all Policy Service nodes, <log details>

- 消息代码: 60061

严重性: 通知 (NOTICE)

消息文本: OCSP 清除缓存操作成功完成 (OCSP Clear Cache operation completed successfully)

消息说明: 已在所有策略服务节点上成功完成 OCSP 清除缓存操作

本地目标消息格式: <timestamp> <seq_num> 60061 NOTICE OCSP: OCSP Clear Cache operation completed successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60061 NOTICE OCSP: OCSP Clear Cache operation completed successfully, <log details>

- 消息代码: 60062
严重性: 通知 (NOTICE)
消息文本: OCSP 清除缓存操作因出现错误而终止 (OCSP Clear Cache operation terminated with error)
消息说明: 在一个或多个策略服务节点上, OCSP 清除缓存操作因出现错误而终止
本地目标消息格式: <timestamp> <seq_num> 60062 NOTICE OCSP: OCSP Clear Cache operation terminated with error, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60062 NOTICE OCSP: OCSP Clear Cache operation terminated with error, <log details>
- 消息代码: 60063
严重性: 通知 (NOTICE)
消息文本: 复制到节点已成功完成 (Replication to node completed successfully)
消息说明: 将数据复制到辅助节点成功完成
本地目标消息格式: <timestamp> <seq_num> 60063 NOTICE Distributed-Management: Replication to node completed successfully, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60063 NOTICE Distributed-Management: Replication to node completed successfully, <log details>
- 消息代码: 60064
严重性: 通知 (NOTICE)
消息文本: 复制到节点失败 (Replication to node failed)
消息说明: 将数据复制到辅助节点失败
本地目标消息格式: <timestamp> <seq_num> 60064 NOTICE Distributed-Management: Replication to node failed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60064 NOTICE Distributed-Management: Replication to node failed, <log details>
- 消息代码: 60065
严重性: 通知 (NOTICE)
消息文本: 已超过管理会话的最大数量 (The maximum number of Administrative sessions have been exceeded)
消息说明: 已超过管理会话的最大数量
本地目标消息格式: <timestamp> <seq_num> 60065 NOTICE Administrator-Login: The maximum number of Administrative sessions have been exceeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60065 NOTICE Administrator-Login: The maximum number of Administrative sessions have been exceeded, <log details>

- 消息代码: 60066

严重性: 通知 (NOTICE)

消息文本: 新旧配置文件之间的增量不匹配 (The delta between the old and the new is not matched)

消息说明: 新旧配置文件之间的增量不匹配

本地目标消息格式: <timestamp> <seq_num> 60066 NOTICE Administrator-Login: The delta between the old and the new is not matched, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60066 NOTICE Administrator-Login: The delta between the old and the new is not matched, <log details>

- 消息代码: 60067

严重性: 信息 (INFO)

消息文本: Profiler Feed Service - 已启动自动下载 (Profiler Feed Service - automatic download initiated)

消息说明: Profiler Feed Service 已开始按计划检查和下载新的和/或更新的配置文件

本地目标消息格式: <timestamp> <seq_num> 60067 INFO FeedService: Profiler Feed Service - automatic download initiated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60067 INFO FeedService: Profiler Feed Service - automatic download initiated, <log details>

- 消息代码: 60068

严重性: 信息 (INFO)

消息文本: Profiler Feed Service - 已启动手动下载 (Profiler Feed Service - manual download initiated)

消息说明: Profiler Feed Service 已开始检查和下载新的和/或更新的配置文件来响应管理员的请求

本地目标消息格式: <timestamp> <seq_num> 60068 INFO FeedService: Profiler Feed Service - manual download initiated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60068 INFO FeedService: Profiler Feed Service - manual download initiated, <log details>

- 消息代码: 60069

严重性: 信息 (INFO)

消息文本: Profiler Feed Service - 已下载配置文件 (Profiler Feed Service - Profiles Downloaded)

消息说明: Profiler Feed Service 已下载新的和/或更新的配置文件

本地目标消息格式: <timestamp> <seq_num> 60069 INFO FeedService: Profiler Feed Service - Profiles Downloaded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60069 INFO FeedService: Profiler Feed Service - Profiles Downloaded, <log details>

- 消息代码: 60070

严重性: 信息 (INFO)

消息文本: Profiler Feed Service - 未下载配置文件 (Profiler Feed Service - No Profiles Downloaded)

消息说明: Profiler Feed Service 找不到任何可下载的新的和/或更新的配置文件

本地目标消息格式: <timestamp> <seq_num> 60070 INFO FeedService: Profiler Feed Service - No Profiles Downloaded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60070 INFO FeedService: Profiler Feed Service - No Profiles Downloaded, <log details>

- 消息代码: 60071

严重性: 警告 (WARN)

消息文本: 源服务器通信问题 (Feed Server communication issue)

消息说明: Profiler Feed Service 无法使用

本地目标消息格式: <timestamp> <seq_num> 60071 WARN FeedService: Feed Server communication issue, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60071 WARN FeedService: Feed Server communication issue, <log details>

- 消息代码: 60072

严重性: 错误 (ERROR)

消息文本: Profiler Feed Service 报告源不可用 (Profiler Feed Service reported that the Feed is unavailable)

消息说明: Profiler Feed Service 无法识别所查询的源

本地目标消息格式: <timestamp> <seq_num> 60072 ERROR FeedService: Profiler Feed Service reported that the Feed is unavailable, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60072 ERROR FeedService: Profiler Feed Service reported that the Feed is unavailable, <log details>

- 消息代码: 60073

严重性: 错误 (ERROR)

消息文本: 查询 Profiler Feed Service 导致意外错误 (Querying the Profiler Feed Service resulted in an unexpected error)

消息说明: 查询 Profiler Feed Service 时, 出现意外错误

本地目标消息格式: <timestamp> <seq_num> 60073 ERROR FeedService: Querying the Profiler Feed Service resulted in an unexpected error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60073 ERROR FeedService: Querying the Profiler Feed Service resulted in an unexpected error, <log details>

- 消息代码: 60074

严重性: 错误 (ERROR)

消息文本: 从 Profiler Feed Service 导入下载的配置文件导致意外错误 (Importing downloaded profiles from the Profiler Feed Service resulted in an unexpected error)

消息说明: 从 Profiler Feed Service 导入下载的配置文件时, 出现意外错误

本地目标消息格式: <timestamp> <seq_num> 60074 ERROR FeedService: Importing downloaded profiles from the Profiler Feed Service resulted in an unexpected error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60074 ERROR FeedService: Importing downloaded profiles from the Profiler Feed Service resulted in an unexpected error, <log details>

- 消息代码: 60075

严重性: 通知 (NOTICE)

消息文本: 发起人身份验证成功 (Sponsor has successfully authenticated)

消息说明: 发起人身份验证成功

本地目标消息格式: <timestamp> <seq_num> 60075 NOTICE Sponsor: Sponsor has successfully authenticated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60075 NOTICE Sponsor: Sponsor has successfully authenticated, <log details>

- 消息代码: 60076

严重性: 通知 (NOTICE)

消息文本: 发起人身份验证失败 (Sponsor authentication has failed)

消息说明: 发起人身份验证失败; 有关详细信息, 请查看失败代码

本地目标消息格式: <timestamp> <seq_num> 60076 NOTICE Sponsor: Sponsor authentication has failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60076 NOTICE Sponsor: Sponsor
authentication has failed, <log details>

- 消息代码: 60077

严重性: 通知 (NOTICE)

消息文本: MyDevices 用户身份验证失败 (MyDevices user authentication has failed)

消息说明: MyDevices 用户身份验证失败

本地目标消息格式: <timestamp> <seq_num> 60077 NOTICE MyDevices: MyDevices user
authentication has failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60077 NOTICE MyDevices: MyDevices
user authentication has failed, <log details>

- 消息代码: 60078

严重性: 信息 (INFO)

消息文本: MyDevices 用户身份验证成功 (MyDevices user has successfully authenticated)

消息说明: MyDevices 用户身份验证成功

本地目标消息格式: <timestamp> <seq_num> 60078 INFO MyDevices: MyDevices user has successfully
authenticated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60078 INFO MyDevices: MyDevices user
has successfully authenticated, <log details>

- 消息代码: 60079

严重性: 信息 (INFO)

消息文本: 检测到建立 SSL 会话失败 (A failure to establish an SSL session was detected)

消息说明: 检测到建立 SSL 会话失败

本地目标消息格式: <timestamp> <seq_num> 60079 INFO Administrator-Login: A failure to establish
an SSL session was detected, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60079 INFO Administrator-Login: A failure
to establish an SSL session was detected, <log details>

- 消息代码: 60080

严重性: 信息 (INFO)

消息文本: SSH CLI 用户已成功登录 (A SSH CLI user has successfully logged in)

消息说明: SSH CLI 用户已成功登录

本地目标消息格式: <timestamp> <seq_num> 60080 INFO Administrator-Login: A SSH CLI user has successfully logged in, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60080 INFO Administrator-Login: A SSH CLI user has successfully logged in, <log details>

- 消息代码: 60081

严重性: 信息 (INFO)

消息文本: SSH CLI 用户尝试登录未成功 (A SSH CLI user has attempted unsuccessfully to login)

消息说明: SSH CLI 用户尝试登录未成功

本地目标消息格式: <timestamp> <seq_num> 60081 INFO Administrator-Login: A SSH CLI user has attempted unsuccessfully to login, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60081 INFO Administrator-Login: A SSH CLI user has attempted unsuccessfully to login, <log details>

- 消息代码: 60082

严重性: 信息 (INFO)

消息文本: SSH CLI 用户已尝试登录, 但帐户被锁定 (A SSH CLI user has attempted to login, however account is locked out)

消息说明: SSH CLI 用户已尝试登录, 但帐户被锁定

本地目标消息格式: <timestamp> <seq_num> 60082 INFO Administrator-Login: A SSH CLI user has attempted to login, however account is locked out, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60082 INFO Administrator-Login: A SSH CLI user has attempted to login, however account is locked out, <log details>

- 消息代码: 60083

严重性: 信息 (INFO)

消息文本: 系统日志服务器配置更改 (Syslog Server configuration change)

消息说明: 系统日志服务器配置已更改

本地目标消息格式: <timestamp> <seq_num> 60083 INFO System-Management: Syslog Server configuration change, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60083 INFO System-Management: Syslog Server configuration change, <log details>

- 消息代码: 60084

严重性: 信息 (INFO)

消息文本: ADEOS CLI 用户配置更改 (ADEOS CLI user configuration change)

消息说明: ADEOS CLI 用户配置发生变更

本地目标消息格式: <timestamp> <seq_num> 60084 INFO System-Management: ADEOS CLI user configuration change, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60084 INFO System-Management: ADEOS CLI user configuration change, <log details>

- 消息代码: 60085

严重性: 信息 (INFO)

消息文本: ADEOS 存储库配置更改 (ADEOS Repository configuration change)

消息说明: ADEOS 存储库配置发生变更

本地目标消息格式: <timestamp> <seq_num> 60085 INFO System-Management: ADEOS Repository configuration change, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60085 INFO System-Management: ADEOS Repository configuration change, <log details>

- 消息代码: 60086

严重性: 信息 (INFO)

消息文本: ADEOS SSH 服务配置更改 (ADEOS SSH Service configuration change)

消息说明: ADEOS SSH 服务配置发生变更

本地目标消息格式: <timestamp> <seq_num> 60086 INFO System-Management: ADEOS SSH Service configuration change, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60086 INFO System-Management: ADEOS SSH Service configuration change, <log details>

- 消息代码: 60087

严重性: 信息 (INFO)

消息文本: ADEOS 最大 SSH CLI 会话数配置更改 (ADEOS Maximum SSH CLI sessions configuration change)

消息说明: ADEOS 最大 CLI 会话数配置发生变更

本地目标消息格式: <timestamp> <seq_num> 60087 INFO System-Management: ADEOS Maximum SSH CLI sessions configuration change, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60087 INFO System-Management: ADEOS Maximum SSH CLI sessions configuration change, <log details>

- 消息代码: 60088
严重性: 信息 (INFO)
消息文本: ADEOS SNMP 代理配置更改 (ADEOS SNMP agent configuration change)
消息说明: ADEOS SNMP 代理配置发生变更
本地目标消息格式: <timestamp> <seq_num> 60088 INFO System-Management: ADEOS SNMP agent configuration change, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60088 INFO System-Management: ADEOS SNMP agent configuration change, <log details>
- 消息代码: 60089
严重性: 信息 (INFO)
消息文本: ADEOS CLI kron 安排程序策略配置更改 (ADEOS CLI kron scheduler policy configuration change)
消息说明: ADEOS CLI kron 安排程序策略配置发生变更
本地目标消息格式: <timestamp> <seq_num> 60089 INFO System-Management: ADEOS CLI kron scheduler policy configuration change, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60089 INFO System-Management: ADEOS CLI kron scheduler policy configuration change, <log details>
- 消息代码: 60090
严重性: 信息 (INFO)
消息文本: ADEOS CLI kron 安排程序发生次数配置更改 (ADEOS CLI kron scheduler occurrence configuration change)
消息说明: ADEOS CLI kron 安排程序发生次数配置发生变更
本地目标消息格式: <timestamp> <seq_num> 60090 INFO System-Management: ADEOS CLI kron scheduler occurrence configuration change, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60090 INFO System-Management: ADEOS CLI kron scheduler occurrence configuration change, <log details>
- 消息代码: 60091
严重性: 信息 (INFO)
消息文本: ADEOS CLI 登录前横幅配置更改 (ADEOS CLI pre-login banner configuration change)
消息说明: ADEOS CLI 登录前横幅配置发生变更
本地目标消息格式: <timestamp> <seq_num> 60091 INFO System-Management: ADEOS CLI pre-login banner configuration change, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60091 INFO System-Management: ADEOS
CLI pre-login banner configuration change, <log details>

- 消息代码: 60092

严重性: 信息 (INFO)

消息文本: ADEOS CLI 登录后横幅配置更改 (ADEOS CLI post-login banner configuration change)

消息说明: ADEOS CLI 登录后横幅配置发生更改

本地目标消息格式: <timestamp> <seq_num> 60092 INFO System-Management: ADEOS CLI
post-login banner configuration change, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60092 INFO System-Management: ADEOS
CLI post-login banner configuration change, <log details>

- 消息代码: 60093

严重性: 信息 (INFO)

消息文本: ISE 备份已启动 (ISE Backup has started)

消息说明: ISE 备份已启动

本地目标消息格式: <timestamp> <seq_num> 60093 INFO System-Management: ISE Backup has
started, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60093 INFO System-Management: ISE
Backup has started, <log details>

- 消息代码: 60094

严重性: 信息 (INFO)

消息文本: ISE 备份已成功完成 (ISE Backup has completed successfully)

消息说明: ISE 备份已成功完成

本地目标消息格式: <timestamp> <seq_num> 60094 INFO System-Management: ISE Backup has
completed successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60094 INFO System-Management: ISE
Backup has completed successfully, <log details>

- 消息代码: 60095

严重性: 错误 (ERROR)

消息文本: ISE 备份失败 (ISE Backup has failed)

消息说明: ISE 备份失败

本地目标消息格式: <timestamp> <seq_num> 60095 ERROR System-Management: ISE Backup has failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60095 ERROR System-Management: ISE Backup has failed, <log details>

- 消息代码: 60096

严重性: 信息 (INFO)

消息文本: ISE 日志备份已启动 (ISE Log backup has started)

消息说明: ISE 日志备份已启动

本地目标消息格式: <timestamp> <seq_num> 60096 INFO System-Management: ISE Log backup has started, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60096 INFO System-Management: ISE Log backup has started, <log details>

- 消息代码: 60097

严重性: 信息 (INFO)

消息文本: ISE 日志备份已成功完成 (ISE Log Backup has completed successfully)

消息说明: ISE 日志备份已成功完成

本地目标消息格式: <timestamp> <seq_num> 60097 INFO System-Management: ISE Log Backup has completed successfully, <log details>

本地目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60097 INFO System-Management: ISE Log Backup has completed successfully, <log details>

- 消息代码: 60098

严重性: 错误 (ERROR)

消息文本: ISE 日志备份失败 (ISE Log Backup has failed)

消息说明: ISE 日志备份失败

本地目标消息格式: <timestamp> <seq_num> 60098 ERROR System-Management: ISE Log Backup has failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60098 ERROR System-Management: ISE Log Backup has failed, <log details>

- 消息代码: 60099

严重性: 信息 (INFO)

消息文本: ISE 恢复已启动 (ISE Restore has started)

消息说明: ISE 恢复已启动

本地目标消息格式: <timestamp> <seq_num> 60099 INFO System-Management: ISE Restore has started, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60099 INFO System-Management: ISE Restore has started, <log details>

- 消息代码: 60100

严重性: 信息 (INFO)

消息文本: ISE 恢复已成功完成 (ISE Restore has completed successfully)

消息说明: ISE 恢复已成功完成

本地目标消息格式: <timestamp> <seq_num> 60100 INFO System-Management: ISE Restore has completed successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60100 INFO System-Management: ISE Restore has completed successfully, <log details>

- 消息代码: 60101

严重性: 错误 (ERROR)

消息文本: ISE 恢复失败 (ISE Restore has failed)

消息说明: ISE 恢复失败

本地目标消息格式: <timestamp> <seq_num> 60101 ERROR System-Management: ISE Restore has failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60101 ERROR System-Management: ISE Restore has failed, <log details>

- 消息代码: 60102

严重性: 信息 (INFO)

消息文本: 应用安装已成功完成 (Application installation completed successfully)

消息说明: 应用安装已成功完成

本地目标消息格式: <timestamp> <seq_num> 60102 INFO System-Management: Application installation completed successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60102 INFO System-Management: Application installation completed successfully, <log details>

- 消息代码: 60103

严重性: 错误 (ERROR)

消息文本: 应用安装失败 (Application installation failed)

消息说明: 应用安装失败

本地目标消息格式: <timestamp> <seq_num> 60103 ERROR System-Management: Application installation failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60103 ERROR System-Management: Application installation failed, <log details>

- 消息代码: 60104

严重性: 信息 (INFO)

消息文本: 应用删除已启动 (Application remove started)

消息说明: 应用删除已启动

本地目标消息格式: <timestamp> <seq_num> 60104 INFO System-Management: Application remove started, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60104 INFO System-Management: Application remove started, <log details>

- 消息代码: 60105

严重性: 信息 (INFO)

消息文本: 应用删除已成功完成 (Application remove completed successfully)

消息说明: 应用删除已成功完成

本地目标消息格式: <timestamp> <seq_num> 60105 INFO System-Management: Application remove completed successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60105 INFO System-Management: Application remove completed successfully, <log details>

- 消息代码: 60106

严重性: 错误 (ERROR)

消息文本: 应用删除失败 (Application remove failed)

消息说明: 应用删除失败

本地目标消息格式: <timestamp> <seq_num> 60106 ERROR System-Management: Application remove failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60106 ERROR System-Management: Application remove failed, <log details>

- 消息代码: 60107

严重性: 错误 (ERROR)

消息文本: 应用升级失败 (Application upgrade failed)

消息说明: 应用升级失败

本地目标消息格式: <timestamp> <seq_num> 60107 ERROR System-Management: Application upgrade failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60107 ERROR System-Management: Application upgrade failed, <log details>

- 消息代码: 60108

严重性: 信息 (INFO)

消息文本: 应用补丁已启动 (Application patch started)

消息说明: 应用补丁已启动

本地目标消息格式: <timestamp> <seq_num> 60108 INFO System-Management: Application patch started, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60108 INFO System-Management: Application patch started, <log details>

- 消息代码: 60109

严重性: 信息 (INFO)

消息文本: 应用补丁删除已启动 (Application patch remove has started)

消息说明: 应用补丁删除已启动

本地目标消息格式: <timestamp> <seq_num> 60109 INFO System-Management: Application patch remove has started, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60109 INFO System-Management: Application patch remove has started, <log details>

- 消息代码: 60111

严重性: 信息 (INFO)

消息文本: 应用补丁删除已成功完成 (Application patch remove has completed successfully)

消息说明: 应用补丁删除已成功完成

本地目标消息格式: <timestamp> <seq_num> 60111 INFO System-Management: Application patch remove has completed successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60111 INFO System-Management: Application patch remove has completed successfully, <log details>

- 消息代码: 60112
 - 严重性: 错误 (ERROR)
 - 消息文本: 应用补丁删除失败 (Application patch remove has failed)
 - 消息说明: 应用补丁删除失败
 - 本地目标消息格式: <timestamp> <seq_num> 60112 ERROR System-Management: Application patch remove has failed, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60112 ERROR System-Management: Application patch remove has failed, <log details>

- 消息代码: 60113
 - 严重性: 警告 (WARNING)
 - 消息文本: 已启动 ISE 服务器重新加载 (ISE server reload has been initiated)
 - 消息说明: 已启动 ISE 服务器重新加载
 - 本地目标消息格式: <timestamp> <seq_num> 60113 WARNING Startup-Shutdown: ISE server reload has been initiated, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60113 WARNING Startup-Shutdown: ISE server reload has been initiated, <log details>

- 消息代码: 60114
 - 严重性: 警告 (WARNING)
 - 消息文本: 已启动 ISE 服务器关闭 (ISE server shutdown has been initiated)
 - 消息说明: 已启动 ISE 服务器关闭
 - 本地目标消息格式: <timestamp> <seq_num> 60114 WARNING Startup-Shutdown: ISE server shutdown has been initiated, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60114 WARNING Startup-Shutdown: ISE server shutdown has been initiated, <log details>

- 消息代码: 60115
 - 严重性: 信息 (INFO)
 - 消息文本: CLI 用户已通过 SSH 登录 (A CLI user has logged in from SSH)
 - 消息说明: CLI 用户已通过 SSH 登录
 - 本地目标消息格式: <timestamp> <seq_num> 60115 INFO Administrator-Login: A CLI user has logged in from SSH, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60115 INFO Administrator-Login: A CLI
user has logged in from SSH, <log details>

- 消息代码: 60116

严重性: 信息 (INFO)

消息文本: CLI 用户已通过 SSH 退出 (A CLI user has logged out from SSH)

消息说明: CLI 用户已通过 SSH 退出

本地目标消息格式: <timestamp> <seq_num> 60116 INFO Administrator-Login: A CLI user has
logged out from SSH, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60116 INFO Administrator-Login: A CLI
user has logged out from SSH, <log details>

- 消息代码: 60117

严重性: 信息 (INFO)

消息文本: ADEOS CLI 用户已被强制退出 (ADEOS CLI user has been force logged out)

消息说明: ADEOS CLI 用户已被强制退出

本地目标消息格式: <timestamp> <seq_num> 60117 INFO System-Management: ADEOS CLI user
has been force logged out, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60117 INFO System-Management: ADEOS
CLI user has been force logged out, <log details>

- 消息代码: 60118

严重性: 信息 (INFO)

消息文本: ADEOS CLI 用户已使用 delete CLI 删除文件 (ADEOS CLI user has used delete CLI to
delete file)

消息说明: ADEOS CLI 用户已使用 delete CLI 删除文件

本地目标消息格式: <timestamp> <seq_num> 60118 INFO System-Management: ADEOS CLI user
has used delete CLI to delete file, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60118 INFO System-Management: ADEOS
CLI user has used delete CLI to delete file, <log details>

- 消息代码: 60119

严重性: 信息 (INFO)

消息文本: ADEOS CLI 用户已使用 copy CLI 复制文件 (ADEOS CLI user has used copy CLI to
copy file)

消息说明: ADEOS CLI 用户已使用 copy CLI 复制文件

本地目标消息格式: <timestamp> <seq_num> 60119 INFO System-Management: ADEOS CLI user has used copy CLI to copy file, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60119 INFO System-Management: ADEOS CLI user has used copy CLI to copy file, <log details>

- 消息代码: 60120

严重性: 信息 (INFO)

消息文本: ADEOS CLI 用户已使用 mkdir CLI 创建目录 (ADEOS CLI user has used mkdir CLI to create a directory)

消息说明: ADEOS CLI 用户已使用 mkdir CLI 创建目录

本地目标消息格式: <timestamp> <seq_num> 60120 INFO System-Management: ADEOS CLI user has used mkdir CLI to create a directory, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60120 INFO System-Management: ADEOS CLI user has used mkdir CLI to create a directory, <log details>

- 消息代码: 60121

严重性: 信息 (INFO)

消息文本: ADEOS CLI 用户已拷出正在运行的系统配置 (ADEOS CLI user has copied out running system configuration)

消息说明: ADEOS CLI 用户已拷出正在运行的系统配置

本地目标消息格式: <timestamp> <seq_num> 60121 INFO System-Management: ADEOS CLI user has copied out running system configuration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60121 INFO System-Management: ADEOS CLI user has copied out running system configuration, <log details>

- 消息代码: 60122

严重性: 信息 (INFO)

消息文本: ADEOS CLI 用户已拷入系统配置 (ADEOS CLI user has copied in system configuration)

消息说明: ADEOS CLI 用户已拷入系统配置

本地目标消息格式: <timestamp> <seq_num> 60122 INFO System-Management: ADEOS CLI user has copied in system configuration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60122 INFO System-Management: ADEOS CLI user has copied in system configuration, <log details>

- 消息代码: 60123

严重性: 信息 (INFO)

消息文本: ADEOS CLI 用户已保存正在运行的系统配置 (ADEOS CLI user has saved running system configuration)

消息说明: ADEOS CLI 用户已保存正在运行的系统配置

本地目标消息格式: <timestamp> <seq_num> 60123 INFO System-Management: ADEOS CLI user has saved running system configuration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60123 INFO System-Management: ADEOS CLI user has saved running system configuration, <log details>

- 消息代码: 60124

严重性: 警告 (WARNING)

消息文本: 由于密码已过期, 因此 ADEOS CLI 用户无法登录 (ADEOS CLI user failed to login because password has expired)

消息说明: 由于密码已过期, 因此 ADEOS CLI 用户无法登录

本地目标消息格式: <timestamp> <seq_num> 60124 WARNING System-Management: ADEOS CLI user failed to login because password has expired, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60124 WARNING System-Management: ADEOS CLI user failed to login because password has expired, <log details>

- 消息代码: 60125

严重性: 信息 (INFO)

消息文本: 检测到格式错误的 SSH 请求 (A malformed SSH requested has been detected)

消息说明: 检测到格式错误的 SSH 请求

本地目标消息格式: <timestamp> <seq_num> 60125 INFO Administrator-Login: A malformed SSH requested has been detected, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60125 INFO Administrator-Login: A malformed SSH requested has been detected, <log details>

- 消息代码: 60126

严重性: 错误 (ERROR)

消息文本: 应用补丁安装失败 (Application patch installation failed)

消息说明: 应用补丁安装失败

本地目标消息格式: <timestamp> <seq_num> 60126 ERROR System-Management: Application patch installation failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60126 ERROR System-Management:
Application patch installation failed, <log details>

- 消息代码: 60127

严重性: 错误 (ERROR)

消息文本: 并发 CLI 会话已达到最大数量 (Maximum number of concurrent CLI sessions has been reached)

消息说明: 并发 CLI 会话已达到最大数量

本地目标消息格式: <timestamp> <seq_num> 60127 ERROR System-Management: Maximum number of concurrent CLI sessions has been reached, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60127 ERROR System-Management:
Maximum number of concurrent CLI sessions has been reached, <log details>

- 消息代码: 60128

严重性: 错误 (ERROR)

消息文本: 尝试从 ADEOS CLI 拷入文件失败 (Failure occurred trying to copy file in from ADEOS CLI)

消息说明: 尝试从 ADEOS CLI 拷入文件失败

本地目标消息格式: <timestamp> <seq_num> 60128 ERROR System-Management: Failure occurred trying to copy file in from ADEOS CLI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60128 ERROR System-Management: Failure occurred trying to copy file in from ADEOS CLI, <log details>

- 消息代码: 60129

严重性: 错误 (ERROR)

消息文本: 尝试从 ADEOS CLI 拷出文件失败 (Failure occurred trying to copy file out from ADEOS CLI)

消息说明: 尝试从 ADEOS CLI 拷出文件失败

本地目标消息格式: <timestamp> <seq_num> 60129 ERROR System-Management: Failure occurred trying to copy file out from ADEOS CLI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60129 ERROR System-Management: Failure occurred trying to copy file out from ADEOS CLI, <log details>

- 消息代码: 60130

严重性: 信息 (INFO)

消息文本: 已配置 ISE 计划备份 (ISE Scheduled Backup has been configured)

消息说明: 已配置 ISE 计划备份

本地目标消息格式: <timestamp> <seq_num> 60130 INFO System-Management: ISE Scheduled Backup has been configured, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60130 INFO System-Management: ISE Scheduled Backup has been configured, <log details>

- 消息代码: 60131

严重性: 信息 (INFO)

消息文本: 已通过 Web UI 创建 ISE 支持捆绑包 (ISE Support bundle has been created from web UI)

消息说明: 已通过 Web UI 创建 ISE 支持捆绑包

本地目标消息格式: <timestamp> <seq_num> 60131 INFO System-Management: ISE Support bundle has been created from web UI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60131 INFO System-Management: ISE Support bundle has been created from web UI, <log details>

- 消息代码: 60132

严重性: 信息 (INFO)

消息文本: 已通过 Web UI 删除 ISE 支持捆绑包 (ISE Support bundle has been deleted from web UI)

消息说明: 已通过 Web UI 删除 ISE 支持捆绑包

本地目标消息格式: <timestamp> <seq_num> 60132 INFO System-Management: ISE Support bundle has been deleted from web UI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60132 INFO System-Management: ISE Support bundle has been deleted from web UI, <log details>

- 消息代码: 60133

严重性: 错误 (ERROR)

消息文本: 通过 Web UI 生成 ISE 支持捆绑包失败 (ISE Support bundle generation from web UI has failed)

消息说明: 通过 Web UI 生成 ISE 支持捆绑包失败

本地目标消息格式: <timestamp> <seq_num> 60133 ERROR System-Management: ISE Support bundle generation from web UI has failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60133 ERROR System-Management: ISE Support bundle generation from web UI has failed, <log details>

- 消息代码: 60134

严重性: 严重 (FATAL)

消息文本: DNS 解析失败 (DNS Resolution failure)

消息说明: 节点上的 DNS 解析失败

本地目标消息格式: <timestamp> <seq_num> 60134 FATAL System-Management: DNS Resolution failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60134 FATAL System-Management: DNS Resolution failure, <log details>

- 消息代码: 60135

严重性: 信息 (INFO)

消息文本: MyDevices 用户 SSO 注销失败 (MyDevices user SSO logout has failed)

消息说明: MyDevices 用户 SSO 注销失败

本地目标消息格式: <timestamp> <seq_num> 60135 INFO MyDevices: MyDevices user SSO logout has failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60135 INFO MyDevices: MyDevices user SSO logout has failed, <log details>

- 消息代码: 60136

严重性: 信息 (INFO)

消息文本: 发起人用户 SSO 注销失败 (Sponsor user SSO logout has failed)

消息说明: 发起人用户 SSO 注销失败

本地目标消息格式: <timestamp> <seq_num> 60136 INFO Sponsor: Sponsor user SSO logout has failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60136 INFO Sponsor: Sponsor user SSO logout has failed, <log details>

- 消息代码: 60150

严重性: 信息 (INFO)

消息文本: 复制缓慢 (Slow Replication)

消息说明: 复制速度慢

本地目标消息格式: <timestamp> <seq_num> 60150 INFO Replication: Slow Replication, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60150 INFO Replication: Slow Replication, <log details>

- 消息代码: 60151
 - 严重性: 警告 (WARN)
 - 消息文本: 复制缓慢 (Slow Replication)
 - 消息说明: 复制速度慢
 - 本地目标消息格式: <timestamp> <seq_num> 60151 WARN Replication: Slow Replication, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60151 WARN Replication: Slow Replication, <log details>

- 消息代码: 60152
 - 严重性: 错误 (ERROR)
 - 消息文本: 复制缓慢 (Slow Replication)
 - 消息说明: 复制速度慢
 - 本地目标消息格式: <timestamp> <seq_num> 60152 ERROR Replication: Slow Replication, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60152 ERROR Replication: Slow Replication, <log details>

- 消息代码: 60153
 - 严重性: 信息 (INFO)
 - 消息文本: 证书已导出 (Certificate has been exported)
 - 消息说明: 证书已导出
 - 本地目标消息格式: <timestamp> <seq_num> 60153 INFO System-Management: Certificate has been exported, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60153 INFO System-Management: Certificate has been exported, <log details>

- 消息代码: 60154
 - 严重性: 信息 (INFO)
 - 消息文本: 应用补丁安装已成功完成 (Application patch install has completed successfully)
 - 消息说明: 应用补丁安装已成功完成
 - 本地目标消息格式: <timestamp> <seq_num> 60154 INFO System-Management: Application patch install has completed successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60154 INFO System-Management: Application patch install has completed successfully, <log details>

- 消息代码: 60155

严重性: 信息 (INFO)

消息文本: 已与系统日志服务器建立安全通信 (Secure communication with syslog server established)

消息说明: 已与系统日志服务器建立安全通信

本地目标消息格式: <timestamp> <seq_num> 60155 INFO System-Management: Secure communication with syslog server established, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60155 INFO System-Management: Secure communication with syslog server established, <log details>

- 消息代码: 60156

严重性: 警告 (WARN)

消息文本: 与系统日志服务器建立安全通信失败 (Secure communication establishment with syslog server failed)

消息说明: 与系统日志服务器建立安全通信失败

本地目标消息格式: <timestamp> <seq_num> 60156 WARN System-Management: Secure communication establishment with syslog server failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60156 WARN System-Management: Secure communication establishment with syslog server failed, <log details>

- 消息代码: 60157

严重性: 错误 (ERROR)

消息文本: 无法将导出的报告文件复制到配置的存储库 (Unable to copy the exported report file to configured repository)

消息说明: 未能将导出的报告文件复制到配置的存储库

本地目标消息格式: <timestamp> <seq_num> 60157 ERROR System-Management: Unable to copy the exported report file to configured repository, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60157 ERROR System-Management: Unable to copy the exported report file to configured repository, <log details>

- 消息代码: 60158

严重性: 信息 (INFO)

消息文本: 已使用此消息记录所有 xGrid 管理员操作 (All xGrid administrator actions are logged using this message)

消息说明：已使用此消息记录所有 xGrid 管理员操作

本地目标消息格式：<timestamp> <seq_num> 60158 INFO System-Management: All xGrid administrator actions are logged using this message, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60158 INFO System-Management: All xGrid administrator actions are logged using this message, <log details>

- 消息代码：60159

严重性：信息 (INFO)

消息文本：已通过远程源 URL 启动终端安全评估要求更新 (Posture requirements update has started from the remote feed URL)

消息说明：系统收到了通过远程源 URL 检查终端安全评估要求更新的请求。已开始更新。

本地目标消息格式：<timestamp> <seq_num> 60159 INFO System-Management: Posture requirements update has started from the remote feed URL, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60159 INFO System-Management: Posture requirements update has started from the remote feed URL, <log details>

- 消息代码：60160

严重性：通知 (NOTICE)

消息文本：已成功完成通过远程源 URL 更新终端安全评估要求 (Successfully finished updating posture requirements from remote feed URL)

消息说明：已成功完成通过远程源 URL 更新终端安全评估

本地目标消息格式：<timestamp> <seq_num> 60160 NOTICE System-Management: Successfully finished updating posture requirements from remote feed URL, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60160 NOTICE System-Management: Successfully finished updating posture requirements from remote feed URL, <log details>

- 消息代码：60161

严重性：错误 (ERROR)

消息文本：无法通过远程源 URL 更新终端安全评估要求 (Failed to update Posture requirements from the remote feed URL)

消息说明：通过远程源 URL 更新终端安全评估失败

本地目标消息格式：<timestamp> <seq_num> 60161 ERROR System-Management: Failed to update Posture requirements from the remote feed URL, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60161 ERROR System-Management: Failed to update Posture requirements from the remote feed URL, <log details>

- 消息代码: 60162
严重性: 调试 (DEBUG)
消息文本: 正在检查远程源 URL 上的已更新终端安全评估要求 (Checking for the updated Posture requirements on the remote feed URL)
消息说明: 开始检查流程, 检查远程源 URL 上有无更新的终端安全评估要求
本地目标消息格式: <timestamp> <seq_num> 60162 DEBUG System-Management: Checking for the updated Posture requirements on the remote feed URL, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60162 DEBUG System-Management: Checking for the updated Posture requirements on the remote feed URL, <log details>
- 消息代码: 60163
严重性: 调试 (DEBUG)
消息文本: 正在处理从远程源 URL 收到的已更新终端安全评估要求 (Processing the updated Posture requirements received from the remote feed URL)
消息说明: 开始处理从远程源 URL 收到的已更新终端安全评估要求
本地目标消息格式: <timestamp> <seq_num> 60163 DEBUG System-Management: Processing the updated Posture requirements received from the remote feed URL, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60163 DEBUG System-Management: Processing the updated Posture requirements received from the remote feed URL, <log details>
- 消息代码: 60164
严重性: 错误 (ERROR)
消息文本: 节点上的 NTP 服务已关闭 (NTP Service is down on the node)
消息说明: 节点上的 NTP 服务已关闭
本地目标消息格式: <timestamp> <seq_num> 60164 ERROR System-Management: NTP Service is down on the node, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60164 ERROR System-Management: NTP Service is down on the node, <log details>
- 消息代码: 60165
严重性: 错误 (ERROR)
消息文本: NTP 无法与配置的服务器同步 (NTP failed to sync with configured servers)
消息说明: NTP 无法与配置的服务器同步
本地目标消息格式: <timestamp> <seq_num> 60165 ERROR System-Management: NTP failed to sync with configured servers, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60165 ERROR System-Management: NTP failed to sync with configured servers, <log details>

- 消息代码: 60166

严重性: 警告 (WARN)

消息文本: 证书即将到期 (Certificate will expire soon)

消息说明: 证书到期警告

本地目标消息格式: <timestamp> <seq_num> 60166 WARN Certificate: Certificate will expire soon, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60166 WARN Certificate: Certificate will expire soon, <log details>

- 消息代码: 60167

严重性: 警告 (WARN)

消息文本: 证书已过期 (Certificate has expired)

消息说明: 证书已过期

本地目标消息格式: <timestamp> <seq_num> 60167 WARN Certificate: Certificate has expired, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60167 WARN Certificate: Certificate has expired, <log details>

- 消息代码: 60168

严重性: 信息 (INFO)

消息文本: 已成功重置会话重复计数 (Session Repeat Count has reset successfully)

消息说明: 已成功重置会话重复计数

本地目标消息格式: <timestamp> <seq_num> 60168 INFO System-Management: Session Repeat Count has reset successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60168 INFO System-Management: Session Repeat Count has reset successfully, <log details>

- 消息代码: 60169

严重性: 信息 (INFO)

消息文本: 会话重复计数重置失败 (Session Repeat Count reset has failed)

消息说明: 会话重复计数重置失败

本地目标消息格式: <timestamp> <seq_num> 60169 INFO System-Management: Session Repeat Count reset has failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60169 INFO System-Management: Session Repeat Count reset has failed, <log details>

- 消息代码: 60170

严重性: 信息 (INFO)

消息文本: 已成功为所有会话重置重复计数 (Resetting Repeat Count is successful for all sessions)

消息说明: 已成功为所有会话重置重复计数

本地目标消息格式: <timestamp> <seq_num> 60170 INFO System-Management: Resetting Repeat Count is successful for all sessions, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60170 INFO System-Management: Resetting Repeat Count is successful for all sessions, <log details>

- 消息代码: 60171

严重性: 信息 (INFO)

消息文本: 为所有会话重置重复计数失败 (Resetting Repeat Count has failed for all sessions)

消息说明: 为所有会话重置重复计数失败

本地目标消息格式: <timestamp> <seq_num> 60171 INFO System-Management: Resetting Repeat Count has failed for all sessions, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60171 INFO System-Management: Resetting Repeat Count has failed for all sessions, <log details>

- 消息代码: 60172

严重性: 信息 (INFO)

消息文本: 报警已确认 (Alarm(s) has/have been acknowledged)

消息说明: 报警已得到确认, 将不会显示在控制板上

本地目标消息格式: <timestamp> <seq_num> 60172 INFO System-Management: Alarm(s) has/have been acknowledged, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60172 INFO System-Management: Alarm(s) has/have been acknowledged, <log details>

- 消息代码: 60173

严重性: 信息 (INFO)

消息文本: 清除过时的报警 (Outdated alarms are purged)

消息说明: 仅保留最近的 15000 条报警, 并清除其余报警

本地目标消息格式: <timestamp> <seq_num> 60173 INFO System-Management: Outdated alarms are purged, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60173 INFO System-Management: Outdated alarms are purged, <log details>

- 消息代码: 60174

严重性: 错误 (ERROR)

消息文本: 无法添加证书吊销列表 (Could not add Certificate Revocation List)

消息说明: 无法添加证书吊销列表。ISE 不会使用证书吊销列表

本地目标消息格式: <timestamp> <seq_num> 60174 ERROR CRL: Could not add Certificate Revocation List, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60174 ERROR CRL: Could not add Certificate Revocation List, <log details>

- 消息代码: 60175

严重性: 错误 (ERROR)

消息文本: 无法下载证书吊销列表 (Could not download Certificate Revocation List)

消息说明: 无法下载证书吊销列表。ISE 不会使用证书吊销列表

本地目标消息格式: <timestamp> <seq_num> 60175 ERROR CRL: Could not download Certificate Revocation List, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60175 ERROR CRL: Could not download Certificate Revocation List, <log details>

- 消息代码: 60176

严重性: 信息 (INFO)

消息文本: 终端安全评估更新 (Posture Update)

消息说明: 终端安全评估更新

本地目标消息格式: <timestamp> <seq_num> 60176 INFO System-Management: Posture Update, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60176 INFO System-Management: Posture Update, <log details>

- 消息代码: 60177

严重性: 错误 (ERROR)

消息文本: 应用升级准备失败 (Application upgrade preparation failed)

消息说明: 应用升级准备失败

本地目标消息格式: <timestamp> <seq_num> 60177 ERROR System-Management: Application upgrade preparation failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60177 ERROR System-Management: Application upgrade preparation failed, <log details>

- 消息代码: 60178

严重性: 信息 (INFO)

消息文本: 应用升级准备成功 (Application upgrade preparation successful)

消息说明: 应用升级准备成功

本地目标消息格式: <timestamp> <seq_num> 60178 INFO System-Management: Application upgrade preparation successful, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60178 INFO System-Management: Application upgrade preparation successful, <log details>

- 消息代码: 60179

严重性: 信息 (INFO)

消息文本: 应用升级准备已启动 (Application upgrade preparation started)

消息说明: 应用升级准备已启动

本地目标消息格式: <timestamp> <seq_num> 60179 INFO System-Management: Application upgrade preparation started, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60179 INFO System-Management: Application upgrade preparation started, <log details>

- 消息代码: 60180

严重性: 警告 (WARN)

消息文本: 系统日志服务器身份检查失败 (Syslog server Identity check failed)

消息说明: 系统日志服务器身份检查失败, 未与系统日志服务器建立安全通信

本地目标消息格式: <timestamp> <seq_num> 60180 WARN System-Management: Syslog server Identity check failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60180 WARN System-Management: Syslog server Identity check failed, <log details>

- 消息代码: 60184

严重性: 信息 (INFO)

消息文本: 控制台 CLI 用户已成功登录 (A console CLI user has successfully logged in)

消息说明: 控制台 CLI 用户已成功登录

本地目标消息格式: <timestamp> <seq_num> 60184 INFO Administrator-Login: A console CLI user has successfully logged in, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60184 INFO Administrator-Login: A console CLI user has successfully logged in, <log details>

- 消息代码: 60185

严重性: 信息 (INFO)

消息文本: 控制台 CLI 用户尝试登录未成功 (A console CLI user has attempted unsuccessfully to login)

消息说明: 控制台 CLI 用户尝试登录未成功

本地目标消息格式: <timestamp> <seq_num> 60185 INFO Administrator-Login: A console CLI user has attempted unsuccessfully to login, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60185 INFO Administrator-Login: A console CLI user has attempted unsuccessfully to login, <log details>

- 消息代码: 60186

严重性: 信息 (INFO)

消息文本: 控制台 CLI 用户已尝试登录, 但帐户被锁定 (A console CLI user has attempted to login, however account is locked out)

消息说明: 控制台 CLI 用户已尝试登录, 但帐户被锁定

本地目标消息格式: <timestamp> <seq_num> 60186 INFO Administrator-Login: A console CLI user has attempted to login, however account is locked out, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60186 INFO Administrator-Login: A console CLI user has attempted to login, however account is locked out, <log details>

- 消息代码: 60187

严重性: 信息 (INFO)

消息文本: 应用升级成功 (Application upgrade succeeded)

消息说明: 应用升级成功

本地目标消息格式: <timestamp> <seq_num> 60187 INFO System-Management: Application upgrade succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60187 INFO System-Management: Application
upgrade succeeded, <log details>

- 消息代码: 60188

严重性: 信息 (INFO)

消息文本: 尝试 SSH 连接失败 (An attempted SSH connection has failed)

消息说明: 尝试 SSH 连接失败

本地目标消息格式: <timestamp> <seq_num> 60188 INFO Administrator-Login: An attempted SSH
connection has failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60188 INFO Administrator-Login: An
attempted SSH connection has failed, <log details>

- 消息代码: 60189

严重性: 信息 (INFO)

消息文本: 已修改终端会话超时 (Terminal Session timeout has been modified)

消息说明: ADEOS CLI 终端会话超时的配置发生变更

本地目标消息格式: <timestamp> <seq_num> 60189 INFO System-Management: Terminal Session
timeout has been modified, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60189 INFO System-Management: Terminal
Session timeout has been modified, <log details>

- 消息代码: 60190

严重性: 信息 (INFO)

消息文本: xGrid 管理员操作 (xGrid Administrator Action)

消息说明: xGrid 管理员操作

本地目标消息格式: <timestamp> <seq_num> 60190 INFO System-Management: xGrid Administrator
Action, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60190 INFO System-Management: xGrid
Administrator Action, <log details>

- 消息代码: 60191

严重性: 错误 (ERROR)

消息文本: 节点上的虚拟机资源不足 (Insufficient Virtual Machine Resources on node)

消息说明: 节点上的虚拟机资源不足

本地目标消息格式: <timestamp> <seq_num> 60191 ERROR System-Management: Insufficient Virtual Machine Resources on node, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60191 ERROR System-Management: Insufficient Virtual Machine Resources on node, <log details>

- 消息代码: 60192

严重性: 错误 (ERROR)

消息文本: 需要在节点上更新固件 (Firmware update required on node)

消息说明: 需要在节点上更新固件

本地目标消息格式: <timestamp> <seq_num> 60192 ERROR System-Management: Firmware update required on node, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60192 ERROR System-Management: Firmware update required on node, <log details>

- 消息代码: 60193

严重性: 信息 (INFO)

消息文本: 已修改 RSA 密钥配置 (RSA key configuration has been modified)

消息说明: ADEOS CLI RSA 密钥配置发生更改

本地目标消息格式: <timestamp> <seq_num> 60193 INFO System-Management: RSA key configuration has been modified, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60193 INFO System-Management: RSA key configuration has been modified, <log details>

- 消息代码: 60194

严重性: 信息 (INFO)

消息文本: 已修改主机密钥配置 (Host key configuration has been modified)

消息说明: ADEOS CLI 主机密钥配置发生更改

本地目标消息格式: <timestamp> <seq_num> 60194 INFO System-Management: Host key configuration has been modified, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60194 INFO System-Management: Host key configuration has been modified, <log details>

- 消息代码: 60195

严重性: 信息 (INFO)

消息文本: CA 服务已启动 (CA Service started)

消息说明: CA 服务已启动

本地目标消息格式: <timestamp> <seq_num> 60195 INFO CA-Service: CA Service started, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60195 INFO CA-Service: CA Service started, <log details>

- 消息代码: 60196

严重性: 信息 (INFO)

消息文本: CA 服务已停止 (CA Service stopped)

消息说明: CA 服务已停止

本地目标消息格式: <timestamp> <seq_num> 60196 INFO CA-Service: CA Service stopped, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60196 INFO CA-Service: CA Service stopped, <log details>

- 消息代码: 60197

严重性: 通知 (NOTICE)

消息文本: 已撤销 ISE CA 颁发的证书。(Revoked ISE CA issued Certificate.)

消息说明: 管理员撤销了 ISE CA 向终端颁发的证书

本地目标消息格式: <timestamp> <seq_num> 60197 NOTICE CA-Service: Revoked ISE CA issued Certificate., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60197 NOTICE CA-Service: Revoked ISE CA issued Certificate., <log details>

- 消息代码: 60198

严重性: 信息 (INFO)

消息文本: 发生 MnT 清除事件 (MnT purge event occurred)

消息说明: 发生 MnT 清除事件

本地目标消息格式: <timestamp> <seq_num> 60198 INFO System-Management: MnT purge event occurred, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60198 INFO System-Management: MnT purge event occurred, <log details>

- 消息代码: 60199

严重性: 信息 (INFO)

消息文本: IP-SGT 映射部署成功 (An IP-SGT mapping was deployed successfully)

消息说明: IP-SGT 映射成功部署到 TrustSec 设备

本地目标消息格式: <timestamp> <seq_num> 60199 INFO TrustSec: An IP-SGT mapping was deployed successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60199 INFO TrustSec: An IP-SGT mapping was deployed successfully, <log details>

- 消息代码: 60200

严重性: 信息 (INFO)

消息文本: IP-SGT 映射部署失败 (An IP-SGT mapping has failed deploying)

消息说明: 向 TrustSec 设备部署 IP-SGT 映射失败

本地目标消息格式: <timestamp> <seq_num> 60200 INFO TrustSec: An IP-SGT mapping has failed deploying, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60200 INFO TrustSec: An IP-SGT mapping has failed deploying, <log details>

- 消息代码: 60201

严重性: 信息 (INFO)

消息文本: 向 TrustSec 设备部署 IP-SGT 成功 (IP-SGT deployment to TrustSec device was successful)

消息说明: 向 TrustSec 设备部署 IP-SGT 成功

本地目标消息格式: <timestamp> <seq_num> 60201 INFO TrustSec: IP-SGT deployment to TrustSec device was successful, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60201 INFO TrustSec: IP-SGT deployment to TrustSec device was successful, <log details>

- 消息代码: 60202

严重性: 信息 (INFO)

消息文本: 向 TrustSec 设备部署 IP-SGT 失败 (IP-SGT deployment to TrustSec device failed)

消息说明: 向 TrustSec 设备部署 IP-SGT 失败

本地目标消息格式: <timestamp> <seq_num> 60202 INFO TrustSec: IP-SGT deployment to TrustSec device failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60202 INFO TrustSec: IP-SGT deployment to TrustSec device failed, <log details>

- 消息代码: 60203

严重性: 信息 (INFO)

消息文本: 向 TrustSec 设备部署 IP-SGT 完毕 (IP-SGT deployment to the TrustSec devices finished)

消息说明: 向 TrustSec 设备部署 IP-SGT 完毕

本地目标消息格式: <timestamp> <seq_num> 60203 INFO TrustSec: IP-SGT deployment to the TrustSec devices finished, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60203 INFO TrustSec: IP-SGT deployment to the TrustSec devices finished, <log details>

- 消息代码: 60204

严重性: 信息 (INFO)

消息文本: 系统根 CLI 帐户已成功登录 (System root CLI account has successfully logged in)

消息说明: 系统根 CLI 帐户已成功登录

本地目标消息格式: <timestamp> <seq_num> 60204 INFO System-Management: System root CLI account has successfully logged in, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60204 INFO System-Management: System root CLI account has successfully logged in, <log details>

- 消息代码: 60205

严重性: 信息 (INFO)

消息文本: CLI 用户已从控制台登录 (A CLI user has logged in from console)

消息说明: CLI 用户已从控制台登录

本地目标消息格式: <timestamp> <seq_num> 60205 INFO Administrator-Login: A CLI user has logged in from console, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60205 INFO Administrator-Login: A CLI user has logged in from console, <log details>

- 消息代码: 60206

严重性: 信息 (INFO)

消息文本: CLI 用户已从控制台退出 (A CLI user has logged out from console)

消息说明: CLI 用户已从控制台退出

本地目标消息格式: <timestamp> <seq_num> 60206 INFO Administrator-Login: A CLI user has logged out from console, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60206 INFO Administrator-Login: A CLI user has logged out from console, <log details>

- 消息代码: 60207
 - 严重性: 信息 (INFO)
 - 消息文本: 已修改日志记录 Loglevel 配置 (logging loglevel configuration has been modified)
 - 消息说明: ADEOS CLI 日志记录 Loglevel 的配置发生更改
 - 本地目标消息格式: <timestamp> <seq_num> 60207 INFO System-Management: logging loglevel configuration has been modified, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60207 INFO System-Management: logging loglevel configuration has been modified, <log details>

- 消息代码: 60208
 - 严重性: 信息 (INFO)
 - 消息文本: 已替换根 CA 证书 (Root CA certificate has been replaced)
 - 消息说明: 已替换根 CA 证书
 - 本地目标消息格式: <timestamp> <seq_num> 60208 INFO System-Management: Root CA certificate has been replaced, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60208 INFO System-Management: Root CA certificate has been replaced, <log details>

- 消息代码: 60209
 - 严重性: 信息 (INFO)
 - 消息文本: CA 服务已启用 (CA service enabled)
 - 消息说明: CA 服务已启用
 - 本地目标消息格式: <timestamp> <seq_num> 60209 INFO System-Management: CA service enabled, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60209 INFO System-Management: CA service enabled, <log details>

- 消息代码: 60210
 - 严重性: 信息 (INFO)
 - 消息文本: CA 服务已禁用 (CA service disabled)
 - 消息说明: CA 服务已禁用
 - 本地目标消息格式: <timestamp> <seq_num> 60210 INFO System-Management: CA service disabled, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60210 INFO System-Management: CA
service disabled, <log details>

- 消息代码: 60211

严重性: 信息 (INFO)

消息文本: ISE 已从第三方 CA 服务器获取下级证书权限 (ISE acquired subordinate from 3rd party
CA server)

消息说明: ISE 已从第三方 CA 服务器获取下级证书权限

本地目标消息格式: <timestamp> <seq_num> 60211 INFO System-Management: ISE acquired
subordinate certificate authority from 3rd party CA server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60211 INFO System-Management: ISE
acquired subordinate certificate authority from 3rd party CA server, <log details>

- 消息代码: 60212

严重性: 警告 (WARNING)

消息文本: 由于缺少证书标签, 因此门户无法在此节点上启动 (Portal could not start on this node
since Certificate tag is missing)

消息说明: 由于缺少证书标签, 因此门户无法在此节点上启动

本地目标消息格式: <timestamp> <seq_num> 60212 WARNING System-Management: Portal could
not start on this node since Certificate tag is missing, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60212 WARNING System-Management:
Portal could not start on this node since Certificate tag is missing, <log details>

- 消息代码: 60213

严重性: 信息 (INFO)

消息文本: CA 密钥被导入操作替换 (CA keys were replaced by import operation)

消息说明: CA 密钥被导入操作替换

本地目标消息格式: <timestamp> <seq_num> 60213 INFO System-Management: CA keys were
replaced by import operation, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60213 INFO System-Management: CA keys
were replaced by import operation, <log details>

- 消息代码: 60214

严重性: 信息 (INFO)

消息文本: CA 密钥已导出 (CA keys were exported)

消息说明: CA 密钥已导出

本地目标消息格式: <timestamp> <seq_num> 60214 INFO System-Management: CA keys were exported, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60214 INFO System-Management: CA keys were exported, <log details>

- 消息代码: 60215

严重性: 信息 (INFO)

消息文本: 终端证书已标记为过期 (Endpoint certs were marked expired)

消息说明: 终端证书已由每天安排的作业标记为过期

本地目标消息格式: <timestamp> <seq_num> 60215 INFO CA-Service: Endpoint certs were marked expired, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60215 INFO CA-Service: Endpoint certs were marked expired, <log details>

- 消息代码: 60216

严重性: 信息 (INFO)

消息文本: 已清除终端证书 (Endpoint certs were purged)

消息说明: 终端证书已由每天安排的作业清除

本地目标消息格式: <timestamp> <seq_num> 60216 INFO CA-Service: Endpoint certs were purged, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60216 INFO CA-Service: Endpoint certs were purged, <log details>

- 消息代码: 60217

严重性: 警告 (WARN)

消息文本: 证书复制失败并将重试 (Certificate replication failed and will be retried)

消息说明: PAP 无法向辅助节点推送复制的证书, 例如通配符证书

本地目标消息格式: <timestamp> <seq_num> 60217 WARN Replication: Certificate replication failed and will be retried, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60217 WARN Replication: Certificate replication failed and will be retried, <log details>

- 消息代码: 60218

严重性: 警告 (WARN)

消息文本: 证书复制失败 (Certificate replication failed)

消息说明: PAP 无法向辅助节点推送复制的证书, 例如通配符证书

本地目标消息格式: <timestamp> <seq_num> 60218 WARN Replication: Certificate replication failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60218 WARN Replication: Certificate replication failed, <log details>

- 消息代码: 60219

严重性: 警告 (WARN)

消息文本: 管理节点未收到监控节点的任何 PAN HA 监控请求 (Administration Node has not received any PAN HA monitoring request from monitoring node)

消息说明: 管理节点未收到监控节点的任何 PAN HA 监控请求

本地目标消息格式: <timestamp> <seq_num> 60219 WARN Distributed-Management: Administration Node has not received any PAN HA monitoring request from monitoring node, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60219 WARN Distributed-Management: Administration Node has not received any PAN HA monitoring request from monitoring node, <log details>

- 消息代码: 60221

严重性: 警告 (WARN)

消息文本: PAN HA 监控配置错误 (Misconfiguration in PAN HA monitoring)

消息说明: PAN HA 监控配置错误

本地目标消息格式: <timestamp> <seq_num> 60221 WARN Distributed-Management: Misconfiguration in PAN HA monitoring, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60221 WARN Distributed-Management: Misconfiguration in PAN HA monitoring, <log details>

- 消息代码: 60222

严重性: 警告 (WARN)

消息文本: PAN 无法访问或运行状况不佳 (PAN is not reachable or unhealthy)

消息说明: PAN 无法访问或运行状况不佳

本地目标消息格式: <timestamp> <seq_num> 60222 WARN Distributed-Management: PAN is not reachable or unhealthy, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60222 WARN Distributed-Management: PAN is not reachable or unhealthy, <log details>

- 消息代码: 60223
 - 严重性: 错误 (ERROR)
 - 消息文本: PAN HA 升级请求失败 (PAN HA Promotion request failed)
 - 消息说明: PAN HA 升级请求失败
 - 本地目标消息格式: <timestamp> <seq_num> 60223 ERROR Distributed-Management: PAN HA Promotion request failed, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60223 ERROR Distributed-Management: PAN HA Promotion request failed, <log details>

- 消息代码: 60224
 - 严重性: 信息 (INFO)
 - 消息文本: 已成功触发目标为辅助 PAN 的自动故障切换 (Automatic failover to the Secondary PAN is successfully triggered)
 - 消息说明: 已成功触发目标为辅助 PAN 的自动故障切换
 - 本地目标消息格式: <timestamp> <seq_num> 60224 INFO Distributed-Management: Automatic failover to the Secondary PAN is successfully triggered, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60224 INFO Distributed-Management: Automatic failover to the Secondary PAN is successfully triggered, <log details>

- 消息代码: 60225
 - 严重性: 错误 (ERROR)
 - 消息文本: 无法构建证书链 (Unable to build the certificate chain)
 - 消息说明: 在主题字段中找到两个或两个以上具有相同 CN 属性值的证书, 这导致构建证书链出错
 - 本地目标消息格式: <timestamp> <seq_num> 60225 ERROR Client Provisioning: Unable to build the certificate chain, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60225 ERROR Client Provisioning: Unable to build the certificate chain, <log details>

- 消息代码: 60226
 - 严重性: 信息 (INFO)
 - 消息文本: 已成功为正在撤销的用户证书执行 CoA 终止 (Successfully performed CoA termination(s) for a user certificate being revoked)
 - 消息说明: 已成功为正在撤销的用户证书执行 CoA 终止

本地目标消息格式: <timestamp> <seq_num> 60226 INFO Certificate: Successfully performed CoA termination(s) for a user certificate being revoked, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60226 INFO Certificate: Successfully performed CoA termination(s) for a user certificate being revoked, <log details>

- 消息代码: 60227

严重性: 信息 (INFO)

消息文本: 无法执行 CoA 终止 (Failed to perform a CoA termination)

消息说明: 请确保 NAD 已配置为在向 ISE 发出 RADIUS access-request 时发送客户端 MAC 地址

本地目标消息格式: <timestamp> <seq_num> 60227 INFO Certificate: Failed to perform a CoA termination, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60227 INFO Certificate: Failed to perform a CoA termination, <log details>

- 消息代码: 60228

严重性: 错误 (ERROR)

消息文本: 无法访问 MSE 服务器 (MSE Server is unreachable)

消息说明: 无法访问 MSE 服务器

本地目标消息格式: <timestamp> <seq_num> 60228 ERROR System-Management: MSE Server is unreachable, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60228 ERROR System-Management: MSE Server is unreachable, <log details>

- 消息代码: 60229

严重性: 信息 (INFO)

消息文本: MSE 服务器重新上线 (MSE Server is back online)

消息说明: MSE 服务器重新上线

本地目标消息格式: <timestamp> <seq_num> 60229 INFO System-Management: MSE Server is back online, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60229 INFO System-Management: MSE Server is back online, <log details>

- 消息代码: 60231

严重性: 信息 (INFO)

消息文本: 已查询 MSE 服务器 (Queried MSE server)

消息说明: 已查询 MSE 服务器, 以获取终端位置

本地目标消息格式: <timestamp> <seq_num> 60231 INFO System-Management: Queried MSE server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60231 INFO System-Management: Queried MSE server, <log details>

- 消息代码: 60232

严重性: 信息 (INFO)

消息文本: 已开始对照自动检索的 CRL 执行持续会话检查 (Started ongoing sessions check against automatically retrieved CRL)

消息说明: 下载 CRL 后, 立即开始执行所有持续 TLS 会话检查。

本地目标消息格式: <timestamp> <seq_num> 60232 INFO System-Management: Started ongoing sessions check against automatically retrieved CRL, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60232 INFO System-Management: Started ongoing sessions check against automatically retrieved CRL, <log details>

- 消息代码: 60233

严重性: 信息 (INFO)

消息文本: 因证书撤销导致终端会话终止 (The endpoint session is terminated due to the revoked certificate)

消息说明: 对照已下载的 CRL 执行持续会话检查后, 撤销的终端证书导致终端会话被终止

本地目标消息格式: <timestamp> <seq_num> 60233 INFO Dynamic-Authorization: The endpoint session is terminated due to the revoked certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60233 INFO Dynamic-Authorization: The endpoint session is terminated due to the revoked certificate, <log details>

- 消息代码: 60234

严重性: 错误 (ERROR)

消息文本: SXP 连接已断开 (The SXP connection has been disconnected)

消息说明: SXP 连接已断开

本地目标消息格式: <timestamp> <seq_num> 60234 ERROR Sxp: The SXP connection has been disconnected, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60234 ERROR Sxp: The SXP connection has been disconnected, <log details>

- 消息代码: 60235

严重性: 信息 (INFO)

消息文本: SXP 连接成功 (SXP connection succeeded)

消息说明: SXP 连接成功

本地目标消息格式: <timestamp> <seq_num> 60235 INFO SXP: SXP connection succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60235 INFO SXP: SXP connection succeeded, <log details>

- 消息代码: 60236

严重性: 警告 (WARN)

消息文本: SXP 连接失败 (SXP connection failed)

消息说明: SXP 连接失败

本地目标消息格式: <timestamp> <seq_num> 60236 WARN SXP: SXP connection failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60236 WARN SXP: SXP connection failed, <log details>

- 消息代码: 60237

严重性: 信息 (INFO)

消息文本: SXP 绑定成功 (SXP binding is successful)

消息说明: SXP 绑定成功

本地目标消息格式: <timestamp> <seq_num> 60237 INFO SXP: SXP binding is successful, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60237 INFO SXP: SXP binding is successful, <log details>

- 消息代码: 60238

严重性: 信息 (INFO)

消息文本: SXP 绑定失败 (SXP binding failed)

消息说明: SXP 绑定失败

本地目标消息格式: <timestamp> <seq_num> 60238 INFO SXP: SXP binding failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60238 INFO SXP: SXP binding failed, <log details>

- 消息代码: 60239

严重性: 警告 (WARN)

消息文本: SXP 绑定发生冲突 (SXP binding conflict has occurred)

消息说明: SXP 绑定发生冲突

本地目标消息格式: <timestamp> <seq_num> 60239 WARN SXP: SXP binding conflict has occurred, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60239 WARN SXP: SXP binding conflict has occurred, <log details>

- 消息代码: 60400

严重性: 信息 (INFO)

消息文本: 已根据网络设备配置文件配置生成策略元素。(Policy elements have been generated based on network device profile configuration.)

消息说明: 已根据网络设备配置文件配置生成策略元素。

本地目标消息格式: <timestamp> <seq_num> 60400 INFO Configuration-Changes: Policy elements have been generated based on network device profile configuration., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60400 INFO Configuration-Changes: Policy elements have been generated based on network device profile configuration., <log details>

- 消息代码: 60401

严重性: 信息 (INFO)

消息文本: 提醒: 分配 NAD 配置文件。(Reminder: Assign NAD Profiles.)

消息说明: 网络接入设备现在具有定义其功能的NAD配置文件。已为现有的所有设备分配默认的思科 NAD 配置文件, 非思科设备应更改此配置文件。

本地目标消息格式: <timestamp> <seq_num> 60401 INFO Configuration-Changes: Reminder: Assign NAD Profiles., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60401 INFO Configuration-Changes: Reminder: Assign NAD Profiles., <log details>

- 消息代码: 60451

严重性: 信息 (INFO)

消息文本: 已在此部署上启用遥测 (Telemetry is enabled on this deployment)

消息说明: 已在此部署上启用遥测

本地目标消息格式: <timestamp> <seq_num> 60451 INFO System-Management: Telemetry is enabled on this deployment, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60451 INFO System-Management: Telemetry
is enabled on this deployment, <log details>

- 消息代码: 60452

严重性: 信息 (INFO)

消息文本: 已在此部署上禁用遥测 (Telemetry is disabled on this deployment)

消息说明: 已在此部署上禁用遥测

本地目标消息格式: <timestamp> <seq_num> 60452 INFO System-Management: Telemetry is disabled
on this deployment, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60452 INFO System-Management: Telemetry
is disabled on this deployment, <log details>

- 消息代码: 60453

严重性: 信息 (INFO)

消息文本: 遥测消息发送成功 (Telemetry messages were sent successfully)

消息说明: 遥测消息发送成功

本地目标消息格式: <timestamp> <seq_num> 60453 INFO System-Management: Telemetry messages
were sent successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60453 INFO System-Management: Telemetry
messages were sent successfully, <log details>

- 消息代码: 60454

严重性: 信息 (INFO)

消息文本: 遥测消息未成功发送 (Telemetry messages were not sent successfully)

消息说明: 遥测消息未发送成功

本地目标消息格式: <timestamp> <seq_num> 60454 INFO System-Management: Telemetry messages
were not sent successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60454 INFO System-Management: Telemetry
messages were not sent successfully, <log details>

- 消息代码: 60501

严重性: 警告 (WARN)

消息文本: ERS xml 输入涉嫌是 XSS 或注入攻击 (ERS xml input is a suspect for XSS or Injection
attack)

消息说明: 请检查您的 xml 输入

本地目标消息格式: <timestamp> <seq_num> 60501 WARN ERS: ERS xml input is a suspect for XSS or Injection attack, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60501 WARN ERS: ERS xml input is a suspect for XSS or Injection attack, <log details>

- 消息代码: 60502

严重性: 警告 (WARN)

消息文本: ERS 发现已弃用的 URL (ERS identified deprecated url)

消息说明: 请求 URL 已弃用, 建议避免使用它

本地目标消息格式: <timestamp> <seq_num> 60502 WARN ERS: ERS identified deprecated url, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60502 WARN ERS: ERS identified deprecated url, <log details>

- 消息代码: 60503

严重性: 警告 (WARN)

消息文本: ERS 发现过时的 URL (ERS identified out-dated url)

消息说明: 请求 URL 已过时, 建议使用较新的 URL。未来版本不会删除此 URL

本地目标消息格式: <timestamp> <seq_num> 60503 WARN ERS: ERS identified out-dated url, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60503 WARN ERS: ERS identified out-dated url, <log details>

- 消息代码: 60504

严重性: 警告 (WARN)

消息文本: ERS 请求的 content-type 信头已过时 (ERS request content-type header is out-dated)

消息说明: 请求的 content-type 信头中描述的请求资源版本已过时。这意味着资源方案已得到修改, 可能已添加或删除一个或多个属性。受过时方案影响, ERS 引擎将使用默认值

本地目标消息格式: <timestamp> <seq_num> 60504 WARN ERS: ERS request content-type header is out-dated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60504 WARN ERS: ERS request content-type header is out-dated, <log details>

- 消息代码: 11319

严重性: 警告 (WARN)

消息文本: TrustSec 仅支持 TLS 1.0 (TrustSec works only with TLS 1.0)

消息说明: TrustSec 仅支持 TLS 1.0, 如果您计划使用 TrustSec, 请确保启用它

本地目标消息格式: <timestamp> <seq_num> 11319 WARN TrustSec: TrustSec works only with TLS 1.0, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 11319 WARN TrustSec: TrustSec works only with TLS 1.0, <log details>

- 消息代码: 60455

严重性: 信息 (INFO)

消息文本: 已在“允许的协议”中选择“简易有线访问”, 但尚未激活身份映射 (Easy Wired is selected on Allowed Protocol but Identity Mapping has NOT been activated)

消息说明: 已在“允许的协议” (Allowed Protocol) 中选择“简易有线访问” (Easy Wired), 但尚未激活身份映射

本地目标消息格式: <timestamp> <seq_num> 60455 INFO System-Management: Easy Wired is selected on Allowed Protocol but Identity Mapping has NOT been activated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60455 INFO System-Management: Easy Wired is selected on Allowed Protocol but Identity Mapping has NOT been activated, <log details>

- 消息代码: 60456

严重性: 信息 (INFO)

消息文本: 已启动 CRL/OCSP 定期证书检查 (Started CRL/OCSP periodic certificate check)

消息说明: 已启动 CRL/OCSP 定期证书检查

本地目标消息格式: <timestamp> <seq_num> 60456 INFO System-Management: Started CRL/OCSP periodic certificate check, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60456 INFO System-Management: Started CRL/OCSP periodic certificate check, <log details>

- 消息代码: 60457

严重性: 信息 (INFO)

消息文本: 管理员 UI 访问的身份验证类型方法 (Authentication Type Method for Admin UI Access)

消息说明: 表示身份验证类型方法配置更新成功的消息

本地目标消息格式: <timestamp> <seq_num> 60457 INFO Admin Access Authentication Method: Authentication Type Method for Admin UI Access, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 60457 INFO Admin Access Authentication Method: Authentication Type Method for Admin UI Access, <log details>

- 消息代码: 60458
 - 严重性: 信息 (INFO)
 - 消息文本: 管理员 UI 访问的身份验证类型方法 (Authentication Type Method for Admin UI Access)
 - 消息说明: 表示身份验证类型方法配置更新不成功的消息
 - 本地目标消息格式: <timestamp> <seq_num> 60458 INFO Admin Access Authentication Method: Authentication Type Method for Admin UI Access, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60458 INFO Admin Access Authentication Method: Authentication Type Method for Admin UI Access, <log details>

- 消息代码: 60459
 - 严重性: 错误 (ERROR)
 - 消息文本: 由于已达到绑定阈值, SXP 绑定未传播 (SXP binding binding not propagated because binding threshold has been reached)
 - 消息说明: SXP 绑定已达到阈值
 - 本地目标消息格式: <timestamp> <seq_num> 60459 ERROR SXP: SXP binding binding not propagated because binding threshold has been reached, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60459 ERROR SXP: SXP binding binding not propagated because binding threshold has been reached, <log details>

- 消息代码: 60460
 - 严重性: 信息 (INFO)
 - 消息文本: 由于帐户处于不活动状态, 已被禁用 (Account disabled due to inactivity)
 - 消息说明: 由于帐户处于不活动状态, 已被禁用
 - 本地目标消息格式: <timestamp> <seq_num> 60460 INFO System-Management: Account disabled due to inactivity, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60460 INFO System-Management: Account disabled due to inactivity, <log details>

- 消息代码: 60461
 - 严重性: 信息 (INFO)
 - 消息文本: 由于用户级别日期到期, 帐户已禁用 (Account disabled due to user level date expiry)
 - 消息说明: 由于用户级别日期到期, 帐户已禁用
 - 本地目标消息格式: <timestamp> <seq_num> 60461 INFO System-Management: Account disabled due to user level date expiry, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60461 INFO System-Management: Account disabled due to user level date expiry, <log details>

- 消息代码: 60462

严重性: 信息 (INFO)

消息文本: 由于全局级别日期到期, 帐户已禁用 (Account disabled due to global level date expiry)

消息说明: 由于全局级别日期到期, 帐户已禁用

本地目标消息格式: <timestamp> <seq_num> 60462 INFO System-Management: Account disabled due to global level date expiry, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60462 INFO System-Management: Account disabled due to global level date expiry, <log details>

- 消息代码: 60463

严重性: 信息 (INFO)

消息文本: 由于全局级别天数到期, 帐户已禁用 (Account disabled due to global level days expiry)

消息说明: 由于全局级别天数到期, 帐户已禁用

本地目标消息格式: <timestamp> <seq_num> 60463 INFO System-Management: Account disabled due to global level days expiry, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60463 INFO System-Management: Account disabled due to global level days expiry, <log details>

- 消息代码: 60464

严重性: 信息 (INFO)

消息文本: Smart Call Home 消息发送成功 (Smart Call Home messages were sent successfully)

消息说明: Smart Call Home 消息发送成功

本地目标消息格式: <timestamp> <seq_num> 60464 INFO System-Management: Smart Call Home messages were sent successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 60464 INFO System-Management: Smart Call Home messages were sent successfully, <log details>

- 消息代码: 60465

严重性: 信息 (INFO)

消息文本: Smart Call Home 消息未发送成功 (Smart Call Home messages were not sent successfully)

消息说明: Smart Call Home 消息未发送成功

本地目标消息格式: <timestamp> <seq_num> 60465 INFO System-Management: Smart Call Home messages were not sent successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 60465 INFO System-Management: Smart Call Home messages were not sent successfully, <log details>

- 消息代码: 61001

严重性: 信息 (INFO)

消息文本: APIC 自签证书已使用 (APIC self signed Certificate was used)

消息说明: APIC 自签证书已使用。ISE 使用自签证书验证了 APIC。

本地目标消息格式: <timestamp> <seq_num> 61001 INFO TrustSec: APIC self signed Certificate was used, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 61001 INFO TrustSec: APIC self signed Certificate was used, <log details>

- 消息代码: 61002

严重性: 信息 (INFO)

消息文本: ISE 已从 IEPG 获知新的 SGT (ISE has learned a new SGT from IEPG)

消息说明: ISE 已从 IEPG 获知新的 SGT

本地目标消息格式: <timestamp> <seq_num> 61002 INFO TrustSec: ISE has learned a new SGT from IEPG, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 61002 INFO TrustSec: ISE has learned a new SGT from IEPG, <log details>

- 消息代码: 61003

严重性: 信息 (INFO)

消息文本: ISE 已将新的 EEPG 传播到 APIC (ISE has propagated a new EEPG to APIC)

消息说明: ISE 已将新的 EEPG 传播到 APIC。

本地目标消息格式: <timestamp> <seq_num> 61003 INFO TrustSec: ISE has propagated a new EEPG to APIC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 61003 INFO TrustSec: ISE has propagated a new EEPG to APIC, <log details>

- 消息代码: 61004

严重性: 信息 (INFO)

消息文本: ISE 已从 APIC 终端获取新的 SXP 映射 (ISE has learned a new SXP mapping from APIC endpoint)

消息说明: ISE 已从 APIC 终端获取新的 SXP 映射

本地目标消息格式: <timestamp> <seq_num> 61004 INFO TrustSec: ISE has learned a new SXP mapping from APIC endpoint, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 61004 INFO TrustSec: ISE has learned a new SXP mapping from APIC endpoint, <log details>

- 消息代码: 61005

严重性: 信息 (INFO)

消息文本: ISE 已将新终端 (SXP 映射) 传播到 APIC (ISE has propagated a new endpoint(SXP mapping) to APIC)

消息说明: ISE 已将新终端 (SXP 映射) 传播到 APIC

本地目标消息格式: <timestamp> <seq_num> 61005 INFO TrustSec: ISE has propagated a new endpoint(SXP mapping) to APIC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 61005 INFO TrustSec: ISE has propagated a new endpoint(SXP mapping) to APIC, <log details>

- 消息代码: 61006

严重性: 信息 (INFO)

消息文本: 由于删除了 IEPG, ISE 已删除 SGT (ISE has removed an SGT due to deleted IEPG)

消息说明: 由于删除了 IEPG, ISE 已删除 SGT

本地目标消息格式: <timestamp> <seq_num> 61006 INFO TrustSec: ISE has removed an SGT due to deleted IEPG, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 61006 INFO TrustSec: ISE has removed an SGT due to deleted IEPG, <log details>

- 消息代码: 61007

严重性: 信息 (INFO)

消息文本: 由于删除了 SGT, ISE 已从 APIC 中删除 EEPG (ISE has removed EEPG from APIC due to SGT deletion)

消息说明: 由于删除了 SGT, ISE 已从 APIC 中删除 EEPG

本地目标消息格式: <timestamp> <seq_num> 61007 INFO TrustSec: ISE has removed EEPG from APIC due to SGT deletion, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 61007 INFO TrustSec: ISE has removed
EEPG from APIC due to SGT deletion, <log details>

- 消息代码: 61008

严重性: 信息 (INFO)

消息文本: 由于在 APIC 上删除了终点, ISE 已删除 SXP 映射 (ISE has removed an SXP mapping
due to endpoint deletion on APIC)

消息说明: 由于在 APIC 上删除了终点, ISE 已删除 SXP 映射

本地目标消息格式: <timestamp> <seq_num> 61008 INFO TrustSec: ISE has removed an SXP mapping
due to endpoint deletion on APIC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 61008 INFO TrustSec: ISE has removed an
SXP mapping due to endpoint deletion on APIC, <log details>

- 消息代码: 61009

严重性: 信息 (INFO)

消息文本: 由于 SXP 映射删除并建立与 APIC 的新 SXP 映射, ISE 已删除终端 APIC (ISE has
removed endpoint APIC due to SXP mapping removal a new SXP mapping to APIC)

消息说明: 由于 SXP 映射删除并建立与 APIC 的新 SXP 映射, ISE 已删除终端 APIC

本地目标消息格式: <timestamp> <seq_num> 61009 INFO TrustSec: ISE has removed endpoint APIC
due to SXP mapping removal a new SXP mapping to APIC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 61009 INFO TrustSec: ISE has removed
endpoint APIC due to SXP mapping removal a new SXP mapping to APIC, <log details>

- 消息代码: 61010

严重性: 信息 (INFO)

消息文本: ISE 已建立与 APIC 的连接 (ISE has established connection to APIC)

消息说明: ISE 已建立与 APIC 的连接

本地目标消息格式: <timestamp> <seq_num> 61010 INFO TrustSec: ISE has established connection
to APIC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 61010 INFO TrustSec: ISE has established
connection to APIC, <log details>

- 消息代码: 61011

严重性: 信息 (INFO)

消息文本: ISE 已从 APIC 断开 (ISE was disconnected from APIC)

消息说明: ISE 已从 APIC 断开

本地目标消息格式: <timestamp> <seq_num> 61011 INFO TrustSec: ISE was disconnected from APIC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 61011 INFO TrustSec: ISE was disconnected from APIC, <log details>

- 消息代码: 61012

严重性: 信息 (INFO)

消息文本: ISE 已成功通过 APIC 身份验证 (ISE has authenticated against APIC successfully)

消息说明: ISE 已成功通过 APIC 身份验证

本地目标消息格式: <timestamp> <seq_num> 61012 INFO TrustSec: ISE has authenticated against APIC successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 61012 INFO TrustSec: ISE has authenticated against APIC successfully, <log details>

- 消息代码: 61013

严重性: 信息 (INFO)

消息文本: ISE 未通过 APIC 身份验证 (ISE failed to authenticate against APIC)

消息说明: ISE 未通过 APIC 身份验证

本地目标消息格式: <timestamp> <seq_num> 61013 INFO TrustSec: ISE failed to authenticate against APIC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 61013 INFO TrustSec: ISE failed to authenticate against APIC, <log details>

- 消息代码: 61014

严重性: 信息 (INFO)

消息文本: ISE 已成功刷新 APIC 身份验证 (ISE has refreshed authentication against APIC successfully)

消息说明: ISE 已成功刷新 APIC 身份验证

本地目标消息格式: <timestamp> <seq_num> 61014 INFO TrustSec: ISE has refreshed authentication against APIC successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 61014 INFO TrustSec: ISE has refreshed authentication against APIC successfully, <log details>

- 消息代码: 61015

严重性: 信息 (INFO)

消息文本: ISE 未能刷新 APIC 身份验证 (ISE failed to refresh authenticate against APIC)

消息说明: ISE 未能刷新 APIC 身份验证

本地目标消息格式: <timestamp> <seq_num> 61015 INFO TrustSec: ISE failed to refresh authenticate against APIC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 61015 INFO TrustSec: ISE failed to refresh authenticate against APIC, <log details>

- 消息代码: 61016

严重性: 信息 (INFO)

消息文本: ISE 未能根据 APIC 刷新 EPG 用户 (ISE failed to refresh EPG subscriber against APIC)

消息说明: ISE 未能根据 APIC 刷新 EPG 用户

本地目标消息格式: <timestamp> <seq_num> 61016 INFO TrustSec: ISE failed to refresh EPG subscriber against APIC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 61016 INFO TrustSec: ISE failed to refresh EPG subscriber against APIC, <log details>

- 消息代码: 61017

严重性: 信息 (INFO)

消息文本: ISE 未能根据 APIC 刷新终端用户 (ISE failed to refresh endpoint subscriber against APIC)

消息说明: ISE 未能根据 APIC 刷新终端用户

本地目标消息格式: <timestamp> <seq_num> 61017 INFO TrustSec: ISE failed to refresh endpoint subscriber against APIC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 61017 INFO TrustSec: ISE failed to refresh endpoint subscriber against APIC, <log details>

- 消息代码: 61018

严重性: 信息 (INFO)

消息文本: ISE 未能根据 APIC 刷新 EEPG 用户 (ISE failed to refresh EEPG subscriber against APIC)

消息说明: ISE 未能根据 APIC 刷新 EEPG 用户

本地目标消息格式: <timestamp> <seq_num> 61018 INFO TrustSec: ISE failed to refresh EEPG subscriber against APIC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 61018 INFO TrustSec: ISE failed to refresh EEPG subscriber against APIC, <log details>

- 消息代码: 61020

严重性: 信息 (INFO)

消息文本: ISE 未能根据 APIC 刷新 L3EXTOUT 用户 (ISE failed to refresh L3EXTOUT subscriber against APIC)

消息说明: ISE 未能根据 APIC 刷新 L3EXTOUT 用户

本地目标消息格式: <timestamp> <seq_num> 61020 INFO TrustSec: ISE failed to refresh L3EXTOUT subscriber against APIC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 61020 INFO TrustSec: ISE failed to refresh L3EXTOUT subscriber against APIC, <log details>

- 消息代码: 61021

严重性: 信息 (INFO)

消息文本: 3 次重试后, ISE 收到类 ID 为 ANY 的 EPG。忽略此 EPG (After 3 retries, ISE recieved EPG with class id: ANY. Ignoring this EPG)

消息说明: 3 次重试后, ISE 收到类 ID 为 ANY 的 EPG。忽略此 EPG

本地目标消息格式: <timestamp> <seq_num> 61021 INFO TrustSec: After 3 retries, ISE recieved EPG with class id: ANY. Ignoring this EPG, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 61021 INFO TrustSec: After 3 retries, ISE recieved EPG with class id: ANY. Ignoring this EPG, <log details>

- 消息代码: 61022

严重性: 信息 (INFO)

消息文本: ISE 未能将 SGT 传播到 EEPG (ISE has failed to propagate SGT to EEPG)

消息说明: ISE 未能将 SGT 传播到 EEPG

本地目标消息格式: <timestamp> <seq_num> 61022 INFO TrustSec: ISE has failed to propagate SGT to EEPG, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 61022 INFO TrustSec: ISE has failed to propagate SGT to EEPG, <log details>

- 消息代码: 61023

严重性: 信息 (INFO)

消息文本: ISE 未能从 APIC 获知 IEPG (ISE has failed to learn IEPG from APIC)

消息说明: ISE 未能从 APIC 获知 IEPG

本地目标消息格式: <timestamp> <seq_num> 61023 INFO TrustSec: ISE has failed to learn IEPG from APIC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 61023 INFO TrustSec: ISE has failed to
learn IEPPG from APIC, <log details>

- 消息代码: 61024

严重性: 信息 (INFO)

消息文本: ISE 未能解析 EPG 的 VRF (ISE has failed to parse VRF for EPG)

消息说明: ISE 未能解析 EPG 的 VRF

本地目标消息格式: <timestamp> <seq_num> 61024 INFO TrustSec: ISE has failed to parse VRF for
EPG, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 61024 INFO TrustSec: ISE has failed to
parse VRF for EPG, <log details>

- 消息代码: 61025

严重性: 信息 (INFO)

消息文本: 打开与 TLS 对等点的安全连接 (Open secure connection with TLS peer)

消息说明: 建立了与 TLS 对等点的安全连接

本地目标消息格式: <timestamp> <seq_num> 61025 INFO System-Management: Open secure
connection with TLS peer, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 61025 INFO System-Management: Open
secure connection with TLS peer, <log details>

- 消息代码: 61026

严重性: 信息 (INFO)

消息文本: 关闭与 TLS 对等点的安全连接 (Shutdown secure connection with TLS peer)

消息说明: 与 TLS 对等点的安全连接关闭

本地目标消息格式: <timestamp> <seq_num> 61026 INFO System-Management: Shutdown secure
connection with TLS peer, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 61026 INFO System-Management: Shutdown
secure connection with TLS peer, <log details>

- 消息代码: 60505

严重性: 错误 (ERROR)

消息文本: 由于输入无效, ERS 请求被拒绝。(ERS request rejected due to invalid input.)

消息说明: 因为输入无效, ERS 请求被拒绝

本地目标消息格式: <timestamp> <seq_num>60505 ERROR ERS ERS request rejected due to invalid input., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>60505 ERROR ERS ERS request rejected due to invalid input., <log details>

- 消息代码: 60506

严重性: 错误 (ERROR)

消息文本: ERS 请求有恶意攻击的嫌疑 (ERS request suspicious of malicious attack)

消息说明: ERS 请求涉嫌恶意攻击。

本地目标消息格式: <timestamp> <seq_num>60506 ERROR ERS ERS request suspicious of malicious attack, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>60506 ERROR ERS ERS request suspicious of malicious attack, <log details>

- 消息代码: 60507

严重性: 错误 (ERROR)

消息文本: 由于用户未经授权, ERS 请求被拒绝。(ERS request rejected due to unauthorized user.)

消息说明: 因为发送请求的用户未经授权, 所以 ERS 请求被拒绝。

本地目标消息格式: <timestamp> <seq_num>60507 ERROR ERS ERS request rejected due to unauthorized user., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>60507 ERROR ERS ERS request rejected due to unauthorized user., <log details>

- 消息代码: 60508

严重性: 错误 (ERROR)

消息文本: 由于非主节点上的请求非法, ERS 请求被拒绝 (ERS request was rejected due to illegal request on a non-primary node)

消息说明: 因为非法请求发送到非主节点, 所以 ERS 请求被拒绝。

本地目标消息格式: <timestamp> <seq_num>60508 ERROR ERS ERS request was rejected due to illegal request on a non-primary node, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>60508 ERROR ERS ERS request was rejected due to illegal request on a non-primary node, <log details>

- 消息代码: 60509

严重性: 错误 (ERROR)

消息文本: 因为超出最大连接数, 所以 ERS 请求被拒绝 (ERS request was denied as maximum possible connection was exceeded)

消息说明: 因为超出最大连接数, 所以 ERS 请求被拒绝

本地目标消息格式: <timestamp> <seq_num>60509 ERROR ERS ERS request was denied as maximum possible connection was exceeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>60509 ERROR ERS ERS request was denied as maximum possible connection was exceeded, <log details>

- 消息代码: 61027

严重性: 警告 (WARN)

消息文本: 收到的 HTTP 请求无效或错误 (Received Invalid or Bad HTTP request)

消息说明: 系统检测到无效或错误的 HTTP 请求。这可能是一次安全攻击

本地目标消息格式: <timestamp> <seq_num>61027 WARN Bad-HTTP-Request Received Invalid or Bad HTTP request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>61027 WARN Bad-HTTP-Request Received Invalid or Bad HTTP request, <log details>

- 消息代码: 61028

严重性: 信息 (INFO)

消息文本: TrustSec 部署验证已启动。(TrustSec deploy verification has started.)

消息说明: TrustSec 部署验证过程已启动。

本地目标消息格式: <timestamp> <seq_num>61028 INFO TrustSec TrustSec deploy verification has started., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>61028 INFO TrustSec TrustSec deploy verification has started., <log details>

- 消息代码: 61029

严重性: 信息 (INFO)

消息文本: TrustSec 部署验证已结束。(TrustSec deploy verification has finished.)

消息说明: TrustSec 部署验证过程已结束。

本地目标消息格式: <timestamp> <seq_num>61029 INFO TrustSec TrustSec deploy verification has finished., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>61029 INFO TrustSec TrustSec deploy verification has finished., <log details>

- 消息代码: 61030
严重性: 信息 (INFO)
消息文本: TrustSec 部署验证已取消。(TrustSec deploy verification was canceled.)
消息说明: TrustSec 部署验证过程已取消, 因为新 TrustSec 部署已开始。
本地目标消息格式: <timestamp> <seq_num>61030 INFO TrustSec TrustSec deploy verification was canceled., <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61030 INFO TrustSec TrustSec deploy verification was canceled., <log details>
- 消息代码: 61031
严重性: 警告 (WARN)
消息文本: TrustSec 部署验证未接到 NAD。(TrustSec deploy verification failed to reach NAD.)
消息说明: TrustSec 部署验证过程未能连接到网络访问设备。
本地目标消息格式: <timestamp> <seq_num>61031 WARN TrustSec TrustSec deploy verification failed to reach NAD., <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61031 WARN TrustSec TrustSec deploy verification failed to reach NAD., <log details>
- 消息代码: 61032
严重性: 警告 (WARN)
消息文本: TrustSec 部署验证 - 策略差异。(TrustSec deploy verification - policy difference.)
消息说明: TrustSec 部署验证过程发现网络访问设备与 ISE TrustSec 配置之间存在差异。
本地目标消息格式: <timestamp> <seq_num>61032 WARN TrustSec TrustSec deploy verification - policy difference., <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61032 WARN TrustSec TrustSec deploy verification - policy difference., <log details>
- 消息代码: 61033
严重性: 信息 (INFO)
消息文本: TrustSec 部署验证过程成功。(TrustSec deployment verification process succeeded.)
消息说明: ISE Trustsec 配置已成功部署到所有网络访问设备。
本地目标消息格式: <timestamp> <seq_num>61033 INFO TrustSec TrustSec deployment verification process succeeded., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61033 INFO TrustSec TrustSec deployment
verification process succeeded., <log details>

- 消息代码: 61034

严重性: 信息 (INFO)

消息文本: 已达到最大资源限制。(Maximum resource limit reached.)

消息说明: 已达到最大资源限制。

本地目标消息格式: <timestamp> <seq_num>61034 INFO ResourceLimits Maximum resource limit
reached., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61034 INFO ResourceLimits Maximum
resource limit reached., <log details>

- 消息代码: 61035

严重性: 信息 (INFO)

消息文本: IP SGT 静态映射已发送到 NAD。(IP SGT static mapping has been sent to the NAD.)

消息说明: IP SGT 静态映射已发送到 NAD。

本地目标消息格式: <timestamp> <seq_num>61035 INFO TrustSec IP SGT static mapping has been
sent to the NAD., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61035 INFO TrustSec IP SGT static mapping
has been sent to the NAD., <log details>

- 消息代码: 61051

严重性: 信息 (INFO)

消息文本: 已配置 Synflood-limit (Synflood-limit configured)

消息说明: 已配置 Synflood-limit

本地目标消息格式: <timestamp> <seq_num>61051 INFO SynfloodLimitConfigured Synflood-limit
configured, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61051 INFO SynfloodLimitConfigured
Synflood-limit configured, <log details>

- 消息代码: 61052

严重性: 信息 (INFO)

消息文本: 已配置 rate-limit (rate-limit configured)

消息说明: 已配置 rate-limit

本地目标消息格式: <timestamp> <seq_num>61052 INFO RateLimitConfigured rate-limit configured, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61052 INFO RateLimitConfigured rate-limit configured, <log details>

- 消息代码: 61053

严重性: 警告 (WARN)

消息文本: 检测到无效的用户输入。不允许使用 * \ \$ @ 字符 (Invalid user input detected. * \ \$ @ characters are not allowed)

消息说明: 检测到无效的用户输入。不允许使用 * \ \$ @ 字符

本地目标消息格式: <timestamp> <seq_num>61053 WARN UserInputControl Invalid user input detected. * \ \$ @ characters are not allowed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61053 WARN UserInputControl Invalid user input detected. * \ \$ @ characters are not allowed, <log details>

- 消息代码: 61054

严重性: 错误 (ERROR)

消息文本: ISE 发现无效的授权配置文件 (ISE found Invalid authorization profile)

消息说明: ISE 发现无效的授权配置文件

本地目标消息格式: <timestamp> <seq_num>61054 ERROR Configuration-Changes ISE found Invalid authorization profile, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61054 ERROR Configuration-Changes ISE found Invalid authorization profile, <log details>

- 消息代码: 61055

严重性: 错误 (ERROR)

消息文本: 队列使用的内存很高 (The memory consumed by the queue is high)

消息说明: 队列使用的内存很高

本地目标消息格式: <timestamp> <seq_num>61055 ERROR System-Management The memory consumed by the queue is high, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61055 ERROR System-Management The memory consumed by the queue is high, <log details>

- 消息代码: 61056

严重性: 错误 (ERROR)

消息文本: 联合链路关闭 (The federation link was down)

消息说明: 联合链路关闭

本地目标消息格式: <timestamp> <seq_num>61056 ERROR System-Management The federation link was down, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61056 ERROR System-Management The federation link was down, <log details>

- 消息代码: 61057

严重性: 错误 (ERROR)

消息文本: 队列可用空间不足 (The space available to the queue is low)

消息说明: 队列可用空间不足

本地目标消息格式: <timestamp> <seq_num>61057 ERROR System-Management The space available to the queue is low, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61057 ERROR System-Management The space available to the queue is low, <log details>

- 消息代码: 61058

严重性: 错误 (ERROR)

消息文本: ISE 无法使用 SGT/SGT-IP 映射更新 APIC 服务器 (ISE has failed to update the APIC server with SGT/SGT-IP mappings)

消息说明: ISE 无法使用 SGT/SGT-IP 映射更新 APIC 服务器

本地目标消息格式: <timestamp> <seq_num>61058 ERROR TrustSec ISE has failed to update the APIC server with SGT/SGT-IP mappings, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61058 ERROR TrustSec ISE has failed to update the APIC server with SGT/SGT-IP mappings, <log details>

- 消息代码: 61059

严重性: 信息 (INFO)

消息文本: 来自客户成功网络的请求 (Request from Customer Success Network)

消息说明: 向客户成功网络请求了部署或支持信息

本地目标消息格式: <timestamp> <seq_num>61059 INFO Administrative and Operational Audit Request from Customer Success Network, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61059 INFO Administrative and Operational Audit Request from Customer Success Network, <log details>

- 消息代码: 61060
 - 严重性: 信息 (INFO)
 - 消息文本: ISE 服务器已注册到 Cisco Support Diagnostics (The ISE server is registered to Cisco Support Diagnostics)
 - 消息说明: ISE 服务器已注册到 Cisco Support Diagnostics
 - 本地目标消息格式: <timestamp> <seq_num>61060 INFO Cisco Support Diagnostics The ISE server is registered to Cisco Support Diagnostics, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61060 INFO Cisco Support Diagnostics The ISE server is registered to Cisco Support Diagnostics, <log details>

- 消息代码: 61061
 - 严重性: 信息 (INFO)
 - 消息文本: ISE 服务器已从 Cisco Support Diagnostics 取消注册 (The ISE server is de-registered from Cisco Support Diagnostics)
 - 消息说明: ISE 服务器已从 Cisco Support Diagnostics 取消注册
 - 本地目标消息格式: <timestamp> <seq_num>61061 INFO Cisco Support Diagnostics The ISE server is de-registered from Cisco Support Diagnostics, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61061 INFO Cisco Support Diagnostics The ISE server is de-registered from Cisco Support Diagnostics, <log details>

- 消息代码: 61062
 - 严重性: 信息 (INFO)
 - 消息文本: Cisco Support Diagnostics 双向连接已启用 (The Cisco Support Diagnostics bi-directional connectivity is enabled)
 - 消息说明: Cisco Support Diagnostics 双向连接已启用
 - 本地目标消息格式: <timestamp> <seq_num>61062 INFO Cisco Support Diagnostics The Cisco Support Diagnostics bi-directional connectivity is enabled, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61062 INFO Cisco Support Diagnostics The Cisco Support Diagnostics bi-directional connectivity is enabled, <log details>

- 消息代码: 61063
 - 严重性: 信息 (INFO)
 - 消息文本: Cisco Support Diagnostics 双向连接已禁用 (The Cisco Support Diagnostics bi-directional connectivity is disabled)
 - 消息说明: Cisco Support Diagnostics 双向连接已禁用

本地目标消息格式: <timestamp> <seq_num>61063 INFO Cisco Support Diagnostics The Cisco Support Diagnostics bi-directional connectivity is disabled, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>61063 INFO Cisco Support Diagnostics The Cisco Support Diagnostics bi-directional connectivity is disabled, <log details>

- 消息代码: 61064

严重性: 信息 (INFO)

消息文本: Cisco Support Diagnostics 双向连接已建立 (The Cisco Support Diagnostics bi-directional connectivity is established)

消息说明: Cisco Support Diagnostics 双向连接已建立

本地目标消息格式: <timestamp> <seq_num>61064 INFO Cisco Support Diagnostics The Cisco Support Diagnostics bi-directional connectivity is established, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>61064 INFO Cisco Support Diagnostics The Cisco Support Diagnostics bi-directional connectivity is established, <log details>

- 消息代码: 61065

严重性: 信息 (INFO)

消息文本: Cisco Support Diagnostics 双向连接已破坏 (The Cisco Support Diagnostics bi-directional connectivity is broken)

消息说明: Cisco Support Diagnostics 双向连接已破坏

本地目标消息格式: <timestamp> <seq_num>61065 INFO Cisco Support Diagnostics The Cisco Support Diagnostics bi-directional connectivity is broken, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>61065 INFO Cisco Support Diagnostics The Cisco Support Diagnostics bi-directional connectivity is broken, <log details>

- 消息代码: 61066

严重性: 信息 (INFO)

消息文本: ISE SSE 服务已登记到 Cisco Support Diagnostics (The ISE SSE services were enrolled to Cisco Support Diagnostics)

消息说明: ISE SSE 服务已登记到 Cisco Support Diagnostics

本地目标消息格式: <timestamp> <seq_num>61066 INFO Cisco Support Diagnostics The ISE SSE services were enrolled to Cisco Support Diagnostics, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>61066 INFO Cisco Support Diagnostics The ISE SSE services were enrolled to Cisco Support Diagnostics, <log details>

- 消息代码: 61067

严重性: 信息 (INFO)

消息文本: ISE SSE 服务已从 Cisco Support Diagnostics 取消注册 (The ISE SSE services were un-enrolled from Cisco Support Diagnostics)

消息说明: ISE SSE 服务已从 Cisco Support Diagnostics 取消注册

本地目标消息格式: <timestamp> <seq_num>61067 INFO Cisco Support Diagnostics The ISE SSE services were un-enrolled from Cisco Support Diagnostics, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>61067 INFO Cisco Support Diagnostics The ISE SSE services were un-enrolled from Cisco Support Diagnostics, <log details>

- 消息代码: 61068

严重性: 警告 (WARNING)

消息文本: ACI 集成性能不足 (ACI Integration Performance Insufficient)

消息说明: ACI 功能遇到性能问题: 无法将网络访问会话生成的所有终端 IP-SGT 映射转发到 ACI。

本地目标消息格式: <timestamp> <seq_num>61068 WARNING Alarm ACI Integration Performance Insufficient, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>61068 WARNING Alarm ACI Integration Performance Insufficient, <log details>

- 消息代码: 61069

严重性: 信息 (INFO)

消息文本: 对 ctsmatrix 的 Rest 请求成功 (Rest request to ctsmatrix succeeded)

消息说明: 对 ctsmatrix 的 Rest 请求成功

本地目标消息格式: <timestamp> <seq_num>61069 INFO Trustsec Audit Rest request to ctsmatrix succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>61069 INFO Trustsec Audit Rest request to ctsmatrix succeeded, <log details>

- 消息代码: 61070

严重性: 信息 (INFO)

消息文本: 对 ctssgacls 的 Rest 请求成功 (Rest request to ctssgacls succeeded)

消息说明: 对 ctssgacls 的 Rest 请求成功

本地目标消息格式: <timestamp> <seq_num>61070 INFO Trustsec Audit Rest request to ctssgacls succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61070 INFO Trustsec Audit Rest request to
ctssgacls succeeded, <log details>

- 消息代码: 61071

严重性: 信息 (INFO)

消息文本: 对 ctsenvdata 的 Rest 请求成功 (Rest request to ctsenvdata succeeded)

消息说明: 对 ctsenvdata 的 Rest 请求成功

本地目标消息格式: <timestamp> <seq_num>61071 INFO Trustsec Audit Rest request to ctsenvdata
succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61071 INFO Trustsec Audit Rest request to
ctsenvdata succeeded, <log details>

- 消息代码: 61072

严重性: 错误 (ERROR)

消息文本: 处理与 Trustsec 审核相关的 REST 请求时出错 (Error processing the REST request related
to Trustsec Audit)

消息说明: 处理与 Trustsec 审核相关的 REST 请求时出错

本地目标消息格式: <timestamp> <seq_num>61072 ERROR Trustsec Audit Error processing the
REST request related to Trustsec Audit, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61072 ERROR Trustsec Audit Error processing
the REST request related to Trustsec Audit, <log details>

- 消息代码: 61073

严重性: 信息 (INFO)

消息文本: Cisco Support Diagnostics 双向连接已破坏 (The Cisco Support Diagnostics bi-directional
connectivity is broken)

消息说明: Cisco Support Diagnostics 双向连接已破坏

本地目标消息格式: <timestamp> <seq_num>61073 INFO Cisco Support Diagnostics The Cisco
Support Diagnostics bi-directional connectivity is broken, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61073 INFO Cisco Support Diagnostics The
Cisco Support Diagnostics bi-directional connectivity is broken, <log details>

- 消息代码: 61074

严重性: 错误 (ERROR)

消息文本: 由于系统证书过期, 节点不同步 (Node went out of sync due to expired system certificate)

消息说明：由于系统证书过期，节点不同步

本地目标消息格式：<timestamp> <seq_num>61074 ERROR Distributed-Management Node went out of sync due to expired system certificate, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61074 ERROR Distributed-Management Node went out of sync due to expired system certificate, <log details>

- 消息代码：61075

严重性：警告 (WARNING)

消息文本：ACI 集成无法联系 DNA-C (ACI Integration cannot contact DNA-C)

消息说明：ACI 功能无法联系 DNA-C

本地目标消息格式：<timestamp> <seq_num>61075 WARNING Alarm ACI Integration cannot contact DNA-C, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61075 WARNING Alarm ACI Integration cannot contact DNA-C, <log details>

- 消息代码：51025

严重性：Web 服务的身份验证失败

消息文本：Web 服务的身份验证失败。(Authentication for web services failed.)

消息说明：通知 (NOTICE)

本地目标消息格式：<timestamp> <seq_num>51025 Authentication for web services failed User change password Authentication for web services failed., <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>51025 Authentication for web services failed User change password Authentication for web services failed., <log details>

- 消息代码：61076

严重性：发起人已成功注销

消息文本：发起人已成功注销 (Sponsor has been successfully logged out)

消息说明：信息 (INFO)

本地目标消息格式：<timestamp> <seq_num>61076 Sponsor has been successfully logged out Sponsor Sponsor has been successfully logged out, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61076 Sponsor has been successfully logged out Sponsor Sponsor has been successfully logged out, <log details>

- 消息代码：61077

严重性：MyDevices 已成功注销

消息文本: MyDevices 已成功注销 (MyDevices has been successfully logged out)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61077 MyDevices has been successfully logged out MyDevices MyDevices has been successfully logged out, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61077 MyDevices has been successfully logged out MyDevices MyDevices has been successfully logged out, <log details>

- 消息代码: 61078

严重性: 对 ctsreportconfig 的 Rest 请求成功

消息文本: 对 ctsreportconfig 的 Rest 请求成功 (Rest request to ctsreportconfig succeeded)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61078 Rest request to ctsreportconfig succeeded Trustsec Audit Rest request to ctsreportconfig succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61078 Rest request to ctsreportconfig succeeded Trustsec Audit Rest request to ctsreportconfig succeeded, <log details>

- 消息代码: 61079

严重性: NAD TrustSec 传播状态

消息文本: NAD TrustSec 传播状态 (NAD TrustSec Propagation Status)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61079 NAD TrustSec Propagation Status Trustsec Audit NAD TrustSec Propagation Status, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61079 NAD TrustSec Propagation Status Trustsec Audit NAD TrustSec Propagation Status, <log details>

- 消息代码: 61083

严重性: ACI 绑定已创建

消息文本: 收到 ACI 绑定创建消息 (Got ACI binding create message)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61083 ACI binding created TrustSec Got ACI binding create message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61083 ACI binding created TrustSec Got ACI binding create message, <log details>

- 消息代码: 61084

严重性: ACI 绑定已更新

消息文本: 收到 ACI 绑定更新消息 (Got ACI binding update message)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61084 ACI binding updated TrustSec Got ACI binding update message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61084 ACI binding updated TrustSec Got ACI binding update message, <log details>

- 消息代码: 61085

严重性: ACI 绑定已删除

消息文本: 收到 ACI 绑定删除消息 (Got ACI binding delete message)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61085 ACI binding deleted TrustSec Got ACI binding delete message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61085 ACI binding deleted TrustSec Got ACI binding delete message, <log details>

- 消息代码: 61087

严重性: ISE 通知了 ACI 绑定已创建

消息文本: ISE 通知了 ACI 绑定已创建 (ISE informed ACI about binding created)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61087 ISE informed ACI about binding created TrustSec ISE informed ACI about binding created, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61087 ISE informed ACI about binding created TrustSec ISE informed ACI about binding created, <log details>

- 消息代码: 61088

严重性: ISE 通知了 ACI 绑定已更新

消息文本: ISE 通知了 ACI 绑定已更新 (ISE informed ACI about binding updated)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61088 ISE informed ACI about binding updated TrustSec ISE informed ACI about binding updated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61088 ISE informed ACI about binding updated TrustSec ISE informed ACI about binding updated, <log details>

- 消息代码: 61089
 - 严重性: ISE 通知了 ACI 绑定已删除
 - 消息文本: ISE 通知了 ACI 绑定已删除 (ISE informed ACI about binding deleted)
 - 消息说明: 信息 (INFO)
 - 本地目标消息格式: <timestamp> <seq_num>61089 ISE informed ACI about binding deleted TrustSec ISE informed ACI about binding deleted, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61089 ISE informed ACI about binding deleted TrustSec ISE informed ACI about binding deleted, <log details>

- 消息代码: 61100
 - 严重性: ISE 已从 ACI 获知新租户
 - 消息文本: ISE 已从 ACI 获知新租户 (ISE has learned a new tenant from ACI)
 - 消息说明: 信息 (INFO)
 - 本地目标消息格式: <timestamp> <seq_num>61100 ISE has learned a new tenant from ACI TrustSec ISE has learned a new tenant from ACI, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61100 ISE has learned a new tenant from ACI TrustSec ISE has learned a new tenant from ACI, <log details>

- 消息代码: 61101
 - 严重性: ISE 已删除 ACI 租户
 - 消息文本: ISE 已删除 ACI 租户 (ISE has removed ACI tenant)
 - 消息说明: 信息 (INFO)
 - 本地目标消息格式: <timestamp> <seq_num>61101 ISE has removed ACI tenant TrustSec ISE has removed ACI tenant, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61101 ISE has removed ACI tenant TrustSec ISE has removed ACI tenant, <log details>

- 消息代码: 61102
 - 严重性: 在 ISE 中未能从 ACI 获知新租户
 - 消息文本: 在 ISE 中未能从 ACI 获知新租户 (Failed to learn new tenant from ACI in ISE)
 - 消息说明: 错误 (ERROR)
 - 本地目标消息格式: <timestamp> <seq_num>61102 Failed to learn new tenant from ACI in ISE TrustSec Failed to learn new tenant from ACI in ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61102 Failed to learn new tenant from ACI
in ISE TrustSec Failed to learn new tenant from ACI in ISE, <log details>

- 消息代码: 61103

严重性: 在 ISE 中未能删除 ACI 租户

消息文本: 在 ISE 中未能删除 ACI 租户 (Failed to remove ACI tenant in ISE)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61103 Failed to remove ACI tenant in ISE TrustSec
Failed to remove ACI tenant in ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61103 Failed to remove ACI tenant in ISE
TrustSec Failed to remove ACI tenant in ISE, <log details>

- 消息代码: 61104

严重性: ISE 已从 SDA 获知新租户

消息文本: ISE 已从 SDA 获知新租户 (ISE has learned a new tenant from SDA)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61104 ISE has learned a new tenant from SDA TrustSec
ISE has learned a new tenant from SDA, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61104 ISE has learned a new tenant from
SDA TrustSec ISE has learned a new tenant from SDA, <log details>

- 消息代码: 61105

严重性: ISE 已获知新的 VN 信息

消息文本: ISE 已获知新的 VN 信息 (IISE has learned a new VN info)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61105 ISE has learned a new VN info TrustSec IISE
has learned a new VN info, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61105 ISE has learned a new VN info TrustSec
IISE has learned a new VN info, <log details>

- 消息代码: 61106

严重性: 未能在 ISE 中创建 VN 信息

消息文本: 未能在 ISE 中创建 VN 信息 (Failed to create VN info in ISE)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61106 Failed to create VN info in ISE TrustSec Failed to create VN info in ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61106 Failed to create VN info in ISE TrustSec Failed to create VN info in ISE, <log details>

- 消息代码: 61107

严重性: ISE 中的 VN 信息已更新

消息文本: ISE 中的 VN 信息已更新 (VN info is updated in ISE)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61107 VN info is updated in ISE TrustSec VN info is updated in ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61107 VN info is updated in ISE TrustSec VN info is updated in ISE, <log details>

- 消息代码: 61108

严重性: 未能更新 ISE 中的 VN 信息

消息文本: 未能更新 ISE 中的 VN 信息 (Failed to update VN info in ISE)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61108 Failed to update VN info in ISE TrustSec Failed to update VN info in ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61108 Failed to update VN info in ISE TrustSec Failed to update VN info in ISE, <log details>

- 消息代码: 61109

严重性: ISE 中的 VN 信息已删除

消息文本: ISE 中的 VN 信息已删除 (VN info is deleted in ISE)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61109 VN info is deleted in ISE TrustSec VN info is deleted in ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61109 VN info is deleted in ISE TrustSec VN info is deleted in ISE, <log details>

- 消息代码: 61110

严重性: 未能删除 ISE 中的 VN 信息

消息文本: 未能删除 ISE 中的 VN 信息 (Failed to deleted VN info in ISE)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61110 Failed to deleted VN info in ISE TrustSec Failed to deleted VN info in ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61110 Failed to deleted VN info in ISE TrustSec Failed to deleted VN info in ISE, <log details>

- 消息代码: 61111

严重性: 域注册过程失败

消息文本: 域注册过程失败 (Domain registration process failed)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61111 Domain registration process failed TrustSec Domain registration process failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61111 Domain registration process failed TrustSec Domain registration process failed, <log details>

- 消息代码: 61112

严重性: 在 SPHUB 中启动域注册过程

消息文本: 在 SPHUB 中启动域注册过程 (Start domain registration process in SPHUB)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61112 Start domain registration process in SPHUB TrustSec Start domain registration process in SPHUB, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61112 Start domain registration process in SPHUB TrustSec Start domain registration process in SPHUB, <log details>

- 消息代码: 61113

严重性: 向域管理器发送证书请求

消息文本: 向域管理器发送证书请求 (Send certificate request to domain manager)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61113 Send certificate request to domain manager TrustSec Send certificate request to domain manager, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61113 Send certificate request to domain manager TrustSec Send certificate request to domain manager, <log details>

- 消息代码: 61114

严重性: 域注册成功完成

消息文本: 域注册成功完成 (Domain registration completed successfully)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61114 Domain registration completed successfully TrustSec Domain registration completed successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61114 Domain registration completed successfully TrustSec Domain registration completed successfully, <log details>

- 消息代码: 61115

严重性: 域注册失败

消息文本: 域注册失败 (Domain registration failed)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61115 Domain registration failed TrustSec DDomain registration failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61115 Domain registration failed TrustSec DDomain registration failed, <log details>

- 消息代码: 61116

严重性: 无法存储 ACI 证书

消息文本: 无法存储 ACI 证书 (Unable to store ACI certificate)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61116 Unable to store ACI certificate TrustSec Unable to store ACI certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61116 Unable to store ACI certificate TrustSec Unable to store ACI certificate, <log details>

- 消息代码: 61117

严重性: ACI 连接器已成功启动

消息文本: ACI 连接器已成功启动 (ACI connector started successfully)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61117 ACI connector started successfully TrustSec ACI connector started successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61117 ACI connector started successfully TrustSec ACI connector started successfully, <log details>

- 消息代码: 61118

严重性：未能启动 ACI 连接器

消息文本：未能启动 ACI 连接器 (Failed to start ACI connector)

消息说明：错误 (ERROR)

本地目标消息格式：<timestamp> <seq_num>61118 Failed to start ACI connector TrustSec Failed to start ACI connector, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61118 Failed to start ACI connector TrustSec Failed to start ACI connector, <log details>

• 消息代码：61119

严重性：域取消注册过程已启动

消息文本：域取消注册过程已启动 (Domain de-registration process started)

消息说明：信息 (INFO)

本地目标消息格式：<timestamp> <seq_num>61119 Domain de-registration process started TrustSec Domain de-registration process started, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61119 Domain de-registration process started TrustSec Domain de-registration process started, <log details>

• 消息代码：61120

严重性：已成功从 ISE 中删除 ACI 证书

消息文本：已成功从 ISE 中删除 ACI 证书 (Successfully deleted ACI certificate from ISE)

消息说明：信息 (INFO)

本地目标消息格式：<timestamp> <seq_num>61120 Successfully deleted ACI certificate from ISE TrustSec Successfully deleted ACI certificate from ISE, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61120 Successfully deleted ACI certificate from ISE TrustSec Successfully deleted ACI certificate from ISE, <log details>

• 消息代码：61121

严重性：未能从 ISE 中删除 ACI 证书

消息文本：未能从 ISE 中删除 ACI 证书 (Failed to delete ACI certificate from ISE)

消息说明：错误 (ERROR)

本地目标消息格式：<timestamp> <seq_num>61121 Failed to delete ACI certificate from ISE TrustSec Failed to delete ACI certificate from ISE, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61121 Failed to delete ACI certificate from ISE TrustSec Failed to delete ACI certificate from ISE, <log details>

- 消息代码: 61122
 - 严重性: 未能删除 ACI 密钥库
 - 消息文本: 未能删除 ACI 密钥库 (Failed to delete ACI keystore)
 - 消息说明: 错误 (ERROR)
 - 本地目标消息格式: <timestamp> <seq_num>61122 Failed to delete ACI keystore TrustSec Failed to delete ACI keystore, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61122 Failed to delete ACI keystore TrustSec Failed to delete ACI keystore, <log details>

- 消息代码: 61123
 - 严重性: ISE 已获知新的 ACI 域
 - 消息文本: ISE 已获知新的 ACI 域 (ISE has learned a new ACI domain)
 - 消息说明: 信息 (INFO)
 - 本地目标消息格式: <timestamp> <seq_num>61123 ISE has learned a new ACI domain TrustSec ISE has learned a new ACI domain, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61123 ISE has learned a new ACI domain TrustSec ISE has learned a new ACI domain, <log details>

- 消息代码: 61124
 - 严重性: 未能获知新的 ACI 域
 - 消息文本: 未能获知新的 ACI 域 (Failed to learn a new ACI domain)
 - 消息说明: 错误 (ERROR)
 - 本地目标消息格式: <timestamp> <seq_num>61124 Failed to learn a new ACI domain TrustSec Failed to learn a new ACI domain, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61124 Failed to learn a new ACI domain TrustSec Failed to learn a new ACI domain, <log details>

- 消息代码: 61125
 - 严重性: ISE 已删除 ACI 域
 - 消息文本: ISE 已删除 ACI 域 (ISE has removed ACI domain)
 - 消息说明: 信息 (INFO)
 - 本地目标消息格式: <timestamp> <seq_num>61125 ISE has removed ACI domain TrustSec ISE has removed ACI domain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61125 ISE has removed ACI domain TrustSec
ISE has removed ACI domain, <log details>

- 消息代码: 61126

严重性: 未能删除 ACI 域

消息文本: 未能删除 ACI 域 (Failed to remove ACI domain)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61126 Failed to remove ACI domain TrustSec Failed to
remove ACI domain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61126 Failed to remove ACI domain TrustSec
Failed to remove ACI domain, <log details>

- 消息代码: 61127

严重性: ISE 已获知新的 SDA 域

消息文本: ISE 已获知新的 SDA 域 (ISE has learned a new SDA domain)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61127 ISE has learned a new SDA domain TrustSec ISE
has learned a new SDA domain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61127 ISE has learned a new SDA domain
TrustSec ISE has learned a new SDA domain, <log details>

- 消息代码: 61128

严重性: 未能获知新的 SDA 域

消息文本: 未能获知新的 SDA 域 (Failed to learn a new SDA domain)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61128 Failed to learn a new SDA domain TrustSec Failed
to learn a new SDA domain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61128 Failed to learn a new SDA domain
TrustSec Failed to learn a new SDA domain, <log details>

- 消息代码: 61129

严重性: ISE 已删除 SDA 域

消息文本: ISE 已删除 SDA 域 (ISE has removed SDA domain)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61129 ISE has removed SDA domain TrustSec ISE has removed SDA domain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61129 ISE has removed SDA domain TrustSec ISE has removed SDA domain, <log details>

- 消息代码: 61130

严重性: 未能删除 SDA 域

消息文本: 未能删除 SDA 域 (Failed to remove SDA domain)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61130 Failed to remove SDA domain TrustSec Failed to remove SDA domain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61130 Failed to remove SDA domain TrustSec Failed to remove SDA domain, <log details>

- 消息代码: 61131

严重性: SDA 对等发起失败。ISE 域注册响应不成功

消息文本: SDA 对等发起失败。ISE 域注册响应不成功 (SDA peering initiation failed. Response from ISE Domain registration is unsuccessful)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61131 SDA peering initiation failed. Response from ISE Domain registration is unsuccessful TrustSec SDA peering initiation failed. Response from ISE Domain registration is unsuccessful, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61131 SDA peering initiation failed. Response from ISE Domain registration is unsuccessful TrustSec SDA peering initiation failed. Response from ISE Domain registration is unsuccessful, <log details>

- 消息代码: 61132

严重性: SDA 对等初始化失败。

消息文本: SDA 对等初始化失败。(SDA peering Initialization failed.)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61132 SDA peering Initialization failed. TrustSec SDA peering Initialization failed., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61132 SDA peering Initialization failed. TrustSec SDA peering Initialization failed., <log details>

- 消息代码: 61133

严重性: SDA 已成功启动对等进程。

消息文本: SDA 已成功启动对等进程。(SDA successfully initiated peering process.)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61133 SDA successfully initiated peering process. TrustSec SDA successfully initiated peering process., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>61133 SDA successfully initiated peering process. TrustSec SDA successfully initiated peering process., <log details>

- 消息代码: 61134

严重性: SDA 域广告未能发布到 ACI

消息文本: SDA 域广告未能发布到 ACI (SDA Domain advertisement failed publishing to ACI)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61134 SDA Domain advertisement failed publishing to ACI TrustSec SDA Domain advertisement failed publishing to ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>61134 SDA Domain advertisement failed publishing to ACI TrustSec SDA Domain advertisement failed publishing to ACI, <log details>

- 消息代码: 61135

严重性: SDA 域广告未能发布到 ISE

消息文本: SDA 域广告未能发布到 ISE (SDA Domain advertisement failed publishing to ISE)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61135 SDA Domain advertisement failed publishing to ISE TrustSec SDA Domain advertisement failed publishing to ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>61135 SDA Domain advertisement failed publishing to ISE TrustSec SDA Domain advertisement failed publishing to ISE, <log details>

- 消息代码: 61136

严重性: SDA 域广告成功发布到 ACI

消息文本: SDA 域广告成功发布到 ACI (Successful SDA Domain advertisement to ACI)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61136 Successful SDA Domain advertisement to ACI TrustSec Successful SDA Domain advertisement to ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>61136 Successful SDA Domain advertisement to ACI TrustSec Successful SDA Domain advertisement to ACI, <log details>

- 消息代码: 61137
 - 严重性: SDA 将 SXP 信息发布到 ISE
 - 消息文本: SDA 将 SXP 信息发布到 ISE (SDA Publishing SXP information to ISE)
 - 消息说明: 信息 (INFO)
 - 本地目标消息格式: <timestamp> <seq_num>61137 SDA Publishing SXP information to ISE TrustSec SDA Publishing SXP information to ISE, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61137 SDA Publishing SXP information to ISE TrustSec SDA Publishing SXP information to ISE, <log details>

- 消息代码: 61138
 - 严重性: 处理 SDA 发起的 mdpGatewayAdv 事件时出错
 - 消息文本: 处理 SDA 发起的 mdpGatewayAdv 事件时出错 (Error processing the mdpGatewayAdv event from SDA)
 - 消息说明: 错误 (ERROR)
 - 本地目标消息格式: <timestamp> <seq_num>61138 Error processing the mdpGatewayAdv event from SDA TrustSec Error processing the mdpGatewayAdv event from SDA, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61138 Error processing the mdpGatewayAdv event from SDA TrustSec Error processing the mdpGatewayAdv event from SDA, <log details>

- 消息代码: 61139
 - 严重性: 将 SDA 网关广告信息发布到 ISE
 - 消息文本: 将 SDA 网关广告信息发布到 ISE (Publishing SDA gateway advertisement information to ISE)
 - 消息说明: 信息 (INFO)
 - 本地目标消息格式: <timestamp> <seq_num>61139 Publishing SDA gateway advertisement information to ISE TrustSec Publishing SDA gateway advertisement information to ISE, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61139 Publishing SDA gateway advertisement information to ISE TrustSec Publishing SDA gateway advertisement information to ISE, <log details>

- 消息代码: 61140
 - 严重性: 将 SDA 网关广告信息发布到 ISE 时出错
 - 消息文本: 将 SDA 网关广告信息发布到 ISE 时出错 (Error in Publishing SDA gateway advertisement information to ISE)
 - 消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61140 Error in Publishing SDA gateway advertisement information to ISE TrustSec Error in Publishing SDA gateway advertisement information to ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61140 Error in Publishing SDA gateway advertisement information to ISE TrustSec Error in Publishing SDA gateway advertisement information to ISE, <log details>

- 消息代码: 61141

严重性: 将 SDA 的 VN 信息发布到 ACI

消息文本: 将 SDA 的 VN 信息发布到 ACI (Publishing SDA's VN information to ACI)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61141 Publishing SDA's VN information to ACI TrustSec Publishing SDA's VN information to ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61141 Publishing SDA's VN information to ACI TrustSec Publishing SDA's VN information to ACI, <log details>

- 消息代码: 61142

严重性: 未能将 SDA 的 VN 信息发布到 ACI

消息文本: 未能将 SDA 的 VN 信息发布到 ACI (Failed to publish SDA's VN information to ACI)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61142 Failed to publish SDA's VN information to ACI TrustSec Failed to publish SDA's VN information to ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61142 Failed to publish SDA's VN information to ACI TrustSec Failed to publish SDA's VN information to ACI, <log details>

- 消息代码: 61143

严重性: 将 SDA 的 VN 信息发布到 ISE

消息文本: 将 SDA 的 VN 信息发布到 ISE (Publishing SDA's VN information to ISE)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61143 Publishing SDA's VN information to ISE TrustSec Publishing SDA's VN information to ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61143 Publishing SDA's VN information to ISE TrustSec Publishing SDA's VN information to ISE, <log details>

- 消息代码: 61144

严重性: 未能处理 SDA 的 VN 信息发布到 ISE 的事件

消息文本: 未能处理 SDA 的 VN 信息发布到 ISE 的事件 (Failed handling the SDA's VN information publish to ISE)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61144 Failed handling the SDA's VN information publish to ISE TrustSec Failed handling the SDA's VN information publish to ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61144 Failed handling the SDA's VN information publish to ISE TrustSec Failed handling the SDA's VN information publish to ISE, <log details>

- 消息代码: 61145

严重性: 将 SDA 扩展 VN 响应发布到 ACI

消息文本: 将 SDA 扩展 VN 响应发布到 ACI (Publishing SDA extend VN response to ACI)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61145 Publishing SDA extend VN response to ACI TrustSec Publishing SDA extend VN response to ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61145 Publishing SDA extend VN response to ACI TrustSec Publishing SDA extend VN response to ACI, <log details>

- 消息代码: 61146

严重性: 未能将 SDA 扩展 VN 响应发布到 ACI

消息文本: 未能将 SDA 扩展 VN 响应发布到 ACI (Failed to publish SDA extend VN response to ACI)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61146 Failed to publish SDA extend VN response to ACI TrustSec Failed to publish SDA extend VN response to ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61146 Failed to publish SDA extend VN response to ACI TrustSec Failed to publish SDA extend VN response to ACI, <log details>

- 消息代码: 61147

严重性: 尚未从 SDA 获知租户。无法将消息发布到 ACI

消息文本: 尚未从 SDA 获知租户。无法将消息发布到 ACI (Tenant was not learned from SDA yet. Cannot publish message to ACI)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61147 Tenant was not learned from SDA yet. Cannot publish message to ACI TrustSec Tenant was not learned from SDA yet. Cannot publish message to ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61147 Tenant was not learned from SDA yet. Cannot publish message to ACI TrustSec Tenant was not learned from SDA yet. Cannot publish message to ACI, <log details>

- 消息代码: 61148

严重性: SDA MdpEndpointGroupAdvEvent 数据解析/存储失败

消息文本: SDA MdpEndpointGroupAdvEvent 数据解析/存储失败 (Failed parsing/storing SDA MdpEndpointGroupAdvEvent data)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61148 Failed parsing/storing SDA MdpEndpointGroupAdvEvent data TrustSec Failed parsing/storing SDA MdpEndpointGroupAdvEvent data, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61148 Failed parsing/storing SDA MdpEndpointGroupAdvEvent data TrustSec Failed parsing/storing SDA MdpEndpointGroupAdvEvent data, <log details>

- 消息代码: 61149

严重性: SDA Ack 消息解析/存储失败

消息文本: SDA Ack 消息解析/存储失败 (Failed parsing/storing the SDA Ack message)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61149 Failed parsing/storing the SDA Ack message TrustSec Failed parsing/storing the SDA Ack message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61149 Failed parsing/storing the SDA Ack message TrustSec Failed parsing/storing the SDA Ack message, <log details>

- 消息代码: 61150

严重性: 将 ACI 扩展 VN 响应发布到 ISE

消息文本: 将 ACI 扩展 VN 响应发布到 ISE (Publishing ACI extend VN response to ISE)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61150 Publishing ACI extend VN response to ISE TrustSec Publishing ACI extend VN response to ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61150 Publishing ACI extend VN response to ISE TrustSec Publishing ACI extend VN response to ISE, <log details>

- 消息代码: 61151

严重性: 未能将 ACI 扩展 VN 响应发布到 ISE

消息文本: 未能将 ACI 扩展 VN 响应发布到 ISE (Failed to publish ACI extend VN response to ISE)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61151 Failed to publish ACI extend VN response to ISE TrustSec Failed to publish ACI extend VN response to ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61151 Failed to publish ACI extend VN response to ISE TrustSec Failed to publish ACI extend VN response to ISE, <log details>

- 消息代码: 61152

严重性: ACI 通知 ISE 它收到了 SDA 扩展 vn

消息文本: ACI 通知 ISE 它收到了 SDA 扩展 vn (ACI notified ISE it received SDA extend vn)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61152 ACI notified ISE it received SDA extend vn TrustSec ACI notified ISE it received SDA extend vn, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61152 ACI notified ISE it received SDA extend vn TrustSec ACI notified ISE it received SDA extend vn, <log details>

- 消息代码: 61153

严重性: SDA 未成功响应 ACI 消息

消息文本: SDA 未成功响应 ACI 消息 (SDA did not respond successfully to ACI message)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61153 SDA did not respond successfully to ACI message TrustSec SDA did not respond successfully to ACI message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61153 SDA did not respond successfully to ACI message TrustSec SDA did not respond successfully to ACI message, <log details>

- 消息代码: 61154

严重性: ISE 成功响应对等状态检索

消息文本: ISE 成功响应对等状态检索 (ISE successfully respond to peering status retrieval)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61154 ISE successfully respond to peering status retrieval TrustSec ISE successfully respond to peering status retrieval, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61154 ISE successfully respond to peering status retrieval TrustSec ISE successfully respond to peering status retrieval, <log details>

- 消息代码: 61156

严重性: SDA 将 SXP 配置发布到 ISE

消息文本: SDA 将 SXP 配置发布到 ISE (SDA published SXP configuration to ISE)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61156 SDA published SXP configuration to ISE TrustSec SDA published SXP configuration to ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61156 SDA published SXP configuration to ISE TrustSec SDA published SXP configuration to ISE, <log details>

- 消息代码: 61157

严重性: ISE 成功接收了 SDA SXP 配置

消息文本: ISE 成功接收了 SDA SXP 配置 (SDA SXP configuration successfully received by ISE)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61157 SDA SXP configuration successfully received by ISE TrustSec SDA SXP configuration successfully received by ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61157 SDA SXP configuration successfully received by ISE TrustSec SDA SXP configuration successfully received by ISE, <log details>

- 消息代码: 61158

严重性: ISE 接收 SDA SXP 配置失败

消息文本: ISE 接收 SDA SXP 配置失败 (ISE failed in receiving SDA SXP configuration)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61158 ISE failed in receiving SDA SXP configuration TrustSec ISE failed in receiving SDA SXP configuration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61158 ISE failed in receiving SDA SXP configuration TrustSec ISE failed in receiving SDA SXP configuration, <log details>

- 消息代码: 61159

严重性: ISE 向 ACI 发布网关广告消息

消息文本: ISE 向 ACI 发布网关广告消息 (ISE publishing Gateway advertisement message to ACI)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61159 ISE publishing Gateway advertisement message to ACI TrustSec ISE publishing Gateway advertisement message to ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61159 ISE publishing Gateway advertisement message to ACI TrustSec ISE publishing Gateway advertisement message to ACI, <log details>

- 消息代码: 61160
 - 严重性: ISE 未能向 ACI 发布网关广告消息
 - 消息文本: ISE 未能向 ACI 发布网关广告消息 (ISE failed to publish Gateway advertisement message to ACI)
 - 消息说明: 错误 (ERROR)
 - 本地目标消息格式: <timestamp> <seq_num>61160 ISE failed to publish Gateway advertisement message to ACI TrustSec ISE failed to publish Gateway advertisement message to ACI, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61160 ISE failed to publish Gateway advertisement message to ACI TrustSec ISE failed to publish Gateway advertisement message to ACI, <log details>

- 消息代码: 61161
 - 严重性: ISE 获知新的 SXP 侦听程序
 - 消息文本: ISE 获知新的 SXP 侦听程序 (ISE learned new SXP Listener)
 - 消息说明: 信息 (INFO)
 - 本地目标消息格式: <timestamp> <seq_num>61161 ISE learned new SXP Listener TrustSec ISE learned new SXP Listener, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61161 ISE learned new SXP Listener TrustSec ISE learned new SXP Listener, <log details>

- 消息代码: 61162
 - 严重性: ISE 更新为 SXP 侦听程序定义的 VN
 - 消息文本: ISE 更新为 SXP 侦听程序定义的 VN (ISE updates VN defined for SXP Listener)
 - 消息说明: 信息 (INFO)
 - 本地目标消息格式: <timestamp> <seq_num>61162 ISE updates VN defined for SXP Listener TrustSec ISE updates VN defined for SXP Listener, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61162 ISE updates VN defined for SXP Listener TrustSec ISE updates VN defined for SXP Listener, <log details>

- 消息代码: 61163
 - 严重性: ISE 获知为 SXP 侦听程序定义的新 VN
 - 消息文本: ISE 获知为 SXP 侦听程序定义的新 VN (ISE learned new VN defined for SXP Listener)
 - 消息说明: 信息 (INFO)
 - 本地目标消息格式: <timestamp> <seq_num>61163 ISE learned new VN defined for SXP Listener TrustSec ISE learned new VN defined for SXP Listener, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61163 ISE learned new VN defined for SXP
Listener TrustSec ISE learned new VN defined for SXP Listener, <log details>

- 消息代码: 61164

严重性: ISE 更新 SXP 侦听程序

消息文本: ISE 更新 SXP 侦听程序 (ISE updates SXP Listener)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61164 ISE updates SXP Listener TrustSec ISE updates
SXP Listener, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61164 ISE updates SXP Listener TrustSec
ISE updates SXP Listener, <log details>

- 消息代码: 61165

严重性: ISE 删除了与 SXP 侦听程序相关的所有 SXP 连接

消息文本: ISE 删除了与 SXP 侦听程序相关的所有 SXP 连接 (ISE removed all SXP connections
related to SXP Listener)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61165 ISE removed all SXP connections related to SXP
Listener TrustSec ISE removed all SXP connections related to SXP Listener, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61165 ISE removed all SXP connections
related to SXP Listener TrustSec ISE removed all SXP connections related to SXP Listener, <log details>

- 消息代码: 61166

严重性: ACI 向 SDA 发布了网关广告消息

消息文本: ACI 向 SDA 发布了网关广告消息 (ACI published Gateway advertisement message to
SDA)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61166 ACI published Gateway advertisement message
to SDA TrustSec ACI published Gateway advertisement message to SDA, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61166 ACI published Gateway advertisement
message to SDA TrustSec ACI published Gateway advertisement message to SDA, <log details>

- 消息代码: 61167

严重性: 向 ISE 发送 ACI 网关广告消息

消息文本: 向 ISE 发送 ACI 网关广告消息 (Send ACI Gateway advertisement message to ISE)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61167 Send ACI Gateway advertisement message to ISE TrustSec Send ACI Gateway advertisement message to ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61167 Send ACI Gateway advertisement message to ISE TrustSec Send ACI Gateway advertisement message to ISE, <log details>

- 消息代码: 61168

严重性: 未能向 ISE 发送 ACI 网关广告消息

消息文本: 未能向 ISE/SDA 发送 ACI 网关广告消息 (Failed to send ACI Gateway advertisement message to ISE/SDA)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61168 Failed to send ACI Gateway advertisement message to ISE TrustSec Failed to send ACI Gateway advertisement message to ISE/SDA, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61168 Failed to send ACI Gateway advertisement message to ISE TrustSec Failed to send ACI Gateway advertisement message to ISE/SDA, <log details>

- 消息代码: 61169

严重性: 成功发送 ACI 网关广告消息

消息文本: 成功发送 ACI 网关广告消息 (Successfully Send ACI Gateway advertisement message)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61169 Successfully Send ACI Gateway advertisement message TrustSec Successfully Send ACI Gateway advertisement message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61169 Successfully Send ACI Gateway advertisement message TrustSec Successfully Send ACI Gateway advertisement message, <log details>

- 消息代码: 61170

严重性: SDA 向 ACI 发布了对等域请求

消息文本: SDA 向 ACI 发布了对等域请求 (SDA published peer domain request to ACI)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61170 SDA published peer domain request to ACI TrustSec SDA published peer domain request to ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61170 SDA published peer domain request to ACI TrustSec SDA published peer domain request to ACI, <log details>

- 消息代码: 61171

严重性: SDA 未能向 ACI 发布对等域请求

消息文本: SDA 未能向 ACI 发布对等域请求 (SDA failed to publish peer domain request to ACI)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61171 SDA failed to publish peer domain request to ACI TrustSec SDA failed to publish peer domain request to ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61171 SDA failed to publish peer domain request to ACI TrustSec SDA failed to publish peer domain request to ACI, <log details>

- 消息代码: 61172

严重性: SDA 向 ACI 发布了对等域响应

消息文本: SDA 向 ACI 发布了对等域响应 (SDA published peer domain response to ACI)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61172 SDA published peer domain response to ACI TrustSec SDA published peer domain response to ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61172 SDA published peer domain response to ACI TrustSec SDA published peer domain response to ACI, <log details>

- 消息代码: 61173

严重性: SDA 未能向 ACI 发布对等域响应

消息文本: SDA 未能向 ACI 发布对等域响应 (SDA failed to publish peer domain response to ACI)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61173 SDA failed to publish peer domain response to ACI TrustSec SDA failed to publish peer domain response to ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61173 SDA failed to publish peer domain response to ACI TrustSec SDA failed to publish peer domain response to ACI, <log details>

- 消息代码: 61174

严重性: 处理对等域请求

消息文本: 处理对等域请求 (Process peer domain request)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61174 Process peer domain request TrustSec Process peer domain request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61174 Process peer domain request TrustSec Process peer domain request, <log details>

- 消息代码: 61175
 - 严重性: 处理对等域响应
 - 消息文本: 处理对等域响应 (Process peer domain response)
 - 消息说明: 信息 (INFO)
 - 本地目标消息格式: <timestamp> <seq_num>61175 Process peer domain response TrustSec Process peer domain response, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61175 Process peer domain response TrustSec Process peer domain response, <log details>

- 消息代码: 61176
 - 严重性: SDA 启动与 ACI 的对等进程
 - 消息文本: SDA 启动与 ACI 的对等进程 (SDA initiate peering process with ACI)
 - 消息说明: 信息 (INFO)
 - 本地目标消息格式: <timestamp> <seq_num>61176 SDA initiate peering process with ACI TrustSec SDA initiate peering process with ACI, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61176 SDA initiate peering process with ACI TrustSec SDA initiate peering process with ACI, <log details>

- 消息代码: 61177
 - 严重性: ACI 启动与 SDA 的对等进程
 - 消息文本: ACI 启动与 SDA 的对等进程 (ACI initiate peering process with SDA)
 - 消息说明: 信息 (INFO)
 - 本地目标消息格式: <timestamp> <seq_num>61177 ACI initiate peering process with SDA TrustSec ACI initiate peering process with SDA, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61177 ACI initiate peering process with SDA TrustSec ACI initiate peering process with SDA, <log details>

- 消息代码: 61178
 - 严重性: 对等已存在
 - 消息文本: 对等已存在 (Peering already exist)
 - 消息说明: 错误 (ERROR)
 - 本地目标消息格式: <timestamp> <seq_num>61178 Peering already exist TrustSec Peering already exist, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61178 Peering already exist TrustSec Peering
already exist, <log details>

- 消息代码: 61179

严重性: 对等进程失败, ACI 域不存在

消息文本: 对等进程失败, ACI 域不存在 (Peering process failed ACI Domain does not exist)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61179 Peering process failed ACI Domain does not exist
TrustSec Peering process failed ACI Domain does not exist, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61179 Peering process failed ACI Domain
does not exist TrustSec Peering process failed ACI Domain does not exist, <log details>

- 消息代码: 61180

严重性: 对等进程失败, SDA 域不存在

消息文本: 对等进程失败, SDA 域不存在 (Peering process failed SDA Domain does not exist)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61180 Peering process failed SDA Domain does not
exist TrustSec Peering process failed SDA Domain does not exist, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61180 Peering process failed SDA Domain
does not exist TrustSec Peering process failed SDA Domain does not exist, <log details>

- 消息代码: 61181

严重性: 在 SDA 和 ACI 之间建立了对等关系

消息文本: 在 SDA 和 ACI 之间建立了对等关系 (Peering established between SDA and ACI)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61181 Peering established between SDA and ACI
TrustSec Peering established between SDA and ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61181 Peering established between SDA and
ACI TrustSec Peering established between SDA and ACI, <log details>

- 消息代码: 61182

严重性: SDA-ACI 对等进程失败

消息文本: SDA-ACI 对等进程失败 (SDA-ACI Peering process failed)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61182 SDA-ACI Peering process failed TrustSec SDA-ACI Peering process failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61182 SDA-ACI Peering process failed TrustSec SDA-ACI Peering process failed, <log details>

- 消息代码: 61183

严重性: 从 ACI 收到了对等域请求

消息文本: 从 ACI 收到了对等域请求 (Received peer domain request from ACI)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61183 Received peer domain request from ACI TrustSec Received peer domain request from ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61183 Received peer domain request from ACI TrustSec Received peer domain request from ACI, <log details>

- 消息代码: 61184

严重性: 未能从 ACI 收到对等域请求

消息文本: 未能从 ACI 收到对等域请求 (Failed to receive peer domain request from ACI)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61184 Failed to receive peer domain request from ACI TrustSec Failed to receive peer domain request from ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61184 Failed to receive peer domain request from ACI TrustSec Failed to receive peer domain request from ACI, <log details>

- 消息代码: 61185

严重性: 从 ACI 向 SDA 发布对等域请求

消息文本: 从 ACI 向 SDA 发布对等域请求 (Publish peer domain request to SDA from ACI)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61185 Publish peer domain request to SDA from ACI TrustSec Publish peer domain request to SDA from ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61185 Publish peer domain request to SDA from ACI TrustSec Publish peer domain request to SDA from ACI, <log details>

- 消息代码: 61186

严重性: 未能从 ACI 向 SDA 发布对等域请求

消息文本: 未能从 ACI 向 SDA 发布对等域请求 (Failed to publish peer domain request to SDA from ACI)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61186 Failed to publish peer domain request to SDA from ACI TrustSec Failed to publish peer domain request to SDA from ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61186 Failed to publish peer domain request to SDA from ACI TrustSec Failed to publish peer domain request to SDA from ACI, <log details>

- 消息代码: 61187

严重性: ACI 和 SDA 之间的对等状态已创建

消息文本: ACI 和 SDA 之间的对等状态已创建 (Peering status between ACI and SDA is created)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61187 Peering status between ACI and SDA is created TrustSec Peering status between ACI and SDA is created, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61187 Peering status between ACI and SDA is created TrustSec Peering status between ACI and SDA is created, <log details>

- 消息代码: 61188

严重性: ACI 和 SDA 之间的对等状态已删除

消息文本: ACI 和 SDA 之间的对等状态已删除 (Peering status between ACI and SDA is removed)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61188 Peering status between ACI and SDA is removed TrustSec Peering status between ACI and SDA is removed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61188 Peering status between ACI and SDA is removed TrustSec Peering status between ACI and SDA is removed, <log details>

- 消息代码: 61189

严重性: 正在将消费者发布到 ACI

消息文本: 正在将消费者发布到 ACI (Publishing consumer to ACI)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61189 Publishing consumer to ACI TrustSec Publishing consumer to ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61189 Publishing consumer to ACI TrustSec Publishing consumer to ACI, <log details>

- 消息代码: 61190
 - 严重性: 未能将消费者发布到 ACI
 - 消息文本: 未能将消费者发布到 ACI (Failed to publish consumer to ACI)
 - 消息说明: 错误 (ERROR)
 - 本地目标消息格式: <timestamp> <seq_num>61190 Failed to publish consumer to ACI TrustSec Failed to publish consumer to ACI, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61190 Failed to publish consumer to ACI TrustSec Failed to publish consumer to ACI, <log details>

- 消息代码: 61191
 - 严重性: 正在将消费者服务请求发布到 ACI
 - 消息文本: 正在将消费者服务请求发布到 ACI (Publishing consumer service request to ACI)
 - 消息说明: 信息 (INFO)
 - 本地目标消息格式: <timestamp> <seq_num>61191 Publishing consumer service request to ACI TrustSec Publishing consumer service request to ACI, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61191 Publishing consumer service request to ACI TrustSec Publishing consumer service request to ACI, <log details>

- 消息代码: 61192
 - 严重性: 未能将消费者服务请求发布到 ACI
 - 消息文本: 未能将消费者服务请求发布到 ACI (Failed to publish consumer service request to ACI)
 - 消息说明: 错误 (ERROR)
 - 本地目标消息格式: <timestamp> <seq_num>61192 Failed to publish consumer service request to ACI TrustSec Failed to publish consumer service request to ACI, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61192 Failed to publish consumer service request to ACI TrustSec Failed to publish consumer service request to ACI, <log details>

- 消息代码: 61193
 - 严重性: 正在从 ISE 删除消费者服务
 - 消息文本: 正在从 ISE 删除消费者服务 (Deleting consumer service from ISE)
 - 消息说明: 信息 (INFO)
 - 本地目标消息格式: <timestamp> <seq_num>61193 Deleting consumer service from ISE TrustSec Deleting consumer service from ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61193 Deleting consumer service from ISE
TrustSec Deleting consumer service from ISE, <log details>

- 消息代码: 61194

严重性: 未能从 ISE 删除消费者服务

消息文本: 未能从 ISE 删除消费者服务 (Failed to delete consumer service from ISE)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61194 Failed to delete consumer service from ISE
TrustSec Failed to delete consumer service from ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61194 Failed to delete consumer service from
ISE TrustSec Failed to delete consumer service from ISE, <log details>

- 消息代码: 61195

严重性: ISE 从 ACI 获知了新 SGACL

消息文本: ISE 从 ACI 获知了新 SGACL (ISE learned new SGACL from ACI)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61195 ISE learned new SGACL from ACI TrustSec ISE
learned new SGACL from ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61195 ISE learned new SGACL from ACI
TrustSec ISE learned new SGACL from ACI, <log details>

- 消息代码: 61196

严重性: 未能从 ACI 获知新 SGACL

消息文本: 未能从 ACI 获知新 SGACL (Failed to learn new SGACL from ACI)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61196 Failed to learn new SGACL from ACI TrustSec
Failed to learn new SGACL from ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61196 Failed to learn new SGACL from ACI
TrustSec Failed to learn new SGACL from ACI, <log details>

- 消息代码: 61197

严重性: 已成功更新从 ACI 获知的 SGACL

消息文本: 已成功更新从 ACI 获知的 SGACL (Successfully updated SGACL which learned from
ACI)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61197 Successfully updated SGACL which learned from ACI TrustSec Successfully updated SGACL which learned from ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61197 Successfully updated SGACL which learned from ACI TrustSec Successfully updated SGACL which learned from ACI, <log details>

- 消息代码: 61198

严重性: 未能更新从 ACI 获知的 SGACL

消息文本: 未能更新从 ACI 获知的 SGACL (Failed to update SGACL which learned from ACI)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61198 Failed to update SGACL which learned from ACI TrustSec Failed to update SGACL which learned from ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61198 Failed to update SGACL which learned from ACI TrustSec Failed to update SGACL which learned from ACI, <log details>

- 消息代码: 61199

严重性: ACI 的 SGACL 已从 ISE 中删除

消息文本: ACI 的 SGACL 已从 ISE 中删除 (ACI, 's SGACL was deleted from ISE)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61199 ACI, 's SGACL was deleted from ISE TrustSec ACI, 's SGACL was deleted from ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61199 ACI, 's SGACL was deleted from ISE TrustSec ACI, 's SGACL was deleted from ISE, <log details>

- 消息代码: 61200

严重性: 未能从 ISE 中删除 ACI 的 SGACL

消息文本: 未能从 ISE 中删除 ACI 的 SGACL (Failed to delete ACI, 's SGACL from ISE)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61200 Failed to delete ACI, 's SGACL from ISE TrustSec Failed to delete ACI, 's SGACL from ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61200 Failed to delete ACI, 's SGACL from ISE TrustSec Failed to delete ACI, 's SGACL from ISE, <log details>

- 消息代码: 61201

严重性: ISE 中已存储 ACI 服务

消息文本: ISE 中已存储 ACI 服务 (Stored ACI Service in ISE)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61201 Stored ACI Service in ISE TrustSec Stored ACI Service in ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>61201 Stored ACI Service in ISE TrustSec Stored ACI Service in ISE, <log details>

- 消息代码: 61202

严重性: 未能在 ISE 中存储 ACI 服务

消息文本: 未能在 ISE 中存储 ACI 服务 (Failed to store ACI Service in ISE)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61202 Failed to store ACI Service in ISE TrustSec Failed to store ACI Service in ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>61202 Failed to store ACI Service in ISE TrustSec Failed to store ACI Service in ISE, <log details>

- 消息代码: 61203

严重性: 已更新 ISE 中的 ACI 服务

消息文本: 已更新 ISE 中的 ACI 服务 (Updated ACI Service in ISE)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61203 Updated ACI Service in ISE TrustSec Updated ACI Service in ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>61203 Updated ACI Service in ISE TrustSec Updated ACI Service in ISE, <log details>

- 消息代码: 61204

严重性: 未能更新 ISE 中的 ACI 服务

消息文本: 未能更新 ISE 中的 ACI 服务 (Failed to update ACI Service in ISE)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61204 Failed to update ACI Service in ISE TrustSec Failed to update ACI Service in ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>61204 Failed to update ACI Service in ISE TrustSec Failed to update ACI Service in ISE, <log details>

- 消息代码: 61205

严重性: 已删除 ISE 中的 ACI 服务

消息文本: 已删除 ISE 中的 ACI 服务 (Deleted ACI Service in ISE)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61205 Deleted ACI Service in ISE TrustSec Deleted ACI Service in ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61205 Deleted ACI Service in ISE TrustSec Deleted ACI Service in ISE, <log details>

- 消息代码: 61206

严重性: 未能删除 ISE 中的 ACI 服务

消息文本: 未能删除 ISE 中的 ACI 服务 (Failed to delete ACI Service in ISE)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61206 Failed to delete ACI Service in ISE TrustSec Failed to delete ACI Service in ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61206 Failed to delete ACI Service in ISE TrustSec Failed to delete ACI Service in ISE, <log details>

- 消息代码: 61207

严重性: mdpConsumerServiceRequest 已发布到 ACI

消息文本: mdpConsumerServiceRequest 已发布到 ACI (Published mdpConsumerServiceRequest to ACI)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61207 Published mdpConsumerServiceRequest to ACI TrustSec Published mdpConsumerServiceRequest to ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61207 Published mdpConsumerServiceRequest to ACI TrustSec Published mdpConsumerServiceRequest to ACI, <log details>

- 消息代码: 61208

严重性: 未能将 mdpConsumerServiceRequest 发布到 ACI

消息文本: 未能将 mdpConsumerServiceRequest 发布到 ACI (Failed to publish mdpConsumerServiceRequest to ACI)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61208 Failed to publish mdpConsumerServiceRequest to ACI TrustSec Failed to publish mdpConsumerServiceRequest to ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61208 Failed to publish

mdpConsumerServiceRequest to ACI TrustSec Failed to publish mdpConsumerServiceRequest to ACI, <log details>

- 消息代码: 61209

严重性: ISE 已将新的 EEPG 传播到 ACI

消息文本: ISE 已将新的 EEPG 传播到 ACI (ISE has propagated a new EEPG to ACI)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61209 ISE has propagated a new EEPG to ACI TrustSec ISE has propagated a new EEPG to ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61209 ISE has propagated a new EEPG to ACI TrustSec ISE has propagated a new EEPG to ACI, <log details>

- 消息代码: 61210

严重性: ISE 未能将新的 EEPG 传播到 ACI

消息文本: ISE 未能将新的 EEPG 传播到 ACI (ISE has failed to propagate a new EEPG to ACI)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61210 ISE has failed to propagate a new EEPG to ACI TrustSec ISE has failed to propagate a new EEPG to ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61210 ISE has failed to propagate a new EEPG to ACI TrustSec ISE has failed to propagate a new EEPG to ACI, <log details>

- 消息代码: 61211

严重性: 从 ISE 收到了终端消息

消息文本: 从 ISE 收到了终端消息 (Received Endpoint message from ISE)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61211 Received Endpoint message from ISE TrustSec Received Endpoint message from ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61211 Received Endpoint message from ISE TrustSec Received Endpoint message from ISE, <log details>

- 消息代码: 61212

严重性: 终端已发布到 ACI

消息文本: 终端已发布到 ACI (Published Endpoint to ACI)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61212 Published Endpoint to ACI TrustSec Published Endpoint to ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61212 Published Endpoint to ACI TrustSec
Published Endpoint to ACI, <log details>

- 消息代码: 61213

严重性: 未能将终端发布到 ACI

消息文本: 未能将终端发布到 ACI (Failed to publish Endpoint to ACI)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61213 Failed to publish Endpoint to ACI TrustSec Failed
to publish Endpoint to ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61213 Failed to publish Endpoint to ACI
TrustSec Failed to publish Endpoint to ACI, <log details>

- 消息代码: 61214

严重性: 正将终端添加发布到 SDA

消息文本: 正将终端添加发布到 SDA (Publishing endpoints addition to SDA)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61214 Publishing endpoints addition to SDA TrustSec
Publishing endpoints addition to SDA, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61214 Publishing endpoints addition to SDA
TrustSec Publishing endpoints addition to SDA, <log details>

- 消息代码: 61215

严重性: 正将终端删除发布到 SDA

消息文本: 正将终端删除发布到 SDA (Publishing endpoints deletion to SDA)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61215 Publishing endpoints deletion to SDA TrustSec
Publishing endpoints deletion to SDA, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61215 Publishing endpoints deletion to SDA
TrustSec Publishing endpoints deletion to SDA, <log details>

- 消息代码: 61216

严重性: 未能将 ACI 绑定发布到 SDA

消息文本: 未能将 ACI 绑定发布到 SDA (Failed to publish ACI binding to SDA)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61216 Failed to publish ACI binding to SDA TrustSec Failed to publish ACI binding to SDA, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61216 Failed to publish ACI binding to SDA TrustSec Failed to publish ACI binding to SDA, <log details>

- 消息代码: 61217

严重性: 未能将消息发布到 SXP

消息文本: 未能将消息发布到 SXP (Failed to publish message to SXP)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61217 Failed to publish message to SXP TrustSec Failed to publish message to SXP, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61217 Failed to publish message to SXP TrustSec Failed to publish message to SXP, <log details>

- 消息代码: 61218

严重性: ACI 绑定已发布到 SXP

消息文本: ACI 绑定已发布到 SXP (Published ACI binding to SXP)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61218 Published ACI binding to SXP TrustSec Published ACI binding to SXP, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61218 Published ACI binding to SXP TrustSec Published ACI binding to SXP, <log details>

- 消息代码: 61219

严重性: 未能将 ACI 绑定发布到 SXP

消息文本: 未能将 ACI 绑定发布到 SXP (Failed to publish ACI binding to SXP)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61219 Failed to publish ACI binding to SXP TrustSec Failed to publish ACI binding to SXP, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61219 Failed to publish ACI binding to SXP TrustSec Failed to publish ACI binding to SXP, <log details>

- 消息代码: 61220

严重性: sxp 绑定已从 SXP 发布到 ISE

消息文本: sxp 绑定已从 SXP 发布到 ISE (Published sxp binding from SXP to ISE)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61220 Published sxp binding from SXP to ISE TrustSec
Published sxp binding from SXP to ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61220 Published sxp binding from SXP to
ISE TrustSec Published sxp binding from SXP to ISE, <log details>

- 消息代码: 61221

严重性: sxp 绑定未能从 SXP 发布到 ISE

消息文本: sxp 绑定未能从 SXP 发布到 ISE (Failed to publish sxp binding from SXP to ISE)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61221 Failed to publish sxp binding from SXP to ISE
TrustSec Failed to publish sxp binding from SXP to ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61221 Failed to publish sxp binding from
SXP to ISE TrustSec Failed to publish sxp binding from SXP to ISE, <log details>

- 消息代码: 61222

严重性: 从 ISE 收到了 EndPointGroup 消息

消息文本: 从 ISE 收到了 EndPointGroup 消息 (Received EndPointGroup message from ACI)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61222 Received EndPointGroup message from ACI
TrustSec Received EndPointGroup message from ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61222 Received EndPointGroup message
from ACI TrustSec Received EndPointGroup message from ACI, <log details>

- 消息代码: 61223

严重性: 未能在 ISE 中存储新的 SGT

消息文本: 未能在 ISE 中存储新的 SGT (Failed to store new SGT in ISE)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61223 Failed to store new SGT in ISE TrustSec Failed
to store new SGT in ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61223 Failed to store new SGT in ISE TrustSec
Failed to store new SGT in ISE, <log details>

- 消息代码: 61224

严重性: 从 SDA 收到了 EndPointGroup 消息

消息文本: 从 SDA 收到了 EndPointGroup 消息 (Received EndPointGroup message from SDA)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61224 Received EndPointGroup message from SDA TrustSec Received EndPointGroup message from SDA, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>61224 Received EndPointGroup message from SDA TrustSec Received EndPointGroup message from SDA, <log details>

- 消息代码: 61225

严重性: SGT 已发布到 ACI

消息文本: SGT 已发布到 ACI (SGT is already published to ACI)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61225 SGT is already published to ACI TrustSec SGT is already published to ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>61225 SGT is already published to ACI TrustSec SGT is already published to ACI, <log details>

- 消息代码: 61226

严重性: SGT 已发布到 ACI

消息文本: SGT 已发布到 ACI (Published SGT to ACI)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61226 Published SGT to ACI TrustSec Published SGT to ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>61226 Published SGT to ACI TrustSec Published SGT to ACI, <log details>

- 消息代码: 61227

严重性: SGT 未能发布到 ACI

消息文本: SGT 未能发布到 ACI (Failed publishing SGT to ACI)

消息说明: 错误 (ERROR)

本地目标消息格式: <timestamp> <seq_num>61227 Failed publishing SGT to ACI TrustSec Failed publishing SGT to ACI, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>61227 Failed publishing SGT to ACI TrustSec Failed publishing SGT to ACI, <log details>

- 消息代码: 61228

严重性: ISE 已根据获知的 IEPG 创建新的 SGT

消息文本: ISE 已根据获知的 IEPG 创建新的 SGT (ISE has created a new SGT based on learned IEPG)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61228 ISE has created a new SGT based on learned IEPG TrustSec ISE has created a new SGT based on learned IEPG, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61228 ISE has created a new SGT based on learned IEPG TrustSec ISE has created a new SGT based on learned IEPG, <log details>

- 消息代码: 61229

严重性: ISE 已根据获知的 IEPG 更新 SGT

消息文本: ISE 已根据获知的 IEPG 更新 SGT (ISE has updated a SGT based on learned IEPG)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61229 ISE has updated a SGT based on learned IEPG TrustSec ISE has updated a SGT based on learned IEPG, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61229 ISE has updated a SGT based on learned IEPG TrustSec ISE has updated a SGT based on learned IEPG, <log details>

- 消息代码: 61230

严重性: ISE 已根据删除的 IEPG 删除 SGT

消息文本: ISE 已根据删除的 IEPG 删除 SGT (ISE has removed a SGT based on deleted IEPG)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61230 ISE has removed a SGT based on deleted IEPG TrustSec ISE has removed a SGT based on deleted IEPG, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>61230 ISE has removed a SGT based on deleted IEPG TrustSec ISE has removed a SGT based on deleted IEPG, <log details>

- 消息代码: 61231

严重性: 接收消息时 Kafka 与 ACI 的连接出错

消息文本: 接收消息时 Kafka 与 ACI 的连接出错 (Kafka connection to ACI error while receiving message)

消息说明: 警告 (WARN)

本地目标消息格式: <timestamp> <seq_num>61231 Kafka connection to ACI error while receiving message TrustSec Kafka connection to ACI error while receiving message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61231 Kafka connection to ACI error while
receiving message TrustSec Kafka connection to ACI error while receiving message, <log details>

- 消息代码: 61232

严重性: 发送消息时 Kafka 与 ACI 的连接出错

消息文本: 发送消息时 Kafka 与 ACI 的连接出错 (Kafka connection to ACI error while sending
message)

消息说明: 警告 (WARN)

本地目标消息格式: <timestamp> <seq_num>61232 Kafka connection to ACI error while sending
message TrustSec Kafka connection to ACI error while sending message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61232 Kafka connection to ACI error while
sending message TrustSec Kafka connection to ACI error while sending message, <log details>

- 消息代码: 61233

严重性: ACI 消息处理失败

消息文本: ACI 消息处理失败 (Handling ACI message failure)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>61233 Handling ACI message failure TrustSec Handling
ACI message failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61233 Handling ACI message failure TrustSec
Handling ACI message failure, <log details>

- 消息代码: 61234

严重性: 收到有未知属性的事件

消息文本: 收到有未知属性的事件 (Got event with unknown properties)

消息说明: 警告 (WARN)

本地目标消息格式: <timestamp> <seq_num>61234 Got event with unknown properties TrustSec Got
event with unknown properties, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>61234 Got event with unknown properties
TrustSec Got event with unknown properties, <log details>

- 消息代码: 62000

严重性: 无代理脚本执行完成

消息文本: 无代理脚本执行完成 (Agentless script execute completed)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>62000 Agentless script execute completed
AgentlessPosture Agentless script execute completed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>62000 Agentless script execute completed
AgentlessPosture Agentless script execute completed, <log details>

- 消息代码: 62001

严重性: 无代理脚本执行失败

消息文本: 无代理脚本执行失败 (Agentless script execute failed)

消息说明: 警告 (WARN)

本地目标消息格式: <timestamp> <seq_num>62001 Agentless script execute failed AgentlessPosture
Agentless script execute failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>62001 Agentless script execute failed
AgentlessPosture Agentless script execute failed, <log details>

- 消息代码: 62002

严重性: 无代理脚本上传完成

消息文本: 无代理脚本上传完成 (Agentless script upload completed)

消息说明: 信息 (INFO)

本地目标消息格式: <timestamp> <seq_num>62002 Agentless script upload completed AgentlessPosture
Agentless script upload completed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>62002 Agentless script upload completed
AgentlessPosture Agentless script upload completed, <log details>

- 消息代码: 62003

严重性: 无代理脚本上传失败

消息文本: 无代理脚本上传失败 (Agentless script upload failed)

消息说明: 警告 (WARN)

本地目标消息格式: <timestamp> <seq_num>62003 Agentless script upload failed AgentlessPosture
Agentless script upload failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>62003 Agentless script upload failed
AgentlessPosture Agentless script upload failed, <log details>

管理员身份验证和授权

- 消息代码: 10000
 - 严重性: 调试 (DEBUG)
 - 消息文本: 已收到管理员身份验证请求 (Received Administrator authentication request)
 - 消息说明: 正在处理传入的管理员身份验证请求
 - 本地目标消息格式: <timestamp> <seq_num> 10000 DEBUG AAC: Received Administrator authentication request, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 10000 DEBUG AAC: Received Administrator authentication request, <log details>

- 消息代码: 10001
 - 严重性: 错误 (ERROR)
 - 消息文本: 内部错误。配置版本不正确 (Internal error. Incorrect configuration version)
 - 消息说明: 发生内部错误: 未确定配置版本
 - 本地目标消息格式: <timestamp> <seq_num> 10001 ERROR AAC: Internal error. Incorrect configuration version, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 10001 ERROR AAC: Internal error. Incorrect configuration version, <log details>

- 消息代码: 10002
 - 严重性: 错误 (ERROR)
 - 消息文本: 内部错误: 无法加载合适的服务 (Internal error: Failure to load appropriate service)
 - 消息说明: 内部错误: 无法加载 AAC 服务
 - 本地目标消息格式: <timestamp> <seq_num> 10002 ERROR AAC: Internal error: Failure to load appropriate service, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 10002 ERROR AAC: Internal error: Failure to load appropriate service, <log details>

- 消息代码: 10003
 - 严重性: 错误 (ERROR)
 - 消息文本: 内部错误: 管理员身份验证收到空白的管理员名称 (Internal error: Administrator authentication received blank Administrator name)
 - 消息说明: 内部错误: 在 AAC RT 组件收到的管理员身份验证请求中, 管理员名称为空白

本地目标消息格式: <timestamp> <seq_num> 10003 ERROR AAC: Internal error: Administrator authentication received blank Administrator name, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 10003 ERROR AAC: Internal error: Administrator authentication received blank Administrator name, <log details>

- 消息代码: 10004

严重性: 错误 (ERROR)

消息文本: 内部错误: 管理员身份验证收到空白的管理员密码 (Internal error: Administrator authentication received blank Administrator password)

消息说明: 内部错误: 在 AAC RT 组件收到的管理员身份验证请求中, 管理员密码为空白

本地目标消息格式: <timestamp> <seq_num> 10004 ERROR AAC: Internal error: Administrator authentication received blank Administrator password, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 10004 ERROR AAC: Internal error: Administrator authentication received blank Administrator password, <log details>

- 消息代码: 10005

严重性: 信息 (INFO)

消息文本: 管理员身份验证成功 (Administrator authenticated successfully)

消息说明: 管理员身份验证成功

本地目标消息格式: <timestamp> <seq_num> 10005 INFO AAC: Administrator authenticated successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 10005 INFO AAC: Administrator authenticated successfully, <log details>

- 消息代码: 10006

严重性: 信息 (INFO)

消息文本: 管理员身份验证失败 (Administrator authentication failed)

消息说明: 管理员身份验证失败

本地目标消息格式: <timestamp> <seq_num> 10006 INFO AAC: Administrator authentication failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 10006 INFO AAC: Administrator authentication failed, <log details>

- 消息代码: 10007

严重性: 错误 (ERROR)

消息文本: 管理员身份验证失败 - 数据库错误 (Administrator authentication failed - DB Error)

消息说明: 管理员身份验证失败 - 数据库错误

本地目标消息格式: <timestamp> <seq_num> 10007 ERROR AAC: Administrator authentication failed - DB Error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 10007 ERROR AAC: Administrator authentication failed - DB Error, <log details>

- 消息代码: 10008

严重性: 调试 (DEBUG)

消息文本: 已接收有效的管理员身份验证请求 (Received valid Administrator authentication request)

消息说明: 已接收有效的管理员身份验证请求

本地目标消息格式: <timestamp> <seq_num> 10008 DEBUG AAC: Received valid Administrator authentication request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 10008 DEBUG AAC: Received valid Administrator authentication request, <log details>

- 消息代码: 10009

严重性: 调试 (DEBUG)

消息文本: 已接收管理员身份验证请求 (Received Administrator authentication request)

消息说明: 已成功执行服务选择

本地目标消息格式: <timestamp> <seq_num> 10009 DEBUG AAC: Received Administrator authentication request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 10009 DEBUG AAC: Received Administrator authentication request, <log details>

- 消息代码: 10010

严重性: 信息 (INFO)

消息文本: 管理员密码更改提醒 (Admin password change reminder)

消息说明: 提醒 - 请更改管理员密码

本地目标消息格式: <timestamp> <seq_num> 10010 INFO AAC: Admin password change reminder, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 10010 INFO AAC: Admin password change reminder, <log details>

- 消息代码: 10011

严重性: 信息 (INFO)

消息文本: 管理员密码已到期, 因此需要更改密码 (Admin password change required due to expired password)

消息说明: 管理员密码已到期 - 请更改密码。

本地目标消息格式: <timestamp> <seq_num> 10011 INFO AAC: Admin password change required due to expired password, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 10011 INFO AAC: Admin password change required due to expired password, <log details>

- 消息代码: 10012

严重性: 信息 (INFO)

消息文本: 由于帐户处于非活动状态, 因此需要更改管理员密码 (Admin password change required due to account inactivity)

消息说明: 由于管理员帐户处于非活动状态, 因此必须更改管理员密码。

本地目标消息格式: <timestamp> <seq_num> 10012 INFO AAC: Admin password change required due to account inactivity, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 10012 INFO AAC: Admin password change required due to account inactivity, <log details>

- 消息代码: 10013

严重性: 信息 (INFO)

消息文本: 管理员帐户设置为“从不禁用” (never disabled) (Admin account set as 'never disabled')

消息说明: 由于已设置“从不禁用” (never disable) 选项, 因此不能禁用管理员帐户。

本地目标消息格式: <timestamp> <seq_num> 10013 INFO AAC: Admin account set as 'never disabled', <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 10013 INFO AAC: Admin account set as 'never disabled', <log details>

- 消息代码: 10014

严重性: 信息 (INFO)

消息文本: 管理员帐户设置为“下次登录时更改密码” (change password on next login) (Admin account set to change password on next login)

消息说明: 管理员帐户设置为“下次登录时更改密码” (change password on next login)

本地目标消息格式: <timestamp> <seq_num> 10014 INFO AAC: Admin account set to change password on next login, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 10014 INFO AAC: Admin account set to
change password on next login, <log details>

身份验证流程诊断

- 消息代码: 22000

严重性: 错误 (ERROR)

消息文本: 身份验证导致出现内部错误 (Authentication resulted in internal error)

消息说明: 身份验证导致出现内部错误

本地目标消息格式: <timestamp> <seq_num> 22000 ERROR Authentication: Authentication resulted
in internal error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22000 ERROR Authentication: Authentication
resulted in internal error, <log details>

- 消息代码: 22001

严重性: 信息 (INFO)

消息文本: 已找到受限属性 (Restricted attribute(s) found)

消息说明: 已找到受限属性

本地目标消息格式: <timestamp> <seq_num> 22001 INFO Authentication: Restricted attribute(s)
found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22001 INFO Authentication: Restricted
attribute(s) found, <log details>

- 消息代码: 22002

严重性: 调试 (DEBUG)

消息文本: 身份验证完成 (Authentication complete)

消息说明: 身份验证完成

本地目标消息格式: <timestamp> <seq_num> 22002 DEBUG Authentication: Authentication complete,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22002 DEBUG Authentication: Authentication
complete, <log details>

- 消息代码: 22003

严重性: 信息 (INFO)

消息文本: 缺少身份验证属性 (Missing attribute for authentication)

消息说明: 缺少身份验证属性

本地目标消息格式: <timestamp> <seq_num> 22003 INFO Authentication: Missing attribute for authentication, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22003 INFO Authentication: Missing attribute for authentication, <log details>

- 消息代码: 22004

严重性: 信息 (INFO)

消息文本: 密码错误 (Wrong password)

消息说明: 密码错误

本地目标消息格式: <timestamp> <seq_num> 22004 INFO Authentication: Wrong password, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22004 INFO Authentication: Wrong password, <log details>

- 消息代码: 22005

严重性: 信息 (INFO)

消息文本: 无法获取 Shell 配置文件对象 (Could not get shell profile object)

消息说明: 无法获取 Shell 配置文件对象

本地目标消息格式: <timestamp> <seq_num> 22005 INFO Authentication: Could not get shell profile object, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22005 INFO Authentication: Could not get shell profile object, <log details>

- 消息代码: 22006

严重性: 信息 (INFO)

消息文本: 未配置 Shell 配置文件对象 (Shell profile object is not configured)

消息说明: 未配置 Shell 配置文件对象

本地目标消息格式: <timestamp> <seq_num> 22006 INFO Authentication: Shell profile object is not configured, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22006 INFO Authentication: Shell profile object is not configured, <log details>

- 消息代码: 22007

严重性: 信息 (INFO)

消息文本: 身份验证请求中没有用户名属性 (Username attribute is not present in the authentication request)

消息说明: 身份验证请求中没有用户名属性。

本地目标消息格式: <timestamp> <seq_num> 22007 INFO Authentication: Username attribute is not present in the authentication request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 22007 INFO Authentication: Username attribute is not present in the authentication request, <log details>

- 消息代码: 22008

严重性: 调试 (DEBUG)

消息文本: 不允许更改启用密码 (Changing enable password is not allowed)

消息说明: 由于要根据常规密码对用户进行身份验证, 因此不允许更改启用密码

本地目标消息格式: <timestamp> <seq_num> 22008 DEBUG Authentication : Changing enable password is not allowed , <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 22008 DEBUG Authentication : Changing enable password is not allowed , <log details>

- 消息代码: 22015

严重性: 调试 (DEBUG)

消息文本: 身份序列继续进入下一个 IDStore (Identity sequence continues to the next IDStore)

消息说明: 身份序列继续进入下一个 IDStore

本地目标消息格式: <timestamp> <seq_num> 22015 DEBUG Workflow: Identity sequence continues to the next IDStore, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 22015 DEBUG Workflow: Identity sequence continues to the next IDStore, <log details>

- 消息代码: 22016

严重性: 调试 (DEBUG)

消息文本: 身份序列已完成 IDStore 的迭代 (Identity sequence completed iterating the IDStores)

消息说明: 身份序列已完成 IDStore 的迭代

本地目标消息格式: <timestamp> <seq_num> 22016 DEBUG Workflow: Identity sequence completed iterating the IDStores, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 22016 DEBUG Workflow: Identity sequence completed iterating the IDStores, <log details>

- 消息代码: 22017
 - 严重性: 信息 (INFO)
 - 消息文本: 选定的身份源是 DenyAccess (Selected Identity Source is DenyAccess)
 - 消息说明: 选定的身份源是 DenyAccess
 - 本地目标消息格式: <timestamp> <seq_num> 22017 INFO Workflow: Selected Identity Source is DenyAccess, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22017 INFO Workflow: Selected Identity Source is DenyAccess, <log details>

- 消息代码: 22019
 - 严重性: 调试 (DEBUG)
 - 消息文本: 以前评估过身份策略; 身份序列继续运行 (Identity Policy was evaluated before; Identity Sequence continuing)
 - 消息说明: 以前评估过身份策略。身份序列继续运行
 - 本地目标消息格式: <timestamp> <seq_num> 22019 DEBUG Workflow: Identity Policy was evaluated before; Identity Sequence continuing, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22019 DEBUG Workflow: Identity Policy was evaluated before; Identity Sequence continuing, <log details>

- 消息代码: 22020
 - 严重性: 错误 (ERROR)
 - 消息文本: 配置错误: 身份源为空 (Configuration error: identity source blank)
 - 消息说明: 配置错误: 身份源为空
 - 本地目标消息格式: <timestamp> <seq_num> 22020 ERROR Workflow: Configuration error: identity source blank, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22020 ERROR Workflow: Configuration error: identity source blank, <log details>

- 消息代码: 22021
 - 严重性: 错误 (ERROR)
 - 消息文本: 配置错误: 身份验证 IDStore 列表为空 (Configuration error: authentication IDStores list blank)
 - 消息说明: 配置错误, 身份验证 IDStore 列表为空
 - 本地目标消息格式: <timestamp> <seq_num> 22021 ERROR Workflow: Configuration error: authentication IDStores list blank, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22021 ERROR Workflow: Configuration
error: authentication IDStores list blank, <log details>

- 消息代码: 22022

严重性: 错误 (ERROR)

消息文本: 设置“故障时打开” (fail open) 选项时出错 (Error in setting fail open options)

消息说明: 设置“故障时打开” (fail open) 选项时出错

本地目标消息格式: <timestamp> <seq_num> 22022 ERROR Workflow: Error in setting fail open
options, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22022 ERROR Workflow: Error in setting
fail open options, <log details>

- 消息代码: 22023

严重性: 信息 (INFO)

消息文本: 继续进行属性检索 (Proceed to attribute retrieval)

消息说明: 身份验证成功完成。继续进行属性检索

本地目标消息格式: <timestamp> <seq_num> 22023 INFO Workflow: Proceed to attribute retrieval,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22023 INFO Workflow: Proceed to attribute
retrieval, <log details>

- 消息代码: 22028

严重性: 信息 (INFO)

消息文本: 身份验证失败且忽略了高级选项 (Authentication failed and the advanced options are
ignored)

消息说明: 用户身份验证失败, 并且忽略了相关身份验证策略的身份部分中指定的高级选项设置。对于 PEAP、LEAP、EAP-FAST 或 RADIUS MSCHAP 身份验证, 当身份验证失败时, ISE 会停止处理请求。

本地目标消息格式: <timestamp> <seq_num> 22028 INFO Workflow: Authentication failed and the
advanced options are ignored, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22028 INFO Workflow: Authentication
failed and the advanced options are ignored, <log details>

- 消息代码: 22034

严重性: 信息 (INFO)

消息文本: 属性检索失败 (Attribute retrieval failed)

消息说明: 属性检索失败

本地目标消息格式: <timestamp> <seq_num> 22034 INFO Workflow: Attribute retrieval failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22034 INFO Workflow: Attribute retrieval failed, <log details>

- 消息代码: 22036

严重性: 信息 (INFO)

消息文本: 已从当前 IDStore 中成功检索到属性 (Retrieved Attributes successfully from current IDStore)

消息说明: 已从当前 IDStore 中成功检索到属性

本地目标消息格式: <timestamp> <seq_num> 22036 INFO Workflow: Retrieved Attributes successfully from current IDStore, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22036 INFO Workflow: Retrieved Attributes successfully from current IDStore, <log details>

- 消息代码: 22037

严重性: 调试 (DEBUG)

消息文本: 已通过身份验证 (Authentication Passed)

消息说明: 已通过身份验证, 正在跳过属性检索

本地目标消息格式: <timestamp> <seq_num> 22037 DEBUG Workflow: Authentication Passed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22037 DEBUG Workflow: Authentication Passed, <log details>

- 消息代码: 22038

严重性: 信息 (INFO)

消息文本: 正在跳过下一个 IDStore 中的属性检索, 因为该 IDStore 是我们进行身份验证的依照对象 (Skipping the next IDStore for attribute retrieval because it is the one we authenticated against)

消息说明: 正在跳过下一个 IDStore 中的属性检索, 因为该 IDStore 是我们进行身份验证的依照对象

本地目标消息格式: <timestamp> <seq_num> 22038 INFO Workflow: Skipping the next IDStore for attribute retrieval because it is the one we authenticated against, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22038 INFO Workflow: Skipping the next
IDStore for attribute retrieval because it is the one we authenticated against, <log details>

- 消息代码: 22039

严重性: 错误 (ERROR)

消息文本: 工作流序列类型无效 (Invalid workflow sequence type)

消息说明: 工作流序列类型无效

本地目标消息格式: <timestamp> <seq_num> 22039 ERROR Workflow: Invalid workflow sequence
type, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22039 ERROR Workflow: Invalid workflow
sequence type, <log details>

- 消息代码: 22040

严重性: 信息 (INFO)

消息文本: 密码错误或共享密钥无效 (Wrong password or invalid shared secret)

消息说明: 密码错误或共享密钥无效

本地目标消息格式: <timestamp> <seq_num> 22040 INFO Authentication: Wrong password or invalid
shared secret, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22040 INFO Authentication: Wrong password
or invalid shared secret, <log details>

- 消息代码: 22043

严重性: 信息 (INFO)

消息文本: 当前的身份存储库不支持该身份验证方式; 正在跳过 (Current Identity Store does not
support the authentication method; Skipping it)

消息说明: 当前的身份存储库不支持该身份验证方式。正在跳过。

本地目标消息格式: <timestamp> <seq_num> 22043 INFO Authentication: Current Identity Store
does not support the authentication method; Skipping it, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22043 INFO Authentication: Current Identity
Store does not support the authentication method; Skipping it, <log details>

- 消息代码: 22044

严重性: 信息 (INFO)

消息文本: 身份策略结果配置为用于基于证书的身份验证方式, 但接收到的是基于密码的身份
验证请求 (Identity policy result is configured for certificate based authentication methods but received
password based)

消息说明: 身份策略结果配置为用于基于证书的身份验证方式, 但接收到的是基于密码的身份验证请求

本地目标消息格式: <timestamp> <seq_num> 22044 INFO Workflow: Identity policy result is configured for certificate based authentication methods but received password based, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 22044 INFO Workflow: Identity policy result is configured for certificate based authentication methods but received password based, <log details>

- 消息代码: 22045

严重性: 信息 (INFO)

消息文本: 身份策略结果配置为用于基于密码的身份验证方式, 但接收到的是基于证书的身份验证请求 (Identity policy result is configured for password based authentication methods but received certificate based authentication request)

消息说明: 身份策略结果配置为用于基于密码的身份验证方式, 但接收到的是基于证书的身份验证请求

本地目标消息格式: <timestamp> <seq_num> 22045 INFO Workflow: Identity policy result is configured for password based authentication methods but received certificate based authentication request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 22045 INFO Workflow: Identity policy result is configured for password based authentication methods but received certificate based authentication request, <log details>

- 消息代码: 22046

严重性: 调试 (DEBUG)

消息文本: 身份序列收到了证书身份验证请求 (Identity sequence received a certificate authentication request)

消息说明: 身份序列收到了证书身份验证请求

本地目标消息格式: <timestamp> <seq_num> 22046 DEBUG Workflow: Identity sequence received a certificate authentication request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 22046 DEBUG Workflow: Identity sequence received a certificate authentication request, <log details>

- 消息代码: 22047

严重性: 调试 (DEBUG)

消息文本: 客户端证书中缺少用户名属性 (User name attribute is missing in client certificate)

消息说明: 客户端证书中缺少用户名属性

本地目标消息格式: <timestamp> <seq_num> 22047 DEBUG Authentication: User name attribute is missing in client certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22047 DEBUG Authentication: User name attribute is missing in client certificate, <log details>

- 消息代码: 22048

严重性: 调试 (DEBUG)

消息文本: 缺少客户端证书二进制数据 (Client certificate binary is missing)

消息说明: 缺少客户端证书二进制数据

本地目标消息格式: <timestamp> <seq_num> 22048 DEBUG Authentication: Client certificate binary is missing, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22048 DEBUG Authentication: Client certificate binary is missing, <log details>

- 消息代码: 22049

严重性: 调试 (DEBUG)

消息文本: 证书的二进制比较失败 (Binary comparison of certificates failed)

消息说明: 证书的二进制比较失败

本地目标消息格式: <timestamp> <seq_num> 22049 DEBUG Authentication: Binary comparison of certificates failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22049 DEBUG Authentication: Binary comparison of certificates failed, <log details>

- 消息代码: 22050

严重性: 信息 (INFO)

消息文本: 在属性检索模式下, 当前 IDStore 中禁用了用户或主机 (User or host disabled in current IDStore in attribute retrieval mode)

消息说明: 在属性检索模式下, 当前 IDStore 中禁用了用户或主机

本地目标消息格式: <timestamp> <seq_num> 22050 INFO Workflow: User or host disabled in current IDStore in attribute retrieval mode, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22050 INFO Workflow: User or host disabled in current IDStore in attribute retrieval mode, <log details>

- 消息代码: 22051

严重性: 信息 (INFO)

消息文本: 内部 IDStore 中禁用了用户或主机, 根据高级选项继续操作 (User or host disabled in Internal IDStore, proceed according to Advanced Option)

消息说明: 内部 IDStore 中禁用了用户或主机, 根据高级选项继续操作

本地目标消息格式: <timestamp> <seq_num> 22051 INFO Workflow: User or host disabled in Internal IDStore, proceed according to Advanced Option, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22051 INFO Workflow: User or host disabled in Internal IDStore, proceed according to Advanced Option, <log details>

- 消息代码: 22052

严重性: 错误 (ERROR)

消息文本: 完成身份验证后, 身份验证 IDStore 为空 (Authentication IDStore empty after completing authentication)

消息说明: 完成身份验证后, 身份验证 IDStore 为空

本地目标消息格式: <timestamp> <seq_num> 22052 ERROR Workflow: Authentication IDStore empty after completing authentication, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22052 ERROR Workflow: Authentication IDStore empty after completing authentication, <log details>

- 消息代码: 22054

严重性: 调试 (DEBUG)

消息文本: 证书的二进制比较成功 (Binary comparison of certificates succeeded)

消息说明: 证书的二进制比较成功。

本地目标消息格式: <timestamp> <seq_num> 22054 DEBUG Authentication: Binary comparison of certificates succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22054 DEBUG Authentication: Binary comparison of certificates succeeded, <log details>

- 消息代码: 22055

严重性: 信息 (INFO)

消息文本: 无法在用户证书中找到预期的“主要用户名 X509 属性” (Principal Username X509 Attribute) (Failed to find expected Principal Username X509 Attribute in user's certificate)

消息说明: 用户证书中不包含已在选定的证书身份验证配置文件中配置的特定“主要用户名 X509 属性” (Principal Username X509 Attribute)。

本地目标消息格式: <timestamp> <seq_num> 22055 INFO Authentication: Failed to find expected Principal Username X509 Attribute in user's certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22055 INFO Authentication: Failed to find
expected Principal Username X509 Attribute in user's certificate, <log details>

- 消息代码: 22056

严重性: 调试 (DEBUG)

消息文本: 在适用的身份存储库中未找到主题 (Subject not found in the applicable identity store(s))

消息说明: 在适用的身份存储库中未找到主题。

本地目标消息格式: <timestamp> <seq_num> 22056 DEBUG Workflow: Subject not found in the
applicable identity store(s), <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22056 DEBUG Workflow: Subject not found
in the applicable identity store(s), <log details>

- 消息代码: 22057

严重性: 信息 (INFO)

消息文本: 已使用为失败的身份验证请求配置的高级选项 (The advanced option that is configured
for a failed authentication request is used)

消息说明: 已使用为失败的身份验证请求配置的高级选项。

本地目标消息格式: <timestamp> <seq_num> 22057 INFO Workflow: The advanced option that is
configured for a failed authentication request is used, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22057 INFO Workflow: The advanced option
that is configured for a failed authentication request is used, <log details>

- 消息代码: 22058

严重性: 信息 (INFO)

消息文本: 已使用为未知用户配置的高级选项 (The advanced option that is configured for an unknown
user is used)

消息说明: 已使用为未知用户配置的高级选项。

本地目标消息格式: <timestamp> <seq_num> 22058 INFO Workflow: The advanced option that is
configured for an unknown user is used, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22058 INFO Workflow: The advanced option
that is configured for an unknown user is used, <log details>

- 消息代码: 22059

严重性: 信息 (INFO)

消息文本: 已使用为流程失败配置的高级选项 (The advanced option that is configured for process
failure is used)

消息说明：已使用为流程失败配置的高级选项。

本地目标消息格式：<timestamp> <seq_num> 22059 INFO Workflow: The advanced option that is configured for process failure is used, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22059 INFO Workflow: The advanced option that is configured for process failure is used, <log details>

- 消息代码：22060

严重性：信息 (INFO)

消息文本：为了防止身份验证请求失败，配置了“继续” (Continue) 高级选项 (The 'Continue' advanced option is configured in case of a failed authentication request)

消息说明：为了防止身份验证请求失败，配置了“继续” (Continue) 高级选项。

本地目标消息格式：<timestamp> <seq_num> 22060 INFO Workflow: The 'Continue' advanced option is configured in case of a failed authentication request, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22060 INFO Workflow: The 'Continue' advanced option is configured in case of a failed authentication request, <log details>

- 消息代码：22061

严重性：信息 (INFO)

消息文本：为了防止身份验证请求失败，配置了“拒绝” (Reject) 高级选项 (The 'Reject' advanced option is configured in case of a failed authentication request)

消息说明：为了防止身份验证请求失败，配置了“拒绝” (Reject) 高级选项。

本地目标消息格式：<timestamp> <seq_num> 22061 INFO Workflow: The 'Reject' advanced option is configured in case of a failed authentication request, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22061 INFO Workflow: The 'Reject' advanced option is configured in case of a failed authentication request, <log details>

- 消息代码：22062

严重性：信息 (INFO)

消息文本：为了防止身份验证请求失败，配置了“丢弃” (Drop) 高级选项 (The 'Drop' advanced option is configured in case of a failed authentication request)

消息说明：为了防止身份验证请求失败，配置了“丢弃” (Drop) 高级选项。

本地目标消息格式：<timestamp> <seq_num> 22062 INFO Workflow: The 'Drop' advanced option is configured in case of a failed authentication request, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22062 INFO Workflow: The 'Drop' advanced option is configured in case of a failed authentication request, <log details>

- 消息代码: 22063
 - 严重性: 信息 (INFO)
 - 消息文本: 密码错误 (Wrong password)
 - 消息说明: 密码错误
 - 本地目标消息格式: <timestamp> <seq_num> 22063 INFO Authentication: Wrong password, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22063 INFO Authentication: Wrong password, <log details>

- 消息代码: 22064
 - 严重性: 调试 (DEBUG)
 - 消息文本: 身份验证方法不受任何适用的身份存储库的支持 (Authentication method is not supported by any applicable identity store(s))
 - 消息说明: 身份验证方法不受任何适用的身份存储库的支持
 - 本地目标消息格式: <timestamp> <seq_num> 22064 DEBUG Workflow: Authentication method is not supported by any applicable identity store(s), <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22064 DEBUG Workflow: Authentication method is not supported by any applicable identity store(s), <log details>

- 消息代码: 22065
 - 严重性: 警告 (WARN)
 - 消息文本: 无法实施访客会话限制, 因为无法访问 MnT 节点 (Guest session limit could not be enforced as MnT node not reachable)
 - 消息说明: 无法实施访客会话限制, 因为无法访问 MnT 节点
 - 本地目标消息格式: <timestamp> <seq_num> 22065 WARN Authentication: Guest session limit could not be enforced as MnT node not reachable, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22065 WARN Authentication: Guest session limit could not be enforced as MnT node not reachable, <log details>

- 消息代码: 22066
 - 严重性: 信息 (INFO)
 - 消息文本: 访客会话限制生效; 正在删除旧的访客会话 (Guest session limit is active; removing older guest sessions)
 - 消息说明: 访客会话限制生效; 正在删除旧的访客会话
 - 本地目标消息格式: <timestamp> <seq_num> 22066 INFO Authentication: Guest session limit is active; removing older guest sessions, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22066 INFO Authentication: Guest session limit is active; removing older guest sessions, <log details>

- 消息代码: 22067

严重性: 警告 (WARN)

消息文本: 访客会话限制响应中缺少用于删除旧访客会话的相关信息 (Guest session limit response is missing relevant information in order to remove old guest sessions)

消息说明: 访客会话限制响应中缺少用于删除旧访客会话的相关信息

本地目标消息格式: <timestamp> <seq_num> 22067 WARN Authentication: Guest session limit response is missing relevant information in order to remove old guest sessions, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22067 WARN Authentication: Guest session limit response is missing relevant information in order to remove old guest sessions, <log details>

- 消息代码: 22068

严重性: 调试 (DEBUG)

消息文本: 在恢复 EAP 会话时跳过了证书的二进制比较。 (Binary comparison of certificates skipped on EAP session resume.)

消息说明: 在恢复 EAP 会话时跳过了证书的二进制比较。

本地目标消息格式: <timestamp> <seq_num> 22068 DEBUG Authentication: Binary comparison of certificates skipped on EAP session resume., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22068 DEBUG Authentication: Binary comparison of certificates skipped on EAP session resume., <log details>

- 消息代码: 22069

严重性: 调试 (DEBUG)

消息文本: 客户端证书中缺少 AD 帐户搜索属性 (AD account search attribute is missing in client certificate)

消息说明: 客户端证书中缺少在“证书身份验证配置文件” (Certificate Authentication Profile) 中为 AD 帐户搜索选择的属性

本地目标消息格式: <timestamp> <seq_num> 22069 DEBUG Authentication: AD account search attribute is missing in client certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22069 DEBUG Authentication: AD account search attribute is missing in client certificate, <log details>

- 消息代码: 22070

严重性: 调试 (DEBUG)

消息文本: 从证书属性中获取身份名称 (Identity name is taken from certificate attribute)

消息说明: 根据“证书身份验证配置文件” (Certificate Authentication Profile) 设置, 从证书属性中获取身份名称

本地目标消息格式: <timestamp> <seq_num> 22070 DEBUG Authentication: Identity name is taken from certificate attribute, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22070 DEBUG Authentication: Identity name is taken from certificate attribute, <log details>

- 消息代码: 22071

严重性: 调试 (DEBUG)

消息文本: 从 AD 帐户隐式 UPN 中获取身份名称 (Identity name is taken from AD account Implicit UPN)

消息说明: 根据“证书身份验证配置文件” (Certificate Authentication Profile) 设置, 从 AD 帐户隐式 UPN 中获取身份名称

本地目标消息格式: <timestamp> <seq_num> 22071 DEBUG Authentication: Identity name is taken from AD account Implicit UPN, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22071 DEBUG Authentication: Identity name is taken from AD account Implicit UPN, <log details>

- 消息代码: 22072

严重性: 信息 (INFO)

消息文本: 已选择身份源序列 (Selected identity source sequence)

消息说明: 已选择身份源序列

本地目标消息格式: <timestamp> <seq_num> 22072 INFO Authentication: Selected identity source sequence, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22072 INFO Authentication: Selected identity source sequence, <log details>

- 消息代码: 22073

严重性: 信息 (INFO)

消息文本: 访客会话限制生效; 正在删除最新的访客会话 (Guest session limit is active; removing newest guest session)

消息说明: 访客会话限制生效; 正在删除最新的访客会话

本地目标消息格式: <timestamp> <seq_num> 22073 INFO Authentication: Guest session limit is active; removing newest guest session, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22073 INFO Authentication: Guest session
limit is active; removing newest guest session, <log details>

- 消息代码: 22074

严重性: 错误 (ERROR)

消息文本: 此协议在 FIPS 模式下禁用。(This Protocol is disabled in FIPS mode.)

消息说明: 此协议在 FIPS 模式下禁用。

本地目标消息格式: <timestamp> <seq_num> 22074 ERROR Authentication: This Protocol is disabled
in FIPS mode., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22074 ERROR Authentication: This Protocol
is disabled in FIPS mode., <log details>

- 消息代码: 22080

严重性: 信息 (INFO)

消息文本: 在会话缓存中创建了新记帐会话 (New accounting session created in Session cache)

消息说明: 在会话缓存中创建了新记帐会话。

本地目标消息格式: <timestamp> <seq_num> 22080 INFO Authentication: New accounting session
created in Session cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22080 INFO Authentication: New accounting
session created in Session cache, <log details>

- 消息代码: 22081

严重性: 信息 (INFO)

消息文本: 已通过最大会话数策略 (Max sessions policy passed)

消息说明: 已通过最大会话数策略。

本地目标消息格式: <timestamp> <seq_num> 22081 INFO Authentication: Max sessions policy passed,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 22081 INFO Authentication: Max sessions
policy passed, <log details>

- 消息代码: 22082

严重性: 信息 (INFO)

消息文本: 已禁用最大会话数策略 (Max sessions policy disabled)

消息说明: 已禁用最大会话数策略。

本地目标消息格式: <timestamp> <seq_num> 22082 INFO Authentication: Max sessions policy disabled, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22082 INFO Authentication: Max sessions policy disabled, <log details>

- 消息代码: 22083

严重性: 信息 (INFO)

消息文本: 用户/组会话计数器在记帐开始时递增 (User/group session counters incremented on accounting start)

消息说明: 用户/组会话计数器在记帐开始时递增

本地目标消息格式: <timestamp> <seq_num> 22083 INFO Authentication: User/group session counters incremented on accounting start, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22083 INFO Authentication: User/group session counters incremented on accounting start, <log details>

- 消息代码: 22084

严重性: 信息 (INFO)

消息文本: 用户/组会话计数器在记帐停止时递减 (User/group session counters decremented on accounting stop)

消息说明: 用户/组会话计数器在记帐停止时递减。已删除会话。

本地目标消息格式: <timestamp> <seq_num> 22084 INFO Authentication: User/group session counters decremented on accounting stop, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22084 INFO Authentication: User/group session counters decremented on accounting stop, <log details>

- 消息代码: 22085

严重性: 信息 (INFO)

消息文本: 记帐会话已在会话缓存中更新 (The accounting session was updated in Session cache)

消息说明: 记帐会话已在会话缓存中更新

本地目标消息格式: <timestamp> <seq_num> 22085 INFO Authentication: The accounting session was updated in Session cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22085 INFO Authentication: The accounting session was updated in Session cache, <log details>

- 消息代码: 22086

严重性: 信息 (INFO)

消息文本: 已清除设备的活动会话 (The active sessions were purged for device)

消息说明: 已清除设备的活动会话

本地目标消息格式: <timestamp> <seq_num> 22086 INFO Authentication: The active sessions were purged for device, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22086 INFO Authentication: The active sessions were purged for device, <log details>

- 消息代码: 22087

严重性: 信息 (INFO)

消息文本: 记帐会话已超时 (The accounting session was timed out)

消息说明: 记帐会话已超时

本地目标消息格式: <timestamp> <seq_num> 22087 INFO Authentication: The accounting session was timed out, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22087 INFO Authentication: The accounting session was timed out, <log details>

- 消息代码: 22088

严重性: 信息 (INFO)

消息文本: 已清除记帐会话 (The accounting session was purged)

消息说明: 已清除记帐会话

本地目标消息格式: <timestamp> <seq_num> 22088 INFO Authentication: The accounting session was purged, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22088 INFO Authentication: The accounting session was purged, <log details>

- 消息代码: 22089

严重性: 信息 (INFO)

消息文本: 不允许新用户会话。已达到最大会话数用户限制 (New user session not permitted. Max sessions user limit has been reached)

消息说明: 不允许新用户会话。已超过最大会话数用户限制。

本地目标消息格式: <timestamp> <seq_num> 22089 INFO Authentication: New user session not permitted. Max sessions user limit has been reached, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22089 INFO Authentication: New user session not permitted. Max sessions user limit has been reached, <log details>

- 消息代码: 22090
 - 严重性: 警告 (WARN)
 - 消息文本: 记帐会话密钥缺少一个或多个属性 (One or more attributes are missing for the accounting Session Key)
 - 消息说明: 记帐会话密钥缺少一个或多个属性。请检查 ACS 和网络设备配置。
 - 本地目标消息格式: <timestamp> <seq_num> 22090 WARN Authentication: One or more attributes are missing for the accounting Session Key, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22090 WARN Authentication: One or more attributes are missing for the accounting Session Key, <log details>

- 消息代码: 22091
 - 严重性: 信息 (INFO)
 - 消息文本: 身份验证失败。由于在全局级别的身份验证尝试失败次数过多, 已禁用帐户 (Authentication failed. User account is disabled due to excessive failed authentication attempts at global level)
 - 消息说明: 身份验证失败。由于在全局级别的身份验证尝试失败次数过多, 已禁用帐户。
 - 本地目标消息格式: <timestamp> <seq_num> 22091 INFO Authentication: Authentication failed. User account is disabled due to excessive failed authentication attempts at global level, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22091 INFO Authentication: Authentication failed. User account is disabled due to excessive failed authentication attempts at global level, <log details>

- 消息代码: 22092
 - 严重性: 信息 (INFO)
 - 消息文本: 未收到会话的记帐开始消息 (No accounting start was received for the session)
 - 消息说明: 未收到会话的记帐开始消息。将忽略此请求。
 - 本地目标消息格式: <timestamp> <seq_num> 22092 INFO Authentication: No accounting start was received for the session, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22092 INFO Authentication: No accounting start was received for the session, <log details>

- 消息代码: 22093
 - 严重性: 信息 (INFO)
 - 消息文本: 发现使用其他用户名的重复会话 (Duplicate session was found with a different user name)
 - 消息说明: 发现使用其他用户名的重复会话。将忽略此请求。检查会话密钥配置。

本地目标消息格式: <timestamp> <seq_num> 22093 INFO Authentication: Duplicate session was found with a different user name, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22093 INFO Authentication: Duplicate session was found with a different user name, <log details>

- 消息代码: 22094

严重性: 信息 (INFO)

消息文本: 未找到审核会话 (Audit session was not found)

消息说明: 未找到审核会话。会话已过期或已清除。

本地目标消息格式: <timestamp> <seq_num> 22094 INFO Authentication: Audit session was not found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22094 INFO Authentication: Audit session was not found, <log details>

- 消息代码: 22095

严重性: 信息 (INFO)

消息文本: 已收到不存在的会话的记帐开始请求 (Accounting start was received for non-existing session)

消息说明: 已收到未在缓存中找到的会话的记帐开始请求。会话未创建或已清除。

本地目标消息格式: <timestamp> <seq_num> 22095 INFO Authentication: Accounting start was received for non-existing session, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22095 INFO Authentication: Accounting start was received for non-existing session, <log details>

- 消息代码: 22096

严重性: 信息 (INFO)

消息文本: 最大会话数策略不适用于代理 (Max session policy is not available for Proxy)

消息说明: 最大会话数策略不适用于代理。

本地目标消息格式: <timestamp> <seq_num> 22096 INFO Authentication: Max session policy is not available for Proxy, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 22096 INFO Authentication: Max session policy is not available for Proxy, <log details>

- 消息代码: 22097

严重性: 信息 (INFO)

消息文本: 不允许新用户会话。已达到组的最大会话数限制 (New user session not permitted. Max sessions group limit has been reached)

消息说明: 不允许新用户会话。已达到组的最大会话数限制。

本地目标消息格式: <timestamp> <seq_num> 22097 INFO Authentication: New user session not permitted. Max sessions group limit has been reached, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 22097 INFO Authentication: New user session not permitted. Max sessions group limit has been reached, <log details>

- 消息代码: 22098

严重性: 信息 (INFO)

消息文本: 不允许新用户会话。已达到组中用户的最大会话数限制 (New user session not permitted. Max sessions user in group limit has been reached)

消息说明: 不允许新用户会话。已达到组中用户的最大会话数限制。

本地目标消息格式: <timestamp> <seq_num> 22098 INFO Authentication: New user session not permitted. Max sessions user in group limit has been reached, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 22098 INFO Authentication: New user session not permitted. Max sessions user in group limit has been reached, <log details>

分布式管理

- 消息代码: 41000

严重性: 警告 (WARN)

消息文本: 未找到内存统计信息 (Memory statistics not found)

消息说明: 用于生成本地系统内存使用情况的系统调用失败。

本地目标消息格式: <timestamp> <seq_num> 41000 WARN Distributed-Management: Memory statistics not found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 41000 WARN Distributed-Management: Memory statistics not found, <log details>

- 消息代码: 41001

严重性: 警告 (WARN)

消息文本: 未找到总内存 (Total memory not found)

消息说明: 用于生成总系统内存的系统调用失败。

本地目标消息格式: <timestamp> <seq_num> 41001 WARN Distributed-Management: Total memory not found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 41001 WARN Distributed-Management:
Total memory not found, <log details>

- 消息代码: 41002

严重性: 警告 (WARN)

消息文本: 未找到总交换 (Total swap not found)

消息说明: 用于生成总交换大小的系统调用失败。

本地目标消息格式: <timestamp> <seq_num> 41002 WARN Distributed-Management: Total swap
not found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 41002 WARN Distributed-Management:
Total swap not found, <log details>

- 消息代码: 41003

严重性: 警告 (WARN)

消息文本: 未找到磁盘大小 (Disk size not found)

消息说明: 用于生成磁盘大小的系统调用失败。

本地目标消息格式: <timestamp> <seq_num> 41003 WARN Distributed-Management: Disk size not
found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 41003 WARN Distributed-Management:
Disk size not found, <log details>

- 消息代码: 41004

严重性: 警告 (WARN)

消息文本: 未找到磁盘设备 (Disk device not found)

消息说明: 用于生成磁盘设备列表的系统调用失败。

本地目标消息格式: <timestamp> <seq_num> 41004 WARN Distributed-Management: Disk device
not found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 41004 WARN Distributed-Management:
Disk device not found, <log details>

- 消息代码: 41005

严重性: 警告 (WARN)

消息文本: 未找到 ISE 版本 (ISE version not found)

消息说明: 用于获取 ISE 软件版本的系统调用失败。

本地目标消息格式: <timestamp> <seq_num> 41005 WARN Distributed-Management: ISE version not found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41005 WARN Distributed-Management: ISE version not found, <log details>

- 消息代码: 41007

严重性: 信息 (INFO)

消息文本: 已找到 ISE 节点记录 (ISE Node record found)

消息说明: 无法在数据库中找到底层 ISE 节点记录。

本地目标消息格式: <timestamp> <seq_num> 41007 INFO Distributed-Management: ISE Node record found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41007 INFO Distributed-Management: ISE Node record found, <log details>

- 消息代码: 41008

严重性: 信息 (INFO)

消息文本: 找到的 ISE 主节点记录接管主要角色 (Primary ISE Node record found taking over primary role)

消息说明: 由于无法为本地设备找到适当的 ISE 节点记录, 但找到了 ISE 主节点记录。因此, 本地节点会接手主要角色。

本地目标消息格式: <timestamp> <seq_num> 41008 INFO Distributed-Management: Primary ISE Node record found taking over primary role, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41008 INFO Distributed-Management: Primary ISE Node record found taking over primary role, <log details>

- 消息代码: 41009

严重性: 信息 (INFO)

消息文本: 已创建默认 ISE 部署 (Default ISE Deployment created)

消息说明: 在系统初始化过程中, 在数据库中创建了默认 ISE 部署记录。这是系统的正常行为。

本地目标消息格式: <timestamp> <seq_num> 41009 INFO Distributed-Management: Default ISE Deployment created, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41009 INFO Distributed-Management: Default ISE Deployment created, <log details>

- 消息代码: 41010

严重性: 信息 (INFO)

消息文本: 已创建默认 ISE 节点 (Default ISE Node created)

消息说明: 在系统初始化过程中, 在数据库中创建了默认 ISE 节点记录。这是系统的正常行为。

本地目标消息格式: <timestamp> <seq_num> 41010 INFO Distributed-Management: Default ISE Node created, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41010 INFO Distributed-Management: Default ISE Node created, <log details>

- 消息代码: 41011

严重性: 信息 (INFO)

消息文本: 节点状态已初始化 (Node Status initialized)

消息说明: 在系统初始化过程中, 节点状态已初始化。

本地目标消息格式: <timestamp> <seq_num> 41011 INFO Distributed-Management: Node Status initialized, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41011 INFO Distributed-Management: Node Status initialized, <log details>

- 消息代码: 41012

严重性: 信息 (INFO)

消息文本: 已注册辅助节点 (Secondary registered)

消息说明: 一个新的 ISE 实例已加入部署中。

本地目标消息格式: <timestamp> <seq_num> 41012 INFO Distributed-Management: Secondary registered, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41012 INFO Distributed-Management: Secondary registered, <log details>

- 消息代码: 41013

严重性: 信息 (INFO)

消息文本: 已撤销注册 ISE 节点, 此节点现正作为主节点运行 (ISE Node has been deregistered and is now running as a Primary node)

消息说明: 已撤销注册 ISE 节点, 此节点现正作为主节点运行

本地目标消息格式: <timestamp> <seq_num> 41013 INFO Distributed-Management: ISE Node has been deregistered and is now running as a Primary node, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41013 INFO Distributed-Management: ISE Node has been deregistered and is now running as a Primary node, <log details>

- 消息代码: 41014
 - 严重性: 错误 (ERROR)
 - 消息文本: 未找到软件版本 (Software version not found)
 - 消息说明: 用于获取 ISE 软件版本的系统调用失败。
 - 本地目标消息格式: <timestamp> <seq_num> 41014 ERROR Distributed-Management: Software version not found, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 41014 ERROR Distributed-Management: Software version not found, <log details>

- 消息代码: 41015
 - 严重性: 错误 (ERROR)
 - 消息文本: 无法运行 (Could not run)
 - 消息说明: 已激活的系统调用无法正确运行。
 - 本地目标消息格式: <timestamp> <seq_num> 41015 ERROR Distributed-Management: Could not run, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 41015 ERROR Distributed-Management: Could not run, <log details>

- 消息代码: 41016
 - 严重性: 错误 (ERROR)
 - 消息文本: 无法读取标准输出 (could not read stdout)
 - 消息说明: 在运行系统调用时, 无法读取系统调用的标准输出。
 - 本地目标消息格式: <timestamp> <seq_num> 41016 ERROR Distributed-Management: could not read stdout, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 41016 ERROR Distributed-Management: could not read stdout, <log details>

- 消息代码: 41017
 - 严重性: 警告 (WARN)
 - 消息文本: 未找到主机名 (Hostname not found)
 - 消息说明: 用于获取本地系统主机名的系统调用失败。
 - 本地目标消息格式: <timestamp> <seq_num> 41017 WARN Distributed-Management: Hostname not found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 41017 WARN Distributed-Management:
Hostname not found, <log details>

- 消息代码: 41018

严重性: 错误 (ERROR)

消息文本: 服务选择策略更新失败 (Service Selection Policy update failed)

消息说明: 在系统初始化过程中, 默认的服务选择策略更新失败。

本地目标消息格式: <timestamp> <seq_num> 41018 ERROR Distributed-Management: Service
Selection Policy update failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 41018 ERROR Distributed-Management:
Service Selection Policy update failed, <log details>

- 消息代码: 41019

严重性: 错误 (ERROR)

消息文本: 无法将关系添加到服务选择策略 (Could not add relation to Service Selection Policy)

消息说明: 在系统初始化过程中, 默认的服务选择策略更新失败。

本地目标消息格式: <timestamp> <seq_num> 41019 ERROR Distributed-Management: Could not
add relation to Service Selection Policy, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 41019 ERROR Distributed-Management:
Could not add relation to Service Selection Policy, <log details>

- 消息代码: 41020

严重性: 错误 (ERROR)

消息文本: 无法初始化服务选择策略 (Could not initialize Service Selection Policy)

消息说明: 在系统初始化过程中, 默认的服务选择策略更新失败。

本地目标消息格式: <timestamp> <seq_num> 41020 ERROR Distributed-Management: Could not
initialize Service Selection Policy, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 41020 ERROR Distributed-Management:
Could not initialize Service Selection Policy, <log details>

- 消息代码: 41021

严重性: 错误 (ERROR)

消息文本: 无法更新 ISE 节点对象 (Could not update ISE Node Object)

消息说明: 无法在系统启动时更新 ISE 节点的本地节点信息。

本地目标消息格式: <timestamp> <seq_num> 41021 ERROR Distributed-Management: Could not update ISE Node Object, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 41021 ERROR Distributed-Management: Could not update ISE Node Object, <log details>

- 消息代码: 41022

严重性: 错误 (ERROR)

消息文本: 收集 NodeInfo 时发生错误 (An error occurred while collecting NodeInfo)

消息说明: 本地节点信息收集失败。

本地目标消息格式: <timestamp> <seq_num> 41022 ERROR Distributed-Management: An error occurred while collecting NodeInfo, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 41022 ERROR Distributed-Management: An error occurred while collecting NodeInfo, <log details>

- 消息代码: 41023

严重性: 错误 (ERROR)

消息文本: 收集复制状态时发生错误 (An error occurred while collecting replication status)

消息说明: 复制状态收集失败。

本地目标消息格式: <timestamp> <seq_num> 41023 ERROR Distributed-Management: An error occurred while collecting replication status, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 41023 ERROR Distributed-Management: An error occurred while collecting replication status, <log details>

- 消息代码: 41024

严重性: 错误 (ERROR)

消息文本: 加载 NodeInfo 时出错 (Error loading NodeInfo)

消息说明: NodeInfo 文件未正确加载。

本地目标消息格式: <timestamp> <seq_num> 41024 ERROR Distributed-Management: Error loading NodeInfo, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 41024 ERROR Distributed-Management: Error loading NodeInfo, <log details>

- 消息代码: 41025

严重性: 错误 (ERROR)

消息文本: NodeInfo 文件包含的信息不完整 (NodeInfo file contains incomplete information)

消息说明: NodeInfo 文件包含的信息不完整, 并且未正确加载。

本地目标消息格式: <timestamp> <seq_num> 41025 ERROR Distributed-Management: NodeInfo file contains incomplete information, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41025 ERROR Distributed-Management: NodeInfo file contains incomplete information, <log details>

- 消息代码: 41026

严重性: 错误 (ERROR)

消息文本: 无法创建管理配置目录 (Management config directory could not be created)

消息说明: 无法创建管理配置目录。

本地目标消息格式: <timestamp> <seq_num> 41026 ERROR Distributed-Management: Management config directory could not be created, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41026 ERROR Distributed-Management: Management config directory could not be created, <log details>

- 消息代码: 41027

严重性: 错误 (ERROR)

消息文本: 无法创建 NodeInfo 文件 (NodeInfo file could not be created)

消息说明: 无法在配置目录中创建 NodeInfo 文件。

本地目标消息格式: <timestamp> <seq_num> 41027 ERROR Distributed-Management: NodeInfo file could not be created, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41027 ERROR Distributed-Management: NodeInfo file could not be created, <log details>

- 消息代码: 41028

严重性: 错误 (ERROR)

消息文本: 未在初始化过程中找到 MAC 地址 (MAC Address not found during initialization)

消息说明: 在初始化过程中, 无法在系统网络接口中找到计算机网络地址。

本地目标消息格式: <timestamp> <seq_num> 41028 ERROR Distributed-Management: MAC Address not found during initialization, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41028 ERROR Distributed-Management: MAC Address not found during initialization, <log details>

- 消息代码: 41029

严重性: 错误 (ERROR)

消息文本: 未在现有节点中找到 ISE 节点记录。ISE 无法启动 (ISE Node record not found in existing nodes. ISE cannot start)

消息说明: 在系统初始化过程中, 未在现有节点中找到代表本地实例的 ISE 节点记录。ISE 管理无法启动。

本地目标消息格式: <timestamp> <seq_num> 41029 ERROR Distributed-Management: ISE Node record not found in existing nodes. ISE cannot start, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 41029 ERROR Distributed-Management: ISE Node record not found in existing nodes. ISE cannot start, <log details>

- 消息代码: 41030

严重性: 错误 (ERROR)

消息文本: 未在 ACSNodeInfo 中找到 MAC ID (MAC Id not found in ACSNodeInfo)

消息说明: 未在数据库的 ACSNodeInfo 记录中找到计算机地址字段。

本地目标消息格式: <timestamp> <seq_num> 41030 ERROR Distributed-Management: MAC Id not found in ACSNodeInfo, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 41030 ERROR Distributed-Management: MAC Id not found in ACSNodeInfo, <log details>

- 消息代码: 41031

严重性: 错误 (ERROR)

消息文本: 正在注册的辅助主机名在主数据库中已经存在 (Registering Secondary Hostname already exists in Primary database)

消息说明: 正在尝试注册辅助主机名。但是, 此主机名在主数据库中已经存在。

本地目标消息格式: <timestamp> <seq_num> 41031 ERROR Distributed-Management: Registering Secondary Hostname already exists in Primary database, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 41031 ERROR Distributed-Management: Registering Secondary Hostname already exists in Primary database, <log details>

- 消息代码: 41032

严重性: 错误 (ERROR)

消息文本: 由于辅助 MAC 地址在主数据库中已经存在, 因此注册失败 (Register failed since Secondary MAC address already exists in the Primary database)

消息说明: 正在尝试注册辅助主机名的计算机地址。但是, 此主机名在主数据库中已经存在。

本地目标消息格式: <timestamp> <seq_num> 41032 ERROR Distributed-Management: Register failed since Secondary MAC address already exists in the Primary database, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 41032 ERROR Distributed-Management:
Register failed since Secondary MAC address already exists in the Primary database, <log details>

- 消息代码: 41033

严重性: 错误 (ERROR)

消息文本: 由于未在主数据库中找到 ISE 辅助节点, 因此撤销注册失败 (Deregistration failed since Secondary ISE Node not found in the Primary database)

消息说明: 由于未在主数据库中找到 ISE 辅助节点记录, 因此 ISE 实例撤销注册失败。

本地目标消息格式: <timestamp> <seq_num> 41033 ERROR Distributed-Management: Deregistration failed since Secondary ISE Node not found in the Primary database, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 41033 ERROR Distributed-Management:
Deregistration failed since Secondary ISE Node not found in the Primary database, <log details>

- 消息代码: 41034

严重性: 错误 (ERROR)

消息文本: 由于未找到 ISE 辅助节点, 因此激活失败 (Activation failed since Secondary ISE Node is not found)

消息说明: 由于未在数据库中找到辅助 ACSNode 记录, 因此通过主数据库激活辅助节点失败。

本地目标消息格式: <timestamp> <seq_num> 41034 ERROR Distributed-Management: Activation failed since Secondary ISE Node is not found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 41034 ERROR Distributed-Management:
Activation failed since Secondary ISE Node is not found, <log details>

- 消息代码: 41035

严重性: 错误 (ERROR)

消息文本: 远程主机不是主 AcsNode (Remote host is not a Primary AcsNode)

消息说明: 在分布式管理中, 由于主机不是主实例, 因此不可能实现到主实例的远程操作连接。

本地目标消息格式: <timestamp> <seq_num> 41035 ERROR Distributed-Management: Remote host is not a Primary AcsNode, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 41035 ERROR Distributed-Management:
Remote host is not a Primary AcsNode, <log details>

- 消息代码: 41036

严重性: 错误 (ERROR)

消息文本: 无法撤销注册 ISE 主节点 (Cannot deregister a Primary ISE Node)

消息说明：无法撤销注册部署的主实例。

本地目标消息格式：<timestamp> <seq_num> 41036 ERROR Distributed-Management: Cannot deregister a Primary ISE Node, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41036 ERROR Distributed-Management: Cannot deregister a Primary ISE Node, <log details>

- 消息代码：41037

严重性：错误 (ERROR)

消息文本：找不到 ISE 部署记录，因此主要初始化不正确 (ISE Deployment record cannot be found, therefore Primary initialization is incorrect)

消息说明：在系统初始化过程中，未找到 ISE 部署记录，并且系统无法正确启动。

本地目标消息格式：<timestamp> <seq_num> 41037 ERROR Distributed-Management: ISE Deployment record cannot be found, therefore Primary initialization is incorrect, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41037 ERROR Distributed-Management: ISE Deployment record cannot be found, therefore Primary initialization is incorrect, <log details>

- 消息代码：41038

严重性：错误 (ERROR)

消息文本：找不到接口配置 (Interface configuration cannot be found)

消息说明：在进行旨在获取网络接口配置的系统调用时出现故障。

本地目标消息格式：<timestamp> <seq_num> 41038 ERROR Distributed-Management: Interface configuration cannot be found, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41038 ERROR Distributed-Management: Interface configuration cannot be found, <log details>

- 消息代码：41039

严重性：错误 (ERROR)

消息文本：找不到网络接口 eth0 (Network interface eth0 cannot be found)

消息说明：在进行旨在获取网络接口 eth0 配置的系统调用时出现故障，并且未找到接口。

本地目标消息格式：<timestamp> <seq_num> 41039 ERROR Distributed-Management: Network interface eth0 cannot be found, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41039 ERROR Distributed-Management: Network interface eth0 cannot be found, <log details>

- 消息代码：41040

严重性: 错误 (ERROR)

消息文本: 找不到网络接口 eth0 硬件地址 (Network interface eth0 hardware address cannot be found)

消息说明: 在进行旨在获取网络接口 eth0 配置硬件地址的系统调用时出现故障, 并且未找到硬件地址。

本地目标消息格式: <timestamp> <seq_num> 41040 ERROR Distributed-Management: Network interface eth0 hardware address cannot be found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41040 ERROR Distributed-Management: Network interface eth0 hardware address cannot be found, <log details>

• 消息代码: 41041

严重性: 错误 (ERROR)

消息文本: 找不到网络接口 eth0 inet 地址 (Network interface eth0 inet address cannot be found)

消息说明: 在进行旨在获取网络接口 eth0 配置 IP 地址的系统调用时出现故障, 并且未找到 IP 地址。

本地目标消息格式: <timestamp> <seq_num> 41041 ERROR Distributed-Management: Network interface eth0 inet address cannot be found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41041 ERROR Distributed-Management: Network interface eth0 inet address cannot be found, <log details>

• 消息代码: 41042

严重性: 错误 (ERROR)

消息文本: 找不到网络接口 eth0 掩码 (Network interface eth0 mask cannot be found)

消息说明: 在进行旨在获取网络接口 eth0 配置子网掩码的系统调用时出现故障, 并且未找到子网掩码。

本地目标消息格式: <timestamp> <seq_num> 41042 ERROR Distributed-Management: Network interface eth0 mask cannot be found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41042 ERROR Distributed-Management: Network interface eth0 mask cannot be found, <log details>

• 消息代码: 41043

严重性: 错误 (ERROR)

消息文本: 无法创建 ACSNodeInfo (Could not create ACSNodeInfo)

消息说明: 系统无法创建 AcsNodeInfo 记录并将其附加到 AcsNode 的实例记录。

本地目标消息格式: <timestamp> <seq_num> 41043 ERROR Distributed-Management: Could not create ACSNodeInfo, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 41043 ERROR Distributed-Management:
Could not create ACSNodeInfo, <log details>

- 消息代码: 41044

严重性: 错误 (ERROR)

消息文本: 无法在主节点中找到重新连接 Acs 实例, 请检查“Acs 主实例列表”(Primary Acs Instance Listing) 页面中是否存在 Acs 实例 (Failure to find the reconnection Acs Instance in the primary, please check that the Acs Instance exists in the Primary Acs Instance Listing page)

消息说明: 在硬件更换或 LocalMode 重新连接过程中, 无法找到具有指定更换关键字的 AcsNode 记录。默认情况下, 此关键字是系统的主机名。

本地目标消息格式: <timestamp> <seq_num> 41044 ERROR Distributed-Management: Failure to find the reconnection Acs Instance in the primary, please check that the Acs Instance exists in the Primary Acs Instance Listing page, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 41044 ERROR Distributed-Management:
Failure to find the reconnection Acs Instance in the primary, please check that the Acs Instance exists in the Primary Acs Instance Listing page, <log details>

- 消息代码: 41045

严重性: 错误 (ERROR)

消息文本: 失败。指定的更换关键字与注册的实例相关 (Failure. Specified replacement keyword is associated with a registered instance)

消息说明: 在硬件更换过程中, 指定的更换关键字与注册的 ISE 实例相关。

本地目标消息格式: <timestamp> <seq_num> 41045 ERROR Distributed-Management: Failure. Specified replacement keyword is associated with a registered instance, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 41045 ERROR Distributed-Management:
Failure. Specified replacement keyword is associated with a registered instance, <log details>

- 消息代码: 41046

严重性: 信息 (INFO)

消息文本: 正在注册到主节点 (Registering to Primary)

消息说明: ISE 实例正在注册到主节点。

本地目标消息格式: <timestamp> <seq_num> 41046 INFO Distributed-Management: Registering to Primary, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 41046 INFO Distributed-Management:
Registering to Primary, <log details>

- 消息代码: 41047

严重性: 信息 (INFO)

消息文本: 开始从主节点完全同步数据 (Initiate Full Sync of Data from Primary)

消息说明: 已经针对指定的 ISE 实例开始从主节点完全同步数据。

本地目标消息格式: <timestamp> <seq_num> 41047 INFO Distributed-Management: Initiate Full Sync of Data from Primary, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41047 INFO Distributed-Management: Initiate Full Sync of Data from Primary, <log details>

- 消息代码: 41048

严重性: 信息 (INFO)

消息文本: 已更换 ACSNode (ACSNode has been replaced)

消息说明: 已正确更换指定的 ISE 实例硬件。

本地目标消息格式: <timestamp> <seq_num> 41048 INFO Distributed-Management: ACSNode has been replaced, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41048 INFO Distributed-Management: ACSNode has been replaced, <log details>

- 消息代码: 41049

严重性: 信息 (INFO)

消息文本: 新 ACSNode 正在注册到主节点 (New ACSNode Registering to Primary)

消息说明: 新的 ISE 实例已注册到主节点。

本地目标消息格式: <timestamp> <seq_num> 41049 INFO Distributed-Management: New ACSNode Registering to Primary, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41049 INFO Distributed-Management: New ACSNode Registering to Primary, <log details>

- 消息代码: 41050

严重性: 信息 (INFO)

消息文本: 正在激活 ACSNode (Activating ACSNode)

消息说明: 正在主节点上激活指定的 ISE 实例。

本地目标消息格式: <timestamp> <seq_num> 41050 INFO Distributed-Management: Activating ACSNode, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41050 INFO Distributed-Management: Activating ACSNode, <log details>

- 消息代码: 41051
严重性: 信息 (INFO)
消息文本: 正在禁用 ACSNode (Deactivating ACSNode)
消息说明: 正在主节点上禁用指定的 ISE 实例。
本地目标消息格式: <timestamp> <seq_num> 41051 INFO Distributed-Management: Deactivating ACSNode, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41051 INFO Distributed-Management: Deactivating ACSNode, <log details>
- 消息代码: 41053
严重性: 信息 (INFO)
消息文本: 将节点升级为主节点 (Promote node to Primary)
消息说明: 正在将指定的 ISE 实例升级为部署的主节点。
本地目标消息格式: <timestamp> <seq_num> 41053 INFO Distributed-Management: Promote node to Primary, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41053 INFO Distributed-Management: Promote node to Primary, <log details>
- 消息代码: 41054
严重性: 信息 (INFO)
消息文本: 正在将辅助节点切换到本地模式操作 (Switching Secondary to Local Mode Operation)
消息说明: 指定的 ISE 实例正在切换到本地模式操作。
本地目标消息格式: <timestamp> <seq_num> 41054 INFO Distributed-Management: Switching Secondary to Local Mode Operation, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41054 INFO Distributed-Management: Switching Secondary to Local Mode Operation, <log details>
- 消息代码: 41055
严重性: 信息 (INFO)
消息文本: 正在将节点升级到新的软件版本 (Upgrading node to new software version)
消息说明: 指定的 ISE 实例正在升级到/通过修补升级到新的软件版本。
本地目标消息格式: <timestamp> <seq_num> 41055 INFO Distributed-Management: Upgrading node to new software version, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 41055 INFO Distributed-Management:
Upgrading node to new software version, <log details>

- 消息代码: 41056

严重性: 信息 (INFO)

消息文本: 应用升级 (Apply upgrade)

消息说明: 正在将软件升级应用到本地 ISE 实例。

本地目标消息格式: <timestamp> <seq_num> 41056 INFO Distributed-Management: Apply upgrade,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 41056 INFO Distributed-Management: Apply
upgrade, <log details>

- 消息代码: 41057

严重性: 信息 (INFO)

消息文本: 正在创建自动备份 (Automatic backup being created)

消息说明: 在应用升级或补丁的过程中正在备份系统。

本地目标消息格式: <timestamp> <seq_num> 41057 INFO Distributed-Management: Automatic
backup being created, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 41057 INFO Distributed-Management:
Automatic backup being created, <log details>

- 消息代码: 41058

严重性: 信息 (INFO)

消息文本: 正在为主节点托管下载捆绑包 (Downloading bundle for Primary hosting)

消息说明: 主节点正在从远程主机下载软件升级/补丁捆绑包, 以便将其托管在主节点上。

本地目标消息格式: <timestamp> <seq_num> 41058 INFO Distributed-Management: Downloading
bundle for Primary hosting, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 41058 INFO Distributed-Management:
Downloading bundle for Primary hosting, <log details>

- 消息代码: 41059

严重性: 信息 (INFO)

消息文本: 节点升级已完成 (Node upgrade completed)

消息说明: 在本地节点上已完成升级或补丁流程。

本地目标消息格式: <timestamp> <seq_num> 41059 INFO Distributed-Management: Node upgrade completed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41059 INFO Distributed-Management: Node upgrade completed, <log details>

- 消息代码: 41060

严重性: 信息 (INFO)

消息文本: 正在启用日志收集器目标 (Enabling Log Collector Target)

消息说明: 正在为 ISE 部署启用日志收集器目标。启用后, 部署中每个实例的远程日志记录将被发送到收集器。

本地目标消息格式: <timestamp> <seq_num> 41060 INFO Distributed-Management: Enabling Log Collector Target, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41060 INFO Distributed-Management: Enabling Log Collector Target, <log details>

- 消息代码: 41061

严重性: 信息 (INFO)

消息文本: 正在禁用日志收集器目标 (Disabling Log Collector Target)

消息说明: 正在为 ISE 部署禁用日志收集器目标。在重新启用之前, 到日志收集器的远程日志记录将停止。

本地目标消息格式: <timestamp> <seq_num> 41061 INFO Distributed-Management: Disabling Log Collector Target, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41061 INFO Distributed-Management: Disabling Log Collector Target, <log details>

- 消息代码: 41062

严重性: 信息 (INFO)

消息文本: 选择日志收集器节点 (Select the Log Collector Node)

消息说明: 已为部署选择日志收集器 ISE 实例。启用日志收集器后, 远程日志记录将显示在收集器上。

本地目标消息格式: <timestamp> <seq_num> 41062 INFO Distributed-Management: Select the Log Collector Node, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41062 INFO Distributed-Management: Select the Log Collector Node, <log details>

- 消息代码: 41063

严重性: 信息 (INFO)

消息文本: 已为日志收集器创建远程系统日志目标 (Remote Syslog Target for Log Collector has been created)

消息说明: 已为日志收集器创建远程系统日志目标, 到日志收集器的远程日志记录将开始。

本地目标消息格式: <timestamp> <seq_num> 41063 INFO Distributed-Management: Remote Syslog Target for Log Collector has been created, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41063 INFO Distributed-Management: Remote Syslog Target for Log Collector has been created, <log details>

- 消息代码: 41064

严重性: 错误 (ERROR)

消息文本: 无法撤销注册部署日志收集器 (The deployment Log Collector cannot be deregistered)

消息说明: 部署中不能不配置日志收集器。撤销注册此节点将删除选定的日志收集器。

本地目标消息格式: <timestamp> <seq_num> 41064 ERROR Distributed-Management: The deployment Log Collector cannot be deregistered, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41064 ERROR Distributed-Management: The deployment Log Collector cannot be deregistered, <log details>

- 消息代码: 41065

严重性: 信息 (INFO)

消息文本: 应用升级诊断消息 (Apply upgrade diagnostic messages)

消息说明: 应用升级诊断消息

本地目标消息格式: <timestamp> <seq_num> 41065 INFO Distributed-Management: Apply upgrade diagnostic messages, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 41065 INFO Distributed-Management: Apply upgrade diagnostic messages, <log details>

外部 MDM

- 消息代码: 89000

严重性: 信息 (INFO)

消息文本: 未注册移动设备管理器 (Mobile device manager unregistered)

消息说明: 未使用移动设备管理器对设备进行注册

本地目标消息格式: <timestamp> <seq_num> 89000 INFO MDM: Mabile device manager unregistered, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89000 INFO MDM: Mabile device manager unregistered, <log details>

- 消息代码: 89001

严重性: 信息 (INFO)

消息文本: 与移动设备管理兼容 (Mobile device management compliant)

消息说明: 设备与移动设备管理兼容

本地目标消息格式: <timestamp> <seq_num> 89001 INFO MDM: Mobile device management compliant, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89001 INFO MDM: Mobile device management compliant, <log details>

- 消息代码: 89002

严重性: 信息 (INFO)

消息文本: 与移动设备管理不兼容 (Mobile device management non-compliant)

消息说明: 设备与移动设备管理不兼容

本地目标消息格式: <timestamp> <seq_num> 89002 INFO MDM: Mobile device management non-compliant, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89002 INFO MDM: Mobile device management non-compliant, <log details>

- 消息代码: 89003

严重性: 警告 (WARN)

消息文本: 无法连接到 MDM 服务器 (Failed to connect to MDM server)

消息说明: 无法连接到 MDM 服务器

本地目标消息格式: <timestamp> <seq_num> 89003 WARN MDM: Failed to connect to MDM server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89003 WARN MDM: Failed to connect to MDM server, <log details>

- 消息代码: 89004

严重性: 错误 (ERROR)

消息文本: MDM 服务器 API 版本不匹配 (MDM server API version mismatch)

消息说明: MDM 服务器 API 版本与 ISE 中配置的版本不匹配

本地目标消息格式: <timestamp> <seq_num> 89004 ERROR MDM: MDM server API version mismatch, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89004 ERROR MDM: MDM server API version mismatch, <log details>

- 消息代码: 89005

严重性: 警告 (WARN)

消息文本: MDM 服务器响应错误 (MDM server response error)

消息说明: MDM 服务器响应错误

本地目标消息格式: <timestamp> <seq_num> 89005 WARN MDM: MDM server response error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89005 WARN MDM: MDM server response error, <log details>

失败尝试

- 消息代码: 5400

严重性: 通知 (NOTICE)

消息文本: 身份验证失败 (Authentication failed)

消息说明: 用户身份验证失败。查看失败原因可了解更多信息

本地目标消息格式: <timestamp> <seq_num> 5400 NOTICE Failed-Attempt: Authentication failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5400 NOTICE Failed-Attempt: Authentication failed, <log details>

- 消息代码: 5401

严重性: 通知 (NOTICE)

消息文本: 身份验证失败 (Authentication failed)

消息说明: 用户身份验证失败。查看失败原因可了解更多信息

本地目标消息格式: <timestamp> <seq_num> 5401 NOTICE Failed-Attempt: Authentication failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5401 NOTICE Failed-Attempt: Authentication failed, <log details>

- 消息代码: 5402
严重性: 通知 (NOTICE)
消息文本: 命令授权失败 (Command Authorization failed)
消息说明: 命令授权失败
本地目标消息格式: <timestamp> <seq_num> 5402 NOTICE Failed-Attempt: Command Authorization failed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5402 NOTICE Failed-Attempt: Command Authorization failed, <log details>
- 消息代码: 5403
严重性: 通知 (NOTICE)
消息文本: 会话授权失败 (Session Authorization failed)
消息说明: 会话授权失败
本地目标消息格式: <timestamp> <seq_num> 5403 NOTICE Device-Administration: Session Authorization failed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5403 NOTICE Device-Administration: Session Authorization failed, <log details>
- 消息代码: 5404
严重性: 通知 (NOTICE)
消息文本: 授权失败 (Authorization failed)
消息说明: 授权失败
本地目标消息格式: <timestamp> <seq_num> 5404 NOTICE Device-Administration: Authorization failed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5404 NOTICE Device-Administration: Authorization failed, <log details>
- 消息代码: 5405
严重性: 通知 (NOTICE)
消息文本: 已丢弃 RADIUS 请求 (RADIUS Request dropped)
消息说明: 已丢弃 RADIUS 请求
本地目标消息格式: <timestamp> <seq_num> 5405 NOTICE Failed-Attempt: RADIUS Request dropped, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 5405 NOTICE Failed-Attempt: RADIUS
Request dropped, <log details>

- 消息代码: 5406

严重性: 通知 (NOTICE)

消息文本: 已丢弃 TACACS+ 请求 (TACACS+ Request dropped)

消息说明: 已丢弃 TACACS+ 请求

本地目标消息格式: <timestamp> <seq_num> 5406 NOTICE Failed-Attempt: TACACS+ Request
dropped, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 5406 NOTICE Failed-Attempt: TACACS+
Request dropped, <log details>

- 消息代码: 5407

严重性: 通知 (NOTICE)

消息文本: TACACS+ 授权失败 (TACACS+ Authorization failed)

消息说明: TACACS+ 授权失败

本地目标消息格式: <timestamp> <seq_num> 5407 NOTICE Failed-Attempt: TACACS+ Authorization
failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 5407 NOTICE Failed-Attempt: TACACS+
Authorization failed, <log details>

- 消息代码: 5408

严重性: 通知 (NOTICE)

消息文本: 命令授权出错 (Command Authorization encountered an error)

消息说明: 命令授权出错。查看失败原因可了解更多信息

本地目标消息格式: <timestamp> <seq_num> 5408 NOTICE Failed-Attempt: Command Authorization
encountered an error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 5408 NOTICE Failed-Attempt: Command
Authorization encountered an error, <log details>

- 消息代码: 5409

严重性: 通知 (NOTICE)

消息文本: 会话授权出错 (Session Authorization encountered an error)

消息说明: 会话授权出错。查看失败原因可了解更多信息

本地目标消息格式: <timestamp> <seq_num> 5409 NOTICE Failed-Attempt: Session Authorization encountered an error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5409 NOTICE Failed-Attempt: Session Authorization encountered an error, <log details>

- 消息代码: 5410

严重性: 通知 (NOTICE)

消息文本: TACACS+ 授权出错 (TACACS+ Authorization encountered an error)

消息说明: TACACS+ 授权出错

本地目标消息格式: <timestamp> <seq_num> 5410 NOTICE Failed-Attempt: TACACS+ Authorization encountered an error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5410 NOTICE Failed-Attempt: TACACS+ Authorization encountered an error, <log details>

- 消息代码: 5411

严重性: 通知 (NOTICE)

消息文本: 请求方停止响应 ISE (Supplicant stopped responding to ISE)

消息说明: 请求方未响应 ISE 发送给它的最后一条信息

本地目标消息格式: <timestamp> <seq_num> 5411 NOTICE Failed-Attempt: Supplicant stopped responding to ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5411 NOTICE Failed-Attempt: Supplicant stopped responding to ISE, <log details>

- 消息代码: 5412

严重性: 通知 (NOTICE)

消息文本: TACACS+ 身份验证请求结束, 但遇到错误 (TACACS+ authentication request ended with error)

消息说明: TACACS+ 身份验证请求结束, 但遇到错误

本地目标消息格式: <timestamp> <seq_num> 5412 NOTICE Failed-Attempt: TACACS+ authentication request ended with error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5412 NOTICE Failed-Attempt: TACACS+ authentication request ended with error, <log details>

- 消息代码: 5413

严重性: 通知 (NOTICE)

消息文本: 已丢弃 RADIUS 记帐请求 (RADIUS Accounting-Request dropped)

消息说明: 已丢弃 RADIUS 记帐请求。

本地目标消息格式: <timestamp> <seq_num> 5413 NOTICE Failed-Attempt: RADIUS Accounting-Request dropped, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5413 NOTICE Failed-Attempt: RADIUS Accounting-Request dropped, <log details>

• 消息代码: 5414

严重性: 通知 (NOTICE)

消息文本: TACACS+ 记帐失败 (TACACS+ accounting has failed)

消息说明: TACACS+ 记帐失败。查看失败原因记录可了解更多信息。

本地目标消息格式: <timestamp> <seq_num> 5414 NOTICE Failed-Attempt: TACACS+ accounting has failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5414 NOTICE Failed-Attempt: TACACS+ accounting has failed, <log details>

• 消息代码: 5415

严重性: 通知 (NOTICE)

消息文本: 更改密码失败 (Change password failed)

消息说明: 用户更改密码失败。查看失败原因可了解更多信息。

本地目标消息格式: <timestamp> <seq_num> 5415 NOTICE Failed-Attempt: Change password failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5415 NOTICE Failed-Attempt: Change password failed, <log details>

• 消息代码: 5416

严重性: 通知 (NOTICE)

消息文本: 已清理 RADIUS PAP 会话 (RADIUS PAP session cleaned up)

消息说明: 已清理 RADIUS PAP 会话

本地目标消息格式: <timestamp> <seq_num> 5416 NOTICE Failed-Attempt: RADIUS PAP session cleaned up, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5416 NOTICE Failed-Attempt: RADIUS PAP session cleaned up, <log details>

• 消息代码: 5417

严重性: 通知 (NOTICE)

消息文本: 动态授权失败 (Dynamic Authorization failed)

消息说明: 动态授权失败

本地目标消息格式: <timestamp> <seq_num> 5417 NOTICE Dynamic-Authorization: Dynamic Authorization failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5417 NOTICE Dynamic-Authorization: Dynamic Authorization failed, <log details>

- 消息代码: 5418

严重性: 通知 (NOTICE)

消息文本: 访客身份验证失败 (Guest Authentication Failed)

消息说明: 访客身份验证失败; 有关详细信息, 请查看失败代码

本地目标消息格式: <timestamp> <seq_num> 5418 NOTICE Guest: Guest Authentication Failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5418 NOTICE Guest: Guest Authentication Failed, <log details>

- 消息代码: 5419

严重性: 通知 (NOTICE)

消息文本: DACL 下载失败 (DACL Download Failed)

消息说明: DACL 下载失败

本地目标消息格式: <timestamp> <seq_num> 5419 NOTICE Failed-Attempt: DACL Download Failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5419 NOTICE Failed-Attempt: DACL Download Failed, <log details>

- 消息代码: 5420

严重性: 通知 (NOTICE)

消息文本: TrustSec 数据下载失败 (TrustSec Data Download Failed)

消息说明: TrustSec 数据下载失败

本地目标消息格式: <timestamp> <seq_num> 5420 NOTICE Failed-Attempt: TrustSec Data Download Failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5420 NOTICE Failed-Attempt: TrustSec Data Download Failed, <log details>

- 消息代码: 5421
严重性: 通知 (NOTICE)
消息文本: TrustSec 对等策略下载失败 (TrustSec Peer Policy Download Failed)
消息说明: TrustSec 对等策略下载失败
本地目标消息格式: <timestamp> <seq_num> 5421 NOTICE Failed-Attempt: TrustSec Peer Policy Download Failed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5421 NOTICE Failed-Attempt: TrustSec Peer Policy Download Failed, <log details>
- 消息代码: 5422
严重性: 通知 (NOTICE)
消息文本: 仅授权失败 (Authorize-Only failed)
消息说明: 仅授权失败。查看失败原因可了解更多信息
本地目标消息格式: <timestamp> <seq_num> 5422 NOTICE Failed-Attempt: Authorize-Only failed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5422 NOTICE Failed-Attempt: Authorize-Only failed, <log details>
- 消息代码: 5423
严重性: 通知 (NOTICE)
消息文本: 设备注册 Web 身份验证失败 (Device Registration Web Authentication Failed)
消息说明: 设备注册 Web 身份验证失败
本地目标消息格式: <timestamp> <seq_num> 5423 NOTICE Guest: Device Registration Web Authentication Failed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5423 NOTICE Guest: Device Registration Web Authentication Failed, <log details>
- 消息代码: 5434
严重性: 警告 (WARN)
消息文本: 终端在同一场景执行了多次失败的身份验证 (Endpoint conducted several failed authentications of the same scenario)
消息说明: 终端在同一场景执行了多次失败的身份验证
本地目标消息格式: <timestamp> <seq_num> 5434 WARN RADIUS: Endpoint conducted several failed authentications of the same scenario, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 5434 WARN RADIUS: Endpoint conducted several failed authentications of the same scenario, <log details>

- 消息代码: 5435

严重性: 警告 (WARN)

消息文本: NAS 在同一场景执行了多次失败的身份验证 (NAS conducted several failed authentications of the same scenario)

消息说明: NAS 在同一场景执行了多次失败的身份验证

本地目标消息格式: <timestamp> <seq_num> 5435 WARN RADIUS: NAS conducted several failed authentications of the same scenario, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 5435 WARN RADIUS: NAS conducted several failed authentications of the same scenario, <log details>

- 消息代码: 5436

严重性: 警告 (WARN)

消息文本: RADIUS 数据包已在处理中 (RADIUS packet already in the process)

消息说明: 忽略此请求, 因为它与当前正在处理的其他数据包重复

本地目标消息格式: <timestamp> <seq_num> 5436 WARN RADIUS: RADIUS packet already in the process, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 5436 WARN RADIUS: RADIUS packet already in the process, <log details>

- 消息代码: 5437

严重性: 警告 (WARN)

消息文本: 现有会话的 RADIUS 数据包重复, 但 RADIUS 参数不同 (Duplicate RADIUS packet for existing session but with different RADIUS parameters)

消息说明: 检测到已处理的数据包或已接受的数据包有重复 RADIUS 请求, 但此次请求至少有一个不同的参数 (源 IP、源端口、RADIUS ID)。正在丢弃。可能是意外的 NAD 行为。

本地目标消息格式: <timestamp> <seq_num> 5437 WARN RADIUS: Duplicate RADIUS packet for existing session but with different RADIUS parameters, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 5437 WARN RADIUS: Duplicate RADIUS packet for existing session but with different RADIUS parameters, <log details>

- 消息代码: 5438

严重性: 警告 (WARN)

消息文本: RADIUS 数据包包含此 PSN 上不存在的会话 (RADIUS packet contains session on this PSN that does not exist)

消息说明: 未在此 ISE 上找到会话。可能是意外的 NAD 行为。根据主机名, 会话属于此 ISE, 但可能已因超时被删除。此数据包到达时间过迟。

本地目标消息格式: <timestamp> <seq_num> 5438 WARN RADIUS: RADIUS packet contains session on this PSN that does not exist, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5438 WARN RADIUS: RADIUS packet contains session on this PSN that does not exist, <log details>

- 消息代码: 5439

严重性: 警告 (WARN)

消息文本: RADIUS 数据包包含此 PSN 上未开始的会话 (RADIUS packet contains session not started on this PSN)

消息说明: 根据主机名, 会话不属于此 ISE。可能是意外的 NAD 行为。NAD 可能在与其他 ISE 开展会话的中途发送了数据包。

本地目标消息格式: <timestamp> <seq_num> 5439 WARN RADIUS: RADIUS packet contains session not started on this PSN, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5439 WARN RADIUS: RADIUS packet contains session not started on this PSN, <log details>

- 消息代码: 5440

严重性: 警告 (WARN)

消息文本: 终端放弃 EAP 会话并开始了新会话 (Endpoint abandoned EAP session and started new)

消息说明: 终端开始了新的身份验证, 而前一身份验证仍在进行。最可能的原因是, 该终端上的请求方已停止执行前一身份验证, 并开始了新的身份验证。正在关闭前一身份验证。

本地目标消息格式: <timestamp> <seq_num> 5440 WARN RADIUS: Endpoint abandoned EAP session and started new, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5440 WARN RADIUS: Endpoint abandoned EAP session and started new, <log details>

- 消息代码: 5441

严重性: 警告 (WARN)

消息文本: 处理前一会话的数据包时, 终端开始了新会话。(Endpoint started new session while the packet of previous session is being processed.) 正在丢弃新会话。

消息说明: 处理前一会话的数据包时, 终端开始了新会话

本地目标消息格式: <timestamp> <seq_num> 5441 WARN RADIUS: Endpoint started new session while the packet of previous session is being processed. Dropping new session., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5441 WARN RADIUS: Endpoint started new session while the packet of previous session is being processed. Dropping new session., <log details>

- 消息代码: 5442

严重性: 警告 (WARN)

消息文本: 由于系统过载, 已丢弃 RADIUS 请求 (RADIUS request dropped due to system overload)

消息说明: 由于系统过载, 已丢弃 RADIUS 请求。此情况可能是由并行身份验证请求过多导致。

本地目标消息格式: <timestamp> <seq_num> 5442 WARN RADIUS: RADIUS request dropped due to system overload, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5442 WARN RADIUS: RADIUS request dropped due to system overload, <log details>

- 消息代码: 5443

严重性: 警告 (WARN)

消息文本: 由于达到 EAP 会话限制, 已丢弃 RADIUS 请求 (RADIUS request dropped due to reaching EAP sessions limit)

消息说明: 由于达到 EAP 会话限制, 已丢弃 RADIUS 请求。此情况可能是由并行 EAP 身份验证请求过多导致。

本地目标消息格式: <timestamp> <seq_num> 5443 WARN RADIUS: RADIUS request dropped due to reaching EAP sessions limit, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5443 WARN RADIUS: RADIUS request dropped due to reaching EAP sessions limit, <log details>

- 消息代码: 5447

严重性: 通知 (NOTICE)

消息文本: 已通过 MDM 身份验证 (MDM Authentication Passed)

消息说明: 已通过 MDM 身份验证

本地目标消息格式: <timestamp> <seq_num> 5447 NOTICE MDM: MDM Authentication Passed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5447 NOTICE MDM: MDM Authentication Passed, <log details>

- 消息代码: 5448

严重性: 通知 (NOTICE)

消息文本: MDM 身份验证失败 (MDM Authentication failed)

消息说明: MDM 身份验证失败; 有关详细信息, 请查看失败代码

本地目标消息格式: <timestamp> <seq_num> 5448 NOTICE MDM: MDM Authentication Failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5448 NOTICE MDM: MDM Authentication Failed, <log details>

- 消息代码: 5449

严重性: 警告 (WARN)

消息文本: 终端对同一场景的身份验证多次失败, 并被拒绝 (Endpoint failed authentication of the same scenario several times and was rejected)

消息说明: 终端对同一场景的身份验证多次失败, 并且所有后续请求将在请求拒绝间隔期间被拒绝

本地目标消息格式: <timestamp> <seq_num> 5449 WARN RADIUS: Endpoint failed authentication of the same scenario several times and was rejected, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5449 WARN RADIUS: Endpoint failed authentication of the same scenario several times and was rejected, <log details>

- 消息代码: 5450

严重性: 通知 (NOTICE)

消息文本: RADIUS DTLS 握手失败 (RADIUS DTLS handshake failed)

消息说明: RADIUS DTLS 握手失败

本地目标消息格式: <timestamp> <seq_num> 5450 NOTICE Failed-Attempt: RADIUS DTLS handshake failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5450 NOTICE Failed-Attempt: RADIUS DTLS handshake failed, <log details>

- 消息代码: 5451

严重性: 信息 (INFO)

消息文本: 社交登录: 用户未向 ISE 应用授予从 Facebook 读取用户信息的权限 (Social Login: User did not grant permission for ISE application to read user's information from Facebook)

消息说明: 表示用户未向 ISE 应用授予从 Facebook 读取用户信息的权限

本地目标消息格式: <timestamp> <seq_num> 5451 INFO GUEST: Social Login: User did not grant permission for ISE application to read user's information from Facebook, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 5451 INFO GUEST: Social Login: User did not grant permission for ISE application to read user's information from Facebook, <log details>

- 消息代码: 5452

严重性: 警告 (WARN)

消息文本: 社交登录: 获取社交用户信息时出错 (Social Login: Error while getting Social User info)

消息说明: 表示获取社交用户信息时出错

本地目标消息格式: <timestamp> <seq_num> 5452 WARN GUEST: Social Login: Error while getting Social User info, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 5452 WARN GUEST: Social Login: Error while getting Social User info, <log details>

访客

- 消息代码: 86001

严重性: 信息 (INFO)

消息文本: 访客用户已进入访客门户登录页 (Guest user has entered the guest portal login page)

消息说明: 访客用户已进入访客门户登录页

本地目标消息格式: <timestamp> <seq_num> 86001 INFO Guest: Guest user has entered the guest portal login page, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 86001 INFO Guest: Guest user has entered the guest portal login page, <log details>

- 消息代码: 86002

严重性: 信息 (INFO)

消息文本: 发起人已暂停访客用户帐户 (Sponsor has suspended a guest user account)

消息说明: 发起人已暂停访客用户帐户

本地目标消息格式: <timestamp> <seq_num> 86002 INFO Guest: Sponsor has suspended a guest user account, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 86002 INFO Guest: Sponsor has suspended a guest user account, <log details>

- 消息代码: 86003

严重性: 信息 (INFO)

消息文本: 发起人已启用访客用户帐户 (Sponsor has enabled a guest user account)

消息说明: 发起人已启用访客用户帐户

本地目标消息格式: <timestamp> <seq_num> 86003 INFO Guest: Sponsor has enabled a guest user account, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 86003 INFO Guest: Sponsor has enabled a guest user account, <log details>

- 消息代码: 86004

严重性: 信息 (INFO)

消息文本: 访客用户已更改密码 (Guest user has changed the password)

消息说明: 访客用户已更改密码

本地目标消息格式: <timestamp> <seq_num> 86004 INFO Guest: Guest user has changed the password, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 86004 INFO Guest: Guest user has changed the password, <log details>

- 消息代码: 86005

严重性: 信息 (INFO)

消息文本: 访客用户已接受使用政策 (Guest user has accepted the Use Policy)

消息说明: 访客用户已接受使用政策

本地目标消息格式: <timestamp> <seq_num> 86005 INFO Guest: Guest user has accepted the Use Policy, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 86005 INFO Guest: Guest user has accepted the Use Policy, <log details>

- 消息代码: 86006

严重性: 信息 (INFO)

消息文本: 已创建访客用户帐户 (Guest user account is created)

消息说明: 已创建访客用户帐户

本地目标消息格式: <timestamp> <seq_num> 86006 INFO Guest: Guest user account is created, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 86006 INFO Guest: Guest user account is created, <log details>

- 消息代码: 86007

严重性: 信息 (INFO)

消息文本: 已更新访客用户帐户 (Guest user account is updated)

消息说明: 已更新访客用户帐户

本地目标消息格式: <timestamp> <seq_num> 86007 INFO Guest: Guest user account is updated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 86007 INFO Guest: Guest user account is updated, <log details>

- 消息代码: 86008

严重性: 信息 (INFO)

消息文本: 已删除访客用户帐户 (Guest user account is deleted)

消息说明: 已删除访客用户帐户

本地目标消息格式: <timestamp> <seq_num> 86008 INFO Guest: Guest user account is deleted, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 86008 INFO Guest: Guest user account is deleted, <log details>

- 消息代码: 86009

严重性: 信息 (INFO)

消息文本: 未找到访客用户 (Guest user is not found)

消息说明: 未在数据库中找到访客用户记录

本地目标消息格式: <timestamp> <seq_num> 86009 INFO Guest: Guest user is not found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 86009 INFO Guest: Guest user is not found, <log details>

- 消息代码: 86010

严重性: 信息 (INFO)

消息文本: 访客用户身份验证失败 (Guest user authentication failed)

消息说明: 访客用户身份验证失败。请检查您的密码和帐户权限

本地目标消息格式: <timestamp> <seq_num> 86010 INFO Guest: Guest user authentication failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 86010 INFO Guest: Guest user authentication failed, <log details>

- 消息代码: 86011
 - 严重性: 信息 (INFO)
 - 消息文本: 未启用访客用户 (Guest user is not enabled)
 - 消息说明: 访客用户身份验证失败。未启用用户。请与您的系统管理员联系
 - 本地目标消息格式: <timestamp> <seq_num> 86011 INFO Guest: Guest user is not enabled, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 86011 INFO Guest: Guest user is not enabled, <log details>

- 消息代码: 86012
 - 严重性: 信息 (INFO)
 - 消息文本: 用户拒绝了“访问-使用”策略 (User declined Access-Use Policy)
 - 消息说明: 访客用户必须先接受“访问-使用”策略, 之后才能被授予网络访问权限
 - 本地目标消息格式: <timestamp> <seq_num> 86012 INFO Guest: User declined Access-Use Policy, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 86012 INFO Guest: User declined Access-Use Policy, <log details>

- 消息代码: 86013
 - 严重性: 信息 (INFO)
 - 消息文本: 找不到门户 (Portal not found)
 - 消息说明: 未在数据库中找到门户。请与您的系统管理员联系
 - 本地目标消息格式: <timestamp> <seq_num> 86013 INFO Guest: Portal not found, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 86013 INFO Guest: Portal not found, <log details>

- 消息代码: 86014
 - 严重性: 信息 (INFO)
 - 消息文本: 用户已暂停 (User is suspended)
 - 消息说明: 用户身份验证失败。用户帐户已暂停
 - 本地目标消息格式: <timestamp> <seq_num> 86014 INFO Guest: User is suspended, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 86014 INFO Guest: User is suspended, <log details>

- 消息代码: 86015
 - 严重性: 信息 (INFO)
 - 消息文本: 密码更改无效 (Invalid Password Change)
 - 消息说明: 密码更改无效。使用符合密码策略的正确密码
 - 本地目标消息格式: <timestamp> <seq_num> 86015 INFO Guest: Invalid Password Change, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 86015 INFO Guest: Invalid Password Change, <log details>

- 消息代码: 86016
 - 严重性: 信息 (INFO)
 - 消息文本: 已超出访客超时设置 (Guest Timeout Exceeded)
 - 消息说明: 服务器超时已超过阈值。请与您的系统管理员联系
 - 本地目标消息格式: <timestamp> <seq_num> 86016 INFO Guest: Guest Timeout Exceeded, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 86016 INFO Guest: Guest Timeout Exceeded, <log details>

- 消息代码: 86017
 - 严重性: 信息 (INFO)
 - 消息文本: 缺少会话 (Session Missing)
 - 消息说明: 缺少 SessionID。请与您的系统管理员联系
 - 本地目标消息格式: <timestamp> <seq_num> 86017 INFO Guest: Session Missing, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 86017 INFO Guest: Session Missing, <log details>

- 消息代码: 86018
 - 严重性: 信息 (INFO)
 - 消息文本: 访客授权更改失败 (Guest Change of Authorization Failed)
 - 消息说明: 访客授权更改失败。请与您的系统管理员联系
 - 本地目标消息格式: <timestamp> <seq_num> 86018 INFO Guest: Guest Change of Authorization Failed, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 86018 INFO Guest: Guest Change of Authorization Failed, <log details>

- 消息代码: 86019
严重性: 信息 (INFO)
消息文本: 已限制访客用户 (Guest User restricted)
消息说明: 已根据时间配置文件限制用户访问。请与您的系统管理员联系
本地目标消息格式: <timestamp> <seq_num> 86019 INFO Guest: Guest User restricted, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 86019 INFO Guest: Guest User restricted,
<log details>
- 消息代码: 86020
严重性: 信息 (INFO)
消息文本: 访客未知错误 (Guest Unknown Error)
消息说明: 用户身份验证失败。请与您的系统管理员联系
本地目标消息格式: <timestamp> <seq_num> 86020 INFO Guest: Guest Unknown Error, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 86020 INFO Guest: Guest Unknown Error,
<log details>
- 消息代码: 86021
严重性: 信息 (INFO)
消息文本: 正在进入设备注册 Web 身份验证门户 (Entering Device Registration Web Authentication Portal)
消息说明: 正在进入设备注册 Web 身份验证门户
本地目标消息格式: <timestamp> <seq_num> 86021 INFO Guest: Entering Device Registration Web Authentication Portal, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 86021 INFO Guest: Entering Device Registration Web Authentication Portal, <log details>
- 消息代码: 86022
严重性: 信息 (INFO)
消息文本: 已接受设备注册 Web 身份验证 AUP (Device Registration Web Authentication AUP Accepted)
消息说明: 已接受设备注册 Web 身份验证 AUP (可接受使用政策)
本地目标消息格式: <timestamp> <seq_num> 86022 INFO Guest: Device Registration Web Authentication AUP Accepted, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num> 86022 INFO Guest: Device Registration
Web Authentication AUP Accepted, <log details>

- 消息代码: 86023

严重性: 信息 (INFO)

消息文本: 已拒绝设备注册 Web 身份验证 AUP (Device Registration Web Authentication AUP Declined)

消息说明: 已拒绝设备注册 Web 身份验证 AUP (可接受使用政策)

本地目标消息格式: <timestamp> <seq_num> 86023 INFO Guest: Device Registration Web
Authentication AUP Declined, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num> 86023 INFO Guest: Device Registration
Web Authentication AUP Declined, <log details>

- 消息代码: 86024

严重性: 信息 (INFO)

消息文本: 设备注册 Web 身份验证门户创建终端成功 (Device Registration Web Authentication
Portal Endpoint Creation Passed)

消息说明: 设备注册 Web 身份验证门户已成功创建终端

本地目标消息格式: <timestamp> <seq_num> 86024 INFO Guest: Device Registration Web
Authentication Portal Endpoint Creation Passed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num> 86024 INFO Guest: Device Registration
Web Authentication Portal Endpoint Creation Passed, <log details>

- 消息代码: 86025

严重性: 错误 (ERROR)

消息文本: 设备注册 Web 身份验证门户创建终端失败 (Device Registration Web Authentication
Portal Endpoint Creation failed)

消息说明: 设备注册 Web 身份验证门户未能创建终端

本地目标消息格式: <timestamp> <seq_num> 86025 ERROR Guest: Device Registration Web
Authentication Portal Endpoint Creation Failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num> 86025 ERROR Guest: Device Registration
Web Authentication Portal Endpoint Creation Failed, <log details>

- 消息代码: 86026

严重性: 错误 (ERROR)

消息文本: 设备注册 Web 身份验证门户 CoA 终止失败 (Device Registration Web Authentication Portal CoA Termination Failed)

消息说明: 设备注册 Web 身份验证门户未能执行 CoA 终止

本地目标消息格式: <timestamp> <seq_num> 86026 ERROR Guest: Device Registration Web Authentication Portal CoA Termination Failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 86026 ERROR Guest: Device Registration Web Authentication Portal CoA Termination Failed, <log details>

- 消息代码: 86027

严重性: 信息 (INFO)

消息文本: 设备注册 Web 身份验证正在发送 CoA 终止消息 (Device Registration Web Authentication sending CoA Termination message)

消息说明: 设备注册 Web 身份验证正在发送 CoA 终止消息

本地目标消息格式: <timestamp> <seq_num> 86027 INFO Guest: Device Registration Web Authentication sending CoA Termination message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 86027 INFO Guest: Device Registration Web Authentication sending CoA Termination message, <log details>

- 消息代码: 86028

严重性: 信息 (INFO)

消息文本: 已成功为删除的访客或暂停的访客执行 CoA 终止 (Successfully performed CoA termination(s) for a deleted guest or a suspended guest)

消息说明: 已成功为删除的访客或暂停的访客执行 CoA 终止

本地目标消息格式: <timestamp> <seq_num> 86028 INFO Guest: Successfully performed CoA termination(s) for a deleted guest or a suspended guest, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 86028 INFO Guest: Successfully performed CoA termination(s) for a deleted guest or a suspended guest, <log details>

- 消息代码: 86029

严重性: 警告 (WARN)

消息文本: 无法执行 CoA 终止 (Failed to perform a CoA termination)

消息说明: 无法执行 CoA 终止

本地目标消息格式: <timestamp> <seq_num> 86029 WARN Guest: Failed to perform a CoA termination, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 86029 WARN Guest: Failed to perform a
CoA termination, <log details>

- 消息代码: 86030

严重性: 信息 (INFO)

消息文本: 发起人用户已接受用户政策 (Sponsor user accepted the user policy)

消息说明: 表示发起人用户已接受用户政策

本地目标消息格式: <timestamp> <seq_num> 86030 INFO GUEST: Sponsor user accepted the user
policy, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 86030 INFO GUEST: Sponsor user accepted
the user policy, <log details>

- 消息代码: 86031

严重性: 信息 (INFO)

消息文本: 发起人用户已拒绝用户政策 (Sponsor user declined the user policy)

消息说明: 表示发起人用户已拒绝用户政策

本地目标消息格式: <timestamp> <seq_num> 86031 INFO GUEST: Sponsor user declined the user
policy, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 86031 INFO GUEST: Sponsor user declined
the user policy, <log details>

身份存储库诊断

- 消息代码: 24000

严重性: 信息 (INFO)

消息文本: 已与 LDAP 服务器建立连接 (Connection established with LDAP server)

消息说明: 已与 LDAP 服务器建立连接

本地目标消息格式: <timestamp> <seq_num> 24000 INFO External-LDAP: Connection established
with LDAP server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24000 INFO External-LDAP: Connection
established with LDAP server, <log details>

- 消息代码: 24001

严重性: 错误 (ERROR)

消息文本: 无法与 LDAP 服务器建立连接 (Cannot establish connection with LDAP server)

消息说明: 无法与 LDAP 服务器建立连接

本地目标消息格式: <timestamp> <seq_num> 24001 ERROR External-LDAP: Cannot establish connection with LDAP server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24001 ERROR External-LDAP: Cannot establish connection with LDAP server, <log details>

- 消息代码: 24002

严重性: 错误 (ERROR)

消息文本: 无法与管理员凭证绑定连接 (Cannot bind connection with administrator credentials)

消息说明: 无法与管理员凭证绑定连接

本地目标消息格式: <timestamp> <seq_num> 24002 ERROR External-LDAP: Cannot bind connection with administrator credentials, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24002 ERROR External-LDAP: Cannot bind connection with administrator credentials, <log details>

- 消息代码: 24003

严重性: 错误 (ERROR)

消息文本: 无法与匿名凭证绑定连接 (Cannot bind connection with anonymous credentials)

消息说明: 无法与匿名凭证绑定连接

本地目标消息格式: <timestamp> <seq_num> 24003 ERROR External-LDAP: Cannot bind connection with anonymous credentials, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24003 ERROR External-LDAP: Cannot bind connection with anonymous credentials, <log details>

- 消息代码: 24004

严重性: 调试 (DEBUG)

消息文本: 已成功完成用户搜索 (User search finished successfully)

消息说明: 已成功完成在 LDAP 服务器中的用户搜索

本地目标消息格式: <timestamp> <seq_num> 24004 DEBUG External-LDAP: User search finished successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24004 DEBUG External-LDAP: User search finished successfully, <log details>

- 消息代码: 24005

严重性: 调试 (DEBUG)

消息文本: 已成功完成主机搜索 (Host search finished successfully)

消息说明: 已成功完成在 LDAP 服务器中的主机搜索

本地目标消息格式: <timestamp> <seq_num> 24005 DEBUG External-LDAP: Host search finished successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24005 DEBUG External-LDAP: Host search finished successfully, <log details>

- 消息代码: 24006

严重性: 错误 (ERROR)

消息文本: 用户搜索结束, 但遇到错误 (User search ended with an error)

消息说明: 用户搜索结束, 但遇到错误

本地目标消息格式: <timestamp> <seq_num> 24006 ERROR External-LDAP: User search ended with an error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24006 ERROR External-LDAP: User search ended with an error, <log details>

- 消息代码: 24007

严重性: 错误 (ERROR)

消息文本: 主机搜索结束, 但遇到错误 (Host search ended with an error)

消息说明: 主机搜索结束, 但遇到错误

本地目标消息格式: <timestamp> <seq_num> 24007 ERROR External-LDAP: Host search ended with an error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24007 ERROR External-LDAP: Host search ended with an error, <log details>

- 消息代码: 24008

严重性: 调试 (DEBUG)

消息文本: 在 LDAP 服务器中未找到用户 (User not found in LDAP Server)

消息说明: 在 LDAP 服务器中未找到用户

本地目标消息格式: <timestamp> <seq_num> 24008 DEBUG External-LDAP: User not found in LDAP Server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24008 DEBUG External-LDAP: User not found in LDAP Server, <log details>

- 消息代码: 24009
 - 严重性: 调试 (DEBUG)
 - 消息文本: 在 LDAP 服务器中未找到主机 (Host not found in LDAP Server)
 - 消息说明: 在 LDAP 服务器中未找到主机
 - 本地目标消息格式: <timestamp> <seq_num> 24009 DEBUG External-LDAP: Host not found in LDAP Server, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24009 DEBUG External-LDAP: Host not found in LDAP Server, <log details>

- 消息代码: 24010
 - 严重性: 调试 (DEBUG)
 - 消息文本: 用户不明确 (Ambiguous user)
 - 消息说明: 在 LDAP 服务器中找到了多个符合指定用户名的用户
 - 本地目标消息格式: <timestamp> <seq_num> 24010 DEBUG External-LDAP: Ambiguous user, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24010 DEBUG External-LDAP: Ambiguous user, <log details>

- 消息代码: 24011
 - 严重性: 调试 (DEBUG)
 - 消息文本: 主机不明确 (Ambiguous host)
 - 消息说明: 在 LDAP 服务器中找到了多个符合指定主机名的用户
 - 本地目标消息格式: <timestamp> <seq_num> 24011 DEBUG External-LDAP: Ambiguous host, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24011 DEBUG External-LDAP: Ambiguous host, <log details>

- 消息代码: 24014
 - 严重性: 调试 (DEBUG)
 - 消息文本: 在 LDAP 中检测到了不合规属性 (Noncompliant attributes detected in LDAP)
 - 消息说明: 在 LDAP 中检测到了不合规属性
 - 本地目标消息格式: <timestamp> <seq_num> 24014 DEBUG External-LDAP: Noncompliant attributes detected in LDAP, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24014 DEBUG External-LDAP: Noncompliant attributes detected in LDAP, <log details>

- 消息代码: 24015

严重性: 调试 (DEBUG)

消息文本: 在 LDAP 服务器上验证用户身份 (Authenticating user against LDAP Server)

消息说明: 在 LDAP 服务器上验证用户身份

本地目标消息格式: <timestamp> <seq_num> 24015 DEBUG External-LDAP: Authenticating user against LDAP Server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24015 DEBUG External-LDAP:
Authenticating user against LDAP Server, <log details>

- 消息代码: 24016

严重性: 调试 (DEBUG)

消息文本: 正在 LDAP 服务器中查找用户 (Looking up user in LDAP Server)

消息说明: 正在 LDAP 服务器中查找用户

本地目标消息格式: <timestamp> <seq_num> 24016 DEBUG External-LDAP: Looking up user in LDAP Server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24016 DEBUG External-LDAP: Looking
up user in LDAP Server, <log details>

- 消息代码: 24017

严重性: 调试 (DEBUG)

消息文本: 正在 LDAP 服务器中查找主机 (Looking up host in LDAP Server)

消息说明: 正在 LDAP 服务器中查找主机

本地目标消息格式: <timestamp> <seq_num> 24017 DEBUG External-LDAP: Looking up host in LDAP Server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24017 DEBUG External-LDAP: Looking
up host in LDAP Server, <log details>

- 消息代码: 24018

严重性: 调试 (DEBUG)

消息文本: 无法检索用户证书 (Cannot retrieve user's certificate)

消息说明: 在 LDAP 服务器中的用户记录上未找到证书

本地目标消息格式: <timestamp> <seq_num> 24018 DEBUG External-LDAP: Cannot retrieve user's certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24018 DEBUG External-LDAP: Cannot retrieve user's certificate, <log details>

- 消息代码: 24019

严重性: 错误 (ERROR)

消息文本: 遇到 LDAP 连接错误 (LDAP connection error was encountered)

消息说明: ISE 无法连接到 LDAP 外部身份存储库

本地目标消息格式: <timestamp> <seq_num> 24019 ERROR External-LDAP: LDAP connection error was encountered, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24019 ERROR External-LDAP: LDAP connection error was encountered, <log details>

- 消息代码: 24020

严重性: 调试 (DEBUG)

消息文本: LDAP 服务器上的用户身份验证失败 (User authentication against the LDAP Server failed)

消息说明: LDAP 服务器上的用户身份验证失败用户输入了错误的密码或 LDAP 服务器中的用户记录已禁用或已过期

本地目标消息格式: <timestamp> <seq_num> 24020 DEBUG External-LDAP: User authentication against the LDAP Server failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24020 DEBUG External-LDAP: User authentication against the LDAP Server failed, <log details>

- 消息代码: 24021

严重性: 错误 (ERROR)

消息文本: 用户身份验证结束, 但遇到错误 (User authentication ended with an error)

消息说明: LDAP 服务器上的用户身份验证结束, 但遇到错误

本地目标消息格式: <timestamp> <seq_num> 24021 ERROR External-LDAP: User authentication ended with an error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24021 ERROR External-LDAP: User authentication ended with an error, <log details>

- 消息代码: 24022

严重性: 调试 (DEBUG)

消息文本: 用户身份验证成功 (User authentication succeeded)

消息说明: LDAP 服务器上的用户身份验证成功

本地目标消息格式: <timestamp> <seq_num> 24022 DEBUG External-LDAP: User authentication succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24022 DEBUG External-LDAP: User authentication succeeded, <log details>

- 消息代码: 24023

严重性: 调试 (DEBUG)

消息文本: 已检索用户组 (User's groups are retrieved)

消息说明: 已从 LDAP 服务器检索用户组

本地目标消息格式: <timestamp> <seq_num> 24023 DEBUG External-LDAP: User's groups are retrieved, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24023 DEBUG External-LDAP: User's groups are retrieved, <log details>

- 消息代码: 24024

严重性: 调试 (DEBUG)

消息文本: 已检索主机组 (Host's groups are retrieved)

消息说明: 已从 LDAP 服务器检索主机组

本地目标消息格式: <timestamp> <seq_num> 24024 DEBUG External-LDAP: Host's groups are retrieved, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24024 DEBUG External-LDAP: Host's groups are retrieved, <log details>

- 消息代码: 24025

严重性: 调试 (DEBUG)

消息文本: 未找到任何用户组 (No user's groups are found)

消息说明: 在 LDAP 服务器上未找到任何用户组

本地目标消息格式: <timestamp> <seq_num> 24025 DEBUG External-LDAP: No user's groups are found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24025 DEBUG External-LDAP: No user's groups are found, <log details>

- 消息代码: 24026

严重性: 调试 (DEBUG)

消息文本: 未找到任何主机组 (No host's groups are found)

消息说明: 在 LDAP 服务器上未找到任何主机组

本地目标消息格式: <timestamp> <seq_num> 24026 DEBUG External-LDAP: No host's groups are found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24026 DEBUG External-LDAP: No host's groups are found, <log details>

- 消息代码: 24027

严重性: 错误 (ERROR)

消息文本: 组搜索结束, 但遇到错误 (Groups search ended with an error)

消息说明: 组搜索结束, 但遇到错误

本地目标消息格式: <timestamp> <seq_num> 24027 ERROR External-LDAP: Groups search ended with an error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24027 ERROR External-LDAP: Groups search ended with an error, <log details>

- 消息代码: 24028

严重性: 调试 (DEBUG)

消息文本: 已检索用户属性 (User's attributes are retrieved)

消息说明: 已从 LDAP 服务器检索用户属性

本地目标消息格式: <timestamp> <seq_num> 24028 DEBUG External-LDAP: User's attributes are retrieved, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24028 DEBUG External-LDAP: User's attributes are retrieved, <log details>

- 消息代码: 24029

严重性: 调试 (DEBUG)

消息文本: 已检索主机属性 (Host's attributes are retrieved)

消息说明: 已从 LDAP 服务器检索主机属性

本地目标消息格式: <timestamp> <seq_num> 24029 DEBUG External-LDAP: Host's attributes are retrieved, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24029 DEBUG External-LDAP: Host's attributes are retrieved, <log details>

- 消息代码: 24030
 - 严重性: 错误 (ERROR)
 - 消息文本: 遇到 SSL 连接错误 (SSL connection error was encountered)
 - 消息说明: 遇到 SSL 连接错误
 - 本地目标消息格式: <timestamp> <seq_num> 24030 ERROR External-LDAP: SSL connection error was encountered, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24030 ERROR External-LDAP: SSL connection error was encountered, <log details>

- 消息代码: 24031
 - 严重性: 信息 (INFO)
 - 消息文本: 正在向主 LDAP 服务器发送请求 (Sending request to primary LDAP server)
 - 消息说明: 正在向主 LDAP 服务器发送请求
 - 本地目标消息格式: <timestamp> <seq_num> 24031 INFO External-LDAP: Sending request to primary LDAP server, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24031 INFO External-LDAP: Sending request to primary LDAP server, <log details>

- 消息代码: 24032
 - 严重性: 信息 (INFO)
 - 消息文本: 正在向辅助 LDAP 服务器发送请求 (Sending request to secondary LDAP server)
 - 消息说明: 正在向辅助 LDAP 服务器发送请求
 - 本地目标消息格式: <timestamp> <seq_num> 24032 INFO External-LDAP: Sending request to secondary LDAP server, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24032 INFO External-LDAP: Sending request to secondary LDAP server, <log details>

- 消息代码: 24033
 - 严重性: 信息 (INFO)
 - 消息文本: 主服务器故障切换。正切换到辅助服务器 (Primary server failover. Switching to secondary server)
 - 消息说明: 无法连接到主服务器
 - 本地目标消息格式: <timestamp> <seq_num> 24033 INFO External-LDAP: Primary server failover. Switching to secondary server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24033 INFO External-LDAP: Primary server failover. Switching to secondary server, <log details>

- 消息代码: 24034

严重性: 信息 (INFO)

消息文本: 辅助服务器故障切换。正切换到主服务器 (Secondary server failover. Switching to primary server)

消息说明: 无法连接到辅助服务器

本地目标消息格式: <timestamp> <seq_num> 24034 INFO External-LDAP: Secondary server failover. Switching to primary server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24034 INFO External-LDAP: Secondary server failover. Switching to primary server, <log details>

- 消息代码: 24035

严重性: 信息 (INFO)

消息文本: 去除域前缀 (Perform domain prefix stripping)

消息说明: 去除域前缀

本地目标消息格式: <timestamp> <seq_num> 24035 INFO External-LDAP: Perform domain prefix stripping, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24035 INFO External-LDAP: Perform domain prefix stripping, <log details>

- 消息代码: 24036

严重性: 信息 (INFO)

消息文本: 去除域后缀 (Perform domain suffix stripping)

消息说明: 去除域后缀

本地目标消息格式: <timestamp> <seq_num> 24036 INFO External-LDAP: Perform domain suffix stripping, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24036 INFO External-LDAP: Perform domain suffix stripping, <log details>

- 消息代码: 24037

严重性: 调试 (DEBUG)

消息文本: 已发送主题搜索请求 (Sent a subject search request)

消息说明: 已发送主题搜索请求。

本地目标消息格式: <timestamp> <seq_num> 24037 DEBUG External-LDAP: Sent a subject search request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24037 DEBUG External-LDAP: Sent a subject search request, <log details>

- 消息代码: 24038

严重性: 调试 (DEBUG)

消息文本: 已收到主题搜索响应 (Received a subject search response)

消息说明: 已收到主题搜索响应。

本地目标消息格式: <timestamp> <seq_num> 24038 DEBUG External-LDAP: Received a subject search response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24038 DEBUG External-LDAP: Received a subject search response, <log details>

- 消息代码: 24039

严重性: 调试 (DEBUG)

消息文本: 已发送主题组搜索请求 (Sent a subject's group search request)

消息说明: 已发送主题组搜索请求。

本地目标消息格式: <timestamp> <seq_num> 24039 DEBUG External-LDAP: Sent a subject's group search request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24039 DEBUG External-LDAP: Sent a subject's group search request, <log details>

- 消息代码: 24040

严重性: 调试 (DEBUG)

消息文本: 已收到主题组搜索响应 (Received a subject's group search response)

消息说明: 已收到主题组搜索响应。

本地目标消息格式: <timestamp> <seq_num> 24040 DEBUG External-LDAP: Received a subject's group search response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24040 DEBUG External-LDAP: Received a subject's group search response, <log details>

- 消息代码: 24041

严重性: 调试 (DEBUG)

消息文本: 已发送主题绑定请求 (Sent subject bind request)

消息说明: 已发送主题绑定请求

本地目标消息格式: <timestamp> <seq_num> 24041 DEBUG External-LDAP: Sent subject bind request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24041 DEBUG External-LDAP: Sent subject bind request, <log details>

- 消息代码: 24042

严重性: 调试 (DEBUG)

消息文本: 已收到主题绑定响应 (Received subject bind response)

消息说明: 已收到主题绑定响应

本地目标消息格式: <timestamp> <seq_num> 24042 DEBUG External-LDAP: Received subject bind response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24042 DEBUG External-LDAP: Received subject bind response, <log details>

- 消息代码: 24043

严重性: 调试 (DEBUG)

消息文本: 已发送管理员绑定请求 (Sent an administrator bind request)

消息说明: 已发送管理员绑定请求。

本地目标消息格式: <timestamp> <seq_num> 24043 DEBUG External-LDAP: Sent an administrator bind request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24043 DEBUG External-LDAP: Sent an administrator bind request, <log details>

- 消息代码: 24044

严重性: 调试 (DEBUG)

消息文本: 已收到管理员绑定响应 (Received an administrator bind response)

消息说明: 已收到管理员绑定响应。

本地目标消息格式: <timestamp> <seq_num> 24044 DEBUG External-LDAP: Received an administrator bind response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24044 DEBUG External-LDAP: Received an administrator bind response, <log details>

- 消息代码: 24050

严重性: 警告 (WARN)

消息文本: 由于密码不存在或为空, 因此无法使用 LDAP 身份库进行身份验证 (Cannot authenticate with LDAP Identity Store because password was not present or was empty)

消息说明: ISE 未收到用户密码或收到的密码为空。在无密码或密码为空的情况下, 无法执行纯密码身份验证

本地目标消息格式: <timestamp> <seq_num> 24050 WARN External-LDAP: Cannot authenticate with LDAP Identity Store because password was not present or was empty, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24050 WARN External-LDAP: Cannot authenticate with LDAP Identity Store because password was not present or was empty, <log details>

- 消息代码: 24051

严重性: 错误 (ERROR)

消息文本: 安全 LDAP 进行 SSL 握手失败, 因为证书链存在未知 CA (Secure LDAP failed SSL handshake because of an unknown CA in the certificates chain)

消息说明: 安全 LDAP 进行 SSL 握手失败, 因为证书链存在未知 CA

本地目标消息格式: <timestamp> <seq_num> 24051 ERROR External-LDAP: Secure LDAP failed SSL handshake because of an unknown CA in the certificates chain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24051 ERROR External-LDAP: Secure LDAP failed SSL handshake because of an unknown CA in the certificates chain, <log details>

- 消息代码: 24052

严重性: 错误 (ERROR)

消息文本: 由于 OCSP 发现证书已撤销, 所以重新进行安全 LDAP 连接 (Secure LDAP connection reconnect due to OCSP found revoked certificate)

消息说明: OCSP 检查结果发现, 已撤销用于 LDAP 连接的证书

本地目标消息格式: <timestamp> <seq_num> 24052 ERROR External-LDAP: Secure LDAP connection reconnect due to OCSP found revoked certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24052 ERROR External-LDAP: Secure LDAP connection reconnect due to OCSP found revoked certificate, <log details>

- 消息代码: 24053

严重性: 错误 (ERROR)

消息文本: 由于 CRL 发现证书已撤销, 所以重新进行安全 LDAP 连接 (Secure LDAP connection reconnect due to CRL found revoked certificate)

消息说明: CRL 检查结果发现, 已撤销用于 LDAP 连接的证书

本地目标消息格式: <timestamp> <seq_num> 24053 ERROR External-LDAP: Secure LDAP connection reconnect due to CRL found revoked certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24053 ERROR External-LDAP: Secure
LDAP connection reconnect due to CRL found revoked certificate, <log details>

- 消息代码: 24054

严重性: 调试 (DEBUG)

消息文本: LDAP 服务器上的用户身份验证检测到用户密码已过期 (User authentication against
LDAP server detected that user password has expired)

消息说明: 密码已过期, 但身份验证还有宽限期。用户需要更改密码

本地目标消息格式: <timestamp> <seq_num> 24054 DEBUG External-LDAP: User authentication
against LDAP server detected that user password has expired, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24054 DEBUG External-LDAP: User
authentication against LDAP server detected that user password has expired, <log details>

- 消息代码: 24055

严重性: 调试 (DEBUG)

消息文本: LDAP 服务器上的用户身份验证检测到用户在密码管理员设置密码后首次进行身份
验证 (User authentication against LDAP server detected that the user is authenticating for the first time
after the password administrator set the password)

消息说明: 用户需要立即更改密码

本地目标消息格式: <timestamp> <seq_num> 24055 DEBUG External-LDAP: User authentication
against LDAP server detected that the user is authenticating for the first time after the password
administrator set the password, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24055 DEBUG External-LDAP: User
authentication against LDAP server detected that the user is authenticating for the first time after the
password administrator set the password, <log details>

- 消息代码: 24056

严重性: 警告 (WARN)

消息文本: LDAP 服务器上的用户身份验证检测到用户密码已过期且身份验证不再有宽限期
(User authentication against LDAP server detected that user password has expired and there are no more
grace authentications)

消息说明: 用户需要联系密码管理员才能重置密码

本地目标消息格式: <timestamp> <seq_num> 24056 WARN External-LDAP: User authentication
against LDAP server detected that user password has expired and there are no more grace authentications,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24056 WARN External-LDAP: User

authentication against LDAP server detected that user password has expired and there are no more grace authentications, <log details>

- 消息代码: 24057

严重性: 警告 (WARN)

消息文本: LDAP 服务器上的用户身份验证检测到密码失败次数已达上限且帐户已锁定 (User authentication against LDAP server detected that the password failure limit has been reached and the account is locked)

消息说明: 用户需要稍后重试或联系密码管理员以重置密码

本地目标消息格式: <timestamp> <seq_num> 24057 WARN External-LDAP: User authentication against LDAP server detected that the password failure limit has been reached and the account is locked, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24057 WARN External-LDAP: User authentication against LDAP server detected that the password failure limit has been reached and the account is locked, <log details>

- 消息代码: 24058

严重性: 错误 (ERROR)

消息文本: LDAP 服务器不支持密码修改扩展操作 (LDAP server does not support password modify extended operation) (RFC 3062)

消息说明: ACS 管理员应在 LDAP 身份库配置上禁用密码更改

本地目标消息格式: <timestamp> <seq_num> 24058 ERROR External-LDAP: LDAP server does not support password modify extended operation (RFC 3062), <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24058 ERROR External-LDAP: LDAP server does not support password modify extended operation (RFC 3062), <log details>

- 消息代码: 24059

严重性: 错误 (ERROR)

消息文本: 用户密码更改结束, 但遇到错误 (User password change ended with an error)

消息说明: 应检查 LDAP 服务器日志以获取更多详细信息

本地目标消息格式: <timestamp> <seq_num> 24059 ERROR External-LDAP: User password change ended with an error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24059 ERROR External-LDAP: User password change ended with an error, <log details>

- 消息代码: 24060

严重性: 信息 (INFO)

消息文本: 正在更改 LDAP 服务器上的用户密码 (Changing user's password on LDAP Server)

消息说明: 正在更改 LDAP 服务器上的用户密码

本地目标消息格式: <timestamp> <seq_num> 24060 INFO External-LDAP: Changing user's password on LDAP Server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24060 INFO External-LDAP: Changing user's password on LDAP Server, <log details>

- 消息代码: 24061

严重性: 调试 (DEBUG)

消息文本: 已发送密码修改请求 (Sent password modify request)

消息说明: 已发送密码修改请求

本地目标消息格式: <timestamp> <seq_num> 24061 DEBUG External-LDAP: Sent password modify request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24061 DEBUG External-LDAP: Sent password modify request, <log details>

- 消息代码: 24062

严重性: 调试 (DEBUG)

消息文本: 收到密码修改响应 (Received password modify response)

消息说明: 收到密码修改响应

本地目标消息格式: <timestamp> <seq_num> 24062 DEBUG External-LDAP: Received password modify response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24062 DEBUG External-LDAP: Received password modify response, <log details>

- 消息代码: 24063

严重性: 警告 (WARN)

消息文本: 用户的密码即将过期 (The user's password will expire soon)

消息说明: 用户的密码即将过期

本地目标消息格式: <timestamp> <seq_num> 24063 WARN External-LDAP: The user's password will expire soon, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24063 WARN External-LDAP: The user's password will expire soon, <log details>

- 消息代码: 24064

严重性: 警告 (WARN)

消息文本: 用户没有足够的权限更改密码 (The user doesn't have sufficient rights to change password)

消息说明: 用户没有足够的权限更改密码

本地目标消息格式: <timestamp> <seq_num> 24064 WARN External-LDAP: The user doesn't have sufficient rights to change password, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24064 WARN External-LDAP: The user doesn't have sufficient rights to change password, <log details>

- 消息代码: 24065

严重性: 警告 (WARN)

消息文本: 新密码不符合 LDAP 密码策略 (The new password does not conform to LDAP password policy)

消息说明: 新密码不符合 LDAP 密码策略

本地目标消息格式: <timestamp> <seq_num> 24065 WARN External-LDAP: The new password does not conform to LDAP password policy, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24065 WARN External-LDAP: The new password does not conform to LDAP password policy, <log details>

- 消息代码: 24066

严重性: 信息 (INFO)

消息文本: 用户密码更改成功 (User password change succeeded)

消息说明: LDAP 服务器上的用户密码更改成功

本地目标消息格式: <timestamp> <seq_num> 24066 INFO External-LDAP: User password change succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24066 INFO External-LDAP: User password change succeeded, <log details>

- 消息代码: 24067

严重性: 警告 (WARN)

消息文本: LDAP 身份存储库配置页面上未启用密码更改 (The password change is not enabled on LDAP Identity Store configuration page)

消息说明: LDAP 身份存储库配置页面上未启用密码更改

本地目标消息格式: <timestamp> <seq_num> 24067 WARN External-LDAP: The password change is not enabled on LDAP Identity Store configuration page, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24067 WARN External-LDAP: The password
change is not enabled on LDAP Identity Store configuration page, <log details>

- 消息代码: 24100

严重性: 调试 (DEBUG)

消息文本: 在主题记录中未找到某些预期属性。默认值 (如果已配置) 将用于这些属性 (Some of the expected attributes are not found on the subject record. The default values, if configured, will be used for these attributes)

消息说明: 在主题记录中未找到某些预期属性。默认值 (如果已配置) 将用于这些属性。

本地目标消息格式: <timestamp> <seq_num> 24100 DEBUG Generic-ID-Store: Some of the expected attributes are not found on the subject record. The default values, if configured, will be used for these attributes, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24100 DEBUG Generic-ID-Store: Some of the expected attributes are not found on the subject record. The default values, if configured, will be used for these attributes, <log details>

- 消息代码: 24101

严重性: 警告 (WARN)

消息文本: 某些检索到的属性包含多个值。这些值会被丢弃。默认值 (如果已配置) 将用于这些属性 (Some of the retrieved attributes contain multiple values. These values are discarded. The default values, if configured, will be used for these attributes)

消息说明: 某些检索到的属性包含多个值。这些值会被丢弃。默认值 (如果已配置) 将用于这些属性。

本地目标消息格式: <timestamp> <seq_num> 24101 WARN Generic-ID-Store: Some of the retrieved attributes contain multiple values. These values are discarded. The default values, if configured, will be used for these attributes, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24101 WARN Generic-ID-Store: Some of the retrieved attributes contain multiple values. These values are discarded. The default values, if configured, will be used for these attributes, <log details>

- 消息代码: 24102

严重性: 警告 (WARN)

消息文本: 某些检索到的属性包含属于不兼容类型的值。这些值会被丢弃。默认值 (如果已配置) 将用于这些属性 (Some of the retrieved attributes contain values that are of an incompatible type. These values are discarded. The default values, if configured, will be used for these attributes)

消息说明: 某些检索到的属性包含属于不兼容类型的值。这些值会被丢弃。默认值 (如果已配置) 将用于这些属性。

本地目标消息格式: <timestamp> <seq_num> 24102 WARN Generic-ID-Store: Some of the retrieved attributes contain values that are of an incompatible type. These values are discarded. The default values, if configured, will be used for these attributes, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24102 WARN Generic-ID-Store: Some of the retrieved attributes contain values that are of an incompatible type. These values are discarded. The default values, if configured, will be used for these attributes, <log details>

- 消息代码: 24201

严重性: 信息 (INFO)

消息文本: 内部身份存储库已成功连接到数据库 (Internal ID Store successfully connected to database)

消息说明: 内部身份存储库已成功连接到数据库

本地目标消息格式: <timestamp><seq_num> 24201 INFO Local-user-DB: Internal ID Store successfully connected to database, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24201 INFO Local-user-DB: Internal ID Store successfully connected to database, <log details>

- 消息代码: 24202

严重性: 错误 (ERROR)

消息文本: 内部身份存储库无法连接到数据库 (Internal ID Store could not connect to the database)

消息说明: 内部身份存储库无法连接到数据库

本地目标消息格式: <timestamp> <seq_num> 24202 ERROR Local-user-DB: Internal ID Store could not connect to the database, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24202 ERROR Local-user-DB: Internal ID Store could not connect to the database, <log details>

- 消息代码: 24203

严重性: 信息 (INFO)

消息文本: 用户需要更改密码 (User need to change password)

消息说明: 已在内部数据库中将用户标记为需要更改密码

本地目标消息格式: <timestamp> <seq_num> 24203 INFO Local-user-DB: User need to change password, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24203 INFO Local-user-DB: User need to change password, <log details>

- 消息代码: 24204

严重性: 信息 (INFO)

消息文本: 密码更改成功 (Password changed successfully)

消息说明: 用户密码已在内部数据库中成功更改

本地目标消息格式: <timestamp> <seq_num> 24204 INFO Local-user-DB: Password changed successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24204 INFO Local-user-DB: Password changed successfully, <log details>

- 消息代码: 24205

严重性: 错误 (ERROR)

消息文本: 无法将密码改为新密码 (Could not change password to new password)

消息说明: 无法在内部数据库中将密码改为新密码

本地目标消息格式: <timestamp> <seq_num> 24205 ERROR Local-user-DB: Could not change password to new password, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24205 ERROR Local-user-DB: Could not change password to new password, <log details>

- 消息代码: 24206

严重性: 信息 (INFO)

消息文本: 用户已禁用 (User disabled)

消息说明: 已在内部数据库中将用户标记为禁用。

本地目标消息格式: <timestamp> <seq_num> 24206 INFO Local-user-DB: User disabled, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24206 INFO Local-user-DB: User disabled, <log details>

- 消息代码: 24207

严重性: 信息 (INFO)

消息文本: 主机已禁用 (Host disabled)

消息说明: 已在内部数据库中将主机标记为禁用。

本地目标消息格式: <timestamp> <seq_num> 24207 INFO Local-user-DB: Host disabled, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24207 INFO Local-user-DB: Host disabled, <log details>

- 消息代码: 24208

严重性: 调试 (DEBUG)

消息文本: 正在内部管理员 IDStore 中查找管理员 (Looking up Admin in Internal Admins IDStore)

消息说明: 正在内部管理员 IDStore 中查找管理员

本地目标消息格式: <timestamp> <seq_num> 24208 DEBUG Local-user-DB: Looking up Admin in Internal Admins IDStore, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24208 DEBUG Local-user-DB: Looking up Admin in Internal Admins IDStore, <log details>

- 消息代码: 24209

严重性: 调试 (DEBUG)

消息文本: 正在内部终端 IDStore 中查找终端 (Looking up Endpoint in Internal Endpoints IDStore)

消息说明: 正在内部终端 IDStore 中查找终端

本地目标消息格式: <timestamp> <seq_num> 24209 DEBUG Local-user-DB: Looking up Endpoint in Internal Endpoints IDStore, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24209 DEBUG Local-user-DB: Looking up Endpoint in Internal Endpoints IDStore, <log details>

- 消息代码: 24210

严重性: 调试 (DEBUG)

消息文本: 正在内部用户 IDStore 中查找用户 (Looking up User in Internal Users IDStore)

消息说明: 正在内部用户 IDStore 中查找用户

本地目标消息格式: <timestamp> <seq_num> 24210 DEBUG Local-user-DB: Looking up User in Internal Users IDStore, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24210 DEBUG Local-user-DB: Looking up User in Internal Users IDStore, <log details>

- 消息代码: 24211

严重性: 调试 (DEBUG)

消息文本: 已在内部终端 IDStore 中找到终端 (Found Endpoint in Internal Endpoints IDStore)

消息说明: 已在内部终端 IDStore 中找到终端

本地目标消息格式: <timestamp> <seq_num> 24211 DEBUG Local-user-DB: Found Endpoint in Internal Endpoints IDStore, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24211 DEBUG Local-user-DB: Found Endpoint in Internal Endpoints IDStore, <log details>

- 消息代码: 24212

严重性: 调试 (DEBUG)

消息文本: 已在内部用户 IDStore 中找到用户 (Found User in Internal Users IDStore)

消息说明: 已在内部用户 IDStore 中找到用户

本地目标消息格式: <timestamp> <seq_num> 24212 DEBUG Local-user-DB: Found User in Internal Users IDStore, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24212 DEBUG Local-user-DB: Found User in Internal Users IDStore, <log details>

- 消息代码: 24213

严重性: 调试 (DEBUG)

消息文本: 已在网络设备和 AAA 客户端中找到 TrustSec 设备 (Found TrustSec Device in Network Devices and AAA Clients)

消息说明: 已在网络设备和 AAA 客户端中找到 TrustSec 设备

本地目标消息格式: <timestamp> <seq_num> 24213 DEBUG Local-user-DB: Found TrustSec Device in Network Devices and AAA Clients, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24213 DEBUG Local-user-DB: Found TrustSec Device in Network Devices and AAA Clients, <log details>

- 消息代码: 24214

严重性: 信息 (INFO)

消息文本: MSCHAP 用于内部用户身份存储库中的更改密码请求 (MSCHAP is used for the change password request in the internal users identity store)

消息说明: MSCHAP 用于内部用户身份存储库中的更改密码请求。

本地目标消息格式: <timestamp> <seq_num> 24214 INFO Local-user-DB: MSCHAP is used for the change password request in the internal users identity store, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24214 INFO Local-user-DB: MSCHAP is used for the change password request in the internal users identity store, <log details>

- 消息代码: 24215

严重性: 信息 (INFO)

消息文本: PAP 用于内部身份存储库中的更改密码请求 (PAP is used for the change password request in the internal identity store)

消息说明: PAP 用于内部身份存储库中的更改密码请求。

本地目标消息格式: <timestamp> <seq_num> 24215 INFO Local-user-DB: PAP is used for the change password request in the internal identity store, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24215 INFO Local-user-DB: PAP is used
for the change password request in the internal identity store, <log details>

- 消息代码: 24216

严重性: 调试 (DEBUG)

消息文本: 在内部用户身份存储库中未找到用户 (The user is not found in the internal users identity store)

消息说明: 在内部用户身份存储库中未找到指定用户。

本地目标消息格式: <timestamp> <seq_num> 24216 DEBUG Local-user-DB: The user is not found
in the internal users identity store, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24216 DEBUG Local-user-DB: The user is
not found in the internal users identity store, <log details>

- 消息代码: 24217

严重性: 调试 (DEBUG)

消息文本: 在内部终端身份存储库中未找到主机 (The host is not found in the internal endpoints
identity store)

消息说明: 在内部终端身份存储库中未找到指定主机。

本地目标消息格式: <timestamp> <seq_num> 24217 DEBUG Local-user-DB: The host is not found
in the internal endpoints identity store, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24217 DEBUG Local-user-DB: The host is
not found in the internal endpoints identity store, <log details>

- 消息代码: 24218

严重性: 调试 (DEBUG)

消息文本: 在 ISE 中的网络设备和 AAA 客户端下未定义 TrustSec 设备 (The TrustSec device is
not defined under Network Devices and AAA Clients in ISE)

消息说明: 在 ISE 中的网络设备和 AAA 客户端下未定义指定的 TrustSec 设备。

本地目标消息格式: <timestamp> <seq_num> 24218 DEBUG Local-user-DB: The TrustSec device
is not defined under Network Devices and AAA Clients in ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24218 DEBUG Local-user-DB: The TrustSec
device is not defined under Network Devices and AAA Clients in ISE, <log details>

- 消息代码: 24219

严重性: 信息 (INFO)

消息文本: 用户帐户已暂停 (User account suspended)

消息说明：用户帐户由于身份验证尝试多次失败而被暂停

本地目标消息格式：<timestamp> <seq_num> 24219 INFO Local-user-DB: User account suspended, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24219 INFO Local-user-DB: User account suspended, <log details>

- 消息代码：24300

严重性：错误 (ERROR)

消息文本：无域控制器可用 (No domain controller available)

消息说明：无域控制器可用

本地目标消息格式：<timestamp> <seq_num> 24300 ERROR External-Active-Directory: No domain controller available, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24300 ERROR External-Active-Directory: No domain controller available, <log details>

- 消息代码：24301

严重性：错误 (ERROR)

消息文本：没有可用的可写入域控制器 (No writable domain controller available)

消息说明：没有可用的可写入域控制器

本地目标消息格式：<timestamp> <seq_num> 24301 ERROR External-Active-Directory: No writable domain controller available, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24301 ERROR External-Active-Directory: No writable domain controller available, <log details>

- 消息代码：24302

严重性：错误 (ERROR)

消息文本：没有可用的全局目录 (No global catalog available)

消息说明：没有可用的全局目录

本地目标消息格式：<timestamp> <seq_num> 24302 ERROR External-Active-Directory: No global catalog available, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24302 ERROR External-Active-Directory: No global catalog available, <log details>

- 消息代码：24303

严重性：警告 (WARN)

消息文本: 与域控制器通信失败 (Communication with domain controller failed)

消息说明: 与域控制器通信失败

本地目标消息格式: <timestamp> <seq_num> 24303 WARN External-Active-Directory: Communication with domain controller failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24303 WARN External-Active-Directory: Communication with domain controller failed, <log details>

- 消息代码: 24304

严重性: 警告 (WARN)

消息文本: 与全局目录通信失败 (Communication with global catalog failed)

消息说明: 与全局目录通信失败

本地目标消息格式: <timestamp> <seq_num> 24304 WARN External-Active-Directory: Communication with global catalog failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24304 WARN External-Active-Directory: Communication with global catalog failed, <log details>

- 消息代码: 24305

严重性: 错误 (ERROR)

消息文本: 已超出故障切换阈值 (Failover threshold has been exceeded)

消息说明: 已超出故障切换阈值

本地目标消息格式: <timestamp> <seq_num> 24305 ERROR External-Active-Directory: Failover threshold has been exceeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24305 ERROR External-Active-Directory: Failover threshold has been exceeded, <log details>

- 消息代码: 24306

严重性: 错误 (ERROR)

消息文本: 无可用的 DNS 服务器 (No DNS server available)

消息说明: 无可用的 DNS 服务器

本地目标消息格式: <timestamp> <seq_num> 24306 ERROR External-Active-Directory: No DNS server available, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24306 ERROR External-Active-Directory: No DNS server available, <log details>

- 消息代码: 24307

严重性: 错误 (ERROR)

消息文本: DNS 服务器返回了错误 (DNS server returned error)

消息说明: DNS 服务器返回了错误

本地目标消息格式: <timestamp> <seq_num> 24307 ERROR External-Active-Directory: DNS server returned error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24307 ERROR External-Active-Directory: DNS server returned error, <log details>

- 消息代码: 24308

严重性: 错误 (ERROR)

消息文本: 未加入任何所需的域 (None of required domains is joined)

消息说明: 未加入任何所需的域

本地目标消息格式: <timestamp> <seq_num> 24308 ERROR External-Active-Directory: None of required domains is joined, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24308 ERROR External-Active-Directory: None of required domains is joined, <log details>

- 消息代码: 24309

严重性: 调试 (DEBUG)

消息文本: 连接点已拒绝没有域标记的身份名称 (Identity name with no domain markup has been rejected by join points)

消息说明: 根据“AD 身份存储库高级设置” (AD Identity Store Advanced Settings), 已拒绝没有域标记的身份名称

本地目标消息格式: <timestamp> <seq_num> 24309 DEBUG External-Active-Directory: Identity name with no domain markup has been rejected by join points, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24309 DEBUG External-Active-Directory: Identity name with no domain markup has been rejected by join points, <log details>

- 消息代码: 24310

严重性: 调试 (DEBUG)

消息文本: 已识别用户主体名称 (UPN) 格式 (User Principal Name (UPN) format recognized)

消息说明: 已识别用户主体名称 (UPN) 格式

本地目标消息格式: <timestamp> <seq_num> 24310 DEBUG External-Active-Directory: User Principal Name (UPN) format recognized, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24310 DEBUG External-Active-Directory:
User Principal Name (UPN) format recognized, <log details>

- 消息代码: 24311

严重性: 调试 (DEBUG)

消息文本: 已识别低级登录 (NetBIOS) 名称格式 (Down-Level Logon (NetBIOS) Name format recognized)

消息说明: 已识别低级登录 (NetBIOS) 名称格式

本地目标消息格式: <timestamp> <seq_num> 24311 DEBUG External-Active-Directory: Down-Level Logon (NetBIOS) Name format recognized, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24311 DEBUG External-Active-Directory:
Down-Level Logon (NetBIOS) Name format recognized, <log details>

- 消息代码: 24312

严重性: 调试 (DEBUG)

消息文本: 已识别 SAM 帐户名称格式 (SAM Account Name format recognized)

消息说明: 已识别 SAM 帐户名称格式

本地目标消息格式: <timestamp> <seq_num> 24312 DEBUG External-Active-Directory: SAM Account Name format recognized, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24312 DEBUG External-Active-Directory:
SAM Account Name format recognized, <log details>

- 消息代码: 24313

严重性: 调试 (DEBUG)

消息文本: 搜索连接点上的匹配帐户 (Search for matching accounts at join point)

消息说明: 搜索连接点上的匹配帐户

本地目标消息格式: <timestamp> <seq_num> 24313 DEBUG External-Active-Directory: Search for matching accounts at join point, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24313 DEBUG External-Active-Directory:
Search for matching accounts at join point, <log details>

- 消息代码: 24314

严重性: 调试 (DEBUG)

消息文本: 在域中未找到任何匹配帐户 (No matching account found in domain)

消息说明: 在域中未找到任何匹配帐户

本地目标消息格式: <timestamp> <seq_num> 24314 DEBUG External-Active-Directory: No matching account found in domain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24314 DEBUG External-Active-Directory: No matching account found in domain, <log details>

- 消息代码: 24315

严重性: 调试 (DEBUG)

消息文本: 在域中找到了一个匹配帐户 (Single matching account found in domain)

消息说明: 在域中找到了一个匹配帐户

本地目标消息格式: <timestamp> <seq_num> 24315 DEBUG External-Active-Directory: Single matching account found in domain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24315 DEBUG External-Active-Directory: Single matching account found in domain, <log details>

- 消息代码: 24316

严重性: 调试 (DEBUG)

消息文本: 在域中找到了多个匹配帐户 (Multiple matching accounts found in domain)

消息说明: 在域中找到了多个匹配帐户

本地目标消息格式: <timestamp> <seq_num> 24316 DEBUG External-Active-Directory: Multiple matching accounts found in domain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24316 DEBUG External-Active-Directory: Multiple matching accounts found in domain, <log details>

- 消息代码: 24317

严重性: 错误 (ERROR)

消息文本: 域中的 LDAP 搜索失败 (LDAP search in domain failed)

消息说明: 域中的 LDAP 搜索失败

本地目标消息格式: <timestamp> <seq_num> 24317 ERROR External-Active-Directory: LDAP search in domain failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24317 ERROR External-Active-Directory: LDAP search in domain failed, <log details>

- 消息代码: 24318

严重性: 调试 (DEBUG)

消息文本: 在林中未找到任何匹配帐户 (No matching account found in forest)

消息说明：在林中未找到任何匹配帐户

本地目标消息格式：<timestamp> <seq_num> 24318 DEBUG External-Active-Directory: No matching account found in forest, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24318 DEBUG External-Active-Directory: No matching account found in forest, <log details>

- 消息代码：24319

严重性：调试 (DEBUG)

消息文本：在林中找到了一个匹配帐户 (Single matching account found in forest)

消息说明：在林中找到了一个匹配帐户

本地目标消息格式：<timestamp> <seq_num> 24319 DEBUG External-Active-Directory: Single matching account found in forest, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24319 DEBUG External-Active-Directory: Single matching account found in forest, <log details>

- 消息代码：24320

严重性：调试 (DEBUG)

消息文本：林中有多个匹配帐户 (Multiple matching accounts in forest)

消息说明：林中有多个匹配帐户

本地目标消息格式：<timestamp> <seq_num> 24320 DEBUG External-Active-Directory: Multiple matching accounts in forest, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24320 DEBUG External-Active-Directory: Multiple matching accounts in forest, <log details>

- 消息代码：24321

严重性：错误 (ERROR)

消息文本：林中的 LDAP 搜索失败 (LDAP search in forest failed)

消息说明：林中的 LDAP 搜索失败

本地目标消息格式：<timestamp> <seq_num> 24321 ERROR External-Active-Directory: LDAP search in forest failed, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24321 ERROR External-Active-Directory: LDAP search in forest failed, <log details>

- 消息代码：24322

严重性：调试 (DEBUG)

消息文本: 身份解析未检测到任何匹配帐户 (Identity resolution detected no matching account)

消息说明: 身份解析未检测到任何匹配帐户

本地目标消息格式: <timestamp> <seq_num> 24322 DEBUG External-Active-Directory: Identity resolution detected no matching account, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24322 DEBUG External-Active-Directory: Identity resolution detected no matching account, <log details>

- 消息代码: 24323

严重性: 调试 (DEBUG)

消息文本: 身份解析检测到了一个匹配帐户 (Identity resolution detected single matching account)

消息说明: 身份解析检测到了一个匹配帐户

本地目标消息格式: <timestamp> <seq_num> 24323 DEBUG External-Active-Directory: Identity resolution detected single matching account, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24323 DEBUG External-Active-Directory: Identity resolution detected single matching account, <log details>

- 消息代码: 24324

严重性: 调试 (DEBUG)

消息文本: 身份解析检测到多个匹配帐户 (Identity resolution detected multiple matching accounts)

消息说明: 身份解析检测到多个匹配帐户

本地目标消息格式: <timestamp> <seq_num> 24324 DEBUG External-Active-Directory: Identity resolution detected multiple matching accounts, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24324 DEBUG External-Active-Directory: Identity resolution detected multiple matching accounts, <log details>

- 消息代码: 24325

严重性: 调试 (DEBUG)

消息文本: 正在解析身份 (Resolving identity)

消息说明: 正在解析身份

本地目标消息格式: <timestamp> <seq_num> 24325 DEBUG External-Active-Directory: Resolving identity, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24325 DEBUG External-Active-Directory: Resolving identity, <log details>

- 消息代码: 24326

严重性: 调试 (DEBUG)

消息文本: 正在按 UPN 搜索主题对象 (Searching subject object by UPN)

消息说明: 正在按 UPN 搜索主题对象

本地目标消息格式: <timestamp> <seq_num> 24326 DEBUG External-Active-Directory: Searching subject object by UPN, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24326 DEBUG External-Active-Directory: Searching subject object by UPN, <log details>

- 消息代码: 24327

严重性: 调试 (DEBUG)

消息文本: 在缓存中找到了主题对象 (Subject object found in a cache)

消息说明: 在缓存中找到了主题对象

本地目标消息格式: <timestamp> <seq_num> 24327 DEBUG External-Active-Directory: Subject object found in a cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24327 DEBUG External-Active-Directory: Subject object found in a cache, <log details>

- 消息代码: 24328

严重性: 调试 (DEBUG)

消息文本: 在缓存中未找到主题对象 (Subject object not found in a cache)

消息说明: 在缓存中未找到主题对象

本地目标消息格式: <timestamp> <seq_num> 24328 DEBUG External-Active-Directory: Subject object not found in a cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24328 DEBUG External-Active-Directory: Subject object not found in a cache, <log details>

- 消息代码: 24329

严重性: 调试 (DEBUG)

消息文本: 主题缓存条目已过期 (Subject cache entry expired)

消息说明: 主题缓存条目已过期

本地目标消息格式: <timestamp> <seq_num> 24329 DEBUG External-Active-Directory: Subject cache entry expired, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24329 DEBUG External-Active-Directory: Subject cache entry expired, <log details>

- 消息代码: 24330
 - 严重性: 调试 (DEBUG)
 - 消息文本: 按名称请求查找 SID 成功 (Lookup SID By Name request succeeded)
 - 消息说明: 按名称请求查找 SID 成功
 - 本地目标消息格式: <timestamp> <seq_num> 24330 DEBUG External-Active-Directory: Lookup SID By Name request succeeded, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24330 DEBUG External-Active-Directory: Lookup SID By Name request succeeded, <log details>

- 消息代码: 24331
 - 严重性: 调试 (DEBUG)
 - 消息文本: 按名称请求查找 SID 失败 (Lookup SID By Name request failed)
 - 消息说明: 按名称请求查找 SID 失败
 - 本地目标消息格式: <timestamp> <seq_num> 24331 DEBUG External-Active-Directory: Lookup SID By Name request failed, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24331 DEBUG External-Active-Directory: Lookup SID By Name request failed, <log details>

- 消息代码: 24332
 - 严重性: 调试 (DEBUG)
 - 消息文本: 按 SID 请求查找对象成功 (Lookup Object By SID request succeeded)
 - 消息说明: 按 SID 请求查找对象成功
 - 本地目标消息格式: <timestamp> <seq_num> 24332 DEBUG External-Active-Directory: Lookup Object By SID request succeeded, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24332 DEBUG External-Active-Directory: Lookup Object By SID request succeeded, <log details>

- 消息代码: 24333
 - 严重性: 调试 (DEBUG)
 - 消息文本: 按 SID 请求查找对象失败 (Lookup Object By SID request failed)
 - 消息说明: 按 SID 请求查找对象失败
 - 本地目标消息格式: <timestamp> <seq_num> 24333 DEBUG External-Active-Directory: Lookup Object By SID request failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24333 DEBUG External-Active-Directory:
Lookup Object By SID request failed, <log details>

- 消息代码: 24336

严重性: 调试 (DEBUG)

消息文本: 已缓存主题对象 (Subject object cached)

消息说明: 已缓存主题对象

本地目标消息格式: <timestamp> <seq_num> 24336 DEBUG External-Active-Directory: Subject
object cached, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24336 DEBUG External-Active-Directory:
Subject object cached, <log details>

- 消息代码: 24337

严重性: 调试 (DEBUG)

消息文本: 身份验证票证 (TGT) 请求成功 (Authentication Ticket (TGT) request succeeded)

消息说明: 身份验证票证 (TGT) 请求成功

本地目标消息格式: <timestamp> <seq_num> 24337 DEBUG External-Active-Directory: Authentication
Ticket (TGT) request succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24337 DEBUG External-Active-Directory:
Authentication Ticket (TGT) request succeeded, <log details>

- 消息代码: 24338

严重性: 调试 (DEBUG)

消息文本: 身份验证票证 (TGT) 请求失败 (Authentication Ticket (TGT) request failed)

消息说明: 身份验证票证 (TGT) 请求失败

本地目标消息格式: <timestamp> <seq_num> 24338 DEBUG External-Active-Directory: Authentication
Ticket (TGT) request failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24338 DEBUG External-Active-Directory:
Authentication Ticket (TGT) request failed, <log details>

- 消息代码: 24339

严重性: 调试 (DEBUG)

消息文本: 服务票证请求成功 (Service Ticket request succeeded)

消息说明: 服务票证请求成功

本地目标消息格式: <timestamp> <seq_num> 24339 DEBUG External-Active-Directory: Service Ticket request succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24339 DEBUG External-Active-Directory: Service Ticket request succeeded, <log details>

- 消息代码: 24340

严重性: 调试 (DEBUG)

消息文本: 服务票证请求失败 (Service Ticket request failed)

消息说明: 服务票证请求失败

本地目标消息格式: <timestamp> <seq_num> 24340 DEBUG External-Active-Directory: Service Ticket request failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24340 DEBUG External-Active-Directory: Service Ticket request failed, <log details>

- 消息代码: 24341

严重性: 调试 (DEBUG)

消息文本: 服务票证验证成功 (Service Ticket validation succeeded)

消息说明: 服务票证验证成功

本地目标消息格式: <timestamp> <seq_num> 24341 DEBUG External-Active-Directory: Service Ticket validation succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24341 DEBUG External-Active-Directory: Service Ticket validation succeeded, <log details>

- 消息代码: 24342

严重性: 调试 (DEBUG)

消息文本: 服务票证验证失败 (Service Ticket validation failed)

消息说明: 服务票证验证失败

本地目标消息格式: <timestamp> <seq_num> 24342 DEBUG External-Active-Directory: Service Ticket validation failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24342 DEBUG External-Active-Directory: Service Ticket validation failed, <log details>

- 消息代码: 24343

严重性: 调试 (DEBUG)

消息文本: RPC 登录请求成功 (RPC Logon request succeeded)

消息说明: RPC 登录请求成功

本地目标消息格式: <timestamp> <seq_num> 24343 DEBUG External-Active-Directory: RPC Logon request succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24343 DEBUG External-Active-Directory: RPC Logon request succeeded, <log details>

- 消息代码: 24344

严重性: 调试 (DEBUG)

消息文本: RPC 登录请求失败 (RPC Logon request failed)

消息说明: RPC 登录请求失败

本地目标消息格式: <timestamp> <seq_num> 24344 DEBUG External-Active-Directory: RPC Logon request failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24344 DEBUG External-Active-Directory: RPC Logon request failed, <log details>

- 消息代码: 24345

严重性: 调试 (DEBUG)

消息文本: RPC 更改密码请求成功 (RPC Change Password request succeeded)

消息说明: RPC 更改密码请求成功

本地目标消息格式: <timestamp> <seq_num> 24345 DEBUG External-Active-Directory: RPC Change Password request succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24345 DEBUG External-Active-Directory: RPC Change Password request succeeded, <log details>

- 消息代码: 24346

严重性: 调试 (DEBUG)

消息文本: RPC 更改密码请求失败 (RPC Change Password request failed)

消息说明: RPC 更改密码请求失败

本地目标消息格式: <timestamp> <seq_num> 24346 DEBUG External-Active-Directory: RPC Change Password request failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24346 DEBUG External-Active-Directory: RPC Change Password request failed, <log details>

- 消息代码: 24347

严重性: 错误 (ERROR)

消息文本: 帐户已禁用 (Account disabled)

消息说明: 帐户已禁用

本地目标消息格式: <timestamp> <seq_num> 24347 ERROR External-Active-Directory: Account disabled, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24347 ERROR External-Active-Directory: Account disabled, <log details>

- 消息代码: 24348

严重性: 错误 (ERROR)

消息文本: 帐户已锁定 (Account locked)

消息说明: 帐户已锁定

本地目标消息格式: <timestamp> <seq_num> 24348 ERROR External-Active-Directory: Account locked, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24348 ERROR External-Active-Directory: Account locked, <log details>

- 消息代码: 24349

严重性: 错误 (ERROR)

消息文本: 帐户已过期 (Account expired)

消息说明: 帐户已过期

本地目标消息格式: <timestamp> <seq_num> 24349 ERROR External-Active-Directory: Account expired, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24349 ERROR External-Active-Directory: Account expired, <log details>

- 消息代码: 24350

严重性: 错误 (ERROR)

消息文本: 密码已过期 (Password expired)

消息说明: 密码已过期

本地目标消息格式: <timestamp> <seq_num> 24350 ERROR External-Active-Directory: Password expired, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24350 ERROR External-Active-Directory: Password expired, <log details>

- 消息代码: 24351

严重性: 调试 (DEBUG)

消息文本: 帐户验证成功 (Account validation succeeded)

消息说明: 帐户验证成功

本地目标消息格式: <timestamp> <seq_num> 24351 DEBUG External-Active-Directory: Account validation succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24351 DEBUG External-Active-Directory: Account validation succeeded, <log details>

• 消息代码: 24352

严重性: 调试 (DEBUG)

消息文本: 身份解析失败 (Identity resolution failed)

消息说明: 身份解析失败

本地目标消息格式: <timestamp> <seq_num> 24352 DEBUG External-Active-Directory: Identity resolution failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24352 DEBUG External-Active-Directory: Identity resolution failed, <log details>

• 消息代码: 24353

严重性: 调试 (DEBUG)

消息文本: 正在解析身份 (Resolving identity)

消息说明: 正在解析身份

本地目标消息格式: <timestamp> <seq_num> 24353 DEBUG External-Active-Directory: Resolving identity, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24353 DEBUG External-Active-Directory: Resolving identity, <log details>

• 消息代码: 24354

严重性: 调试 (DEBUG)

消息文本: LDAP 抓取未在域中找到匹配帐户 (LDAP fetch found no matching account in domain)

消息说明: LDAP 抓取未在域中找到匹配帐户

本地目标消息格式: <timestamp> <seq_num> 24354 DEBUG External-Active-Directory: LDAP fetch found no matching account in domain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24354 DEBUG External-Active-Directory: LDAP fetch found no matching account in domain, <log details>

- 消息代码: 24355
严重性: 调试 (DEBUG)
消息文本: LDAP 抓取成功 (LDAP fetch succeeded)
消息说明: LDAP 抓取成功
本地目标消息格式: <timestamp> <seq_num> 24355 DEBUG External-Active-Directory: LDAP fetch succeeded, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24355 DEBUG External-Active-Directory: LDAP fetch succeeded, <log details>
- 消息代码: 24356
严重性: 错误 (ERROR)
消息文本: LDAP 抓取失败 (LDAP fetch failed)
消息说明: LDAP 抓取失败
本地目标消息格式: <timestamp> <seq_num> 24356 ERROR External-Active-Directory: LDAP fetch failed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24356 ERROR External-Active-Directory: LDAP fetch failed, <log details>
- 消息代码: 24357
严重性: 调试 (DEBUG)
消息文本: 重写了传入身份 (Incoming identity was rewritten)
消息说明: 重写了传入身份
本地目标消息格式: <timestamp> <seq_num> 24357 DEBUG External-Active-Directory: Incoming identity was rewritten, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24357 DEBUG External-Active-Directory: Incoming identity was rewritten, <log details>
- 消息代码: 24358
严重性: 调试 (DEBUG)
消息文本: 未找到任何现存身份重写规则的匹配项 (Match was not found for any existing identity rewrite rule)
消息说明: 未找到任何现存身份重写规则的匹配项
本地目标消息格式: <timestamp> <seq_num> 24358 DEBUG External-Active-Directory: Match was not found for any existing identity rewrite rule, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24358 DEBUG External-Active-Directory:
Match was not found for any existing identity rewrite rule, <log details>

- 消息代码: 24359

严重性: 调试 (DEBUG)

消息文本: 未重写传入身份 (Incoming identity was not rewritten)

消息说明: 未重写传入身份

本地目标消息格式: <timestamp> <seq_num> 24359 DEBUG External-Active-Directory: Incoming
identity was not rewritten, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24359 DEBUG External-Active-Directory:
Incoming identity was not rewritten, <log details>

- 消息代码: 24360

严重性: 调试 (DEBUG)

消息文本: [诊断步骤]: 已找到身份, 但因其不在身份验证域内, 所以已被过滤掉 ([Diagnostic
step]: Identity was found, but filtered since it is not in authentication domsins)

消息说明: [诊断步骤]: 已找到身份, 但因其不在身份验证域内, 所以已被过滤掉

本地目标消息格式: <timestamp> <seq_num> 24360 DEBUG External-Active-Directory: [Diagnostic
step]: Identity was found, but filtered since it is not in authentication domsins, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24360 DEBUG External-Active-Directory:
[Diagnostic step]: Identity was found, but filtered since it is not in authentication domsins, <log details>

- 消息代码: 24361

严重性: 信息 (INFO)

消息文本: 部分已配置的加入点禁用计算机身份验证 (Machine authentication is disabled for some
of the configured join points)

消息说明: 部分已配置的加入点禁用计算机身份验证

本地目标消息格式: <timestamp> <seq_num> 24361 INFO External-Active-Directory: Machine
authentication is disabled for some of the configured join points, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24361 INFO External-Active-Directory:
Machine authentication is disabled for some of the configured join points, <log details>

- 消息代码: 24362

严重性: 调试 (DEBUG)

消息文本: 客户端证书与 AD 帐户证书相匹配 (Client certificate matches AD account certificate)

消息说明: 客户端证书与 AD 帐户证书相匹配

本地目标消息格式: <timestamp> <seq_num> 24362 DEBUG Authentication: Client certificate matches AD account certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24362 DEBUG Authentication: Client certificate matches AD account certificate, <log details>

- 消息代码: 24363

严重性: 调试 (DEBUG)

消息文本: 客户端证书与 AD 帐户证书不匹配 (Client certificate does not match AD account certificate)

消息说明: 客户端证书与 AD 帐户证书不匹配

本地目标消息格式: <timestamp> <seq_num> 24363 DEBUG Authentication: Client certificate does not match AD account certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24363 DEBUG Authentication: Client certificate does not match AD account certificate, <log details>

- 消息代码: 24364

严重性: 调试 (DEBUG)

消息文本: 使用证书匹配解析证书身份模糊性 (Resolve certificate identity ambiguity using certificates match)

消息说明: 使用证书匹配解析证书身份模糊性

本地目标消息格式: <timestamp> <seq_num> 24364 DEBUG Authentication: Resolve certificate identity ambiguity using certificates match, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24364 DEBUG Authentication: Resolve certificate identity ambiguity using certificates match, <log details>

- 消息代码: 24365

严重性: 调试 (DEBUG)

消息文本: 使用密码验证解析身份模糊性 (Resolve identity ambiguity using password verification)

消息说明: 使用密码验证解析身份模糊性

本地目标消息格式: <timestamp> <seq_num> 24365 DEBUG Authentication: Resolve identity ambiguity using password verification, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24365 DEBUG Authentication: Resolve identity ambiguity using password verification, <log details>

- 消息代码: 24366

严重性: 调试 (DEBUG)

消息文本: 正在跳过未加入的域 (Skipping unjoined domain)

消息说明: 由于 ISE 未加入指定域, 因此跳过了加入点中的身份搜索

本地目标消息格式: <timestamp> <seq_num> 24366 DEBUG External-Active-Directory: Skipping unjoined domain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24366 DEBUG External-Active-Directory: Skipping unjoined domain, <log details>

- 消息代码: 24367

严重性: 信息 (INFO)

消息文本: 正在跳过无法使用的域 (Skipping unusable domain)

消息说明: 由于指定的域无法使用, 因此跳过了加入点中的身份搜索

本地目标消息格式: <timestamp> <seq_num> 24367 INFO External-Active-Directory: Skipping unusable domain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24367 INFO External-Active-Directory: Skipping unusable domain, <log details>

- 消息代码: 24368

严重性: 信息 (INFO)

消息文本: 正在跳过不可用的域 (Skipping unavailable domain)

消息说明: 由于指定的域不可用, 因此跳过了加入点中的身份搜索

本地目标消息格式: <timestamp> <seq_num> 24368 INFO External-Active-Directory: Skipping unavailable domain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24368 INFO External-Active-Directory: Skipping unavailable domain, <log details>

- 消息代码: 24369

严重性: 信息 (INFO)

消息文本: 正在跳过不可用的林 (Skipping unavailable forest)

消息说明: 由于指定的林不可用, 因此跳过了加入点中的身份搜索

本地目标消息格式: <timestamp> <seq_num> 24369 INFO External-Active-Directory: Skipping unavailable forest, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24369 INFO External-Active-Directory: Skipping unavailable forest, <log details>

- 消息代码: 24370
 - 严重性: 错误 (ERROR)
 - 消息文本: 已撤销用户凭证。(User credentials have been revoked.)
 - 消息说明: 已撤销用户凭证。
 - 本地目标消息格式: <timestamp> <seq_num> 24370 ERROR External-Active-Directory: User credentials have been revoked., <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24370 ERROR External-Active-Directory: User credentials have been revoked., <log details>

- 消息代码: 24371
 - 严重性: 错误 (ERROR)
 - 消息文本: ISE 计算机帐户没有获取组所需的权限。(The ISE machine account does not have the required privileges to fetch groups.)
 - 消息说明: ISE 计算机帐户没有获取组所需的权限。
 - 本地目标消息格式: <timestamp> <seq_num> 24371 ERROR External-Active-Directory: The ISE machine account does not have the required privileges to fetch groups., <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24371 ERROR External-Active-Directory: The ISE machine account does not have the required privileges to fetch groups., <log details>

- 消息代码: 24400
 - 严重性: 信息 (INFO)
 - 消息文本: 已成功与 ISE Active Directory 代理建立连接 (Connection to ISE Active Directory agent established successfully)
 - 消息说明: 已成功与 ISE Active Directory 代理建立连接
 - 本地目标消息格式: <timestamp> <seq_num> 24400 INFO External-Active-Directory: Connection to ISE Active Directory agent established successfully, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24400 INFO External-Active-Directory: Connection to ISE Active Directory agent established successfully, <log details>

- 消息代码: 24401
 - 严重性: 错误 (ERROR)
 - 消息文本: 无法与 ISE Active Directory 代理建立连接 (Could not establish connection with ISE Active Directory agent)
 - 消息说明: 无法与 ISE Active Directory 代理建立连接
 - 本地目标消息格式: <timestamp> <seq_num> 24401 ERROR External-Active-Directory: Could not establish connection with ISE Active Directory agent, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24401 ERROR External-Active-Directory:
Could not establish connection with ISE Active Directory agent, <log details>

- 消息代码: 24402

严重性: 信息 (INFO)

消息文本: Active Directory 用户身份验证成功 (User authentication against Active Directory succeeded)

消息说明: Active Directory 用户身份验证成功

本地目标消息格式: <timestamp> <seq_num> 24402 INFO External-Active-Directory: User
authentication against Active Directory succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24402 INFO External-Active-Directory:
User authentication against Active Directory succeeded, <log details>

- 消息代码: 24403

严重性: 错误 (ERROR)

消息文本: Active Directory 用户身份验证失败 (User authentication against Active Directory failed)

消息说明: Active Directory 用户身份验证失败

本地目标消息格式: <timestamp> <seq_num> 24403 ERROR External-Active-Directory: User
authentication against Active Directory failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24403 ERROR External-Active-Directory:
User authentication against Active Directory failed, <log details>

- 消息代码: 24404

严重性: 调试 (DEBUG)

消息文本: Active Directory 操作因输入参数无效而失败 (Active Directory operation failed because
of an invalid input parameter)

消息说明: Active Directory 操作因输入参数无效而失败

本地目标消息格式: <timestamp> <seq_num> 24404 DEBUG External-Active-Directory: Active
Directory operation failed because of an invalid input parameter, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24404 DEBUG External-Active-Directory:
Active Directory operation failed because of an invalid input parameter, <log details>

- 消息代码: 24405

严重性: 错误 (ERROR)

消息文本: Active Directory 操作因超时错误而失败 (Active Directory operation failed because of a
timeout error)

消息说明: Active Directory 操作因超时错误而失败

本地目标消息格式: <timestamp> <seq_num> 24405 ERROR External-Active-Directory: Active Directory operation failed because of a timeout error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24405 ERROR External-Active-Directory: Active Directory operation failed because of a timeout error, <log details>

- 消息代码: 24406

严重性: 调试 (DEBUG)

消息文本: Active Directory 用户身份验证失败, 因为用户的凭证无效 (User authentication against Active Directory failed since user has invalid credentials)

消息说明: Active Directory 用户身份验证失败, 因为用户的凭证无效

本地目标消息格式: <timestamp> <seq_num> 24406 DEBUG External-Active-Directory: User authentication against Active Directory failed since user has invalid credentials, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24406 DEBUG External-Active-Directory: User authentication against Active Directory failed since user has invalid credentials, <log details>

- 消息代码: 24407

严重性: 调试 (DEBUG)

消息文本: Active Directory 用户身份验证失败, 因为用户需要更改自己的密码 (User authentication against Active Directory failed since user is required to change his password)

消息说明: Active Directory 用户身份验证失败, 因为用户需要更改自己的密码

本地目标消息格式: <timestamp> <seq_num> 24407 DEBUG External-Active-Directory: User authentication against Active Directory failed since user is required to change his password, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24407 DEBUG External-Active-Directory: User authentication against Active Directory failed since user is required to change his password, <log details>

- 消息代码: 24408

严重性: 调试 (DEBUG)

消息文本: Active Directory 用户身份验证失败, 因为用户输入的密码错误 (User authentication against Active Directory failed since user has entered the wrong password)

消息说明: Active Directory 用户身份验证失败, 因为用户输入的密码错误

本地目标消息格式: <timestamp> <seq_num> 24408 DEBUG External-Active-Directory: User authentication against Active Directory failed since user has entered the wrong password, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24408 DEBUG External-Active-Directory:

User authentication against Active Directory failed since user has entered the wrong password, <log details>

- 消息代码: 24409

严重性: 调试 (DEBUG)

消息文本: Active Directory 用户身份验证失败, 因为用户的帐户已禁用 (User authentication against Active Directory failed since the user's account is disabled)

消息说明: Active Directory 用户身份验证失败, 因为用户的帐户已禁用

本地目标消息格式: <timestamp> <seq_num> 24409 DEBUG External-Active-Directory: User authentication against Active Directory failed since the user's account is disabled, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24409 DEBUG External-Active-Directory: User authentication against Active Directory failed since the user's account is disabled, <log details>

- 消息代码: 24410

严重性: 调试 (DEBUG)

消息文本: Active Directory 用户身份验证失败, 因为已认定用户登录时间被限制 (User authentication against Active Directory failed since user is considered to be in restricted logon hours)

消息说明: Active Directory 用户身份验证失败, 因为已认定用户登录时间被限制

本地目标消息格式: <timestamp> <seq_num> 24410 DEBUG External-Active-Directory: User authentication against Active Directory failed since user is considered to be in restricted logon hours, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24410 DEBUG External-Active-Directory: User authentication against Active Directory failed since user is considered to be in restricted logon hours, <log details>

- 消息代码: 24411

严重性: 调试 (DEBUG)

消息文本: 在 Active Directory 上更改密码失败, 因为用户的密码不合规 (Change password against Active Directory failed since user has a non-compliant password)

消息说明: 在 Active Directory 上更改密码失败, 因为用户的密码不合规

本地目标消息格式: <timestamp> <seq_num> 24411 DEBUG External-Active-Directory: Change password against Active Directory failed since user has a non-compliant password, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24411 DEBUG External-Active-Directory: Change password against Active Directory failed since user has a non-compliant password, <log details>

- 消息代码: 24412

严重性: 调试 (DEBUG)

消息文本: 在 Active Directory 中找不到用户 (User not found in Active Directory)

消息说明: 在 Active Directory 中找不到用户

本地目标消息格式: <timestamp> <seq_num> 24412 DEBUG External-Active-Directory: User not found in Active Directory, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24412 DEBUG External-Active-Directory: User not found in Active Directory, <log details>

- 消息代码: 24413

严重性: 调试 (DEBUG)

消息文本: Active Directory 无法识别用户的域 (User's domain is not recognized by Active Directory)

消息说明: Active Directory 无法识别用户的域

本地目标消息格式: <timestamp> <seq_num> 24413 DEBUG External-Active-Directory: User's domain is not recognized by Active Directory, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24413 DEBUG External-Active-Directory: User's domain is not recognized by Active Directory, <log details>

- 消息代码: 24414

严重性: 调试 (DEBUG)

消息文本: Active Directory 用户身份验证失败, 因为用户的帐户已过期 (User authentication against Active Directory failed since the user's account has expired)

消息说明: Active Directory 用户身份验证失败, 因为用户的帐户已过期

本地目标消息格式: <timestamp> <seq_num> 24414 DEBUG External-Active-Directory: User authentication against Active Directory failed since the user's account has expired, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24414 DEBUG External-Active-Directory: User authentication against Active Directory failed since the user's account has expired, <log details>

- 消息代码: 24415

严重性: 调试 (DEBUG)

消息文本: Active Directory 用户身份验证失败, 因为用户的帐户已锁定 (User authentication against Active Directory failed since user's account is locked out)

消息说明: Active Directory 用户身份验证失败, 因为用户的帐户已锁定

本地目标消息格式: <timestamp> <seq_num> 24415 DEBUG External-Active-Directory: User authentication against Active Directory failed since user's account is locked out, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24415 DEBUG External-Active-Directory: User authentication against Active Directory failed since user's account is locked out, <log details>

- 消息代码: 24416
 - 严重性: 信息 (INFO)
 - 消息文本: 从 Active Directory 检索用户组成功 (User's Groups retrieval from Active Directory succeeded)
 - 消息说明: 从 Active Directory 检索用户组成功
 - 本地目标消息格式: <timestamp> <seq_num> 24416 INFO External-Active-Directory: User's Groups retrieval from Active Directory succeeded, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24416 INFO External-Active-Directory: User's Groups retrieval from Active Directory succeeded, <log details>

- 消息代码: 24417
 - 严重性: 错误 (ERROR)
 - 消息文本: 从 Active Directory 检索用户组失败 (User's Groups retrieval from Active Directory failed)
 - 消息说明: 从 Active Directory 检索用户组失败
 - 本地目标消息格式: <timestamp> <seq_num> 24417 ERROR External-Active-Directory: User's Groups retrieval from Active Directory failed, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24417 ERROR External-Active-Directory: User's Groups retrieval from Active Directory failed, <log details>

- 消息代码: 24418
 - 严重性: 错误 (ERROR)
 - 消息文本: Active Directory 上的计算机身份验证失败, 因为已在配置中将其禁用 (Machine authentication against Active Directory failed since it is disabled in configuration)
 - 消息说明: Active Directory 上的计算机身份验证失败, 因为已在配置中将其禁用
 - 本地目标消息格式: <timestamp> <seq_num> 24418 ERROR External-Active-Directory: Machine authentication against Active Directory failed since it is disabled in configuration, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24418 ERROR External-Active-Directory: Machine authentication against Active Directory failed since it is disabled in configuration, <log details>

- 消息代码: 24419
 - 严重性: 错误 (ERROR)
 - 消息文本: 从 Active Directory 检索用户属性失败 (User's Attributes retrieval from Active Directory failed)
 - 消息说明: 从 Active Directory 检索用户属性失败
 - 本地目标消息格式: <timestamp> <seq_num> 24419 ERROR External-Active-Directory: User's Attributes retrieval from Active Directory failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24419 ERROR External-Active-Directory:
User's Attributes retrieval from Active Directory failed, <log details>

- 消息代码: 24420

严重性: 信息 (INFO)

消息文本: 从 Active Directory 检索用户属性成功 (User's Attributes retrieval from Active Directory succeeded)

消息说明: 从 Active Directory 检索用户属性成功

本地目标消息格式: <timestamp> <seq_num> 24420 INFO External-Active-Directory: User's Attributes retrieval from Active Directory succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24420 INFO External-Active-Directory:
User's Attributes retrieval from Active Directory succeeded, <log details>

- 消息代码: 24421

严重性: 调试 (DEBUG)

消息文本: 在 Active Directory 上更改密码失败, 因为已在配置中将其禁用 (Change password against Active Directory failed since it is disabled in configuration)

消息说明: 在 Active Directory 上更改密码失败, 因为已在配置中将其禁用

本地目标消息格式: <timestamp> <seq_num> 24421 DEBUG External-Active-Directory: Change password against Active Directory failed since it is disabled in configuration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24421 DEBUG External-Active-Directory:
Change password against Active Directory failed since it is disabled in configuration, <log details>

- 消息代码: 24422

严重性: 信息 (INFO)

消息文本: ISE 已确认 Active Directory 中用户的上一次成功的计算机身份验证 (ISE has confirmed previous successful machine authentication for user in Active Directory)

消息说明: ISE 已确认 Active Directory 中用户的上一次成功的计算机身份验证

本地目标消息格式: <timestamp> <seq_num> 24422 INFO External-Active-Directory: ISE has confirmed previous successful machine authentication for user in Active Directory, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24422 INFO External-Active-Directory: ISE has confirmed previous successful machine authentication for user in Active Directory, <log details>

- 消息代码: 24423

严重性: 调试 (DEBUG)

消息文本: ISE 未能确认上一次成功的计算机身份验证 (ISE has not been able to confirm previous successful machine authentication)

消息说明: ISE 未能确认上一次成功的计算机身份验证

本地目标消息格式: <timestamp> <seq_num> 24423 DEBUG External-Active-Directory: ISE has not been able to confirm previous successful machine authentication, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24423 DEBUG External-Active-Directory: ISE has not been able to confirm previous successful machine authentication, <log details>

- 消息代码: 24424

严重性: 调试 (DEBUG)

消息文本: 在 Active Directory 中检测到了不合规属性 (Noncompliant attributes detected in Active Directory)

消息说明: 在 Active Directory 中检测到了不合规属性

本地目标消息格式: <timestamp> <seq_num> 24424 DEBUG External-Active-Directory: Noncompliant attributes detected in Active Directory, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24424 DEBUG External-Active-Directory: Noncompliant attributes detected in Active Directory, <log details>

- 消息代码: 24425

严重性: 信息 (INFO)

消息文本: Active Directory 上的用户更改密码成功 (User change password against Active Directory succeeded)

消息说明: Active Directory 上的用户更改密码成功

本地目标消息格式: <timestamp> <seq_num> 24425 INFO External-Active-Directory: User change password against Active Directory succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24425 INFO External-Active-Directory: User change password against Active Directory succeeded, <log details>

- 消息代码: 24426

严重性: 错误 (ERROR)

消息文本: Active Directory 上的用户更改密码失败 (User change password against Active Directory failed)

消息说明: Active Directory 上的用户更改密码失败

本地目标消息格式: <timestamp> <seq_num> 24426 ERROR External-Active-Directory: User change password against Active Directory failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24426 ERROR External-Active-Directory:
User change password against Active Directory failed, <log details>

- 消息代码: 24427

严重性: 错误 (ERROR)

消息文本: 访问 Active Directory 失败 (Access to Active Directory failed)

消息说明: 访问 Active Directory 失败

本地目标消息格式: <timestamp> <seq_num> 24427 ERROR External-Active-Directory: Access to
Active Directory failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24427 ERROR External-Active-Directory:
Access to Active Directory failed, <log details>

- 消息代码: 24428

严重性: 错误 (ERROR)

消息文本: 在 LRPC、LDAP 或 KERBEROS 中发生了与连接相关的错误 (Connection related error
has occurred in either LRPC, LDAP or KERBEROS)

消息说明: 此 RPC 连接问题可能是由于末节收到了错误数据造成的

本地目标消息格式: <timestamp> <seq_num> 24428 ERROR External-Active-Directory: Connection
related error has occurred in either LRPC, LDAP or KERBEROS, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24428 ERROR External-Active-Directory:
Connection related error has occurred in either LRPC, LDAP or KERBEROS, <log details>

- 消息代码: 24429

严重性: 错误 (ERROR)

消息文本: 无法与 Active Directory 建立连接 (Could not establish connection with Active Directory)

消息说明: 无法与 Active Directory 建立连接

本地目标消息格式: <timestamp> <seq_num> 24429 ERROR External-Active-Directory: Could not
establish connection with Active Directory, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24429 ERROR External-Active-Directory:
Could not establish connection with Active Directory, <log details>

- 消息代码: 24430

严重性: 调试 (DEBUG)

消息文本: 正在 Active Directory 上验证用户身份 (Authenticating user against Active Directory)

消息说明: 正在 Active Directory 上验证用户身份

本地目标消息格式: <timestamp> <seq_num> 24430 DEBUG External-Active-Directory: Authenticating user against Active Directory, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24430 DEBUG External-Active-Directory: Authenticating user against Active Directory, <log details>

- 消息代码: 24431

严重性: 调试 (DEBUG)

消息文本: 正在 Active Directory 上验证计算机身份 (Authenticating machine against Active Directory)

消息说明: 正在 Active Directory 上验证计算机身份

本地目标消息格式: <timestamp> <seq_num> 24431 DEBUG External-Active-Directory: Authenticating machine against Active Directory, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24431 DEBUG External-Active-Directory: Authenticating machine against Active Directory, <log details>

- 消息代码: 24432

严重性: 调试 (DEBUG)

消息文本: 正在 Active Directory 中查找用户 (Looking up user in Active Directory)

消息说明: 正在 Active Directory 中查找用户

本地目标消息格式: <timestamp> <seq_num> 24432 DEBUG External-Active-Directory: Looking up user in Active Directory, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24432 DEBUG External-Active-Directory: Looking up user in Active Directory, <log details>

- 消息代码: 24433

严重性: 调试 (DEBUG)

消息文本: 正在 Active Directory 中查找计算机 (Looking up machine in Active Directory)

消息说明: 正在 Active Directory 中查找计算机

本地目标消息格式: <timestamp> <seq_num> 24433 DEBUG External-Active-Directory: Looking up machine in Active Directory, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24433 DEBUG External-Active-Directory: Looking up machine in Active Directory, <log details>

- 消息代码: 24434

严重性: 调试 (DEBUG)

消息文本: 正在 Active Directory 中更改密码 (Performing Change Password in Active Directory)

消息说明：正在 Active Directory 中更改密码

本地目标消息格式：<timestamp> <seq_num> 24434 DEBUG External-Active-Directory: Performing Change Password in Active Directory, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24434 DEBUG External-Active-Directory: Performing Change Password in Active Directory, <log details>

- 消息代码：24435

严重性：信息 (INFO)

消息文本：从 Active Directory 检索计算机组成功 (Machine Groups retrieval from Active Directory succeeded)

消息说明：从 Active Directory 检索计算机组成功

本地目标消息格式：<timestamp> <seq_num> 24435 INFO External-Active-Directory: Machine Groups retrieval from Active Directory succeeded, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24435 INFO External-Active-Directory: Machine Groups retrieval from Active Directory succeeded, <log details>

- 消息代码：24436

严重性：错误 (ERROR)

消息文本：在 Active Directory 中查找计算机失败 (Machine Lookup in Active Directory failed)

消息说明：在 Active Directory 中查找计算机失败

本地目标消息格式：<timestamp> <seq_num> 24436 ERROR External-Active-Directory: Machine Lookup in Active Directory failed, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24436 ERROR External-Active-Directory: Machine Lookup in Active Directory failed, <log details>

- 消息代码：24437

严重性：调试 (DEBUG)

消息文本：在 Active Directory 中找不到计算机 (Machine not found in Active Directory)

消息说明：在 Active Directory 中找不到计算机

本地目标消息格式：<timestamp> <seq_num> 24437 DEBUG External-Active-Directory: Machine not found in Active Directory, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24437 DEBUG External-Active-Directory: Machine not found in Active Directory, <log details>

- 消息代码：24438

严重性: 错误 (ERROR)

消息文本: 在 Active Directory 中发现特定计算机多次出现 (Found multiple occurrences of the machine in Active Directory)

消息说明: 在 Active Directory 中发现特定计算机多次出现

本地目标消息格式: <timestamp> <seq_num> 24438 ERROR External-Active-Directory: Found multiple occurrences of the machine in Active Directory, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24438 ERROR External-Active-Directory: Found multiple occurrences of the machine in Active Directory, <log details>

- 消息代码: 24439

严重性: 信息 (INFO)

消息文本: 从 Active Directory 检索计算机属性成功 (Machine Attributes retrieval from Active Directory succeeded)

消息说明: 从 Active Directory 检索计算机属性成功

本地目标消息格式: <timestamp> <seq_num> 24439 INFO External-Active-Directory: Machine Attributes retrieval from Active Directory succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24439 INFO External-Active-Directory: Machine Attributes retrieval from Active Directory succeeded, <log details>

- 消息代码: 24440

严重性: 错误 (ERROR)

消息文本: Active Directory 中不存在计算机主组名称 (Machine primary group name does not exist in Active Directory)

消息说明: Active Directory 中不存在计算机主组名称

本地目标消息格式: <timestamp> <seq_num> 24440 ERROR External-Active-Directory: Machine primary group name does not exist in Active Directory, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24440 ERROR External-Active-Directory: Machine primary group name does not exist in Active Directory, <log details>

- 消息代码: 24441

严重性: 错误 (ERROR)

消息文本: 不允许 ISE 计算机帐户登录 (ISE machine account is not permitted to log on)

消息说明: 不允许 ISE 计算机帐户登录

本地目标消息格式: <timestamp> <seq_num> 24441 ERROR External-Active-Directory: ISE machine account is not permitted to log on, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24441 ERROR External-Active-Directory:
ISE machine account is not permitted to log on, <log details>

- 消息代码: 24442

严重性: 错误 (ERROR)

消息文本: 从 Active Directory 检索用户相关对象的操作失败 (User-related object retrieval operation from Active Directory has failed)

消息说明: 从 Active Directory 检索用户相关对象的操作失败

本地目标消息格式: <timestamp> <seq_num> 24442 ERROR External-Active-Directory: User-related object retrieval operation from Active Directory has failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24442 ERROR External-Active-Directory:
User-related object retrieval operation from Active Directory has failed, <log details>

- 消息代码: 24443

严重性: 信息 (INFO)

消息文本: 从 Active Directory 检索用户组部分成功 (User's Groups retrieval from Active Directory succeeded partially)

消息说明: 只进行了部分用户组检索。这是因为按组 SID 查找失败, 或未找到该“规范名称”属性。

本地目标消息格式: <timestamp> <seq_num> 24443 INFO External-Active-Directory: User's Groups retrieval from Active Directory succeeded partially, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24443 INFO External-Active-Directory:
User's Groups retrieval from Active Directory succeeded partially, <log details>

- 消息代码: 24444

严重性: 错误 (ERROR)

消息文本: Active Directory 操作因 ISE 中某个未指定的错误而失败 (Active Directory operation has failed because of an unspecified error in the ISE)

消息说明: Active Directory 操作因 ISE 中某个未指定的错误而失败

本地目标消息格式: <timestamp> <seq_num> 24444 ERROR External-Active-Directory: Active Directory operation has failed because of an unspecified error in the ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24444 ERROR External-Active-Directory:
Active Directory operation has failed because of an unspecified error in the ISE, <log details>

- 消息代码: 24445

严重性: 信息 (INFO)

消息文本: 从 Active Directory 检索计算机组部分成功 (Machine Groups retrieval from Active Directory succeeded partially)

消息说明: 只进行了计算机组部分检索, 因为未找到“规范名称”属性。

本地目标消息格式: <timestamp> <seq_num> 24445 INFO External-Active-Directory: Machine Groups retrieval from Active Directory succeeded partially, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24445 INFO External-Active-Directory: Machine Groups retrieval from Active Directory succeeded partially, <log details>

- 消息代码: 24446

严重性: 错误 (ERROR)

消息文本: 无法访问 Active Directory 域控制器 (Active Directory domain controller is unreachable)

消息说明: 无法访问 Active Directory 域控制器

本地目标消息格式: <timestamp> <seq_num> 24446 ERROR External-Active-Directory: Active Directory domain controller is unreachable, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24446 ERROR External-Active-Directory: Active Directory domain controller is unreachable, <log details>

- 消息代码: 24447

严重性: 错误 (ERROR)

消息文本: Active Directory 中的 ISE 设备计算机帐户已禁用、删除或重置 (ISE appliance machine account in Active Directory is disabled, deleted or reset)

消息说明: Active Directory 中的 ISE 设备计算机帐户已禁用、删除或重置。

本地目标消息格式: <timestamp> <seq_num> 24447 ERROR External-Active-Directory: ISE appliance machine account in Active Directory is disabled, deleted or reset, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24447 ERROR External-Active-Directory: ISE appliance machine account in Active Directory is disabled, deleted or reset, <log details>

- 消息代码: 24448

严重性: 错误 (ERROR)

消息文本: 从 Active Directory 检索用户对象因超时错误而失败 (User object retrieval from Active Directory failed because of a timeout error)

消息说明: 从 Active Directory 检索用户对象因超时错误而失败

本地目标消息格式: <timestamp> <seq_num> 24448 ERROR External-Active-Directory: User object retrieval from Active Directory failed because of a timeout error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24448 ERROR External-Active-Directory:
User object retrieval from Active Directory failed because of a timeout error, <log details>

- 消息代码: 24449

严重性: 错误 (ERROR)

消息文本: 从 Active Directory 检索用户组因超时错误而失败 (User's Groups retrieval from Active Directory failed because of a timeout error)

消息说明: 从 Active Directory 检索用户组因超时错误而失败

本地目标消息格式: <timestamp> <seq_num> 24449 ERROR External-Active-Directory: User's Groups retrieval from Active Directory failed because of a timeout error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24449 ERROR External-Active-Directory:
User's Groups retrieval from Active Directory failed because of a timeout error, <log details>

- 消息代码: 24450

严重性: 错误 (ERROR)

消息文本: 从 Active Directory 检索用户属性因超时错误而失败 (User's Attributes retrieval from Active Directory failed because of a timeout error)

消息说明: 从 Active Directory 检索用户属性因超时错误而失败

本地目标消息格式: <timestamp> <seq_num> 24450 ERROR External-Active-Directory: User's Attributes retrieval from Active Directory failed because of a timeout error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24450 ERROR External-Active-Directory:
User's Attributes retrieval from Active Directory failed because of a timeout error, <log details>

- 消息代码: 24451

严重性: 错误 (ERROR)

消息文本: 从 Active Directory 检索计算机对象因超时错误而失败 (Machine object retrieval from Active Directory failed because of a timeout error)

消息说明: 从 Active Directory 检索计算机对象因超时错误而失败

本地目标消息格式: <timestamp> <seq_num> 24451 ERROR External-Active-Directory: Machine object retrieval from Active Directory failed because of a timeout error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24451 ERROR External-Active-Directory:
Machine object retrieval from Active Directory failed because of a timeout error, <log details>

- 消息代码: 24452

严重性: 错误 (ERROR)

消息文本: 从 Active Directory 检索计算机主组因超时错误而失败 (Machine primary group retrieval from Active Directory failed because of a timeout error)

消息说明: 从 Active Directory 检索计算机主组因超时错误而失败

本地目标消息格式: <timestamp> <seq_num> 24452 ERROR External-Active-Directory: Machine primary group retrieval from Active Directory failed because of a timeout error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24452 ERROR External-Active-Directory: Machine primary group retrieval from Active Directory failed because of a timeout error, <log details>

- 消息代码: 24453

严重性: 错误 (ERROR)

消息文本: 从 Active Directory 检索计算机属性因超时错误而失败 (Machine Attributes retrieval from Active Directory failed because of a timeout error)

消息说明: 从 Active Directory 检索计算机属性因超时错误而失败

本地目标消息格式: <timestamp> <seq_num> 24453 ERROR External-Active-Directory: Machine Attributes retrieval from Active Directory failed because of a timeout error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24453 ERROR External-Active-Directory: Machine Attributes retrieval from Active Directory failed because of a timeout error, <log details>

- 消息代码: 24454

严重性: 错误 (ERROR)

消息文本: Active Directory 用户身份验证因超时错误而失败 (User authentication against Active Directory failed because of a timeout error)

消息说明: Active Directory 用户身份验证因超时错误而失败

本地目标消息格式: <timestamp> <seq_num> 24454 ERROR External-Active-Directory: User authentication against Active Directory failed because of a timeout error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24454 ERROR External-Active-Directory: User authentication against Active Directory failed because of a timeout error, <log details>

- 消息代码: 24455

严重性: 错误 (ERROR)

消息文本: 在 Active Directory 上更改密码因超时错误而失败 (Change password against Active Directory failed because of a timeout error)

消息说明: 在 Active Directory 上更改密码因超时错误而失败

本地目标消息格式: <timestamp> <seq_num> 24455 ERROR External-Active-Directory: Change password against Active Directory failed because of a timeout error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24455 ERROR External-Active-Directory:
Change password against Active Directory failed because of a timeout error, <log details>

- 消息代码: 24456

严重性: 警告 (WARN)

消息文本: 未能成功检索所有用户 Active Directory 组。其中一个组未按其 SID 进行检索 (Not all user Active Directory groups are retrieved successfully. One of the groups was not retrieved by its SID)

消息说明: 未能成功检索所有用户 Active Directory 组。其中一个组未按其 SID 进行检索

本地目标消息格式: <timestamp> <seq_num> 24456 WARN External-Active-Directory: Not all user Active Directory groups are retrieved successfully. One of the groups was not retrieved by its SID, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24456 WARN External-Active-Directory:
Not all user Active Directory groups are retrieved successfully. One of the groups was not retrieved by its SID, <log details>

- 消息代码: 24457

严重性: 警告 (WARN)

消息文本: 未能成功检索所有用户 Active Directory 组。一个或多个组规范名称未检索 (Not all user Active Directory groups are retrieved successfully. One or more of the group's canonical name was not retrieved)

消息说明: 未能成功检索所有用户 Active Directory 组。一个或多个组规范名称未检索

本地目标消息格式: <timestamp> <seq_num> 24457 WARN External-Active-Directory: Not all user Active Directory groups are retrieved successfully. One or more of the group's canonical name was not retrieved, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24457 WARN External-Active-Directory:
Not all user Active Directory groups are retrieved successfully. One or more of the group's canonical name was not retrieved, <log details>

- 消息代码: 24458

严重性: 警告 (WARN)

消息文本: 未能成功检索所有 Active Directory 属性 (Not all Active Directory attributes are retrieved successfully)

消息说明: 未能成功检索所有 Active Directory 属性

本地目标消息格式: <timestamp> <seq_num> 24458 WARN External-Active-Directory: Not all Active Directory attributes are retrieved successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24458 WARN External-Active-Directory:
Not all Active Directory attributes are retrieved successfully, <log details>

- 消息代码: 24459
 - 严重性: 警告 (WARN)
 - 消息文本: 主机 memberOf 组不存在或无法检索 (Host memberOf groups do not exist or cannot be retrieved)
 - 消息说明: 主机 memberOf 组不存在或无法检索
 - 本地目标消息格式: <timestamp> <seq_num> 24459 WARN External-Active-Directory: Host memberOf groups do not exist or cannot be retrieved, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24459 WARN External-Active-Directory: Host memberOf groups do not exist or cannot be retrieved, <log details>
- 消息代码: 24460
 - 严重性: 错误 (ERROR)
 - 消息文本: 该用户名在 Active Directory 中多次出现 (There are multiple occurrences of the user name in the Active directory)
 - 消息说明: 该用户名在 Active Directory 中多次出现
 - 本地目标消息格式: <timestamp> <seq_num> 24460 ERROR External-Active-Directory: There are multiple occurrences of the user name in the Active directory, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24460 ERROR External-Active-Directory: There are multiple occurrences of the user name in the Active directory, <log details>
- 消息代码: 24461
 - 严重性: 错误 (ERROR)
 - 消息文本: 无法在 Active Directory 中使用“用户查找”找到用户 (Could not locate the user in the Active directory using User Lookup)
 - 消息说明: 无法在 Active Directory 中使用“用户查找”找到用户
 - 本地目标消息格式: <timestamp> <seq_num> 24461 ERROR External-Active-Directory: Could not locate the user in the Active directory using User Lookup, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24461 ERROR External-Active-Directory: Could not locate the user in the Active directory using User Lookup, <log details>
- 消息代码: 24462
 - 严重性: 错误 (ERROR)
 - 消息文本: ISE Active Directory 模块内存不足 (The ISE Active Directory module does not have sufficient memory)
 - 消息说明: ISE Active Directory 模块内存不足

本地目标消息格式: <timestamp> <seq_num> 24462 ERROR External-Active-Directory: The ISE Active Directory module does not have sufficient memory, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24462 ERROR External-Active-Directory: The ISE Active Directory module does not have sufficient memory, <log details>

- 消息代码: 24463

严重性: 错误 (ERROR)

消息文本: ISE Active Directory 出现内部错误 (Internal error in the ISE Active Directory)

消息说明: 与 Active Directory 有关的函数可能收到非法的参数、选项或会话处理程序。或者, 此目录可能缺少参数、选项或会话处理程序。

本地目标消息格式: <timestamp> <seq_num> 24463 ERROR External-Active-Directory: Internal error in the ISE Active Directory, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24463 ERROR External-Active-Directory: Internal error in the ISE Active Directory, <log details>

- 消息代码: 24464

严重性: 错误 (ERROR)

消息文本: Active Directory 没有所需的权限 (The Active Directory does not have the required privileges)

消息说明: Active Directory 没有执行指定任务所需的权限。

本地目标消息格式: <timestamp> <seq_num> 24464 ERROR External-Active-Directory: The Active Directory does not have the required privileges, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24464 ERROR External-Active-Directory: The Active Directory does not have the required privileges, <log details>

- 消息代码: 24465

严重性: 错误 (ERROR)

消息文本: ISE 未加入 Active Directory 域控制器 (ISE is not joined to an Active Directory Domain Controller)

消息说明: ISE 未加入 Active Directory 域控制器

本地目标消息格式: <timestamp> <seq_num> 24465 ERROR External-Active-Directory: ISE is not joined to an Active Directory Domain Controller, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24465 ERROR External-Active-Directory: ISE is not joined to an Active Directory Domain Controller, <log details>

- 消息代码: 24466

严重性: 错误 (ERROR)

消息文本: ISE Active Directory 代理已关闭 (ISE Active Directory agent is down)

消息说明: ISE Active Directory 代理已关闭

本地目标消息格式: <timestamp> <seq_num> 24466 ERROR External-Active-Directory: ISE Active Directory agent is down, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24466 ERROR External-Active-Directory: ISE Active Directory agent is down, <log details>

- 消息代码: 24467

严重性: 错误 (ERROR)

消息文本: 无法检索指定对象 (Could not retrieve the specified object)

消息说明: 无法检索指定对象, 因为该对象属于无法访问的域

本地目标消息格式: <timestamp> <seq_num> 24467 ERROR External-Active-Directory: Could not retrieve the specified object, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24467 ERROR External-Active-Directory: Could not retrieve the specified object, <log details>

- 消息代码: 24468

严重性: 错误 (ERROR)

消息文本: 无法从 Active Directory 检索用户证书 (Failed to retrieve the user certificate from Active Directory)

消息说明: 无法从 Active Directory 检索用户证书。

本地目标消息格式: <timestamp> <seq_num> 24468 ERROR External-Active-Directory: Failed to retrieve the user certificate from Active Directory, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24468 ERROR External-Active-Directory: Failed to retrieve the user certificate from Active Directory, <log details>

- 消息代码: 24469

严重性: 信息 (INFO)

消息文本: 已从 Active Directory 成功检索用户证书 (The user certificate was retrieved from Active Directory successfully)

消息说明: 已从 Active Directory 成功检索用户证书。

本地目标消息格式: <timestamp> <seq_num> 24469 INFO External-Active-Directory: The user certificate was retrieved from Active Directory successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24469 INFO External-Active-Directory:
The user certificate was retrieved from Active Directory successfully, <log details>

- 消息代码: 24470

严重性: 信息 (INFO)

消息文本: Active Directory 上的计算机身份验证成功 (Machine authentication against Active Directory is successful)

消息说明: Active Directory 上的计算机身份验证成功。

本地目标消息格式: <timestamp> <seq_num> 24470 INFO External-Active-Directory: Machine authentication against Active Directory is successful, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24470 INFO External-Active-Directory:
Machine authentication against Active Directory is successful, <log details>

- 消息代码: 24471

严重性: 信息 (INFO)

消息文本: Active Directory 不支持更改 EnablePassword 选项 (Active Directory does not support the change EnablePassword option)

消息说明: Active Directory 不支持更改 EnablePassword 选项。

本地目标消息格式: <timestamp> <seq_num> 24471 INFO External-Active-Directory: Active Directory does not support the change EnablePassword option, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24471 INFO External-Active-Directory:
Active Directory does not support the change EnablePassword option, <log details>

- 消息代码: 24472

严重性: 调试 (DEBUG)

消息文本: 用户或主机帐户被锁定; 正在将 IdentityAccessRestricted 标记设为 True (The user or host account is locked out; setting the IdentityAccessRestricted flag to true)

消息说明: 用户或主机帐户被锁定; ISE 将 IdentityAccessRestricted 标记设为 True。

本地目标消息格式: <timestamp> <seq_num> 24472 DEBUG External-Active-Directory: The user or host account is locked out; setting the IdentityAccessRestricted flag to true, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24472 DEBUG External-Active-Directory:
The user or host account is locked out; setting the IdentityAccessRestricted flag to true, <log details>

- 消息代码: 24473

严重性: 调试 (DEBUG)

消息文本: 用户密码已过期; 正在将 IdentityAccessRestricted 标记设为 True (The user's password has expired; setting the IdentityAccessRestricted flag to true)

消息说明: 用户密码已过期; ISE 将 IdentityAccessRestricted 标记设为 True。

本地目标消息格式: <timestamp> <seq_num> 24473 DEBUG External-Active-Directory: The user's password has expired; setting the IdentityAccessRestricted flag to true, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24473 DEBUG External-Active-Directory: The user's password has expired; setting the IdentityAccessRestricted flag to true, <log details>

- 消息代码: 24474

严重性: 调试 (DEBUG)

消息文本: 用户或主机的帐户已过期; 正在将 IdentityAccessRestricted 标记设为 True (The user's or host's account has expired; setting the IdentityAccessRestricted flag to true)

消息说明: 用户或主机的帐户已过期; ISE 将 IdentityAccessRestricted 标记设为 True。

本地目标消息格式: <timestamp> <seq_num> 24474 DEBUG External-Active-Directory: The user's or host's account has expired; setting the IdentityAccessRestricted flag to true, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24474 DEBUG External-Active-Directory: The user's or host's account has expired; setting the IdentityAccessRestricted flag to true, <log details>

- 消息代码: 24475

严重性: 调试 (DEBUG)

消息文本: 用户或主机的帐户已禁用; 正在将 IdentityAccessRestricted 标记设为 True (The user's or host's account is disabled; setting the IdentityAccessRestricted flag to true)

消息说明: 用户或主机的帐户已禁用; ISE 将 IdentityAccessRestricted 标记设为 True。

本地目标消息格式: <timestamp> <seq_num> 24475 DEBUG External-Active-Directory: The user's or host's account is disabled; setting the IdentityAccessRestricted flag to true, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24475 DEBUG External-Active-Directory: The user's or host's account is disabled; setting the IdentityAccessRestricted flag to true, <log details>

- 消息代码: 24476

严重性: 调试 (DEBUG)

消息文本: 用户或主机的帐户已限制登录时间; 正在将 IdentityAccessRestricted 标记设为 True (The user's or host's account is in restricted logon hours; setting the IdentityAccessRestricted flag to true)

消息说明: 用户或主机的帐户已限制登录时间; ISE 将 IdentityAccessRestricted 标记设为 True。

本地目标消息格式: <timestamp> <seq_num> 24476 DEBUG External-Active-Directory: The user's or host's account is in restricted logon hours; setting the IdentityAccessRestricted flag to true. true, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24476 DEBUG External-Active-Directory:
The user's or host's account is in restricted logon hours; setting the IdentityAccessRestricted flag to true.
true, <log details>

- 消息代码: 24477

严重性: 调试 (DEBUG)

消息文本: 不允许用户使用当前工作站登录到 Active Directory; 正在将 IdentityAccessRestricted 标记设为 True (The user is not permitted to log in to Active Directory using the current workstation; setting the IdentityAccessRestricted flag to true)

消息说明: 不允许用户使用当前工作站登录到 Active Directory; 正在将 IdentityAccessRestricted 标记设为 True。

本地目标消息格式: <timestamp> <seq_num> 24477 DEBUG External-Active-Directory: The user is not permitted to log in to Active Directory using the current workstation; setting the IdentityAccessRestricted flag to true, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24477 DEBUG External-Active-Directory:
The user is not permitted to log in to Active Directory using the current workstation; setting the IdentityAccessRestricted flag to true, <log details>

- 消息代码: 24478

严重性: 警告 (WARN)

消息文本: 验证 Active Directory 中的用户或主机时出错; 未更改 IdentityAccessRestricted 标记 (Error while validating the user or host in Active Directory; the IdentityAccessRestricted flag is not altered)

消息说明: 如果验证 Active Directory 中的用户或主机时出现错误, 则 ISE 不会更改 IdentityAccessRestricted 标记。

本地目标消息格式: <timestamp> <seq_num> 24478 WARN External-Active-Directory: Error while validating the user or host in Active Directory; the IdentityAccessRestricted flag is not altered, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24478 WARN External-Active-Directory:
Error while validating the user or host in Active Directory; the IdentityAccessRestricted flag is not altered, <log details>

- 消息代码: 24479

严重性: 警告 (WARN)

消息文本: 并非 Active Directory 组中的所有计算机均已被检索; 该组的一个或多个规范名称未被检索 (Not all machines in the Active Directory groups are retrieved; one or more of the group's canonical name is not retrieved)

消息说明: 并非 Active Directory 组中的所有计算机均已被检索; 该组的一个或多个规范名称未被检索。

本地目标消息格式: <timestamp> <seq_num> 24479 WARN External-Active-Directory: Not all machines in the Active Directory groups are retrieved; one or more of the group's canonical name is not retrieved, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24479 WARN External-Active-Directory: Not all machines in the Active Directory groups are retrieved; one or more of the group's canonical name is not retrieved, <log details>

- 消息代码: 24480

严重性: 错误 (ERROR)

消息文本: 从 Active Directory 检索计算机相关对象的操作失败 (The machine-related object retrieval operation from Active Directory has failed)

消息说明: 从 Active Directory 检索计算机相关对象的操作失败。

本地目标消息格式: <timestamp> <seq_num> 24480 ERROR External-Active-Directory: The machine-related object retrieval operation from Active Directory has failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24480 ERROR External-Active-Directory: The machine-related object retrieval operation from Active Directory has failed, <log details>

- 消息代码: 24481

严重性: 错误 (ERROR)

消息文本: 从 Active Directory 检索计算机的属性失败 (The machine's attribute retrieval from Active Directory has failed)

消息说明: 从 Active Directory 检索计算机的属性失败。

本地目标消息格式: <timestamp> <seq_num> 24481 ERROR External-Active-Directory: The machine's attribute retrieval from Active Directory has failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24481 ERROR External-Active-Directory: The machine's attribute retrieval from Active Directory has failed, <log details>

- 消息代码: 24482

严重性: 信息 (INFO)

消息文本: 从 Active Directory 检索计算机证书成功 (Successfully retrieved the machine certificate from Active Directory)

消息说明: 从 Active Directory 检索计算机证书成功。

本地目标消息格式: <timestamp> <seq_num> 24482 INFO External-Active-Directory: Successfully retrieved the machine certificate from Active Directory, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24482 INFO External-Active-Directory: Successfully retrieved the machine certificate from Active Directory, <log details>

- 消息代码: 24483
 - 严重性: 错误 (ERROR)
 - 消息文本: 无法从 Active Directory 检索计算机证书 (Failed to retrieve the machine certificate from Active Directory)
 - 消息说明: 无法从 Active Directory 检索计算机证书。
 - 本地目标消息格式: <timestamp> <seq_num> 24483 ERROR External-Active-Directory: Failed to retrieve the machine certificate from Active Directory, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24483 ERROR External-Active-Directory: Failed to retrieve the machine certificate from Active Directory, <log details>

- 消息代码: 24484
 - 严重性: 调试 (DEBUG)
 - 消息文本: 由于计算机的密码已过期, 因此 Active Directory 上的计算机身份验证失败 (Machine authentication against Active Directory has failed because the machine's password has expired)
 - 消息说明: 由于计算机的密码已过期, 因此 Active Directory 上的计算机身份验证失败。
 - 本地目标消息格式: <timestamp> <seq_num> 24484 DEBUG External-Active-Directory: Machine authentication against Active Directory has failed because the machine's password has expired, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24484 DEBUG External-Active-Directory: Machine authentication against Active Directory has failed because the machine's password has expired, <log details>

- 消息代码: 24485
 - 严重性: 调试 (DEBUG)
 - 消息文本: 由于密码错误, Active Directory 上的计算机身份验证失败 (Machine authentication against Active Directory has failed because of wrong password)
 - 消息说明: 由于密码错误, Active Directory 上的计算机身份验证失败。
 - 本地目标消息格式: <timestamp> <seq_num> 24485 DEBUG External-Active-Directory: Machine authentication against Active Directory has failed because of wrong password, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24485 DEBUG External-Active-Directory: Machine authentication against Active Directory has failed because of wrong password, <log details>

- 消息代码: 24486
 - 严重性: 调试 (DEBUG)
 - 消息文本: 由于计算机的帐户已禁用, 因此 Active Directory 上的计算机身份验证失败 (Machine authentication against Active Directory has failed because the machine's account is disabled)

消息说明：由于计算机的帐户已禁用，因此 Active Directory 上的计算机身份验证失败。

本地目标消息格式：<timestamp> <seq_num> 24486 DEBUG External-Active-Directory: Machine authentication against Active Directory has failed because the machine's account is disabled, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24486 DEBUG External-Active-Directory: Machine authentication against Active Directory has failed because the machine's account is disabled, <log details>

- 消息代码：24487

严重性：调试 (DEBUG)

消息文本：由于已认定计算机登录时间被限制，因此 Active Directory 上的计算机身份验证失败 (Machine authentication against Active Directory failed since machine is considered to be in restricted logon hours)

消息说明：由于已认定计算机登录时间被限制，因此 Active Directory 上的计算机身份验证失败

本地目标消息格式：<timestamp> <seq_num> 24487 DEBUG External-Active-Directory: Machine authentication against Active Directory failed since machine is considered to be in restricted logon hours, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24487 DEBUG External-Active-Directory: Machine authentication against Active Directory failed since machine is considered to be in restricted logon hours, <log details>

- 消息代码：24488

严重性：调试 (DEBUG)

消息文本：Active Directory 无法识别计算机的域 (The machine's domain is not recognized by Active Directory)

消息说明：Active Directory 无法识别计算机的域。

本地目标消息格式：<timestamp> <seq_num> 24488 DEBUG External-Active-Directory: The machine's domain is not recognized by Active Directory, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24488 DEBUG External-Active-Directory: The machine's domain is not recognized by Active Directory, <log details>

- 消息代码：24489

严重性：调试 (DEBUG)

消息文本：由于计算机的帐户已过期，因此 Active Directory 上的计算机身份验证失败 (Machine authentication against Active Directory has failed because the machine's account has expired)

消息说明：由于计算机的帐户已过期，因此 Active Directory 上的计算机身份验证失败。

本地目标消息格式: <timestamp> <seq_num> 24489 DEBUG External-Active-Directory: Machine authentication against Active Directory has failed because the machine's account has expired, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24489 DEBUG External-Active-Directory: Machine authentication against Active Directory has failed because the machine's account has expired, <log details>

- 消息代码: 24490

严重性: 调试 (DEBUG)

消息文本: 由于计算机的帐户已锁定, 因此 Active Directory 上的计算机身份验证失败 (Machine authentication against Active Directory has failed because the machine's account is locked out)

消息说明: 由于计算机的帐户已锁定, 因此 Active Directory 上的计算机身份验证失败。

本地目标消息格式: <timestamp> <seq_num> 24490 DEBUG External-Active-Directory: Machine authentication against Active Directory has failed because the machine's account is locked out, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24490 DEBUG External-Active-Directory: Machine authentication against Active Directory has failed because the machine's account is locked out, <log details>

- 消息代码: 24491

严重性: 调试 (DEBUG)

消息文本: 由于计算机的凭证无效, 因此 Active Directory 上的计算机身份验证失败 (Machine authentication against Active Directory has failed because the machine has invalid credentials)

消息说明: 由于计算机的凭证无效, 因此 Active Directory 上的计算机身份验证失败。

本地目标消息格式: <timestamp> <seq_num> 24491 DEBUG External-Active-Directory: Machine authentication against Active Directory has failed because the machine has invalid credentials, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24491 DEBUG External-Active-Directory: Machine authentication against Active Directory has failed because the machine has invalid credentials, <log details>

- 消息代码: 24492

严重性: 错误 (ERROR)

消息文本: Active Directory 上的计算机身份验证失败 (Machine authentication against Active Directory has failed)

消息说明: Active Directory 上的计算机身份验证失败。

本地目标消息格式: <timestamp> <seq_num> 24492 ERROR External-Active-Directory: Machine authentication against Active Directory has failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24492 ERROR External-Active-Directory:
Machine authentication against Active Directory has failed, <log details>

- 消息代码: 24493

严重性: 错误 (ERROR)

消息文本: ISE 使用其计算机凭证与 Active Directory 通信时遇到问题 (ISE has problems communicating with Active Directory using its machine credentials)

消息说明: ISE 使用其计算机凭证与 Active Directory 通信时遇到问题。

本地目标消息格式: <timestamp> <seq_num> 24493 ERROR External-Active-Directory: ISE has problems communicating with Active Directory using its machine credentials, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24493 ERROR External-Active-Directory:
ISE has problems communicating with Active Directory using its machine credentials, <log details>

- 消息代码: 24494

严重性: 错误 (ERROR)

消息文本: Active Directory DNS 服务器不可用 (Active Directory DNS servers are not available)

消息说明: Active Directory DNS 服务器不可用。

本地目标消息格式: <timestamp> <seq_num> 24494 ERROR External-Active-Directory: Active Directory DNS servers are not available, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24494 ERROR External-Active-Directory:
Active Directory DNS servers are not available, <log details>

- 消息代码: 24495

严重性: 错误 (ERROR)

消息文本: Active Directory 服务器不可用 (Active Directory servers are not available)

消息说明: Active Directory 服务器不可用。

本地目标消息格式: <timestamp> <seq_num> 24495 ERROR External-Active-Directory: Active Directory servers are not available, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24495 ERROR External-Active-Directory:
Active Directory servers are not available, <log details>

- 消息代码: 24496

严重性: 警告 (WARN)

消息文本: 因白名单或黑名单限制, 身份验证被拒绝 (Authentication rejected due to a white or black list restriction)

消息说明：因白名单或黑名单限制，身份验证被拒绝

本地目标消息格式：<timestamp> <seq_num> 24496 WARN External-Active-Directory: Authentication rejected due to a white or black list restriction, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24496 WARN External-Active-Directory: Authentication rejected due to a white or black list restriction, <log details>

- 消息代码：24497

严重性：错误 (ERROR)

消息文本：所选 Active Directory 范围为空 (Selected Active Directory Scope is empty)

消息说明：所选 Active Directory 范围为空

本地目标消息格式：<timestamp> <seq_num> 24497 ERROR External-Active-Directory: Selected Active Directory Scope is empty, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24497 ERROR External-Active-Directory: Selected Active Directory Scope is empty, <log details>

- 消息代码：24498

严重性：错误 (ERROR)

消息文本：解析身份超过时间限制 (Resolve identity exceeded time limit)

消息说明：从 Active Directory 检索用户属性因超时错误而失败

本地目标消息格式：<timestamp> <seq_num> 24498 ERROR External-Active-Directory: Resolve identity exceeded time limit, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24498 ERROR External-Active-Directory: Resolve identity exceeded time limit, <log details>

- 消息代码：24500

严重性：调试 (DEBUG)

消息文本：正在 RSA SecurID 服务器上验证用户身份 (Authenticating user against the RSA SecurID Server)

消息说明：正在 RSA SecurID 服务器上验证用户身份。

本地目标消息格式：<timestamp> <seq_num> 24500 DEBUG External-RSA-SecurID-Server: Authenticating user against the RSA SecurID Server, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24500 DEBUG External-RSA-SecurID-Server: Authenticating user against the RSA SecurID Server, <log details>

- 消息代码：24501

严重性: 调试 (DEBUG)

消息文本: 已与 RSA SecurID 服务器建立会话 (A session is established with the RSA SecurID Server)

消息说明: 已与 RSA SecurID 服务器建立会话。

本地目标消息格式: <timestamp> <seq_num> 24501 DEBUG External-RSA-SecurID-Server: A session is established with the RSA SecurID Server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24501 DEBUG External-RSA-SecurID-Server: A session is established with the RSA SecurID Server, <log details>

- 消息代码: 24502

严重性: 调试 (DEBUG)

消息文本: 与 RSA SecurID 服务器的会话已关闭 (The session with RSA SecurID Server is closed)

消息说明: 与 RSA SecurID 服务器的会话已关闭

本地目标消息格式: <timestamp> <seq_num> 24502 DEBUG External-RSA-SecurID-Server: The session with RSA SecurID Server is closed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24502 DEBUG External-RSA-SecurID-Server: The session with RSA SecurID Server is closed, <log details>

- 消息代码: 24503

严重性: 错误 (ERROR)

消息文本: 无法与 RSA SecurID 服务器建立会话 (Cannot establish a session with the RSA SecurID Server)

消息说明: 无法与 RSA SecurID 服务器建立会话。

本地目标消息格式: <timestamp> <seq_num> 24503 ERROR External-RSA-SecurID-Server: Cannot establish a session with the RSA SecurID Server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24503 ERROR External-RSA-SecurID-Server: Cannot establish a session with the RSA SecurID Server, <log details>

- 消息代码: 24504

严重性: 错误 (ERROR)

消息文本: 锁定用户请求失败 (The lock user request has failed)

消息说明: 锁定用户请求失败。

本地目标消息格式: <timestamp> <seq_num> 24504 ERROR External-RSA-SecurID-Server: The lock user request has failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24504 ERROR External-RSA-SecurID-Server: The lock user request has failed, <log details>

- 消息代码: 24505
严重性: 调试 (DEBUG)
消息文本: 用户身份验证成功 (User authentication has succeeded)
消息说明: RSA SecurID 服务器上的用户身份验证成功。
本地目标消息格式: <timestamp> <seq_num> 24505 DEBUG External-RSA-SecurID-Server: User authentication has succeeded, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24505 DEBUG External-RSA-SecurID-Server: User authentication has succeeded, <log details>
- 消息代码: 24506
严重性: 调试 (DEBUG)
消息文本: 检查密码操作成功 (Check passcode operation succeeded)
消息说明: RSA SecurID 服务器上的检查密码操作成功
本地目标消息格式: <timestamp> <seq_num> 24506 DEBUG External-RSA-SecurID-Server: Check passcode operation succeeded, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24506 DEBUG External-RSA-SecurID-Server: Check passcode operation succeeded, <log details>
- 消息代码: 24507
严重性: 调试 (DEBUG)
消息文本: Next Tokencode 操作成功 (Next Tokencode operation succeeded)
消息说明: RSA SecurID 服务器上的 Next Tokencode 操作成功
本地目标消息格式: <timestamp> <seq_num> 24507 DEBUG External-RSA-SecurID-Server: Next Tokencode operation succeeded, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24507 DEBUG External-RSA-SecurID-Server: Next Tokencode operation succeeded, <log details>
- 消息代码: 24508
严重性: 调试 (DEBUG)
消息文本: 用户身份验证失败 (User authentication failed)
消息说明: RSA SecurID 服务器上的用户身份验证失败
本地目标消息格式: <timestamp> <seq_num> 24508 DEBUG External-RSA-SecurID-Server: User authentication failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24508 DEBUG External-RSA-SecurID-Server:
User authentication failed, <log details>

- 消息代码: 24509

严重性: 调试 (DEBUG)

消息文本: 检查密码导致需要 Next Tokencode (Check passcode resulted in Next Tokencode required)

消息说明: 检查密码导致需要 Next Tokencode

本地目标消息格式: <timestamp> <seq_num> 24509 DEBUG External-RSA-SecurID-Server: Check
passcode resulted in Next Tokencode required, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24509 DEBUG External-RSA-SecurID-Server:
Check passcode resulted in Next Tokencode required, <log details>

- 消息代码: 24510

严重性: 调试 (DEBUG)

消息文本: 检查密码导致需要设置新 PIN (Check passcode resulted in setting New PIN required)

消息说明: 检查密码导致需要设置新 PIN

本地目标消息格式: <timestamp> <seq_num> 24510 DEBUG External-RSA-SecurID-Server: Check
passcode resulted in setting New PIN required, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24510 DEBUG External-RSA-SecurID-Server:
Check passcode resulted in setting New PIN required, <log details>

- 消息代码: 24511

严重性: 错误 (ERROR)

消息文本: RSA SecurID 服务器上的检查密码操作导致错误 (Check passcode operation against RSA
SecurID Server resulted in error)

消息说明: RSA SecurID 服务器上的检查密码操作导致错误

本地目标消息格式: <timestamp> <seq_num> 24511 ERROR External-RSA-SecurID-Server: Check
passcode operation against RSA SecurID Server resulted in error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24511 ERROR External-RSA-SecurID-Server:
Check passcode operation against RSA SecurID Server resulted in error, <log details>

- 消息代码: 24512

严重性: 错误 (ERROR)

消息文本: RSA SecurID 服务器中的 Next Tokencode 操作导致错误 (Next tokencode operation in
RSA SecurID Server resulted in error)

消息说明: RSA SecurID 服务器中的 Next Tokencode 操作导致错误

本地目标消息格式: <timestamp> <seq_num> 24512 ERROR External-RSA-SecurID-Server: Next tokencode operation in RSA SecurID Server resulted in error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24512 ERROR External-RSA-SecurID-Server:
Next tokencode operation in RSA SecurID Server resulted in error, <log details>

- 消息代码: 24513

严重性: 错误 (ERROR)

消息文本: RSA SecurID 服务器中的设置新 PIN 操作导致错误 (Set New PIN operation in RSA SecurID Server resulted in error)

消息说明: RSA SecurID 服务器中的设置新 PIN 操作导致错误

本地目标消息格式: <timestamp> <seq_num> 24513 ERROR External-RSA-SecurID-Server: Set New PIN operation in RSA SecurID Server resulted in error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24513 ERROR External-RSA-SecurID-Server:
Set New PIN operation in RSA SecurID Server resulted in error, <log details>

- 消息代码: 24514

严重性: 调试 (DEBUG)

消息文本: RSA SecurID 服务器中的 Next Tokencode 操作失败 (Next tokencode operation in RSA SecurID Server failed)

消息说明: RSA SecurID 服务器中的 Next Tokencode 操作失败

本地目标消息格式: <timestamp> <seq_num> 24514 DEBUG External-RSA-SecurID-Server: Next tokencode operation in RSA SecurID Server failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24514 DEBUG External-RSA-SecurID-Server:
Next tokencode operation in RSA SecurID Server failed, <log details>

- 消息代码: 24515

严重性: 调试 (DEBUG)

消息文本: RSA SecurID 服务器中的设置新 PIN 操作失败 (Set New PIN operation in RSA SecurID Server failed)

消息说明: RSA SecurID 服务器中的设置新 PIN 操作失败

本地目标消息格式: <timestamp> <seq_num> 24515 DEBUG External-RSA-SecurID-Server: Set New PIN operation in RSA SecurID Server failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24515 DEBUG External-RSA-SecurID-Server:
Set New PIN operation in RSA SecurID Server failed, <log details>

- 消息代码: 24516
 - 严重性: 调试 (DEBUG)
 - 消息文本: 新 PIN 设置成功 (New PIN was set successfully)
 - 消息说明: 新 PIN 设置成功
 - 本地目标消息格式: <timestamp> <seq_num> 24516 DEBUG External-RSA-SecurID-Server: New PIN was set successfully, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24516 DEBUG External-RSA-SecurID-Server: New PIN was set successfully, <log details>

- 消息代码: 24517
 - 严重性: 调试 (DEBUG)
 - 消息文本: 用户接受系统的 PIN (User accepts system's PIN)
 - 消息说明: 用户已选择接受系统的 PIN
 - 本地目标消息格式: <timestamp> <seq_num> 24517 DEBUG External-RSA-SecurID-Server: User accepts system's PIN, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24517 DEBUG External-RSA-SecurID-Server: User accepts system's PIN, <log details>

- 消息代码: 24518
 - 严重性: 调试 (DEBUG)
 - 消息文本: 用户已取消新 PIN 操作; RSA SecurID 服务器上的用户身份验证失败 (User canceled New PIN operation; User authentication against RSA SecurIDServer failed)
 - 消息说明: 用户已取消新 PIN 操作; RSA SecurID 服务器上的用户身份验证失败
 - 本地目标消息格式: <timestamp> <seq_num> 24518 DEBUG External-RSA-SecurID-Server: User canceled New PIN operation; User authentication against RSA SecurIDServer failed, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24518 DEBUG External-RSA-SecurID-Server: User canceled New PIN operation; User authentication against RSA SecurIDServer failed, <log details>

- 消息代码: 24519
 - 严重性: 调试 (DEBUG)
 - 消息文本: 用户输入的 PIN 无效; PIN 必须仅包含字母数字字符 (User entered invalid PIN; PIN must only contain alpha-numeric characters)
 - 消息说明: 用户输入的 PIN 无效; PIN 必须仅包含字母数字字符
 - 本地目标消息格式: <timestamp> <seq_num> 24519 DEBUG External-RSA-SecurID-Server: User entered invalid PIN; PIN must only contain alpha-numeric characters, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24519 DEBUG External-RSA-SecurID-Server:
User entered invalid PIN; PIN must only contain alpha-numeric characters, <log details>

- 消息代码: 24520

严重性: 调试 (DEBUG)

消息文本: 用户输入的 PIN 无效; PIN 必须仅包含数字字符 (User entered invalid PIN; PIN must only contain numeric characters)

消息说明: 用户输入的 PIN 无效; PIN 必须仅包含数字字符

本地目标消息格式: <timestamp> <seq_num> 24520 DEBUG External-RSA-SecurID-Server: User entered invalid PIN; PIN must only contain numeric characters, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24520 DEBUG External-RSA-SecurID-Server:
User entered invalid PIN; PIN must only contain numeric characters, <log details>

- 消息代码: 24521

严重性: 调试 (DEBUG)

消息文本: 用户输入的 PIN 长度无效 (User entered PIN with invalid length)

消息说明: 用户输入的 PIN 长度无效

本地目标消息格式: <timestamp> <seq_num> 24521 DEBUG External-RSA-SecurID-Server: User entered PIN with invalid length, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24521 DEBUG External-RSA-SecurID-Server:
User entered PIN with invalid length, <log details>

- 消息代码: 24522

严重性: 调试 (DEBUG)

消息文本: 已接受 PIN。请等待系统更改令牌代码, 然后使用新密码重新进行身份验证。(PIN Accepted. Wait for the token code to change, then reauthenticate using the new passcode.)

消息说明: 已接受 PIN。请等待系统更改令牌代码, 然后使用新密码重新进行身份验证。

本地目标消息格式: <timestamp> <seq_num> 24522 DEBUG External-RSA-SecurID-Server: PIN Accepted. Wait for the token code to change, then reauthenticate using the new passcode., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24522 DEBUG External-RSA-SecurID-Server:
PIN Accepted. Wait for the token code to change, then reauthenticate using the new passcode., <log details>

- 消息代码: 24523

严重性: 调试 (DEBUG)

消息文本: 已返回要求用户输入下一个令牌代码的质询 (Returned challenge asking the user to enter next tokencode)

消息说明: 已返回要求用户输入下一个令牌代码的质询

本地目标消息格式: <timestamp> <seq_num> 24523 DEBUG External-RSA-SecurID-Server: Returned challenge asking the user to enter next tokencode, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24523 DEBUG External-RSA-SecurID-Server: Returned challenge asking the user to enter next tokencode, <log details>

- 消息代码: 24524

严重性: 调试 (DEBUG)

消息文本: 已收到用户对下一个令牌代码质询的响应 (Received user response for next tokencode challenge)

消息说明: 已收到用户对下一个令牌代码质询的响应

本地目标消息格式: <timestamp> <seq_num> 24524 DEBUG External-RSA-SecurID-Server: Received user response for next tokencode challenge, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24524 DEBUG External-RSA-SecurID-Server: Received user response for next tokencode challenge, <log details>

- 消息代码: 24525

严重性: 调试 (DEBUG)

消息文本: 已返回要求用户接受系统的 PIN 的质询 (Returned challenge asking the user to accept system's PIN)

消息说明: 已返回要求用户接受系统的 PIN 的质询

本地目标消息格式: <timestamp> <seq_num> 24525 DEBUG External-RSA-SecurID-Server: Returned challenge asking the user to accept system's PIN, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24525 DEBUG External-RSA-SecurID-Server: Returned challenge asking the user to accept system's PIN, <log details>

- 消息代码: 24526

严重性: 调试 (DEBUG)

消息文本: 已收到用户对接受系统 PIN 这一质询的响应 (Received user response for accept system PIN challenge)

消息说明: 已收到用户对接受系统 PIN 这一质询的响应

本地目标消息格式: <timestamp> <seq_num> 24526 DEBUG External-RSA-SecurID-Server: Received user response for accept system PIN challenge, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24526 DEBUG External-RSA-SecurID-Server:
Received user response for accept system PIN challenge, <log details>

- 消息代码: 24527

严重性: 调试 (DEBUG)

消息文本: 已返回要求用户输入新 PIN 的质询 (Returned challenge asking the user to enter new PIN)

消息说明: 已返回要求用户输入新 PIN 的质询

本地目标消息格式: <timestamp> <seq_num> 24527 DEBUG External-RSA-SecurID-Server: Returned
challenge asking the user to enter new PIN, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24527 DEBUG External-RSA-SecurID-Server:
Returned challenge asking the user to enter new PIN, <log details>

- 消息代码: 24528

严重性: 调试 (DEBUG)

消息文本: 已收到用户对输入新 PIN 这一质询的响应 (Received user response for enter new PIN
challenge)

消息说明: 已收到用户对输入新 PIN 这一质询的响应

本地目标消息格式: <timestamp> <seq_num> 24528 DEBUG External-RSA-SecurID-Server: Received
user response for enter new PIN challenge, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24528 DEBUG External-RSA-SecurID-Server:
Received user response for enter new PIN challenge, <log details>

- 消息代码: 24529

严重性: 调试 (DEBUG)

消息文本: 已返回向用户显示其新 PIN 的质询 (Returned challenge displaying the user his new PIN)

消息说明: 已返回向用户显示其新 PIN 的质询

本地目标消息格式: <timestamp> <seq_num> 24529 DEBUG External-RSA-SecurID-Server: Returned
challenge displaying the user his new PIN, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24529 DEBUG External-RSA-SecurID-Server:
Returned challenge displaying the user his new PIN, <log details>

- 消息代码: 24530

严重性: 调试 (DEBUG)

消息文本: 已收到用户对显示其新 PIN 这一质询的响应 (Received user response for challenge
displaying him his new PIN)

消息说明: 已收到用户对显示其新 PIN 这一质询的响应

本地目标消息格式: <timestamp> <seq_num> 24530 DEBUG External-RSA-SecurID-Server: Received user response for challenge displaying him his new PIN, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24530 DEBUG External-RSA-SecurID-Server: Received user response for challenge displaying him his new PIN, <log details>

- 消息代码: 24531

严重性: 调试 (DEBUG)

消息文本: 已返回要求用户重新输入新 PIN 的质询 (Returned challenge asking the user to reenter new PIN)

消息说明: 已返回要求用户重新输入新 PIN 的质询

本地目标消息格式: <timestamp> <seq_num> 24531 DEBUG External-RSA-SecurID-Server: Returned challenge asking the user to reenter new PIN, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24531 DEBUG External-RSA-SecurID-Server: Returned challenge asking the user to reenter new PIN, <log details>

- 消息代码: 24532

严重性: 调试 (DEBUG)

消息文本: 已收到用户对要求其重新输入新 PIN 这一质询的响应 (Received user response for challenge asking the user to reenter new PIN)

消息说明: 已收到用户对要求其重新输入新 PIN 这一质询的响应

本地目标消息格式: <timestamp> <seq_num> 24532 DEBUG External-RSA-SecurID-Server: Received user response for challenge asking the user to reenter new PIN, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24532 DEBUG External-RSA-SecurID-Server: Received user response for challenge asking the user to reenter new PIN, <log details>

- 消息代码: 24533

严重性: 错误 (ERROR)

消息文本: 用户已重新输入其他 PIN (User reentered a different PIN)

消息说明: 用户已重新输入其他 PIN

本地目标消息格式: <timestamp> <seq_num> 24533 ERROR External-RSA-SecurID-Server: User reentered a different PIN, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24533 ERROR External-RSA-SecurID-Server: User reentered a different PIN, <log details>

- 消息代码: 24534

严重性: 调试 (DEBUG)

消息文本: 已返回询问用户是要接受系统的 PIN 还是要自己输入新 PIN 的质询 (Returned challenge asking the user whether he is going to accept system's PIN or will enter a new PIN by himself)

消息说明: 已返回询问用户是要接受系统的 PIN 还是要自己输入新 PIN 的质询

本地目标消息格式: <timestamp> <seq_num> 24534 DEBUG External-RSA-SecurID-Server: Returned challenge asking the user whether he is going to accept system's PIN or will enter a new PIN by himself, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24534 DEBUG External-RSA-SecurID-Server: Returned challenge asking the user whether he is going to accept system's PIN or will enter a new PIN by himself, <log details>

- 消息代码: 24535

严重性: 调试 (DEBUG)

消息文本: 已收到用户对询问其是要接受系统的 PIN 还是要输入新 PIN 这一质询的响应 (Received user response for challenge asking the user to accept system's PIN or enter a new PIN)

消息说明: 已收到用户对询问其是要接受系统的 PIN 还是要输入新 PIN 这一质询的响应

本地目标消息格式: <timestamp> <seq_num> 24535 DEBUG External-RSA-SecurID-Server: Received user response for challenge asking the user to accept system's PIN or enter a new PIN, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24535 DEBUG External-RSA-SecurID-Server: Received user response for challenge asking the user to accept system's PIN or enter a new PIN, <log details>

- 消息代码: 24536

严重性: 调试 (DEBUG)

消息文本: 用户已选择输入新 PIN (User chose to enter a new PIN)

消息说明: 用户已选择输入新 PIN

本地目标消息格式: <timestamp> <seq_num> 24536 DEBUG External-RSA-SecurID-Server: User chose to enter a new PIN, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24536 DEBUG External-RSA-SecurID-Server: User chose to enter a new PIN, <log details>

- 消息代码: 24537

严重性: 调试 (DEBUG)

消息文本: 用户已选择接受系统的 PIN (User chose to accept system's PIN)

消息说明: 用户已选择接受系统的 PIN

本地目标消息格式: <timestamp> <seq_num> 24537 DEBUG External-RSA-SecurID-Server: User chose to accept system's PIN, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24537 DEBUG External-RSA-SecurID-Server: User chose to accept system's PIN, <log details>

- 消息代码: 24538

严重性: 调试 (DEBUG)

消息文本: RSA 会话失效 (RSA Session was invalidated)

消息说明: 因会话期间代理配置更改导致 RSA 会话失效

本地目标消息格式: <timestamp> <seq_num> 24538 DEBUG External-RSA-SecurID-Server: RSA Session was invalidated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24538 DEBUG External-RSA-SecurID-Server: RSA Session was invalidated, <log details>

- 消息代码: 24539

严重性: 信息 (INFO)

消息文本: 已加载 RSA 代理配置, 已启动 RSA 代理 (RSA agent configuration loaded, RSA agent started)

消息说明: 已加载 RSA 代理配置, 已启动 RSA 代理

本地目标消息格式: <timestamp> <seq_num> 24539 INFO External-RSA-SecurID-Server: RSA agent configuration loaded, RSA agent started, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24539 INFO External-RSA-SecurID-Server: RSA agent configuration loaded, RSA agent started, <log details>

- 消息代码: 24540

严重性: 信息 (INFO)

消息文本: 已初始化 RSA 代理配置, 已启动 RSA 代理 (RSA agent configuration initialized, RSA agent started)

消息说明: 已初始化 RSA 代理配置, 已启动 RSA 代理

本地目标消息格式: <timestamp> <seq_num> 24540 INFO External-RSA-SecurID-Server: RSA agent configuration initialized, RSA agent started, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24540 INFO External-RSA-SecurID-Server: RSA agent configuration initialized, RSA agent started, <log details>

- 消息代码: 24541

严重性: 信息 (INFO)

消息文本: 已更新 RSA 代理配置, 已重新启动 RSA 代理 (RSA agent configuration updated, RSA agent restarted)

消息说明: 已更新 RSA 代理配置, 已重新启动 RSA 代理

本地目标消息格式: <timestamp> <seq_num> 24541 INFO External-RSA-SecurID-Server: RSA agent configuration updated, RSA agent restarted, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24541 INFO External-RSA-SecurID-Server: RSA agent configuration updated, RSA agent restarted, <log details>

- 消息代码: 24542

严重性: 信息 (INFO)

消息文本: 已删除 RSA 代理配置, 已停止 RSA 代理 (RSA agent configuration deleted, RSA agent stopped)

消息说明: 已删除 RSA 代理配置, 已停止 RSA 代理

本地目标消息格式: <timestamp> <seq_num> 24542 INFO External-RSA-SecurID-Server: RSA agent configuration deleted, RSA agent stopped, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24542 INFO External-RSA-SecurID-Server: RSA agent configuration deleted, RSA agent stopped, <log details>

- 消息代码: 24543

严重性: 调试 (DEBUG)

消息文本: RSA 会话超时, 会话已取消 (RSA session timeout, session cancelled)

消息说明: RSA 会话超时, 会话已取消

本地目标消息格式: <timestamp> <seq_num> 24543 DEBUG External-RSA-SecurID-Server: RSA session timeout, session cancelled, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24543 DEBUG External-RSA-SecurID-Server: RSA session timeout, session cancelled, <log details>

- 消息代码: 24544

严重性: 错误 (ERROR)

消息文本: RSA 代理初始化失败 (RSA agent initialization failed)

消息说明: RSA 代理初始化失败

本地目标消息格式: <timestamp> <seq_num> 24544 ERROR External-RSA-SecurID-Server: RSA agent initialization failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24544 ERROR External-RSA-SecurID-Server: RSA agent initialization failed, <log details>

- 消息代码: 24545
严重性: 信息 (INFO)
消息文本: securID 文件已删除 (The securid file has been removed)
消息说明: securID 文件已删除
本地目标消息格式: <timestamp> <seq_num> 24545 INFO External-RSA-SecurID-Server: The securid file has been removed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24545 INFO External-RSA-SecurID-Server: The securid file has been removed, <log details>
- 消息代码: 24546
严重性: 信息 (INFO)
消息文本: 已删除 sdstatus.12 文件 (The sdstatus.12 file has been removed)
消息说明: 已删除 sdstatus.12 文件
本地目标消息格式: <timestamp> <seq_num> 24546 INFO External-RSA-SecurID-Server: The sdstatus.12 file has been removed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24546 INFO External-RSA-SecurID-Server: The sdstatus.12 file has been removed, <log details>
- 消息代码: 24547
严重性: 警告 (WARN)
消息文本: RSA 请求超时已过期。RSA 身份验证会话已取消 (RSA request timeout expired. RSA authentication session cancelled)
消息说明: RSA 请求超时已过期。RSA 身份验证会话已取消。
本地目标消息格式: <timestamp> <seq_num> 24547 WARN External-RSA-SecurID-Server: RSA request timeout expired. RSA authentication session cancelled, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24547 WARN External-RSA-SecurID-Server: RSA request timeout expired. RSA authentication session cancelled, <log details>
- 消息代码: 24548
严重性: 错误 (ERROR)
消息文本: RSA 代理配置加载失败 (RSA agent configuration load failed)
消息说明: RSA 代理配置加载失败
本地目标消息格式: <timestamp> <seq_num> 24548 ERROR External-RSA-SecurID-Server: RSA agent configuration load failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24548 ERROR External-RSA-SecurID-Server:
RSA agent configuration load failed, <log details>

- 消息代码: 24549

严重性: 错误 (ERROR)

消息文本: RSA 代理配置初始化失败 (RSA agent configuration initialization failed)

消息说明: RSA 代理配置初始化失败

本地目标消息格式: <timestamp> <seq_num> 24549 ERROR External-RSA-SecurID-Server: RSA
agent configuration initialization failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24549 ERROR External-RSA-SecurID-Server:
RSA agent configuration initialization failed, <log details>

- 消息代码: 24550

严重性: 错误 (ERROR)

消息文本: RSA 代理配置更新失败 (RSA agent configuration update failed)

消息说明: RSA 代理配置更新失败

本地目标消息格式: <timestamp> <seq_num> 24550 ERROR External-RSA-SecurID-Server: RSA
agent configuration update failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24550 ERROR External-RSA-SecurID-Server:
RSA agent configuration update failed, <log details>

- 消息代码: 24551

严重性: 警告 (WARN)

消息文本: RSA 请求被拒绝, 因为 RSA 代理初始化失败 (RSA request is declined, because RSA
agent initialization has failed)

消息说明: RSA 请求被拒绝, 因为 RSA 代理初始化失败。

本地目标消息格式: <timestamp> <seq_num> 24551 WARN External-RSA-SecurID-Server: RSA
request is declined, because RSA agent initialization has failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24551 WARN External-RSA-SecurID-Server:
RSA request is declined, because RSA agent initialization has failed, <log details>

- 消息代码: 24552

严重性: 调试 (DEBUG)

消息文本: 来自 RSA 服务器的拒绝响应被视为未找到用户 (Reject response from the RSA server
is considered as User not found)

消息说明: 根据 RSA 身份存储库的配置, 来自 RSA 服务器的拒绝响应被视为未找到用户。

本地目标消息格式: <timestamp> <seq_num> 24552 DEBUG External-RSA-SecurID-Server: Reject response from the RSA server is considered as User not found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24552 DEBUG External-RSA-SecurID-Server: Reject response from the RSA server is considered as User not found, <log details>

- 消息代码: 24553

严重性: 调试 (DEBUG)

消息文本: 已缓存用户记录 (User record was cached)

消息说明: 在 RSA SecurID 服务器上身份验证成功后, 已缓存用户记录。

本地目标消息格式: <timestamp> <seq_num> 24553 DEBUG External-RSA-SecurID-Server: User record was cached, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24553 DEBUG External-RSA-SecurID-Server: User record was cached, <log details>

- 消息代码: 24554

严重性: 调试 (DEBUG)

消息文本: 未缓存用户记录 (User record was not cached)

消息说明: 未缓存用户记录。

本地目标消息格式: <timestamp> <seq_num> 24554 DEBUG External-RSA-SecurID-Server: User record was not cached, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24554 DEBUG External-RSA-SecurID-Server: User record was not cached, <log details>

- 消息代码: 24555

严重性: 调试 (DEBUG)

消息文本: 已在缓存中找到用户记录 (User record was found in the cache)

消息说明: 已从缓存中找到并检索到用户记录

本地目标消息格式: <timestamp> <seq_num> 24555 DEBUG External-RSA-SecurID-Server: User record was found in the cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24555 DEBUG External-RSA-SecurID-Server: User record was found in the cache, <log details>

- 消息代码: 24556

严重性: 调试 (DEBUG)

消息文本: 在缓存中找不到用户记录 (User record was not found in the cache)

消息说明: 在缓存中找不到用户记录。

本地目标消息格式: <timestamp> <seq_num> 24556 DEBUG External-RSA-SecurID-Server: User record was not found in the cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24556 DEBUG External-RSA-SecurID-Server: User record was not found in the cache, <log details>

- 消息代码: 24557

严重性: 调试 (DEBUG)

消息文本: 在缓存中搜索用户记录时出错 (An error occurred while searching for user records in the cache)

消息说明: 在缓存中搜索用户记录时出错。

本地目标消息格式: <timestamp> <seq_num> 24557 DEBUG External-RSA-SecurID-Server: An error occurred while searching for user records in the cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24557 DEBUG External-RSA-SecurID-Server: An error occurred while searching for user records in the cache, <log details>

- 消息代码: 24558

严重性: 调试 (DEBUG)

消息文本: 未在 RSA 身份存储库配置中启用用户缓存 (User cache is not enabled in the RSA identity store configuration)

消息说明: 未在 RSA 身份存储库配置中启用用户缓存。

本地目标消息格式: <timestamp> <seq_num> 24558 DEBUG External-RSA-SecurID-Server: User cache is not enabled in the RSA identity store configuration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24558 DEBUG External-RSA-SecurID-Server: User cache is not enabled in the RSA identity store configuration, <log details>

- 消息代码: 24559

严重性: 调试 (DEBUG)

消息文本: 正在 RSA 身份存储库中搜索用户 (Searching for user in the RSA identity store)

消息说明: 正在 RSA 身份存储库中搜索用户。

本地目标消息格式: <timestamp> <seq_num> 24559 DEBUG External-RSA-SecurID-Server: Searching for user in the RSA identity store, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24559 DEBUG External-RSA-SecurID-Server: Searching for user in the RSA identity store, <log details>

- 消息代码: 24560
严重性: 调试 (DEBUG)
消息文本: 正在 RSA 身份存储库密码缓存中搜索用户记录 (Searching for user record in RSA identity store Passcode cache)
消息说明: 已启用 RSA 身份存储库的令牌缓存。正在搜索 RSA 身份存储库密码缓存中的用户记录, 以便通过缓存进行身份验证。
本地目标消息格式: <timestamp> <seq_num> 24560 DEBUG External-RSA-SecurID-Server: Searching for user record in RSA identity store Passcode cache, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24560 DEBUG External-RSA-SecurID-Server: Searching for user record in RSA identity store Passcode cache, <log details>
- 消息代码: 24561
严重性: 调试 (DEBUG)
消息文本: 在密码缓存中找到用户记录 (User record was found in Passcode cache)
消息说明: 在 RSA 身份存储库密码缓存中找到用户记录。
本地目标消息格式: <timestamp> <seq_num> 24561 DEBUG External-RSA-SecurID-Server: User record was found in Passcode cache, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24561 DEBUG External-RSA-SecurID-Server: User record was found in Passcode cache, <log details>
- 消息代码: 24562
严重性: 调试 (DEBUG)
消息文本: 在密码缓存中未找到用户记录 (User record was not found in Passcode cache)
消息说明: 在 RSA 身份存储库密码缓存中未找到用户记录。ISE 将尝试根据 RSA 身份存储库对用户进行身份验证。
本地目标消息格式: <timestamp> <seq_num> 24562 DEBUG External-RSA-SecurID-Server: User record was not found in Passcode cache, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24562 DEBUG External-RSA-SecurID-Server: User record was not found in Passcode cache, <log details>
- 消息代码: 24563
严重性: 调试 (DEBUG)
消息文本: 在密码缓存中搜索用户记录时出错 (An error occurred while searching for user record in the Passcode cache)
消息说明: 在密码缓存中搜索用户记录时出错。

本地目标消息格式: <timestamp> <seq_num> 24563 DEBUG External-RSA-SecurID-Server: An error occurred while searching for user record in the Passcode cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24563 DEBUG External-RSA-SecurID-Server: An error occurred while searching for user record in the Passcode cache, <log details>

- 消息代码: 24564

严重性: 调试 (DEBUG)

消息文本: 未在 RSA 身份存储库配置中启用密码缓存 (Passcode cache is not enabled in the RSA identity store configuration)

消息说明: 未在 RSA 身份存储库配置中启用密码缓存。

本地目标消息格式: <timestamp> <seq_num> 24564 DEBUG External-RSA-SecurID-Server: Passcode cache is not enabled in the RSA identity store configuration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24564 DEBUG External-RSA-SecurID-Server: Passcode cache is not enabled in the RSA identity store configuration, <log details>

- 消息代码: 24565

严重性: 调试 (DEBUG)

消息文本: 通过密码缓存传递了身份验证 (Authentication passed via Passcode cache)

消息说明: 在密码缓存中找到用户记录, 密码与身份验证请求中的密码匹配。通过密码缓存传递了身份验证。

本地目标消息格式: <timestamp> <seq_num> 24565 DEBUG External-RSA-SecurID-Server: Authentication passed via Passcode cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24565 DEBUG External-RSA-SecurID-Server: Authentication passed via Passcode cache, <log details>

- 消息代码: 24566

严重性: 调试 (DEBUG)

消息文本: 缓存的密码与身份验证请求中的密码不匹配。密码将从缓存中删除 (Cached Passcode doesn't match passcode in authentication request. Passcode will be removed from the cache)

消息说明: 缓存的密码与身份验证请求中的密码不匹配。ISE 将尝试根据 RSA 身份存储库对用户进行身份验证。

本地目标消息格式: <timestamp> <seq_num> 24566 DEBUG External-RSA-SecurID-Server: Cached Passcode doesn't match passcode in authentication request. Passcode will be removed from the cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24566 DEBUG External-RSA-SecurID-Server:

Cached Passcode doesn't match passcode in authentication request. Passcode will be removed from the cache, <log details>

- 消息代码: 24567

严重性: 调试 (DEBUG)

消息文本: 用户记录已缓存在密码缓存中 (User record was cached in Passcode cache)

消息说明: 在 RSA SecurID 服务器上身份验证成功后, 用户记录已缓存在密码缓存中。

本地目标消息格式: <timestamp> <seq_num> 24567 DEBUG External-RSA-SecurID-Server: User record was cached in Passcode cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24567 DEBUG External-RSA-SecurID-Server: User record was cached in Passcode cache, <log details>

- 消息代码: 24568

严重性: 调试 (DEBUG)

消息文本: 用户记录未缓存在密码缓存中 (User record was not cached in Passcode cache)

消息说明: 用户记录未缓存在密码缓存中

本地目标消息格式: <timestamp> <seq_num> 24568 DEBUG External-RSA-SecurID-Server: User record was not cached in Passcode cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24568 DEBUG External-RSA-SecurID-Server: User record was not cached in Passcode cache, <log details>

- 消息代码: 24600

严重性: 信息 (INFO)

消息文本: 已创建 RADIUS 令牌身份存储库 (RADIUS token identity store is created)

消息说明: 已创建 RADIUS 令牌身份存储库。

本地目标消息格式: <timestamp> <seq_num> 24600 INFO Radius-Token: RADIUS token identity store is created, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24600 INFO Radius-Token: RADIUS token identity store is created, <log details>

- 消息代码: 24601

严重性: 信息 (INFO)

消息文本: RADIUS 令牌身份存储库已破坏 (RADIUS token identity store is destroyed)

消息说明: 已破坏 RADIUS 令牌身份存储库。

本地目标消息格式: <timestamp> <seq_num> 24601 INFO Radius-Token: RADIUS token identity store is destroyed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num> 24601 INFO Radius-Token: RADIUS token
identity store is destroyed, <log details>

- 消息代码: 24602

严重性: 信息 (INFO)

消息文本: RADIUS 令牌身份存储库配置了静态提示 (RADIUS token identity store is configured
with static prompt)

消息说明: RADIUS 令牌身份存储库配置了静态提示。

本地目标消息格式: <timestamp> <seq_num> 24602 INFO Radius-Token: RADIUS token identity
store is configured with static prompt, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num> 24602 INFO Radius-Token: RADIUS token
identity store is configured with static prompt, <log details>

- 消息代码: 24603

严重性: 信息 (INFO)

消息文本: 已将 RADIUS 令牌身份存储库配置为从 RADIUS 令牌服务器获取提示 (RADIUS token
identity store configured to obtain prompt from RADIUS token server)

消息说明: 已将 RADIUS 令牌身份存储库配置为从 RADIUS 令牌服务器获取提示

本地目标消息格式: <timestamp> <seq_num> 24603 INFO Radius-Token: RADIUS token identity
store configured to obtain prompt from RADIUS token server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num> 24603 INFO Radius-Token: RADIUS token
identity store configured to obtain prompt from RADIUS token server, <log details>

- 消息代码: 24604

严重性: 信息 (INFO)

消息文本: 已创建 RADIUS 令牌主服务器 (RADIUS token primary server was created)

消息说明: 已创建 RADIUS 令牌主服务器

本地目标消息格式: <timestamp> <seq_num> 24604 INFO Radius-Token: RADIUS token primary
server was created, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num> 24604 INFO Radius-Token: RADIUS token
primary server was created, <log details>

- 消息代码: 24605

严重性: 信息 (INFO)

消息文本: 已创建 RADIUS 令牌辅助服务器 (RADIUS token secondary server was created)

消息说明: 已创建 RADIUS 令牌辅助服务器

本地目标消息格式: <timestamp> <seq_num> 24605 INFO Radius-Token: RADIUS token secondary server was created, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24605 INFO Radius-Token: RADIUS token secondary server was created, <log details>

- 消息代码: 24606

严重性: 信息 (INFO)

消息文本: 已将 RADIUS 令牌身份存储库配置为在拒绝身份验证时失败 (RADIUS token identity store configured to fail on authentication reject)

消息说明: 已将 RADIUS 令牌身份存储库配置为在拒绝身份验证时失败

本地目标消息格式: <timestamp> <seq_num> 24606 INFO Radius-Token: RADIUS token identity store configured to fail on authentication reject, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24606 INFO Radius-Token: RADIUS token identity store configured to fail on authentication reject, <log details>

- 消息代码: 24607

严重性: 信息 (INFO)

消息文本: 已将 RADIUS 令牌身份存储库配置为在拒绝身份验证时返回未知用户错误 (RADIUS token identity store configured to return unknown user error on authentication reject)

消息说明: 已将 RADIUS 令牌身份存储库配置为在拒绝身份验证时返回未知用户错误

本地目标消息格式: <timestamp> <seq_num> 24607 INFO Radius-Token: RADIUS token identity store configured to return unknown user error on authentication reject, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24607 INFO Radius-Token: RADIUS token identity store configured to return unknown user error on authentication reject, <log details>

- 消息代码: 24608

严重性: 错误 (ERROR)

消息文本: RADIUS 令牌身份存储库因错误输入而失败 (RADIUS token identity store failed due to wrong input)

消息说明: RADIUS 令牌身份存储库因错误输入而失败。

本地目标消息格式: <timestamp> <seq_num> 24608 ERROR Radius-Token: RADIUS token identity store failed due to wrong input, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24608 ERROR Radius-Token: RADIUS token identity store failed due to wrong input, <log details>

- 消息代码: 24609
严重性: 信息 (INFO)
消息文本: RADIUS 令牌身份存储库正在主服务器上进行身份验证 (RADIUS token identity store is authenticating against the primary server)
消息说明: RADIUS 令牌身份存储库正在主服务器上进行身份验证。
本地目标消息格式: <timestamp> <seq_num> 24609 INFO Radius-Token: RADIUS token identity store is authenticating against the primary server, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24609 INFO Radius-Token: RADIUS token identity store is authenticating against the primary server, <log details>
- 消息代码: 24610
严重性: 信息 (INFO)
消息文本: RADIUS 令牌身份存储库正在辅助服务器上进行身份验证 (RADIUS token identity store is authenticating against the secondary server)
消息说明: RADIUS 令牌身份存储库正在辅助服务器上进行身份验证。
本地目标消息格式: <timestamp> <seq_num> 24610 INFO Radius-Token: RADIUS token identity store is authenticating against the secondary server, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24610 INFO Radius-Token: RADIUS token identity store is authenticating against the secondary server, <log details>
- 消息代码: 24611
严重性: 错误 (ERROR)
消息文本: RADIUS 令牌服务器配置错误 (RADIUS token server configuration error)
消息说明: RADIUS 令牌服务器配置错误
本地目标消息格式: <timestamp> <seq_num> 24611 ERROR Radius-Token: RADIUS token server configuration error, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24611 ERROR Radius-Token: RADIUS token server configuration error, <log details>
- 消息代码: 24612
严重性: 信息 (INFO)
消息文本: RADIUS 令牌服务器上的身份验证成功 (Authentication against the RADIUS token server succeeded)
消息说明: RADIUS 令牌服务器上的身份验证成功。
本地目标消息格式: <timestamp> <seq_num> 24612 INFO Radius-Token: Authentication against the RADIUS token server succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24612 INFO Radius-Token: Authentication
against the RADIUS token server succeeded, <log details>

- 消息代码: 24613

严重性: 错误 (ERROR)

消息文本: RADIUS 令牌服务器上的身份验证失败 (Authentication against the RADIUS token server failed)

消息说明: RADIUS 令牌服务器上的身份验证失败。

本地目标消息格式: <timestamp> <seq_num> 24613 ERROR Radius-Token: Authentication against
the RADIUS token server failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24613 ERROR Radius-Token: Authentication
against the RADIUS token server failed, <log details>

- 消息代码: 24614

严重性: 信息 (INFO)

消息文本: RADIUS 令牌服务器身份验证失败被解译为未知用户失败 (RADIUS token server
authentication failure is translated as Unknown user failure)

消息说明: RADIUS 令牌服务器身份验证失败被解译为未知用户失败。

本地目标消息格式: <timestamp> <seq_num> 24614 INFO Radius-Token: RADIUS token server
authentication failure is translated as Unknown user failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24614 INFO Radius-Token: RADIUS token
server authentication failure is translated as Unknown user failure, <log details>

- 消息代码: 24615

严重性: 信息 (INFO)

消息文本: RADIUS 令牌身份存储库收到了访问质询响应 (RADIUS token identity store received
access challenge response)

消息说明: RADIUS 令牌身份存储库收到了访问质询响应。

本地目标消息格式: <timestamp> <seq_num> 24615 INFO Radius-Token: RADIUS token identity
store received access challenge response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24615 INFO Radius-Token: RADIUS token
identity store received access challenge response, <log details>

- 消息代码: 24616

严重性: 错误 (ERROR)

消息文本: RADIUS 令牌身份存储库收到了超时错误 (RADIUS token identity store received timeout error)

消息说明: RADIUS 令牌身份存储库收到了超时错误

本地目标消息格式: <timestamp> <seq_num> 24616 ERROR Radius-Token: RADIUS token identity store received timeout error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24616 ERROR Radius-Token: RADIUS token identity store received timeout error, <log details>

- 消息代码: 24617

严重性: 错误 (ERROR)

消息文本: RADIUS 令牌身份存储库收到了外部错误 (RADIUS token identity store received external error)

消息说明: RADIUS 令牌身份存储库收到了外部错误

本地目标消息格式: <timestamp> <seq_num> 24617 ERROR Radius-Token: RADIUS token identity store received external error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24617 ERROR Radius-Token: RADIUS token identity store received external error, <log details>

- 消息代码: 24618

严重性: 错误 (ERROR)

消息文本: RADIUS 令牌身份存储库收到了未知错误 (RADIUS token identity store received unknown error)

消息说明: RADIUS 令牌身份存储库收到了未知错误

本地目标消息格式: <timestamp> <seq_num> 24618 ERROR Radius-Token: RADIUS token identity store received unknown error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24618 ERROR Radius-Token: RADIUS token identity store received unknown error, <log details>

- 消息代码: 24619

严重性: 调试 (DEBUG)

消息文本: 在 RADIUS 令牌身份存储库中检测到了不合规属性 (Non-compliant attributes detected in the RADIUS token identity store)

消息说明: 在 RADIUS 令牌身份存储库中检测到了不合规属性。

本地目标消息格式: <timestamp> <seq_num> 24619 DEBUG Radius-Token: Non-compliant attributes detected in the RADIUS token identity store, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24619 DEBUG Radius-Token: Non-compliant
attributes detected in the RADIUS token identity store, <log details>

- 消息代码: 24620

严重性: 信息 (INFO)

消息文本: 在 RADIUS 令牌服务器上身份验证后, 更改了用户名格式 (User name format was
changed after authentication with the RADIUS token server)

消息说明: 在 RADIUS 令牌服务器上身份验证后, 更改了用户名格式。

本地目标消息格式: <timestamp> <seq_num> 24620 INFO Radius-Token: User name format was
changed after authentication with the RADIUS token server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24620 INFO Radius-Token: User name
format was changed after authentication with the RADIUS token server, <log details>

- 消息代码: 24621

严重性: 信息 (INFO)

消息文本: 已将 RADIUS 令牌身份存储库配置为返回定义的提示 (RADIUS token identity store
configured to return defined prompt)

消息说明: 已将 RADIUS 令牌身份存储库配置为返回定义的提示。

本地目标消息格式: <timestamp> <seq_num> 24621 INFO Radius-Token: RADIUS token identity
store configured to return defined prompt, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24621 INFO Radius-Token: RADIUS token
identity store configured to return defined prompt, <log details>

- 消息代码: 24622

严重性: 信息 (INFO)

消息文本: 已将 RADIUS 令牌身份存储库配置为从 RADIUS 令牌服务器返回提示 (RADIUS token
identity store configured to return prompt from the RADIUS token server)

消息说明: 已将 RADIUS 令牌身份存储库配置为从 RADIUS 令牌服务器返回提示。

本地目标消息格式: <timestamp> <seq_num> 24622 INFO Radius-Token: RADIUS token identity
store configured to return prompt from the RADIUS token server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24622 INFO Radius-Token: RADIUS token
identity store configured to return prompt from the RADIUS token server, <log details>

- 消息代码: 24623

严重性: 调试 (DEBUG)

消息文本: 已缓存用户记录 (User record was cached)

消息说明: RADIUS 令牌服务器上的身份验证成功后, 缓存了用户记录

本地目标消息格式: <timestamp> <seq_num> 24623 DEBUG Radius-Token: User record was cached, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24623 DEBUG Radius-Token: User record was cached, <log details>

- 消息代码: 24624

严重性: 调试 (DEBUG)

消息文本: 未缓存用户记录 (User record was not cached)

消息说明: 未缓存用户记录。

本地目标消息格式: <timestamp> <seq_num> 24624 DEBUG Radius-Token: User record was not cached, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24624 DEBUG Radius-Token: User record was not cached, <log details>

- 消息代码: 24625

严重性: 调试 (DEBUG)

消息文本: 在缓存中找到了用户记录 (User record found in the cache)

消息说明: 已从缓存中找到并检索到用户记录。

本地目标消息格式: <timestamp> <seq_num> 24625 DEBUG Radius-Token: User record found in the cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24625 DEBUG Radius-Token: User record found in the cache, <log details>

- 消息代码: 24626

严重性: 调试 (DEBUG)

消息文本: 在缓存中找不到用户记录 (User record not found in the cache)

消息说明: 在缓存中找不到用户记录。

本地目标消息格式: <timestamp> <seq_num> 24626 DEBUG Radius-Token: User record not found in the cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24626 DEBUG Radius-Token: User record not found in the cache, <log details>

- 消息代码: 24627

严重性: 调试 (DEBUG)

消息文本: 在缓存中搜索用户记录时出错 (An error occurred while searching for user records in the cache)

消息说明: 在缓存中搜索用户记录时出错。

本地目标消息格式: <timestamp> <seq_num> 24627 DEBUG Radius-Token: An error occurred while searching for user records in the cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24627 DEBUG Radius-Token: An error occurred while searching for user records in the cache, <log details>

- **消息代码:** 24628

严重性: 调试 (DEBUG)

消息文本: 未在 RADIUS 令牌身份存储库配置中启用用户缓存 (User cache not enabled in the RADIUS token identity store configuration)

消息说明: 未在 RADIUS 令牌身份存储库配置中启用用户缓存。

本地目标消息格式: <timestamp> <seq_num> 24628 DEBUG Radius-Token: User cache not enabled in the RADIUS token identity store configuration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24628 DEBUG Radius-Token: User cache not enabled in the RADIUS token identity store configuration, <log details>

- **消息代码:** 24629

严重性: 调试 (DEBUG)

消息文本: 正在 RADIUS 令牌身份存储库中搜索用户 (Searching for user in the RADIUS token identity store)

消息说明: 正在 RADIUS 令牌身份存储库中搜索用户。

本地目标消息格式: <timestamp> <seq_num> 24629 DEBUG Radius-Token: Searching for user in the RADIUS token identity store, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24629 DEBUG Radius-Token: Searching for user in the RADIUS token identity store, <log details>

- **消息代码:** 24630

严重性: 错误 (ERROR)

消息文本: 无法通过名称获取服务器 IP (Failed to get Server IP by name)

消息说明: 无法通过名称获取服务器 IP

本地目标消息格式: <timestamp> <seq_num> 24630 ERROR Radius-Token: Failed to get Server IP by name, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24630 ERROR Radius-Token: Failed to get
Server IP by name, <log details>

- 消息代码: 24631

严重性: 调试 (DEBUG)

消息文本: 正在内部访客 IDStore 中查找用户 (Looking up User in Internal Guests IDStore)

消息说明: 正在内部用户 IDStore 中查找用户

本地目标消息格式: <timestamp> <seq_num> 24631 DEBUG Local-user-DB: Looking up User in
Internal Guests IDStore, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24631 DEBUG Local-user-DB: Looking up
User in Internal Guests IDStore, <log details>

- 消息代码: 24632

严重性: 调试 (DEBUG)

消息文本: 已在内部访客 IDStore 中找到用户 (Found User in Internal Guests IDStore)

消息说明: 已在内部访客 IDStore 中找到用户

本地目标消息格式: <timestamp> <seq_num> 24632 DEBUG Local-user-DB: Found User in Internal
Guests IDStore, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24632 DEBUG Local-user-DB: Found User
in Internal Guests IDStore, <log details>

- 消息代码: 24633

严重性: 调试 (DEBUG)

消息文本: 在内部访客身份存储库中找不到用户 (The user is not found in the internal guests identity
store)

消息说明: 在内部访客身份存储库中找不到指定用户。

本地目标消息格式: <timestamp> <seq_num> 24633 DEBUG Local-user-DB: The user is not found
in the internal guests identity store, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24633 DEBUG Local-user-DB: The user is
not found in the internal guests identity store, <log details>

- 消息代码: 24634

严重性: 调试 (DEBUG)

消息文本: 正在 RADIUS 令牌身份存储库密码缓存中搜索用户记录 (Searching for user record in
RADIUS token identity store Passcode cache)

消息说明：已启用 RADIUS 令牌身份存储库的令牌缓存。正在搜索 RADIUS 令牌身份存储库密码缓存中的用户记录，以便通过缓存进行身份验证。

本地目标消息格式：<timestamp> <seq_num> 24634 DEBUG Radius-Token: Searching for user record in RADIUS token identity store Passcode cache, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24634 DEBUG Radius-Token: Searching for user record in RADIUS token identity store Passcode cache, <log details>

- 消息代码：24635

严重性：调试 (DEBUG)

消息文本：在密码缓存中找到用户记录 (User record was found in Passcode cache)

消息说明：在 RADIUS 令牌身份存储库密码缓存中找到用户记录。

本地目标消息格式：<timestamp> <seq_num> 24635 DEBUG Radius-Token: User record was found in Passcode cache, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24635 DEBUG Radius-Token: User record was found in Passcode cache, <log details>

- 消息代码：24636

严重性：调试 (DEBUG)

消息文本：在密码缓存中未找到用户记录 (User record was not found in Passcode cache)

消息说明：在 RADIUS 令牌身份存储库密码缓存中未找到用户记录。ISE 将尝试根据 RADIUS 令牌身份存储库对用户进行身份验证。

本地目标消息格式：<timestamp> <seq_num> 24636 DEBUG Radius-Token: User record was not found in Passcode cache, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24636 DEBUG Radius-Token: User record was not found in Passcode cache, <log details>

- 消息代码：24637

严重性：调试 (DEBUG)

消息文本：在密码缓存中搜索用户记录时出错 (An error occurred while searching for user record in the Passcode cache)

消息说明：在密码缓存中搜索用户记录时出错。

本地目标消息格式：<timestamp> <seq_num> 24637 DEBUG Radius-Token: An error occurred while searching for user record in the Passcode cache, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24637 DEBUG Radius-Token: An error occurred while searching for user record in the Passcode cache, <log details>

- 消息代码: 24638

严重性: 调试 (DEBUG)

消息文本: 未在 RADIUS 令牌身份存储库配置中启用密码缓存 (Passcode cache is not enabled in the RADIUS token identity store configuration)

消息说明: 未在 RADIUS 令牌身份存储库配置中启用密码缓存。

本地目标消息格式: <timestamp> <seq_num> 24638 DEBUG Radius-Token: Passcode cache is not enabled in the RADIUS token identity store configuration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24638 DEBUG Radius-Token: Passcode cache is not enabled in the RADIUS token identity store configuration, <log details>

- 消息代码: 24639

严重性: 调试 (DEBUG)

消息文本: 通过密码缓存传递了身份验证 (Authentication passed via Passcode cache)

消息说明: 在密码缓存中找到用户记录, 密码与身份验证请求中的密码匹配。通过密码缓存传递了身份验证。

本地目标消息格式: <timestamp> <seq_num> 24639 DEBUG Radius-Token: Authentication passed via Passcode cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24639 DEBUG Radius-Token: Authentication passed via Passcode cache, <log details>

- 消息代码: 24640

严重性: 调试 (DEBUG)

消息文本: 缓存的密码与身份验证请求中的密码不匹配。密码将从缓存中删除 (Cached Passcode doesn't match passcode in authentication request. Passcode will be removed from the cache)

消息说明: 缓存的密码与身份验证请求中的密码不匹配。ISE 将尝试根据 RADIUS 令牌身份存储库对用户进行身份验证。

本地目标消息格式: <timestamp> <seq_num> 24640 DEBUG Radius-Token: Cached Passcode doesn't match passcode in authentication request. Passcode will be removed from the cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24640 DEBUG Radius-Token: Cached Passcode doesn't match passcode in authentication request. Passcode will be removed from the cache, <log details>

- 消息代码: 24641

严重性: 调试 (DEBUG)

消息文本: 用户记录已缓存在密码缓存中 (User record was cached in Passcode cache)

消息说明: 在 RADIUS 令牌 SecurID 服务器上身份验证成功后, 用户记录已缓存在密码缓存中。

本地目标消息格式: <timestamp> <seq_num> 24641 DEBUG Radius-Token: User record was cached in Passcode cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24641 DEBUG Radius-Token: User record was cached in Passcode cache, <log details>

- 消息代码: 24642

严重性: 调试 (DEBUG)

消息文本: 用户记录未缓存在密码缓存中 (User record was not cached in Passcode cache)

消息说明: 用户记录未缓存在密码缓存中。

本地目标消息格式: <timestamp> <seq_num> 24642 DEBUG Radius-Token: User record was not cached in Passcode cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24642 DEBUG Radius-Token: User record was not cached in Passcode cache, <log details>

- 消息代码: 24700

严重性: 调试 (DEBUG)

消息文本: 通过证书解析身份成功 (Identity resolution by certificate succeeded)

消息说明: 通过证书解析身份成功

本地目标消息格式: <timestamp> <seq_num> 24700 DEBUG External-Active-Directory: Identity resolution by certificate succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24700 DEBUG External-Active-Directory: Identity resolution by certificate succeeded, <log details>

- 消息代码: 24701

严重性: 调试 (DEBUG)

消息文本: 通过证书解析身份失败 (Identity resolution by certificate failed)

消息说明: 通过证书解析身份失败

本地目标消息格式: <timestamp> <seq_num> 24701 DEBUG External-Active-Directory: Identity resolution by certificate failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24701 DEBUG External-Active-Directory: Identity resolution by certificate failed, <log details>

- 消息代码: 24702

严重性: 调试 (DEBUG)

消息文本: 通过证书解析身份未找到匹配的帐户 (Identity resolution by certificate found no matching account)

消息说明: 通过证书解析身份未找到匹配的帐户

本地目标消息格式: <timestamp> <seq_num> 24702 DEBUG External-Active-Directory: Identity resolution by certificate found no matching account, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24702 DEBUG External-Active-Directory: Identity resolution by certificate found no matching account, <log details>

- 消息代码: 24703

严重性: 调试 (DEBUG)

消息文本: 通过证书解析身份找到了模糊匹配的帐户 (Identity resolution by certificate found ambiguous accounts)

消息说明: 通过证书解析身份找到了模糊匹配的帐户

本地目标消息格式: <timestamp> <seq_num> 24703 DEBUG External-Active-Directory: Identity resolution by certificate found ambiguous accounts, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24703 DEBUG External-Active-Directory: Identity resolution by certificate found ambiguous accounts, <log details>

- 消息代码: 24704

严重性: 调试 (DEBUG)

消息文本: 身份验证失败, 因为身份凭证的信息不够明确 (Authentication failed because identity credentials are ambiguous)

消息说明: 身份验证已找到多个与给定凭证 (即身份名称和密码) 匹配的帐户

本地目标消息格式: <timestamp> <seq_num> 24704 DEBUG External-Active-Directory: Authentication failed because identity credentials are ambiguous, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24704 DEBUG External-Active-Directory: Authentication failed because identity credentials are ambiguous, <log details>

- 消息代码: 24705

严重性: 调试 (DEBUG)

消息文本: 身份验证失败, 因为 ISE 服务器未加入所需的域 (Authentication failed because ISE server is not joined to required domains)

消息说明: 身份验证失败, 因为 ISE 服务器未加入所需的域

本地目标消息格式: <timestamp> <seq_num> 24705 DEBUG External-Active-Directory: Authentication failed because ISE server is not joined to required domains, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24705 DEBUG External-Active-Directory:
Authentication failed because ISE server is not joined to required domains, <log details>

- 消息代码: 24706

严重性: 调试 (DEBUG)

消息文本: 身份验证失败, 因为 NTLM 已被阻止 (Authentication failed because NTLM was blocked)

消息说明: 身份验证失败, 因为 NTLM 已被阻止

本地目标消息格式: <timestamp> <seq_num> 24706 DEBUG External-Active-Directory: Authentication failed because NTLM was blocked, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24706 DEBUG External-Active-Directory:
Authentication failed because NTLM was blocked, <log details>

- 消息代码: 24707

严重性: 调试 (DEBUG)

消息文本: 身份验证失败, 因为所有身份名称均已被拒绝 (Authentication failed because all identity names have been rejected)

消息说明: 根据 AD 身份存储库高级设置, 所有身份名称均已被拒绝, 因此身份验证失败。

本地目标消息格式: <timestamp> <seq_num> 24707 DEBUG External-Active-Directory: Authentication failed because all identity names have been rejected, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24707 DEBUG External-Active-Directory:
Authentication failed because all identity names have been rejected, <log details>

- 消息代码: 24708

严重性: 调试 (DEBUG)

消息文本: 在 Active Directory 中找不到用户。某些身份验证域不可用 (User not found in Active Directory. Some authentication domains were not available)

消息说明: 在 Active Directory 中找不到用户。在身份解析过程中, 某些身份验证域不可用

本地目标消息格式: <timestamp> <seq_num> 24708 DEBUG External-Active-Directory: User not found in Active Directory. Some authentication domains were not available, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24708 DEBUG External-Active-Directory:
User not found in Active Directory. Some authentication domains were not available, <log details>

- 消息代码: 24709

严重性: 调试 (DEBUG)

消息文本: 在 Active Directory 中找不到主机。某些身份验证域不可用 (Host not found in Active Directory. Some authentication domains were not available)

消息说明：在 Active Directory 中找不到主机。在身份解析过程中，某些身份验证域不可用

本地目标消息格式：<timestamp> <seq_num> 24709 DEBUG External-Active-Directory: Host not found in Active Directory. Some authentication domains were not available, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24709 DEBUG External-Active-Directory: Host not found in Active Directory. Some authentication domains were not available, <log details>

- 消息代码：24710

严重性：调试 (DEBUG)

消息文本：已将身份解析配置为在所需的域不可用时丢弃请求 (Identity resolution is configured to drop request if required domain is not available)

消息说明：已将身份解析配置为在所需的域不可用时丢弃请求

本地目标消息格式：<timestamp> <seq_num> 24710 DEBUG External-Active-Directory: Identity resolution is configured to drop request if required domain is not available, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24710 DEBUG External-Active-Directory: Identity resolution is configured to drop request if required domain is not available, <log details>

- 消息代码：24711

严重性：调试 (DEBUG)

消息文本：域控制器无法通过信任路径将请求传递到帐户域 (Domain controller cannot pass request through the trust path to the account domain)

消息说明：域控制器无法通过信任路径将请求从加入点域传递到用户帐户所在的域

本地目标消息格式：<timestamp> <seq_num> 24711 DEBUG External-Active-Directory: Domain controller cannot pass request through the trust path to the account domain, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24711 DEBUG External-Active-Directory: Domain controller cannot pass request through the trust path to the account domain, <log details>

- 消息代码：24712

严重性：调试 (DEBUG)

消息文本：身份验证失败，因为域信任受到限制 (Authentication failed because domain trust is restricted)

消息说明：身份验证失败，因为域信任受到限制

本地目标消息格式：<timestamp> <seq_num> 24712 DEBUG External-Active-Directory: Authentication failed because domain trust is restricted, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24712 DEBUG External-Active-Directory: Authentication failed because domain trust is restricted, <log details>

- 消息代码: 24713

严重性: 调试 (DEBUG)

消息文本: ISE 对等体已确认 Active Directory 中用户的上一次成功的计算机身份验证 (ISE peer has confirmed previous successful machine authentication for user in Active Directory)

消息说明: ISE 对等体已确认 Active Directory 中用户的上一次成功的计算机身份验证

本地目标消息格式: <timestamp> <seq_num> 24713 DEBUG External-Active-Directory: ISE peer has confirmed previous successful machine authentication for user in Active Directory, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24713 DEBUG External-Active-Directory: ISE peer has confirmed previous successful machine authentication for user in Active Directory, <log details>

- 消息代码: 24714

严重性: 调试 (DEBUG)

消息文本: ISE 对等体未确认 Active Directory 中用户的上一次成功的计算机身份验证 (ISE peers have not confirmed previous successful machine authentication for user in Active Directory)

消息说明: ISE 对等体未确认 Active Directory 中用户的上一次成功的计算机身份验证

本地目标消息格式: <timestamp> <seq_num> 24714 DEBUG External-Active-Directory: ISE peers have not confirmed previous successful machine authentication for user in Active Directory, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24714 DEBUG External-Active-Directory: ISE peers have not confirmed previous successful machine authentication for user in Active Directory, <log details>

- 消息代码: 24715

严重性: 调试 (DEBUG)

消息文本: ISE 未确认 Active Directory 中用户的上一次成功的本地计算机身份验证 (ISE has not confirmed locally previous successful machine authentication for user in Active Directory)

消息说明: ISE 未确认 Active Directory 中用户的上一次成功的本地计算机身份验证。ACS 正在询问对等体是否确认

本地目标消息格式: <timestamp> <seq_num> 24715 DEBUG External-Active-Directory: ISE has not confirmed locally previous successful machine authentication for user in Active Directory, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24715 DEBUG External-Active-Directory: ISE has not confirmed locally previous successful machine authentication for user in Active Directory, <log details>

- 消息代码: 24800

严重性: 信息 (INFO)

消息文本: 已导出 SAML 门户元数据 (SAML Portal metadata was exported)

消息说明: 已导出 SAML 门户元数据

本地目标消息格式: <timestamp> <seq_num> 24800 INFO System-Management: SAML Portal metadata was exported, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24800 INFO System-Management: SAML Portal metadata was exported, <log details>

- 消息代码: 24801

严重性: 信息 (INFO)

消息文本: 无法解码 SAML 请求 (Unable to decode SAML request)

消息说明: 无法解码 SAML 请求

本地目标消息格式: <timestamp> <seq_num> 24801 INFO External-SAML-IdP: Unable to decode SAML request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24801 INFO External-SAML-IdP: Unable to decode SAML request, <log details>

- 消息代码: 24802

严重性: 信息 (INFO)

消息文本: 为“用户名”使用了未知的 SAML 属性值类型断言 (Unknown SAML attribute value type assertion used for 'username')

消息说明: 为“用户名”使用了未知的 SAML 属性值类型断言

本地目标消息格式: <timestamp> <seq_num> 24802 INFO External-SAML-IdP: Unknown SAML attribute value type assertion used for 'username', <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24802 INFO External-SAML-IdP: Unknown SAML attribute value type assertion used for 'username', <log details>

- 消息代码: 24803

严重性: 信息 (INFO)

消息文本: 无法找到“用户名”属性断言 (Unable to find 'username' attribute assertion)

消息说明: 无法找到“用户名”属性断言

本地目标消息格式: <timestamp> <seq_num> 24803 INFO External-SAML-IdP: Unable to find 'username' attribute assertion, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24803 INFO External-SAML-IdP: Unable to find 'username' attribute assertion, <log details>

- 消息代码: 24804

严重性: 信息 (INFO)

消息文本: SAML 消息的预期目标 (绑定要求) 不存在 (SAML message intended destination (required by binding) was not present)

消息说明: SAML 消息的预期目标 (绑定要求) 不存在

本地目标消息格式: <timestamp> <seq_num> 24804 INFO External-SAML-IdP: SAML message intended destination (required by binding) was not present, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24804 INFO External-SAML-IdP: SAML message intended destination (required by binding) was not present, <log details>

• 消息代码: 24805

严重性: 信息 (INFO)

消息文本: SAML 消息的预期目标终端与接收者终端不匹配 (SAML message intended destination endpoint did not match recipient endpoint)

消息说明: SAML 消息的预期目标终端与接收者终端不匹配

本地目标消息格式: <timestamp> <seq_num> 24805 INFO External-SAML-IdP: SAML message intended destination endpoint did not match recipient endpoint, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24805 INFO External-SAML-IdP: SAML message intended destination endpoint did not match recipient endpoint, <log details>

• 消息代码: 24806

严重性: 警告 (WARN)

消息文本: SAML IdentityProvider 证书无效 (SAML IdentityProvider Certificate is not valid)

消息说明: SAML IdentityProvider 证书无效

本地目标消息格式: <timestamp> <seq_num> 24806 WARN External-SAML-IdP: SAML IdentityProvider Certificate is not valid, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24806 WARN External-SAML-IdP: SAML IdentityProvider Certificate is not valid, <log details>

• 消息代码: 24807

严重性: 警告 (WARN)

消息文本: 未检查 SAML IdentityProvider 证书 (SAML IdentityProvider Certificate was not checked)

消息说明: 未检查 SAML IdentityProvider 证书

本地目标消息格式: <timestamp> <seq_num> 24807 WARN External-SAML-IdP: SAML IdentityProvider Certificate was not checked, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num> 24807 WARN External-SAML-IdP: SAML
IdentityProvider Certificate was not checked, <log details>

- 消息代码: 24808

严重性: 警告 (WARN)

消息文本: SAML IdentityProvider 证书已过期 (SAML IdentityProvider Certificate is expired)

消息说明: SAML IdentityProvider 证书已过期

本地目标消息格式: <timestamp> <seq_num> 24808 WARN External-SAML-IdP: SAML
IdentityProvider Certificate is expired, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num> 24808 WARN External-SAML-IdP: SAML
IdentityProvider Certificate is expired, <log details>

- 消息代码: 24809

严重性: 警告 (WARN)

消息文本: SAML IdentityProvider 证书已撤销 (SAML IdentityProvider Certificate is revoked)

消息说明: SAML IdentityProvider 证书已撤销

本地目标消息格式: <timestamp> <seq_num> 24809 WARN External-SAML-IdP: SAML
IdentityProvider Certificate is revoked, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num> 24809 WARN External-SAML-IdP: SAML
IdentityProvider Certificate is revoked, <log details>

- 消息代码: 24810

严重性: 警告 (WARN)

消息文本: SAML IdentityProvider CA 证书无效 (SAML IdentityProvider CA Certificate is not valid)

消息说明: SAML IdentityProvider CA 证书无效

本地目标消息格式: <timestamp> <seq_num> 24810 WARN External-SAML-IdP: SAML
IdentityProvider CA Certificate is not valid, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num> 24810 WARN External-SAML-IdP: SAML
IdentityProvider CA Certificate is not valid, <log details>

- 消息代码: 24811

严重性: 信息 (INFO)

消息文本: 因请求者方面出现错误而导致系统无法执行请求 (The request could not be performed
due to an error on the part of the requester)

消息说明: 因请求者方面出现错误而导致系统无法执行请求

本地目标消息格式: <timestamp> <seq_num> 24811 INFO External-SAML-IdP: The request could not be performed due to an error on the part of the requester, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24811 INFO External-SAML-IdP: The request could not be performed due to an error on the part of the requester, <log details>

- 消息代码: 24812

严重性: 信息 (INFO)

消息文本: 因 SAML 响应者或 SAML 授权机构方面出现错误而导致系统无法执行请求 (The request could not be performed due to an error on the part of the SAML responder or SAML authority)

消息说明: 因 SAML 响应者或 SAML 授权机构方面出现错误而导致系统无法执行请求

本地目标消息格式: <timestamp> <seq_num> 24812 INFO External-SAML-IdP: The request could not be performed due to an error on the part of the SAML responder or SAML authority, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24812 INFO External-SAML-IdP: The request could not be performed due to an error on the part of the SAML responder or SAML authority, <log details>

- 消息代码: 24813

严重性: 信息 (INFO)

消息文本: 由于请求消息的版本不正确, 因此 SAML 响应者无法处理该请求 (The SAML responder could not process the request because the version of the request message was incorrect)

消息说明: 由于请求消息的版本不正确, 因此 SAML 响应者无法处理该请求

本地目标消息格式: <timestamp> <seq_num> 24813 INFO External-SAML-IdP: The SAML responder could not process the request because the version of the request message was incorrect, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24813 INFO External-SAML-IdP: The SAML responder could not process the request because the version of the request message was incorrect, <log details>

- 消息代码: 24814

严重性: 信息 (INFO)

消息文本: 响应提供者无法成功验证主体身份 (The responding provider was unable to successfully authenticate the principal)

消息说明: 响应提供者无法成功验证主体身份

本地目标消息格式: <timestamp> <seq_num> 24814 INFO External-SAML-IdP: The responding provider was unable to successfully authenticate the principal, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24814 INFO External-SAML-IdP: The responding provider was unable to successfully authenticate the principal, <log details>

- 消息代码: 24815
 - 严重性: 信息 (INFO)
 - 消息文本: saml:Attribute 或 saml:AttributeValue 元素中遇到了意外或无效的内容 (Unexpected or invalid content was encountered within a saml:Attribute or saml:AttributeValue element)
 - 消息说明: saml:Attribute 或 saml:AttributeValue 元素中遇到了意外或无效的内容
 - 本地目标消息格式: <timestamp> <seq_num> 24815 INFO External-SAML-IdP: Unexpected or invalid content was encountered within a saml:Attribute or saml:AttributeValue element, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24815 INFO External-SAML-IdP: Unexpected or invalid content was encountered within a saml:Attribute or saml:AttributeValue element, <log details>

- 消息代码: 24816
 - 严重性: 信息 (INFO)
 - 消息文本: SAML 响应者或 SAML 授权机构能够处理请求, 但已选择不作响应。(The SAML responder or SAML authority is able to process the request but has chosen not to respond.)
 - 消息说明: SAML 响应者或 SAML 授权机构能够处理请求, 但已选择不作响应。当请求消息的安全环境存忧, 或从特定请求者收到的请求消息的序列存忧时, 可能使用此状态代码
 - 本地目标消息格式: <timestamp> <seq_num> 24816 INFO External-SAML-IdP: The SAML responder or SAML authority is able to process the request but has chosen not to respond., <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24816 INFO External-SAML-IdP: The SAML responder or SAML authority is able to process the request but has chosen not to respond., <log details>

- 消息代码: 24817
 - 严重性: 信息 (INFO)
 - 消息文本: SAML 响应者或 SAML 授权机构不支持指定的请求 (The SAML responder or SAML authority does not support the request)
 - 消息说明: SAML 响应者或 SAML 授权机构不支持指定的请求
 - 本地目标消息格式: <timestamp> <seq_num> 24817 INFO External-SAML-IdP: The SAML responder or SAML authority does not support the request, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24817 INFO External-SAML-IdP: The SAML responder or SAML authority does not support the request, <log details>

- 消息代码: 24818
 - 严重性: 信息 (INFO)
 - 消息文本: SAML 响应者无法使用请求中指定的协议绑定正确履行请求 (The SAML responder cannot properly fulfil the request using the protocol binding specified in the request)

消息说明: SAML 响应者无法使用请求中指定的协议绑定正确履行请求

本地目标消息格式: <timestamp> <seq_num> 24818 INFO External-SAML-IdP: The SAML responder cannot properly fulfil the request using the protocol binding specified in the request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24818 INFO External-SAML-IdP: The SAML responder cannot properly fulfil the request using the protocol binding specified in the request, <log details>

- 消息代码: 24819

严重性: 信息 (INFO)

消息文本: 无法从 SAML 响应检索签名证书 (Failed to retrieve signing certificate from the SAML response)

消息说明: 无法从 SAML 响应检索签名证书

本地目标消息格式: <timestamp> <seq_num> 24819 INFO External-SAML-IdP: Failed to retrieve signing certificate from the SAML response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24819 INFO External-SAML-IdP: Failed to retrieve signing certificate from the SAML response, <log details>

- 消息代码: 24820

严重性: 调试 (DEBUG)

消息文本: 断言中不包含颁发者 (Assertion does not contain Issuer)

消息说明: 断言必须包含颁发者

本地目标消息格式: <timestamp> <seq_num> 24820 DEBUG External-SAML-IdP: Assertion does not contain Issuer, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24820 DEBUG External-SAML-IdP: Assertion does not contain Issuer, <log details>

- 消息代码: 24821

严重性: 调试 (DEBUG)

消息文本: 断言中不包含身份验证语句 (Assertion does not contain authentication statement)

消息说明: 断言中必须包含身份验证语句

本地目标消息格式: <timestamp> <seq_num> 24821 DEBUG External-SAML-IdP: Assertion does not contain authentication statement, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24821 DEBUG External-SAML-IdP: Assertion does not contain authentication statement, <log details>

- 消息代码: 24822

严重性: 调试 (DEBUG)

消息文本: 断言中不包含受众限制条件 (Assertion does not contain audience restriction conditions)

消息说明: 断言中必须包含受众限制条件

本地目标消息格式: <timestamp> <seq_num> 24822 DEBUG External-SAML-IdP: Assertion does not contain audience restriction conditions, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24822 DEBUG External-SAML-IdP: Assertion does not contain audience restriction conditions, <log details>

- 消息代码: 24823

严重性: 调试 (DEBUG)

消息文本: 断言的受众限制条件中不包含匹配的运营商标识符 (Assertion does not contain matching service provider identifier in the audience restriction conditions)

消息说明: 断言的受众限制条件中必须包含匹配的运营商标识符

本地目标消息格式: <timestamp> <seq_num> 24823 DEBUG External-SAML-IdP: Assertion does not contain matching service provider identifier in the audience restriction conditions, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24823 DEBUG External-SAML-IdP: Assertion does not contain matching service provider identifier in the audience restriction conditions, <log details>

- 消息代码: 24824

严重性: 调试 (DEBUG)

消息文本: 主题确认中不包含主题确认数据 (Subject confirmation does not contain subject confirmation data)

消息说明: 主题确认中必须包含主题确认数据

本地目标消息格式: <timestamp> <seq_num> 24824 DEBUG External-SAML-IdP: Subject confirmation does not contain subject confirmation data, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24824 DEBUG External-SAML-IdP: Subject confirmation does not contain subject confirmation data, <log details>

- 消息代码: 24825

严重性: 调试 (DEBUG)

消息文本: 响应中必须包含一个断言 (The response must contain single assertion)

消息说明: 响应中必须包含一个断言

本地目标消息格式: <timestamp> <seq_num> 24825 DEBUG External-SAML-IdP: The response must contain single assertion, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24825 DEBUG External-SAML-IdP: The response must contain single assertion, <log details>

- 消息代码: 24826

严重性: 调试 (DEBUG)

消息文本: 接收者与断言使用 URL 不匹配 (Recipient does not match assertion consumption URL)

消息说明: 接收者必须与断言使用 URL 相匹配

本地目标消息格式: <timestamp> <seq_num> 24826 DEBUG External-SAML-IdP: Recipient does not match assertion consumption URL, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24826 DEBUG External-SAML-IdP: Recipient does not match assertion consumption URL, <log details>

- 消息代码: 24827

严重性: 调试 (DEBUG)

消息文本: 主题确认数据中不包含 NotOnOrAfter (Subject confirmation data does not contain NotOnOrAfter)

消息说明: 主题确认数据中必须包含 NotOnOrAfter

本地目标消息格式: <timestamp> <seq_num> 24827 DEBUG External-SAML-IdP: Subject confirmation data does not contain NotOnOrAfter, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24827 DEBUG External-SAML-IdP: Subject confirmation data does not contain NotOnOrAfter, <log details>

- 消息代码: 24828

严重性: 调试 (DEBUG)

消息文本: 断言已过期 (Assertion is expired)

消息说明: 断言已过期

本地目标消息格式: <timestamp> <seq_num> 24828 DEBUG External-SAML-IdP: Assertion is expired, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24828 DEBUG External-SAML-IdP: Assertion is expired, <log details>

- 消息代码: 24829

严重性: 调试 (DEBUG)

消息文本: 主题确认数据中的 IP 地址与最终用户 IP 地址不匹配 (Subject confirmation data IP address does not match end user IP address)

消息说明：主题确认数据中的 IP 地址与最终用户 IP 地址不匹配

本地目标消息格式：<timestamp> <seq_num> 24829 DEBUG External-SAML-IdP: Subject confirmation data IP address does not match end user IP address, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24829 DEBUG External-SAML-IdP: Subject confirmation data IP address does not match end user IP address, <log details>

- 消息代码：24830

严重性：调试 (DEBUG)

消息文本：主题确认数据中不包含 InResponseTo (Subject confirmation data does not contain InResponseTo)

消息说明：主题确认数据中必须包含 InResponseTo

本地目标消息格式：<timestamp> <seq_num> 24830 DEBUG External-SAML-IdP: Subject confirmation data does not contain InResponseTo, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24830 DEBUG External-SAML-IdP: Subject confirmation data does not contain InResponseTo, <log details>

- 消息代码：24831

严重性：调试 (DEBUG)

消息文本：InResponseTo 与原始请求 ID 不匹配 (The InResponseTo does not match the original request id)

消息说明：InResponseTo 必须与原始请求 ID 相匹配

本地目标消息格式：<timestamp> <seq_num> 24831 DEBUG External-SAML-IdP: The InResponseTo does not match the original request id, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24831 DEBUG External-SAML-IdP: The InResponseTo does not match the original request id, <log details>

- 消息代码：24832

严重性：调试 (DEBUG)

消息文本：颁发者格式不等于 urn:oasis:names:tc:SAML:2.0:nameid-format:entity (Issuer format is not equal to urn:oasis:names:tc:SAML:2.0:nameid-format:entity)

消息说明：颁发者格式必须等同于 urn:oasis:names:tc:SAML:2.0:nameid-format:entity

本地目标消息格式：<timestamp> <seq_num> 24832 DEBUG External-SAML-IdP: Issuer format is not equal to urn:oasis:names:tc:SAML:2.0:nameid-format:entity, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24832 DEBUG External-SAML-IdP: Issuer format is not equal to urn:oasis:names:tc:SAML:2.0:nameid-format:entity, <log details>

- 消息代码: 24833
 - 严重性: 调试 (DEBUG)
 - 消息文本: 颁发者与身份提供商 ID 不匹配 (Issuer does not match Identity Provider ID)
 - 消息说明: 颁发者与身份提供商 ID 不匹配
 - 本地目标消息格式: <timestamp> <seq_num> 24833 DEBUG External-SAML-IdP: Issuer does not match Identity Provider ID, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24833 DEBUG External-SAML-IdP: Issuer does not match Identity Provider ID, <log details>

- 消息代码: 24834
 - 严重性: 调试 (DEBUG)
 - 消息文本: 断言中不包含主题 (Assertion does not contain subject)
 - 消息说明: 断言必须包含主题
 - 本地目标消息格式: <timestamp> <seq_num> 24834 DEBUG External-SAML-IdP: Assertion does not contain subject, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24834 DEBUG External-SAML-IdP: Assertion does not contain subject, <log details>

- 消息代码: 24835
 - 严重性: 调试 (DEBUG)
 - 消息文本: 断言中不包含主题确认 (Assertion does not contain subject confirmation)
 - 消息说明: 断言必须包含主题确认
 - 本地目标消息格式: <timestamp> <seq_num> 24835 DEBUG External-SAML-IdP: Assertion does not contain subject confirmation, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24835 DEBUG External-SAML-IdP: Assertion does not contain subject confirmation, <log details>

- 消息代码: 24836
 - 严重性: 调试 (DEBUG)
 - 消息文本: 断言中不包含不记名主题确认 (Assertion does not contain bearer subject confirmation)
 - 消息说明: 断言中必须包含不记名主题确认
 - 本地目标消息格式: <timestamp> <seq_num> 24836 DEBUG External-SAML-IdP: Assertion does not contain bearer subject confirmation, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24836 DEBUG External-SAML-IdP: Assertion
does not contain bearer subject confirmation, <log details>

- 消息代码: 24837

严重性: 调试 (DEBUG)

消息文本: 已签名的响应中不包含目标 (The signed response does not contain a Destination)

消息说明: 已签名的响应中必须包含目标

本地目标消息格式: <timestamp> <seq_num> 24837 DEBUG External-SAML-IdP: The signed response
does not contain a Destination, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24837 DEBUG External-SAML-IdP: The
signed response does not contain a Destination, <log details>

- 消息代码: 24838

严重性: 调试 (DEBUG)

消息文本: 响应中的目标与断言使用者 URL 不匹配 (The Destination on the response does not match
the assertion consumer URL)

消息说明: 响应中的目标必须与断言使用者 URL 相匹配

本地目标消息格式: <timestamp> <seq_num> 24838 DEBUG External-SAML-IdP: The Destination
on the response does not match the assertion consumer URL, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24838 DEBUG External-SAML-IdP: The
Destination on the response does not match the assertion consumer URL, <log details>

- 消息代码: 24839

严重性: 调试 (DEBUG)

消息文本: 响应中不包含断言 (The response does not contain assertion)

消息说明: 响应中必须包含断言

本地目标消息格式: <timestamp> <seq_num> 24839 DEBUG External-SAML-IdP: The response does
not contain assertion, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24839 DEBUG External-SAML-IdP: The
response does not contain assertion, <log details>

- 消息代码: 24840

严重性: 调试 (DEBUG)

消息文本: 响应签名无效 (The response signature is invalid)

消息说明: 响应签名无效

本地目标消息格式: <timestamp> <seq_num> 24840 DEBUG External-SAML-IdP: The response signature is invalid, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24840 DEBUG External-SAML-IdP: The response signature is invalid, <log details>

- 消息代码: 24841

严重性: 调试 (DEBUG)

消息文本: 响应签名未根据 IdP 签名证书进行验证 (Response signature did not validate against the IdP signature certificate)

消息说明: 响应签名未根据在 ISE 中的 SAML 身份提供商上配置的签名证书进行验证

本地目标消息格式: <timestamp> <seq_num> 24841 DEBUG External-SAML-IdP: Response signature did not validate against the IdP signature certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24841 DEBUG External-SAML-IdP: Response signature did not validate against the IdP signature certificate, <log details>

- 消息代码: 24842

严重性: 调试 (DEBUG)

消息文本: 响应中的断言签名无效 (The assertion signature on the response is invalid)

消息说明: 响应中的断言签名无效

本地目标消息格式: <timestamp> <seq_num> 24842 DEBUG External-SAML-IdP: The assertion signature on the response is invalid, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24842 DEBUG External-SAML-IdP: The assertion signature on the response is invalid, <log details>

- 消息代码: 24843

严重性: 调试 (DEBUG)

消息文本: 断言签名未根据 IdP 签名证书进行验证 (Assertion signature is not not validated against the IdP signature certificate)

消息说明: 断言签名未根据在 ISE 中的 SAML 身份提供商上配置的签名证书进行验证

本地目标消息格式: <timestamp> <seq_num> 24843 DEBUG External-SAML-IdP: Assertion signature is not not validated against the IdP signature certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24843 DEBUG External-SAML-IdP: Assertion signature is not not validated against the IdP signature certificate, <log details>

- 消息代码: 24844

严重性: 调试 (DEBUG)

消息文本: SAML 响应和断言均已签名 (Neither SAML response nor assertion are signed)

消息说明: SAML 响应和断言均已签名

本地目标消息格式: <timestamp> <seq_num> 24844 DEBUG External-SAML-IdP: Neither SAML response nor assertion are signed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24844 DEBUG External-SAML-IdP: Neither SAML response nor assertion are signed, <log details>

- 消息代码: 24845

严重性: 调试 (DEBUG)

消息文本: SAML 响应只能包含一个签名证书 (SAML response can contain only one signing certificate)

消息说明: SAML 响应包含多个证书, 因此无法确定该用哪个证书进行签名验证

本地目标消息格式: <timestamp> <seq_num> 24845 DEBUG External-SAML-IdP: SAML response can contain only one signing certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24845 DEBUG External-SAML-IdP: SAML response can contain only one signing certificate, <log details>

- 消息代码: 24846

严重性: 调试 (DEBUG)

消息文本: 在 IdP 上配置了多个证书, 但无法确定用于签名的证书 (Several certificates are configured on IdP, however can not determine certificate for signature)

消息说明: 在 ISE 中的 SAML 身份提供商上配置了多个证书, 但 SAML 响应中不包含签名证书。无法确定该用哪个证书进行签名验证

本地目标消息格式: <timestamp> <seq_num> 24846 DEBUG External-SAML-IdP: Several certificates are configured on IdP, however can not determine certificate for signature, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 24846 DEBUG External-SAML-IdP: Several certificates are configured on IdP, however can not determine certificate for signature, <log details>

- 消息代码: 24847

严重性: 调试 (DEBUG)

消息文本: 证书无效 (Certificate is invalid)

消息说明: 证书无效

本地目标消息格式: <timestamp> <seq_num> 24847 DEBUG External-SAML-IdP: Certificate is invalid, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24847 DEBUG External-SAML-IdP:
Certificate is invalid, <log details>

- 消息代码: 24848

严重性: 调试 (DEBUG)

消息文本: 无法从 IdP 配置获取签名证书 (Failed to get signing certificate from IdP configuration)

消息说明: ISE 中的身份提供商配置出现意外问题, 因此无法获取签名证书

本地目标消息格式: <timestamp> <seq_num> 24848 DEBUG External-SAML-IdP: Failed to get
signing certificate from IdP configuration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24848 DEBUG External-SAML-IdP: Failed
to get signing certificate from IdP configuration, <log details>

- 消息代码: 24849

严重性: 调试 (DEBUG)

消息文本: 正在连接到外部 ODBC 数据库 (Connecting to external ODBC database)

消息说明: ISE 将与外部 ODBC 数据库建立新连接

本地目标消息格式: <timestamp> <seq_num> 24849 DEBUG External-ODBC: Connecting to external
ODBC database, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24849 DEBUG External-ODBC: Connecting
to external ODBC database, <log details>

- 消息代码: 24850

严重性: 调试 (DEBUG)

消息文本: 已成功连接到外部 ODBC 数据库 (Successfully connected to external ODBC database)

消息说明: ISE 已成功建立与外部 ODBC 数据库的新连接

本地目标消息格式: <timestamp> <seq_num> 24850 DEBUG External-ODBC: Successfully connected
to external ODBC database, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24850 DEBUG External-ODBC: Successfully
connected to external ODBC database, <log details>

- 消息代码: 24851

严重性: 调试 (DEBUG)

消息文本: 连接到外部 ODBC 数据库失败 (Connection to external ODBC database failed)

消息说明: ISE 未能与外部 ODBC 数据库建立新连接

本地目标消息格式: <timestamp> <seq_num> 24851 DEBUG External-ODBC: Connection to external ODBC database failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24851 DEBUG External-ODBC: Connection to external ODBC database failed, <log details>

- 消息代码: 24852

严重性: 调试 (DEBUG)

消息文本: 在外部 ODBC 数据库中执行纯文本密码身份验证 (Perform plain text password authentication in external ODBC database)

消息说明: ISE 开始在外部 ODBC 数据库上进行纯文本密码身份验证

本地目标消息格式: <timestamp> <seq_num> 24852 DEBUG External-ODBC: Perform plain text password authentication in external ODBC database, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24852 DEBUG External-ODBC: Perform plain text password authentication in external ODBC database, <log details>

- 消息代码: 24853

严重性: 调试 (DEBUG)

消息文本: 外部 ODBC 数据库中的纯文本密码身份验证成功 (Plain text password authentication in external ODBC database succeeded)

消息说明: 外部 ODBC 数据库中的纯文本密码身份验证成功

本地目标消息格式: <timestamp> <seq_num> 24853 DEBUG External-ODBC: Plain text password authentication in external ODBC database succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24853 DEBUG External-ODBC: Plain text password authentication in external ODBC database succeeded, <log details>

- 消息代码: 24854

严重性: 调试 (DEBUG)

消息文本: 外部 ODBC 数据库中的纯文本密码身份验证失败 (Plain text password authentication in external ODBC database failed)

消息说明: 外部 ODBC 数据库中的纯文本密码身份验证失败

本地目标消息格式: <timestamp> <seq_num> 24854 DEBUG External-ODBC: Plain text password authentication in external ODBC database failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24854 DEBUG External-ODBC: Plain text password authentication in external ODBC database failed, <log details>

- 消息代码: 24855

严重性: 调试 (DEBUG)

消息文本: 期望外部 ODBC 数据库已存储程序在记录集中返回结果 (Expect external ODBC database stored procedure to return results in a recordset)

消息说明: 期望外部 ODBC 数据库已存储程序在记录集中返回结果

本地目标消息格式: <timestamp> <seq_num> 24855 DEBUG External-ODBC: Expect external ODBC database stored procedure to return results in a recordset, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24855 DEBUG External-ODBC: Expect external ODBC database stored procedure to return results in a recordset, <log details>

- 消息代码: 24856

严重性: 调试 (DEBUG)

消息文本: 期望外部 ODBC 数据库已存储程序在输出参数中返回结果 (Expect external ODBC database stored procedure to return results in output parameters)

消息说明: 期望外部 ODBC 数据库已存储程序在输出参数中返回结果

本地目标消息格式: <timestamp> <seq_num> 24856 DEBUG External-ODBC: Expect external ODBC database stored procedure to return results in output parameters, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24856 DEBUG External-ODBC: Expect external ODBC database stored procedure to return results in output parameters, <log details>

- 消息代码: 24857

严重性: 调试 (DEBUG)

消息文本: 未能处理返回的记录集中外部 ODBC 数据库已存储程序的结果 (Failed processing external ODBC database stored procedure results in a returned recordset)

消息说明: 未能处理返回的记录集中外部 ODBC 数据库已存储程序的结果

本地目标消息格式: <timestamp> <seq_num> 24857 DEBUG External-ODBC: Failed processing external ODBC database stored procedure results in a returned recordset, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24857 DEBUG External-ODBC: Failed processing external ODBC database stored procedure results in a returned recordset, <log details>

- 消息代码: 24858

严重性: 调试 (DEBUG)

消息文本: 未能处理返回的输出参数中外部 ODBC 数据库已存储程序的结果 (Failed processing external ODBC database stored procedure results in a returned output parameters)

消息说明: 未能处理返回的输出参数中外部 ODBC 数据库已存储程序的结果

本地目标消息格式: <timestamp> <seq_num> 24858 DEBUG External-ODBC: Failed processing external ODBC database stored procedure results in a returned output parameters, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24858 DEBUG External-ODBC: Failed
processing external ODBC database stored procedure results in a returned output parameters, <log details>

- 消息代码: 24859

严重性: 调试 (DEBUG)

消息文本: 调用外部 ODBC 数据库已存储程序失败 (Failed calling external ODBC database stored
procedure)

消息说明: ISE 未能调用为特定凭证检查类型配置的外部 ODBC 数据库已存储程序

本地目标消息格式: <timestamp> <seq_num> 24859 DEBUG External-ODBC: Failed calling external
ODBC database stored procedure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24859 DEBUG External-ODBC: Failed
calling external ODBC database stored procedure, <log details>

- 消息代码: 24860

严重性: 调试 (DEBUG)

消息文本: ODBC 数据库指示纯文本密码身份验证失败 (ODBC database indicated plain text password
authentication failure)

消息说明: ODBC 数据库指示纯文本密码身份验证失败

本地目标消息格式: <timestamp> <seq_num> 24860 DEBUG External-ODBC: ODBC database
indicated plain text password authentication failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24860 DEBUG External-ODBC: ODBC
database indicated plain text password authentication failure, <log details>

- 消息代码: 24861

严重性: 调试 (DEBUG)

消息文本: 从外部 ODBC 数据库获取纯文本密码 (Perform fetch of plain text password from external
ODBC database)

消息说明: ISE 开始从外部 ODBC 数据库获取纯文本密码

本地目标消息格式: <timestamp> <seq_num> 24861 DEBUG External-ODBC: Perform fetch of plain
text password from external ODBC database, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24861 DEBUG External-ODBC: Perform
fetch of plain text password from external ODBC database, <log details>

- 消息代码: 24862

严重性: 调试 (DEBUG)

消息文本: 从外部 ODBC 数据库获取纯文本密码成功 (Fetch plain text password from external ODBC database succeeded)

消息说明: 从外部 ODBC 数据库获取纯文本密码成功

本地目标消息格式: <timestamp> <seq_num> 24862 DEBUG External-ODBC: Fetch plain text password from external ODBC database succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24862 DEBUG External-ODBC: Fetch plain text password from external ODBC database succeeded, <log details>

- 消息代码: 24863

严重性: 调试 (DEBUG)

消息文本: 从外部 ODBC 数据库获取纯文本密码失败 (Fetch plain text password from external ODBC database failed)

消息说明: 从外部 ODBC 数据库获取纯文本密码失败

本地目标消息格式: <timestamp> <seq_num> 24863 DEBUG External-ODBC: Fetch plain text password from external ODBC database failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24863 DEBUG External-ODBC: Fetch plain text password from external ODBC database failed, <log details>

- 消息代码: 24864

严重性: 调试 (DEBUG)

消息文本: ODBC 数据库指示获取纯文本密码失败 (ODBC database indicated fetching plain text password failure)

消息说明: ODBC 数据库指示获取纯文本密码失败

本地目标消息格式: <timestamp> <seq_num> 24864 DEBUG External-ODBC: ODBC database indicated fetching plain text password failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24864 DEBUG External-ODBC: ODBC database indicated fetching plain text password failure, <log details>

- 消息代码: 24865

严重性: 调试 (DEBUG)

消息文本: 在外部 ODBC 数据库中执行用户查找 (Perform lookup of the user external ODBC database)

消息说明: ISE 开始在外部 ODBC 数据库中查找用户

本地目标消息格式: <timestamp> <seq_num> 24865 DEBUG External-ODBC: Perform lookup of the user external ODBC database, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24865 DEBUG External-ODBC: Perform
lookup of the user external ODBC database, <log details>

- 消息代码: 24866

严重性: 调试 (DEBUG)

消息文本: 在外部 ODBC 数据库中查找用户成功 (Lookup of the user in external ODBC database
succeeded)

消息说明: 在外部 ODBC 数据库中查找用户成功

本地目标消息格式: <timestamp> <seq_num> 24866 DEBUG External-ODBC: Lookup of the user in
external ODBC database succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24866 DEBUG External-ODBC: Lookup
of the user in external ODBC database succeeded, <log details>

- 消息代码: 24867

严重性: 调试 (DEBUG)

消息文本: 在外部 ODBC 数据库中查找用户失败 (Lookup of the user in external ODBC database
failed)

消息说明: 在外部 ODBC 数据库中查找用户失败

本地目标消息格式: <timestamp> <seq_num> 24867 DEBUG External-ODBC: Lookup of the user in
external ODBC database failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24867 DEBUG External-ODBC: Lookup
of the user in external ODBC database failed, <log details>

- 消息代码: 24868

严重性: 调试 (DEBUG)

消息文本: ODBC 数据库指示用户查找失败 (ODBC database indicated user lookup failure)

消息说明: ODBC 数据库指示用户查找失败

本地目标消息格式: <timestamp> <seq_num> 24868 DEBUG External-ODBC: ODBC database
indicated user lookup failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 24868 DEBUG External-ODBC: ODBC
database indicated user lookup failure, <log details>

- 消息代码: 24869

严重性: 调试 (DEBUG)

消息文本: 获取外部 ODBC 数据库中的用户组 (Perform fetching of the user groups in external
ODBC database)

消息说明: ISE 开始获取外部 ODBC 数据库中的用户组

本地目标消息格式: <timestamp> <seq_num> 24869 DEBUG External-ODBC: Perform fetching of the user groups in external ODBC database, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24869 DEBUG External-ODBC: Perform fetching of the user groups in external ODBC database, <log details>

- 消息代码: 24870

严重性: 调试 (DEBUG)

消息文本: 成功获取外部 ODBC 数据库中的用户组 (Fetching of the user groups in external ODBC database succeeded)

消息说明: 成功获取外部 ODBC 数据库中的用户组

本地目标消息格式: <timestamp> <seq_num> 24870 DEBUG External-ODBC: Fetching of the user groups in external ODBC database succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24870 DEBUG External-ODBC: Fetching of the user groups in external ODBC database succeeded, <log details>

- 消息代码: 24871

严重性: 调试 (DEBUG)

消息文本: 未能获取外部 ODBC 数据库中的用户组 (Fetching of the user groups in external ODBC database failed)

消息说明: 未能获取外部 ODBC 数据库中的用户组

本地目标消息格式: <timestamp> <seq_num> 24871 DEBUG External-ODBC: Fetching of the user groups in external ODBC database failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24871 DEBUG External-ODBC: Fetching of the user groups in external ODBC database failed, <log details>

- 消息代码: 24872

严重性: 调试 (DEBUG)

消息文本: 获取外部 ODBC 数据库中的用户属性 (Perform fetching of the user attributes in external ODBC database)

消息说明: ISE 开始获取外部 ODBC 数据库中的用户属性

本地目标消息格式: <timestamp> <seq_num> 24872 DEBUG External-ODBC: Perform fetching of the user attributes in external ODBC database, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24872 DEBUG External-ODBC: Perform fetching of the user attributes in external ODBC database, <log details>

- 消息代码: 24873
 - 严重性: 调试 (DEBUG)
 - 消息文本: 成功获取外部 ODBC 数据库中的用户属性 (Fetching of the user attributes in external ODBC database succeeded)
 - 消息说明: 成功获取外部 ODBC 数据库中的用户属性
 - 本地目标消息格式: <timestamp> <seq_num> 24873 DEBUG External-ODBC: Fetching of the user attributes in external ODBC database succeeded, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24873 DEBUG External-ODBC: Fetching of the user attributes in external ODBC database succeeded, <log details>

- 消息代码: 24874
 - 严重性: 调试 (DEBUG)
 - 消息文本: 未能获取外部 ODBC 数据库中的用户属性 (Fetching of the user attributes in external ODBC database failed)
 - 消息说明: 未能获取外部 ODBC 数据库中的用户属性
 - 本地目标消息格式: <timestamp> <seq_num> 24874 DEBUG External-ODBC: Fetching of the user attributes in external ODBC database failed, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24874 DEBUG External-ODBC: Fetching of the user attributes in external ODBC database failed, <log details>

- 消息代码: 24875
 - 严重性: 调试 (DEBUG)
 - 消息文本: 未能处理从外部 ODBC 数据库获取用户属性的结果 (Failed to process results of fetching of the user attributes from external ODBC database)
 - 消息说明: 未能处理从外部 ODBC 数据库获取用户属性的结果
 - 本地目标消息格式: <timestamp> <seq_num> 24875 DEBUG External-ODBC: Failed to process results of fetching of the user attributes from external ODBC database, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24875 DEBUG External-ODBC: Failed to process results of fetching of the user attributes from external ODBC database, <log details>

- 消息代码: 24876
 - 严重性: 调试 (DEBUG)
 - 消息文本: 未能处理从外部 ODBC 数据库获取用户组的结果 (Failed to process results of fetching of the user groups from external ODBC database)
 - 消息说明: 未能处理从外部 ODBC 数据库获取用户组的结果

本地目标消息格式: <timestamp> <seq_num> 24876 DEBUG External-ODBC: Failed to process results of fetching of the user groups from external ODBC database, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24876 DEBUG External-ODBC: Failed to process results of fetching of the user groups from external ODBC database, <log details>

- 消息代码: 24877

严重性: 信息 (INFO)

消息文本: 不支持主题格式永久或临时作为身份属性 (Subject formats persistent or transient are not supported as Identity Attribute)

消息说明: 断言中的主题格式为永久或临时。不支持这些格式作为身份属性

本地目标消息格式: <timestamp> <seq_num> 24877 INFO External-SAML-IdP: Subject formats persistent or transient are not supported as Identity Attribute, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24877 INFO External-SAML-IdP: Subject formats persistent or transient are not supported as Identity Attribute, <log details>

- 消息代码: 24878

严重性: 调试 (DEBUG)

消息文本: 重试失败的 ODBC 操作 (Retry failed ODBC operation)

消息说明: 上一 ODBC 操作失败, 可以重试。再试一次

本地目标消息格式: <timestamp> <seq_num> 24878 DEBUG External-ODBC: Retry failed ODBC operation, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24878 DEBUG External-ODBC: Retry failed ODBC operation, <log details>

- 消息代码: 24879

严重性: 信息 (INFO)

消息文本: 未设置身份提供商元数据 (Identity provider metadata is not set)

消息说明: 身份提供商元数据未加载

本地目标消息格式: <timestamp> <seq_num> 24879 INFO External-SAML-IdP: Identity provider metadata is not set, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 24879 INFO External-SAML-IdP: Identity provider metadata is not set, <log details>

- 消息代码: 24880

严重性: 警告 (WARN)

消息文本: ODBC 操作因超时而失败 (ODBC operation failed due to timeout elapsed)

消息说明: ODBC 操作因超时而失败

本地目标消息格式: <timestamp> <seq_num> 24880 WARN External-ODBC: ODBC operation failed due to timeout elapsed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24880 WARN External-ODBC: ODBC operation failed due to timeout elapsed, <log details>

- 消息代码: 24890

严重性: 警告 (WARN)

消息文本: 社交登录操作失败 (Social Login operation failed)

消息说明: 社交登录操作失败。检查邮件详细信息以了解更多信息

本地目标消息格式: <timestamp> <seq_num> 24890 WARN External-Social-Login: Social Login operation failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24890 WARN External-Social-Login: Social Login operation failed, <log details>

- 消息代码: 24716

严重性: 信息 (INFO)

消息文本: Active Directory Kerberos 票证身份验证成功 (Active Directory Kerberos ticket authentication succeeded)

消息说明: Active Directory Kerberos 票证身份验证成功

本地目标消息格式: <timestamp> <seq_num> 24716 INFO External-Active-Directory Active Directory Kerberos ticket authentication succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24716 INFO External-Active-Directory Active Directory Kerberos ticket authentication succeeded, <log details>

- 消息代码: 24717

严重性: 错误 (ERROR)

消息文本: Active Directory Kerberos 票证身份验证失败 (Active Directory Kerberos ticket authentication failed)

消息说明: Active Directory Kerberos 票证身份验证失败

本地目标消息格式: <timestamp> <seq_num> 24717 ERROR External-Active-Directory Active Directory Kerberos ticket authentication failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 24717 ERROR External-Active-Directory Active Directory Kerberos ticket authentication failed, <log details>

- 消息代码: 24718
严重性: 错误 (ERROR)
消息文本: Active Directory Kerberos 票证已过期 (Active Directory Kerberos ticket expired)
消息说明: Active Directory Kerberos 票证已过期
本地目标消息格式: <timestamp> <seq_num>24718 ERROR External-Active-Directory Active Directory Kerberos ticket expired, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>24718 ERROR External-Active-Directory Active Directory Kerberos ticket expired, <log details>
- 消息代码: 24719
严重性: 调试 (DEBUG)
消息文本: Active Directory Kerberos 票证身份验证失败, 因为 ISE 帐户密码不匹配、完整性检查失败或票证过期 (Active Directory Kerberos ticket authentication failed because of the ISE account password mismatch, integrity check failure or expired ticket)
消息说明: Active Directory Kerberos 票证身份验证失败, 因为 ISE 帐户密码不匹配、完整性检查失败或票证过期
本地目标消息格式: <timestamp> <seq_num>24719 DEBUG External-Active-Directory Active Directory Kerberos ticket authentication failed because of the ISE account password mismatch, integrity check failure or expired ticket, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>24719 DEBUG External-Active-Directory Active Directory Kerberos ticket authentication failed because of the ISE account password mismatch, integrity check failure or expired ticket, <log details>
- 消息代码: 24900
严重性: 错误 (ERROR)
消息文本: 加载 LDAP ID 存储库失败, 因为主连接或辅助连接用的 CA 未知或缺失 (Loading LDAP ID Store failed because of an unknown or missing CA for primary or secondary connection)
消息说明: nan
本地目标消息格式: <timestamp> <seq_num>24900 ERROR ID-Stores-Configuration Loading LDAP ID Store failed because of an unknown or missing CA for primary or secondary connection, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>24900 ERROR ID-Stores-Configuration Loading LDAP ID Store failed because of an unknown or missing CA for primary or secondary connection, <log details>
- 消息代码: 24901
严重性: 错误 (ERROR)

消息文本: 加载 ID 存储库序列失败, 因为 ID 存储库缺失或损坏 (Loading ID Store Sequence failed because of missing or corrupted ID Store)

消息说明: nan

本地目标消息格式: <timestamp> <seq_num>24901 ERROR ID-Stores-Configuration Loading ID Store Sequence failed because of missing or corrupted ID Store, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>24901 ERROR ID-Stores-Configuration Loading ID Store Sequence failed because of missing or corrupted ID Store, <log details>

内部 MDM

- 消息代码: 89050

严重性: 信息 (INFO)

消息文本: 已提交管理操作 (Administrative action submitted)

消息说明: 已提交管理操作 (指定类型)

本地目标消息格式: <timestamp> <seq_num> 89050 INFO MDM: Administrative action submitted, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89050 INFO MDM: Administrative action submitted, <log details>

- 消息代码: 89051

严重性: 信息 (INFO)

消息文本: 管理操作已传送到移动设备 (Administrative action delivered to mobile device)

消息说明: 表示移动设备已确认管理操作 (指定类型)

本地目标消息格式: <timestamp> <seq_num> 89051 INFO MDM: Administrative action delivered to mobile device, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89051 INFO MDM: Administrative action delivered to mobile device, <log details>

- 消息代码: 89052

严重性: 错误 (ERROR)

消息文本: 管理操作失败 (Administrative action failed)

消息说明: 表示移动设备管理操作失败 (指定类型)

本地目标消息格式: <timestamp> <seq_num> 89052 ERROR MDM: Administrative action failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89052 ERROR MDM: Administrative action failed, <log details>

- 消息代码: 89100

严重性: 信息 (INFO)

消息文本: 已发起移动设备注册 (Mobile device enrollment initiated)

消息说明: 表示已开始移动设备注册

本地目标消息格式: <timestamp> <seq_num> 89100 INFO MDM: Mobile device enrollment initiated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89100 INFO MDM: Mobile device enrollment initiated, <log details>

- 消息代码: 89101

严重性: 错误 (ERROR)

消息文本: 移动设备注册失败 (Mobile device enrollment failed)

消息说明: 由于某种原因, 移动设备注册已终止

本地目标消息格式: <timestamp> <seq_num> 89101 ERROR MDM: Mobile device enrollment failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89101 ERROR MDM: Mobile device enrollment failed, <log details>

- 消息代码: 89102

严重性: 信息 (INFO)

消息文本: 已成功注册移动设备 (Mobile device enrolled successfully)

消息说明: 已成功注册移动设备

本地目标消息格式: <timestamp> <seq_num> 89102 INFO MDM: Mobile device enrolled successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89102 INFO MDM: Mobile device enrolled successfully, <log details>

- 消息代码: 89103

严重性: 信息 (INFO)

消息文本: 已撤销移动设备注册 (Mobile device deregistered)

消息说明: 已完成移动设备的撤销注册

本地目标消息格式: <timestamp> <seq_num> 89103 INFO MDM: Mobile device deregistered, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 89103 INFO MDM: Mobile device deregistered, <log details>

- 消息代码: 89104

严重性: 信息 (INFO)

消息文本: 已初始化移动设备服务 (Mobile Device Service initialized)

消息说明: 已完成移动设备服务初始化

本地目标消息格式: <timestamp> <seq_num> 89104 INFO MDM: Mobile Device Service initialized, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 89104 INFO MDM: Mobile Device Service initialized, <log details>

- 消息代码: 89105

严重性: 错误 (ERROR)

消息文本: 移动设备服务初始化失败 (Mobile Device Service initialization failed)

消息说明: 移动设备服务无法启动

本地目标消息格式: <timestamp> <seq_num> 89105 ERROR MDM: Mobile Device Service initialization failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 89105 ERROR MDM: Mobile Device Service initialization failed, <log details>

- 消息代码: 89106

严重性: 信息 (INFO)

消息文本: 移动设备服务已停止 (Mobile Device Service stopped)

消息说明: 移动设备服务已终止

本地目标消息格式: <timestamp> <seq_num> 89106 INFO MDM: Mobile Device Service stopped, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 89106 INFO MDM: Mobile Device Service stopped, <log details>

- 消息代码: 89107

严重性: 错误 (ERROR)

消息文本: 无法向移动设备发送通知 (Unable to send notifications to mobile device)

消息说明：表示无法通过推送通知系统通知移动设备

本地目标消息格式：<timestamp> <seq_num> 89107 ERROR MDM: Unable to send notifications to mobile device, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89107 ERROR MDM: Unable to send notifications to mobile device, <log details>

- 消息代码：89108

严重性：警告 (WARN)

消息文本：APNS 证书即将到期 (APNS Certificate is about to expire)

消息说明：表示用于通知服务的 APNS 证书将很快到期

本地目标消息格式：<timestamp> <seq_num> 89108 WARN MDM: APNS Certificate is about to expire, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89108 WARN MDM: APNS Certificate is about to expire, <log details>

- 消息代码：89109

严重性：警告 (WARN)

消息文本：终端证书即将到期。(Endpoint certificate is going to expire soon.)

消息说明：表示用于 MDM 操作的终端证书即将到期（不足已配置续约期限的 1/2），这意味着之前的自动续约已经失败。

本地目标消息格式：<timestamp> <seq_num> 89109 WARN MDM: Endpoint certificate is going to expire soon., <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89109 WARN MDM: Endpoint certificate is going to expire soon., <log details>

- 消息代码：89110

严重性：错误 (ERROR)

消息文本：未授权移动设备签入请求。(Mobile Device check-in request is not authorized.)

消息说明：表示由于未知/撤销/到期的客户端证书，未授权移动设备签入请求。

本地目标消息格式：<timestamp> <seq_num> 89110 ERROR MDM: Mobile Device check-in request is not authorized., <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89110 ERROR MDM: Mobile Device check-in request is not authorized., <log details>

- 消息代码：89111

严重性: 信息 (INFO)

消息文本: 已授权移动设备签入请求。(Mobile Device check-in request is authorized.)

消息说明: 表示未授权移动设备签入请求。

本地目标消息格式: <timestamp> <seq_num> 89111 INFO MDM: Mobile Device check-in request is authorized., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89111 INFO MDM: Mobile Device check-in request is authorized., <log details>

- 消息代码: 89112

严重性: 信息 (INFO)

消息文本: 已续约终端证书。(Endpoint certificate is renewed.)

消息说明: 表示已续约用于 MDM 操作的终端证书。

本地目标消息格式: <timestamp> <seq_num> 89112 INFO MDM: Endpoint certificate is renewed., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89112 INFO MDM: Endpoint certificate is renewed., <log details>

- 消息代码: 89113

严重性: 警告 (WARN)

消息文本: 检测到非活动移动设备 (Inactive Mobile Device is detected)

消息说明: 表示移动设备不再处于活动状态并可能未注册

本地目标消息格式: <timestamp> <seq_num> 89113 WARN MDM: Inactive Mobile Device is detected, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89113 WARN MDM: Inactive Mobile Device is detected, <log details>

- 消息代码: 89114

严重性: 信息 (INFO)

消息文本: 接收到地理定位坐标 (GeoLocation coordinates received)

消息说明: 表示移动设备已发回地理定位坐标

本地目标消息格式: <timestamp> <seq_num> 89114 INFO MDM: GeoLocation coordinates received, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89114 INFO MDM: GeoLocation coordinates received, <log details>

- 消息代码: 89115
严重性: 信息 (INFO)
消息文本: 已安装配置文件 (Profile Installed)
消息说明: 表示移动设备已安装配置文件。配置文件信息在事件详细信息属性中提供。
本地目标消息格式: <timestamp> <seq_num> 89115 INFO MDM: Profile Installed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89115 INFO MDM: Profile Installed, <log details>
- 消息代码: 89116
严重性: 信息 (INFO)
消息文本: 已删除配置文件 (Profile Removed)
消息说明: 表示移动设备已删除配置文件。配置文件信息在事件详细信息属性中提供
本地目标消息格式: <timestamp> <seq_num> 89116 INFO MDM: Profile Removed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89116 INFO MDM: Profile Removed, <log details>
- 消息代码: 89117
严重性: 信息 (INFO)
消息文本: 已安装应用 (Application Installed)
消息说明: 表示移动设备已安装应用。应用信息在事件详细信息属性中提供
本地目标消息格式: <timestamp> <seq_num> 89117 INFO MDM: Application Installed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89117 INFO MDM: Application Installed, <log details>
- 消息代码: 89118
严重性: 信息 (INFO)
消息文本: 已删除应用 (Application Removed)
消息说明: 表示移动设备已删除应用。应用信息在事件详细信息属性中提供
本地目标消息格式: <timestamp> <seq_num> 89118 INFO MDM: Application Removed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89118 INFO MDM: Application Removed, <log details>
- 消息代码: 89119

严重性: 警告 (WARN)

消息文本: 设备重新评估失败。(Device reassessment has failed.)

消息说明: 表示管理员或用户发起的定期设备重新评估失败。失败原因在事件详细信息中提供。

本地目标消息格式: <timestamp> <seq_num> 89119 WARN MDM: Device reassessment has failed., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89119 WARN MDM: Device reassessment has failed., <log details>

• 消息代码: 89132

严重性: 警告 (WARN)

消息文本: 终端证书即将到期。(Endpoint certificate is going to expire soon.)

消息说明: 表示用于 MDM 操作的终端证书即将到期 (不足已配置续约期限的 1/4), 这意味着其之前根据已配置续约周期进行的自动续约已经失败。

本地目标消息格式: <timestamp> <seq_num> 89132 WARN MDM: Endpoint certificate is going to expire soon., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89132 WARN MDM: Endpoint certificate is going to expire soon., <log details>

• 消息代码: 89133

严重性: 错误 (ERROR)

消息文本: 终端证书已过期。(Endpoint certificate has expired.)

消息说明: 表示用于 MDM 操作的终端证书已过期。必须重新注册移动设备。

本地目标消息格式: <timestamp> <seq_num> 89133 ERROR MDM: Endpoint certificate has expired., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89133 ERROR MDM: Endpoint certificate has expired., <log details>

• 消息代码: 89142

严重性: 错误 (ERROR)

消息文本: 调配操作失败。(Provisioning operation failed.)

消息说明: 表示调配操作 (配置文件/应用) 已经失败。配置文件/应用信息和失败原因在事件详细信息中提供。

本地目标消息格式: <timestamp> <seq_num> 89142 ERROR MDM: Provisioning operation failed., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89142 ERROR MDM: Provisioning operation failed., <log details>

- 消息代码: 89143

严重性: 信息 (INFO)

消息文本: 移动设备记录已更新有新的设备信息 (Mobile device record is updated with new device information)

消息说明: 表示已检索移动设备信息 (操作系统版本、AnyConnect 版本等) 并更新数据库记录。更新信息在事件详细信息中提供。

本地目标消息格式: <timestamp> <seq_num> 89143 INFO MDM: Mobile device record is updated with new device information, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89143 INFO MDM: Mobile device record is updated with new device information, <log details>

- 消息代码: 89144

严重性: 警告 (WARN)

消息文本: 终端证书续约失败。(Endpoint certificate renewal has failed.)

消息说明: 表示用于 MDM 操作的终端证书续约失败。将在下一次定期重新评估期间再次尝试续约证书。

本地目标消息格式: <timestamp> <seq_num> 89144 WARN MDM: Endpoint certificate renewal has failed., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89144 WARN MDM: Endpoint certificate renewal has failed., <log details>

- 消息代码: 89149

严重性: 信息 (INFO)

消息文本: 移动设备符合策略 (Mobile device is compliant)

消息说明: 表示设备符合移动设备管理策略

本地目标消息格式: <timestamp> <seq_num> 89149 INFO MDM: Mobile device is compliant, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89149 INFO MDM: Mobile device is compliant, <log details>

- 消息代码: 89150

严重性: 信息 (INFO)

消息文本: 移动设备不符合策略 (Mobile device is not compliant)

消息说明: 表示设备不符合移动设备管理策略

本地目标消息格式: <timestamp> <seq_num> 89150 INFO MDM: Mobile device is not compliant, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89150 INFO MDM: Mobile device is not compliant, <log details>

- 消息代码: 89151

严重性: 警告 (WARN)

消息文本: 可撤销由外部 CA 颁发的证书, 因为移动设备不再使用该证书。(Certificate issued by external CA can be revoked because the mobile device no longer uses it.)

消息说明: 表示移动设备不再需要外部 CA 生成的客户端证书。您可以手动撤销证书, 以确保更高的安全性。

本地目标消息格式: <timestamp> <seq_num> 89151 WARN MDM: Certificate issued by external CA can be revoked because the mobile device no longer uses it., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89151 WARN MDM: Certificate issued by external CA can be revoked because the mobile device no longer uses it., <log details>

- 消息代码: 89152

严重性: 信息 (INFO)

消息文本: 已发起移动设备撤销注册 (Mobile device unenrollment initiated)

消息说明: 表示已开始移动设备撤销注册

本地目标消息格式: <timestamp> <seq_num> 89152 INFO MDM: Mobile device unenrollment initiated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89152 INFO MDM: Mobile device unenrollment initiated, <log details>

- 消息代码: 89153

严重性: 错误 (ERROR)

消息文本: 缺少用于通知系统的证书。(Certificates missing for Notification Systems.)

消息说明: 表示对 ISE 进行身份验证所需的一个或多个身份证书未配置到移动设备通知系统。

本地目标消息格式: <timestamp> <seq_num> 89153 ERROR MDM: Certificates missing for Notification Systems., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89153 ERROR MDM: Certificates missing for Notification Systems., <log details>

- 消息代码: 89154
严重性: 错误 (ERROR)
消息文本: Apple 批量购买计划 (VPP) 服务令牌无效。(Apple Volume Purchase Plan (VPP) service token is invalid.)
消息说明: 表示 Apple 批量购买计划 (VPP) 的服务令牌无效。
本地目标消息格式: <timestamp> <seq_num> 89154 ERROR MDM: Apple Volume Purchase Plan (VPP) service token is invalid., <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89154 ERROR MDM: Apple Volume Purchase Plan (VPP) service token is invalid., <log details>
- 消息代码: 89155
严重性: 错误 (ERROR)
消息文本: 无法访问 Apple 批量购买计划 (VPP) 服务。(Failed to access Apple Volume Purchase Plan (VPP) services.)
消息说明: 访问 Apple 批量购买计划 (VPP) 服务时出错。详细信息在事件详细信息中提供。
本地目标消息格式: <timestamp> <seq_num> 89155 ERROR MDM: Failed to access Apple Volume Purchase Plan (VPP) services., <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89155 ERROR MDM: Failed to access Apple Volume Purchase Plan (VPP) services., <log details>
- 消息代码: 89156
严重性: 错误 (ERROR)
消息文本: 无法访问 CMCS 服务器 (CMCS server unreachable)
消息说明: ISE 无法与思科 MDM 云服务通信
本地目标消息格式: <timestamp> <seq_num> 89156 ERROR MDM: CMCS server unreachable, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89156 ERROR MDM: CMCS server unreachable, <log details>
- 消息代码: 89157
严重性: 错误 (ERROR)
消息文本: CMCS 身份验证失败 (CMCS authentication failure)
消息说明: ISE 无法使用思科 MDM 云服务进行身份验证
本地目标消息格式: <timestamp> <seq_num> 89157 ERROR MDM: CMCS authentication failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89157 ERROR MDM: CMCS authentication failure, <log details>

- 消息代码: 89158

严重性: 错误 (ERROR)

消息文本: 无法访问 APNS 服务器 (APNS server unreachable)

消息说明: ISE 无法与 Apple 推送通知系统 (APNS) 通信

本地目标消息格式: <timestamp> <seq_num> 89158 ERROR MDM: APNS server unreachable, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89158 ERROR MDM: APNS server unreachable, <log details>

- 消息代码: 89159

严重性: 错误 (ERROR)

消息文本: APNS 身份验证失败 (APNS authentication failure)

消息说明: ISE 无法使用 Apple 推送通知系统 (APNS) 进行身份验证

本地目标消息格式: <timestamp> <seq_num> 89159 ERROR MDM: APNS authentication failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89159 ERROR MDM: APNS authentication failure, <log details>

- 消息代码: 89160

严重性: 信息 (INFO)

消息文本: MDM 用户身份验证已完成 (MDM User Authentication completed)

消息说明: 移动设备注册的用户身份验证部分已完成

本地目标消息格式: <timestamp> <seq_num> 89160 INFO MDM: MDM User Authentication completed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89160 INFO MDM: MDM User Authentication completed, <log details>

内部操作诊断

- 消息代码: 30000

严重性: 严重 (FATAL)

消息文本: 未知的严重管理错误 (Unknown fatal management error)

消息说明: MGMT 严重未知错误。要进行恢复, 请尝试重新运行 ISE

本地目标消息格式: <timestamp> <seq_num> 30000 FATAL MGMT: Unknown fatal management error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 30000 FATAL MGMT: Unknown fatal management error, <log details>

- 消息代码: 31000

严重性: 错误 (ERROR)

消息文本: 无法初始化通知调度程序 (Could not initialize notification dispatcher)

消息说明: 无法初始化通知调度程序

本地目标消息格式: <timestamp> <seq_num> 31000 ERROR Notification-Dispatcher: Could not initialize notification dispatcher, <log details>

本地目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 31000 ERROR Notification-Dispatcher: Could not initialize notification dispatcher, <log details>

- 消息代码: 31001

严重性: 错误 (ERROR)

消息文本: 无法发送配置通知消息 (Could not send configuration notification message)

消息说明: 无法发送配置通知消息

本地目标消息格式: <timestamp> <seq_num> 31001 ERROR Notification-Dispatcher: Could not send configuration notification message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 31001 ERROR Notification-Dispatcher: Could not send configuration notification message, <log details>

- 消息代码: 31100

严重性: 调试 (DEBUG)

消息文本: 已开始应用配置更改 (Applying configuration changes initiated)

消息说明: 已开始在运行时应用配置更改

本地目标消息格式: <timestamp> <seq_num> 31100 DEBUG Configuration-Notifications: Applying configuration changes initiated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 31100 DEBUG Configuration-Notifications: Applying configuration changes initiated, <log details>

- 消息代码: 31101

严重性: 调试 (DEBUG)

消息文本: 应用配置更改成功 (Applying configuration changes succeeded)

消息说明: 在运行时应用配置更改成功。已激活新的配置版本

本地目标消息格式: <timestamp> <seq_num> 31101 DEBUG Configuration-Notifications: Applying configuration changes succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 31101 DEBUG Configuration-Notifications: Applying configuration changes succeeded, <log details>

- 消息代码: 31102

严重性: 严重 (FATAL)

消息文本: 应用配置更改失败 (Applying configuration changes failed)

消息说明: 应用配置更改失败。运行时流程将重启。

本地目标消息格式: <timestamp> <seq_num> 31102 FATAL Configuration-Notifications: Applying configuration changes failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 31102 FATAL Configuration-Notifications: Applying configuration changes failed, <log details>

- 消息代码: 31103

严重性: 调试 (DEBUG)

消息文本: 启动配置加载成功 (Start up configuration load succeeded)

消息说明: 启动配置加载成功

本地目标消息格式: <timestamp> <seq_num> 31103 DEBUG Configuration-Notifications: Start up configuration load succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 31103 DEBUG Configuration-Notifications: Start up configuration load succeeded, <log details>

- 消息代码: 31104

严重性: 严重 (FATAL)

消息文本: 启动配置加载失败 (Start up configuration load failed)

消息说明: 启动配置加载失败。运行时流程将停止

本地目标消息格式: <timestamp> <seq_num> 31104 FATAL Configuration-Notifications: Start up configuration load failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 31104 FATAL Configuration-Notifications: Start up configuration load failed, <log details>

- 消息代码: 31105
 - 严重性: 警告 (WARN)
 - 消息文本: 已忽略事务 (Transaction is ignored)
 - 消息说明: 已忽略具有错误 ID 的事务。运行时间正等待具有其他 ID 的事务。
 - 本地目标消息格式: <timestamp> <seq_num> 31105 WARN Configuration-Notifications: Transaction is ignored, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 31105 WARN Configuration-Notifications: Transaction is ignored, <log details>

- 消息代码: 31106
 - 严重性: 严重 (FATAL)
 - 消息文本: 配置管理无法转换配置更改。(Configuration management could not translate configuration change.) 运行时配置更改不会生效。
 - 消息说明: 配置管理无法转换配置更改。运行时配置更改不会生效。
 - 本地目标消息格式: <timestamp> <seq_num> 31106 FATAL Configuration-Notifications: Configuration management could not translate configuration change. Runtime configuration changes will not take effect, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 31106 FATAL Configuration-Notifications: Configuration management could not translate configuration change. Runtime configuration changes will not take effect, <log details>

- 消息代码: 31107
 - 严重性: 信息 (INFO)
 - 消息文本: 冷配置重启完成 (Cold configuration restart complete)
 - 消息说明: 冷配置重启完成
 - 本地目标消息格式: <timestamp> <seq_num> 31107 INFO Configuration-Notifications: Cold configuration restart complete, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 31107 INFO Configuration-Notifications: Cold configuration restart complete, <log details>

- 消息代码: 31108
 - 严重性: 严重 (FATAL)
 - 消息文本: 冷配置重启失败 (Cold configuration restart failed)
 - 消息说明: 冷配置重启失败。运行时流程将重启。

本地目标消息格式: <timestamp> <seq_num> 31108 FATAL Configuration-Notifications: Cold configuration restart failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 31108 FATAL Configuration-Notifications: Cold configuration restart failed, <log details>

- 消息代码: 31109

严重性: 信息 (INFO)

消息文本: 热配置重启完成 (Warm configuration restart complete)

消息说明: 热配置重启完成

本地目标消息格式: <timestamp> <seq_num> 31109 INFO Configuration-Notifications: Warm configuration restart complete, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 31109 INFO Configuration-Notifications: Warm configuration restart complete, <log details>

- 消息代码: 31110

严重性: 警告 (WARN)

消息文本: 热配置重启失败 (Warm configuration restart failed)

消息说明: 热配置重启失败。回退到冷配置重启

本地目标消息格式: <timestamp> <seq_num> 31110 WARN Configuration-Notifications: Warm configuration restart failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 31110 WARN Configuration-Notifications: Warm configuration restart failed, <log details>

- 消息代码: 31111

严重性: 警告 (WARN)

消息文本: 运行时通知不同步 (The Runtime notifications are out of sync)

消息说明: 运行时通知不同步。向管理发出同步消息。

本地目标消息格式: <timestamp> <seq_num> 31111 WARN Configuration-Notifications: The Runtime notifications are out of sync, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 31111 WARN Configuration-Notifications: The Runtime notifications are out of sync, <log details>

- 消息代码: 31200

严重性: 错误 (ERROR)

消息文本: 遇到无效/空的日志记录 (Encountered invalid/Null Log Record encountered)

消息说明：无效或空的日志记录

本地目标消息格式：<timestamp> <seq_num> 31200 ERROR Audit-Flow: Encountered invalid/Null Log Record encountered, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 31200 ERROR Audit-Flow: Encountered invalid/Null Log Record encountered, <log details>

- 消息代码：31201

严重性：错误 (ERROR)

消息文本：遇到无效或空的系统消息 (Encountered invalid or null system message)

消息说明：无法通过操作码创建相应的系统消息

本地目标消息格式：<timestamp> <seq_num> 31201 ERROR Audit-Flow: Encountered invalid or null system message, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 31201 ERROR Audit-Flow: Encountered invalid or null system message, <log details>

- 消息代码：31202

严重性：错误 (ERROR)

消息文本：遇到无效或空的用户情境 (Encountered invalid or null user context)

消息说明：遇到无效或空的用户情境

本地目标消息格式：<timestamp> <seq_num> 31202 ERROR Audit-Flow: Encountered invalid or null user context, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 31202 ERROR Audit-Flow: Encountered invalid or null user context, <log details>

- 消息代码：31203

严重性：错误 (ERROR)

消息文本：记录成功登录的审核记录时出错 (Encountered error while recording the audit record for successful login)

消息说明：记录成功登录的审核记录时出错

本地目标消息格式：<timestamp> <seq_num> 31203 ERROR Audit-Flow: Encountered error while recording the audit record for successful login, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 31203 ERROR Audit-Flow: Encountered error while recording the audit record for successful login, <log details>

- 消息代码：31204

严重性: 错误 (ERROR)

消息文本: 记录失败登录的审核记录时出错 (Encountered error while recording the audit record for failed login)

消息说明: 记录失败登录的审核记录时出错

本地目标消息格式: <timestamp> <seq_num> 31204 ERROR Audit-Flow: Encountered error while recording the audit record for failed login, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 31204 ERROR Audit-Flow: Encountered error while recording the audit record for failed login, <log details>

- 消息代码: 31205

严重性: 错误 (ERROR)

消息文本: 记录注销的审核记录时出错 (Encountered error while recording the audit record for logout)

消息说明: 记录注销的审核记录时出错

本地目标消息格式: <timestamp> <seq_num> 31205 ERROR Audit-Flow: Encountered error while recording the audit record for logout, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 31205 ERROR Audit-Flow: Encountered error while recording the audit record for logout, <log details>

- 消息代码: 31206

严重性: 错误 (ERROR)

消息文本: 记录故障切换模式的审核记录时出错 (Encountered error while recording the audit record for failover mode)

消息说明: 记录故障切换模式的审核记录时出错

本地目标消息格式: <timestamp> <seq_num> 31206 ERROR Audit-Flow: Encountered error while recording the audit record for failover mode, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 31206 ERROR Audit-Flow: Encountered error while recording the audit record for failover mode, <log details>

- 消息代码: 31207

严重性: 错误 (ERROR)

消息文本: 记录会话超时的审核记录时出错 (Encountered error while recording the audit record for session timeout)

消息说明: 记录会话超时的审核记录时出错

本地目标消息格式: <timestamp> <seq_num> 31207 ERROR Audit-Flow: Encountered error while recording the audit record for session timeout, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 31207 ERROR Audit-Flow: Encountered
error while recording the audit record for session timeout, <log details>

- 消息代码: 31500

严重性: 信息 (INFO)

消息文本: 已启动管理 (Started Management)

消息说明: 已启动管理

本地目标消息格式: <timestamp> <seq_num> 31500 INFO Startup-Shutdown: Started Management,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 31500 INFO Startup-Shutdown: Started
Management, <log details>

- 消息代码: 31501

严重性: 信息 (INFO)

消息文本: 已停止管理 (Stopped Management)

消息说明: 已停止管理

本地目标消息格式: <timestamp> <seq_num> 31501 INFO Startup-Shutdown: Stopped Management,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 31501 INFO Startup-Shutdown: Stopped
Management, <log details>

- 消息代码: 31502

严重性: 信息 (INFO)

消息文本: 已启动运行时 (Started Runtime)

消息说明: 已启动运行时

本地目标消息格式: <timestamp> <seq_num> 31502 INFO Startup-Shutdown: Started Runtime, <log
details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 31502 INFO Startup-Shutdown: Started
Runtime, <log details>

- 消息代码: 31503

严重性: 信息 (INFO)

消息文本: 已停止运行时 (Stopped Runtime)

消息说明: 已停止运行时

本地目标消息格式: <timestamp> <seq_num> 31503 INFO Startup-Shutdown: Stopped Runtime, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 31503 INFO Startup-Shutdown: Stopped Runtime, <log details>

- 消息代码: 31504

严重性: 严重 (FATAL)

消息文本: 加密模块无法初始化 (The cryptographic module could not initialize)

消息说明: 加密模块无法初始化

本地目标消息格式: <timestamp> <seq_num> 31504 FATAL Startup-Shutdown: The cryptographic module could not initialize, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 31504 FATAL Startup-Shutdown: The cryptographic module could not initialize, <log details>

- 消息代码: 32000

严重性: 信息 (INFO)

消息文本: 已启动日志记录组件 (Started logging component)

消息说明: 已启动日志记录组件

本地目标消息格式: <timestamp> <seq_num> 32000 INFO Logging: Started logging component, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 32000 INFO Logging: Started logging component, <log details>

- 消息代码: 32001

严重性: 信息 (INFO)

消息文本: 关闭日志记录组件 (Shut down logging component)

消息说明: 关闭日志记录组件

本地目标消息格式: <timestamp> <seq_num> 32001 INFO Logging: Shut down logging component, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 32001 INFO Logging: Shut down logging component, <log details>

- 消息代码: 32002

严重性: 调试 (DEBUG)

消息文本: 使用启动默认配置 (Using startup default configuration)

消息说明：使用启动默认配置

本地目标消息格式：<timestamp> <seq_num> 32002 DEBUG Logging: Using startup default configuration, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 32002 DEBUG Logging: Using startup default configuration, <log details>

- 消息代码：32005

严重性：警告 (WARN)

消息文本：无法将消息记录到记录器 (Could not log message to logger)

消息说明：无法将消息记录到记录器

本地目标消息格式：<timestamp> <seq_num> 32005 WARN Logging: Could not log message to logger, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 32005 WARN Logging: Could not log message to logger, <log details>

- 消息代码：32006

严重性：警告 (WARN)

消息文本：无法登录到关键记录器 (Could not log to critical logger)

消息说明：无法登录到关键记录器

本地目标消息格式：<timestamp> <seq_num> 32006 WARN Logging: Could not log to critical logger, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 32006 WARN Logging: Could not log to critical logger, <log details>

- 消息代码：32008

严重性：调试 (DEBUG)

消息文本：日志记录组件现已准备好接收配置更改 (Logging component now ready to receive configuration changes)

消息说明：已成功订阅日志记录，可以接收日志记录配置更改

本地目标消息格式：<timestamp> <seq_num> 32008 DEBUG Logging: Logging component now ready to receive configuration changes, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 32008 DEBUG Logging: Logging component now ready to receive configuration changes, <log details>

- 消息代码：32012

严重性: 错误 (ERROR)

消息文本: 无法写入本地存储文件 (Could not write to local storage file)

消息说明: 无法写入本地存储 CSV 文件

本地目标消息格式: <timestamp> <seq_num> 32012 ERROR Logging: Could not write to local storage file, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 32012 ERROR Logging: Could not write to local storage file, <log details>

- 消息代码: 32013

严重性: 错误 (ERROR)

消息文本: 无法创建本地存储文件 (Could not create a local storage file)

消息说明: 无法创建本地存储 CSV 文件

本地目标消息格式: <timestamp> <seq_num> 32013 ERROR Logging: Could not create a local storage file, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 32013 ERROR Logging: Could not create a local storage file, <log details>

- 消息代码: 32014

严重性: 错误 (ERROR)

消息文本: 无法删除本地存储 CSV 文件 (Could not delete a local storage CSV file)

消息说明: 无法删除本地存储 CSV 文件

本地目标消息格式: <timestamp> <seq_num> 32014 ERROR Logging: Could not delete a local storage CSV file, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 32014 ERROR Logging: Could not delete a local storage CSV file, <log details>

- 消息代码: 32015

严重性: 调试 (DEBUG)

消息文本: 已删除本地存储文件 (Local storage file deleted)

消息说明: 已删除本地存储 CSV 文件

本地目标消息格式: <timestamp> <seq_num> 32015 DEBUG Logging: Local storage file deleted, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 32015 DEBUG Logging: Local storage file deleted, <log details>

- 消息代码: 32016
 - 严重性: 严重 (FATAL)
 - 消息文本: 系统已达到低磁盘空间限制 (System reached low disk space limit)
 - 消息说明: 系统已达到低磁盘空间限制。将本地存储清除设置更改为可用空间
 - 本地目标消息格式: <timestamp> <seq_num> 32016 FATAL Logging: System reached low disk space limit, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 32016 FATAL Logging: System reached low disk space limit, <log details>

- 消息代码: 32017
 - 严重性: 严重 (FATAL)
 - 消息文本: 无法打开 UDP 套接字 (Could not to open a UDP socket)
 - 消息说明: 无法打开 UDP 套接字
 - 本地目标消息格式: <timestamp> <seq_num> 32017 FATAL Logging: Could not to open a UDP socket, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 32017 FATAL Logging: Could not to open a UDP socket, <log details>

- 消息代码: 32018
 - 严重性: 警告 (WARN)
 - 消息文本: 无法在套接字上发送数据 (Could not send data on socket)
 - 消息说明: 无法在套接字上发送数据
 - 本地目标消息格式: <timestamp> <seq_num> 32018 WARN Logging: Could not send data on socket, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 32018 WARN Logging: Could not send data on socket, <log details>

- 消息代码: 32025
 - 严重性: 调试 (DEBUG)
 - 消息文本: 已查看本地存储文件 (Rolled over local storage file)
 - 消息说明: 已查看本地存储 CSV 文件
 - 本地目标消息格式: <timestamp> <seq_num> 32025 DEBUG Logging: Rolled over local storage file, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 32025 DEBUG Logging: Rolled over local storage file, <log details>

- 消息代码: 32026

严重性: 错误 (ERROR)

消息文本: 无法查看本地存储文件 (Could not roll over local storage file)

消息说明: 无法查看本地存储 CSV 文件

本地目标消息格式: <timestamp> <seq_num> 32026 ERROR Logging: Could not roll over local storage file, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 32026 ERROR Logging: Could not roll over local storage file, <log details>

- 消息代码: 33101

严重性: 信息 (INFO)

消息文本: 已创建新的 ISE 配置会话 (Created new ISE configuration session)

消息说明: 已调用 acs-config CLI

本地目标消息格式: <timestamp> <seq_num> 33101 INFO CLI: Created new ISE configuration session, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 33101 INFO CLI: Created new ISE configuration session, <log details>

- 消息代码: 33102

严重性: 信息 (INFO)

消息文本: 用户成功登录到 ISE 配置模式 (Successful user login to ISE configuration mode)

消息说明: ISE 管理员已登录到 ISE 配置模式

本地目标消息格式: <timestamp> <seq_num> 33102 INFO CLI: Successful user login to ISE configuration mode, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 33102 INFO CLI: Successful user login to ISE configuration mode, <log details>

- 消息代码: 33103

严重性: 信息 (INFO)

消息文本: 用户登录到 ISE 配置模式失败 (User login to ISE configuration mode failed)

消息说明: 登录到 ISE 配置模式失败

本地目标消息格式: <timestamp> <seq_num> 33103 INFO CLI: User login to ISE configuration mode failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 33103 INFO CLI: User login to ISE configuration mode failed, <log details>

- 消息代码: 33104

严重性: 信息 (INFO)

消息文本: 已关闭 ISE 配置会话 (Closed ISE configuration session)

消息说明: 已关闭 ISE 配置会话。可能是因为请求超时

本地目标消息格式: <timestamp> <seq_num> 33104 INFO CLI: Closed ISE configuration session, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 33104 INFO CLI: Closed ISE configuration session, <log details>

- 消息代码: 33105

严重性: 信息 (INFO)

消息文本: 设置调试日志级别 (Set debug log level)

消息说明: 通过 CLI 设置特定组件的调试日志级别。(请参阅属性)。

本地目标消息格式: <timestamp> <seq_num> 33105 INFO CLI: Set debug log level, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 33105 INFO CLI: Set debug log level, <log details>

- 消息代码: 33106

严重性: 信息 (INFO)

消息文本: 设置默认调试日志级别 (Set default debug log level)

消息说明: 将一个组件或一群组件的调试日志级别重置为默认级别 (“警告” (warn))

本地目标消息格式: <timestamp> <seq_num> 33106 INFO CLI: Set default debug log level, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 33106 INFO CLI: Set default debug log level, <log details>

- 消息代码: 33107

严重性: 调试 (DEBUG)

消息文本: 显示调试日志状态 (Show debugging log status)

消息说明：已调用显示调试日志 CLI（请参阅属性组件）。

本地目标消息格式：<timestamp> <seq_num> 33107 DEBUG CLI: Show debugging log status, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 33107 DEBUG CLI: Show debugging log status, <log details>

- 消息代码：33108

严重性：信息 (INFO)

消息文本：将管理员密码重置为其默认值 (Reset admin password to its default value)

消息说明：CLI 将 ACSAdmin 用户重置为其默认值

本地目标消息格式：<timestamp> <seq_num> 33108 INFO CLI: Reset admin password to its default value, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 33108 INFO CLI: Reset admin password to its default value, <log details>

- 消息代码：33201

严重性：错误 (ERROR)

消息文本：AD 操作失败 (AD Operation failure)

消息说明：ISE 在以下情况下出现失败：在初始化事件以加入 Active Directory 域时。在从 Active Directory 域断开连接时；在从 Active Directory 域获取状态时。

本地目标消息格式：<timestamp> <seq_num> 33201 ERROR Configuration-Notifications: AD Operation failure, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 33201 ERROR Configuration-Notifications: AD Operation failure, <log details>

- 消息代码：33202

严重性：信息 (INFO)

消息文本：AD 操作成功 (AD Operation Success)

消息说明：ISE 出于以下原因初始化事件：为了加入 AD 域。为了从 AD 域断开连接；为了从 AD 域获取状态。

本地目标消息格式：<timestamp> <seq_num> 33202 INFO Configuration-Notifications: AD Operation Success, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 33202 INFO Configuration-Notifications: AD Operation Success, <log details>

- 消息代码: 33203
严重性: 信息 (INFO)
消息文本: 重置点击计数 (Hit Count reset)
消息说明: 管理员请求为配置的所有策略重置点击计数计数器
本地目标消息格式: <timestamp> <seq_num> 33203 INFO Notification-Dispatcher: Hit Count reset, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 33203 INFO Notification-Dispatcher: Hit Count reset, <log details>
- 消息代码: 33204
严重性: 信息 (INFO)
消息文本: 重新收集点击计数 (Hit Count recollect)
消息说明: 发起定期请求, 以便为配置的所有策略收集和累积点击计数计数器值。
本地目标消息格式: <timestamp> <seq_num> 33204 INFO Notification-Dispatcher: Hit Count recollect, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 33204 INFO Notification-Dispatcher: Hit Count recollect, <log details>
- 消息代码: 33205
严重性: 错误 (ERROR)
消息文本: 一般 PI 错误 (General PI error)
消息说明: ISE Web 服务调配组件发现意外错误。
本地目标消息格式: <timestamp> <seq_num> 33205 ERROR PI: General PI error, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 33205 ERROR PI: General PI error, <log details>
- 消息代码: 33206
严重性: 信息 (INFO)
消息文本: AD 操作信息 (AD Operation information)
消息说明: 以下情况下显示的 ISE 信息: 在初始化事件以加入 Active Directory 域时。在从 Active Directory 域断开连接时; 在从 Active Directory 域获取状态时。
本地目标消息格式: <timestamp> <seq_num> 33206 INFO Configuration-Notifications: AD Operation information, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 33206 INFO Configuration-Notifications:
AD Operation information, <log details>

- 消息代码: 33207

严重性: 警告 (WARN)

消息文本: AD 操作警告 (AD Operation warning)

消息说明: ISE 在从 Active Directory 域中获取状态时遇到警告。

本地目标消息格式: <timestamp> <seq_num> 33207 WARN Configuration-Notifications: AD Operation
warning, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 33207 WARN Configuration-Notifications:
AD Operation warning, <log details>

- 消息代码: 33208

严重性: 调试 (DEBUG)

消息文本: AD 连接测试结果 (Result for testing connection against AD)

消息说明: 有关 Active Directory 服务器测试连接情况的 ISE 报告。

本地目标消息格式: <timestamp> <seq_num> 33208 DEBUG Configuration-Notifications: Result for
testing connection against AD, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 33208 DEBUG Configuration-Notifications:
Result for testing connection against AD, <log details>

- 消息代码: 33209

严重性: 调试 (DEBUG)

消息文本: LDAP 连接测试结果 (Result for testing connection against LDAP)

消息说明: 有关 LDAP 服务器测试连接情况的 ISE 报告。

本地目标消息格式: <timestamp> <seq_num> 33209 DEBUG Configuration-Notifications: Result for
testing connection against LDAP, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 33209 DEBUG Configuration-Notifications:
Result for testing connection against LDAP, <log details>

- 消息代码: 33210

严重性: 调试 (DEBUG)

消息文本: LDAP 流量信息 (LDAP traffic info)

消息说明: LDAP 服务器的 LDAP 流量信息。

本地目标消息格式: <timestamp> <seq_num> 33210 DEBUG Configuration-Notifications: LDAP traffic info, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 33210 DEBUG Configuration-Notifications: LDAP traffic info, <log details>

- 消息代码: 33211

严重性: 信息 (INFO)

消息文本: ISE 正在使用自签名证书进行管理界面身份验证 (ISE is using a self signed certificate for Management Interface authentication)

消息说明: ISE 正在使用自签名证书进行管理界面身份验证

本地目标消息格式: <timestamp> <seq_num> 33211 INFO System-Management: ISE is using a self signed certificate for Management Interface authentication, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 33211 INFO System-Management: ISE is using a self signed certificate for Management Interface authentication, <log details>

- 消息代码: 33212

严重性: 警告 (WARN)

消息文本: 由于系统故障, ISE 无法为管理界面加载关联的证书 (Due to system failure, ISE could not load the associated certificate for the Management Interface)

消息说明: 由于系统故障, ISE 无法为管理界面加载关联的证书。使用了默认的自签名证书。

本地目标消息格式: <timestamp> <seq_num> 33212 WARN System-Management: Due to system failure, ISE could not load the associated certificate for the Management Interface, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 33212 WARN System-Management: Due to system failure, ISE could not load the associated certificate for the Management Interface, <log details>

- 消息代码: 33300

严重性: 错误 (ERROR)

消息文本: 一般 GUI 错误 (General GUI error)

消息说明: ISE 图形用户界面发现意外错误。

本地目标消息格式: <timestamp> <seq_num> 33300 ERROR Graphical-user-interface: General GUI error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 33300 ERROR Graphical-user-interface: General GUI error, <log details>

- 消息代码: 32500

严重性: 错误 (ERROR)

消息文本: 一般数据库错误 (General database error)

消息说明: 一般数据库错误

本地目标消息格式: <timestamp> <seq_num> 32500 ERROR Local-DB: General database error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num> <timestamp> <seq_num> 32500 ERROR Local-DB: General database error, <log details>

- 消息代码: 32600

严重性: 信息 (INFO)

消息文本: 已连接消息总线 (Connected message bus)

消息说明: 已连接消息总线

本地目标消息格式: <timestamp> <seq_num> 32600 INFO Message-Bus: Connected message bus, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num> <timestamp> <seq_num> 32600 INFO Message-Bus: Connected message bus, <log details>

- 消息代码: 32601

严重性: 错误 (ERROR)

消息文本: 无法启动消息总线 (Could not start message bus)

消息说明: 无法启动消息总线

本地目标消息格式: <timestamp> <seq_num> 32601 ERROR Message-Bus: Could not start message bus, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num> <timestamp> <seq_num> 32601 ERROR Message-Bus: Could not start message bus, <log details>

- 消息代码: 32602

严重性: 信息 (INFO)

消息文本: 正在重新尝试连接消息总线 (Retrying message bus connection)

消息说明: 正在重新尝试连接消息总线

本地目标消息格式: <timestamp> <seq_num> 32602 INFO Message-Bus: Retrying message bus connection, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num> <timestamp> <seq_num> 32602 INFO Message-Bus: Retrying message bus connection, <log details>

- 消息代码: 32603

严重性: 错误 (ERROR)

消息文本: 已丢弃连接。正在重新连接 (Dropped connection. Reconnecting)

消息说明: 已丢弃连接。正在重新连接

本地目标消息格式: <timestamp> <seq_num> 32603 ERROR Message-Bus: Dropped connection. Reconnecting, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 32603 ERROR Message-Bus: Dropped connection. Reconnecting, <log details>

- 消息代码: 32604

严重性: 错误 (ERROR)

消息文本: 未知总线错误 (Unknown bus error)

消息说明: 未知总线错误

本地目标消息格式: <timestamp> <seq_num> 32604 ERROR Message-Bus: Unknown bus error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 32604 ERROR Message-Bus: Unknown bus error, <log details>

- 消息代码: 32605

严重性: 错误 (ERROR)

消息文本: 未知属性 (Unknown attribute)

消息说明: 未知属性

本地目标消息格式: <timestamp> <seq_num> 32605 ERROR Message-Bus: Unknown attribute, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 32605 ERROR Message-Bus: Unknown attribute, <log details>

- 消息代码: 32606

严重性: 错误 (ERROR)

消息文本: 已丢弃未知消息类型 (Dropped unknown message type)

消息说明: 已丢弃未知消息类型

本地目标消息格式: <timestamp> <seq_num> 32606 ERROR Message-Bus: Dropped unknown message type, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 32606 ERROR Message-Bus: Dropped unknown message type, <log details>

- 消息代码: 32607
严重性: 信息 (INFO)
消息文本: 缺少属性 (Missing attribute)
消息说明: 缺少属性
本地目标消息格式: <timestamp> <seq_num> 32607 INFO Message-Bus: Missing attribute, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 32607 INFO Message-Bus: Missing attribute, <log details>
- 消息代码: 32700
严重性: 警告 (WARN)
消息文本: 内部错误导致进入故障切换模式。配置更改可能不会生效 (Failover mode caused by an internal error. Configuration changes may not take effect)
消息说明: 内部错误导致进入故障切换模式。配置更改可能不会生效
本地目标消息格式: <timestamp> <seq_num> 32700 WARN Administrator-Login: Failover mode caused by an internal error. Configuration changes may not take effect, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 32700 WARN Administrator-Login: Failover mode caused by an internal error. Configuration changes may not take effect, <log details>
- 消息代码: 33400
严重性: 信息 (INFO)
消息文本: 已添加证书撤销列表 (Certificate Revocation List was added)
消息说明: 已下载证书撤销列表, 并将由 ISE 使用
本地目标消息格式: <timestamp> <seq_num> 33400 INFO CRL: Certificate Revocation List was added, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 33400 INFO CRL: Certificate Revocation List was added, <log details>
- 消息代码: 33450
严重性: 信息 (INFO)
消息文本: 已收到清除 OCSP 缓存的请求 (Received a request to clear OCSP cache)
消息说明: 已收到清除 OCSP 缓存的请求
本地目标消息格式: <timestamp> <seq_num> 33450 INFO OCSP: Received a request to clear OCSP cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 33450 INFO OCSP: Received a request to
clear OCSP cache, <log details>

- 消息代码: 33451

严重性: 信息 (INFO)

消息文本: 成功清除 OCSP 缓存 (Successfully clear OCSP cache)

消息说明: 成功清除 OCSP 缓存

本地目标消息格式: <timestamp> <seq_num> 33451 INFO OCSP: Successfully clear OCSP cache,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 33451 INFO OCSP: Successfully clear OCSP
cache, <log details>

- 消息代码: 33452

严重性: 错误 (ERROR)

消息文本: 无法清除 OCSP 缓存 (Failed to clear OCSP cache)

消息说明: 无法清除 OCSP 缓存

本地目标消息格式: <timestamp> <seq_num> 33452 ERROR OCSP: Failed to clear OCSP cache,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 33452 ERROR OCSP: Failed to clear OCSP
cache, <log details>

- 消息代码: 33500

严重性: 错误 (ERROR)

消息文本: 无法初始化 EAP-TLS (Could not initialize EAP-TLS)

消息说明: 无法初始化 EAP-TLS 模块, 系统将禁用此模块。

本地目标消息格式: <timestamp> <seq_num> 33500 ERROR EAP: Could not initialize EAP-TLS,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 33500 ERROR EAP: Could not initialize
EAP-TLS, <log details>

- 消息代码: 33501

严重性: 错误 (ERROR)

消息文本: 无法初始化 EAP-FAST (Could not initialize EAP-FAST)

消息说明: 无法初始化 EAP-FAST 模块, 系统将禁用此模块

本地目标消息格式: <timestamp> <seq_num> 33501 ERROR EAP: Could not initialize EAP-FAST, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 33501 ERROR EAP: Could not initialize EAP-FAST, <log details>

- 消息代码: 33502

严重性: 错误 (ERROR)

消息文本: 无法初始化 PEAP (Could not initialize PEAP)

消息说明: 无法初始化 PEAP 模块, 系统将禁用此模块

本地目标消息格式: <timestamp> <seq_num> 33502 ERROR EAP: Could not initialize PEAP, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 33502 ERROR EAP: Could not initialize PEAP, <log details>

- 消息代码: 33503

严重性: 警告 (WARN)

消息文本: 为 EAP-TLS 配置的 CTL 为空 (A blank CTL was configured for EAP-TLS)

消息说明: 在 EAP-TLS 模块的初始化中配置的 CTL 为空

本地目标消息格式: <timestamp> <seq_num> 33503 WARN EAP: A blank CTL was configured for EAP-TLS, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 33503 WARN EAP: A blank CTL was configured for EAP-TLS, <log details>

- 消息代码: 33504

严重性: 警告 (WARN)

消息文本: CTL 初始化失败 (CTL initialization failed)

消息说明: EAP-TLS 或 EAP-FAST 模块无法初始化部分 CTL 配置。

本地目标消息格式: <timestamp> <seq_num> 33504 WARN EAP: CTL initialization failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 33504 WARN EAP: CTL initialization failed, <log details>

- 消息代码: 33505

严重性: 警告 (WARN)

消息文本: 无法初始化 EAP-TLS 服务器证书 (Could not initialize EAP-TLS server-certificate)

消息说明：由于配置问题，EAP-TLS 模块无法初始化服务器证书。

本地目标消息格式：<timestamp> <seq_num> 33505 WARN EAP: Could not initialize EAP-TLS server-certificate, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 33505 WARN EAP: Could not initialize EAP-TLS server-certificate, <log details>

- 消息代码：33506

严重性：警告 (WARN)

消息文本：无法初始化 EAP-FAST 服务器证书 (Could not initialize EAP-FAST server-certificate)

消息说明：由于配置问题，EAP-FAST 模块无法初始化服务器证书。此问题仅影响 EAP-FAST 的经过验证的调配模式。

本地目标消息格式：<timestamp> <seq_num> 33506 WARN EAP: Could not initialize EAP-FAST server-certificate, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 33506 WARN EAP: Could not initialize EAP-FAST server-certificate, <log details>

- 消息代码：33507

严重性：警告 (WARN)

消息文本：无法初始化 PEAP 服务器证书 (Could not initialize PEAP server-certificate)

消息说明：由于配置问题，EAP-TLS 模块无法初始化服务器证书。

本地目标消息格式：<timestamp> <seq_num> 33507 WARN EAP: Could not initialize PEAP server-certificate, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 33507 WARN EAP: Could not initialize PEAP server-certificate, <log details>

- 消息代码：33508

严重性：警告 (WARN)

消息文本：无法初始化完整的 EAP-TLS 服务器证书链 (Could not initialize the complete EAP-TLS server-certificate chain)

消息说明：由于配置问题，EAP-TLS 模块无法初始化完整的服务器证书链。

本地目标消息格式：<timestamp> <seq_num> 33508 WARN EAP: Could not initialize the complete EAP-TLS server-certificate chain, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 33508 WARN EAP: Could not initialize the complete EAP-TLS server-certificate chain, <log details>

- 消息代码：33509

严重性: 警告 (WARN)

消息文本: PEAP 无法完全初始化服务器证书链 (PEAP failed to completely initialize the server-certificate chain)

消息说明: 由于配置问题, PEAP 模块无法初始化完整的服务器证书链。

本地目标消息格式: <timestamp> <seq_num> 33509 WARN EAP: PEAP failed to completely initialize the server-certificate chain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 33509 WARN EAP: PEAP failed to completely initialize the server-certificate chain, <log details>

- 消息代码: 33510

严重性: 警告 (WARN)

消息文本: 无法初始化完整的 EAP-FAST 服务器证书链 (Could not initialize the complete EAP-FAST server-certificate chain)

消息说明: 由于配置问题, EAP-FAST 模块无法初始化完整的服务器证书链。

本地目标消息格式: <timestamp> <seq_num> 33510 WARN EAP: Could not initialize the complete EAP-FAST server-certificate chain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 33510 WARN EAP: Could not initialize the complete EAP-FAST server-certificate chain, <log details>

- 消息代码: 34000

严重性: 信息 (INFO)

消息文本: 正在附加事务 (Appending transaction)

消息说明: 事务已应用到配置, 并已附加到事务日志

本地目标消息格式: <timestamp> <seq_num> 34000 INFO Replication: Appending transaction, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34000 INFO Replication: Appending transaction, <log details>

- 消息代码: 34001

严重性: 信息 (INFO)

消息文本: 正在调度事务 (Dispatching transaction)

消息说明: 已将事务发送到辅助节点进行复制

本地目标消息格式: <timestamp> <seq_num> 34001 INFO Replication: Dispatching transaction, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 34001 INFO Replication: Dispatching
transaction, <log details>2

- 消息代码: 34002

严重性: 信息 (INFO)

消息文本: 已收到事务 (Received transaction)

消息说明: 已从主节点收到事务

本地目标消息格式: <timestamp> <seq_num> 34002 INFO Replication: Received transaction, <log
details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 34002 INFO Replication: Received transaction,
<log details>

- 消息代码: 34003

严重性: 信息 (INFO)

消息文本: 已应用事务 (Applied transaction)

消息说明: 复制的事务已应用到本地配置

本地目标消息格式: <timestamp> <seq_num> 34003 INFO Replication: Applied transaction, <log
details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 34003 INFO Replication: Applied transaction,
<log details>

- 消息代码: 34005

严重性: 严重 (FATAL)

消息文本: 策略缓存同步失败 (Policy cache sync failed)

消息说明: 无法同步策略缓存

本地目标消息格式: <timestamp> <seq_num> 34005 FATAL Replication: Policy cache sync failed,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 34005 FATAL Replication: Policy cache
sync failed, <log details>

- 消息代码: 34050

严重性: 信息 (INFO)

消息文本: RT 控制端口已启用 (RT Control port is up)

消息说明: RT 正在 RT 控制端口上进行侦听。

本地目标消息格式: <timestamp> <seq_num> 34050 INFO RT-Control: RT Control port is up, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 34050 INFO RT-Control: RT Control port is up, <log details>

- 消息代码: 34051

严重性: 错误 (ERROR)

消息文本: 已阻止 RT 控制端口 (RT Control port is blocked)

消息说明: RT 无法打开 RT 控制端口。RT 控制服务不可用。RT 将尝试重新打开端口。

本地目标消息格式: <timestamp><seq_num> 34051 ERROR RT-Control: RT Control port is blocked, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 34051 ERROR RT-Control: RT Control port is blocked, <log details>

- 消息代码: 34110

严重性: 错误 (ERROR)

消息文本: 处理 REST 请求时出错 (Error processing the REST request)

消息说明: 服务器在处理 REST 请求时出错

本地目标消息格式: <timestamp> <seq_num> 34110 ERROR REST: Error processing the REST request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 34110 ERROR REST: Error processing the REST request, <log details>

- 消息代码: 34111

严重性: 信息 (INFO)

消息文本: 成功处理 REST 请求 (Successfully processed the REST request)

消息说明: 成功处理 REST 请求

本地目标消息格式: <timestamp> <seq_num> 34111 INFO REST: Successfully processed the REST request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 34111 INFO REST: Successfully processed the REST request, <log details>

- 消息代码: 34112

严重性: 错误 (ERROR)

消息文本: REST 请求数据无效 (Invalid REST request data)

消息说明: REST 请求数据的语法无效

本地目标消息格式: <timestamp> <seq_num> 34112 ERROR REST: Invalid REST request data, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34112 ERROR REST: Invalid REST request data, <log details>

- 消息代码: 34113

严重性: 警告 (WARN)

消息文本: 未找到指定资源 (Specified resource not found)

消息说明: 未找到指定资源

本地目标消息格式: <timestamp> <seq_num> 34113 WARN REST: Specified resource not found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34113 WARN REST: Specified resource not found, <log details>

- 消息代码: 34114

严重性: 警告 (WARN)

消息文本: 指定资源已存在 (Specified resource already exists)

消息说明: 指定资源已存在

本地目标消息格式: <timestamp> <seq_num> 34114 WARN REST: Specified resource already exists, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34114 WARN REST: Specified resource already exists, <log details>

- 消息代码: 34115

严重性: 警告 (WARN)

消息文本: 指定的关联资源不存在 (Specified associated resource does not exist)

消息说明: 指定的关联资源不存在

本地目标消息格式: <timestamp> <seq_num> 34115 WARN REST: Specified associated resource does not exist, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34115 WARN REST: Specified associated resource does not exist, <log details>

- 消息代码: 34116

严重性: 警告 (WARN)

消息文本: 未找到指定策略 (Specified policy is not found)

消息说明: 未找到指定策略

本地目标消息格式: <timestamp> <seq_num> 34116 WARN REST: Specified policy is not found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34116 WARN REST: Specified policy is not found, <log details>

- 消息代码: 34117

严重性: 错误 (ERROR)

消息文本: 连接远程源 URL 时出错 (Error connecting to remote feed URL)

消息说明: 此消息在远程源站点关闭时生成

本地目标消息格式: <timestamp> <seq_num> 34117 ERROR Client Provisioning: Error connecting to remote feed URL, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34117 ERROR Client Provisioning: Error connecting to remote feed URL, <log details>

- 消息代码: 34118

严重性: 错误 (ERROR)

消息文本: 处理来自思科下载源站点的软件包时出错 (Error processing package from Cisco download feed site)

消息说明: 处理来自思科下载源站点的软件包时出错

本地目标消息格式: <timestamp> <seq_num> 34118 ERROR Client Provisioning: Error processing package from Cisco download feed site, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34118 ERROR Client Provisioning: Error processing package from Cisco download feed site, <log details>

- 消息代码: 34119

严重性: 错误 (ERROR)

消息文本: 配置文件从 NAC 管理器收到有关通知事件的错误响应 (Profile received an error response from NAC Manager for notification event)

消息说明: 分析器向 NAC 管理器发送了一个通知事件, 但由于 NAC 管理器无法处理此事件, 因此通知失败。请查看 NAC 管理器日志, 了解详细信息

本地目标消息格式: <timestamp> <seq_num> 34119 ERROR Profiler: Profile received an error response from NAC Manager for notification event, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 34119 ERROR Profiler: Profile received an error response from NAC Manager for notification event, <log details>

- 消息代码: 34120

严重性: 错误 (ERROR)

消息文本: 分析器无法连接到 NAC 管理器 (Profiler failed to get the connection to NAC Manager)

消息说明: 分析器向 NAC 管理器发送了一个通知事件, 但由于无法连接到 NAC 管理器, 因此通知失败

本地目标消息格式: <timestamp> <seq_num> 34120 ERROR Profiler: Profiler failed to get the connection to NAC Manager, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 34120 ERROR Profiler: Profiler failed to get the connection to NAC Manager, <log details>

- 消息代码: 34123

严重性: 严重 (FATAL)

消息文本: 虚拟内存使用率高表示此进程可能会耗尽内存资源 (The virtual memory usage is high indicating the process may be running out of memory resources)

消息说明: 虚拟内存高表示此进程可能会耗尽内存资源

本地目标消息格式: <timestamp> <seq_num> 34123 FATAL System-Management: The virtual memory usage is high indicating the process may be running out of memory resources, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 34123 FATAL System-Management: The virtual memory usage is high indicating the process may be running out of memory resources, <log details>

- 消息代码: 34124

严重性: 严重 (FATAL)

消息文本: 由于内存资源较低, 并发 EAP 会话数量将受到限制 (Due to low memory resources the amount of concurrent EAP sessions will be limited)

消息说明: 由于内存资源较低, 并发 EAP 会话数量将受到限制

本地目标消息格式: <timestamp> <seq_num> 34124 FATAL System-Management: Due to low memory resources the amount of concurrent EAP sessions will be limited, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 34124 FATAL System-Management: Due to low memory resources the amount of concurrent EAP sessions will be limited, <log details>

- 消息代码: 34125

严重性: 严重 (FATAL)

消息文本: 由于内存资源较低, CRL 无法更新。(Due to low memory resources a CRL could not be updated.)

消息说明: 由于内存资源较低, CRL 无法更新。

本地目标消息格式: <timestamp> <seq_num> 34125 FATAL System-Management: Due to low memory resources a CRL could not be updated., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34125 FATAL System-Management: Due to low memory resources a CRL could not be updated., <log details>

- 消息代码: 34126

严重性: 警告 (WARN)

消息文本: 远程系统日志目标不可用 (Remote syslog target is unavailable)

消息说明: 远程系统日志目标不可用

本地目标消息格式: <timestamp> <seq_num> 34126 WARN System-Management: Remote syslog target is unavailable, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34126 WARN System-Management: Remote syslog target is unavailable, <log details>

- 消息代码: 34127

严重性: 警告 (WARN)

消息文本: 远程系统日志目标连接恢复 (Remote syslog target connection resume)

消息说明: 远程系统日志目标连接恢复

本地目标消息格式: <timestamp> <seq_num> 34127 WARN System-Management: Remote syslog target connection resume, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34127 WARN System-Management: Remote syslog target connection resume, <log details>

- 消息代码: 34128

严重性: 调试 (DEBUG)

消息文本: 已清除远程系统日志目标缓冲区 (Remote syslog target buffer is cleared)

消息说明: 因配置更改而清除远程系统日志目标缓冲区

本地目标消息格式: <timestamp> <seq_num> 34128 DEBUG System-Management: Remote syslog target buffer is cleared, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34128 DEBUG System-Management: Remote syslog target buffer is cleared, <log details>

- 消息代码: 34129
严重性: 警告 (WARN)
消息文本: 无法初始化系统日志客户端证书 (Could not initialize syslog client certificate)
消息说明: 由于配置问题, 无法初始化系统日志客户端证书
本地目标消息格式: <timestamp> <seq_num> 34129 WARN System-Management: Could not initialize syslog client certificate, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34129 WARN System-Management: Could not initialize syslog client certificate, <log details>
- 消息代码: 34130
严重性: 警告 (WARN)
消息文本: 系统日志服务器证书的 CTL 为空 (CTL for syslog server certificate is empty)
消息说明: 系统日志服务器证书的 CTL 为空。不接受任何系统日志服务器
本地目标消息格式: <timestamp> <seq_num> 34130 WARN System-Management: CTL for syslog server certificate is empty, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34130 WARN System-Management: CTL for syslog server certificate is empty, <log details>
- 消息代码: 34131
严重性: 警告 (WARN)
消息文本: 无法初始化完整的系统日志客户端证书链 (Could not initialize the complete syslog client certificate chain)
消息说明: 由于配置问题, 无法初始化完整的系统日志客户端证书链
本地目标消息格式: <timestamp> <seq_num> 34131 WARN System-Management: Could not initialize the complete syslog client certificate chain, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34131 WARN System-Management: Could not initialize the complete syslog client certificate chain, <log details>
- 消息代码: 34132
严重性: 信息 (INFO)
消息文本: 与系统日志服务器进行 TLS 握手成功 (TLS handshake with syslog server succeeded)
消息说明: 与系统日志服务器进行 TLS 握手成功
本地目标消息格式: <timestamp> <seq_num> 34132 INFO System-Management: TLS handshake with syslog server succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 34132 INFO System-Management: TLS handshake with syslog server succeeded, <log details>

- 消息代码: 34133

严重性: 警告 (WARN)

消息文本: 与系统日志服务器进行 TLS 握手失败 (TLS handshake with syslog server failed)

消息说明: 与系统日志服务器进行 TLS 握手失败

本地目标消息格式: <timestamp> <seq_num> 34133 WARN System-Management: TLS handshake with syslog server failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 34133 WARN System-Management: TLS handshake with syslog server failed, <log details>

- 消息代码: 34134

严重性: 警告 (WARN)

消息文本: 无法初始化系统日志服务器证书验证的 CTL (Could not initialize CTL for syslog server certificate verification)

消息说明: 无法初始化系统日志服务器证书验证的 CTL

本地目标消息格式: <timestamp> <seq_num> 34134 WARN System-Management: Could not initialize CTL for syslog server certificate verification, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 34134 WARN System-Management: Could not initialize CTL for syslog server certificate verification, <log details>

- 消息代码: 34135

严重性: 警告 (WARN)

消息文本: 系统日志服务器运行缓慢或关闭。正在删除缓冲的系统日志消息。(Syslog server is slow or down. Buffered syslog messages are being deleted.)

消息说明: 系统日志服务器运行缓慢、关闭或无法读取系统日志消息。正在删除缓冲的系统日志消息。这可能是由于服务器、网络或负载均衡器问题所致。

本地目标消息格式: <timestamp> <seq_num> 34135 WARN System-Management: Syslog server is slow or down. Buffered syslog messages are being deleted., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 34135 WARN System-Management: Syslog server is slow or down. Buffered syslog messages are being deleted., <log details>

- 消息代码: 34137

严重性: 警告 (WARN)

消息文本: 安全系统日志服务器已拒绝 ISE 系统日志客户端证书 (Secure syslog server rejected ISE syslog client certificate)

消息说明: 安全系统日志服务器已拒绝 ISE 系统日志客户端证书

本地目标消息格式: <timestamp> <seq_num> 34137 WARN System-Management: Secure syslog server rejected ISE syslog client certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34137 WARN System-Management: Secure syslog server rejected ISE syslog client certificate, <log details>

- 消息代码: 34138

严重性: 警告 (WARN)

消息文本: 由于系统日志服务器证书链中存在不受支持的证书, 因此 ISE 进行安全系统日志连接时失败 (ISE failed secure syslog connection because of unsupported certificate in syslog server certificate chain)

消息说明: 由于系统日志服务器证书链中存在不受支持的证书, 因此 ISE 进行安全系统日志连接时失败

本地目标消息格式: <timestamp> <seq_num> 34138 WARN System-Management: ISE failed secure syslog connection because of unsupported certificate in syslog server certificate chain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34138 WARN System-Management: ISE failed secure syslog connection because of unsupported certificate in syslog server certificate chain, <log details>

- 消息代码: 34139

严重性: 警告 (WARN)

消息文本: 由于 ISE 无法为签署系统日志服务器证书的 CA 下载 CRL, 因此它在进行安全系统日志连接时失败 (ISE failed secure syslog connection because it was unable to download CRL for the CA that signed syslog server certificate)

消息说明: 由于 ISE 无法为签署系统日志服务器证书的 CA 下载 CRL, 因此它在进行安全系统日志连接时失败

本地目标消息格式: <timestamp> <seq_num> 34139 WARN System-Management: ISE failed secure syslog connection because it was unable to download CRL for the CA that signed syslog server certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34139 WARN System-Management: ISE failed secure syslog connection because it was unable to download CRL for the CA that signed syslog server certificate, <log details>

- 消息代码: 34140

严重性: 警告 (WARN)

消息文本: 由于系统日志服务器证书链中存在未知证书, 因此 ISE 在进行安全系统日志连接时失败 (ISE failed secure syslog connection because of unknown certificate in syslog server certificate chain)

消息说明: 由于系统日志服务器证书链中存在未知证书, 因此 ISE 在进行安全系统日志连接时失败

本地目标消息格式: <timestamp> <seq_num> 34140 WARN System-Management: ISE failed secure syslog connection because of unknown certificate in syslog server certificate chain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34140 WARN System-Management: ISE failed secure syslog connection because of unknown certificate in syslog server certificate chain, <log details>

- 消息代码: 34141

严重性: 警告 (WARN)

消息文本: 由于系统日志服务器证书链中存在过期证书, 因此 ISE 在进行安全系统日志连接时失败 (ISE failed secure syslog connection because of expired certificate in syslog server certificate chain)

消息说明: 由于系统日志服务器证书链中存在过期证书, 因此 ISE 在进行安全系统日志连接时失败

本地目标消息格式: <timestamp> <seq_num> 34141 WARN System-Management: ISE failed secure syslog connection because of expired certificate in syslog server certificate chain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34141 WARN System-Management: ISE failed secure syslog connection because of expired certificate in syslog server certificate chain, <log details>

- 消息代码: 34142

严重性: 警告 (WARN)

消息文本: 由于签署系统日志服务器证书的 CA 的 CRL 已过期, 因此 ISE 在进行安全系统日志连接时失败 (ISE failed secure syslog connection because of expired CRL for the CA that signed syslog server certificate)

消息说明: 由于签署系统日志服务器证书的 CA 的 CRL 已过期, 因此 ISE 在进行安全系统日志连接时失败

本地目标消息格式: <timestamp> <seq_num> 34142 WARN System-Management: ISE failed secure syslog connection because of expired CRL for the CA that signed syslog server certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34142 WARN System-Management: ISE failed secure syslog connection because of expired CRL for the CA that signed syslog server certificate, <log details>

- 消息代码: 34143

严重性: 警告 (WARN)

消息文本: 由于系统日志服务器证书链中存在已撤销的证书, 因此 ISE 在进行安全系统日志连接时失败 (ISE failed secure syslog connection because of revoked certificate in syslog server certificate chain)

消息说明: 由于系统日志服务器证书链中存在已撤销的证书, 因此 ISE 在进行安全系统日志连接时失败

本地目标消息格式: <timestamp> <seq_num> 34143 WARN System-Management: ISE failed secure syslog connection because of revoked certificate in syslog server certificate chain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34143 WARN System-Management: ISE failed secure syslog connection because of revoked certificate in syslog server certificate chain, <log details>

- 消息代码: 34144

严重性: 警告 (WARN)

消息文本: 由于系统日志服务器证书链中存在损坏的证书, 因此 ISE 在进行安全系统日志连接时失败 (ISE failed secure syslog connection because of bad certificate in syslog server certificate chain)

消息说明: 由于系统日志服务器证书链中存在损坏的证书, 因此 ISE 在进行安全系统日志连接时失败

本地目标消息格式: <timestamp> <seq_num> 34144 WARN System-Management: ISE failed secure syslog connection because of bad certificate in syslog server certificate chain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34144 WARN System-Management: ISE failed secure syslog connection because of bad certificate in syslog server certificate chain, <log details>

- 消息代码: 34145

严重性: 警告 (WARN)

消息文本: 由于 OCSP 查找到已撤销的证书, 安全系统日志连接重新连接 (Secure syslog connection reconnect due to OCSP found revoked certificate)

消息说明: OCSP 检查结果发现, 已撤销用于系统日志连接的证书

本地目标消息格式: <timestamp> <seq_num> 34145 WARN System-Management: Secure syslog connection reconnect due to OCSP found revoked certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34145 WARN System-Management: Secure syslog connection reconnect due to OCSP found revoked certificate, <log details>

- 消息代码: 34146

严重性: 警告 (WARN)

消息文本: 由于 CRL 查找到已撤销的证书, 因此安全系统日志连接重新连接 (Secure syslog connection reconnect due to CRL found revoked certificate)

消息说明: CRL 检查结果发现, 已撤销用于系统日志连接的证书

本地目标消息格式: <timestamp> <seq_num> 34146 WARN System-Management: Secure syslog connection reconnect due to CRL found revoked certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34146 WARN System-Management: Secure syslog connection reconnect due to CRL found revoked certificate, <log details>

- 消息代码: 34147

严重性: 警告 (WARN)

消息文本: JGroups TLS 握手失败 (JGroups TLS Handshake Failed)

消息说明: JGroups TLS 握手失败

本地目标消息格式: <timestamp> <seq_num> 34147 WARN System-Management: JGroups TLS Handshake Failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34147 WARN System-Management: JGroups TLS Handshake Failed, <log details>

- 消息代码: 34148

严重性: 信息 (INFO)

消息文本: JGroups TLS 握手成功 (JGroups TLS Handshake Succeeded)

消息说明: JGroups TLS 握手成功

本地目标消息格式: <timestamp> <seq_num> 34148 INFO System-Management: JGroups TLS Handshake Succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34148 INFO System-Management: JGroups TLS Handshake Succeeded, <log details>

- 消息代码: 34149

严重性: 警告 (WARN)

消息文本: HTTPS TLS 握手失败 (HTTPS TLS Handshake Failed)

消息说明: HTTPS TLS 握手失败

本地目标消息格式: <timestamp> <seq_num> 34149 WARN System-Management: HTTPS TLS Handshake Failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34149 WARN System-Management: HTTPS TLS Handshake Failed, <log details>

- 消息代码: 34150

严重性: 信息 (INFO)

消息文本: HTTPS TLS 握手成功 (HTTPS TLS Handshake Succeeded)

消息说明: HTTPS TLS 握手成功

本地目标消息格式: <timestamp> <seq_num> 34150 INFO System-Management: HTTPS TLS Handshake Succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34150 INFO System-Management: HTTPS TLS Handshake Succeeded, <log details>

- 消息代码: 34151

严重性: 警告 (WARN)

消息文本: 证书验证失败 (Certificate Validation Failed)

消息说明: 证书验证失败

本地目标消息格式: <timestamp> <seq_num> 34151 WARN System-Management: Certificate Validation Failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34151 WARN System-Management: Certificate Validation Failed, <log details>

- 消息代码: 34152

严重性: 信息 (INFO)

消息文本: 证书验证成功 (Certificate Validation Succeeded)

消息说明: 证书验证成功

本地目标消息格式: <timestamp> <seq_num> 34152 INFO System-Management: Certificate Validation Succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34152 INFO System-Management: Certificate Validation Succeeded, <log details>

- 消息代码: 34153

严重性: 警告 (WARN)

消息文本: 安全 LDAP ID 存储库连接失败 (Secure LDAP ID Store Connecion Failed)

消息说明: 安全 LDAP 身份存储库连接失败

本地目标消息格式: <timestamp> <seq_num> 34153 WARN System-Management: Secure LDAP ID Store Connecion Failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34153 WARN System-Management: Secure LDAP ID Store Connecion Failed, <log details>

- 消息代码: 34154

严重性: 信息 (INFO)

消息文本: 安全 LDAP ID 存储库连接成功 (Secure LDAP ID Store Connecion Succeeded)

消息说明: 安全 LDAP 身份存储库连接成功

本地目标消息格式: <timestamp> <seq_num> 34154 INFO System-Management: Secure LDAP ID Store Connecion Succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34154 INFO System-Management: Secure LDAP ID Store Connecion Succeeded, <log details>

• 消息代码: 34155

严重性: 错误 (ERROR)

消息文本: 已存在具有相同 MAC 地址的终端 (Endpoint with the same Mac Address already exists)

消息说明: 已存在具有相同 MAC 地址的终端

本地目标消息格式: <timestamp> <seq_num> 34155 ERROR REST: Endpoint with the same Mac Address already exists, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34155 ERROR REST: Endpoint with the same Mac Address already exists, <log details>

• 消息代码: 34156

严重性: 信息 (INFO)

消息文本: 已重置 CARS 网络配置 (CARS Network configuration has been reset)

消息说明: 已重置 CARS 网络配置

本地目标消息格式: <timestamp> <seq_num> 34156 INFO System-Management: CARS Network configuration has been reset, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34156 INFO System-Management: CARS Network configuration has been reset, <log details>

• 消息代码: 34157

严重性: 错误 (ERROR)

消息文本: 无法初始化 EAP-TTLS (Could not initialize EAP-TTLS)

消息说明: 无法初始化 EAP-TTLS 模块, 系统将禁用此模块。

本地目标消息格式: <timestamp> <seq_num> 34157 ERROR EAP: Could not initialize EAP-TTLS, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34157 ERROR EAP: Could not initialize EAP-TTLS, <log details>

• 消息代码: 34158

严重性: 警告 (WARN)

消息文本: 无法初始化 EAP-TTLS 服务器证书 (Could not initialize EAP-TTLS server-certificate)

消息说明: 由于配置问题, EAP-TTLS 模块无法初始化服务器证书。

本地目标消息格式: <timestamp> <seq_num> 34158 WARN EAP: Could not initialize EAP-TTLS server-certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34158 WARN EAP: Could not initialize EAP-TTLS server-certificate, <log details>

- 消息代码: 34159

严重性: 信息 (INFO)

消息文本: 成功建立 LDAPS 连接 (LDAPS connection established successfully)

消息说明: 成功建立 LDAPS 连接

本地目标消息格式: <timestamp> <seq_num> 34159 INFO System-Management: LDAPS connection established successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34159 INFO System-Management: LDAPS connection established successfully, <log details>

- 消息代码: 34160

严重性: 信息 (INFO)

消息文本: 成功终止 LDAPS 连接 (LDAPS connection terminated successfully)

消息说明: 成功终止 LDAPS 连接

本地目标消息格式: <timestamp> <seq_num> 34160 INFO System-Management: LDAPS connection terminated successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34160 INFO System-Management: LDAPS connection terminated successfully, <log details>

- 消息代码: 34161

严重性: 警告 (WARN)

消息文本: 出现 SSL 错误, 建立 LDAPS 连接失败 (LDAPS connection establishment failed with SSL error)

消息说明: 出现 SSL 错误, 建立 LDAPS 连接失败

本地目标消息格式: <timestamp> <seq_num> 34161 WARN System-Management: LDAPS connection establishment failed with SSL error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34161 WARN System-Management: LDAPS connection establishment failed with SSL error, <log details>

- 消息代码: 34162
 - 严重性: 警告 (WARN)
 - 消息文本: 出现 SSL 错误, LDAPS 连接终止 (LDAPS connection terminated with SSL error)
 - 消息说明: 出现 SSL 错误, LDAPS 连接终止
 - 本地目标消息格式: <timestamp> <seq_num> 34162 WARN System-Management: LDAPS connection terminated with SSL error, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34162 WARN System-Management: LDAPS connection terminated with SSL error, <log details>

- 消息代码: 34163
 - 严重性: 警告 (WARN)
 - 消息文本: 出现非 SSL 错误, 建立 LDAPS 连接失败 (LDAPS connection establishment failed with non-SSL error)
 - 消息说明: 出现非 SSL 错误, 建立 LDAPS 连接失败
 - 本地目标消息格式: <timestamp> <seq_num> 34163 WARN System-Management: LDAPS connection establishment failed with non-SSL error, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34163 WARN System-Management: LDAPS connection establishment failed with non-SSL error, <log details>

- 消息代码: 34164
 - 严重性: 警告 (WARN)
 - 消息文本: 出现非 SSL 错误, LDAPS 连接终止 (LDAPS connection terminated with non-SSL error)
 - 消息说明: 出现非 SSL 错误, LDAPS 连接终止
 - 本地目标消息格式: <timestamp> <seq_num> 34164 WARN System-Management: LDAPS connection terminated with non-SSL error, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 34164 WARN System-Management: LDAPS connection terminated with non-SSL error, <log details>

- 消息代码: 33511
 - 严重性: 警告 (WARN)
 - 消息文本: 无法初始化 TEAP 服务器证书 (Could not initialize TEAP server-certificate)
 - 消息说明: nan
 - 本地目标消息格式: <timestamp> <seq_num>33511 WARN EAP Could not initialize TEAP server-certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>33511 WARN EAP Could not initialize TEAP
server-certificate, <log details>

- 消息代码: 33512

严重性: 警告 (WARN)

消息文本: 无法初始化完整的 TEAP 服务器证书链 (Could not initialize the complete TEAP
server-certificate chain)

消息说明: nan

本地目标消息格式: <timestamp> <seq_num>33512 WARN EAP Could not initialize the complete
TEAP server-certificate chain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>33512 WARN EAP Could not initialize the
complete TEAP server-certificate chain, <log details>

- 消息代码: 33513

严重性: 错误 (ERROR)

消息文本: 无法初始化 TEAP (Could not initialize TEAP)

消息说明: nan

本地目标消息格式: <timestamp> <seq_num>33513 ERROR EAP Could not initialize TEAP, <log
details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>33513 ERROR EAP Could not initialize
TEAP, <log details>

- 消息代码: 33514

严重性: 调试 (DEBUG)

消息文本: 发送的 TEAP 结果 TLV 表明成功 (Sent TEAP Result TLV indicating success)

消息说明: nan

本地目标消息格式: <timestamp> <seq_num>33514 DEBUG EAP Sent TEAP Result TLV indicating
success, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>33514 DEBUG EAP Sent TEAP Result TLV
indicating success, <log details>

- 消息代码: 33515

严重性: 调试 (DEBUG)

消息文本: 发送的 TEAP 结果 TLV 表明失败 (Sent TEAP Result TLV indicating failure)

消息说明: nan

本地目标消息格式: <timestamp> <seq_num>33515 DEBUG EAP Sent TEAP Result TLV indicating failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>33515 DEBUG EAP Sent TEAP Result TLV indicating failure, <log details>

- 消息代码: 33516

严重性: 调试 (DEBUG)

消息文本: 发送的 TEAP 中间结果 TLV 表明成功 (Sent TEAP Intermediate Result TLV indicating success)

消息说明: nan

本地目标消息格式: <timestamp> <seq_num>33516 DEBUG EAP Sent TEAP Intermediate Result TLV indicating success, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>33516 DEBUG EAP Sent TEAP Intermediate Result TLV indicating success, <log details>

- 消息代码: 33517

严重性: 调试 (DEBUG)

消息文本: 发送的 TEAP 中间结果 TLV 表明失败 (Sent TEAP Intermediate Result TLV indicating failure)

消息说明: nan

本地目标消息格式: <timestamp> <seq_num>33517 DEBUG EAP Sent TEAP Intermediate Result TLV indicating failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>33517 DEBUG EAP Sent TEAP Intermediate Result TLV indicating failure, <log details>

- 消息代码: 33518

严重性: 警告 (WARN)

消息文本: 没有用于完整握手 TEAP 身份验证的密码

消息说明: nan

本地目标消息格式: <timestamp> <seq_num>33518 WARN EAP No cipher for full handshake TEAP authentication, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>33518 WARN EAP No cipher for full handshake TEAP authentication, <log details>

许可

- 消息代码: 35000
严重性: 警告 (WARN)
消息文本: 智能许可注册失败 (Smart Licensing registration failed)
消息说明: 智能许可注册失败
本地目标消息格式: <timestamp> <seq_num> 35000 WARN Licensing: Smart Licensing registration failed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35000 WARN Licensing: Smart Licensing registration failed, <log details>
- 消息代码: 35001
严重性: 警告 (WARN)
消息文本: 智能许可已禁用 (Smart Licensing disabled)
消息说明: 智能许可已禁用
本地目标消息格式: <timestamp> <seq_num> 35001 WARN Licensing: Smart Licensing disabled, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35001 WARN Licensing: Smart Licensing disabled, <log details>
- 消息代码: 35002
严重性: 信息 (INFO)
消息文本: 智能许可通信故障 (Smart Licensing communication failure)
消息说明: 智能许可通信故障
本地目标消息格式: <timestamp> <seq_num> 35002 INFO Licensing: Smart Licensing communication failure, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35002 INFO Licensing: Smart Licensing communication failure, <log details>
- 消息代码: 35003
严重性: 信息 (INFO)
消息文本: 智能许可通信已恢复 (Smart Licensing communication restored)
消息说明: 智能许可通信已恢复

本地目标消息格式: <timestamp> <seq_num> 35003 INFO Licensing: Smart Licensing communication restored, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35003 INFO Licensing: Smart Licensing communication restored, <log details>

- 消息代码: 35004

严重性: 信息 (INFO)

消息文本: 智能许可 ID 证书续签失败 (Smart Licensing Id Certificate renew failure)

消息说明: 智能许可 ID 证书续签失败

本地目标消息格式: <timestamp> <seq_num> 35004 INFO Licensing: Smart Licensing Id Certificate renew failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35004 INFO Licensing: Smart Licensing Id Certificate renew failure, <log details>

- 消息代码: 35005

严重性: 信息 (INFO)

消息文本: 智能许可 ID 证书续签成功 (Smart Licensing Id Certificate renew success)

消息说明: 智能许可 ID 证书续签成功

本地目标消息格式: <timestamp> <seq_num> 35005 INFO Licensing: Smart Licensing Id Certificate renew success, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35005 INFO Licensing: Smart Licensing Id Certificate renew success, <log details>

- 消息代码: 35006

严重性: 警告 (WARN)

消息文本: 智能许可代理不合规 (Smart Licensing Agent is Out Of Compliance)

消息说明: 智能许可代理不合规

本地目标消息格式: <timestamp> <seq_num> 35006 WARN Licensing: Smart Licensing Agent is Out Of Compliance, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35006 WARN Licensing: Smart Licensing Agent is Out Of Compliance, <log details>

- 消息代码: 35007

严重性: 警告 (WARN)

消息文本: 智能许可评估期已过期 (Smart Licensing evaluation period expired)

消息说明: 智能许可评估期已过期

本地目标消息格式: <timestamp> <seq_num> 35007 WARN Licensing: Smart Licensing evaluation period expired, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35007 WARN Licensing: Smart Licensing evaluation period expired, <log details>

- 消息代码: 35008

严重性: 警告 (WARN)

消息文本: 智能许可授权已过期 (Smart Licensing authorization expired)

消息说明: 智能许可授权已过期

本地目标消息格式: <timestamp> <seq_num> 35008 WARN Licensing: Smart Licensing authorization expired, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35008 WARN Licensing: Smart Licensing authorization expired, <log details>

- 消息代码: 35009

严重性: 警告 (WARN)

消息文本: 发出的智能许可请求无效 (Invalid Smart Licensing request issued)

消息说明: 发出的智能许可请求无效

本地目标消息格式: <timestamp> <seq_num> 35009 WARN Licensing: Invalid Smart Licensing request issued, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35009 WARN Licensing: Invalid Smart Licensing request issued, <log details>

- 消息代码: 35010

严重性: 警告 (WARN)

消息文本: 许可证设置为即将到期 (License is set to expire soon)

消息说明: ISE 部署中当前安装的许可证设置为即将到期。

本地目标消息格式: <timestamp> <seq_num> 35010 WARN Licensing: License is set to expire soon, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35010 WARN Licensing: License is set to expire soon, <log details>

- 消息代码: 35011

严重性: 错误 (ERROR)

消息文本: 许可证已过期 (License expired)

消息说明: ISE 部署中的许可证已过期。

本地目标消息格式: <timestamp> <seq_num> 35011 ERROR Licensing: License expired, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 35011 ERROR Licensing: License expired,
<log details>

- 消息代码: 35012

严重性: 警告 (WARN)

消息文本: 基本许可证的设备计数已超出限制 (Device count exceeded for base license)

消息说明: 基本许可证的设备计数已超出限制。升级到所需的大型部署。

本地目标消息格式: <timestamp> <seq_num> 35012 WARN Licensing: Device count exceeded for
base license, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 35012 WARN Licensing: Device count
exceeded for base license, <log details>

- 消息代码: 35013

严重性: 错误 (ERROR)

消息文本: 许可证删除失败 (License deletion failed)

消息说明: 许可证删除失败

本地目标消息格式: <timestamp> <seq_num> 35013 ERROR Licensing: License deletion failed, <log
details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 35013 ERROR Licensing: License deletion
failed, <log details>

- 消息代码: 35014

严重性: 错误 (ERROR)

消息文本: 许可证创建失败 (License create failed)

消息说明: 许可证创建失败

本地目标消息格式: <timestamp> <seq_num> 35014 ERROR Licensing: License create failed, <log
details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 35014 ERROR Licensing: License create
failed, <log details>

- 消息代码: 35015

严重性: 错误 (ERROR)

消息文本: 许可证更新失败 (License update failed)

消息说明: 许可证更新失败

本地目标消息格式: <timestamp> <seq_num> 35015 ERROR Licensing: License update failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 35015 ERROR Licensing: License update failed, <log details>

• 消息代码: 35016

严重性: 信息 (INFO)

消息文本: 智能许可注册成功 (Smart Licensing registration success)

消息说明: 智能许可注册成功

本地目标消息格式: <timestamp> <seq_num> 35016 INFO Licensing: Smart Licensing registration success, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 35016 INFO Licensing: Smart Licensing registration success, <log details>

• 消息代码: 35017

严重性: 信息 (INFO)

消息文本: 智能许可授权续订成功 (Smart Licensing authorization renewal success)

消息说明: 智能许可授权续订成功

本地目标消息格式: <timestamp> <seq_num> 35017 INFO Licensing: Smart Licensing authorization renewal success, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 35017 INFO Licensing: Smart Licensing authorization renewal success, <log details>

• 消息代码: 35018

严重性: 警告 (WARN)

消息文本: 智能许可授权续订失败 (Smart Licensing authorization renewal failure)

消息说明: 智能许可授权续订失败

本地目标消息格式: <timestamp> <seq_num> 35018 WARN Licensing: Smart Licensing authorization renewal failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 35018 WARN Licensing: Smart Licensing authorization renewal failure, <log details>

- 消息代码: 35019
 - 严重性: 信息 (INFO)
 - 消息文本: 智能许可取消注册成功 (Smart Licensing de-registration success)
 - 消息说明: 智能许可取消注册成功
 - 本地目标消息格式: <timestamp> <seq_num> 35019 INFO Licensing: Smart Licensing de-registration success, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35019 INFO Licensing: Smart Licensing de-registration success, <log details>

- 消息代码: 35020
 - 严重性: 警告 (WARN)
 - 消息文本: 智能许可取消注册失败 (Smart Licensing de-registration failure)
 - 消息说明: 智能许可取消注册失败
 - 本地目标消息格式: <timestamp> <seq_num> 35020 WARN Licensing: Smart Licensing de-registration failure, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35020 WARN Licensing: Smart Licensing de-registration failure, <log details>

- 消息代码: 35021
 - 严重性: 警告 (WARN)
 - 消息文本: 智能许可 ID 证书已过期 (Smart Licensing id certificate expired)
 - 消息说明: 智能许可 ID 证书已过期
 - 本地目标消息格式: <timestamp> <seq_num> 35021 WARN Licensing: Smart Licensing id certificate expired, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35021 WARN Licensing: Smart Licensing id certificate expired, <log details>

- 消息代码: 35022
 - 严重性: 信息 (INFO)
 - 消息文本: 智能许可 HA 角色已更改 (Smart Licensing HA Role changed)
 - 消息说明: 智能许可 HA 角色已更改
 - 本地目标消息格式: <timestamp> <seq_num> 35022 INFO Licensing: Smart Licensing HA Role changed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 35022 INFO Licensing: Smart Licensing
HA Role changed, <log details>

- 消息代码: 35023

严重性: 信息 (INFO)

消息文本: 90 天内许可证到期 (License expiring within 90 Days)

消息说明: 90 天内许可证到期

本地目标消息格式: <timestamp> <seq_num> 35023 INFO Licensing: License expiring within 90
Days, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 35023 INFO Licensing: License expiring
within 90 Days, <log details>

- 消息代码: 35024

严重性: 警告 (WARN)

消息文本: 60 天内许可证到期 (License expiring within 60 Days)

消息说明: 60 天内许可证到期

本地目标消息格式: <timestamp> <seq_num> 35024 WARN Licensing: License expiring within 60
Days, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 35024 WARN Licensing: License expiring
within 60 Days, <log details>

- 消息代码: 35025

严重性: 错误 (ERROR)

消息文本: 30 天内许可证到期 (License expiring within 30 Days)

消息说明: 30 天内许可证到期

本地目标消息格式: <timestamp> <seq_num> 35025 ERROR Licensing: License expiring within 30
Days, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 35025 ERROR Licensing: License expiring
within 30 Days, <log details>

- 消息代码: 35026

严重性: 错误 (ERROR)

消息文本: 5 天或更长时间里许可证不合规 (License Out of Compliance for 5 or more days)

消息说明: 5 天或更长时间里许可证不合规

本地目标消息格式: <timestamp> <seq_num> 35026 ERROR Licensing: License Out of Compliance for 5 or more days, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35026 ERROR Licensing: License Out of Compliance for 5 or more days, <log details>

- 消息代码: 35027

严重性: 错误 (ERROR)

消息文本: 15 天或更长时间内许可证不合规 (License Out of Compliance for 15 or more days)

消息说明: 15 天或更长时间内许可证不合规

本地目标消息格式: <timestamp> <seq_num> 35027 ERROR Licensing: License Out of Compliance for 15 or more days, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35027 ERROR Licensing: License Out of Compliance for 15 or more days, <log details>

- 消息代码: 35028

严重性: 错误 (ERROR)

消息文本: 30 天或更长时间内许可证不合规 (License Out of Compliance for 30 or more days)

消息说明: 30 天或更长时间内许可证不合规

本地目标消息格式: <timestamp> <seq_num> 35028 ERROR Licensing: License Out of Compliance for 30 or more days, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35028 ERROR Licensing: License Out of Compliance for 30 or more days, <log details>

- 消息代码: 35029

严重性: 错误 (ERROR)

消息文本: 许可证不合规超过 45 天, 服务配置已禁用 (License Out of Compliance for more than 45 Days Services Configuration Disabled)

消息说明: 许可证不合规超过 45 天, 服务配置已禁用

本地目标消息格式: <timestamp> <seq_num> 35029 ERROR Licensing: License Out of Compliance for more than 45 Days Services Configuration Disabled, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35029 ERROR Licensing: License Out of Compliance for more than 45 Days Services Configuration Disabled, <log details>

- 消息代码: 35030

严重性: 警告 (WARN)

消息文本: 许可证会话使用率超过 100% (License exceeded 100% session usage)

消息说明: 许可证会话使用率超过 100%

本地目标消息格式: <timestamp> <seq_num> 35030 WARN Licensing: License exceeded 100% session usage, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35030 WARN Licensing: License exceeded 100% session usage, <log details>

- 消息代码: 35031

严重性: 错误 (ERROR)

消息文本: 许可证会话使用率超过 125% (License exceeded 125% session usage)

消息说明: 许可证会话使用率超过 125%

本地目标消息格式: <timestamp> <seq_num> 35031 ERROR Licensing: License exceeded 125% session usage, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35031 ERROR Licensing: License exceeded 125% session usage, <log details>

- 消息代码: 35032

严重性: 信息 (INFO)

消息文本: 90 天内许可证到期 (License expiring Within 90 Days)

消息说明: 90 天内许可证到期

本地目标消息格式: <timestamp> <seq_num> 35032 INFO Licensing: License expiring Within 90 Days, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35032 INFO Licensing: License expiring Within 90 Days, <log details>

- 消息代码: 35033

严重性: 警告 (WARN)

消息文本: 60 天内许可证到期 (License expiring Within 60 Days)

消息说明: 60 天内许可证到期

本地目标消息格式: <timestamp> <seq_num> 35033 WARN Licensing: License expiring Within 60 Days, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35033 WARN Licensing: License expiring Within 60 Days, <log details>

- 消息代码: 35034

严重性: 错误 (ERROR)

消息文本: 30 天内许可证到期 (License expiring Within 30 Days)

消息说明: 30 天内许可证到期

本地目标消息格式: <timestamp> <seq_num> 35034 ERROR Licensing: License expiring Within 30 Days, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 35034 ERROR Licensing: License expiring Within 30 Days, <log details>

- 消息代码: 35035

严重性: 错误 (ERROR)

消息文本: 许可证已过期 (License expired)

消息说明: 许可证已过期

本地目标消息格式: <timestamp> <seq_num> 35035 ERROR Licensing: License expired, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 35035 ERROR Licensing: License expired, <log details>

- 消息代码: 35036

严重性: 信息 (INFO)

消息文本: 90 天内许可证到期 (License expiring Within 90 Days)

消息说明: 90 天内许可证到期

本地目标消息格式: <timestamp> <seq_num> 35036 INFO Licensing: License expiring Within 90 Days, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 35036 INFO Licensing: License expiring Within 90 Days, <log details>

- 消息代码: 35037

严重性: 警告 (WARN)

消息文本: 60 天内许可证到期 (License expiring Within 60 Days)

消息说明: 60 天内许可证到期

本地目标消息格式: <timestamp> <seq_num> 35037 WARN Licensing: License expiring Within 60 Days, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 35037 WARN Licensing: License expiring Within 60 Days, <log details>

- 消息代码: 35038
 - 严重性: 错误 (ERROR)
 - 消息文本: 30 天内许可证到期 (License expiring Within 30 Days)
 - 消息说明: 30 天内许可证到期
 - 本地目标消息格式: <timestamp> <seq_num> 35038 ERROR Licensing: License expiring Within 30 Days, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35038 ERROR Licensing: License expiring Within 30 Days, <log details>

- 消息代码: 35039
 - 严重性: 错误 (ERROR)
 - 消息文本: 许可证已过期 (License expired)
 - 消息说明: 许可证已过期
 - 本地目标消息格式: <timestamp> <seq_num> 35039 ERROR Licensing: License expired, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 35039 ERROR Licensing: License expired, <log details>

- 消息代码: 35040
 - 严重性: 警告 (WARN)
 - 消息文本: 安装的 VM 许可证比部署的 VM 节点少 (Fewer VM licenses installed than VM nodes deployed)
 - 消息说明: 安装的 VM 许可证数量少于部署的 VM 节点数量
 - 本地目标消息格式: <timestamp> <seq_num>35040 WARN Licensing Fewer VM licenses installed than VM nodes deployed, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>35040 WARN Licensing Fewer VM licenses installed than VM nodes deployed, <log details>

- 消息代码: 35041
 - 严重性: 警告 (WARN)
 - 消息文本: 安装的设备管理员许可证比部署的设备管理员节点少 (Fewer Device Admin licenses installed than Device Admin nodes deployed)
 - 消息说明: 安装的设备管理员许可证数量少于部署的设备管理员节点数量
 - 本地目标消息格式: <timestamp> <seq_num>35041 WARN Licensing Fewer Device Admin licenses installed than Device Admin nodes deployed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>35041 WARN Licensing Fewer Device
Admin licenses installed than Device Admin nodes deployed, <log details>

MDM 诊断

- 消息代码: 89200

严重性: 错误 (ERROR)

消息文本: 在移动设备注册请求中遇到无效负载。(Invalid payload encountered in immobile device enrollment request.)

消息说明: 表示注册请求包含无效负载。

本地目标消息格式: <timestamp> <seq_num> 89200 ERROR MDM: Invalid payload encountered in immobile device enrollment request., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89200 ERROR MDM: Invalid payload encountered in immobile device enrollment request., <log details>

- 消息代码: 89201

严重性: 错误 (ERROR)

消息文本: 在移动设备注册请求中遇到无效会话。(Invalid session encountered in mobile device enrollment request.)

消息说明: 表示注册请求包含无效的会话信息。

本地目标消息格式: <timestamp> <seq_num> 89201 ERROR MDM: Invalid session encountered in mobile device enrollment request., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89201 ERROR MDM: Invalid session encountered in mobile device enrollment request., <log details>

- 消息代码: 89202

严重性: 错误 (ERROR)

消息文本: 处理移动设备注册请求时遇到身份验证失败。(Authentication failure encountered while handling mobile device enrollment request.)

消息说明: 表示身份验证失败导致注册请求失败。

本地目标消息格式: <timestamp> <seq_num> 89202 ERROR MDM: Authentication failure encountered while handling mobile device enrollment request., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89202 ERROR MDM: Authentication failure encountered while handling mobile device enrollment request., <log details>

- 消息代码: 89203

严重性: 错误 (ERROR)

消息文本: 处理移动设备注册请求时遇到授权失败。(Authorization failure encountered while handling mobile device enrollment request.)

消息说明: 表示注册请求包含无效的授权信息。

本地目标消息格式: <timestamp> <seq_num> 89203 ERROR MDM: Authorization failure encountered while handling mobile device enrollment request., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89203 ERROR MDM: Authorization failure encountered while handling mobile device enrollment request., <log details>

- 消息代码: 89204

严重性: 错误 (ERROR)

消息文本: 处理移动设备注册请求时遇到授权失败。用户必须在重试注册之前卸载 iOS MDM 配置文件。(Authorization failure encountered while handling mobile device enrollment request. The user must uninstall the iOS MDM profile before retrying the enrollment.)

消息说明: 表示注册请求包含无效的授权信息。用户必须在重试注册之前卸载 iOS MDM 配置文件。

本地目标消息格式: <timestamp> <seq_num> 89204 ERROR MDM: Authorization failure encountered while handling mobile device enrollment request. The user must uninstall the iOS MDM profile before retrying the enrollment., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89204 ERROR MDM: Authorization failure encountered while handling mobile device enrollment request. The user must uninstall the iOS MDM profile before retrying the enrollment., <log details>

- 消息代码: 89205

严重性: 错误 (ERROR)

消息文本: 处理移动设备注册请求时遇到内部错误。(Internal error encountered while handling mobile device enrollment request.)

消息说明: 表示 ISE 内部错误导致注册请求失败。

本地目标消息格式: <timestamp> <seq_num> 89205 ERROR MDM: Internal error encountered while handling mobile device enrollment request., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89205 ERROR MDM: Internal error encountered while handling mobile device enrollment request., <log details>

- 消息代码: 89206

严重性: 错误 (ERROR)

消息文本: 移动设备注册尝试已过期。(Mobile device enrollment attempt has expired.)

消息说明：表示未在可接受的时间段内完成注册尝试。

本地目标消息格式：<timestamp> <seq_num> 89206 ERROR MDM: Mobile device enrollment attempt has expired., <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89206 ERROR MDM: Mobile device enrollment attempt has expired., <log details>

- 消息代码：89207

严重性：错误 (ERROR)

消息文本：处理注册请求时遇到不受支持的移动设备平台。(Unsupported mobile device platform encountered while handling enrollment request.)

消息说明：表示移动设备不符合平台版本的最低要求。事件详细信息中提供平台版本。

本地目标消息格式：<timestamp> <seq_num> 89207 ERROR MDM: Unsupported mobile device platform encountered while handling enrollment request., <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89207 ERROR MDM: Unsupported mobile device platform encountered while handling enrollment request., <log details>

- 消息代码：89208

严重性：错误 (ERROR)

消息文本：已超过身份验证最大尝试次数。(Maximum number of authentication attempts has been exceeded.)

消息说明：表示在注册过程中超过了身份验证的最大尝试次数。

本地目标消息格式：<timestamp> <seq_num> 89208 ERROR MDM: Maximum number of authentication attempts has been exceeded., <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89208 ERROR MDM: Maximum number of authentication attempts has been exceeded., <log details>

- 消息代码：89209

严重性：错误 (ERROR)

消息文本：由于没有匹配的 MDM 配置文件，移动设备注册请求失败。(Mobile device enrollment request failed due to no matching MDM profile.)

消息说明：表示没有为此移动设备配置 MDM 配置文件。

本地目标消息格式：<timestamp> <seq_num> 89209 ERROR MDM: Mobile device enrollment request failed due to no matching MDM profile., <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89209 ERROR MDM: Mobile device enrollment request failed due to no matching MDM profile., <log details>

- 消息代码: 89210

严重性: 错误 (ERROR)

消息文本: 由于未配置 MDM 信任锚, 移动设备注册请求失败 (Mobile device enrollment request failed due to unconfigured MDM trust anchor)

消息说明: 表示未配置 MDM 信任锚。设备无法注册。

本地目标消息格式: <timestamp> <seq_num> 89210 ERROR MDM: Mobile device enrollment request failed due to unconfigured MDM trust anchor, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89210 ERROR MDM: Mobile device enrollment request failed due to unconfigured MDM trust anchor, <log details>

- 消息代码: 89211

严重性: 错误 (ERROR)

消息文本: 在移动设备签入请求中遇到无效负载。(Invalid payload encountered in immobile device check-in request.)

消息说明: 表示签入请求包含无效负载。

本地目标消息格式: <timestamp> <seq_num> 89211 ERROR MDM: Invalid payload encountered in immobile device check-in request., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89211 ERROR MDM: Invalid payload encountered in immobile device check-in request., <log details>

- 消息代码: 89212

严重性: 错误 (ERROR)

消息文本: 处理签入请求时遇到不受支持的移动设备平台。(Unsupported mobile device platform encountered while handling check-in request.)

消息说明: 表示移动设备不符合平台版本的最低要求。事件详细信息中提供平台版本。

本地目标消息格式: <timestamp> <seq_num> 89212 ERROR MDM: Unsupported mobile device platform encountered while handling check-in request., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89212 ERROR MDM: Unsupported mobile device platform encountered while handling check-in request., <log details>

- 消息代码: 89213

严重性: 错误 (ERROR)

消息文本: 配置文件签名失败。(Profile signing failed.)

消息说明: 表示通过已配置的配置文件签名证书对配置文件进行加密签名失败。

本地目标消息格式: <timestamp> <seq_num> 89213 ERROR MDM: Profile signing failed., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89213 ERROR MDM: Profile signing failed.,
<log details>

- 消息代码: 89214

严重性: 错误 (ERROR)

消息文本: 配置文件加密失败。(Profile encryption failed.)

消息说明: 表示配置文件的密码加密失败。

本地目标消息格式: <timestamp> <seq_num> 89214 ERROR MDM: Profile encryption failed., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89214 ERROR MDM: Profile encryption failed., <log details>

- 消息代码: 89215

严重性: 错误 (ERROR)

消息文本: 处理配置文件调配请求时遇到无效负载。(Invalid payload encountered while handling profile provisioning request.)

消息说明: 表示由于遇到无效负载, 配置文件调配请求失败。

本地目标消息格式: <timestamp> <seq_num> 89215 ERROR MDM: Invalid payload encountered while handling profile provisioning request., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89215 ERROR MDM: Invalid payload encountered while handling profile provisioning request., <log details>

- 消息代码: 89216

严重性: 错误 (ERROR)

消息文本: 处理配置文件调配请求时遇到授权失败。(Authorization failure encountered while handling profile provisioning request.)

消息说明: 表示授权失败导致配置文件调配请求失败。

本地目标消息格式: <timestamp> <seq_num> 89216 ERROR MDM: Authorization failure encountered while handling profile provisioning request., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 89216 ERROR MDM: Authorization failure encountered while handling profile provisioning request., <log details>

- 消息代码: 89217

严重性: 错误 (ERROR)

消息文本: 处理配置文件调配请求时遇到内部错误。(Internal error encountered while handling profile provisioning request.)

消息说明：表示 ISE 内部错误导致配置文件调配请求失败。

本地目标消息格式：<timestamp> <seq_num> 89217 ERROR MDM: Internal error encountered while handling profile provisioning request., <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89217 ERROR MDM: Internal error encountered while handling profile provisioning request., <log details>

- 消息代码：89218

严重性：错误 (ERROR)

消息文本：由于 MDM 证书配置错误，配置文件签名失败。(Profile signing failed due to misconfiguration of the MDM certificate.)

消息说明：表示 MDM 证书链的配置错误导致配置文件加密签名失败。

本地目标消息格式：<timestamp> <seq_num> 89218 ERROR MDM: Profile signing failed due to misconfiguration of the MDM certificate., <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89218 ERROR MDM: Profile signing failed due to misconfiguration of the MDM certificate., <log details>

- 消息代码：89219

严重性：错误 (ERROR)

消息文本：应用请求超时。(The application request timed out.)

消息说明：表示应用请求超时。

本地目标消息格式：<timestamp> <seq_num> 89219 ERROR MDM: The application request timed out., <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89219 ERROR MDM: The application request timed out., <log details>

- 消息代码：89220

严重性：错误 (ERROR)

消息文本：处理应用请求时遇到内部错误。(Internal error encountered while handling application request.)

消息说明：表示 ISE 内部错误导致应用请求失败。

本地目标消息格式：<timestamp> <seq_num> 89220 ERROR MDM: Internal error encountered while handling application request., <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89220 ERROR MDM: Internal error encountered while handling application request., <log details>

- 消息代码：89221

严重性: 错误 (ERROR)

消息文本: 配置文件请求超时 (The profile request timed out)

消息说明: 表示配置文件请求超时

本地目标消息格式: <timestamp> <seq_num> 89221 ERROR MDM: The profile request timed out, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89221 ERROR MDM: The profile request timed out, <log details>

• 消息代码: 89222

严重性: 错误 (ERROR)

消息文本: 超过令牌重置最大次数 (Maximum number of token resets exceeded)

消息说明: 表示用户已经超过令牌重置尝试的最大次数, 他们需要等待一段时间才能再次重置令牌

本地目标消息格式: <timestamp> <seq_num> 89222 ERROR MDM: Maximum number of token resets exceeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89222 ERROR MDM: Maximum number of token resets exceeded, <log details>

• 消息代码: 89223

严重性: 错误 (ERROR)

消息文本: 无法发送令牌 (Failed to send token)

消息说明: 表示无法使用配置的 SMS 或电子邮件信息向用户发送令牌

本地目标消息格式: <timestamp> <seq_num> 89223 ERROR MDM: Failed to send token, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89223 ERROR MDM: Failed to send token, <log details>

• 消息代码: 89224

严重性: 错误 (ERROR)

消息文本: 令牌配置不完整 (Token configurations are incomplete)

消息说明: 表示令牌配置不完整。请确保已为用户配置 SMS 或电子邮件信息

本地目标消息格式: <timestamp> <seq_num> 89224 ERROR MDM: Token configurations are incomplete, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 89224 ERROR MDM: Token configurations are incomplete, <log details>

我的设备

- 消息代码: 88000

严重性: 信息 (INFO)

消息文本: 已成功添加设备 (终端) (Successfully added a device (endpoint))

消息说明: 已成功添加设备 (终端)

本地目标消息格式: <timestamp> <seq_num> 88000 INFO MyDevices: Successfully added a device (endpoint), <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 88000 INFO MyDevices: Successfully added a device (endpoint), <log details>

- 消息代码: 88001

严重性: 错误 (ERROR)

消息文本: 无法添加设备 (终端) (Failed to added a device (endpoint))

消息说明: 请验证 MAC 地址格式是否有效以及是否尚未注册 MAC 地址

本地目标消息格式: <timestamp> <seq_num> 88001 ERROR MyDevices: Failed to added a device (endpoint), <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 88001 ERROR MyDevices: Failed to added a device (endpoint), <log details>

- 消息代码: 88002

严重性: 信息 (INFO)

消息文本: 已成功修改设备 (终端) (Successfully modified the device (endpoint))

消息说明: 已成功修改设备 (终端)

本地目标消息格式: <timestamp> <seq_num> 88002 INFO MyDevices: Successfully modified the device (endpoint), <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 88002 INFO MyDevices: Successfully modified the device (endpoint), <log details>

- 消息代码: 88003

严重性: 错误 (ERROR)

消息文本: 无法修改设备 (终端) (Failed to modify the device (endpoint))

消息说明: 终端可能不存在或与服务器/数据库的通信出现错误。请与您的管理员联系

本地目标消息格式: <timestamp> <seq_num> 88003 ERROR MyDevices: Failed to modify the device (endpoint), <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 88003 ERROR MyDevices: Failed to modify the device (endpoint), <log details>

- 消息代码: 88004

严重性: 信息 (INFO)

消息文本: 已成功删除设备 (终端) (Successfully deleted the device (endpoint))

消息说明: 已成功删除设备 (终端)

本地目标消息格式: <timestamp> <seq_num> 88004 INFO MyDevices: Successfully deleted the device (endpoint), <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 88004 INFO MyDevices: Successfully deleted the device (endpoint), <log details>

- 消息代码: 88005

严重性: 错误 (ERROR)

消息文本: 无法删除设备 (终端) (Failed to delete the device (endpoint))

消息说明: 终端可能不存在或与服务器/数据库的通信出现错误。请与您的管理员联系

本地目标消息格式: <timestamp> <seq_num> 88005 ERROR MyDevices: Failed to delete the device (endpoint), <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 88005 ERROR MyDevices: Failed to delete the device (endpoint), <log details>

- 消息代码: 88006

严重性: 信息 (INFO)

消息文本: 已成功将设备加入黑名单 (终端) (Successfully blacklisted the device (endpoint))

消息说明: 已成功将设备加入黑名单 (终端)

本地目标消息格式: <timestamp> <seq_num> 88006 INFO MyDevices: Successfully blacklisted the device (endpoint), <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 88006 INFO MyDevices: Successfully blacklisted the device (endpoint), <log details>

- 消息代码: 88007

严重性: 错误 (ERROR)

消息文本: 无法将设备加入黑名单 (终端) (Failed to blacklist the device (endpoint))

消息说明：终端可能不存在或与服务器/数据库的通信出现错误。请与您的管理员联系

本地目标消息格式：<timestamp> <seq_num> 88007 ERROR MyDevices: Failed to blacklist the device (endpoint), <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 88007 ERROR MyDevices: Failed to blacklist the device (endpoint), <log details>

- 消息代码：88008

严重性：信息 (INFO)

消息文本：已成功恢复设备（终端）(Successfully reinstated the device (endpoint))

消息说明：已成功恢复设备（终端）

本地目标消息格式：<timestamp> <seq_num> 88008 INFO MyDevices: Successfully reinstated the device (endpoint), <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 88008 INFO MyDevices: Successfully reinstated the device (endpoint), <log details>

- 消息代码：88009

严重性：错误 (ERROR)

消息文本：无法恢复设备（终端）(Failed to reinstate the device (endpoint))

消息说明：终端可能不存在或与服务器/数据库的通信出现错误。请与您的管理员联系

本地目标消息格式：<timestamp> <seq_num> 88009 ERROR MyDevices: Failed to reinstate the device (endpoint), <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 88009 ERROR MyDevices: Failed to reinstate the device (endpoint), <log details>

- 消息代码：88010

严重性：信息 (INFO)

消息文本：已成功注册/调配设备（终端）(Successfully registered/provisioned the device (endpoint))

消息说明：已成功注册/调配设备（终端）

本地目标消息格式：<timestamp> <seq_num> 88010 INFO MyDevices: Successfully registered/provisioned the device (endpoint), <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 88010 INFO MyDevices: Successfully registered/provisioned the device (endpoint), <log details>

- 消息代码：88011

严重性：错误 (ERROR)

消息文本: 无法注册/调配设备 (终端) (Failed to register/provision the device (endpoint))

消息说明: 请与管理员联系

本地目标消息格式: <timestamp> <seq_num> 88011 ERROR MyDevices: Failed to register/provision the device (endpoint), <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 88011 ERROR MyDevices: Failed to register/provision the device (endpoint), <log details>

- 消息代码: 88012

严重性: 信息 (INFO)

消息文本: 已成功执行 CoA 终止 (Successfully performed a CoA termination)

消息说明: 已成功执行 CoA 终止

本地目标消息格式: <timestamp> <seq_num> 88012 INFO MyDevices: Successfully performed a CoA termination, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 88012 INFO MyDevices: Successfully performed a CoA termination, <log details>

- 消息代码: 88013

严重性: 错误 (ERROR)

消息文本: 无法执行 CoA 终止 (Failed to perform a CoA termination)

消息说明: 请确保 NAD 已配置为在向 ISE 发出 RADIUS access-request 时发送客户端 MAC 地址。

本地目标消息格式: <timestamp> <seq_num> 88013 ERROR MyDevices: Failed to perform a CoA termination, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 88013 ERROR MyDevices: Failed to perform a CoA termination, <log details>

- 消息代码: 88014

严重性: 信息 (INFO)

消息文本: 已成功执行 CoA 重新身份验证 (Successfully performed a CoA re-authentication)

消息说明: 已成功执行 CoA 重新身份验证

本地目标消息格式: <timestamp> <seq_num> 88014 INFO MyDevices: Successfully performed a CoA re-authentication, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 88014 INFO MyDevices: Successfully performed a CoA re-authentication, <log details>

- 消息代码: 88015
严重性: 错误 (ERROR)
消息文本: 无法执行 CoA 重新身份验证 (Failed to perform a CoA re-authentication)
消息说明: 请与管理员联系
本地目标消息格式: <timestamp> <seq_num> 88015 ERROR MyDevices: Failed to perform a CoA re-authentication, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 88015 ERROR MyDevices: Failed to perform a CoA re-authentication, <log details>

通过身份验证

- 消息代码: 5200
严重性: 通知 (NOTICE)
消息文本: 身份验证成功 (Authentication succeeded)
消息说明: 用户身份验证成功结束
本地目标消息格式: <timestamp> <seq_num> 5200 NOTICE Passed-Authentication: Authentication succeeded, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5200 NOTICE Passed-Authentication: Authentication succeeded, <log details>
- 消息代码: 5201
严重性: 通知 (NOTICE)
消息文本: 身份验证成功 (Authentication succeeded)
消息说明: 用户身份验证成功结束
本地目标消息格式: <timestamp> <seq_num> 5201 NOTICE Passed-Authentication: Authentication succeeded, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5201 NOTICE Passed-Authentication: Authentication succeeded, <log details>
- 消息代码: 5202
严重性: 通知 (NOTICE)
消息文本: 命令授权成功 (Command Authorization succeeded)
消息说明: 已通过请求的命令授权

本地目标消息格式: <timestamp> <seq_num> 5202 NOTICE Device-Administration: Command Authorization succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5202 NOTICE Device-Administration: Command Authorization succeeded, <log details>

- 消息代码: 5203

严重性: 通知 (NOTICE)

消息文本: 会话授权成功 (Session Authorization succeeded)

消息说明: 已通过请求的会话授权

本地目标消息格式: <timestamp> <seq_num> 5203 NOTICE Device-Administration: Session Authorization succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5203 NOTICE Device-Administration: Session Authorization succeeded, <log details>

- 消息代码: 5204

严重性: 通知 (NOTICE)

消息文本: 更改密码成功 (Change password succeeded)

消息说明: 用户更改密码成功完成

本地目标消息格式: <timestamp> <seq_num> 5204 NOTICE Passed-Authentication: Change password succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5204 NOTICE Passed-Authentication: Change password succeeded, <log details>

- 消息代码: 5205

严重性: 通知 (NOTICE)

消息文本: 动态授权成功 (Dynamic Authorization succeeded)

消息说明: 动态授权成功

本地目标消息格式: <timestamp> <seq_num> 5205 NOTICE Dynamic-Authorization: Dynamic Authorization succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5205 NOTICE Dynamic-Authorization: Dynamic Authorization succeeded, <log details>

- 消息代码: 5206

严重性: 通知 (NOTICE)

消息文本: PAC 已调配 (PAC provisioned)

消息说明: 带内 PAC 调配成功后, 访问被拒绝

本地目标消息格式: <timestamp> <seq_num> 5206 NOTICE Passed-Authentication: PAC provisioned, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5206 NOTICE Passed-Authentication: PAC provisioned, <log details>

- 消息代码: 5231

严重性: 通知 (NOTICE)

消息文本: 已通过访客身份验证 (Guest Authentication Passed)

消息说明: 已通过访客身份验证

本地目标消息格式: <timestamp> <seq_num> 5231 NOTICE Guest: Guest Authentication Passed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5231 NOTICE Guest: Guest Authentication Passed, <log details>

- 消息代码: 5232

严重性: 通知 (NOTICE)

消息文本: DACL 下载成功 (DACL Download Succeeded)

消息说明: DACL 下载成功

本地目标消息格式: <timestamp> <seq_num> 5232 NOTICE Passed-Authentication: DACL Download Succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5232 NOTICE Passed-Authentication: DACL Download Succeeded, <log details>

- 消息代码: 5233

严重性: 通知 (NOTICE)

消息文本: TrustSec 数据下载成功 (TrustSec Data Download Succeeded)

消息说明: TrustSec 数据下载成功

本地目标消息格式: <timestamp> <seq_num> 5233 NOTICE Passed-Authentication: TrustSec Data Download Succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5233 NOTICE Passed-Authentication: TrustSec Data Download Succeeded, <log details>

- 消息代码: 5234

严重性: 通知 (NOTICE)

消息文本: TrustSec 对等策略下载成功 (TrustSec Peer Policy Download Succeeded)

消息说明: TrustSec 对等策略下载成功

本地目标消息格式: <timestamp> <seq_num> 5234 NOTICE Passed-Authentication: TrustSec Peer Policy Download Succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5234 NOTICE Passed-Authentication: TrustSec Peer Policy Download Succeeded, <log details>

- 消息代码: 5236

严重性: 通知 (NOTICE)

消息文本: 仅授权成功 (Authorize-Only succeeded)

消息说明: 仅授权成功结束

本地目标消息格式: <timestamp> <seq_num> 5236 NOTICE Passed-Authentication: Authorize-Only succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5236 NOTICE Passed-Authentication: Authorize-Only succeeded, <log details>

- 消息代码: 5237

严重性: 通知 (NOTICE)

消息文本: 已通过设备注册 Web 身份验证 (Device Registration Web Authentication Passed)

消息说明: 已通过设备注册 Web 身份验证

本地目标消息格式: <timestamp> <seq_num> 5237 NOTICE Guest: Device Registration Web Authentication Passed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5237 NOTICE Guest: Device Registration Web Authentication Passed, <log details>

- 消息代码: 5238

严重性: 警告 (WARN)

消息文本: 已修复终端身份验证问题 (Endpoint authentication problem was fixed)

消息说明: 已修复终端身份验证问题

本地目标消息格式: <timestamp> <seq_num> 5238 WARN RADIUS: Endpoint authentication problem was fixed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 5238 WARN RADIUS: Endpoint authentication problem was fixed, <log details>

- 消息代码: 5239

严重性: 警告 (WARN)

消息文本: 已修复 NAS 问题 (NAS problem was fixed)

消息说明: 已修复 NAS 问题

本地目标消息格式: <timestamp> <seq_num> 5239 WARN RADIUS: NAS problem was fixed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 5239 WARN RADIUS: NAS problem was fixed, <log details>

- 消息代码: 5240

严重性: 信息 (INFO)

消息文本: 已发布先前拒绝的终端以继续身份验证 (Previously rejected endpoint was released to continue authentications)

消息说明: 已发布先前拒绝的终端以继续身份验证

本地目标消息格式: <timestamp> <seq_num> 5240 INFO RADIUS: Previously rejected endpoint was released to continue authentications, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 5240 INFO RADIUS: Previously rejected endpoint was released to continue authentications, <log details>

- 消息代码: 5241

严重性: 通知 (NOTICE)

消息文本: RADIUS DTLS 握手成功 (RADIUS DTLS handshake succeeded)

消息说明: RADIUS DTLS 握手成功

本地目标消息格式: <timestamp> <seq_num> 5241 NOTICE Passed-Authentication: RADIUS DTLS handshake succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 5241 NOTICE Passed-Authentication: RADIUS DTLS handshake succeeded, <log details>

被动 ID

- 消息代码: 90046

严重性: 错误 (ERROR)

消息文本: 内部错误 (Internal error)

消息说明: 内部错误

本地目标消息格式: <timestamp> <seq_num> 90046 ERROR PassiveID: Internal error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90046 ERROR PassiveID: Internal error,
<log details>

- 消息代码: 90047

严重性: 信息 (INFO)

消息文本: PassiveID 现在是主节点 (PassiveID is now the primary node)

消息说明: PassiveID 现在是主节点

本地目标消息格式: <timestamp> <seq_num> 90047 INFO PassiveID: PassiveID is now the primary
node, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90047 INFO PassiveID: PassiveID is now
the primary node, <log details>

- 消息代码: 90048

严重性: 信息 (INFO)

消息文本: PassiveID 不再是主节点 (PassiveID is no longer the primary node)

消息说明: PassiveID 不再是主节点

本地目标消息格式: <timestamp> <seq_num> 90048 INFO PassiveID: PassiveID is no longer the
primary node, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90048 INFO PassiveID: PassiveID is no
longer the primary node, <log details>

- 消息代码: 90049

严重性: 信息 (INFO)

消息文本: 已选择 PassiveID 主节点 (PassiveID primary node was elected)

消息说明: 已选择 PassiveID 主节点

本地目标消息格式: <timestamp> <seq_num> 90049 INFO PassiveID: PassiveID primary node was
elected, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90049 INFO PassiveID: PassiveID primary
node was elected, <log details>

- 消息代码: 90050

严重性: 错误 (ERROR)

消息文本: PassiveID 主节点无响应 (PassiveID primary node is not responsive)

消息说明: PassiveID 主节点无响应

本地目标消息格式: <timestamp> <seq_num> 90050 ERROR PassiveID: PassiveID primary node is not responsive, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90050 ERROR PassiveID: PassiveID primary node is not responsive, <log details>

- 消息代码: 90051

严重性: 信息 (INFO)

消息文本: 服务已启动 (Service started)

消息说明: 服务已启动

本地目标消息格式: <timestamp> <seq_num> 90051 INFO PassiveID: Service started, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90051 INFO PassiveID: Service started, <log details>

- 消息代码: 90052

严重性: 错误 (ERROR)

消息文本: 保持连接在 PassiveID 服务之间不可用 (Keep alive between PassiveID services is unavailable)

消息说明: 保持连接在 PassiveID 服务之间不可用

本地目标消息格式: <timestamp> <seq_num> 90052 ERROR PassiveID: Keep alive between PassiveID services is unavailable, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90052 ERROR PassiveID: Keep alive between PassiveID services is unavailable, <log details>

- 消息代码: 90053

严重性: 错误 (ERROR)

消息文本: 无法解析 PassiveID 服务名称 (Cannot resolve PassiveID service name)

消息说明: 无法解析 PassiveID 服务名称

本地目标消息格式: <timestamp> <seq_num> 90053 ERROR PassiveID: Cannot resolve PassiveID service name, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90053 ERROR PassiveID: Cannot resolve PassiveID service name, <log details>

- 消息代码: 90054

严重性: 信息 (INFO)

消息文本: 已设置活动 PassiveID 服务 (Active PassiveID service is set)

消息说明: 已设置活动 PassiveID 服务

本地目标消息格式: <timestamp> <seq_num> 90054 INFO PassiveID: Active PassiveID service is set, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90054 INFO PassiveID: Active PassiveID service is set, <log details>

- 消息代码: 90055

严重性: 信息 (INFO)

消息文本: 已设置备用 PassiveID 服务 (Standby PassiveID service is set)

消息说明: 已设置备用 PassiveID 服务

本地目标消息格式: <timestamp> <seq_num> 90055 INFO PassiveID: Standby PassiveID service is set, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90055 INFO PassiveID: Standby PassiveID service is set, <log details>

- 消息代码: 90056

严重性: 错误 (ERROR)

消息文本: 服务无法应用配置, 服务不可用 (Service cannot apply configuration, service is unavailable)

消息说明: 服务无法应用配置, 服务不可用

本地目标消息格式: <timestamp> <seq_num> 90056 ERROR PassiveID: Service cannot apply configuration, service is unavailable, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90056 ERROR PassiveID: Service cannot apply configuration, service is unavailable, <log details>

- 消息代码: 90057

严重性: 信息 (INFO)

消息文本: 服务已应用配置 (Service applied configuration)

消息说明: 服务已应用配置

本地目标消息格式: <timestamp> <seq_num> 90057 INFO PassiveID: Service applied configuration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90057 INFO PassiveID: Service applied configuration, <log details>

- 消息代码: 90058

严重性: 错误 (ERROR)

消息文本: 无法解析主机名 (Cannot resolve hostname)

消息说明: 无法解析主机名

本地目标消息格式: <timestamp> <seq_num> 90058 ERROR PassiveID: Cannot resolve hostname, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90058 ERROR PassiveID: Cannot resolve hostname, <log details>

- 消息代码: 90059

严重性: 错误 (ERROR)

消息文本: 无法获取域控制器 Windows 版本 (Cannot get Domain Controller Windows version)

消息说明: 无法获取域控制器 Windows 版本

本地目标消息格式: <timestamp> <seq_num> 90059 ERROR PassiveID: Cannot get Domain Controller Windows version, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90059 ERROR PassiveID: Cannot get Domain Controller Windows version, <log details>

- 消息代码: 90060

严重性: 错误 (ERROR)

消息文本: 不支持域控制器 Windows 版本 (Domain Controller Windows version is unsupported)

消息说明: 不支持域控制器 Windows 版本

本地目标消息格式: <timestamp> <seq_num> 90060 ERROR PassiveID: Domain Controller Windows version is unsupported, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90060 ERROR PassiveID: Domain Controller Windows version is unsupported, <log details>

- 消息代码: 90061

严重性: 错误 (ERROR)

消息文本: 无法获取域控制器 NetBIOS (Cannot get Domain Controller NetBIOS)

消息说明: 无法获取域控制器 NetBIOS

本地目标消息格式: <timestamp> <seq_num> 90061 ERROR PassiveID: Cannot get Domain Controller NetBIOS, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90061 ERROR PassiveID: Cannot get Domain Controller NetBIOS, <log details>

- 消息代码: 90062

严重性: 错误 (ERROR)

消息文本: 无法连接到域控制器 (Cannot connect to Domain Controller)

消息说明: 无法连接到域控制器

本地目标消息格式: <timestamp> <seq_num> 90062 ERROR PassiveID: Cannot connect to Domain Controller, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90062 ERROR PassiveID: Cannot connect to Domain Controller, <log details>

- 消息代码: 90063

严重性: 信息 (INFO)

消息文本: 已成功与域控制器建立连接 (Successfully establish connection to Domain Controller)

消息说明: 已成功与域控制器建立连接

本地目标消息格式: <timestamp> <seq_num> 90063 INFO PassiveID: Successfully establish connection to Domain Controller, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90063 INFO PassiveID: Successfully establish connection to Domain Controller, <log details>

- 消息代码: 90064

严重性: 错误 (ERROR)

消息文本: 无法获取历史登录事件 (Cannot get history login events)

消息说明: 无法获取历史登录事件

本地目标消息格式: <timestamp> <seq_num> 90064 ERROR PassiveID: Cannot get history login events, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90064 ERROR PassiveID: Cannot get history login events, <log details>

- 消息代码: 90065

严重性: 调试 (DEBUG)

消息文本: 已收到历史登录事件 (Received history login events)

消息说明: 已收到历史登录事件

本地目标消息格式: <timestamp> <seq_num> 90065 DEBUG PassiveID: Received history login events, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90065 DEBUG PassiveID: Received history login events, <log details>

- 消息代码: 90066
 - 严重性: 错误 (ERROR)
 - 消息文本: 已断开与域控制器的连接 (Lost connection with Domain Controller)
 - 消息说明: 已断开与域控制器的连接
 - 本地目标消息格式: <timestamp> <seq_num> 90066 ERROR PassiveID: Lost connection with Domain Controller, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90066 ERROR PassiveID: Lost connection with Domain Controller, <log details>

- 消息代码: 90067
 - 严重性: 调试 (DEBUG)
 - 消息文本: 已接收登录事件 (Received login event)
 - 消息说明: 已接收登录事件
 - 本地目标消息格式: <timestamp> <seq_num> 90067 DEBUG PassiveID: Received login event, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90067 DEBUG PassiveID: Received login event, <log details>

- 消息代码: 90068
 - 严重性: 调试 (DEBUG)
 - 消息文本: 已接收计算机登录事件 (Received machine login event)
 - 消息说明: 已接收计算机登录事件
 - 本地目标消息格式: <timestamp> <seq_num> 90068 DEBUG PassiveID: Received machine login event, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90068 DEBUG PassiveID: Received machine login event, <log details>

- 消息代码: 90069
 - 严重性: 调试 (DEBUG)
 - 消息文本: 已替换本地 IP (Replaced local IP)
 - 消息说明: 已替换本地 IP
 - 本地目标消息格式: <timestamp> <seq_num> 90069 DEBUG PassiveID: Replaced local IP, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90069 DEBUG PassiveID: Replaced local
IP, <log details>

- 消息代码: 90070

严重性: 警告 (WARN)

消息文本: 已接收不正确的登录事件 (Received incorrect login event)

消息说明: 已接收不正确的登录事件

本地目标消息格式: <timestamp> <seq_num> 90070 WARN PassiveID: Received incorrect login
event, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90070 WARN PassiveID: Received incorrect
login event, <log details>

- 消息代码: 90071

严重性: 警告 (WARN)

消息文本: 已接收不受支持的登录事件 (Received unsupported login event)

消息说明: 已接收不受支持的登录事件

本地目标消息格式: <timestamp> <seq_num> 90071 WARN PassiveID: Received unsupported login
event, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90071 WARN PassiveID: Received
unsupported login event, <log details>

- 消息代码: 90072

严重性: 调试 (DEBUG)

消息文本: 已过滤登录事件 (Filtered login event)

消息说明: 已过滤登录事件

本地目标消息格式: <timestamp> <seq_num> 90072 DEBUG PassiveID: Filtered login event, <log
details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90072 DEBUG PassiveID: Filtered login
event, <log details>

- 消息代码: 90073

严重性: 错误 (ERROR)

消息文本: 由于超过存储大小, 已丢弃登录事件 (Login events are being dropped as storage size has
been exceeded)

消息说明: 由于超过存储大小, 已丢弃登录事件

本地目标消息格式: <timestamp> <seq_num> 90073 ERROR PassiveID: Login events are being dropped as storage size has been exceeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90073 ERROR PassiveID: Login events are being dropped as storage size has been exceeded, <log details>

- 消息代码: 90074

严重性: 调试 (DEBUG)

消息文本: 已将登录事件转发到会话目录 (Forwarded login event to session directory)

消息说明: 已将登录事件转发到会话目录

本地目标消息格式: <timestamp> <seq_num> 90074 DEBUG PassiveID: Forwarded login event to session directory, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90074 DEBUG PassiveID: Forwarded login event to session directory, <log details>

- 消息代码: 90075

严重性: 错误 (ERROR)

消息文本: 无法将登录事件转发到会话目录 (Cannot forward login event to session directory)

消息说明: 无法将登录事件转发到会话目录

本地目标消息格式: <timestamp> <seq_num> 90075 ERROR PassiveID: Cannot forward login event to session directory, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90075 ERROR PassiveID: Cannot forward login event to session directory, <log details>

- 消息代码: 90076

严重性: 信息 (INFO)

消息文本: 在过去 24 小时内处理的事件数量 (The number of events handled in the last 24 hours)

消息说明: 在过去 24 小时内处理的事件数量

本地目标消息格式: <timestamp> <seq_num> 90076 INFO PassiveID: The number of events handled in the last 24 hours, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90076 INFO PassiveID: The number of events handled in the last 24 hours, <log details>

- 消息代码: 90077

严重性: 调试 (DEBUG)

消息文本: 在前一小时内处理的事件数量 (The number of events handled in the last hour)

消息说明：在前一小时内处理的事件数量

本地目标消息格式：<timestamp> <seq_num> 90077 DEBUG PassiveID: The number of events handled in the last hour, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90077 DEBUG PassiveID: The number of events handled in the last hour, <log details>

- 消息代码：90078

严重性：信息 (INFO)

消息文本：已关闭与域控制器的连接 (Closed connection to Domain Controller)

消息说明：已关闭与域控制器的连接

本地目标消息格式：<timestamp> <seq_num> 90078 INFO PassiveID: Closed connection to Domain Controller, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90078 INFO PassiveID: Closed connection to Domain Controller, <log details>

- 消息代码：90079

严重性：信息 (INFO)

消息文本：服务关闭 (Service shutdown)

消息说明：服务关闭

本地目标消息格式：<timestamp> <seq_num> 90079 INFO PassiveID: Service shutdown, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90079 INFO PassiveID: Service shutdown, <log details>

- 消息代码：90080

严重性：通知 (NOTICE)

消息文本：PassiveID 服务已收集详细信息 (PassiveID service collected details)

消息说明：PassiveID 服务已收集详细信息

本地目标消息格式：<timestamp> <seq_num> 90080 NOTICE PassiveID: PassiveID service collected details, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90080 NOTICE PassiveID: PassiveID service collected details, <log details>

- 消息代码：90081

严重性：错误 (ERROR)

消息文本: 无法启动 REST 服务器 (Failed to start REST server)

消息说明: 无法启动 REST 服务器

本地目标消息格式: <timestamp> <seq_num> 90081 ERROR PassiveID: Failed to start REST server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90081 ERROR PassiveID: Failed to start REST server, <log details>

- 消息代码: 90082

严重性: 错误 (ERROR)

消息文本: 无法打开系统日志端口 (Failed to open syslog port)

消息说明: 无法打开系统日志端口

本地目标消息格式: <timestamp> <seq_num> 90082 ERROR PassiveID: Failed to open syslog port, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90082 ERROR PassiveID: Failed to open syslog port, <log details>

- 消息代码: 90083

严重性: 通知 (NOTICE)

消息文本: 已将注销事件转发到会话目录 (Forwarded logout event to session directory)

消息说明: 已将注销事件转发到会话目录

本地目标消息格式: <timestamp> <seq_num> 90083 NOTICE PassiveID: Forwarded logout event to session directory, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90083 NOTICE PassiveID: Forwarded logout event to session directory, <log details>

- 消息代码: 90084

严重性: 信息 (INFO)

消息文本: 终端探测器服务正在启动 (Endpoint Probe Service is Starting)

消息说明: 终端探测器服务正在启动

本地目标消息格式: <timestamp> <seq_num> 90084 INFO PassiveID: Endpoint Probe Service is Starting, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90084 INFO PassiveID: Endpoint Probe Service is Starting, <log details>

- 消息代码: 90085

严重性: 信息 (INFO)

消息文本: 终端探测器服务已停止 (Endpoint Probe Service Stopped)

消息说明: 终端探测器服务已停止

本地目标消息格式: <timestamp> <seq_num> 90085 INFO PassiveID: Endpoint Probe Service Stopped, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90085 INFO PassiveID: Endpoint Probe Service Stopped, <log details>

- 消息代码: 90086

严重性: 严重 (FATAL)

消息文本: 终端探测器服务意外终止 (Endpoint Probe unexpected service termination)

消息说明: 终端探测器服务已停止

本地目标消息格式: <timestamp> <seq_num> 90086 FATAL PassiveID: Endpoint Probe unexpected service termination, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90086 FATAL PassiveID: Endpoint Probe unexpected service termination, <log details>

- 消息代码: 90088

严重性: 信息 (INFO)

消息文本: 终端探测器配置更新域管理员列表 (Endpoint Probe configuration update domain admin list)

消息说明: 终端探测器只能监控已知的域管理员, 列表已更新

本地目标消息格式: <timestamp> <seq_num> 90088 INFO PassiveID: Endpoint Probe configuration update domain admin list, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90088 INFO PassiveID: Endpoint Probe configuration update domain admin list, <log details>

- 消息代码: 90089

严重性: 调试 (DEBUG)

消息文本: 终端探测器配置更新域信息 (Endpoint Probe configuration update domain information)

消息说明: 终端探测器只能监控已知的域管理员, 列表已更新

本地目标消息格式: <timestamp> <seq_num> 90089 DEBUG PassiveID: Endpoint Probe configuration update domain information, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90089 DEBUG PassiveID: Endpoint Probe configuration update domain information, <log details>

- 消息代码: 90090
严重性: 信息 (INFO)
消息文本: 终端探测器配置已删除域管理员 (Endpoint Probe configuration deleted a domain admin)
消息说明: 终端探测器只能监控已知的域管理员, 列表已更新
本地目标消息格式: <timestamp> <seq_num> 90090 INFO PassiveID: Endpoint Probe configuration deleted a domain admin, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90090 INFO PassiveID: Endpoint Probe configuration deleted a domain admin, <log details>
- 消息代码: 90091
严重性: 信息 (INFO)
消息文本: 终端探测器服务状态已更改为“已禁用”(disabled) (Endpoint Probe service status changed to disabled)
消息说明: 终端探测器服务状态已更改为“已禁用”(disabled)
本地目标消息格式: <timestamp> <seq_num> 90091 INFO PassiveID: Endpoint Probe service status changed to disabled, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90091 INFO PassiveID: Endpoint Probe service status changed to disabled, <log details>
- 消息代码: 90092
严重性: 信息 (INFO)
消息文本: 终端探测器服务状态已更改为“已启用”(enabled) (Endpoint Probe service status changed to enabled)
消息说明: 终端探测器服务状态已更改为“已启用”(enabled)
本地目标消息格式: <timestamp> <seq_num> 90092 INFO PassiveID: Endpoint Probe service status changed to enabled, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90092 INFO PassiveID: Endpoint Probe service status changed to enabled, <log details>
- 消息代码: 90093
严重性: 信息 (INFO)
消息文本: 终端探测器服务状态已更改, 结果出错! (Endpoint Probe service status changed result with ERROR !)
消息说明: 无法更改当前探测器状态, 请查看调试日志以了解详细信息
本地目标消息格式: <timestamp> <seq_num> 90093 INFO PassiveID: Endpoint Probe service status changed result with ERROR !, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90093 INFO PassiveID: Endpoint Probe
service status changed result with ERROR !, <log details>

- 消息代码: 90094

严重性: 信息 (INFO)

消息文本: 终端探测器服务状态已更改, 结果出错! (Endpoint Probe service status changed result with ERROR !)

消息说明: 无法更改当前探测器状态, 请查看调试日志以了解详细信息

本地目标消息格式: <timestamp> <seq_num> 90094 INFO PassiveID: Endpoint Probe service status
changed result with ERROR !, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90094 INFO PassiveID: Endpoint Probe
service status changed result with ERROR !, <log details>

- 消息代码: 90095

严重性: 信息 (INFO)

消息文本: 终端探测器服务状态已更改为“已启用”(enabled)! (Endpoint Probe service status
changed to enabled !)

消息说明: 仅 PIC 模式, 终端探测器设置已设置为“已启用”(Enabled)(PIC mode only, Endpoint
Probe Setting set to Enabled)

本地目标消息格式: <timestamp> <seq_num> 90095 INFO PassiveID: Endpoint Probe service status
changed to enabled !, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90095 INFO PassiveID: Endpoint Probe
service status changed to enabled !, <log details>

- 消息代码: 90096

严重性: 信息 (INFO)

消息文本: 终端探测器服务状态已更改为“已禁用”(disabled)! (Endpoint Probe service status
changed to disabled !)

消息说明: 仅 PIC 模式, 终端探测器设置已设置为“已禁用”(disabled)(PIC mode only, Endpoint
Probe Setting set to disabled)

本地目标消息格式: <timestamp> <seq_num> 90096 INFO PassiveID: Endpoint Probe service status
changed to disabled !, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90096 INFO PassiveID: Endpoint Probe
service status changed to disabled !, <log details>

- 消息代码: 90097

严重性: 错误 (ERROR)

消息文本: 终端探测器配置应用新配置, 结果出错 (Endpoint Probe configuration apply new configuration result with error)

消息说明: 未成功创建终端探测器配置。请尝试重新运行服务以修复问题

本地目标消息格式: <timestamp> <seq_num> 90097 ERROR PassiveID: Endpoint Probe configuration apply new configuration result with error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 90097 ERROR PassiveID: Endpoint Probe configuration apply new configuration result with error, <log details>

- 消息代码: 90098

严重性: 错误 (ERROR)

消息文本: 终端探测器删除配置, 结果出错 (Endpoint Probe delete configuration result with error)

消息说明: 未成功删除终端探测器配置。请尝试重新运行服务以修复问题

本地目标消息格式: <timestamp> <seq_num> 90098 ERROR PassiveID: Endpoint Probe delete configuration result with error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 90098 ERROR PassiveID: Endpoint Probe delete configuration result with error, <log details>

- 消息代码: 90099

严重性: 错误 (ERROR)

消息文本: 终端探测器更新配置, 结果出错 (Endpoint Probe update configuration result with error)

消息说明: 未成功更新终端探测器配置。请尝试重新运行服务以修复问题

本地目标消息格式: <timestamp> <seq_num> 90099 ERROR PassiveID: Endpoint Probe update configuration result with error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 90099 ERROR PassiveID: Endpoint Probe update configuration result with error, <log details>

- 消息代码: 90100

严重性: 错误 (ERROR)

消息文本: 已完成终端探测器手动检查, 但出现错误 (Endpoint Probe Manual Check completed with error)

消息说明: 在终端手动检查请求期间发生意外错误

本地目标消息格式: <timestamp> <seq_num> 90100 ERROR PassiveID: Endpoint Probe Manual Check completed with error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90100 ERROR PassiveID: Endpoint Probe
Manual Check completed with error, <log details>

- 消息代码: 90101

严重性: 信息 (INFO)

消息文本: 正在启动终端探测器手动检查 (Endpoint Probe Manual Check starting)

消息说明: 正在启动手动终端检查

本地目标消息格式: <timestamp> <seq_num> 90101 INFO PassiveID: Endpoint Probe Manual Check
starting, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90101 INFO PassiveID: Endpoint Probe
Manual Check starting, <log details>

- 消息代码: 90102

严重性: 信息 (INFO)

消息文本: 正在启动终端探测器计划程序 (Endpoint Probe Scheduler starting)

消息说明: 正在开始检查终端。正在检索要查询的会话列表

本地目标消息格式: <timestamp> <seq_num> 90102 INFO PassiveID: Endpoint Probe Scheduler
starting, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90102 INFO PassiveID: Endpoint Probe
Scheduler starting, <log details>

- 消息代码: 90103

严重性: 调试 (DEBUG)

消息文本: 终端探测器完成获取终端列表以验证当前登录身份 (Endpoint Probe complete fetching
endpoint list to verify current login identity)

消息说明: 已检索要查询的终端列表

本地目标消息格式: <timestamp> <seq_num> 90103 DEBUG PassiveID: Endpoint Probe complete
fetching endpoint list to verify current login identity, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90103 DEBUG PassiveID: Endpoint Probe
complete fetching endpoint list to verify current login identity, <log details>

- 消息代码: 90104

严重性: 信息 (INFO)

消息文本: 已成功完成终端探测器监控检查。(Endpoint Probe monitor check completed successfully.)

消息说明: 已完成查询所有终端

本地目标消息格式: <timestamp> <seq_num> 90104 INFO PassiveID: Endpoint Probe monitor check completed successfully., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90104 INFO PassiveID: Endpoint Probe monitor check completed successfully., <log details>

- 消息代码: 90105

严重性: 错误 (ERROR)

消息文本: 已完成终端探测器监控检查, 但出现错误 (Endpoint Probe monitor check completed with ERROR)

消息说明: 未成功完成终端检查

本地目标消息格式: <timestamp> <seq_num> 90105 ERROR PassiveID: Endpoint Probe monitor check completed with ERROR, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90105 ERROR PassiveID: Endpoint Probe monitor check completed with ERROR, <log details>

- 消息代码: 90106

严重性: 调试 (DEBUG)

消息文本: 正在启动终端探测器计划程序管理器 (Endpoint Probe Scheduler Manager Starting)

消息说明: 正在设置探测器以定期检查终端

本地目标消息格式: <timestamp> <seq_num> 90106 DEBUG PassiveID: Endpoint Probe Scheduler Manager Starting, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90106 DEBUG PassiveID: Endpoint Probe Scheduler Manager Starting, <log details>

- 消息代码: 90107

严重性: 调试 (DEBUG)

消息文本: 已取消终端探测器计划程序管理器 (Endpoint Probe Scheduler Manager canceled)

消息说明: 已停止查询新终端

本地目标消息格式: <timestamp> <seq_num> 90107 DEBUG PassiveID: Endpoint Probe Scheduler Manager canceled, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90107 DEBUG PassiveID: Endpoint Probe Scheduler Manager canceled, <log details>

- 消息代码: 90108

严重性: 调试 (DEBUG)

消息文本: 终端探测器正在终端上启用 WMI (Endpoint Probe enabling WMI on Endpoint)

消息说明: WMI 服务未在终端上启用, 已为进一步检查而启用

本地目标消息格式: <timestamp> <seq_num> 90108 DEBUG PassiveID: Endpoint Probe enabling WMI on Endpoint, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90108 DEBUG PassiveID: Endpoint Probe enabling WMI on Endpoint, <log details>

- 消息代码: 90109

严重性: 调试 (DEBUG)

消息文本: 终端探测器无法在终端上启用 WMI (Endpoint Probe failed to enable WMI on Endpoint)

消息说明: 无法在终端上启用 WMI。请验证 Active Directory 配置凭证

本地目标消息格式: <timestamp> <seq_num> 90109 DEBUG PassiveID: Endpoint Probe failed to enable WMI on Endpoint, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90109 DEBUG PassiveID: Endpoint Probe failed to enable WMI on Endpoint, <log details>

- 消息代码: 90110

严重性: 调试 (DEBUG)

消息文本: 终端探测器正在终端上启用 WMI (Endpoint Probe enabling WMI on Endpoint)

消息说明: WMI 服务未在终端上启用, 将进行设置以供进一步检查。

本地目标消息格式: <timestamp> <seq_num> 90110 DEBUG PassiveID: Endpoint Probe enabling WMI on Endpoint, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90110 DEBUG PassiveID: Endpoint Probe enabling WMI on Endpoint, <log details>

- 消息代码: 90111

严重性: 调试 (DEBUG)

消息文本: 终端域管理员凭证对于提供的域未知 (Endpoint domain admin credentials are not known for provided DOMAIN)

消息说明: 检查您的 PassiveID Active Directory 配置, 这是否是已知域?

本地目标消息格式: <timestamp> <seq_num> 90111 DEBUG PassiveID: Endpoint domain admin credentials are not known for provided DOMAIN, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90111 DEBUG PassiveID: Endpoint domain admin credentials are not known for provided DOMAIN, <log details>

- 消息代码: 90112
 - 严重性: 调试 (DEBUG)
 - 消息文本: 终端探测器检查, 结果为用户仍处于活动状态 (Endpoint probe check result with user is still active)
 - 消息说明: 当前已知用户仍处于登录状态
 - 本地目标消息格式: <timestamp> <seq_num> 90112 DEBUG PassiveID: Endpoint probe check result with user is still active, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90112 DEBUG PassiveID: Endpoint probe check result with user is still active, <log details>

- 消息代码: 90113
 - 严重性: 调试 (DEBUG)
 - 消息文本: 终端探测器检查, 结果为用户仍处于活动状态 (Endpoint probe check result with user is still active)
 - 消息说明: 当前已知用户不再处于登录状态。正在删除会话
 - 本地目标消息格式: <timestamp> <seq_num> 90113 DEBUG PassiveID: Endpoint probe check result with user is still active, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90113 DEBUG PassiveID: Endpoint probe check result with user is still active, <log details>

- 消息代码: 90114
 - 严重性: 调试 (DEBUG)
 - 消息文本: 终端探测器检查, 结果为无法访问终端 (Endpoint probe check result with unreachable endpoint)
 - 消息说明: 无法访问终端。请验证与终端的连接
 - 本地目标消息格式: <timestamp> <seq_num> 90114 DEBUG PassiveID: Endpoint probe check result with unreachable endpoint, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90114 DEBUG PassiveID: Endpoint probe check result with unreachable endpoint, <log details>

- 消息代码: 90115
 - 严重性: 警告 (WARN)
 - 消息文本: 终端探测器: DNS 反向查找失败。(Endpoint Probe : DNS reverse lookup failed.)
 - 消息说明: DNS 反向查找对于成功监控终端是必需的
 - 本地目标消息格式: <timestamp> <seq_num> 90115 WARN PassiveID: Endpoint Probe : DNS reverse lookup failed ., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90115 WARN PassiveID: Endpoint Probe
: DNS reverse lookup failed ., <log details>

- 消息代码: 90116

严重性: 信息 (INFO)

消息文本: 终端探测器配置中要监控的终端网络子网列表 (Endpoint Probe configuration list of endpoint network subnet to monitor)

消息说明: 此节点将仅监控与其中一个已配置子网匹配的终端

本地目标消息格式: <timestamp> <seq_num> 90116 INFO PassiveID: Endpoint Probe configuration list of endpoint network subnet to monitor, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90116 INFO PassiveID: Endpoint Probe configuration list of endpoint network subnet to monitor, <log details>

- 消息代码: 90117

严重性: 调试 (DEBUG)

消息文本: 终端探测器会话总数需要有效登录用户 (Endpoint Probe Total number of session need valid login user)

消息说明: DNS 反向查找对于成功监控终端登录用户是必需的。

本地目标消息格式: <timestamp> <seq_num> 90117 DEBUG PassiveID: Endpoint Probe Total number of session need valid login user, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90117 DEBUG PassiveID: Endpoint Probe Total number of session need valid login user, <log details>

- 消息代码: 90118

严重性: 严重 (FATAL)

消息文本: 在系统日志探测器启动期间发生严重错误 (Fatal error occurred during SYSLOG probe startup)

消息说明: 在系统日志探测器启动期间发生严重错误

本地目标消息格式: <timestamp> <seq_num> 90118 FATAL PassiveID: Fatal error occurred during SYSLOG probe startup, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90118 FATAL PassiveID: Fatal error occurred during SYSLOG probe startup, <log details>

- 消息代码: 90119

严重性: 信息 (INFO)

消息文本: 开始侦听 tcp 端口 (Start listening to tcp port)

消息说明: 开始侦听 tcp 端口

本地目标消息格式: <timestamp> <seq_num> 90119 INFO PassiveID: Start listening to tcp port, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90119 INFO PassiveID: Start listening to tcp port, <log details>

- 消息代码: 90120

严重性: 信息 (INFO)

消息文本: 开始侦听 udp 端口 (Start listening to udp port)

消息说明: 开始侦听 udp 端口

本地目标消息格式: <timestamp> <seq_num> 90120 INFO PassiveID: Start listening to udp port, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90120 INFO PassiveID: Start listening to udp port, <log details>

- 消息代码: 90121

严重性: 信息 (INFO)

消息文本: 已应用主机名模板 (Applied template for hostname)

消息说明: 已应用主机名模板

本地目标消息格式: <timestamp> <seq_num> 90121 INFO PassiveID: Applied template for hostname, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90121 INFO PassiveID: Applied template for hostname, <log details>

- 消息代码: 90122

严重性: 错误 (ERROR)

消息文本: 对于系统日志客户端的 DNS 解析失败, 无法解析来自此客户端的消息 (DNS resolution failed for syslog client, Will not parse messages from this client)

消息说明: 对于系统日志客户端的 DNS 解析失败, 无法解析来自此客户端的消息, 请检查 DNS 能否将 IP 解析为主机名

本地目标消息格式: <timestamp> <seq_num> 90122 ERROR PassiveID: DNS resolution failed for syslog client, Will not parse messages from this client, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90122 ERROR PassiveID: DNS resolution failed for syslog client, Will not parse messages from this client, <log details>

- 消息代码: 90123

严重性: 调试 (DEBUG)

消息文本: 接收来自未知客户端的消息, 正在丢弃消息 (Receive message from unkown client, Dropping message)

消息说明: 接收来自未知客户端的消息, 正在丢弃消息

本地目标消息格式: <timestamp> <seq_num> 90123 DEBUG PassiveID: Receive message from unkown client, Dropping message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90123 DEBUG PassiveID: Receive message from unkown client, Dropping message, <log details>

- 消息代码: 90124

严重性: 调试 (DEBUG)

消息文本: 接收未知系统日志格式消息 (Receive unkown syslog format message)

消息说明: 接收未知系统日志格式消息

本地目标消息格式: <timestamp> <seq_num> 90124 DEBUG PassiveID: Receive unkown syslog format message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90124 DEBUG PassiveID: Receive unkown syslog format message, <log details>

- 消息代码: 90125

严重性: 警告 (WARN)

消息文本: 在 ISE/ACS 系统日志消息中找不到会话 ID (Couldn't find session ID in ISE/ACS syslog message)

消息说明: 在 ISE/ACS 系统日志消息中找不到会话 ID

本地目标消息格式: <timestamp> <seq_num> 90125 WARN PassiveID: Couldn't find session ID in ISE/ACS syslog message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90125 WARN PassiveID: Couldn't find session ID in ISE/ACS syslog message, <log details>

- 消息代码: 90126

严重性: 警告 (WARN)

消息文本: 在 ISE/ACS 系统日志消息中找不到 IP 地址 (Couldn't find IP address in ISE/ACS syslog message)

消息说明: 在 ISE/ACS 系统日志消息中找不到 IP 地址

本地目标消息格式: <timestamp> <seq_num> 90126 WARN PassiveID: Couldn't find IP address in ISE/ACS syslog message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90126 WARN PassiveID: Couldn't find IP
address in ISE/ACS syslog message, <log details>

- 消息代码: 90127

严重性: 警告 (WARN)

消息文本: 在没有通过身份验证的情况下接收 ISE/ACS 启动/更新 RADIUS 消息, 无法创建
PassiveID 会话 (Receive ISE/ACS start/update radius message without pass authentication, Can't create
PassiveID session)

消息说明: 在没有通过身份验证的情况下接收 ISE/ACS 启动/更新 RADIUS 消息, 无法创建
PassiveID 会话

本地目标消息格式: <timestamp> <seq_num> 90127 WARN PassiveID: Receive ISE/ACS start/update
radius message without pass authentication, Can't create PassiveID session, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90127 WARN PassiveID: Receive ISE/ACS
start/update radius message without pass authentication, Can't create PassiveID session, <log details>

- 消息代码: 90128

严重性: 错误 (ERROR)

消息文本: 无法应用配置 (Failed to apply configuration)

消息说明: 无法应用配置

本地目标消息格式: <timestamp> <seq_num> 90128 ERROR PassiveID: Failed to apply configuration,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90128 ERROR PassiveID: Failed to apply
configuration, <log details>

- 消息代码: 90129

严重性: 错误 (ERROR)

消息文本: 错误 (Error)

消息说明: 无法将 DHCP 事件发布到 MNT

本地目标消息格式: <timestamp> <seq_num> 90129 ERROR PassiveID: Error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90129 ERROR PassiveID: Error, <log
details>

- 消息代码: 90130

严重性: 错误 (ERROR)

消息文本: 错误 (Error)

消息说明: 无法从 Active Directory 检索广告用户信息

本地目标消息格式: <timestamp> <seq_num> 90130 ERROR PassiveID: Error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90130 ERROR PassiveID: Error, <log details>

- 消息代码: 90131

严重性: 错误 (ERROR)

消息文本: 错误 (Error)

消息说明: 无法将系统日志提供程序主机名解析为 IP 地址

本地目标消息格式: <timestamp> <seq_num> 90131 ERROR PassiveID: Error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90131 ERROR PassiveID: Error, <log details>

- 消息代码: 90132

严重性: 调试 (DEBUG)

消息文本: 无法解析系统日志消息 (Could not parse Syslog message)

消息说明: 无法解析系统日志消息

本地目标消息格式: <timestamp> <seq_num> 90132 DEBUG PassiveID: Could not parse Syslog message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90132 DEBUG PassiveID: Could not parse Syslog message, <log details>

- 消息代码: 90133

严重性: 错误 (ERROR)

消息文本: 系统日志消息格式无效 (Invalid Syslog message format)

消息说明: 系统日志消息格式无效

本地目标消息格式: <timestamp> <seq_num> 90133 ERROR PassiveID: Invalid Syslog message format, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90133 ERROR PassiveID: Invalid Syslog message format, <log details>

- 消息代码: 90134

严重性: 错误 (ERROR)

消息文本: 无法解析消息中的系统日志主机名 (Could not parse Syslog hostname from message)

消息说明: 无法解析消息中的系统日志主机名

本地目标消息格式: <timestamp> <seq_num> 90134 ERROR PassiveID: Could not parse Syslog hostname from message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90134 ERROR PassiveID: Could not parse Syslog hostname from message, <log details>

- 消息代码: 90135

严重性: 调试 (DEBUG)

消息文本: 已接收消息 (Message received)

消息说明: 已接收消息

本地目标消息格式: <timestamp> <seq_num> 90135 DEBUG PassiveID: Message received, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90135 DEBUG PassiveID: Message received, <log details>

- 消息代码: 90136

严重性: 警告 (WARN)

消息文本: 系统日志协议服务器出错 (Syslog protocol server error)

消息说明: 接收到错误格式的消息, 已丢弃

本地目标消息格式: <timestamp> <seq_num> 90136 WARN PassiveID: Syslog protocol server error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90136 WARN PassiveID: Syslog protocol server error, <log details>

- 消息代码: 90137

严重性: 通知 (NOTICE)

消息文本: 系统日志侦听程序已启用 (Syslog listener is up)

消息说明: 系统日志侦听程序已启用

本地目标消息格式: <timestamp> <seq_num> 90137 NOTICE PassiveID: Syslog listener is up, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90137 NOTICE PassiveID: Syslog listener is up, <log details>

- 消息代码: 90138

严重性: 通知 (NOTICE)

消息文本: 系统日志侦听程序已关闭 (Syslog listener is down)

消息说明: 系统日志侦听程序已关闭

本地目标消息格式: <timestamp> <seq_num> 90138 NOTICE PassiveID: Syslog listener is down, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90138 NOTICE PassiveID: Syslog listener is down, <log details>

- 消息代码: 90139

严重性: 调试 (DEBUG)

消息文本: 收到身份映射消息, 已丢弃 (Identity Mapping message received, dropped)

消息说明: 收到身份映射消息, 已丢弃

本地目标消息格式: <timestamp> <seq_num> 90139 DEBUG PassiveID: Identity Mapping message received, dropped, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90139 DEBUG PassiveID: Identity Mapping message received, dropped, <log details>

- 消息代码: 90140

严重性: 信息 (INFO)

消息文本: 已解析消息 (Message parsed)

消息说明: 已解析消息

本地目标消息格式: <timestamp> <seq_num> 90140 INFO PassiveID: Message parsed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90140 INFO PassiveID: Message parsed, <log details>

- 消息代码: 90141

严重性: 调试 (DEBUG)

消息文本: 收到的消息不完整, 已丢弃 (Incomplete message received, dropped)

消息说明: 收到的消息不完整, 已丢弃

本地目标消息格式: <timestamp> <seq_num> 90141 DEBUG PassiveID: Incomplete message received, dropped, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90141 DEBUG PassiveID: Incomplete message received, dropped, <log details>

- 消息代码: 90142

严重性: 信息 (INFO)

消息文本: 未找到具有凭证的 Active Directory。终端检查不会运行 (No Active Directory with credentials were found. Endpoint check will not run)

消息说明: 未找到具有凭证的 Active Directory。终端探测不会运行

本地目标消息格式: <timestamp> <seq_num> 90142 INFO PassiveID: No Active Directory with credentials were found. Endpoint check will not run, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90142 INFO PassiveID: No Active Directory with credentials were found. Endpoint check will not run, <log details>

- 消息代码: 90143

严重性: 信息 (INFO)

消息文本: 此 IP 不属于任何已配置子网。终端检查不会运行 (This IP is not part of any configured subnet. Endpoint check will not run)

消息说明: 此 IP 不属于任何已配置子网。终端检查不会运行

本地目标消息格式: <timestamp> <seq_num> 90143 INFO PassiveID: This IP is not part of any configured subnet. Endpoint check will not run, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90143 INFO PassiveID: This IP is not part of any configured subnet. Endpoint check will not run, <log details>

- 消息代码: 90200

严重性: 信息 (INFO)

消息文本: REST 服务器已成功启动。(REST server started successfully.)

消息说明: 正在等待传入请求

本地目标消息格式: <timestamp> <seq_num> 90200 INFO PassiveID: REST server started successfully., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90200 INFO PassiveID: REST server started successfully., <log details>

- 消息代码: 90201

严重性: 信息 (INFO)

消息文本: 已为客户端发布新身份验证令牌。(New authentication token was issued for client.)

消息说明: 令牌将在进一步请求中使用。

本地目标消息格式: <timestamp> <seq_num> 90201 INFO PassiveID: New authentication token was issued for client., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90201 INFO PassiveID: New authentication token was issued for client., <log details>

- 消息代码: 90202

严重性: 错误 (ERROR)

消息文本: 身份验证请求失败 (Authentication request failed)

消息说明: 检查用于初始基本身份验证的凭证

本地目标消息格式: <timestamp> <seq_num> 90202 ERROR PassiveID: Authentication request failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90202 ERROR PassiveID: Authentication request failed, <log details>

- 消息代码: 90203

严重性: 信息 (INFO)

消息文本: 已根据客户端请求撤销令牌。(Token was revoked according to client request.)

消息说明: 将拒绝具有撤销令牌的进一步请求。

本地目标消息格式: <timestamp> <seq_num> 90203 INFO PassiveID: Token was revoked according to client request., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90203 INFO PassiveID: Token was revoked according to client request., <log details>

- 消息代码: 90204

严重性: 错误 (ERROR)

消息文本: 无法将 IP 反向解析为主机名 (Failed to reverse resolve ip to hostname)

消息说明: 无法将 IP 反向解析为主机名, 为 REST 客户端主机配置反向 DNS。

本地目标消息格式: <timestamp> <seq_num> 90204 ERROR PassiveID: Failed to reverse resolve ip to hostname, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 90204 ERROR PassiveID: Failed to reverse resolve ip to hostname, <log details>

- 消息代码: 90205

严重性: 调试 (DEBUG)

消息文本: 已丢弃来自未知客户端的请求。(Request from unknown client was dropped.)

消息说明: 已丢弃来自未知客户端的请求。尝试在 ISE 中配置客户端。

本地目标消息格式: <timestamp> <seq_num> 90205 DEBUG PassiveID: Request from unknown clinet was dropped., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90205 DEBUG PassiveID: Request from unknown clinet was dropped., <log details>

- 消息代码: 90206

严重性: 错误 (ERROR)

消息文本: 由于令牌无效或缺失, 请求遭丢弃。(Request dropped due to invalid or missing token.)

消息说明: 由于令牌无效或缺失, 请求遭丢弃。确保客户端发送有效令牌。

本地目标消息格式: <timestamp> <seq_num> 90206 ERROR PassiveID: Request dropped due to invalid or missing token., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90206 ERROR PassiveID: Request dropped due to invalid or missing token., <log details>

- 消息代码: 90300

严重性: 错误 (ERROR)

消息文本: 探测器未收到代理发出的 keep-alive 信号。(Probe didn't receive keep-alive signal from agent.)

消息说明: 确保代理正常运行。

本地目标消息格式: <timestamp> <seq_num> 90300 ERROR PassiveID: Probe didn't receive keep-alive signal from agent., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90300 ERROR PassiveID: Probe didn't receive keep-alive signal from agent., <log details>

- 消息代码: 90301

严重性: 错误 (ERROR)

消息文本: 探测器收到的客户端状态数量不正确。(Probe received incorrect number of client status.)

消息说明: 检查调试日志以获取更多信息。

本地目标消息格式: <timestamp> <seq_num> 90301 ERROR PassiveID: Probe received incorrect number of client status., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90301 ERROR PassiveID: Probe received incorrect number of client status., <log details>

- 消息代码: 90500

严重性: 通知 (NOTICE)

消息文本: 新身份映射 (New Identity Mapping)

消息说明: 收到 PassiveID 新映射事件

本地目标消息格式: <timestamp> <seq_num> 90500 NOTICE PassiveID: New Identity Mapping, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90500 NOTICE PassiveID: New Identity Mapping, <log details>

- 消息代码: 90501

严重性: 通知 (NOTICE)

消息文本: 更新身份映射 (Update Identity Mapping)

消息说明: 收到 PassiveID 更新映射事件

本地目标消息格式: <timestamp> <seq_num> 90501 NOTICE PassiveID: Update Identity Mapping, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90501 NOTICE PassiveID: Update Identity Mapping, <log details>

- 消息代码: 90502

严重性: 通知 (NOTICE)

消息文本: 删除身份映射 (Remove Identity Mapping)

消息说明: 收到 PassiveID 删除映射事件

本地目标消息格式: <timestamp> <seq_num> 90502 NOTICE PassiveID: Remove Identity Mapping, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 90502 NOTICE PassiveID: Remove Identity Mapping, <log details>

策略诊断

- 消息代码: 15001

严重性: 错误 (ERROR)

消息文本: 适配器必须至少包含一个值 (Adapter must contain at least one value)

消息说明: 这是数据库配置问题

本地目标消息格式: <timestamp> <seq_num> 15001 ERROR Policy: Adapter must contain at least one value, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 15001 ERROR Policy: Adapter must contain at least one value, <log details>

- 消息代码: 15002

严重性: 错误 (ERROR)

消息文本: 配置的运算符与值类型不匹配 (Configured operator failed to match the value type)

消息说明: 这是数据库配置问题, 运算符和值类型不匹配

本地目标消息格式: <timestamp> <seq_num> 15002 ERROR Policy: Configured operator failed to match the value type, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 15002 ERROR Policy: Configured operator failed to match the value type, <log details>

- 消息代码: 15003

严重性: 错误 (ERROR)

消息文本: 数据库配置不正确 (Incorrect database configuration)

消息说明: 数据库配置不正确

本地目标消息格式: <timestamp> <seq_num> 15003 ERROR Policy: Incorrect database configuration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 15003 ERROR Policy: Incorrect database configuration, <log details>

- 消息代码: 15004

严重性: 调试 (DEBUG)

消息文本: 已匹配规则 (Matched rule)

消息说明: 已匹配规则

本地目标消息格式: <timestamp> <seq_num> 15004 DEBUG Policy: Matched rule, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 15004 DEBUG Policy: Matched rule, <log details>

- 消息代码: 15005

严重性: 调试 (DEBUG)

消息文本: 已匹配监控的规则 (Matched monitored rule)

消息说明: 已匹配监控的规则

本地目标消息格式: <timestamp> <seq_num> 15005 DEBUG Policy: Matched monitored rule, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 15005 DEBUG Policy: Matched monitored rule, <log details>

- 消息代码: 15006

严重性: 调试 (DEBUG)

消息文本: 已匹配默认规则 (Matched Default Rule)

消息说明: 已匹配策略默认规则

本地目标消息格式: <timestamp> <seq_num> 15006 DEBUG Policy: Matched Default Rule, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 15006 DEBUG Policy: Matched Default Rule, <log details>

- 消息代码: 15007

严重性: 错误 (ERROR)

消息文本: 策略结果类型不符合预期结果 (Policy result type did not match expected result)

消息说明: 策略结果类型不符合预期结果

本地目标消息格式: <timestamp> <seq_num> 15007 ERROR Policy: Policy result type did not match expected result, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 15007 ERROR Policy: Policy result type did not match expected result, <log details>

- 消息代码: 15008

严重性: 调试 (DEBUG)

消息文本: 正在评估服务选择策略 (Evaluating Service Selection Policy)

消息说明: 正在评估服务选择策略

本地目标消息格式: <timestamp> <seq_num> 15008 DEBUG Policy: Evaluating Service Selection Policy, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 15008 DEBUG Policy: Evaluating Service Selection Policy, <log details>

- 消息代码: 15009

严重性: 调试 (DEBUG)

消息文本: 未配置例外授权策略 (Exception Authorization Policy not configured)

消息说明: 未配置例外授权策略

本地目标消息格式: <timestamp> <seq_num> 15009 DEBUG Policy: Exception Authorization Policy not configured, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15009 DEBUG Policy: Exception Authorization Policy not configured, <log details>

- 消息代码: 15010

严重性: 错误 (ERROR)

消息文本: 未配置身份策略 (Identity policy is not configured)

消息说明: 未配置身份策略。

本地目标消息格式: <timestamp> <seq_num> 15010 ERROR Policy: Identity policy is not configured, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15010 ERROR Policy: Identity policy is not configured, <log details>

- 消息代码: 15011

严重性: 信息 (INFO)

消息文本: 未配置授权策略 (Authorization Policy not configured)

消息说明: 未配置授权策略

本地目标消息格式: <timestamp> <seq_num> 15011 INFO Policy: Authorization Policy not configured, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15011 INFO Policy: Authorization Policy not configured, <log details>

- 消息代码: 15012

严重性: 调试 (DEBUG)

消息文本: 选定的访问服务 (Selected Access Service)

消息说明: 选定的访问服务

本地目标消息格式: <timestamp> <seq_num> 15012 DEBUG Policy: Selected Access Service, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15012 DEBUG Policy: Selected Access Service, <log details>

- 消息代码: 15013

严重性: 调试 (DEBUG)

消息文本: 选定的身份源 (Selected Identity Source)

消息说明: 选定的身份源

本地目标消息格式: <timestamp> <seq_num> 15013 DEBUG Policy: Selected Identity Source, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15013 DEBUG Policy: Selected Identity Source, <log details>

- 消息代码: 15015

严重性: 错误 (ERROR)

消息文本: 找不到 ID 存储区 (Could not find ID Store)

消息说明: 在数据库中找不到 ID 存储区

本地目标消息格式: <timestamp> <seq_num> 15015 ERROR Policy: Could not find ID Store, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15015 ERROR Policy: Could not find ID Store, <log details>

- 消息代码: 15016

严重性: 调试 (DEBUG)

消息文本: 选定的授权配置文件 (Selected Authorization Profile)

消息说明: 选定的授权配置文件

本地目标消息格式: <timestamp> <seq_num> 15016 DEBUG Policy: Selected Authorization Profile, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15016 DEBUG Policy: Selected Authorization Profile, <log details>

- 消息代码: 15017

严重性: 调试 (DEBUG)

消息文本: 选定的 Shell 配置文件 (Selected Shell Profile)

消息说明: 选定的 Shell 配置文件

本地目标消息格式: <timestamp> <seq_num> 15017 DEBUG Policy: Selected Shell Profile, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15017 DEBUG Policy: Selected Shell Profile, <log details>

- 消息代码: 15018

严重性: 调试 (DEBUG)

消息文本: 选定的命令集 (Selected Command Set)

消息说明: 选定的命令集

本地目标消息格式: <timestamp> <seq_num> 15018 DEBUG Policy: Selected Command Set, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15018 DEBUG Policy: Selected Command Set, <log details>

• 消息代码: 15019

严重性: 调试 (DEBUG)

消息文本: 找不到选定的授权配置文件 (Could not find selected Authorization Profiles)

消息说明: 找不到选定的授权配置文件

本地目标消息格式: <timestamp> <seq_num> 15019 DEBUG Policy: Could not find selected Authorization Profiles, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15019 DEBUG Policy: Could not find selected Authorization Profiles, <log details>

• 消息代码: 15020

严重性: 警告 (WARN)

消息文本: 找不到选定的 Shell 配置文件 (Could not find selected Shell Profiles)

消息说明: 找不到选定的 Shell 配置文件

本地目标消息格式: <timestamp> <seq_num> 15020 WARN Policy: Could not find selected Shell Profiles, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15020 WARN Policy: Could not find selected Shell Profiles, <log details>

• 消息代码: 15021

严重性: 错误 (ERROR)

消息文本: 找不到选定的命令集 (Could not find selected Command Set)

消息说明: 找不到选定的命令集

本地目标消息格式: <timestamp> <seq_num> 15021 ERROR Policy: Could not find selected Command Set, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15021 ERROR Policy: Could not find selected Command Set, <log details>

- 消息代码: 15022
 - 严重性: 错误 (ERROR)
 - 消息文本: 找不到选定的访问服务 (Could not find selected Access Service)
 - 消息说明: 找不到选定的访问服务
 - 本地目标消息格式: <timestamp> <seq_num> 15022 ERROR Policy: Could not find selected Access Service, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15022 ERROR Policy: Could not find selected Access Service, <log details>

- 消息代码: 15023
 - 严重性: 调试 (DEBUG)
 - 消息文本: 无法匹配规则 (Could not match rule)
 - 消息说明: 无法匹配规则
 - 本地目标消息格式: <timestamp> <seq_num> 15023 DEBUG Policy: Could not match rule, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15023 DEBUG Policy: Could not match rule, <log details>

- 消息代码: 15024
 - 严重性: 信息 (INFO)
 - 消息文本: 不允许使用 PAP (PAP is not allowed)
 - 消息说明: 不允许使用 PAP
 - 本地目标消息格式: <timestamp> <seq_num> 15024 INFO Policy: PAP is not allowed, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15024 INFO Policy: PAP is not allowed, <log details>

- 消息代码: 15025
 - 严重性: 调试 (DEBUG)
 - 消息文本: 未配置外部策略检查策略 (External Policy Check Policy not configured)
 - 消息说明: 未配置外部策略检查策略
 - 本地目标消息格式: <timestamp> <seq_num> 15025 DEBUG Posture: External Policy Check Policy not configured, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15025 DEBUG Posture: External Policy Check Policy not configured, <log details>

- 消息代码: 15026
严重性: 调试 (DEBUG)
消息文本: 未找到外部策略服务器 (External Policy Server not found)
消息说明: 未找到外部策略服务器
本地目标消息格式: <timestamp> <seq_num> 15026 DEBUG Posture: External Policy Server not found, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 15026 DEBUG Posture: External Policy Server not found, <log details>
- 消息代码: 15027
严重性: 调试 (DEBUG)
消息文本: 已选择外部策略服务器 (External Policy Server selected)
消息说明: 已选择外部策略服务器
本地目标消息格式: <timestamp> <seq_num> 15027 DEBUG Posture: External Policy Server selected, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 15027 DEBUG Posture: External Policy Server selected, <log details>
- 消息代码: 15028
严重性: 调试 (DEBUG)
消息文本: 正在向外部策略服务器发送请求 (Sending request to External Policy Server)
消息说明: 正在向外部策略服务器发送请求
本地目标消息格式: <timestamp> <seq_num> 15028 DEBUG Posture: Sending request to External Policy Server, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 15028 DEBUG Posture: Sending request to External Policy Server, <log details>
- 消息代码: 15029
严重性: 调试 (DEBUG)
消息文本: 无法从外部策略服务器检索属性 (Could not retrieve attributes from External Policy Server)
消息说明: 无法从外部策略服务器检索属性
本地目标消息格式: <timestamp> <seq_num> 15029 DEBUG Posture: Could not retrieve attributes from External Policy Server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 15029 DEBUG Posture: Could not retrieve
attributes from External Policy Server, <log details>

- 消息代码: 15030

严重性: 调试 (DEBUG)

消息文本: 外部策略服务器明显配置不当 (Apparent misconfiguration of External Policy Server)

消息说明: 外部策略服务器明显配置不当

本地目标消息格式: <timestamp> <seq_num> 15030 DEBUG Posture: Apparent misconfiguration of
External Policy Server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 15030 DEBUG Posture: Apparent
misconfiguration of External Policy Server, <log details>

- 消息代码: 15031

严重性: 调试 (DEBUG)

消息文本: 已检索到外部策略属性 (External Policy attributes retrieved)

消息说明: 已检索到外部策略属性

本地目标消息格式: <timestamp> <seq_num> 15031 DEBUG Posture: External Policy attributes
retrieved, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 15031 DEBUG Posture: External Policy
attributes retrieved, <log details>

- 消息代码: 15032

严重性: 调试 (DEBUG)

消息文本: 正在评估外部策略检查策略 (Evaluating External Policy Check Policy)

消息说明: 正在评估外部策略检查策略

本地目标消息格式: <timestamp> <seq_num> 15032 DEBUG Policy: Evaluating External Policy
Check Policy, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 15032 DEBUG Policy: Evaluating External
Policy Check Policy, <log details>

- 消息代码: 15033

严重性: 信息 (INFO)

消息文本: 未配置组映射策略 (Group Mapping Policy not configured)

消息说明: 未配置组映射策略

本地目标消息格式: <timestamp> <seq_num> 15033 INFO Policy: Group Mapping Policy not configured, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15033 INFO Policy: Group Mapping Policy not configured, <log details>

- 消息代码: 15034

严重性: 调试 (DEBUG)

消息文本: 跳过外部策略检查 (Skip External Policy Check)

消息说明: 跳过外部策略检查

本地目标消息格式: <timestamp> <seq_num> 15034 DEBUG Posture: Skip External Policy Check, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15034 DEBUG Posture: Skip External Policy Check, <log details>

- 消息代码: 15035

严重性: 调试 (DEBUG)

消息文本: 正在评估例外授权策略 (Evaluating Exception Authorization Policy)

消息说明: 正在评估例外授权策略

本地目标消息格式: <timestamp> <seq_num> 15035 DEBUG Policy: Evaluating Exception Authorization Policy, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15035 DEBUG Policy: Evaluating Exception Authorization Policy, <log details>

- 消息代码: 15036

严重性: 调试 (DEBUG)

消息文本: 正在评估授权策略 (Evaluating Authorization Policy)

消息说明: 正在评估授权策略

本地目标消息格式: <timestamp> <seq_num> 15036 DEBUG Policy: Evaluating Authorization Policy, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15036 DEBUG Policy: Evaluating Authorization Policy, <log details>

- 消息代码: 15037

严重性: 调试 (DEBUG)

消息文本: 使用之前选定的访问服务 (Using previously selected Access Service)

消息说明：使用之前选定的访问服务

本地目标消息格式：<timestamp> <seq_num> 15037 DEBUG Policy: Using previously selected Access Service, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15037 DEBUG Policy: Using previously selected Access Service, <log details>

- 消息代码：15038

严重性：调试 (DEBUG)

消息文本：由于必要属性缺失或格式错误，正在跳过外部策略 (Skipping External Policy because of missing or malformed required attributes)

消息说明：由于必要属性缺失或格式错误，正在跳过外部策略

本地目标消息格式：<timestamp> <seq_num> 15038 DEBUG Posture: Skipping External Policy because of missing or malformed required attributes, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15038 DEBUG Posture: Skipping External Policy because of missing or malformed required attributes, <log details>

- 消息代码：15039

严重性：信息 (INFO)

消息文本：已根据授权配置文件拒绝 (Rejected per authorization profile)

消息说明：选定的授权配置文件包含 ACCESS_REJECT 属性

本地目标消息格式：<timestamp> <seq_num> 15039 INFO RADIUS: Rejected per authorization profile, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15039 INFO RADIUS: Rejected per authorization profile, <log details>

- 消息代码：15040

严重性：信息 (INFO)

消息文本：证书配置文件中未定义用户名属性 (User name attribute not defined in certificate profile)

消息说明：证书配置文件中未定义用户名属性

本地目标消息格式：<timestamp> <seq_num> 15040 INFO Policy: User name attribute not defined in certificate profile, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15040 INFO Policy: User name attribute not defined in certificate profile, <log details>

- 消息代码：15041

严重性: 调试 (DEBUG)

消息文本: 正在评估身份策略 (Evaluating Identity Policy)

消息说明: 正在评估身份策略

本地目标消息格式: <timestamp> <seq_num> 15041 DEBUG Policy: Evaluating Identity Policy, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 15041 DEBUG Policy: Evaluating Identity Policy, <log details>

- 消息代码: 15042

严重性: 信息 (INFO)

消息文本: 不符合任何规则 (No rule was matched)

消息说明: 接受评估的策略不符合任何规则

本地目标消息格式: <timestamp> <seq_num> 15042 INFO Policy: No rule was matched, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 15042 INFO Policy: No rule was matched, <log details>

- 消息代码: 15043

严重性: 信息 (INFO)

消息文本: 动态属性值不可用 (Dynamic attribute value is unavailable)

消息说明: 动态属性值不可用, 包含该值的引用属性不存在

本地目标消息格式: <timestamp> <seq_num> 15043 INFO Policy: Dynamic attribute value is unavailable, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 15043 INFO Policy: Dynamic attribute value is unavailable, <log details>

- 消息代码: 15044

严重性: 调试 (DEBUG)

消息文本: 正在评估组映射策略 (Evaluating Group Mapping Policy)

消息说明: 正在评估组映射策略

本地目标消息格式: <timestamp> <seq_num> 15044 DEBUG Policy: Evaluating Group Mapping Policy, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 15044 DEBUG Policy: Evaluating Group Mapping Policy, <log details>

- 消息代码: 15045
 - 严重性: 错误 (ERROR)
 - 消息文本: 不允许使用 CHAP (CHAP is not allowed)
 - 消息说明: 不允许使用 CHAP。
 - 本地目标消息格式: <timestamp> <seq_num> 15045 ERROR Policy: CHAP is not allowed, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15045 ERROR Policy: CHAP is not allowed, <log details>

- 消息代码: 15046
 - 严重性: 错误 (ERROR)
 - 消息文本: 允许的协议下禁用 MS-CHAP v1。 (MS-CHAP v1 is disabled under allowed protocols.)
 - 消息说明: 允许的协议下禁用 MS-CHAP v1。
 - 本地目标消息格式: <timestamp> <seq_num> 15046 ERROR Policy: MS-CHAP v1 is disabled under allowed protocols., <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15046 ERROR Policy: MS-CHAP v1 is disabled under allowed protocols., <log details>

- 消息代码: 15047
 - 严重性: 错误 (ERROR)
 - 消息文本: 允许的协议下禁用 MS-CHAP v2。 (MS-CHAP v2 is disabled under allowed protocols.)
 - 消息说明: 允许的协议下禁用 MS-CHAP v2。
 - 本地目标消息格式: <timestamp> <seq_num> 15047 ERROR Policy: MS-CHAP v2 is disabled under allowed protocols., <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15047 ERROR Policy: MS-CHAP v2 is disabled under allowed protocols., <log details>

- 消息代码: 15048
 - 严重性: 调试 (DEBUG)
 - 消息文本: 已查询 PIP (Queried PIP)
 - 消息说明: 策略引擎已针对策略引用的属性查询了 PIP
 - 本地目标消息格式: <timestamp> <seq_num> 15048 DEBUG Policy: Queried PIP, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15048 DEBUG Policy: Queried PIP, <log details>

- 消息代码: 15049
严重性: 调试 (DEBUG)
消息文本: 正在评估策略组 (Evaluating Policy Group)
消息说明: 正在评估策略组
本地目标消息格式: <timestamp> <seq_num> 15049 DEBUG Policy: Evaluating Policy Group, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15049 DEBUG Policy: Evaluating Policy Group, <log details>
- 消息代码: 15050
严重性: 调试 (DEBUG)
消息文本: 网络访问设备不支持 VLAN 配置 (Network Access Device does not support configuration of VLAN)
消息说明: 网络访问设备不支持 VLAN 配置
本地目标消息格式: <timestamp> <seq_num> 15050 DEBUG Policy: Network Access Device does not support configuration of VLAN, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15050 DEBUG Policy: Network Access Device does not support configuration of VLAN, <log details>
- 消息代码: 15051
严重性: 调试 (DEBUG)
消息文本: 网络访问设备不支持 ACL 配置 (Network Access Device does not support configuration of ACL)
消息说明: 网络访问设备不支持 ACL 配置
本地目标消息格式: <timestamp> <seq_num> 15051 DEBUG Policy: Network Access Device does not support configuration of ACL, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 15051 DEBUG Policy: Network Access Device does not support configuration of ACL, <log details>
- 消息代码: 15052
严重性: 调试 (DEBUG)
消息文本: 指定的授权配置文件不适用于此网络访问设备 (Authorization profile/s specified are not suited for this Network Access Device)
消息说明: 指定的授权配置文件不适用于此网络访问设备
本地目标消息格式: <timestamp> <seq_num> 15052 DEBUG Policy: Authorization profile/s specified are not suited for this Network Access Device, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 15052 DEBUG Policy: Authorization profile/s
specified are not suited for this Network Access Device, <log details>

- 消息代码: 15053

严重性: 调试 (DEBUG)

消息文本: 网络访问设备不支持 CoA (Network Access Device does not support CoA)

消息说明: 网络访问设备不支持 CoA

本地目标消息格式: <timestamp> <seq_num> 15053 DEBUG Policy: Network Access Device does
not support CoA, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 15053 DEBUG Policy: Network Access
Device does not support CoA, <log details>

- 消息代码: 15054

严重性: 调试 (DEBUG)

消息文本: 正在发送 SNMP 集: (Sending SNMP set :)

消息说明: 正在发送 SNMP 集:

本地目标消息格式: <timestamp> <seq_num> 15054 DEBUG Policy: Sending SNMP set :, <log
details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 15054 DEBUG Policy: Sending SNMP set
:, <log details>

- 消息代码: 15055

严重性: 调试 (DEBUG)

消息文本: SNMP CoA 失败 (SNMP CoA failed)

消息说明: SNMP CoA 失败

本地目标消息格式: <timestamp> <seq_num> 15055 DEBUG Policy: SNMP CoA failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 15055 DEBUG Policy: SNMP CoA failed,
<log details>

- 消息代码: 15056

严重性: 错误 (ERROR)

消息文本: 未定义门户设置中所选接口的 IP 地址 (IP Address for interface selected in portal settings
is undefined)

消息说明: 未定义门户设置中所选接口的 IP 地址。请使用 CLI 为所选接口配置 IP 地址

本地目标消息格式: <timestamp> <seq_num> 15056 ERROR Policy: IP Address for interface selected in portal settings is undefined, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 15056 ERROR Policy: IP Address for interface selected in portal settings is undefined, <log details>

终端安全评估和客户端调配审核

- 消息代码: 87000

严重性: 通知 (NOTICE)

消息文本: 已从终端接收终端安全评估报告 (Received a posture report from an endpoint)

消息说明: 已从终端接收终端安全评估报告

本地目标消息格式: <timestamp> <seq_num> 87000 NOTICE Posture: Received a posture report from an endpoint, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 87000 NOTICE Posture: Received a posture report from an endpoint, <log details>

- 消息代码: 87001

严重性: 通知 (NOTICE)

消息文本: 终端安全评估服务已从终端接收重新评估报告 (Posture service received a reassessment report from an endpoint)

消息说明: 已从终端接收 PRA 报告请求

本地目标消息格式: <timestamp> <seq_num> 87001 NOTICE Posture: Posture service received a reassessment report from an endpoint, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 87001 NOTICE Posture: Posture service received a reassessment report from an endpoint, <log details>

- 消息代码: 87002

严重性: 通知 (NOTICE)

消息文本: 正在终止终端会话: 重新评估超时 (Terminating endpoint session: reassessment timeout)

消息说明: 由于重新评估超时, 已向设备发出授权更改请求, 以终止当前终端会话

本地目标消息格式: <timestamp> <seq_num> 87002 NOTICE Posture: Terminating endpoint session: reassessment timeout, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 87002 NOTICE Posture: Terminating endpoint session: reassessment timeout, <log details>

- 消息代码: 87004
严重性: 通知 (NOTICE)
消息文本: 终端安全评估服务已从终端接收 USB 检查报告 (Posture service received a USB-check report from an endpoint)
消息说明: 已从终端接收 USB 检查报告消息
本地目标消息格式: <timestamp> <seq_num> 87004 NOTICE Posture: Posture service received a USB-check report from an endpoint, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 87004 NOTICE Posture: Posture service received a USB-check report from an endpoint, <log details>
- 消息代码: 87500
严重性: 通知 (NOTICE)
消息文本: 客户端调配成功 (Client provisioning succeeded)
消息说明: 客户端调配成功
本地目标消息格式: <timestamp> <seq_num> 87500 NOTICE Client Provisioning: Client provisioning succeeded, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 87500 NOTICE Client Provisioning: Client provisioning succeeded, <log details>
- 消息代码: 87501
严重性: 通知 (NOTICE)
消息文本: 客户端调配失败 (Client provisioning failed)
消息说明: 客户端调配失败
本地目标消息格式: <timestamp> <seq_num> 87501 NOTICE Client Provisioning: Client provisioning failed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 87501 NOTICE Client Provisioning: Client provisioning failed, <log details>
- 消息代码: 87600
严重性: 通知 (NOTICE)
消息文本: 请求方调配成功 (Supplicant provisioning succeeded)
消息说明: 客户端的请求方调配成功
本地目标消息格式: <timestamp> <seq_num> 87600 NOTICE Supplicant Provisioning: Supplicant provisioning succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 87600 NOTICE Supplicant Provisioning:
Supplicant provisioning succeeded, <log details>

- 消息代码: 87601

严重性: 通知 (NOTICE)

消息文本: 请求方调配失败 (Supplicant provisioning failed)

消息说明: 请求方调配失败

本地目标消息格式: <timestamp> <seq_num> 87601 NOTICE Supplicant Provisioning: Supplicant
provisioning failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 87601 NOTICE Supplicant Provisioning:
Supplicant provisioning failed, <log details>

- 消息代码: 87602

严重性: 通知 (NOTICE)

消息文本: 正在进行请求方调配 (Supplicant provisioning is in progress)

消息说明: 正在进行请求方调配

本地目标消息格式: <timestamp> <seq_num> 87602 NOTICE Supplicant Provisioning: Supplicant
provisioning is in progress, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 87602 NOTICE Supplicant Provisioning:
Supplicant provisioning is in progress, <log details>

- 消息代码: 87603

严重性: 通知 (NOTICE)

消息文本: 已禁用请求方调配 (Supplicant provisioning disabled)

消息说明: 已禁用客户端的请求方调配

本地目标消息格式: <timestamp> <seq_num> 87603 NOTICE Supplicant Provisioning: Supplicant
provisioning disabled, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 87603 NOTICE Supplicant Provisioning:
Supplicant provisioning disabled, <log details>

- 消息代码: 87604

严重性: 警告 (WARN)

消息文本: CA 服务器关闭 (CA Server is down)

消息说明: CA 服务器关闭

本地目标消息格式: <timestamp> <seq_num> 87604 WARN Supplicant Provisioning: CA Server is down, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 87604 WARN Supplicant Provisioning: CA Server is down, <log details>

- 消息代码: 87605

严重性: 信息 (INFO)

消息文本: CA 服务器已启用 (CA Server is up)

消息说明: CA 服务器已启用

本地目标消息格式: <timestamp> <seq_num> 87605 INFO Supplicant Provisioning: CA Server is up, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 87605 INFO Supplicant Provisioning: CA Server is up, <log details>

- 消息代码: 87606

严重性: 错误 (ERROR)

消息文本: 证书请求转发失败 (Certificate request forwarding failed)

消息说明: 证书请求转发失败

本地目标消息格式: <timestamp> <seq_num> 87606 ERROR Supplicant Provisioning: Certificate request forwarding failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 87606 ERROR Supplicant Provisioning: Certificate request forwarding failed, <log details>

- 消息代码: 87607

严重性: 警告 (WARN)

消息文本: OCSP 事务数量过多 (High volume of OCSP transactions)

消息说明: OCSP 事务数量过多

本地目标消息格式: <timestamp> <seq_num> 87607 WARN Supplicant Provisioning: High volume of OCSP transactions, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 87607 WARN Supplicant Provisioning: High volume of OCSP transactions, <log details>

- 消息代码: 87608

严重性: 警告 (WARN)

消息文本: EST 服务关闭 (EST Service is down)

消息说明: EST 服务关闭

本地目标消息格式: <timestamp> <seq_num> 87608 WARN Supplicant Provisioning: EST Service is down, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 87608 WARN Supplicant Provisioning: EST Service is down, <log details>

- 消息代码: 87609

严重性: 信息 (INFO)

消息文本: EST 服务已启用 (EST Service is up)

消息说明: EST 服务已启用

本地目标消息格式: <timestamp> <seq_num> 87609 INFO Supplicant Provisioning: EST Service is up, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 87609 INFO Supplicant Provisioning: EST Service is up, <log details>

- 消息代码: 87750

严重性: 通知 (NOTICE)

消息文本: 终端保护服务已接收执行操作的请求 (Endpoint Protection Service has received a request to perform an operation)

消息说明: 终端保护服务在终端上执行请求的操作

本地目标消息格式: <timestamp> <seq_num> 87750 NOTICE EPS: Endpoint Protection Service has received a request to perform an operation, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 87750 NOTICE EPS: Endpoint Protection Service has received a request to perform an operation, <log details>

- 消息代码: 87751

严重性: 通知 (NOTICE)

消息文本: 终端保护服务已获得操作结果 (Endpoint Protection Service has obtained the result of an operation)

消息说明: 终端保护服务将操作结果存储在“操作状态”(Operation Status)中

本地目标消息格式: <timestamp> <seq_num> 87751 NOTICE EPS: Endpoint Protection Service has obtained the result of an operation, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 87751 NOTICE EPS: Endpoint Protection Service has obtained the result of an operation, <log details>

- 消息代码: 87752

严重性: 通知 (NOTICE)

消息文本: 手动证书调配门户 - 已提交请求 (Manual Certificate Provisioning Portal - Request submitted)

消息说明: 从手动证书调配门户发起了证书请求

本地目标消息格式: <timestamp> <seq_num> 87752 NOTICE Internal CA: Manual Certificate Provisioning Portal - Request submitted, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 87752 NOTICE Internal CA: Manual Certificate Provisioning Portal - Request submitted, <log details>

- 消息代码: 87753

严重性: 通知 (NOTICE)

消息文本: 手动证书调配门户 - 状态更新 (Manual Certificate Provisioning Portal - Status Update)

消息说明: 证书请求状态更新

本地目标消息格式: <timestamp> <seq_num> 87753 NOTICE Internal CA: Manual Certificate Provisioning Portal - Status Update, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 87753 NOTICE Internal CA: Manual Certificate Provisioning Portal - Status Update, <log details>

- 消息代码: 87754

严重性: 通知 (NOTICE)

消息文本: 手动证书调配门户 - 发生用户登录 (Manual Certificate Provisioning Portal - User login occurred)

消息说明: 为登录手动证书调配门户的用户创建了新会话

本地目标消息格式: <timestamp> <seq_num> 87754 NOTICE Internal CA: Manual Certificate Provisioning Portal - User login occurred, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 87754 NOTICE Internal CA: Manual Certificate Provisioning Portal - User login occurred, <log details>

- 消息代码: 87901

严重性: 通知 (NOTICE)

消息文本: 终端脚本已调配新作业以执行脚本 (EndPoint Scripts Provisioned a new job for script execution)

消息说明: 已成功创建新作业以在选定终端上执行管理员脚本

本地目标消息格式: <timestamp> <seq_num> 87901 EndPoint Scripts Provisioned a new job for script execution EndPoint Scripts Provisioning A new job has been successfully created to execute admin scripts on the selected end-points, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num>87901 EndPoint Scripts Provisioned a new
job for script execution EndPoint Scripts Provisioning A new job has been successfully created to execute
admin scripts on the selected end-points, <log details>

- 消息代码: 87921

严重性: 通知 (NOTICE)

消息文本: 已从终端获取终端脚本执行结果 (Result of EndPoint Scripts execution from an endpoint
obtained)

消息说明: 已从给定列表收到终端的终端脚本执行报告

本地目标消息格式: <timestamp> <seq_num>87921 Result of EndPoint Scripts execution from an
endpoint obtained EndPoint Scripts Provisioning Endpoint scripts execution report of an endpoint from
the given list is received, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num>87921 Result of EndPoint Scripts execution
from an endpoint obtained EndPoint Scripts Provisioning Endpoint scripts execution report of an endpoint
from the given list is received, <log details>

终端安全评估和客户端调配诊断

- 消息代码: 83001

严重性: 调试 (DEBUG)

消息文本: 来自终端的终端安全评估请求符合策略 (Posture request from endpoint matched the
policy)

消息说明: 来自终端的终端安全评估请求符合策略

本地目标消息格式: <timestamp> <seq_num> 83001 DEBUG Posture: Posture request from endpoint
matched the policy, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num> 83001 DEBUG Posture: Posture request
from endpoint matched the policy, <log details>

- 消息代码: 83003

严重性: 调试 (DEBUG)

消息文本: 已收到来自终端的重新评估请求 (Received a reassessment request from an endpoint)

消息说明: 已收到来自终端的重新评估请求

本地目标消息格式: <timestamp> <seq_num> 83003 DEBUG Posture: Received a reassessment request
from an endpoint, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 83003 DEBUG Posture: Received a
reassessment request from an endpoint, <log details>

- 消息代码: 83007

严重性: 警告 (WARN)

消息文本: 正在终止不合规的终端会话 (Terminating the non-compliant endpoint session)

消息说明: 向设备发出了授权更改请求, 以终止当前不合规的终端会话

本地目标消息格式: <timestamp> <seq_num> 83007 WARN Posture: Terminating the non-compliant
endpoint session, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 83007 WARN Posture: Terminating the
non-compliant endpoint session, <log details>

- 消息代码: 83009

严重性: 信息 (INFO)

消息文本: 已终止客户端上的 NAC 代理 (NAC agent on client is terminated)

消息说明: 最终用户已关闭客户端上的 NAC 代理

本地目标消息格式: <timestamp> <seq_num> 83009 INFO Posture: NAC agent on client is terminated,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 83009 INFO Posture: NAC agent on client
is terminated, <log details>

- 消息代码: 83015

严重性: 信息 (INFO)

消息文本: 终端安全评估服务正在触发授权更改请求 (Posture service is triggering a Change Of
Authorization request)

消息说明: 由于会话终端安全评估状态发生变化, 因此终端安全评估服务触发了新的授权更改
请求

本地目标消息格式: <timestamp> <seq_num> 83015 INFO Posture: Posture service is triggering a
Change Of Authorization request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 83015 INFO Posture: Posture service is
triggering a Change Of Authorization request, <log details>

- 消息代码: 84002

严重性: 警告 (WARN)

消息文本: 已禁用调配。您目前不能执行任何与调配相关的操作 (Provisioning is disabled. You
are not allowed to perform any provisioning related operations at this time)

消息说明：已禁用调配。您目前不能执行任何与调配相关的操作

本地目标消息格式：<timestamp> <seq_num> 84002 WARN Client Provisioning: Provisioning is disabled. You are not allowed to perform any provisioning related operations at this time, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 84002 WARN Client Provisioning: Provisioning is disabled. You are not allowed to perform any provisioning related operations at this time, <log details>

- 消息代码：84003

严重性：警告 (WARN)

消息文本：因版本与代理版本不兼容，未调配终端安全评估组件 (Posture component not provisioned due to version incompatibility with agent version)

消息说明：服务器上的终端安全评估组件与代理版本不兼容，因此未对其进行调配

本地目标消息格式：<timestamp> <seq_num> 84003 WARN Client Provisioning: Posture component not provisioned due to version incompatibility with agent version, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 84003 WARN Client Provisioning: Posture component not provisioned due to version incompatibility with agent version, <log details>

- 消息代码：85000

严重性：信息 (INFO)

消息文本：终端保护服务正在触发授权更改请求 (Endpoint Protection Service is triggering a Change Of Authorization request)

消息说明：终端保护服务正在触发新的授权更改请求

本地目标消息格式：<timestamp> <seq_num> 85000 INFO EPS: Endpoint Protection Service is triggering a Change Of Authorization request, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 85000 INFO EPS: Endpoint Protection Service is triggering a Change Of Authorization request, <log details>

Profiler

- 消息代码：80001

严重性：信息 (INFO)

消息文本：发生分析器终端收集事件 (Profiler EndPoint collection event occurred)

消息说明：在发生分析器终端收集事件时生成此消息

本地目标消息格式：<timestamp> <seq_num> 80001 INFO Profiler: Profiler EndPoint collection event occurred, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 80001 INFO Profiler: Profiler EndPoint
collection event occurred, <log details>

- 消息代码: 80002

严重性: 信息 (INFO)

消息文本: 发生分析器终端分析事件 (Profiler EndPoint profiling event occurred)

消息说明: 在发生分析器终端分析事件时生成此消息

本地目标消息格式: <timestamp> <seq_num> 80002 INFO Profiler: Profiler EndPoint profiling event
occurred, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 80002 INFO Profiler: Profiler EndPoint
profiling event occurred, <log details>

- 消息代码: 80003

严重性: 错误 (ERROR)

消息文本: 未能加载分析器探测 (Profiler Probe failed to load)

消息说明: 在无法启动探测时生成此消息

本地目标消息格式: <timestamp> <seq_num> 80003 ERROR Profiler: Profiler Probe failed to load,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 80003 ERROR Profiler: Profiler Probe failed
to load, <log details>

- 消息代码: 80004

严重性: 信息 (INFO)

消息文本: 发生分析器性能计数器快照更新事件 (Profiler Performance Counters Snapshot update
event occurred)

消息说明: 在报告新的分析器性能计数器快照时生成此消息

本地目标消息格式: <timestamp> <seq_num> 80004 INFO Profiler: Profiler Performance Counters
Snapshot update event occurred, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 80004 INFO Profiler: Profiler Performance
Counters Snapshot update event occurred, <log details>

- 消息代码: 80005

严重性: 信息 (INFO)

消息文本: 发生分析器异常操作执行事件 (Profiler Exception Action execution occurred)

消息说明: 在分析器终端接受分析并符合异常规则时生成此消息

本地目标消息格式: <timestamp> <seq_num> 80005 INFO Profiler: Profiler Exception Action execution occurred, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 80005 INFO Profiler: Profiler Exception Action execution occurred, <log details>

- 消息代码: 80006

严重性: 信息 (INFO)

消息文本: 分析器触发授权更改请求 (Profiler is triggering Change Of Authorization Request)

消息说明: 分析器触发授权更改请求

本地目标消息格式: <timestamp> <seq_num> 80006 INFO Profiler: Profiler is triggering Change Of Authorization Request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 80006 INFO Profiler: Profiler is triggering Change Of Authorization Request, <log details>

- 消息代码: 80007

严重性: 调试 (DEBUG)

消息文本: 已发出分析器 SNMP 请求 (Profiler SNMP request sent)

消息说明: 在分析器发出 SNMP 请求时生成此消息。

本地目标消息格式: <timestamp> <seq_num> 80007 DEBUG Profiler: Profiler SNMP request sent, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 80007 DEBUG Profiler: Profiler SNMP request sent, <log details>

- 消息代码: 80008

严重性: 调试 (DEBUG)

消息文本: 收到分析器 SNMP 响应 (Profiler SNMP response received)

消息说明: 在分析器 SNMP 收到响应时生成此消息。

本地目标消息格式: <timestamp> <seq_num> 80008 DEBUG Profiler: Profiler SNMP response received, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 80008 DEBUG Profiler: Profiler SNMP response received, <log details>

- 消息代码: 80009

严重性: 错误 (ERROR)

消息文本: 分析器 SNMP 请求失败 (Profiler SNMP request failure)

消息说明：在分析器 SNMP 请求失败时生成此消息。

本地目标消息格式：<timestamp> <seq_num> 80009 ERROR Profiler: Profiler SNMP request failure, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 80009 ERROR Profiler: Profiler SNMP request failure, <log details>

- 消息代码：80010

严重性：信息 (INFO)

消息文本：已发出分析器 DNS 请求 (Profiler DNS request sent)

消息说明：在分析器发出 DNS 请求时生成此消息。

本地目标消息格式：<timestamp> <seq_num> 80010 INFO Profiler: Profiler DNS request sent, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 80010 INFO Profiler: Profiler DNS request sent, <log details>

- 消息代码：80013

严重性：信息 (INFO)

消息文本：发生分析器终端源分析事件 (Profiler EndPoint feed profiling event occurred)

消息说明：由于源服务策略，分析器重新分析终端

本地目标消息格式：<timestamp> <seq_num> 80013 INFO Profiler: Profiler EndPoint feed profiling event occurred, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 80013 INFO Profiler: Profiler EndPoint feed profiling event occurred, <log details>

- 消息代码：80014

严重性：信息 (INFO)

消息文本：发生分析器终端清除事件 (Profiler EndPoint purge event occurred)

消息说明：在评估分析器终端清除策略并且符合该策略时生成此消息

本地目标消息格式：<timestamp> <seq_num> 80014 INFO Profiler: Profiler EndPoint purge event occurred, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 80014 INFO Profiler: Profiler EndPoint purge event occurred, <log details>

- 消息代码：80015

严重性：警告 (WARN)

消息文本: 已达到分析器队列大小限制。(Profiler queue size limit has been reached.)

消息说明: 已达到分析器队列大小限制。在达到队列大小限制以后, 再收到的事件将被丢弃。

本地目标消息格式: <timestamp> <seq_num> 80015 WARN Profiler: Profiler queue size limit has been reached., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 80015 WARN Profiler: Profiler queue size limit has been reached, <log details>

- 消息代码: 80016

严重性: 警告 (WARN)

消息文本: 检测到异常行为 (Anomalous behavior detected)

消息说明: 已启用 MAC 欺骗检测且终端表现出异常行为

本地目标消息格式: <timestamp> <seq_num> 80016 WARN Profiler: Anomalous behavior detected, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 80016 WARN Profiler: Anomalous behavior detected, <log details>

RADIUS 记账

- 消息代码: 3000

严重性: 通知 (NOTICE)

消息文本: RADIUS 记帐开始请求 (RADIUS Accounting start request)

消息说明: RADIUS 记帐开始请求

本地目标消息格式: <timestamp> <seq_num> 3000 NOTICE Radius-Accounting: RADIUS Accounting start request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 3000 NOTICE Radius-Accounting: RADIUS Accounting start request, <log details>

- 消息代码: 3001

严重性: 通知 (NOTICE)

消息文本: RADIUS 记帐停止请求 (RADIUS Accounting stop request)

消息说明: RADIUS 记帐停止请求

本地目标消息格式: <timestamp> <seq_num> 3001 NOTICE Radius-Accounting: RADIUS Accounting stop request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 3001 NOTICE Radius-Accounting: RADIUS
Accounting stop request, <log details>

- 消息代码: 3002

严重性: 通知 (NOTICE)

消息文本: RADIUS 记帐监视器更新 (RADIUS Accounting watchdog update)

消息说明: RADIUS 记帐监视器更新

本地目标消息格式: <timestamp> <seq_num> 3002 NOTICE Radius-Accounting: RADIUS Accounting
watchdog update, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 3002 NOTICE Radius-Accounting: RADIUS
Accounting watchdog update, <log details>

- 消息代码: 3003

严重性: 通知 (NOTICE)

消息文本: RADIUS 记帐已启用 (RADIUS Accounting is on)

消息说明: RADIUS 记帐已启用

本地目标消息格式: <timestamp> <seq_num> 3003 NOTICE Radius-Accounting: RADIUS Accounting
is on, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 3003 NOTICE Radius-Accounting: RADIUS
Accounting is on, <log details>

- 消息代码: 3004

严重性: 通知 (NOTICE)

消息文本: RADIUS 记帐已关闭 (RADIUS Accounting is off)

消息说明: RADIUS 记帐已关闭

本地目标消息格式: <timestamp> <seq_num> 3004 NOTICE Radius-Accounting: RADIUS Accounting
is off, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 3004 NOTICE Radius-Accounting: RADIUS
Accounting is off, <log details>

- 消息代码: 3005

严重性: 通知 (NOTICE)

消息文本: RADIUS 记帐隧道启动请求 (RADIUS Accounting tunnel start request)

消息说明: RADIUS 记帐隧道启动请求

本地目标消息格式: <timestamp> <seq_num> 3005 NOTICE Radius-Accounting: RADIUS Accounting tunnel start request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 3005 NOTICE Radius-Accounting: RADIUS Accounting tunnel start request, <log details>

- 消息代码: 3006

严重性: 通知 (NOTICE)

消息文本: RADIUS 记帐隧道停止请求 (RADIUS Accounting tunnel stop request)

消息说明: RADIUS 记帐隧道停止请求

本地目标消息格式: <timestamp> <seq_num> 3006 NOTICE Radius-Accounting: RADIUS Accounting tunnel stop request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 3006 NOTICE Radius-Accounting: RADIUS Accounting tunnel stop request, <log details>

- 消息代码: 3007

严重性: 通知 (NOTICE)

消息文本: 已拒绝 RADIUS 记帐隧道 (RADIUS Accounting tunnel rejected)

消息说明: 已拒绝 RADIUS 记帐隧道

本地目标消息格式: <timestamp> <seq_num> 3007 NOTICE Radius-Accounting: RADIUS Accounting tunnel rejected, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 3007 NOTICE Radius-Accounting: RADIUS Accounting tunnel rejected, <log details>

- 消息代码: 3008

严重性: 通知 (NOTICE)

消息文本: RADIUS 记帐隧道链路启动 (RADIUS Accounting tunnel link start)

消息说明: RADIUS 记帐隧道链路启动

本地目标消息格式: <timestamp> <seq_num> 3008 NOTICE Radius-Accounting: RADIUS Accounting tunnel link start, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 3008 NOTICE Radius-Accounting: RADIUS Accounting tunnel link start, <log details>

- 消息代码: 3009

严重性: 通知 (NOTICE)

消息文本: RADIUS 记帐隧道链路停止 (RADIUS Accounting tunnel link stop)

消息说明: RADIUS 记帐隧道链路停止

本地目标消息格式: <timestamp> <seq_num> 3009 NOTICE Radius-Accounting: RADIUS Accounting tunnel link stop, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 3009 NOTICE Radius-Accounting: RADIUS Accounting tunnel link stop, <log details>

- 消息代码: 3010

严重性: 通知 (NOTICE)

消息文本: 已拒绝 RADIUS 记帐隧道链路 (RADIUS Accounting tunnel link rejected)

消息说明: 已拒绝 RADIUS 记帐隧道链路

本地目标消息格式: <timestamp> <seq_num> 3010 NOTICE Radius-Accounting: RADIUS Accounting tunnel link rejected, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 3010 NOTICE Radius-Accounting: RADIUS Accounting tunnel link rejected, <log details>

RADIUS 诊断

- 消息代码: 11001

严重性: 调试 (DEBUG)

消息文本: 已收到 RADIUS Access-Request (Received RADIUS Access-Request)

消息说明: 已收到 RADIUS Access-Request

本地目标消息格式: <timestamp> <seq_num> 11001 DEBUG RADIUS: Received RADIUS Access-Request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11001 DEBUG RADIUS: Received RADIUS Access-Request, <log details>

- 消息代码: 11002

严重性: 调试 (DEBUG)

消息文本: 已收到 RADIUS Access-Accept (Returned RADIUS Access-Accept)

消息说明: 已收到 RADIUS Access-Accept - 身份验证成功

本地目标消息格式: <timestamp> <seq_num> 11002 DEBUG RADIUS: Returned RADIUS Access-Accept, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11002 DEBUG RADIUS: Returned RADIUS Access-Accept, <log details>

- 消息代码: 11003
严重性: 调试 (DEBUG)
消息文本: 已收到 RADIUS Access-Reject (Returned RADIUS Access-Reject)
消息说明: 已收到 RADIUS Access-Reject - 身份验证失败
本地目标消息格式: <timestamp> <seq_num> 11003 DEBUG RADIUS: Returned RADIUS Access-Reject, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11003 DEBUG RADIUS: Returned RADIUS Access-Reject, <log details>
- 消息代码: 11004
严重性: 调试 (DEBUG)
消息文本: 已收到 RADIUS Accounting-Request (Received RADIUS Accounting-Request)
消息说明: 已收到 RADIUS Accounting-Request
本地目标消息格式: <timestamp> <seq_num> 11004 DEBUG RADIUS: Received RADIUS Accounting-Request, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11004 DEBUG RADIUS: Received RADIUS Accounting-Request, <log details>
- 消息代码: 11005
严重性: 调试 (DEBUG)
消息文本: 已返回 RADIUS Accounting-Response (Returned RADIUS Accounting-Response)
消息说明: 已返回 RADIUS Accounting-Response - 确认收到 Accounting-Request
本地目标消息格式: <timestamp> <seq_num> 11005 DEBUG RADIUS: Returned RADIUS Accounting-Response, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11005 DEBUG RADIUS: Returned RADIUS Accounting-Response, <log details>
- 消息代码: 11006
严重性: 调试 (DEBUG)
消息文本: 已返回 RADIUS Access-Challenge (Returned RADIUS Access-Challenge)
消息说明: 已返回 RADIUS Access-Challenge, 要求提供更多信息
本地目标消息格式: <timestamp> <seq_num> 11006 DEBUG RADIUS: Returned RADIUS Access-Challenge, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11006 DEBUG RADIUS: Returned RADIUS
Access-Challenge, <log details>

- 消息代码: 11007

严重性: 调试 (DEBUG)

消息文本: 找不到网络设备或 AAA 客户端 (Could not locate Network Device or AAA Client)

消息说明: 在身份验证过程中通过 IP 访问 NAS 时找不到网络设备或 AAA 客户端。

本地目标消息格式: <timestamp> <seq_num> 11007 DEBUG RADIUS: Could not locate Network
Device or AAA Client, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11007 DEBUG RADIUS: Could not locate
Network Device or AAA Client, <log details>

- 消息代码: 11008

严重性: 调试 (DEBUG)

消息文本: 已收到 Service-Type = Call Check, 但没有 Calling-Station-ID (Received Service-Type
= Call Check (but there is no Calling-Station-ID))

消息说明: 虽然请求包含值为 Call Check (10) 的 Service-Type 属性, 但未检测到主机查询用例。
这是因为请求中未提供 Calling-Station-ID 属性

本地目标消息格式: <timestamp> <seq_num> 11008 DEBUG RADIUS: Received Service-Type =
Call Check (but there is no Calling-Station-ID), <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11008 DEBUG RADIUS: Received
Service-Type = Call Check (but there is no Calling-Station-ID), <log details>

- 消息代码: 11009

严重性: 信息 (INFO)

消息文本: RADIUS 侦听程序已启动 (RADIUS listener started)

消息说明: 开始侦听提交的端口上传入的 RADIUS 请求

本地目标消息格式: <timestamp> <seq_num> 11009 INFO RADIUS: RADIUS listener started, <log
details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11009 INFO RADIUS: RADIUS listener
started, <log details>

- 消息代码: 11010

严重性: 信息 (INFO)

消息文本: RADIUS 侦听程序已停止 (RADIUS listener stopped)

消息说明: 停止侦听 RADIUS 请求

本地目标消息格式: <timestamp> <seq_num> 11010 INFO RADIUS: RADIUS listener stopped, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11010 INFO RADIUS: RADIUS listener stopped, <log details>

- 消息代码: 11011

严重性: 错误 (ERROR)

消息文本: RADIUS 侦听程序打开失败 (RADIUS listener failed to open)

消息说明: 无法打开一个或多个用于接收 RADIUS 请求的端口

本地目标消息格式: <timestamp> <seq_num> 11011 ERROR RADIUS: RADIUS listener failed to open, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11011 ERROR RADIUS: RADIUS listener failed to open, <log details>

- 消息代码: 11012

严重性: 错误 (ERROR)

消息文本: RADIUS 数据包含有无效的信头 (RADIUS packet contains invalid header)

消息说明: RADIUS 数据包的信头未正确解析

本地目标消息格式: <timestamp> <seq_num> 11012 ERROR RADIUS: RADIUS packet contains invalid header, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11012 ERROR RADIUS: RADIUS packet contains invalid header, <log details>

- 消息代码: 11014

严重性: 错误 (ERROR)

消息文本: RADIUS 数据包含有无效的属性 (RADIUS packet contains invalid attribute(s))

消息说明: RADIUS 数据包中的一个属性未正确解析

本地目标消息格式: <timestamp> <seq_num> 11014 ERROR RADIUS: RADIUS packet contains invalid attribute(s), <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11014 ERROR RADIUS: RADIUS packet contains invalid attribute(s), <log details>

- 消息代码: 11015

严重性: 警告 (WARN)

消息文本: Access-Request 必须至少包含一个 NAS-IP-Address、NAS-IPv6-Address 或 NAS-Identifier; 继续处理 (An Access-Request MUST contain at least a NAS-IP-Address, NAS-IPv6-Address, or a NAS-Identifier; Continue processing)

消息说明: 根据 RADIUS 标准, Access-Request 必须至少包含一个 NAS-IP-Address、NAS-IPv6-Address 或 NAS-Identifier。系统已忽略此条件并继续处理。

本地目标消息格式: <timestamp> <seq_num> 11015 WARN RADIUS: An Access-Request MUST contain at least a NAS-IP-Address, NAS-IPv6-Address, or a NAS-Identifier; Continue processing, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11015 WARN RADIUS: An Access-Request MUST contain at least a NAS-IP-Address, NAS-IPv6-Address, or a NAS-Identifier; Continue processing, <log details>

- 消息代码: 11016

严重性: 调试 (DEBUG)

消息文本: 正在将 EAP 协议结果转换为 RADIUS 结果 (Translating EAP protocol result into RADIUS result)

消息说明: 正在将 EAP 协议结果转换为 RADIUS 结果

本地目标消息格式: <timestamp> <seq_num> 11016 DEBUG RADIUS: Translating EAP protocol result into RADIUS result, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11016 DEBUG RADIUS: Translating EAP protocol result into RADIUS result, <log details>

- 消息代码: 11017

严重性: 调试 (DEBUG)

消息文本: RADIUS 已创建新会话 (RADIUS created a new session)

消息说明: RADIUS 为请求创建了新会话

本地目标消息格式: <timestamp> <seq_num> 11017 DEBUG RADIUS: RADIUS created a new session, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11017 DEBUG RADIUS: RADIUS created a new session, <log details>

- 消息代码: 11018

严重性: 调试 (DEBUG)

消息文本: RADIUS 在重复使用现有会话 (RADIUS is re-using an existing session)

消息说明: RADIUS 在处理此请求时重复使用现有会话

本地目标消息格式: <timestamp> <seq_num> 11018 DEBUG RADIUS: RADIUS is re-using an existing session, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11018 DEBUG RADIUS: RADIUS is
re-using an existing session, <log details>

- 消息代码: 11019

严重性: 信息 (INFO)

消息文本: 已选择 DenyAccess 服务 (Selected DenyAccess Service)

消息说明: 服务选择策略已选择 DenyAccess 服务

本地目标消息格式: <timestamp> <seq_num> 11019 INFO RADIUS: Selected DenyAccess Service,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11019 INFO RADIUS: Selected DenyAccess
Service, <log details>

- 消息代码: 11020

严重性: 错误 (ERROR)

消息文本: RADIUS 会话授权未返回有效结果 (RADIUS session authorization did not return a valid
result)

消息说明: 发生意外错误。RADIUS 会话授权应返回有效结果。

本地目标消息格式: <timestamp> <seq_num> 11020 ERROR RADIUS: RADIUS session authorization
did not return a valid result, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11020 ERROR RADIUS: RADIUS session
authorization did not return a valid result, <log details>

- 消息代码: 11021

严重性: 错误 (ERROR)

消息文本: RADIUS 无法破译密码。数据包缺少必要属性 (RADIUS could not decipher password.
packet missing necessary attributes)

消息说明: 由于数据包没有必需属性, 因此 RADIUS 无法破译密码

本地目标消息格式: <timestamp> <seq_num> 11021 ERROR RADIUS: RADIUS could not decipher
password. packet missing necessary attributes, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11021 ERROR RADIUS: RADIUS could
not decipher password. packet missing necessary attributes, <log details>

- 消息代码: 11022

严重性: 调试 (DEBUG)

消息文本: 已添加授权配置文件中指定的 dACL (Added the dACL specified in the Authorization
Profile)

消息说明：已将授权配置文件中指定的可下载 ACL (dACL) 添加到应在响应中返回的属性集

本地目标消息格式：<timestamp> <seq_num> 11022 DEBUG DACL: Added the dACL specified in the Authorization Profile, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11022 DEBUG DACL: Added the dACL specified in the Authorization Profile, <log details>

- 消息代码：11023

严重性：警告 (WARN)

消息文本：找不到请求的 dACL。这是一个未知的 dACL 名称 (The requested dACL is not found. This is an unknown dACL name)

消息说明：找不到授权配置文件中指定的可下载 ACL (dACL)

本地目标消息格式：<timestamp> <seq_num> 11023 WARN DACL: The requested dACL is not found. This is an unknown dACL name, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11023 WARN DACL: The requested dACL is not found. This is an unknown dACL name, <log details>

- 消息代码：11024

严重性：错误 (ERROR)

消息文本：请求 dACL 的 Access-Request 缺少 Message-Authenticator 属性。请求被拒绝 (The Access-Request for the requested dACL is missing a Message-Authenticator attribute. The request is rejected)

消息说明：Access-Request 没有可下载 ACL 请求需要的 Message-Authenticator 属性。因此，请求被拒绝

本地目标消息格式：<timestamp> <seq_num> 11024 ERROR DACL: The Access-Request for the requested dACL is missing a Message-Authenticator attribute. The request is rejected, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11024 ERROR DACL: The Access-Request for the requested dACL is missing a Message-Authenticator attribute. The request is rejected, <log details>

- 消息代码：11025

严重性：错误 (ERROR)

消息文本：请求 dACL 的 Access-Request 缺少值为 aaa:event=acl-download 的 cisco-av-pair 属性。请求被拒绝 (The Access-Request for the requested dACL is missing a cisco-av-pair attribute with the value aaa:event=acl-download. The request is rejected)

消息说明：Access-Request 缺少可下载 ACL 请求需要的值为 aaa:event=acl-download 的 cisco-av-pair 属性。因此，请求被拒绝。

本地目标消息格式: <timestamp> <seq_num> 11025 ERROR DACL: The Access-Request for the requested dACL is missing a cisco-av-pair attribute with the value aaa:event=acl-download. The request is rejected, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11025 ERROR DACL: The Access-Request for the requested dACL is missing a cisco-av-pair attribute with the value aaa:event=acl-download. The request is rejected, <log details>

- 消息代码: 11026

严重性: 错误 (ERROR)

消息文本: 找不到请求的 dACL (The requested dACL is not found)

消息说明: 找不到 Access-Request 中请求的可下载 ACL 版本。因此, 请求被拒绝。

本地目标消息格式: <timestamp> <seq_num> 11026 ERROR DACL: The requested dACL is not found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11026 ERROR DACL: The requested dACL is not found, <log details>

- 消息代码: 11027

严重性: 调试 (DEBUG)

消息文本: 检测到主机查询用例 (Detected Host Lookup UseCase) (Service-Type = Call Check (10))

消息说明: 检测到主机查询用例 (Service-Type = Call Check (10))

本地目标消息格式: <timestamp> <seq_num> 11027 DEBUG RADIUS: Detected Host Lookup UseCase (Service-Type = Call Check (10)), <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11027 DEBUG RADIUS: Detected Host Lookup UseCase (Service-Type = Call Check (10)), <log details>

- 消息代码: 11028

严重性: 调试 (DEBUG)

消息文本: 检测到主机查询用例 (Detected Host Lookup UseCase) (UserName = Calling-Station-ID)

消息说明: 检测到主机查询用例 (UserName = Calling-Station-ID)

本地目标消息格式: <timestamp> <seq_num> 11028 DEBUG RADIUS: Detected Host Lookup UseCase (UserName = Calling-Station-ID), <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11028 DEBUG RADIUS: Detected Host Lookup UseCase (UserName = Calling-Station-ID), <log details>

- 消息代码: 11029

严重性: 警告 (WARN)

消息文本: RADIUS 数据包类型不受支持 (Unsupported RADIUS packet type)

消息说明: ISE 不支持 RADIUS 数据包类型

本地目标消息格式: <timestamp> <seq_num> 11029 WARN RADIUS: Unsupported RADIUS packet type, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11029 WARN RADIUS: Unsupported RADIUS packet type, <log details>

- 消息代码: 11030

严重性: 警告 (WARN)

消息文本: RADIUS 数据包预解析失败 (Pre-parsing of the RADIUS packet failed)

消息说明: RADIUS 数据包预解析失败。此数据包似乎不是有效的 RADIUS 数据包

本地目标消息格式: <timestamp> <seq_num> 11030 WARN RADIUS: Pre-parsing of the RADIUS packet failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11030 WARN RADIUS: Pre-parsing of the RADIUS packet failed, <log details>

- 消息代码: 11031

严重性: 警告 (WARN)

消息文本: RADIUS 数据包类型不是有效的请求 (RADIUS packet type is not a valid Request)

消息说明: RADIUS 数据包类型不是有效的请求。

本地目标消息格式: <timestamp> <seq_num> 11031 WARN RADIUS: RADIUS packet type is not a valid Request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11031 WARN RADIUS: RADIUS packet type is not a valid Request, <log details>

- 消息代码: 11032

严重性: 信息 (INFO)

消息文本: 所选访问服务类型不是设备管理类型 (Selected Access Service type is not Device Administration)

消息说明: 只有设备管理类型的访问服务才能处理 TACACS+ 请求

本地目标消息格式: <timestamp> <seq_num> 11032 INFO RADIUS: Selected Access Service type is not Device Administration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11032 INFO RADIUS: Selected Access Service type is not Device Administration, <log details>

- 消息代码: 11033
 - 严重性: 信息 (INFO)
 - 消息文本: 所选服务类型不是网络访问类型 (Selected Service type is not Network Access)
 - 消息说明: 只有网络访问类型的访问服务才能处理 RADIUS 请求
 - 本地目标消息格式: <timestamp> <seq_num> 11033 INFO RADIUS: Selected Service type is not Network Access, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11033 INFO RADIUS: Selected Service type is not Network Access, <log details>

- 消息代码: 11034
 - 严重性: 调试 (DEBUG)
 - 消息文本: 进程主机查找已禁用。(无法应用 Service-Type = Call Check (10)) (Process Host Lookup is disabled. (Service-Type = Call Check (10) cannot be applied))
 - 消息说明: 未在允许的协议中启用进程主机查询选项; 因此已忽略早期检测到的 Service-Type = Call Check (10)
 - 本地目标消息格式: <timestamp> <seq_num> 11034 DEBUG RADIUS: Process Host Lookup is disabled. (Service-Type = Call Check (10) cannot be applied), <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11034 DEBUG RADIUS: Process Host Lookup is disabled. (Service-Type = Call Check (10) cannot be applied), <log details>

- 消息代码: 11035
 - 严重性: 警告 (WARN)
 - 消息文本: 与请求的 dACL 关联的会话已超时 (The session associated with the requested dACL has timed out)
 - 消息说明: 与请求的可下载 ACL (dACL) 关联的会话已超时。请求被拒绝
 - 本地目标消息格式: <timestamp> <seq_num> 11035 WARN DACL: The session associated with the requested dACL has timed out, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11035 WARN DACL: The session associated with the requested dACL has timed out, <log details>

- 消息代码: 11036
 - 严重性: 警告 (WARN)
 - 消息文本: Message-Authenticator RADIUS 属性无效 (The Message-Authenticator RADIUS attribute is invalid)
 - 消息说明: Message-Authenticator RADIUS 属性无效。这可能是由于共享密钥不匹配。

本地目标消息格式: <timestamp> <seq_num> 11036 WARN RADIUS: The Message-Authenticator RADIUS attribute is invalid, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11036 WARN RADIUS: The Message-Authenticator RADIUS attribute is invalid, <log details>

- 消息代码: 11037

严重性: 错误 (ERROR)

消息文本: 已丢弃通过不受支持的端口接收的记帐请求 (Dropped accounting request received via unsupported port)

消息说明: 记帐请求已被丢弃, 因为它通过不受支持的 UDP 端口号接收的。

本地目标消息格式: <timestamp> <seq_num> 11037 ERROR RADIUS: Dropped accounting request received via unsupported port, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11037 ERROR RADIUS: Dropped accounting request received via unsupported port, <log details>

- 消息代码: 11038

严重性: 警告 (WARN)

消息文本: RADIUS Accounting-Request 信头包含无效的身份验证器字段 (RADIUS Accounting-Request header contains invalid Authenticator field)

消息说明: ISE 无法验证 RADIUS Accounting-Request 数据包信头中的身份验证器字段。请注意, 不应将身份验证器字段与 Message-Authenticator RADIUS 属性混淆。

本地目标消息格式: <timestamp> <seq_num> 11038 WARN RADIUS: RADIUS Accounting-Request header contains invalid Authenticator field, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11038 WARN RADIUS: RADIUS Accounting-Request header contains invalid Authenticator field, <log details>

- 消息代码: 11039

严重性: 信息 (INFO)

消息文本: 由于出现严重日志记录错误, RADIUS 身份验证请求被拒绝 (RADIUS authentication request rejected due to critical logging error)

消息说明: 由于出现严重日志记录错误, RADIUS 身份验证请求被拒绝。

本地目标消息格式: <timestamp> <seq_num> 11039 INFO RADIUS: RADIUS authentication request rejected due to critical logging error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11039 INFO RADIUS: RADIUS authentication request rejected due to critical logging error, <log details>

- 消息代码: 11040
严重性: 信息 (INFO)
消息文本: 由于出现严重日志记录错误, RADIUS 记帐请求已丢弃 (RADIUS accounting request dropped due to critical logging error)
消息说明: 由于出现严重日志记录错误, RADIUS 记帐请求已丢弃。
本地目标消息格式: <timestamp> <seq_num> 11040 INFO RADIUS: RADIUS accounting request dropped due to critical logging error, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11040 INFO RADIUS: RADIUS accounting request dropped due to critical logging error, <log details>
- 消息代码: 11041
严重性: 警告 (WARN)
消息文本: RADIUS PAP 会话超时 (RADIUS PAP session timed out)
消息说明: RADIUS PAP 会话超时。
本地目标消息格式: <timestamp> <seq_num> 11041 WARN RADIUS: RADIUS PAP session timed out, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11041 WARN RADIUS: RADIUS PAP session timed out, <log details>
- 消息代码: 11042
严重性: 调试 (DEBUG)
消息文本: 收到重复的 RADIUS 请求; 正在重新发送之前的响应 (Received duplicate RADIUS request; retransmitting previous response)
消息说明: 收到重复的 RADIUS 请求。正在重新发送之前发送的对应 RADIUS 响应。
本地目标消息格式: <timestamp> <seq_num> 11042 DEBUG RADIUS: Received duplicate RADIUS request; retransmitting previous response, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11042 DEBUG RADIUS: Received duplicate RADIUS request; retransmitting previous response, <log details>
- 消息代码: 11043
严重性: 调试 (DEBUG)
消息文本: 已收到 RADIUS CoA 请求 (Received RADIUS CoA request)
消息说明: 已收到 RADIUS CoA 请求
本地目标消息格式: <timestamp> <seq_num> 11043 DEBUG RADIUS: Received RADIUS CoA request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11043 DEBUG RADIUS: Received RADIUS
CoA request, <log details>

- 消息代码: 11044

严重性: 调试 (DEBUG)

消息文本: 已收到 RADIUS 断开连接请求 (Received RADIUS disconnect request)

消息说明: 已收到 RADIUS 断开连接请求

本地目标消息格式: <timestamp> <seq_num> 11044 DEBUG RADIUS: Received RADIUS disconnect
request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11044 DEBUG RADIUS: Received RADIUS
disconnect request, <log details>

- 消息代码: 11045

严重性: 调试 (DEBUG)

消息文本: 已返回 RADIUS CoA ACK (Returned RADIUS CoA ACK)

消息说明: 已返回 RADIUS CoA ACK

本地目标消息格式: <timestamp> <seq_num> 11045 DEBUG RADIUS: Returned RADIUS CoA
ACK, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11045 DEBUG RADIUS: Returned RADIUS
CoA ACK, <log details>

- 消息代码: 11046

严重性: 调试 (DEBUG)

消息文本: 已返回 RADIUS CoA NAK (Returned RADIUS CoA NAK)

消息说明: 已返回 RADIUS CoA NAK

本地目标消息格式: <timestamp> <seq_num> 11046 DEBUG RADIUS: Returned RADIUS CoA
NAK, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11046 DEBUG RADIUS: Returned RADIUS
CoA NAK, <log details>

- 消息代码: 11047

严重性: 调试 (DEBUG)

消息文本: 已返回 RADIUS 断开连接 ACK (Returned RADIUS disconnect ACK)

消息说明: 已返回 RADIUS 断开连接 ACK

本地目标消息格式: <timestamp> <seq_num> 11047 DEBUG RADIUS: Returned RADIUS disconnect ACK, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11047 DEBUG RADIUS: Returned RADIUS disconnect ACK, <log details>

- 消息代码: 11048

严重性: 调试 (DEBUG)

消息文本: 已返回 RADIUS 断开连接 NAK (Returned RADIUS disconnect NAK)

消息说明: 已返回 RADIUS 断开连接 NAK

本地目标消息格式: <timestamp> <seq_num> 11048 DEBUG RADIUS: Returned RADIUS disconnect NAK, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11048 DEBUG RADIUS: Returned RADIUS disconnect NAK, <log details>

- 消息代码: 11049

严重性: 信息 (INFO)

消息文本: 将使用 RADIUS 默认网络设备的设置 (Settings of RADIUS default network device will be used)

消息说明: 将使用 RADIUS 默认网络设备的设置

本地目标消息格式: <timestamp> <seq_num> 11049 INFO RADIUS: Settings of RADIUS default network device will be used, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11049 INFO RADIUS: Settings of RADIUS default network device will be used, <log details>

- 消息代码: 11051

严重性: 警告 (WARN)

消息文本: RADIUS 数据包包含无效的状态属性 (RADIUS packet contains invalid state attribute)

消息说明: RADIUS 数据包中的状态属性与任何活动会话均不匹配。

本地目标消息格式: <timestamp> <seq_num> 11051 WARN RADIUS: RADIUS packet contains invalid state attribute, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11051 WARN RADIUS: RADIUS packet contains invalid state attribute, <log details>

- 消息代码: 11052

严重性: 错误 (ERROR)

消息文本: 由于端口号不受支持, 身份验证请求已丢弃 (Authentication request dropped due to unsupported port number)

消息说明: 由于身份验证请求是通过不受支持的端口号接收的, 因此已被丢弃。

本地目标消息格式: <timestamp> <seq_num> 11052 ERROR RADIUS: Authentication request dropped due to unsupported port number, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11052 ERROR RADIUS: Authentication request dropped due to unsupported port number, <log details>

- 消息代码: 11053

严重性: 警告 (WARN)

消息文本: 传出 RADIUS 数据包中的属性无效 - 可能某些属性超过其大小限制 (Invalid attributes in outgoing radius packet - possibly some attributes exceeded their size limit)

消息说明: RADIUS 响应数据包无效。一个可能的原因是, 至少有一个属性超过允许的长度, 或附加到此响应数据包的属性的总大小超过 4k (RADIUS 数据包大小上限)

本地目标消息格式: <timestamp> <seq_num> 11053 WARN RADIUS: Invalid attributes in outgoing radius packet - possibly some attributes exceeded their size limit, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11053 WARN RADIUS: Invalid attributes in outgoing radius packet - possibly some attributes exceeded their size limit, <log details>

- 消息代码: 11054

严重性: 警告 (WARN)

消息文本: 由于已安装无线许可证, 来自非无线设备的请求已丢弃 (Request from a non-wireless device was dropped due to installed Wireless license)

消息说明: 由于安装的许可证仅适用于无线设备, 因此来自非无线设备的 RADIUS 请求已被丢弃

本地目标消息格式: <timestamp> <seq_num> 11054 WARN RADIUS: Request from a non-wireless device was dropped due to installed Wireless license, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11054 WARN RADIUS: Request from a non-wireless device was dropped due to installed Wireless license, <log details>

- 消息代码: 11055

严重性: 信息 (INFO)

消息文本: 检测到此会话的用户名更改。此会话的属性将从缓存中删除 (User name change detected for the session. Attributes for the session will be removed from the cache)

消息说明: 检测到此会话的用户名更改。此会话的属性将从缓存中删除

本地目标消息格式: <timestamp> <seq_num> 11055 INFO RADIUS: User name change detected for the session. Attributes for the session will be removed from the cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11055 INFO RADIUS: User name change detected for the session. Attributes for the session will be removed from the cache, <log details>

- 消息代码: 11056

严重性: 信息 (INFO)

消息文本: 接收的数据包与之前处理的 (不是最后一个) RADIUS 请求数据包重复 (Duplicate of previously processed (but not the last) RADIUS Request packet received)

消息说明: 接收的数据包与之前处理的 (不是最后一个) RADIUS 请求数据包重复

本地目标消息格式: <timestamp> <seq_num> 11056 INFO RADIUS: Duplicate of previously processed (but not the last) RADIUS Request packet received, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11056 INFO RADIUS: Duplicate of previously processed (but not the last) RADIUS Request packet received, <log details>

- 消息代码: 11057

严重性: 警告 (WARN)

消息文本: 缺少所请求 RADIUS 的 Access-Request (The Access-Request for the requested RADIUS is missing)

消息说明: 请提及 Message-Authenticator RADIUS 属性在允许的协议中配置为必填项

本地目标消息格式: <timestamp> <seq_num> 11057 WARN RADIUS: The Access-Request for the requested RADIUS is missing, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11057 WARN RADIUS: The Access-Request for the requested RADIUS is missing, <log details>

- 消息代码: 11100

严重性: 调试 (DEBUG)

消息文本: RADIUS 客户端即将发送请求 (RADIUS-Client about to send request)

消息说明: RADIUS 客户端即将发送请求

本地目标消息格式: <timestamp> <seq_num> 11100 DEBUG RADIUS-Client: RADIUS-Client about to send request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11100 DEBUG RADIUS-Client: RADIUS-Client about to send request, <log details>

- 消息代码: 11101

严重性: 调试 (DEBUG)

消息文本: RADIUS 客户端已收到响应 (RADIUS-Client received response)

消息说明: RADIUS 客户端已收到响应

本地目标消息格式: <timestamp> <seq_num> 11101 DEBUG RADIUS-Client: RADIUS-Client received response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11101 DEBUG RADIUS-Client: RADIUS-Client received response, <log details>

- 消息代码: 11102

严重性: 调试 (DEBUG)

消息文本: RADIUS 客户端已经以静默方式丢弃无效响应 (RADIUS-Client silently discarded invalid response)

消息说明: RADIUS 客户端已经以静默方式丢弃无效响应

本地目标消息格式: <timestamp> <seq_num> 11102 DEBUG RADIUS-Client: RADIUS-Client silently discarded invalid response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11102 DEBUG RADIUS-Client: RADIUS-Client silently discarded invalid response, <log details>

- 消息代码: 11103

严重性: 错误 (ERROR)

消息文本: RADIUS 客户端在处理流程中遇到错误 (RADIUS-Client encountered error during processing flow)

消息说明: RADIUS 客户端在处理流程中遇到错误

本地目标消息格式: <timestamp> <seq_num> 11103 ERROR RADIUS-Client: RADIUS-Client encountered error during processing flow, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11103 ERROR RADIUS-Client: RADIUS-Client encountered error during processing flow, <log details>

- 消息代码: 11104

严重性: 调试 (DEBUG)

消息文本: RADIUS 客户端请求因超时到期 (RADIUS-Client request timeout expired)

消息说明: RADIUS 客户端请求因超时到期

本地目标消息格式: <timestamp> <seq_num> 11104 DEBUG RADIUS-Client: RADIUS-Client request timeout expired, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11104 DEBUG RADIUS-Client: RADIUS-Client request timeout expired, <log details>

- 消息代码: 11105

严重性: 调试 (DEBUG)

消息文本: 收到来自 ISE 中使用 KeyWrap 配置的设备的请求 (Request received from a device that is configured with KeyWrap in ISE.)

消息说明: 收到来自 ISE 中使用 KeyWrap 配置的设备的请求

本地目标消息格式: <timestamp> <seq_num> 11105 DEBUG RADIUS-Client: Request received from a device that is configured with KeyWrap in ISE., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 11105 DEBUG RADIUS-Client: Request received from a device that is configured with KeyWrap in ISE., <log details>

- 消息代码: 11106

严重性: 调试 (DEBUG)

消息文本: KeyWrap 配置出错 (Error in KeyWrap configuration)

消息说明: KeyWrap 配置出错

本地目标消息格式: <timestamp> <seq_num> 11106 DEBUG RADIUS-Client: Error in KeyWrap configuration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 11106 DEBUG RADIUS-Client: Error in KeyWrap configuration, <log details>

- 消息代码: 11107

严重性: 调试 (DEBUG)

消息文本: 缺少 KeyWrap 所需的属性 (Required attributes for KeyWrap are missing)

消息说明: 缺少 KeyWrap 所需的属性

本地目标消息格式: <timestamp> <seq_num> 11107 DEBUG RADIUS-Client: Required attributes for KeyWrap are missing, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 11107 DEBUG RADIUS-Client: Required attributes for KeyWrap are missing, <log details>

- 消息代码: 11108

严重性: 调试 (DEBUG)

消息文本: 缺少 KeyWrap 必需的 EapMessage 属性 (Missing required EapMessage attribute for KeyWrap)

消息说明: 来自已启用 KeyWrap 的设备的 RADIUS 请求缺少必需的 EapMessage 属性

本地目标消息格式: <timestamp> <seq_num> 11108 DEBUG RADIUS-Client: Missing required EapMessage attribute for KeyWrap, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11108 DEBUG RADIUS-Client: Missing
required EapMessage attribute for KeyWrap, <log details>

- 消息代码: 11109

严重性: 调试 (DEBUG)

消息文本: RADIUS 请求错误地包含 KeyWrap 和 MessageAuthenticator 属性 (RADIUS request
improperly contains both KeyWrap and MessageAuthenticator attributes)

消息说明: RADIUS 请求错误地包含 KeyWrap 和 MessageAuthenticator 属性

本地目标消息格式: <timestamp> <seq_num> 11109 DEBUG RADIUS-Client: RADIUS request
improperly contains both KeyWrap and MessageAuthenticator attributes, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11109 DEBUG RADIUS-Client: RADIUS
request improperly contains both KeyWrap and MessageAuthenticator attributes, <log details>

- 消息代码: 11110

严重性: 调试 (DEBUG)

消息文本: 从启用 KeyWrap 的设备收到请求。KeyWrap 中存在 TunnelPassword 属性。(Request
received from a KeyWrap enabled device. The TunnelPassword attribute is present in KeyWrap.)

消息说明: 从启用 KeyWrap 的设备收到请求。KeyWrap 中存在 TunnelPassword 属性。

本地目标消息格式: <timestamp> <seq_num> 11110 DEBUG RADIUS-Client: Request received from
a KeyWrap enabled device. The TunnelPassword attribute is present in KeyWrap., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11110 DEBUG RADIUS-Client: Request
received from a KeyWrap enabled device. The TunnelPassword attribute is present in KeyWrap., <log
details>

- 消息代码: 11111

严重性: 调试 (DEBUG)

消息文本: 收到包含 KeyWrap 属性的 RADIUS 请求。不过, ISE 中未为发出请求设备配置
KeyWrap。(RADIUS request has been received with KeyWrap attributes. However, KeyWrap is not
configured for the requesting device in ISE.)

消息说明: 收到包含 KeyWrap 属性的 RADIUS 请求。不过, ISE 中未为发出请求设备配置
KeyWrap。

本地目标消息格式: <timestamp> <seq_num> 11111 DEBUG RADIUS-Client: RADIUS request has
been received with KeyWrap attributes. However, KeyWrap is not configured for the requesting device
in ISE., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11111 DEBUG RADIUS-Client: RADIUS
request has been received with KeyWrap attributes. However, KeyWrap is not configured for the requesting
device in ISE., <log details>

- 消息代码: 11112
严重性: 调试 (DEBUG)
消息文本: 已接受来自 PAC_OPAQUE 的 KeyWrap 密钥。(KeyWrap keys accepted from PAC_OPAQUE.)
消息说明: 已接受来自 PAC_OPAQUE 的 KeyWrap 密钥。
本地目标消息格式: <timestamp> <seq_num> 11112 DEBUG RADIUS-Client: KeyWrap keys accepted from PAC_OPAQUE., <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11112 DEBUG RADIUS-Client: KeyWrap keys accepted from PAC_OPAQUE., <log details>
- 消息代码: 11113
严重性: 调试 (DEBUG)
消息文本: KeyWrap 在代理中不受支持。(KeyWrap is not supported in Proxy.)
消息说明: KeyWrap 在代理中不受支持。
本地目标消息格式: <timestamp> <seq_num> 11113 DEBUG RADIUS-Client: KeyWrap is not supported in Proxy., <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11113 DEBUG RADIUS-Client: KeyWrap is not supported in Proxy., <log details>
- 消息代码: 11114
严重性: 调试 (DEBUG)
消息文本: RADIUS 请求数据包中的 KeyWrap 参数与此会话中早期的 KeyWrap 请求不兼容。(KeyWrap parameters on RADIUS request packet are not compatible with the earlier KeyWrap request in this session.)
消息说明: RADIUS 请求数据包中的 KeyWrap 参数与此会话中早期的 KeyWrap 请求不兼容。
本地目标消息格式: <timestamp> <seq_num> 11114 DEBUG RADIUS-Client: KeyWrap parameters on RADIUS request packet are not compatible with the earlier KeyWrap request in this session., <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11114 DEBUG RADIUS-Client: KeyWrap parameters on RADIUS request packet are not compatible with the earlier KeyWrap request in this session., <log details>
- 消息代码: 11115
严重性: 错误 (ERROR)
消息文本: AAA 客户端消息身份验证器代码密钥与配置的 ISE 服务器消息身份验证器代码密钥不匹配。(The AAA Client Message Authenticator Code Key does not match the configured ISE Server Message Authenticator Code Key.)

消息说明: AAA 客户端消息身份验证器代码密钥与配置的 ISE 服务器消息身份验证器代码密钥不匹配。

本地目标消息格式: <timestamp> <seq_num> 11115 ERROR RADIUS: The AAA Client Message Authenticator Code Key does not match the configured ISE Server Message Authenticator Code Key., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11115 ERROR RADIUS: The AAA Client Message Authenticator Code Key does not match the configured ISE Server Message Authenticator Code Key., <log details>

- 消息代码: 11116

严重性: 调试 (DEBUG)

消息文本: 已拼接来自会话缓存的现有会话 (Stitched existing session from Session Cache)

消息说明: 已拼接来自会话缓存的现有会话。会话 ID 已重新使用。

本地目标消息格式: <timestamp> <seq_num> 11116 DEBUG RADIUS: Stitched existing session from Session Cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11116 DEBUG RADIUS: Stitched existing session from Session Cache, <log details>

- 消息代码: 11117

严重性: 调试 (DEBUG)

消息文本: 已生成新的会话 ID (Generated a new session ID)

消息说明: 已生成基于 Radius 属性的新会话 ID

本地目标消息格式: <timestamp> <seq_num> 11117 DEBUG RADIUS: Generated a new session ID, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11117 DEBUG RADIUS: Generated a new session ID, <log details>

- 消息代码: 11200

严重性: 错误 (ERROR)

消息文本: 收到无效的动态授权请求 (Received invalid dynamic authorization request)

消息说明: 收到一个无效的动态授权请求。

本地目标消息格式: <timestamp> <seq_num> 11200 ERROR Dynamic-Authorization: Received invalid dynamic authorization request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11200 ERROR Dynamic-Authorization: Received invalid dynamic authorization request, <log details>

- 消息代码: 11201
严重性: 调试 (DEBUG)
消息文本: 收到断开连接动态授权请求 (Received disconnect dynamic authorization request)
消息说明: 收到一个断开连接动态授权请求
本地目标消息格式: <timestamp> <seq_num> 11201 DEBUG Dynamic-Authorization: Received disconnect dynamic authorization request, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11201 DEBUG Dynamic-Authorization: Received disconnect dynamic authorization request, <log details>
- 消息代码: 11202
严重性: 调试 (DEBUG)
消息文本: 收到断开连接和端口关闭动态授权请求 (Received disconnect and port shutdown dynamic authorization request)
消息说明: 收到一个断开连接和端口关闭动态授权请求
本地目标消息格式: <timestamp> <seq_num> 11202 DEBUG Dynamic-Authorization: Received disconnect and port shutdown dynamic authorization request, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11202 DEBUG Dynamic-Authorization: Received disconnect and port shutdown dynamic authorization request, <log details>
- 消息代码: 11203
严重性: 调试 (DEBUG)
消息文本: 收到断开连接和端口退回动态授权请求 (Received disconnect and port shutdown dynamic authorization request)
消息说明: 收到一个断开连接和端口退回动态授权请求
本地目标消息格式: <timestamp> <seq_num> 11203 DEBUG Dynamic-Authorization: Received disconnect and port bounce dynamic authorization request, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11203 DEBUG Dynamic-Authorization: Received disconnect and port bounce dynamic authorization request, <log details>
- 消息代码: 11204
严重性: 调试 (DEBUG)
消息文本: 收到重新验证请求 (Received reauthenticate request)
消息说明: 收到一个重新验证请求
本地目标消息格式: <timestamp> <seq_num> 11204 DEBUG Dynamic-Authorization: Received reauthenticate request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11204 DEBUG Dynamic-Authorization:
Received reauthenticate request, <log details>

- 消息代码: 11205

严重性: 错误 (ERROR)

消息文本: 找不到网络访问设备 (Could not find Network Access Device)

消息说明: 找不到为应用动态授权更改指定的网络访问设备。

本地目标消息格式: <timestamp> <seq_num> 11205 ERROR Dynamic-Authorization: Could not find
Network Access Device, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11205 ERROR Dynamic-Authorization:
Could not find Network Access Device, <log details>

- 消息代码: 11206

严重性: 错误 (ERROR)

消息文本: 找不到客户端 ISE 节点 (Could not find Client ISE Node)

消息说明: 找不到客户端 ISE 节点。

本地目标消息格式: <timestamp> <seq_num> 11206 ERROR Dynamic-Authorization: Could not find
Client ISE Node, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11206 ERROR Dynamic-Authorization:
Could not find Client ISE Node, <log details>

- 消息代码: 11207

严重性: 调试 (DEBUG)

消息文本: 收到断开连接动态授权响应 (Received disconnect dynamic authorization response)

消息说明: 收到一个断开连接动态授权响应

本地目标消息格式: <timestamp> <seq_num> 11207 DEBUG Dynamic-Authorization: Received
disconnect dynamic authorization response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11207 DEBUG Dynamic-Authorization:
Received disconnect dynamic authorization response, <log details>

- 消息代码: 11208

严重性: 调试 (DEBUG)

消息文本: 收到断开连接和端口关闭动态授权响应 (Received disconnect and port shutdown dynamic
authorization response)

消息说明: 收到一个断开连接和端口关闭动态授权响应

本地目标消息格式: <timestamp> <seq_num> 11208 DEBUG Dynamic-Authorization: Received disconnect and port shutdown dynamic authorization response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11208 DEBUG Dynamic-Authorization: Received disconnect and port shutdown dynamic authorization response, <log details>

- 消息代码: 11209

严重性: 调试 (DEBUG)

消息文本: 收到断开连接和端口退回动态授权响应 (Received disconnect and port shutdown dynamic authorization response)

消息说明: 收到断开连接和端口退回动态授权响应。

本地目标消息格式: <timestamp> <seq_num> 11209 DEBUG Dynamic-Authorization: Received disconnect and port bounce dynamic authorization response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11209 DEBUG Dynamic-Authorization: Received disconnect and port bounce dynamic authorization response, <log details>

- 消息代码: 11210

严重性: 调试 (DEBUG)

消息文本: 收到重新验证响应 (Received reauthenticate response)

消息说明: 收到重新验证响应。

本地目标消息格式: <timestamp> <seq_num> 11210 DEBUG Dynamic-Authorization: Received a reauthenticate response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11210 DEBUG Dynamic-Authorization: Received a reauthenticate response, <log details>

- 消息代码: 11211

严重性: 调试 (DEBUG)

消息文本: 以代理方式向 ISE 中的动态授权客户端发送请求 (Proxying request to Dynamic Authorization Client ISE)

消息说明: 将您的请求转发到 ISE 中的动态授权客户端。

本地目标消息格式: <timestamp> <seq_num> 11211 DEBUG Dynamic-Authorization: Proxying request to Dynamic Authorization Client ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11211 DEBUG Dynamic-Authorization: Proxying request to Dynamic Authorization Client ISE, <log details>

- 消息代码: 11212

严重性: 调试 (DEBUG)

消息文本: 将您的请求转发到网络访问设备 (Forwarding your request to Network Access Device)

消息说明: 将您的请求转发到网络访问设备。

本地目标消息格式: <timestamp> <seq_num> 11212 DEBUG Dynamic-Authorization: Forwarding your request to Network Access Device, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11212 DEBUG Dynamic-Authorization: Forwarding your request to Network Access Device, <log details>

- 消息代码: 11213

严重性: 警告 (WARN)

消息文本: 发送动态授权请求后, 未收到网络访问设备的响应 (No response received from Network Access Device after sending a Dynamic Authorization request)

消息说明: 发送动态授权请求后, 未收到网络访问设备的响应

本地目标消息格式: <timestamp> <seq_num> 11213 WARN Dynamic-Authorization: No response received from Network Access Device after sending a Dynamic Authorization request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11213 WARN Dynamic-Authorization: No response received from Network Access Device after sending a Dynamic Authorization request, <log details>

- 消息代码: 11214

严重性: 警告 (WARN)

消息文本: 从网络访问设备收到的响应无效 (An invalid response received from Network Access Device)

消息说明: 从网络访问设备收到的响应无效。

本地目标消息格式: <timestamp> <seq_num> 11214 WARN Dynamic-Authorization: An invalid response received from Network Access Device, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11214 WARN Dynamic-Authorization: An invalid response received from Network Access Device, <log details>

- 消息代码: 11215

严重性: 警告 (WARN)

消息文本: 未从 ISE 中的动态授权客户端收到响应 (No response has been received from Dynamic Authorization Client in ISE)

消息说明: 未从 ISE 中的动态授权客户端收到响应。

本地目标消息格式: <timestamp> <seq_num> 11215 WARN Dynamic-Authorization: No response has been received from Dynamic Authorization Client in ISE, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11215 WARN Dynamic-Authorization: No
response has been received from Dynamic Authorization Client in ISE, <log details>

- 消息代码: 11216

严重性: 错误 (ERROR)

消息文本: 内部代理 PAC 生成失败 (The Internal Proxy PAC generation has failed)

消息说明: 内部代理 PAC 生成失败。

本地目标消息格式: <timestamp> <seq_num> 11216 ERROR Dynamic-Authorization: The Internal
Proxy PAC generation has failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11216 ERROR Dynamic-Authorization:
The Internal Proxy PAC generation has failed, <log details>

- 消息代码: 11217

严重性: 调试 (DEBUG)

消息文本: 已准备好断开连接动态授权请求 (Prepared the disconnect dynamic authorization request)

消息说明: 已准备好断开连接动态授权请求。

本地目标消息格式: <timestamp> <seq_num> 11217 DEBUG Dynamic-Authorization: Prepared the
disconnect dynamic authorization request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11217 DEBUG Dynamic-Authorization:
Prepared the disconnect dynamic authorization request, <log details>

- 消息代码: 11218

严重性: 调试 (DEBUG)

消息文本: 已准备好断开连接和端口关闭动态授权请求 (Prepared the disconnect and port shutdown
dynamic authorization request)

消息说明: 已准备好断开连接和端口关闭动态授权请求。

本地目标消息格式: <timestamp> <seq_num> 11218 DEBUG Dynamic-Authorization: Prepared the
disconnect and port shutdown dynamic authorization request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11218 DEBUG Dynamic-Authorization:
Prepared the disconnect and port shutdown dynamic authorization request, <log details>

- 消息代码: 11219

严重性: 调试 (DEBUG)

消息文本: 已准备好断开连接和端口退回动态授权请求 (Prepared the disconnect and port bounce
dynamic authorization request)

消息说明：已准备好断开连接和端口退回动态授权请求。

本地目标消息格式：<timestamp> <seq_num> 11219 DEBUG Dynamic-Authorization: Prepared the disconnect and port bounce dynamic authorization request, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11219 DEBUG Dynamic-Authorization: Prepared the disconnect and port bounce dynamic authorization request, <log details>

- 消息代码：11220

严重性：调试 (DEBUG)

消息文本：已准备好重新验证请求 (Prepared the reauthenticate request)

消息说明：已准备好重新验证请求。

本地目标消息格式：<timestamp> <seq_num> 11220 DEBUG Dynamic-Authorization: Prepared the reauthenticate request, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11220 DEBUG Dynamic-Authorization: Prepared the reauthenticate request, <log details>

- 消息代码：11221

严重性：调试 (DEBUG)

消息文本：收到断开连接动态授权 ACK 响应 (Received disconnect dynamic authorization ACK response)

消息说明：收到断开连接动态授权 ACK 响应。

本地目标消息格式：<timestamp> <seq_num> 11221 DEBUG Dynamic-Authorization: Received a disconnect dynamic authorization ACK response, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11221 DEBUG Dynamic-Authorization: Received a disconnect dynamic authorization ACK response, <log details>

- 消息代码：11222

严重性：调试 (DEBUG)

消息文本：收到断开连接动态授权 NAK 响应 (Received disconnect dynamic authorization NAK response)

消息说明：收到断开连接动态授权 NAK 响应。

本地目标消息格式：<timestamp> <seq_num> 11222 DEBUG Dynamic-Authorization: Received a disconnect dynamic authorization NAK response, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11222 DEBUG Dynamic-Authorization: Received a disconnect dynamic authorization NAK response, <log details>

- 消息代码：11223

严重性: 调试 (DEBUG)

消息文本: 收到动态授权 CoA ACK 响应 (Received dynamic authorization CoA ACK response)

消息说明: 收到动态授权 CoA ACK 响应。

本地目标消息格式: <timestamp> <seq_num> 11223 DEBUG Dynamic-Authorization: Received a dynamic authorization CoA ACK response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 11223 DEBUG Dynamic-Authorization: Received a dynamic authorization CoA ACK response, <log details>

- 消息代码: 11224

严重性: 调试 (DEBUG)

消息文本: 收到动态授权 CoA NAK 响应 (Received dynamic authorization CoA NAK response)

消息说明: 收到动态授权 CoA NAK 响应。

本地目标消息格式: <timestamp> <seq_num> 11224 DEBUG Dynamic-Authorization: Received a dynamic authorization CoA NAK response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 11224 DEBUG Dynamic-Authorization: Received a dynamic authorization CoA NAK response, <log details>

- 消息代码: 11225

严重性: 信息 (INFO)

消息文本: 由于出现重大日志记录错误, 动态授权请求被拒绝 (The dynamic authorization request was rejected due to a critical logging error)

消息说明: 由于出现重大日志记录错误, 动态授权请求被拒绝。

本地目标消息格式: <timestamp> <seq_num> 11225 INFO Dynamic-Authorization: The dynamic authorization request was rejected due to a critical logging error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 11225 INFO Dynamic-Authorization: The dynamic authorization request was rejected due to a critical logging error, <log details>

- 消息代码: 11226

严重性: 错误 (ERROR)

消息文本: 已从部署取消注册作为动态授权客户端的 ISE 代理节点 (ISE Proxy Node, functioning as Dynamic Authorization Client, is deregistered from the deployment)

消息说明: 已从部署取消注册作为动态授权客户端的 ISE 代理节点。

本地目标消息格式: <timestamp> <seq_num> 11226 ERROR Dynamic-Authorization: ISE Proxy Node, functioning as Dynamic Authorization Client, is deregistered from the deployment, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 11226 ERROR Dynamic-Authorization: ISE

Proxy Node, functioning as Dynamic Authorization Client, is deregistered from the deployment, <log details>

- 消息代码: 11227

严重性: 错误 (ERROR)

消息文本: 已在部署中将作为动态授权客户端的 ISE 代理节点标记为非活动状态 (ISE Proxy Node, functioning as Dynamic Authorization Client, is marked as inactive in the deployment)

消息说明: 已在部署中将作为动态授权客户端的 ISE 代理节点标记为非活动状态。

本地目标消息格式: <timestamp> <seq_num> 11227 ERROR Dynamic-Authorization: ISE Proxy Node, functioning as Dynamic Authorization Client, is marked as inactive in the deployment, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11227 ERROR Dynamic-Authorization: ISE Proxy Node, functioning as Dynamic Authorization Client, is marked as inactive in the deployment, <log details>

- 消息代码: 11300

严重性: 警告 (WARN)

消息文本: 找不到 TrustSec 设备 (Could not locate TrustSec Device)

消息说明: 使用 SGA ID 找不到 TrustSec 设备。

本地目标消息格式: <timestamp> <seq_num> 11300 WARN SGA: Could not locate TrustSec Device, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11300 WARN SGA: Could not locate TrustSec Device, <log details>

- 消息代码: 11301

严重性: 信息 (INFO)

消息文本: 已找到 TrustSec 设备 (TrustSec Device found)

消息说明: 已成功使用 TrustSec ID 找到了 TrustSec 设备。

本地目标消息格式: <timestamp> <seq_num> 11301 INFO SGA: TrustSec Device found, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11301 INFO SGA: TrustSec Device found, <log details>

- 消息代码: 11302

严重性: 警告 (WARN)

消息文本: 收到不包含 cts-pac-opaque cisco-av-pair 属性的安全 RADIUS 请求 (Received Secure RADIUS request without a cts-pac-opaque cisco-av-pair attribute)

消息说明：此请求不包含以值 cts-pac-opaque 开头的 cisco-av-pair 属性。此值是安全 RADIUS 请求的必需属性。

本地目标消息格式：<timestamp> <seq_num> 11302 WARN RADIUS: Received Secure RADIUS request without a cts-pac-opaque cisco-av-pair attribute, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 11302 WARN RADIUS: Received Secure RADIUS request without a cts-pac-opaque cisco-av-pair attribute, <log details>

- 消息代码：11303

严重性：警告 (WARN)

消息文本：无法解析 cts-pac-opaque 属性 (Could not parse the cts-pac-opaque attribute)

消息说明：未解析包含在安全 RADIUS 请求中的 cts-pac-opaque cisco-av-pair 属性。

本地目标消息格式：<timestamp> <seq_num> 11303 WARN RADIUS: Could not parse the cts-pac-opaque attribute, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 11303 WARN RADIUS: Could not parse the cts-pac-opaque attribute, <log details>

- 消息代码：11304

严重性：警告 (WARN)

消息文本：无法检索请求的安全组标签 (Could not retrieve requested Security Group Tag)

消息说明：安全组标签请求包含一个不存在的值。

本地目标消息格式：<timestamp> <seq_num> 11304 WARN SGA: Could not retrieve requested Security Group Tag, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 11304 WARN SGA: Could not retrieve requested Security Group Tag, <log details>

- 消息代码：11305

严重性：信息 (INFO)

消息文本：无法检索请求的安全组 ACL (Could not retrieve requested Security Group ACL)

消息说明：安全组 ACL 请求包含一个不存在的值。

本地目标消息格式：<timestamp> <seq_num> 11305 INFO SGA: Could not retrieve requested Security Group ACL, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 11305 INFO SGA: Could not retrieve requested Security Group ACL, <log details>

- 消息代码：11306

严重性: 警告 (WARN)

消息文本: PAC 已过期 (PAC has expired)

消息说明: cts-pac-opaque RADIUS 属性中收到的 PAC 已过期。

本地目标消息格式: <timestamp> <seq_num> 11306 WARN RADIUS: PAC has expired, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11306 WARN RADIUS: PAC has expired,
<log details>

- 消息代码: 11307

严重性: 错误 (ERROR)

消息文本: RADIUS CHAP 属性不正确 (Incorrect RADIUS CHAP attribute)

消息说明: RADIUS CHAP 属性不正确。

本地目标消息格式: <timestamp> <seq_num> 11307 ERROR RADIUS: Incorrect RADIUS CHAP attribute, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11307 ERROR RADIUS: Incorrect RADIUS CHAP attribute, <log details>

- 消息代码: 11308

严重性: 错误 (ERROR)

消息文本: RADIUS MS-CHAP v1 属性不正确 (Incorrect RADIUS MS-CHAP v1 attribute)

消息说明: RADIUS MS-CHAP v1 属性不正确。

本地目标消息格式: <timestamp> <seq_num> 11308 ERROR RADIUS: Incorrect RADIUS MS-CHAP v1 attribute, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11308 ERROR RADIUS: Incorrect RADIUS MS-CHAP v1 attribute, <log details>

- 消息代码: 11309

严重性: 错误 (ERROR)

消息文本: RADIUS MS-CHAP v2 属性不正确 (Incorrect RADIUS MS-CHAP v2 attribute)

消息说明: RADIUS MS-CHAP v2 属性不正确。

本地目标消息格式: <timestamp> <seq_num> 11309 ERROR RADIUS: Incorrect RADIUS MS-CHAP v2 attribute, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11309 ERROR RADIUS: Incorrect RADIUS MS-CHAP v2 attribute, <log details>

- 消息代码: 11310
 - 严重性: 信息 (INFO)
 - 消息文本: 已向客户端发送安全组访问控制列表 (Sent Security Group Access Control List to client)
 - 消息说明: 已成功向客户端发送安全组访问控制列表。
 - 本地目标消息格式: <timestamp> <seq_num> 11310 INFO SGA: Sent Security Group Access Control List to client, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11310 INFO SGA: Sent Security Group Access Control List to client, <log details>

- 消息代码: 11311
 - 严重性: 信息 (INFO)
 - 消息文本: 找不到安全组访问控制列表的 ACE (Failed to locate ACE of Security Group Access Control List)
 - 消息说明: 在安全组访问控制列表中找不到 ACE 号。
 - 本地目标消息格式: <timestamp> <seq_num> 11311 INFO SGA: Failed to locate ACE of Security Group Access Control List, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11311 INFO SGA: Failed to locate ACE of Security Group Access Control List, <log details>

- 消息代码: 11312
 - 严重性: 信息 (INFO)
 - 消息文本: 已向客户端发送安全组访问控制列表数据片段; 正在等待后续请求以下载剩余 ACE (Sent fragmented Security Group Access Control List data to client; awaiting follow-up request to download remaining ACEs)
 - 消息说明: 已成功向客户端发送安全组访问控制列表数据片段。
 - 本地目标消息格式: <timestamp> <seq_num> 11312 INFO SGA: Sent fragmented Security Group Access Control List data to client; awaiting follow-up request to download remaining ACEs, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11312 INFO SGA: Sent fragmented Security Group Access Control List data to client; awaiting follow-up request to download remaining ACEs, <log details>

- 消息代码: 11313
 - 严重性: 警告 (WARN)
 - 消息文本: ISE 检测到为网络设备或终端调配了未知的 SGT。(ISE detected that the Unknown SGT was provisioned to a network device or endpoint.)
 - 消息说明: ISE 在授权流程中调配了未知的 SGT。不应将未知 SGT 指定为已知流程的一部分

本地目标消息格式: <timestamp> <seq_num> 11313 WARN SGA: ISE detected that the Unknown SGT was provisioned to a network device or endpoint., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11313 WARN SGA: ISE detected that the Unknown SGT was provisioned to a network device or endpoint., <log details>

- 消息代码: 11314

严重性: 警告 (WARN)

消息文本: ISE 检测到格式不正确的 TrustSec PAC。(ISE detected a malformed TrustSec PAC.)

消息说明: ISE 无法解析从设备收到的 TrustSec PAC。

本地目标消息格式: <timestamp> <seq_num> 11314 WARN SGA: ISE detected a malformed TrustSec PAC., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11314 WARN SGA: ISE detected a malformed TrustSec PAC., <log details>

- 消息代码: 11315

严重性: 警告 (WARN)

消息文本: TrustSec 环境数据请求失败 (TrustSec environment data request failed)

消息说明: ISE 收到非法环境数据请求

本地目标消息格式: <timestamp> <seq_num> 11315 WARN SGA: TrustSec environment data request failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11315 WARN SGA: TrustSec environment data request failed, <log details>

- 消息代码: 11316

严重性: 警告 (WARN)

消息文本: 已忽略 TrustSec CoA 消息 (TrustSec CoA message ignored)

消息说明: ISE 发送了 TrustSec CoA 信息但未收到响应。验证网络设备是否支持 CoA。查看网络设备配置

本地目标消息格式: <timestamp> <seq_num> 11316 WARN SGA: TrustSec CoA message ignored, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11316 WARN SGA: TrustSec CoA message ignored, <log details>

- 消息代码: 11317

严重性: 警告 (WARN)

消息文本: TrustSec SSH 连接失败 (TrustSec SSH connection failed)

消息说明: ISE 无法建立与网络设备的 SSH 连接。验证“网络设备”页面中的网络设备 SSH 凭据类似于在网络设备上配置的凭证。通过 ISE (IP 地址) 检查网络设备是否已启用 SSH 连接

本地目标消息格式: <timestamp> <seq_num> 11317 WARN SGA: TrustSec SSH connection failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11317 WARN SGA: TrustSec SSH connection failed, <log details>

- 消息代码: 11318

严重性: 警告 (WARN)

消息文本: 某些 TrustSec 网络设备没有最新的 ISE IP-SGT 映射配置 (Some TrustSec network devices don't have the latest ISE IP-SGT mapping configuration)

消息说明: ISE 识别到某些网络设备拥有与 ISE 不同的 IP-SGT 映射集。使用 IP-SGT 映射部署选项更新设备

本地目标消息格式: <timestamp> <seq_num> 11318 WARN SGA: Some TrustSec network devices don't have the latest ISE IP-SGT mapping configuration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11318 WARN SGA: Some TrustSec network devices don't have the latest ISE IP-SGT mapping configuration, <log details>

- 消息代码: 11320

严重性: 调试 (DEBUG)

消息文本: 已向客户端发送环境数据片段; 正在等待后续请求以下载剩余数据 (Sent fragmented Environment data to client; awaiting follow-up request to download remaining data)

消息说明: 已成功向客户端发送环境数据片段。

本地目标消息格式: <timestamp> <seq_num> 11320 DEBUG SGA: Sent fragmented Environment data to client; awaiting follow-up request to download remaining data, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11320 DEBUG SGA: Sent fragmented Environment data to client; awaiting follow-up request to download remaining data, <log details>

- 消息代码: 11321

严重性: 警告 (WARN)

消息文本: TrustSec 默认出口策略被更改 (TrustSec default egress policy was modified)

消息说明: TrustSec 默认出口策略信元被更改, 请确保它与您的安全策略一致

本地目标消息格式: <timestamp> <seq_num> 11321 WARN SGA: TrustSec default egress policy was modified, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11321 WARN SGA: TrustSec default egress
policy was modified, <log details>

- 消息代码: 11322

严重性: 信息 (INFO)

消息文本: Trustsec 出口策略已成功下载 (Trustsec egress policy was successfully downloaded)

消息说明: Trustsec 出口策略已成功下载

本地目标消息格式: <timestamp> <seq_num> 11322 INFO SGA: Trustsec egress policy was successfully
downloaded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11322 INFO SGA: Trustsec egress policy
was successfully downloaded, <log details>

- 消息代码: 11323

严重性: 信息 (INFO)

消息文本: 未能下载 Trustsec 出口策略 (Failed to download Trustsec egress policy)

消息说明: 未能下载 Trustsec 出口策略

本地目标消息格式: <timestamp> <seq_num> 11323 INFO SGA: Failed to download Trustsec egress
policy, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11323 INFO SGA: Failed to download
Trustsec egress policy, <log details>

- 消息代码: 11324

严重性: 警告 (WARN)

消息文本: 未能发送有关工作流程操作的邮件 (Failed to send mail regarding workflow operation)

消息说明: 未能发送有关工作流程操作的邮件

本地目标消息格式: <timestamp> <seq_num> 11324 WARN SGA: Failed to send mail regarding
workflow operation, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11324 WARN SGA: Failed to send mail
regarding workflow operation, <log details>

- 消息代码: 11325

严重性: 信息 (INFO)

消息文本: Trustsec 安全组访问控制列表 (SGACL) 已成功下载 (Trustsec security group access
control list (SGACL) was successfully downloaded)

消息说明: 已成功向客户端发送安全组访问控制列表数据。

本地目标消息格式: <timestamp> <seq_num> 11325 INFO SGA: Trustsec security group access control list (SGACL) was successfully downloaded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11325 INFO SGA: Trustsec security group access control list (SGACL) was successfully downloaded, <log details>

- 消息代码: 11350

严重性: 警告 (WARN)

消息文本: 检测到代理循环; 正在丢弃请求 (Detected proxy loop; dropping request)

消息说明: ISE 检测到代理循环, 因此 ISE 服务器的 IP 地址已存在于曾转发此 RADIUS 请求的 RADIUS 代理服务器序列中。为避免在无尽的代理循环中毫无意义地继续转发此请求, ISE 已将其丢弃。

本地目标消息格式: <timestamp> <seq_num> 11350 WARN RADIUS-Proxy: Detected proxy loop; dropping request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11350 WARN RADIUS-Proxy: Detected proxy loop; dropping request, <log details>

- 消息代码: 11351

严重性: 警告 (WARN)

消息文本: 无法读取 RADIUS 服务器序列配置; 正在丢弃请求 (Failed to read RADIUS server sequence configuration; dropping request)

消息说明: 在尝试读取 RADIUS 服务器序列配置时, ISE 检测到错误。正在丢弃请求。

本地目标消息格式: <timestamp> <seq_num> 11351 WARN RADIUS-Proxy: Failed to read RADIUS server sequence configuration; dropping request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11351 WARN RADIUS-Proxy: Failed to read RADIUS server sequence configuration; dropping request, <log details>

- 消息代码: 11352

严重性: 警告 (WARN)

消息文本: 响应 Proxy-State 属性验证失败 (Response Proxy-State attribute validation failed)

消息说明: 响应 Proxy-State 属性必须包含此 ISE 标记才能验证来自外部 RADIUS 服务器的请求是否与其发送的请求匹配。验证失败。正在丢弃请求。

本地目标消息格式: <timestamp> <seq_num> 11352 WARN RADIUS-Proxy: Response Proxy-State attribute validation failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11352 WARN RADIUS-Proxy: Response Proxy-State attribute validation failed, <log details>

- 消息代码: 11353
 - 严重性: 警告 (WARN)
 - 消息文本: 没有其他外部 RADIUS 服务器; 无法执行故障转移 (No more external RADIUS servers; can't perform failover)
 - 消息说明: 没有配置其他外部 RADIUS 服务器, 因此不能执行故障转移。正在丢弃请求。
 - 本地目标消息格式: <timestamp> <seq_num> 11353 WARN RADIUS-Proxy: No more external RADIUS servers; can't perform failover, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11353 WARN RADIUS-Proxy: No more external RADIUS servers; can't perform failover, <log details>
- 消息代码: 11354
 - 严重性: 警告 (WARN)
 - 消息文本: 收到记帐请求, 但本地和远程记帐均未配置 (Accounting request received but neither local nor remote accounting is configured.)
 - 消息说明: 收到记帐请求, 但本地和远程记帐均未配置。
 - 本地目标消息格式: <timestamp> <seq_num> 11354 WARN RADIUS-Proxy: Accounting request received but neither local nor remote accounting is configured, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11354 WARN RADIUS-Proxy: Accounting request received but neither local nor remote accounting is configured, <log details>
- 消息代码: 11355
 - 严重性: 信息 (INFO)
 - 消息文本: 开始将请求转发给远程 RADIUS 服务器 (Start forwarding request to remote RADIUS server)
 - 消息说明: 请求正在从为选定的 ISE 代理服务配置的列表中转发到下一个远程 RADIUS 服务器。
 - 本地目标消息格式: <timestamp> <seq_num> 11355 INFO RADIUS-Proxy: Start forwarding request to remote RADIUS server, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11355 INFO RADIUS-Proxy: Start forwarding request to remote RADIUS server, <log details>
- 消息代码: 11356
 - 严重性: 警告 (WARN)
 - 消息文本: 无法将请求转发到当前的远程 RADIUS 服务器 (Failed to forward request to current remote TACACS server)

消息说明：由于以下原因，当前的远程 RADIUS 服务器无法处理转发的请求：远程 RADIUS 服务器关闭；未正确配置远程 RADIUS 服务器；远程 RADIUS 服务器已丢弃请求。

本地目标消息格式：<timestamp> <seq_num> 11356 WARN RADIUS-Proxy: Failed to forward request to current remote RADIUS server, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 11356 WARN RADIUS-Proxy: Failed to forward request to current remote RADIUS server, <log details>

- 消息代码：11357

严重性：信息 (INFO)

消息文本：已成功向当前的远程 RADIUS 服务器转发请求 (Successfully forwarded request to current remote RADIUS server)

消息说明：当前的远程 RADIUS 服务器已成功处理转发的请求并回复有效的响应，响应正在转发回 NAS。

本地目标消息格式：<timestamp> <seq_num> 11357 INFO RADIUS-Proxy: Successfully forwarded request to current remote RADIUS server, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 11357 INFO RADIUS-Proxy: Successfully forwarded request to current remote RADIUS server, <log details>

- 消息代码：11358

严重性：信息 (INFO)

消息文本：收到 RADIUS 服务器序列请求。(Received request for RADIUS server sequence.)

消息说明：RADIUS 服务器序列已收到传入请求。正在验证请求并准备将其转发到已配置的外部 RADIUS 服务器。

本地目标消息格式：<timestamp> <seq_num> 11358 INFO RADIUS-Proxy: Received request for RADIUS server sequence., <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 11358 INFO RADIUS-Proxy: Received request for RADIUS server sequence., <log details>

- 消息代码：11359

严重性：信息 (INFO)

消息文本：无法向当前的远程 RADIUS 服务器转发请求；收到无效的响应 (Failed to forward request to current remote RADIUS server; an invalid response was received)

消息说明：当前的远程 RADIUS 服务器已回复无效的响应，响应将转发到下一个远程 RADIUS 服务器（如果有）。

本地目标消息格式：<timestamp> <seq_num> 11359 INFO RADIUS-Proxy: Failed to forward request to current remote RADIUS server; an invalid response was received, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11359 INFO RADIUS-Proxy: Failed to forward request to current remote RADIUS server; an invalid response was received, <log details>

- 消息代码: 11360

严重性: 警告 (WARN)

消息文本: RADIUS 服务器序列无法验证传入请求 (RADIUS server sequence failed to validate incoming request)

消息说明: RADIUS 服务器序列无法验证传入请求。

本地目标消息格式: <timestamp> <seq_num> 11360 WARN RADIUS-Proxy: RADIUS server sequence failed to validate incoming request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11360 WARN RADIUS-Proxy: RADIUS server sequence failed to validate incoming request, <log details>

- 消息代码: 11361

严重性: 信息 (INFO)

消息文本: 传入身份验证请求有效 (Valid incoming authentication request)

消息说明: RADIUS 服务器序列收到有效的传入身份验证请求。

本地目标消息格式: <timestamp> <seq_num> 11361 INFO RADIUS-Proxy: Valid incoming authentication request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11361 INFO RADIUS-Proxy: Valid incoming authentication request, <log details>

- 消息代码: 11362

严重性: 信息 (INFO)

消息文本: 传入记帐请求有效 (Valid incoming accounting request)

消息说明: RADIUS 服务器序列收到有效的传入记帐请求。

本地目标消息格式: <timestamp> <seq_num> 11362 INFO RADIUS-Proxy: Valid incoming accounting request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11362 INFO RADIUS-Proxy: Valid incoming accounting request, <log details>

- 消息代码: 11363

严重性: 信息 (INFO)

消息文本: RADIUS 服务器序列正在执行本地记账 (RADIUS server sequence performing local accounting)

消息说明: RADIUS 服务器序列正在基于收到的传入记账请求执行本地记账。

本地目标消息格式: <timestamp> <seq_num> 11363 INFO RADIUS-Proxy: RADIUS server sequence performing local accounting, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11363 INFO RADIUS-Proxy: RADIUS server sequence performing local accounting, <log details>

- 消息代码: 11364

严重性: 信息 (INFO)

消息文本: RADIUS 服务器序列正在执行远程记账 (RADIUS server sequence performing remote accounting)

消息说明: RADIUS 服务器序列正在基于收到的传入记账请求执行远程记账。

本地目标消息格式: <timestamp> <seq_num> 11364 INFO RADIUS-Proxy: RADIUS server sequence performing remote accounting, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11364 INFO RADIUS-Proxy: RADIUS server sequence performing remote accounting, <log details>

- 消息代码: 11365

严重性: 信息 (INFO)

消息文本: 向外部 RADIUS 服务器发送请求之前先修改属性 (Modify attributes before sending request to external radius server)

消息说明: RADIUS 服务器序列正在修改属性, 之后再向外部 RADIUS 服务器发送请求

本地目标消息格式: <timestamp> <seq_num> 11365 INFO RADIUS-Proxy: Modify attributes before sending request to external radius server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11365 INFO RADIUS-Proxy: Modify attributes before sending request to external radius server, <log details>

- 消息代码: 11366

严重性: 信息 (INFO)

消息文本: 发送 RADIUS 访问接受之前先修改属性

消息说明: RADIUS 服务器序列正在修改属性, 之后再发送 RADIUS 接受。

本地目标消息格式: <timestamp> <seq_num> 11366 INFO RADIUS-Proxy: Modify attributes before sending RADIUS Access-Accept, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11366 INFO RADIUS-Proxy: Modify attributes before sending RADIUS Access-Accept, <log details>

- 消息代码: 11367

严重性: 信息 (INFO)

消息文本: 无法添加属性, 因为属性已存在 (Could not add attribute(s) since attribute already exist)

消息说明: 由于属性已存在, 且不允许存在多个属性, 因此无法向请求添加属性。

本地目标消息格式: <timestamp> <seq_num> 11367 INFO RADIUS-Proxy: Could not add attribute(s) since attribute already exist, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11367 INFO RADIUS-Proxy: Could not add attribute(s) since attribute already exist, <log details>

• 消息代码: 11368

严重性: 调试 (DEBUG)

消息文本: 请在外部 RADIUS 服务器上查看日志, 以确定准确的故障原因。(Please review logs on the External RADIUS Server to determine the precise failure reason.)

消息说明: 请在外部 RADIUS 服务器上查看日志, 以确定准确的故障原因。

本地目标消息格式: <timestamp> <seq_num> 11368 DEBUG RADIUS-Proxy: Please review logs on the External RADIUS Server to determine the precise failure reason., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11368 DEBUG RADIUS-Proxy: Please review logs on the External RADIUS Server to determine the precise failure reason., <log details>

• 消息代码: 11369

严重性: 警告 (WARN)

消息文本: 代理请求被拒绝, 因为处理之前相关 EAP 消息的外部 RADIUS 服务器现已停机 (Proxy request was rejected, as the external RADIUS server that handled previous related EAP messages is now down)

消息说明: ISE 收到 RADIUS 代理请求, 但处理之前相关 EAP 消息的外部 RADIUS 服务器现已停机。由于缺少之前 EAP 消息的上下文, 因此向其他外部 RADIUS 服务器发送此请求没有意义。

本地目标消息格式: <timestamp> <seq_num> 11369 WARN RADIUS-Proxy: Proxy request was rejected, as the external RADIUS server that handled previous related EAP messages is now down, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11369 WARN RADIUS-Proxy: Proxy request was rejected, as the external RADIUS server that handled previous related EAP messages is now down, <log details>

• 消息代码: 11400

严重性: 警告 (WARN)

消息文本: “允许的协议” 不允许更改 EAP-MSCHAP 密码 (EAP-MSCHAP password change not allowed by the Allowed Protocols)

消息说明：尝试更改密码失败，因为“允许的协议”中禁用了更改 MS-CHAPv2 内部方法的密码。

本地目标消息格式：<timestamp> <seq_num> 11400 WARN EAP: EAP-MSCHAP password change not allowed by the Allowed Protocols, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11400 WARN EAP: EAP-MSCHAP password change not allowed by the Allowed Protocols, <log details>

- 消息代码：11401

严重性：信息 (INFO)

消息文本：已于带内 PAC 调配成功后准备好“RADIUS 访问-拒绝” (Prepared RADIUS Access-Reject after the successful in-band PAC provisioning)

消息说明：作为标准带内 PAC 调配行为的一部分，即使 PAC 请求成功获得批准，系统也会返回“EAP-失败”和“RADIUS 访问-拒绝”结果。很明显，这是误导性的结果值，但这是正常的，它不表示真正失败，您可以/应该忽略它，不会出现安全问题。（当用户尝试使用当前调配的 PAC 实际进行身份验证时，ISE 日志很可能随之显示 EAP-FAST 对话。）

本地目标消息格式：<timestamp> <seq_num> 11401 INFO EAP: Prepared RADIUS Access-Reject after the successful in-band PAC provisioning, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11401 INFO EAP: Prepared RADIUS Access-Reject after the successful in-band PAC provisioning, <log details>

- 消息代码：11402

严重性：警告 (WARN)

消息文本：“允许的协议”不允许更改 EAP-GTC 密码 (EAP-GTC password change not allowed by the Allowed Protocols)

消息说明：尝试更改密码失败，因为相关“允许的协议”不允许更改 EAP-GTC 内部方法的密码。

本地目标消息格式：<timestamp> <seq_num> 11402 WARN EAP: EAP-GTC password change not allowed by the Allowed Protocols, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11402 WARN EAP: EAP-GTC password change not allowed by the Allowed Protocols, <log details>

- 消息代码：11500

严重性：警告 (WARN)

消息文本：收到无效或意外的 EAP 负载 (Invalid or unexpected EAP payload received)

消息说明：内部错误，可能来自请求方：无法验证 EAP 负载。

本地目标消息格式：<timestamp> <seq_num> 11500 WARN EAP: Invalid or unexpected EAP payload received, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11500 WARN EAP: Invalid or unexpected
EAP payload received, <log details>

- 消息代码: 11501

严重性: 警告 (WARN)

消息文本: 无效的 EAP 负载 (Invalid EAP payload)

消息说明: 内部错误, 可能来自请求方: 无法验证 EAP 负载。

本地目标消息格式: <timestamp> <seq_num> 11501 WARN EAP: Invalid EAP payload, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11501 WARN EAP: Invalid EAP payload,
<log details>

- 消息代码: 11502

严重性: 警告 (WARN)

消息文本: EAP 数据包含有无效的类型 (EAP packet contains invalid type)

消息说明: 内部错误, 可能来自请求方: EAP 数据包包含无效的 EAP 类型; 找不到对应的协议
处理程序。

本地目标消息格式: <timestamp> <seq_num> 11502 WARN EAP: EAP packet contains invalid type,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11502 WARN EAP: EAP packet contains
invalid type, <log details>

- 消息代码: 11503

严重性: 信息 (INFO)

消息文本: 已准备好 EAP 成功 (Prepared EAP-Success)

消息说明: 已创建 EAP 成功数据包, 该数据包将附加到 RADIUS 消息中。

本地目标消息格式: <timestamp> <seq_num> 11503 INFO EAP: Prepared EAP-Success, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11503 INFO EAP: Prepared EAP-Success,
<log details>

- 消息代码: 11504

严重性: 信息 (INFO)

消息文本: 已准备好 EAP 失败 (Prepared EAP-Failure)

消息说明: 已创建 EAP 成功数据包, 该数据包将附加到 RADIUS 消息中。

本地目标消息格式: <timestamp> <seq_num> 11504 INFO EAP: Prepared EAP-Failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11504 INFO EAP: Prepared EAP-Failure,
<log details>

- 消息代码: 11506

严重性: 信息 (INFO)

消息文本: 已准备 EAP 请求/身份 (Prepared EAP-Request/Identity)

消息说明: 已创建 EAP 请求/身份数据包, 该数据包将附加到 RADIUS 消息中。

本地目标消息格式: <timestamp> <seq_num> 11506 INFO EAP: Prepared EAP-Request/Identity,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11506 INFO EAP: Prepared
EAP-Request/Identity, <log details>

- 消息代码: 11507

严重性: 信息 (INFO)

消息文本: 已提取 EAP 响应/身份 (Extracted EAP-Response/Identity)

消息说明: 已从 RADIUS 消息中提取 EAP 响应/身份数据包。

本地目标消息格式: <timestamp> <seq_num> 11507 INFO EAP: Extracted EAP-Response/Identity,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11507 INFO EAP: Extracted
EAP-Response/Identity, <log details>

- 消息代码: 11508

严重性: 警告 (WARN)

消息文本: EAP 响应/身份包含无效的身份数据 (EAP-Response/Identity contains invalid identity data)

消息说明: 作为回退处理的一部分, 由于 PAC 无效, 内部方法提取了 EAP 响应/身份数据包。由于此数据包的身份数据与最初收到的身份不匹配, 因此被视为无效。

本地目标消息格式: <timestamp> <seq_num> 11508 WARN EAP: EAP-Response/Identity contains
invalid identity data, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11508 WARN EAP: EAP-Response/Identity
contains invalid identity data, <log details>

- 消息代码: 11509

严重性: 警告 (WARN)

消息文本: “允许的协议” 不允许任何 EAP 协议 (Allowed Protocols does not allow any EAP protocols)

消息说明: EAP 协商失败, 因为“允许的协议”没有启用基于 EAP 的协议。

本地目标消息格式: <timestamp> <seq_num> 11509 WARN EAP: Allowed Protocols does not allow any EAP protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11509 WARN EAP: Allowed Protocols does not allow any EAP protocols, <log details>

- 消息代码: 11510

严重性: 警告 (WARN)

消息文本: 请求方已拒绝身份验证策略选择的 EAP 方法, 但未提议其他方法; EAP 协商失败 (Supplicant declined EAP method selected by Authentication Policy but did not propose another one; EAP negotiation failed)

消息说明: 在之前的 EAP 消息中, ISE 启动了身份验证策略选择的 EAP 方法。请求方通过发送 EAP NAK 消息拒绝了此 EAP 方法, 但未提议准备执行的其他 EAP 方法。因此, EAP 协商失败。

本地目标消息格式: <timestamp> <seq_num> 11510 WARN EAP: Supplicant declined EAP method selected by Authentication Policy but did not propose another one; EAP negotiation failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11510 WARN EAP: Supplicant declined EAP method selected by Authentication Policy but did not propose another one; EAP negotiation failed, <log details>

- 消息代码: 11511

严重性: 警告 (WARN)

消息文本: 已提取的 EAP 响应/NAK 数据包未请求任何 EAP 协议; EAP 协商失败 (Extracted EAP-Response/NAK packet not requesting any EAP protocols; EAP-negotiation failed)

消息说明: 从 RADIUS 消息中提取了无效的 EAP 响应/NAK 数据包。此数据包拒绝了较早提供的基于 EAP 的协议。然而, 根据客户端请求方的配置, 它并不请求任何其他协议。

本地目标消息格式: <timestamp> <seq_num> 11511 WARN EAP: Extracted EAP-Response/NAK packet not requesting any EAP protocols; EAP-negotiation failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11511 WARN EAP: Extracted EAP-Response/NAK packet not requesting any EAP protocols; EAP-negotiation failed, <log details>

- 消息代码: 11512

严重性: 信息 (INFO)

消息文本: 已提取的 EAP 响应/NAK 数据包请求使用不受支持的 EAP 协议; EAP 协商失败 (Extracted EAP-Response/NAK packet requesting to use unsupported EAP protocol; EAP-negotiation failed)

消息说明: 从 RADIUS 消息中提取的 EAP 响应/NAK 数据包拒绝之前提议的基于 EAP 的协议，且根据客户端请求方的配置，请求改为使用其他协议。但是，ISE 目前不支持所请求的基于 EAP 的协议。

本地目标消息格式: <timestamp> <seq_num> 11512 INFO EAP: Extracted EAP-Response/NAK packet requesting to use unsupported EAP protocol; EAP-negotiation failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11512 INFO EAP: Extracted EAP-Response/NAK packet requesting to use unsupported EAP protocol; EAP-negotiation failed, <log details>

- **消息代码:** 11513

严重性: 警告 (WARN)

消息文本: 在当前 EAP 对话中提取了第二个 EAP 响应/NAK; EAP 协商失败 (Extracted second EAP-Response/NAK in current EAP conversation; failed to negotiate EAP)

消息说明: 在当前 EAP 对话中，第二次从 RADIUS 消息中提取 EAP 响应/NAK 数据包并拒绝之前提议的基于 EAP 的协议。

本地目标消息格式: <timestamp> <seq_num> 11513 WARN EAP: Extracted second EAP-Response/NAK in current EAP conversation; failed to negotiate EAP, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11513 WARN EAP: Extracted second EAP-Response/NAK in current EAP conversation; failed to negotiate EAP, <log details>

- **消息代码:** 11514

严重性: 警告 (WARN)

消息文本: 意外收到空 TLS 消息; 视为客户端拒绝 (Unexpectedly received empty TLS message; treating as a rejection by the client)

消息说明: 当尝试与客户端协商 TLS 握手时，ISE 期望收到非空 TLS 消息或 TLS 警报消息，但收到空 TLS 消息。这可能是因为 ISE 和请求方在实施协议方面存在不一致。例如，有一个已知的问题是，XP 请求方发送空 TLS 消息而不是非空 TLS 提示消息。也可能是所涉及的请求方由于某种原因不信任 ISE 服务器证书。ISE 将意外消息视作客户端拒绝建立隧道的信号。

本地目标消息格式: <timestamp> <seq_num> 11514 WARN EAP: Unexpectedly received empty TLS message; treating as a rejection by the client, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11514 WARN EAP: Unexpectedly received empty TLS message; treating as a rejection by the client, <log details>

- **消息代码:** 11515

严重性: 警告 (WARN)

消息文本: 请求方已拒绝身份验证策略选择的 EAP 方法，但未提议其他方法; EAP 协商失败 (Supplicant declined inner EAP method selected by Authentication Policy but did not proposed another one; inner EAP negotiation failed)

消息说明：在之前的内部 EAP 消息中，ISE 启动了身份验证策略选择的内部 EAP 方法。请求方通过发送 EAP NAK 消息拒绝了此内部 EAP 方法，但未提议准备执行的其他内部 EAP 方法。因此，内部 EAP 协商失败。

本地目标消息格式：<timestamp> <seq_num> 11515 WARN EAP: Supplicant declined inner EAP method selected by Authentication Policy but did not proposed another one; inner EAP negotiation failed, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11515 WARN EAP: Supplicant declined inner EAP method selected by Authentication Policy but did not proposed another one; inner EAP negotiation failed, <log details>

- 消息代码：11516

严重性：警告 (WARN)

消息文本：已提取的 EAP 响应/NAK 数据包未为内部 EAP 方法请求任何 EAP 协议；EAP 协商失败 (Extracted EAP-Response/NAK packet not requesting any EAP protocols for inner EAP method; inner EAP-negotiation failed)

消息说明：从在外部 EAP 方法中遇到的 EAP 响应数据包中，提取的 EAP 响应/NAK 数据包拒绝之前为内部 EAP 方法提议的基于 EAP 的协议，但（根据客户端请求方的配置）未请求任何其他协议。内部 EAP 方法协商失败。

本地目标消息格式：<timestamp> <seq_num> 11516 WARN EAP: Extracted EAP-Response/NAK packet not requesting any EAP protocols for inner EAP method; inner EAP-negotiation failed, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11516 WARN EAP: Extracted EAP-Response/NAK packet not requesting any EAP protocols for inner EAP method; inner EAP-negotiation failed, <log details>

- 消息代码：11517

严重性：警告 (WARN)

消息文本：已提取的 EAP 响应/NAK 数据包请求使用不受支持的内部 EAP 协议；内部 EAP 协商失败 (Extracted EAP-Response/NAK packet requesting to use unsupported inner EAP protocol; inner EAP-negotiation failed)

消息说明：从在外部 EAP 方法中遇到的 EAP 响应数据包中，提取的 EAP 响应/NAK 数据包拒绝之前为内部 EAP 方法提议的基于 EAP 的协议，并根据客户端请求方的配置请求改为使用其他协议。但是，ISE 目前不支持所请求的基于内部 EAP 的协议。内部 EAP 方法协商失败。

本地目标消息格式：<timestamp> <seq_num> 11517 WARN EAP: Extracted EAP-Response/NAK packet requesting to use unsupported inner EAP protocol; inner EAP-negotiation failed, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11517 WARN EAP: Extracted EAP-Response/NAK packet requesting to use unsupported inner EAP protocol; inner EAP-negotiation failed, <log details>

• 消息代码: 11518

严重性: 警告 (WARN)

消息文本: 在当前内部 EAP 对话中提取了第二个 EAP 响应/NAK; 内部 EAP 协商失败 (Extracted second EAP-Response/NAK in current inner EAP conversation; inner EAP-negotiation failed)

消息说明: 在当前内部 EAP 对话中, 第二次从外部 EAP 方法中提取 EAP 响应数据包并拒绝之前为内部 EAP 方法提议的基于 EAP 的协议。内部 EAP 方法协商失败。

本地目标消息格式: <timestamp> <seq_num> 11518 WARN EAP: Extracted second EAP-Response/NAK in current inner EAP conversation; inner EAP-negotiation failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11518 WARN EAP: Extracted second EAP-Response/NAK in current inner EAP conversation; inner EAP-negotiation failed, <log details>

• 消息代码: 11519

严重性: 信息 (INFO)

消息文本: 已为内部 EAP 方法准备好 EAP 成功 (Prepared EAP-Success for inner EAP method)

消息说明: 已创建 EAP 成功数据包, 用于封装到外部 EAP 方法的传出 EAP 请求数据包中, 并最终附加到 RADIUS 消息中。

本地目标消息格式: <timestamp> <seq_num> 11519 INFO EAP: Prepared EAP-Success for inner EAP method, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11519 INFO EAP: Prepared EAP-Success for inner EAP method, <log details>

• 消息代码: 11520

严重性: 信息 (INFO)

消息文本: 已为内部 EAP 方法准备好 EAP 失败 (Prepared EAP-Failure for inner EAP method)

消息说明: 已创建 EAP 失败数据包, 用于封装到外部 EAP 方法的传出 EAP 请求数据包中, 并最终附加到 RADIUS 消息中。

本地目标消息格式: <timestamp> <seq_num> 11520 INFO EAP: Prepared EAP-Failure for inner EAP method, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11520 INFO EAP: Prepared EAP-Failure for inner EAP method, <log details>

• 消息代码: 11521

严重性: 信息 (INFO)

消息文本: 已为内部 EAP 方法准备好 EAP 请求/身份 (Prepared EAP-Request/Identity for inner EAP method)

消息说明：已创建 EAP 请求/身份数据包，用于封装到外部 EAP 方法的传出 EAP 请求数据包中，并最终附加到 RADIUS 消息中。

本地目标消息格式：<timestamp> <seq_num> 11521 INFO EAP: Prepared EAP-Request/Identity for inner EAP method, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11521 INFO EAP: Prepared EAP-Request/Identity for inner EAP method, <log details>

- 消息代码：11522

严重性：信息 (INFO)

消息文本：已为内部 EAP 方法提取 EAP 响应/身份 (Extracted EAP-Response/Identity for inner EAP method)

消息说明：从外部 EAP 方法中遇到的 EAP 响应数据包中，为内部 EAP 方法提取了 EAP 响应/身份数据包。

本地目标消息格式：<timestamp> <seq_num> 11522 INFO EAP: Extracted EAP-Response/Identity for inner EAP method, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11522 INFO EAP: Extracted EAP-Response/Identity for inner EAP method, <log details>

- 消息代码：11523

严重性：警告 (WARN)

消息文本：收到无效或意外的内部 EAP 负载 (Invalid or unexpected inner-EAP payload received)

消息说明：可能是请求方出现内部错误：无法验证 EAP 内部方法负载。

本地目标消息格式：<timestamp> <seq_num> 11523 WARN EAP: Invalid or unexpected inner-EAP payload received, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11523 WARN EAP: Invalid or unexpected inner-EAP payload received, <log details>

- 消息代码：11524

严重性：警告 (WARN)

消息文本：无效的内部 EAP 负载 (Invalid inner-EAP payload)

消息说明：可能是请求方出现内部错误：无法验证 EAP 内部方法负载。

本地目标消息格式：<timestamp> <seq_num> 11524 WARN EAP: Invalid inner-EAP payload, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11524 WARN EAP: Invalid inner-EAP payload, <log details>

- 消息代码: 11800

严重性: 信息 (INFO)

消息文本: 已准备提议使用 EAP-MSCHAP 和质询的 EAP 请求 (Prepared EAP-Request proposing EAP-MSCHAP with challenge)

消息说明: 已创建一个 EAP 请求数据包, 提议使用 EAP-MSCHAP 协议, 同时提供 MSCHAP 质询, 用于附加到 RADIUS 消息。建议使用 EAP-MSCHAP 协议的原因在于此协议是“允许的协议”中允许使用的其中一个基于 EAP 的协议。

本地目标消息格式: <timestamp> <seq_num> 11800 INFO EAP: Prepared EAP-Request proposing EAP-MSCHAP with challenge, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11800 INFO EAP: Prepared EAP-Request proposing EAP-MSCHAP with challenge, <log details>

- 消息代码: 11801

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应/NAK 请求改为使用 EAP-MSCHAP (Extracted EAP-Response/NAK requesting to use EAP-MSCHAP instead)

消息说明: 从 RADIUS 消息中提取的 EAP 响应/NAK 数据包拒绝之前提议的基于 EAP 的协议, 且根据客户端请求方的配置, 请求改为使用 EAP-MSCHAP。

本地目标消息格式: <timestamp> <seq_num> 11801 INFO EAP: Extracted EAP-Response/NAK requesting to use EAP-MSCHAP instead, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11801 INFO EAP: Extracted EAP-Response/NAK requesting to use EAP-MSCHAP instead, <log details>

- 消息代码: 11802

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应包含 EAP-MSCHAP 质询-响应, 且接受将 EAP-MSCHAP 用作协商协议 (Extracted EAP-Response containing EAP-MSCHAP challenge-response and accepting EAP-MSCHAP as negotiated)

消息说明: 从 RADIUS 消息中提取的 EAP 响应数据包含有 EAP-MSCHAP 质询-响应, 且接受将 EAP-MSCHAP 用作协商协议。

本地目标消息格式: <timestamp> <seq_num> 11802 INFO EAP: Extracted EAP-Response containing EAP-MSCHAP challenge-response and accepting EAP-MSCHAP as negotiated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11802 INFO EAP: Extracted EAP-Response containing EAP-MSCHAP challenge-response and accepting EAP-MSCHAP as negotiated, <log details>

- 消息代码: 11803

严重性: 警告 (WARN)

消息文本: 由于 EAP-MSCHAP 未在“允许的协议”中获得允许, 因此 EAP 协商失败 (Failed to negotiate EAP because EAP-MSCHAP not allowed in the Allowed Protocols)

消息说明: 客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前提议的基于 EAP 的协议, 且请求改为使用 EAP-MSCHAP。但是, EAP-MSCHAP 未在“允许的协议”中获得允许。

本地目标消息格式: <timestamp> <seq_num> 11803 WARN EAP: Failed to negotiate EAP because EAP-MSCHAP not allowed in the Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11803 WARN EAP: Failed to negotiate EAP because EAP-MSCHAP not allowed in the Allowed Protocols, <log details>

- 消息代码: 11804

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应包含 MSCHAP 质询-响应 (Extracted EAP-Response containing MSCHAP challenge-response)

消息说明: 继续使用 EAP-MSCHAP 协议; 处理已提取的 EAP 响应中的 EAP-MSCHAP 质询-响应。

本地目标消息格式: <timestamp> <seq_num> 11804 INFO EAP: Extracted EAP-Response containing MSCHAP challenge-response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11804 INFO EAP: Extracted EAP-Response containing MSCHAP challenge-response, <log details>

- 消息代码: 11805

严重性: 信息 (INFO)

消息文本: 已准备包含其他 EAP-MSCHAP 质询的 EAP 请求 (Prepared EAP-Request with another EAP-MSCHAP challenge)

消息说明: 为了继续使用 EAP-MSCHAP 协议, 已创建包含其他 EAP-MSCHAP 质询的 EAP 请求数据包, 用于附加到 RADIUS 消息。

本地目标消息格式: <timestamp> <seq_num> 11805 INFO EAP: Prepared EAP-Request with another EAP-MSCHAP challenge, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11805 INFO EAP: Prepared EAP-Request with another EAP-MSCHAP challenge, <log details>

- 消息代码: 11806

严重性: 信息 (INFO)

消息文本: 已为内部方法准备提议使用 EAP-MSCHAP 和质询的 EAP 请求 (Prepared EAP-Request for inner method proposing EAP-MSCHAP with challenge)

消息说明：已创建一个 EAP 请求数据包，提议对内部方法使用 EAP-MSCHAP 协议，同时提供 MSCHAP 质询，用于附加到 RADIUS 消息。建议使用 EAP-MSCHAP 协议的原因在于此协议是“允许的协议”中允许使用的其中一个基于 EAP 的协议。

本地目标消息格式：<timestamp> <seq_num> 11806 INFO EAP: Prepared EAP-Request for inner method proposing EAP-MSCHAP with challenge, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11806 INFO EAP: Prepared EAP-Request for inner method proposing EAP-MSCHAP with challenge, <log details>

- 消息代码：11807

严重性：信息 (INFO)

消息文本：提取的内部方法 EAP 响应/NAK 请求改为使用 EAP-MSCHAP (Extracted EAP-Response/NAK for inner method requesting to use EAP-MSCHAP instead)

消息说明：从在外部 EAP 方法中遇到的 EAP 响应数据包中，提取的 EAP 响应/NAK 数据包拒绝之前为内部方法提议的基于 EAP 的协议，并根据客户端请求方的配置请求改为使用 EAP-MSCHAP。

本地目标消息格式：<timestamp> <seq_num> 11807 INFO EAP: Extracted EAP-Response/NAK for inner method requesting to use EAP-MSCHAP instead, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11807 INFO EAP: Extracted EAP-Response/NAK for inner method requesting to use EAP-MSCHAP instead, <log details>

- 消息代码：11808

严重性：信息 (INFO)

消息文本：提取的 EAP 响应包含内部方法 EAP-MSCHAP 质询-响应，且接受将 EAP-MSCHAP 用作协商协议 (Extracted EAP-Response containing EAP-MSCHAP challenge-response for inner method and accepting EAP-MSCHAP as negotiated)

消息说明：从在外部 EAP 方法中遇到的 EAP 响应数据包中，提取的 EAP 响应数据包含有 EAP-MSCHAP 质询-响应，且接受将 EAP-MSCHAP 用作内部方法的协商协议。

本地目标消息格式：<timestamp> <seq_num> 11808 INFO EAP: Extracted EAP-Response containing EAP-MSCHAP challenge-response for inner method and accepting EAP-MSCHAP as negotiated, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11808 INFO EAP: Extracted EAP-Response containing EAP-MSCHAP challenge-response for inner method and accepting EAP-MSCHAP as negotiated, <log details>

- 消息代码：11809

严重性：警告 (WARN)

消息文本：由于 EAP-MSCHAPv2 未在“允许的协议”中获得允许，因此 EAP 协商失败 (Failed to negotiate EAP for inner method because EAP-MSCHAPv2 not allowed in the Allowed Protocols)

消息说明：客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前为内部方法提议的基于 EAP 的协议，且请求改为使用 EAP-MSCHAPv2。但是，EAP-MSCHAPv2 未在“允许的协议”中获得允许。

本地目标消息格式：<timestamp> <seq_num> 11809 WARN EAP: Failed to negotiate EAP for inner method because EAP-MSCHAPv2 not allowed in the Allowed Protocols, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11809 WARN EAP: Failed to negotiate EAP for inner method because EAP-MSCHAPv2 not allowed in the Allowed Protocols, <log details>

- 消息代码：11810

严重性：信息 (INFO)

消息文本：提取的内部方法 EAP 响应包含 MSCHAP 质询-响应 (Extracted EAP-Response for inner method containing MSCHAP challenge-response)

消息说明：继续使用内部 EAP-MSCHAP 协议；处理已提取的 EAP 响应中的 EAP-MSCHAP 质询-响应。

本地目标消息格式：<timestamp> <seq_num> 11810 INFO EAP: Extracted EAP-Response for inner method containing MSCHAP challenge-response, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11810 INFO EAP: Extracted EAP-Response for inner method containing MSCHAP challenge-response, <log details>

- 消息代码：11811

严重性：信息 (INFO)

消息文本：已准备包含其他 EAP-MSCHAP 质询的内部方法 EAP 请求 (Prepared EAP-Request for inner method with another EAP-MSCHAP challenge)

消息说明：为了继续使用内部 EAP-MSCHAP 协议，已创建包含其他 EAP-MSCHAP 质询的 EAP 请求数据包，用于封装到外部 EAP 方法的传出 EAP 请求数据包中，并最终附加到 RADIUS 消息中。

本地目标消息格式：<timestamp> <seq_num> 11811 INFO EAP: Prepared EAP-Request for inner method with another EAP-MSCHAP challenge, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11811 INFO EAP: Prepared EAP-Request for inner method with another EAP-MSCHAP challenge, <log details>

- 消息代码：11812

严重性：信息 (INFO)

消息文本：EAP-MSCHAP 身份验证成功 (EAP-MSCHAP authentication succeeded)

消息说明：EAP-MSCHAP 身份验证成功。

本地目标消息格式：<timestamp> <seq_num> 11812 INFO EAP: EAP-MSCHAP authentication succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11812 INFO EAP: EAP-MSCHAP
authentication succeeded, <log details>

- 消息代码: 11813

严重性: 信息 (INFO)

消息文本: EAP-MSCHAP 身份验证失败 (EAP-MSCHAP authentication failed)

消息说明: EAP-MSCHAP 身份验证失败。

本地目标消息格式: <timestamp> <seq_num> 11813 INFO EAP: EAP-MSCHAP authentication failed,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11813 INFO EAP: EAP-MSCHAP
authentication failed, <log details>

- 消息代码: 11814

严重性: 信息 (INFO)

消息文本: 内部 EAP-MSCHAP 身份验证成功 (Inner EAP-MSCHAP authentication succeeded)

消息说明: 内部 EAP 方法的 EAP-MSCHAP 身份验证成功。

本地目标消息格式: <timestamp> <seq_num> 11814 INFO EAP: Inner EAP-MSCHAP authentication
succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11814 INFO EAP: Inner EAP-MSCHAP
authentication succeeded, <log details>

- 消息代码: 11815

严重性: 信息 (INFO)

消息文本: 内部 EAP-MSCHAP 身份验证失败 (Inner EAP-MSCHAP authentication failed)

消息说明: 内部 EAP 方法的 EAP-MSCHAP 身份验证失败。

本地目标消息格式: <timestamp> <seq_num> 11815 INFO EAP: Inner EAP-MSCHAP authentication
failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11815 INFO EAP: Inner EAP-MSCHAP
authentication failed, <log details>

- 消息代码: 11816

严重性: 警告 (WARN)

消息文本: MSCHAP 用户名与内部方法 EAP 响应/身份不匹配 (MSCHAP username doesn't match
inner method EAP-Response/Identity)

消息说明: MSCHAP 用户名与内部方法 EAP 响应/身份数据包中收到的用户名不匹配。可能是因为客户端的请求方预配置的另一个用户名与用户输入的用户名不匹配。

本地目标消息格式: <timestamp> <seq_num> 11816 WARN EAP: MSCHAP username doesn't match inner method EAP-Response/Identity, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11816 WARN EAP: MSCHAP username doesn't match inner method EAP-Response/Identity, <log details>

- 消息代码: 11817

严重性: 警告 (WARN)

消息文本: 收到意外的 EAP-MSCHAP 消息 (Received unexpected EAP-MSCHAP message)

消息说明: ISE 期望收到特定 EAP-MSCHAP 消息, 但收到其他消息。这可能是因为 ISE 和请求方之间协议的实施不一致导致的。

本地目标消息格式: <timestamp> <seq_num> 11817 WARN EAP: Received unexpected EAP-MSCHAP message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11817 WARN EAP: Received unexpected EAP-MSCHAP message, <log details>

- 消息代码: 11818

严重性: 信息 (INFO)

消息文本: 未能解析 EAP-MSCHAP 数据包 (Failed to parse EAP-MSCHAP packet)

消息说明: 未能解析 EAP-MSCHAP 数据包。

本地目标消息格式: <timestamp> <seq_num> 11818 INFO EAP: Failed to parse EAP-MSCHAP packet, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11818 INFO EAP: Failed to parse EAP-MSCHAP packet, <log details>

- 消息代码: 11819

严重性: 信息 (INFO)

消息文本: 接收到包含无效参数的 EAP-MSCHAP 数据包 (Received EAP-MSCHAP packet with invalid argument)

消息说明: 接收到包含无效参数的 EAP-MSCHAP 数据包。

本地目标消息格式: <timestamp> <seq_num> 11819 INFO EAP: Received EAP-MSCHAP packet with invalid argument, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11819 INFO EAP: Received EAP-MSCHAP packet with invalid argument, <log details>

- 消息代码: 11821
严重性: 信息 (INFO)
消息文本: EAP-MSCHAP 密码更改尝试失败 (EAP-MSCHAP password change attempt failed)
消息说明: 尝试更改密码失败, 因为“允许的协议”中未启用更改 MS-CHAPv2 内部方法的密码更改。
本地目标消息格式: <timestamp> <seq_num> 11821 INFO EAP: EAP-MSCHAP password change attempt failed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11821 INFO EAP: EAP-MSCHAP password change attempt failed, <log details>
- 消息代码: 11822
严重性: 调试 (DEBUG)
消息文本: EAP-MSCHAP 密码更改尝试通过 (EAP-MSCHAP password change attempt passed)
消息说明: 更改 EAP-MSCHAP 密码的尝试已通过。
本地目标消息格式: <timestamp> <seq_num> 11822 DEBUG EAP: EAP-MSCHAP password change attempt passed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11822 DEBUG EAP: EAP-MSCHAP password change attempt passed, <log details>
- 消息代码: 11823
严重性: 信息 (INFO)
消息文本: EAP-MSCHAP 身份验证尝试失败 (EAP-MSCHAP authentication attempt failed)
消息说明: EAP-MSCHAP 身份验证尝试失败。
本地目标消息格式: <timestamp> <seq_num> 11823 INFO EAP: EAP-MSCHAP authentication attempt failed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11823 INFO EAP: EAP-MSCHAP authentication attempt failed, <log details>
- 消息代码: 11824
严重性: 调试 (DEBUG)
消息文本: EAP-MSCHAP 身份验证尝试通过 (EAP-MSCHAP authentication attempt passed)
消息说明: EAP-MSCHAP 身份验证尝试通过。
本地目标消息格式: <timestamp> <seq_num> 11824 DEBUG EAP: EAP-MSCHAP authentication attempt passed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11824 DEBUG EAP: EAP-MSCHAP
authentication attempt passed, <log details>

- 消息代码: 11825

严重性: 警告 (WARN)

消息文本: MSCHAP 内部方法用户名缺失 (MSCHAP inner method username is missing)

消息说明: 内部方法 EAP 响应/身份数据包中收到的用户名为空。可能是因为用户没有输入用户名。

本地目标消息格式: <timestamp> <seq_num> 11825 WARN EAP: MSCHAP inner method username
is missing, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 11825 WARN EAP: MSCHAP inner method
username is missing, <log details>

- 消息代码: 12000

严重性: 信息 (INFO)

消息文本: 已准备提议使用 EAP-MD5 和质询的 EAP 请求 (Prepared EAP-Request proposing
EAP-MD5 with challenge)

消息说明: 已创建一个 EAP 请求数据包, 提议使用 EAP-MD5 协议, 同时提供 EAP-MD5 质询,
用于附加到 RADIUS 消息。建议使用 EAP-MD5 协议的原因在于此协议是“允许的协议”中允
许使用的其中一个基于 EAP 的协议。

本地目标消息格式: <timestamp> <seq_num> 12000 INFO EAP: Prepared EAP-Request proposing
EAP-MD5 with challenge, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12000 INFO EAP: Prepared EAP-Request
proposing EAP-MD5 with challenge, <log details>

- 消息代码: 12001

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应/NAK 请求改为使用 EAP-MD5 (Extracted EAP-Response/NAK requesting
to use EAP-MD5 instead)

消息说明: 从 RADIUS 消息中提取的 EAP 响应/NAK 数据包拒绝之前提议的基于 EAP 的协议,
且根据客户端请求方的配置, 请求改为使用 EAP-MD5。

本地目标消息格式: <timestamp> <seq_num> 12001 INFO EAP: Extracted EAP-Response/NAK
requesting to use EAP-MD5 instead, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12001 INFO EAP: Extracted
EAP-Response/NAK requesting to use EAP-MD5 instead, <log details>

- 消息代码: 12002

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应包含 EAP-MD5 质询-响应, 且接受将 EAP-MD5 用作协商协议 (Extracted EAP-Response containing EAP-MD5 challenge-response and accepting EAP-MD5 as negotiated)

消息说明: 从 RADIUS 消息中提取的 EAP 响应数据包含有 EAP-MD5 质询-响应, 且接受将 EAP-MD5 用作协商协议。

本地目标消息格式: <timestamp> <seq_num> 12002 INFO EAP: Extracted EAP-Response containing EAP-MD5 challenge-response and accepting EAP-MD5 as negotiated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12002 INFO EAP: Extracted EAP-Response containing EAP-MD5 challenge-response and accepting EAP-MD5 as negotiated, <log details>

- 消息代码: 12003

严重性: 警告 (WARN)

消息文本: 由于 EAP-MD5 未在“允许的协议”中获得允许, 因此 EAP 协商失败 (Failed to negotiate EAP because EAP-MD5 not allowed in the Allowed Protocols)

消息说明: 客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前提议的基于 EAP 的协议, 且请求改为使用 EAP-MD5。但是, EAP-MD5 未在“允许的协议”中获得允许。

本地目标消息格式: <timestamp> <seq_num> 12003 WARN EAP: Failed to negotiate EAP because EAP-MD5 not allowed in the Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12003 WARN EAP: Failed to negotiate EAP because EAP-MD5 not allowed in the Allowed Protocols, <log details>

- 消息代码: 12004

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应包含 EAP-MD5 质询-响应 (Extracted EAP-Response containing EAP-MD5 challenge-response)

消息说明: 继续使用 EAP-MD5 协议; 处理已提取的 EAP 响应中的 EAP-MD5 质询-响应。

本地目标消息格式: <timestamp> <seq_num> 12004 INFO EAP: Extracted EAP-Response containing EAP-MD5 challenge-response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12004 INFO EAP: Extracted EAP-Response containing EAP-MD5 challenge-response, <log details>

- 消息代码: 12005

严重性: 信息 (INFO)

消息文本: EAP-MD5 身份验证成功 (EAP-MD5 authentication succeeded)

消息说明: EAP-MD5 身份验证成功。

本地目标消息格式: <timestamp> <seq_num> 12005 INFO EAP: EAP-MD5 authentication succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12005 INFO EAP: EAP-MD5 authentication succeeded, <log details>

- 消息代码: 12006

严重性: 信息 (INFO)

消息文本: EAP-MD5 身份验证失败 (EAP-MD5 authentication failed)

消息说明: EAP-MD5 身份验证失败。

本地目标消息格式: <timestamp> <seq_num> 12006 INFO EAP: EAP-MD5 authentication failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12006 INFO EAP: EAP-MD5 authentication failed, <log details>

- 消息代码: 12007

严重性: 警告 (WARN)

消息文本: 内部错误 - EAP-MD5 状态无效 (Internal error - invalid EAP-MD5 state)

消息说明: 内部错误: EAP-MD5 状态无效。

本地目标消息格式: <timestamp> <seq_num> 12007 WARN EAP: Internal error - invalid EAP-MD5 state, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12007 WARN EAP: Internal error - invalid EAP-MD5 state, <log details>

- 消息代码: 12008

严重性: 信息 (INFO)

消息文本: 未能解析 EAP-MD5 数据包 (Failed to parse EAP-MD5 packet)

消息说明: 未能解析 EAP-MD5 数据包。

本地目标消息格式: <timestamp> <seq_num> 12008 INFO EAP: Failed to parse EAP-MD5 packet, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12008 INFO EAP: Failed to parse EAP-MD5 packet, <log details>

- 消息代码: 12100

严重性: 信息 (INFO)

消息文本: 已准备提议使用 EAP-FAST 和质询的 EAP 请求 (Prepared EAP-Request proposing EAP-FAST with challenge)

消息说明: 已创建一个 EAP 请求数据包, 提议使用 EAP-FAST 协议, 同时提供 EAP-FAST 质询, 用于附加到 RADIUS 消息。建议使用 EAP-FAST 协议的原因在于此协议是“允许的协议”中允许使用的其中一个基于 EAP 的协议。

本地目标消息格式: <timestamp> <seq_num> 12100 INFO EAP: Prepared EAP-Request proposing EAP-FAST with challenge, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12100 INFO EAP: Prepared EAP-Request proposing EAP-FAST with challenge, <log details>

- **消息代码:** 12101

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应/NAK 请求改为使用 EAP-FAST (Extracted EAP-Response/NAK requesting to use EAP-FAST instead)

消息说明: 从 RADIUS 消息中提取的 EAP 响应/NAK 数据包拒绝之前提议的基于 EAP 的协议, 且根据客户端请求方的配置, 请求改为使用 EAP-FAST。

本地目标消息格式: <timestamp> <seq_num> 12101 INFO EAP: Extracted EAP-Response/NAK requesting to use EAP-FAST instead, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12101 INFO EAP: Extracted EAP-Response/NAK requesting to use EAP-FAST instead, <log details>

- **消息代码:** 12102

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应包含 EAP-FAST 质询-响应, 且接受将 EAP-FAST 用作协商协议 (Extracted EAP-Response containing EAP-FAST challenge-response and accepting EAP-FAST as negotiated)

消息说明: 从 RADIUS 消息中提取的 EAP 响应数据包含有 EAP-FAST 质询-响应, 且接受将 EAP-FAST 用作协商协议。

本地目标消息格式: <timestamp> <seq_num> 12102 INFO EAP: Extracted EAP-Response containing EAP-FAST challenge-response and accepting EAP-FAST as negotiated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12102 INFO EAP: Extracted EAP-Response containing EAP-FAST challenge-response and accepting EAP-FAST as negotiated, <log details>

- **消息代码:** 12103

严重性: 警告 (WARN)

消息文本: 由于 EAP-FAST 未在“允许的协议”中获得允许, 因此 EAP 协商失败 (Failed to negotiate EAP because EAP-FAST not allowed in the Allowed Protocols)

消息说明：客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前提议的基于 EAP 的协议，且请求改为使用 EAP-FAST。但是，EAP-FAST 未在“允许的协议”中获得允许。

本地目标消息格式：<timestamp> <seq_num> 12103 WARN EAP: Failed to negotiate EAP because EAP-FAST not allowed in the Allowed Protocols, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12103 WARN EAP: Failed to negotiate EAP because EAP-FAST not allowed in the Allowed Protocols, <log details>

- 消息代码：12104

严重性：信息 (INFO)

消息文本：提取的 EAP 响应包含 EAP-FAST 质询-响应 (Extracted EAP-Response containing EAP-FAST challenge-response)

消息说明：继续使用 EAP-FAST 协议；处理已提取的 EAP 响应中的 EAP-FAST 质询-响应。

本地目标消息格式：<timestamp> <seq_num> 12104 INFO EAP: Extracted EAP-Response containing EAP-FAST challenge-response, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12104 INFO EAP: Extracted EAP-Response containing EAP-FAST challenge-response, <log details>

- 消息代码：12105

严重性：信息 (INFO)

消息文本：已准备包含其他 EAP-FAST 质询的 EAP 请求 (Prepared EAP-Request with another EAP-FAST challenge)

消息说明：为了继续使用 EAP-FAST 协议，已创建包含其他 EAP-FAST 质询的 EAP 请求数据包，用于附加到 RADIUS 消息。

本地目标消息格式：<timestamp> <seq_num> 12105 INFO EAP: Prepared EAP-Request with another EAP-FAST challenge, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12105 INFO EAP: Prepared EAP-Request with another EAP-FAST challenge, <log details>

- 消息代码：12106

严重性：信息 (INFO)

消息文本：EAP-FAST 身份验证阶段成功完成 (EAP-FAST authentication phase finished successfully)

消息说明：EAP-FAST 身份验证阶段成功完成。

本地目标消息格式：<timestamp> <seq_num> 12106 INFO EAP: EAP-FAST authentication phase finished successfully, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12106 INFO EAP: EAP-FAST authentication phase finished successfully, <log details>

- 消息代码: 12107
严重性: 信息 (INFO)
消息文本: EAP-FAST 调配阶段成功完成 (EAP-FAST provisioning phase finished successfully)
消息说明: EAP-FAST 调配阶段成功完成。
本地目标消息格式: <timestamp> <seq_num> 12107 INFO EAP: EAP-FAST provisioning phase finished successfully, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12107 INFO EAP: EAP-FAST provisioning phase finished successfully, <log details>
- 消息代码: 12108
严重性: 警告 (WARN)
消息文本: EAP-FAST 身份验证失败 (EAP-FAST authentication failed)
消息说明: EAP-FAST 身份验证失败。
本地目标消息格式: <timestamp> <seq_num> 12108 WARN EAP: EAP-FAST authentication failed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12108 WARN EAP: EAP-FAST authentication failed, <log details>
- 消息代码: 12109
严重性: 信息 (INFO)
消息文本: EAP-FAST 调配阶段完成 (EAP-FAST provisioning phase finished)
消息说明: 已完成 EAP-FAST PAC 调配阶段。根据标准, 即使 PAC 请求成功获得批准, 也将返回“EAP-失败”和“RADIUS 访问-拒绝”结果。因此, 需要检查 PAC 是否确实出现问题。
本地目标消息格式: <timestamp> <seq_num> 12109 INFO EAP: EAP-FAST provisioning phase finished, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12109 INFO EAP: EAP-FAST provisioning phase finished, <log details>
- 消息代码: 12110
严重性: 警告 (WARN)
消息文本: PAC 验证失败 (PAC verification failed)
消息说明: 从客户端收到未能通过验证的 PAC。
本地目标消息格式: <timestamp> <seq_num> 12110 WARN EAP: PAC verification failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12110 WARN EAP: PAC verification failed,
<log details>

- 消息代码: 12111

严重性: 警告 (WARN)

消息文本: PAC 包含无效的授权 ID (PAC contains invalid Authority ID)

消息说明: 客户端 PAC 的授权 ID 与处理身份验证请求的 ISE 服务器的授权 ID 不匹配, 这可能是
因为客户端的 PAC 是由另一个 ISE 创建的。

本地目标消息格式: <timestamp> <seq_num> 12111 WARN EAP: PAC contains invalid Authority
ID, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12111 WARN EAP: PAC contains invalid
Authority ID, <log details>

- 消息代码: 12112

严重性: 警告 (WARN)

消息文本: PAC 包含无效的 PAC 类型 (PAC contains invalid PAC type)

消息说明: 从客户端收到包含无效 PAC 类型的 PAC。

本地目标消息格式: <timestamp> <seq_num> 12112 WARN EAP: PAC contains invalid PAC type,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12112 WARN EAP: PAC contains invalid
PAC type, <log details>

- 消息代码: 12113

严重性: 警告 (WARN)

消息文本: PAC 已过期 - 拒绝此 PAC

消息说明: 从客户端收到已过期的 PAC。拒绝此 PAC。

本地目标消息格式: <timestamp> <seq_num> 12113 WARN EAP: PAC has expired - rejecting it,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12113 WARN EAP: PAC has expired -
rejecting it, <log details>

- 消息代码: 12114

严重性: 警告 (WARN)

消息文本: PAC 包含无效的身份验证标签 (PAC contains invalid Authentication Tag)

消息说明: 从客户端收到包含无效身份验证标签的 PAC。

本地目标消息格式: <timestamp> <seq_num> 12114 WARN EAP: PAC contains invalid Authentication Tag, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12114 WARN EAP: PAC contains invalid Authentication Tag, <log details>

- 消息代码: 12115

严重性: 信息 (INFO)

消息文本: 已成功完成 EAP-FAST PAC 调配/更新 (Successfully finished EAP-FAST PAC provisioning/update)

消息说明: 已成功完成 EAP-FAST PAC 调配/更新。

本地目标消息格式: <timestamp> <seq_num> 12115 INFO EAP: Successfully finished EAP-FAST PAC provisioning/update, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12115 INFO EAP: Successfully finished EAP-FAST PAC provisioning/update, <log details>

- 消息代码: 12116

严重性: 警告 (WARN)

消息文本: 客户端发送的 TEAP 结果 TLV 表明失败 (Client sent Result TLV indicating failure)

消息说明: EAP-FAST 身份验证失败, 因为客户端发送的结果 TLV 表明失败。

本地目标消息格式: <timestamp> <seq_num> 12116 WARN EAP: Client sent Result TLV indicating failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12116 WARN EAP: Client sent Result TLV indicating failure, <log details>

- 消息代码: 12117

严重性: 警告 (WARN)

消息文本: EAP-FAST 内部方法以失败告终 (EAP-FAST inner method finished with failure)

消息说明: EAP-FAST 内部方法以失败告终。

本地目标消息格式: <timestamp> <seq_num> 12117 WARN EAP: EAP-FAST inner method finished with failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12117 WARN EAP: EAP-FAST inner method finished with failure, <log details>

- 消息代码: 12118

严重性: 警告 (WARN)

消息文本: EAP-FAST 加密绑定验证失败 (EAP-FAST cryptobinding verification failed)

消息说明: EAP-FAST 加密绑定验证失败。

本地目标消息格式: <timestamp> <seq_num> 12118 WARN EAP: EAP-FAST cryptobinding verification failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12118 WARN EAP: EAP-FAST cryptobinding verification failed, <log details>

- 消息代码: 12119

严重性: 信息 (INFO)

消息文本: EAP-FAST 需要主动更新即将到期的 PAC (EAP-FAST needs to proactively update PAC that is about to expire)

消息说明: EAP-FAST 需要主动更新即将到期的 PAC。

本地目标消息格式: <timestamp> <seq_num> 12119 INFO EAP: EAP-FAST needs to proactively update PAC that is about to expire, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12119 INFO EAP: EAP-FAST needs to proactively update PAC that is about to expire, <log details>

- 消息代码: 12120

严重性: 警告 (WARN)

消息文本: “允许的协议” 不允许进行匿名调配和经过验证的调配 (Neither anonymous nor authenticated provisioning allowed by Allowed Protocols)

消息说明: 由于相关“允许的协议” 不允许进行匿名和经过验证的带内 PAC 调配, 因此尝试调配 PAC 失败。

本地目标消息格式: <timestamp> <seq_num> 12120 WARN EAP: Neither anonymous nor authenticated provisioning allowed by Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12120 WARN EAP: Neither anonymous nor authenticated provisioning allowed by Allowed Protocols, <log details>

- 消息代码: 12121

严重性: 警告 (WARN)

消息文本: 客户端没有为匿名 PAC 调配提供适当的密码 (Client didn't provide suitable ciphers for anonymous PAC-provisioning)

消息说明: 客户端的请求方发出的 EAP-FAST 带内 PAC 调配请求已由内部指定密码。此密码与“允许的协议”配置当前允许的以下调配方法不兼容: 匿名带内 PAC 调配。如果您需要此调配方法, 则此消息表明请求方配置不正确, 或者不能用于使用当前版本的 ISE 执行匿名调配。如果您需要经过验证的调配方法, 则此消息表明“允许的协议”配置当前不允许使用经过验证的带内 PAC 调配。

本地目标消息格式: <timestamp> <seq_num> 12121 WARN EAP: Client didn't provide suitable ciphers for anonymous PAC-provisioning, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12121 WARN EAP: Client didn't provide suitable ciphers for anonymous PAC-provisioning, <log details>

- 消息代码: 12122

严重性: 警告 (WARN)

消息文本: 客户端没有为经过验证的 PAC 调配提供适当的密码 (Client didn't provide suitable ciphers for authenticated PAC provisioning)

消息说明: 客户端的请求方发出的 EAP-FAST 带内 PAC 配置请求已由内部指定密码, 该密码与“允许的协议”配置当前允许的以下唯一调配方法不兼容: 经过验证的带内 PAC 调配。如果确实需要此调配方法, 则此消息表明请求方配置不正确, 或者不能用于使用当前版本的 ISE 执行经过验证的调配。或者, 如果确实需要匿名调配方法, 则此消息表明“允许的协议”配置当前不允许使用匿名带内 PAC 调配。

本地目标消息格式: <timestamp> <seq_num> 12122 WARN EAP: Client didn't provide suitable ciphers for authenticated PAC provisioning, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12122 WARN EAP: Client didn't provide suitable ciphers for authenticated PAC provisioning, <log details>

- 消息代码: 12123

严重性: 警告 (WARN)

消息文本: 客户端没有为匿名或经过验证的 PAC 调配提供适当的密码 (Client didn't provide suitable ciphers for either anonymous or authenticated PAC-provisioning)

消息说明: 客户端的请求方发出的 EAP-FAST 带内 PAC 调配请求已由内部指定密码。此密码与“允许的协议”配置当前允许的以下两种调配方法不兼容: 匿名带内 PAC 调配或经过验证的带内 PAC 调配。这表明请求方配置不正确, 或者不能用于使用当前版本的 ISE 执行 PAC 调配。

本地目标消息格式: <timestamp> <seq_num> 12123 WARN EAP: Client didn't provide suitable ciphers for either anonymous or authenticated PAC-provisioning, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12123 WARN EAP: Client didn't provide suitable ciphers for either anonymous or authenticated PAC-provisioning, <log details>

- 消息代码: 12124

严重性: 信息 (INFO)

消息文本: 已跳过 EAP-FAST 内部方法 (EAP-FAST inner method skipped)

消息说明: 已跳过 EAP-FAST 内部方法。

本地目标消息格式: <timestamp> <seq_num> 12124 INFO EAP: EAP-FAST inner method skipped, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12124 INFO EAP: EAP-FAST inner method
skipped, <log details>

- 消息代码: 12125

严重性: 信息 (INFO)

消息文本: 已开始 EAP-FAST 内部方法 (EAP-FAST inner method started)

消息说明: 已开始 EAP-FAST 内部方法。

本地目标消息格式: <timestamp> <seq_num> 12125 INFO EAP: EAP-FAST inner method started,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12125 INFO EAP: EAP-FAST inner method
started, <log details>

- 消息代码: 12126

严重性: 调试 (DEBUG)

消息文本: EAP-FAST 加密绑定验证通过 (EAP-FAST cryptobinding verification passed)

消息说明: EAP-FAST 加密绑定验证通过。

本地目标消息格式: <timestamp> <seq_num> 12126 DEBUG EAP: EAP-FAST cryptobinding
verification passed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12126 DEBUG EAP: EAP-FAST
cryptobinding verification passed, <log details>

- 消息代码: 12127

严重性: 信息 (INFO)

消息文本: 已批准 EAP-FAST 客户端 PAC 请求 (Approved EAP-FAST client PAC request)

消息说明: 已批准客户端请求方调配 PAC 的 EAP-FAST 请求。

本地目标消息格式: <timestamp> <seq_num> 12127 INFO EAP: Approved EAP-FAST client PAC
request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12127 INFO EAP: Approved EAP-FAST
client PAC request, <log details>

- 消息代码: 12128

严重性: 信息 (INFO)

消息文本: EAP-FAST 内部方法成功完成 (EAP-FAST inner method finished successfully)

消息说明: EAP-FAST 内部方法成功完成。

本地目标消息格式: <timestamp> <seq_num> 12128 INFO EAP: EAP-FAST inner method finished successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12128 INFO EAP: EAP-FAST inner method finished successfully, <log details>

- 消息代码: 12129

严重性: 警告 (WARN)

消息文本: EAP-FAST 调配失败。(EAP-FAST provisioning failed.) 常见错误

消息说明: EAP-FAST 调配失败。无法建立安全隧道。

本地目标消息格式: <timestamp> <seq_num> 12129 WARN EAP: EAP-FAST provisioning failed. General error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12129 WARN EAP: EAP-FAST provisioning failed. General error, <log details>

- 消息代码: 12130

严重性: 警告 (WARN)

消息文本: 未能解密 PAC (Failed to decrypt PAC)

消息说明: 未能解密从客户端的请求方收到的 PAC。

本地目标消息格式: <timestamp> <seq_num> 12130 WARN EAP: Failed to decrypt PAC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12130 WARN EAP: Failed to decrypt PAC, <log details>

- 消息代码: 12131

严重性: 信息 (INFO)

消息文本: EAP-FAST 为进行 PAC 调配建立了匿名隧道 (EAP-FAST built anonymous tunnel for purpose of PAC provisioning)

消息说明: EAP-FAST 完全握手成功完成 - 已为进行第 0 阶段的 PAC 调配建立匿名隧道。

本地目标消息格式: <timestamp> <seq_num> 12131 INFO EAP: EAP-FAST built anonymous tunnel for purpose of PAC provisioning, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12131 INFO EAP: EAP-FAST built anonymous tunnel for purpose of PAC provisioning, <log details>

- 消息代码: 12132

严重性: 信息 (INFO)

消息文本: EAP-FAST 为进行身份验证建立基于 PAC 的隧道 (EAP-FAST built PAC-based tunnel for purpose of authentication)

消息说明: EAP-FAST 短时握手成功完成 - 为进行第 1 阶段的身份验证建立基于 PAC 的隧道。

本地目标消息格式: <timestamp> <seq_num> 12132 INFO EAP: EAP-FAST built PAC-based tunnel for purpose of authentication, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12132 INFO EAP: EAP-FAST built PAC-based tunnel for purpose of authentication, <log details>

- 消息代码: 12133

严重性: 警告 (WARN)

消息文本: 已成功更新种子密钥 (Successfully updated Seed key)

消息说明: 已成功更新用于进一步生成主密钥的种子密钥。

本地目标消息格式: <timestamp> <seq_num> 12133 WARN EAP: Successfully updated Seed key, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12133 WARN EAP: Successfully updated Seed key, <log details>

- 消息代码: 12134

严重性: 警告 (WARN)

消息文本: 未能更新种子密钥 (Failed to update seed key)

消息说明: 内部错误: 未能更新进一步生成主密钥所需的种子密钥, 这很可能是因为无法正确获取内部配置对象。

本地目标消息格式: <timestamp> <seq_num> 12134 WARN EAP: Failed to update seed key, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12134 WARN EAP: Failed to update seed key, <log details>

- 消息代码: 12135

严重性: 信息 (INFO)

消息文本: 已更新主密钥生成期 (Updated Master Key Generation period)

消息说明: 已更新主密钥生成期。

本地目标消息格式: <timestamp> <seq_num> 12135 INFO EAP: Updated Master Key Generation period, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12135 INFO EAP: Updated Master Key Generation period, <log details>

- 消息代码: 12136
严重性: 信息 (INFO)
消息文本: 已向客户端发送 NDAC 身份验证 (Sent NDAC Authentication to client)
消息说明: 已向客户端发送 NDAC 身份验证。
本地目标消息格式: <timestamp> <seq_num> 12136 INFO EAP: Sent NDAC Authentication to client, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12136 INFO EAP: Sent NDAC Authentication to client, <log details>
- 消息代码: 12137
严重性: 信息 (INFO)
消息文本: 已从客户端收到 NDAC 身份验证响应 (Received NDAC Authentication response from client)
消息说明: 已从客户端收到 NDAC 身份验证响应。
本地目标消息格式: <timestamp> <seq_num> 12137 INFO EAP: Received NDAC Authentication response from client, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12137 INFO EAP: Received NDAC Authentication response from client, <log details>
- 消息代码: 12138
严重性: 信息 (INFO)
消息文本: 已收到授权 PAC (Received Authorization PAC)
消息说明: 已从客户端收到授权 PAC。
本地目标消息格式: <timestamp> <seq_num> 12138 INFO EAP: Received Authorization PAC, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12138 INFO EAP: Received Authorization PAC, <log details>
- 消息代码: 12139
严重性: 信息 (INFO)
消息文本: 匿名 TLS 重新协商成功 (Anonymous TLS renegotiation succeeded)
消息说明: EAP-FAST 匿名 TLS 重新协商成功完成
本地目标消息格式: <timestamp> <seq_num> 12139 INFO EAP: Anonymous TLS renegotiation succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12139 INFO EAP: Anonymous TLS renegotiation succeeded, <log details>

- 消息代码: 12140

严重性: 警告 (WARN)

消息文本: 匿名 TLS 重新协商失败 (Anonymous TLS renegotiation failed)

消息说明: 匿名 TLS 重新协商失败。

本地目标消息格式: <timestamp> <seq_num> 12140 WARN EAP: Anonymous TLS renegotiation failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12140 WARN EAP: Anonymous TLS renegotiation failed, <log details>

- 消息代码: 12141

严重性: 警告 (WARN)

消息文本: 未能找到旧主密钥 (Failed to find Legacy Master Key)

消息说明: 未能找到 EAP-FAST 旧主密钥。

本地目标消息格式: <timestamp> <seq_num> 12141 WARN EAP: Failed to find Legacy Master Key, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12141 WARN EAP: Failed to find Legacy Master Key, <log details>

- 消息代码: 12142

严重性: 警告 (WARN)

消息文本: 旧主密钥过期 (Legacy Master Key expired)

消息说明: EAP-FAST 旧主密钥过期。

本地目标消息格式: <timestamp> <seq_num> 12142 WARN EAP: Legacy Master Key expired, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12142 WARN EAP: Legacy Master Key expired, <log details>

- 消息代码: 12143

严重性: 警告 (WARN)

消息文本: 未能派生 EAP-FAST 主密钥 (Failed to derive EAP-FAST Master Key)

消息说明: 未能派生 EAP-FAST 主密钥。

本地目标消息格式: <timestamp> <seq_num> 12143 WARN EAP: Failed to derive EAP-FAST Master Key, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12143 WARN EAP: Failed to derive EAP-FAST Master Key, <log details>

- 消息代码: 12144

严重性: 警告 (WARN)

消息文本: 在无效 PAC 上回退: 服务器上未配置可用的其他密码 (Fallback on invalid PAC: no available additional cipher configured on server)

消息说明: 在无效 PAC 上回退: 服务器上未配置可用的其他密码。

本地目标消息格式: <timestamp> <seq_num> 12144 WARN EAP: Fallback on invalid PAC: no available additional cipher configured on server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12144 WARN EAP: Fallback on invalid PAC: no available additional cipher configured on server, <log details>

- 消息代码: 12145

严重性: 警告 (WARN)

消息文本: 无法执行多个无效的 PAC 回退 (Cannot perform more than one invalid PAC fallback)

消息说明: 客户端的请求方似乎出现内部问题, 正在一次 EAP-FAST 对话过程中不正确地尝试多次发送无效 PAC。

本地目标消息格式: <timestamp> <seq_num> 12145 WARN EAP: Cannot perform more than one invalid PAC fallback, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12145 WARN EAP: Cannot perform more than one invalid PAC fallback, <log details>

- 消息代码: 12146

严重性: 警告 (WARN)

消息文本: 客户端侧没有用于无效 PAC 回退的密码 (No cipher on client side for invalid PAC fallback)

消息说明: 由于客户端的请求方建议的任何密码套件都与无效的 PAC 回退不兼容, 因此 ISE 无法完成 TLS 握手。这可能是由手动调配的 PAC 不再有效, 并且“允许的协议”中的配置不允许使用客户端期望的任何形式的带内 PAC 调配导致的。

本地目标消息格式: <timestamp> <seq_num> 12146 WARN EAP: No cipher on client side for invalid PAC fallback, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12146 WARN EAP: No cipher on client side for invalid PAC fallback, <log details>

- 消息代码: 12147
 - 严重性: 警告 (WARN)
 - 消息文本: 计算机身份验证已禁用 (Machine Authentication is disabled)
 - 消息说明: EAP-FAST 身份验证失败, 因为计算机身份验证已禁用。
 - 本地目标消息格式: <timestamp> <seq_num> 12147 WARN EAP: Machine Authentication is disabled, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 12147 WARN EAP: Machine Authentication is disabled, <log details>

- 消息代码: 12148
 - 严重性: 信息 (INFO)
 - 消息文本: “允许的协议” 不允许无状态会话恢复; 正执行完整身份验证 (Allowed Protocols does not allow Stateless Session Resume; performing full authentication)
 - 消息说明: “允许的协议” 配置不允许无状态会话恢复; 正执行完整身份验证。
 - 本地目标消息格式: <timestamp> <seq_num> 12148 INFO EAP: Allowed Protocols does not allow Stateless Session Resume; performing full authentication, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 12148 INFO EAP: Allowed Protocols does not allow Stateless Session Resume; performing full authentication, <log details>

- 消息代码: 12149
 - 严重性: 信息 (INFO)
 - 消息文本: EAP-FAST 为进行 PAC 调配建立了经过验证的隧道 (EAP-FAST built authenticated tunnel for purpose of PAC provisioning)
 - 消息说明: EAP-FAST 完全握手成功完成 - 已为进行第 0 阶段的 PAC 调配建立经过验证的隧道。
 - 本地目标消息格式: <timestamp> <seq_num> 12149 INFO EAP: EAP-FAST built authenticated tunnel for purpose of PAC provisioning, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 12149 INFO EAP: EAP-FAST built authenticated tunnel for purpose of PAC provisioning, <log details>

- 消息代码: 12151
 - 严重性: 信息 (INFO)
 - 消息文本: 在无效的 PAC 上执行回退以进行调配 (Perform fallback on invalid PAC to provisioning)
 - 消息说明: ISE 在身份验证过程中收到无效的 PAC, 且执行回退以进行 PAC 调配。
 - 本地目标消息格式: <timestamp> <seq_num> 12151 INFO EAP: Perform fallback on invalid PAC to provisioning, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12151 INFO EAP: Perform fallback on
invalid PAC to provisioning, <log details>

- 消息代码: 12152

严重性: 警告 (WARN)

消息文本: PAC 调配请求遭拒, 因为请求方未能遵守协议 (Rejected PAC provisioning request
because supplicant failed to adhere to protocol)

消息说明: 由于客户端的请求方未能正确遵守 EAP-FAST 协议, 因此 PAC 调配请求遭拒。它不仅未能向接近完成调配的 PAC 发送 ACK, 而且未能向隧道 PAC 或计算机 PAC 发送有效的其他请求以继续进行调配。

本地目标消息格式: <timestamp> <seq_num> 12152 WARN EAP: Rejected PAC provisioning request
because supplicant failed to adhere to protocol, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12152 WARN EAP: Rejected PAC
provisioning request because supplicant failed to adhere to protocol, <log details>

- 消息代码: 12153

严重性: 警告 (WARN)

消息文本: EAP-FAST 进行 SSL/TLS 握手失败, 因为客户端拒绝 ISE 本地证书 (EAP-FAST failed
SSL/TLS handshake because the client rejected the ISE local-certificate)

消息说明: EAP-FAST 进行 SSL/TLS 握手失败, 因为客户端拒绝 ISE 本地证书

本地目标消息格式: <timestamp> <seq_num> 12153 WARN EAP: EAP-FAST failed SSL/TLS
handshake because the client rejected the ISE local-certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12153 WARN EAP: EAP-FAST failed
SSL/TLS handshake because the client rejected the ISE local-certificate, <log details>

- 消息代码: 12154

严重性: 警告 (WARN)

消息文本: 在客户端发出警报后, EAP-FAST 进行 SSL/TLS 握手失败 (EAP-FAST failed SSL/TLS
handshake after a client alert)

消息说明: 在客户端发出警报后, EAP-FAST 进行 SSL/TLS 握手失败

本地目标消息格式: <timestamp> <seq_num> 12154 WARN EAP: EAP-FAST failed SSL/TLS
handshake after a client alert, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12154 WARN EAP: EAP-FAST failed
SSL/TLS handshake after a client alert, <log details>

- 消息代码: 12155

严重性: 警告 (WARN)

消息文本: 此对话已请求一个隧道 PAC。(One Tunnel PAC has already been requested in this conversation.) 其他隧道 PAC 请求将被忽略

消息说明: 此对话已请求一个隧道 PAC。其他隧道 PAC 请求将被忽略

本地目标消息格式: <timestamp> <seq_num> 12155 WARN EAP: One Tunnel PAC has already been requested in this conversation. Another Tunnel PAC request will be ignored, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12155 WARN EAP: One Tunnel PAC has already been requested in this conversation. Another Tunnel PAC request will be ignored, <log details>

- 消息代码: 12156

严重性: 警告 (WARN)

消息文本: 此对话已请求一个 CTS PAC。(One CTS PAC has already been requested in this conversation.) 其他隧道 PAC 请求将被忽略

消息说明: 此对话已请求一个 CTS PAC。其他隧道 PAC 请求将被忽略

本地目标消息格式: <timestamp> <seq_num> 12156 WARN EAP: One CTS PAC has already been requested in this conversation. Another Tunnel PAC request will be ignored, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12156 WARN EAP: One CTS PAC has already been requested in this conversation. Another Tunnel PAC request will be ignored, <log details>

- 消息代码: 12157

严重性: 警告 (WARN)

消息文本: 此对话已请求一个隧道 PAC。(One Tunnel PAC has already been requested in this conversation.) 其他 CTS PAC 请求将被忽略

消息说明: 此对话已请求一个隧道 PAC。其他 CTS PAC 请求将被忽略

本地目标消息格式: <timestamp> <seq_num> 12157 WARN EAP: One Tunnel PAC has already been requested in this conversation. Another CTS PAC request will be ignored, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12157 WARN EAP: One Tunnel PAC has already been requested in this conversation. Another CTS PAC request will be ignored, <log details>

- 消息代码: 12158

严重性: 警告 (WARN)

消息文本: 此对话已请求一个 CTS PAC。(One CTS PAC has already been requested in this conversation.) 其他 CTS PAC 请求将被忽略

消息说明: 此对话已请求一个 CTS PAC。其他 CTS PAC 请求将被忽略

本地目标消息格式: <timestamp> <seq_num> 12158 WARN EAP: One CTS PAC has already been requested in this conversation. Another CTS PAC request will be ignored, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12158 WARN EAP: One CTS PAC has
already been requested in this conversation. Another CTS PAC request will be ignored, <log details>

- 消息代码: 12159

严重性: 警告 (WARN)

消息文本: 此对话已请求一个计算机 PAC。(One Machine PAC has already been requested in this
conversation.) 其他计算机 PAC 请求将被忽略

消息说明: 此对话已请求一个计算机 PAC。其他计算机 PAC 请求将被忽略

本地目标消息格式: <timestamp> <seq_num> 12159 WARN EAP: One Machine PAC has already
been requested in this conversation. Another Machine PAC request will be ignored, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12159 WARN EAP: One Machine PAC has
already been requested in this conversation. Another Machine PAC request will be ignored, <log details>

- 消息代码: 12160

严重性: 警告 (WARN)

消息文本: 无法在匿名调配中调配计算机 PAC。(Cannot provision Machine PAC on anonymous
provisioning.) 只能在经过验证的调配中调配计算机 PAC

消息说明: 无法在匿名调配中调配计算机 PAC。只能在经过验证的调配中调配计算机 PAC

本地目标消息格式: <timestamp> <seq_num> 12160 WARN EAP: Cannot provision Machine PAC
on anonymous provisioning. Machine PAC can be provisioned only on authenticated provisioning, <log
details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12160 WARN EAP: Cannot provision
Machine PAC on anonymous provisioning. Machine PAC can be provisioned only on authenticated
provisioning, <log details>

- 消息代码: 12161

严重性: 警告 (WARN)

消息文本: 当无状态会话恢复功能被禁用时, 无法调配授权 PAC (Cannot provision Authorization
PAC when the stateless session resume is disabled)

消息说明: 当无状态会话恢复功能被禁用时, 无法调配授权 PAC。在服务设置中启用无状态会
话恢复, 以允许授权 PAC 调配

本地目标消息格式: <timestamp> <seq_num> 12161 WARN EAP: Cannot provision Authorization
PAC when the stateless session resume is disabled, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12161 WARN EAP: Cannot provision
Authorization PAC when the stateless session resume is disabled, <log details>

- 消息代码: 12162

严重性: 警告 (WARN)

消息文本: 无法在匿名调配中调配授权 PAC。(Cannot provision Authorization PAC on anonymous provisioning.) 只能在经过验证的调配中调配授权 PAC

消息说明: 无法在匿名调配中调配授权 PAC。只能在经过验证的调配中调配授权 PAC

本地目标消息格式: <timestamp> <seq_num> 12162 WARN EAP: Cannot provision Authorization PAC on anonymous provisioning. Authorization PAC can be provisioned only on authenticated provisioning, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12162 WARN EAP: Cannot provision Authorization PAC on anonymous provisioning. Authorization PAC can be provisioned only on authenticated provisioning, <log details>

- 消息代码: 12163

严重性: 警告 (WARN)

消息文本: 此会话已经请求了一个授权 PAC。(One Authorization PAC has already been requested in this conversation.) 其他授权 PAC 请求将被忽略

消息说明: 此会话已经请求了一个授权 PAC。其他授权 PAC 请求将被忽略

本地目标消息格式: <timestamp> <seq_num> 12163 WARN EAP: One Authorization PAC has already been requested in this conversation. Another Authorization PAC request will be ignored, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12163 WARN EAP: One Authorization PAC has already been requested in this conversation. Another Authorization PAC request will be ignored, <log details>

- 消息代码: 12164

严重性: 警告 (WARN)

消息文本: 请求的 PAC 类型无效。(Invalid PAC type requested.) 忽略此请求

消息说明: 请求的 PAC 类型无效。忽略此请求

本地目标消息格式: <timestamp> <seq_num> 12164 WARN EAP: Invalid PAC type requested. Ignoring this request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12164 WARN EAP: Invalid PAC type requested. Ignoring this request, <log details>

- 消息代码: 12165

严重性: 警告 (WARN)

消息文本: 授权 PAC I-ID 与用户身份不匹配。(Authorization PAC I-ID does not match user identity.) 忽略此授权 PAC 请求

消息说明: 授权 PAC I-ID 与用户身份不匹配。忽略此授权 PAC 请求

本地目标消息格式: <timestamp> <seq_num> 12165 WARN EAP: Authorization PAC I-ID does not match user identity. Ignoring this Authorization PAC request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12165 WARN EAP: Authorization PAC I-ID does not match user identity. Ignoring this Authorization PAC request, <log details>

- 消息代码: 12166

严重性: 警告 (WARN)

消息文本: 计算机 PAC 请求不包含 I-ID。 (Machine PAC request does not contain I-ID.) 忽略此计算机 PAC 请求

消息说明: 计算机 PAC 请求不包含 I-ID。忽略此计算机 PAC 请求

本地目标消息格式: <timestamp> <seq_num> 12166 WARN EAP: Machine PAC request does not contain I-ID. Ignoring this Machine PAC request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12166 WARN EAP: Machine PAC request does not contain I-ID. Ignoring this Machine PAC request, <log details>

- 消息代码: 12167

严重性: 警告 (WARN)

消息文本: 授权 PAC 只能与隧道 PAC 一起提供 (Authorization PAC can be provided only with Tunnel PAC)

消息说明: 授权 PAC 只能与隧道 PAC 一起提供

本地目标消息格式: <timestamp> <seq_num> 12167 WARN EAP: Authorization PAC can be provided only with Tunnel PAC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12167 WARN EAP: Authorization PAC can be provided only with Tunnel PAC, <log details>

- 消息代码: 12168

严重性: 信息 (INFO)

消息文本: 收到 CTS PAC (Received CTS PAC)

消息说明: 从客户端收到 CTS PAC

本地目标消息格式: <timestamp> <seq_num> 12168 INFO EAP: Received CTS PAC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12168 INFO EAP: Received CTS PAC, <log details>

- 消息代码: 12169

严重性: 信息 (INFO)

消息文本: 已成功完成 EAP-FAST 隧道 PAC 调配/更新 (Successfully finished EAP-FAST tunnel PAC provisioning/update)

消息说明: 已成功完成 EAP-FAST 隧道 PAC 调配或更新。

本地目标消息格式: <timestamp> <seq_num> 12169 INFO EAP: Successfully finished EAP-FAST tunnel PAC provisioning/update, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12169 INFO EAP: Successfully finished EAP-FAST tunnel PAC provisioning/update, <log details>

- 消息代码: 12170

严重性: 信息 (INFO)

消息文本: 已成功完成 EAP-FAST 计算机 PAC 调配/更新 (Successfully finished EAP-FAST machine PAC provisioning/update)

消息说明: 已成功完成 EAP-FAST 计算机 PAC 调配或更新。

本地目标消息格式: <timestamp> <seq_num> 12170 INFO EAP: Successfully finished EAP-FAST machine PAC provisioning/update, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12170 INFO EAP: Successfully finished EAP-FAST machine PAC provisioning/update, <log details>

- 消息代码: 12171

严重性: 信息 (INFO)

消息文本: 已成功完成 EAP-FAST 用户授权 PAC 调配/更新 (Successfully finished EAP-FAST user authorization PAC provisioning/update)

消息说明: 已成功完成 EAP-FAST 用户授权 PAC 调配或更新。

本地目标消息格式: <timestamp> <seq_num> 12171 INFO EAP: Successfully finished EAP-FAST user authorization PAC provisioning/update, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12171 INFO EAP: Successfully finished EAP-FAST user authorization PAC provisioning/update, <log details>

- 消息代码: 12172

严重性: 信息 (INFO)

消息文本: 已成功完成 EAP-FAST 终端安全评估 PAC 调配/更新 (Successfully finished EAP-FAST posture PAC provisioning/update)

消息说明: 已成功完成 EAP-FAST 终端安全评估 PAC 调配或更新。

本地目标消息格式: <timestamp> <seq_num> 12172 INFO EAP: Successfully finished EAP-FAST posture PAC provisioning/update, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12172 INFO EAP: Successfully finished
EAP-FAST posture PAC provisioning/update, <log details>

- 消息代码: 12173

严重性: 信息 (INFO)

消息文本: 已成功完成 EAP-FAST CTS PAC 调配/更新 (Successfully finished EAP-FAST CTS PAC
provisioning/update)

消息说明: 已成功完成 EAP-FAST CTS PAC 调配或更新。

本地目标消息格式: <timestamp> <seq_num> 12173 INFO EAP: Successfully finished EAP-FAST
CTS PAC provisioning/update, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12173 INFO EAP: Successfully finished
EAP-FAST CTS PAC provisioning/update, <log details>

- 消息代码: 12174

严重性: 信息 (INFO)

消息文本: 收到计算机 PAC (Received Machine PAC)

消息说明: 从客户端收到计算机 PAC。

本地目标消息格式: <timestamp> <seq_num> 12174 INFO EAP: Received Machine PAC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12174 INFO EAP: Received Machine PAC,
<log details>

- 消息代码: 12175

严重性: 信息 (INFO)

消息文本: 收到隧道 PAC (Received Tunnel PAC)

消息说明: 从客户端收到隧道 PAC。

本地目标消息格式: <timestamp> <seq_num> 12175 INFO EAP: Received Tunnel PAC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12175 INFO EAP: Received Tunnel PAC,
<log details>

- 消息代码: 12176

严重性: 信息 (INFO)

消息文本: EAP-FAST 无 PAC 完全握手成功完成 (EAP-FAST PAC-less full handshake finished
successfully)

消息说明: 使用 EAP-FAST 身份验证的无 PAC 模式。已使用完全握手成功建立隧道。

本地目标消息格式: <timestamp> <seq_num> 12176 INFO EAP: EAP-FAST PAC-less full handshake finished successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 12176 INFO EAP: EAP-FAST PAC-less full handshake finished successfully, <log details>

- 消息代码: 12177

严重性: 警告 (WARN)

消息文本: 没有用于无 PAC EAP-FAST 身份验证的密码 (No cipher for PAC-less EAP-FAST authentication)

消息说明: 在进行 EAP-FAST 的 TLS 握手部分的过程中, 由客户端的请求方指定的密码与“允许的协议”配置中当前配置的无 PAC 操作模式不兼容。这可能是由于请求方的配置不正确, 或者一般来说, 本身不能与使用当前版本的 ISE 的无 PAC EAP-FAST 身份验证配合使用。

本地目标消息格式: <timestamp> <seq_num> 12177 WARN EAP: No cipher for PAC-less EAP-FAST authentication, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 12177 WARN EAP: No cipher for PAC-less EAP-FAST authentication, <log details>

- 消息代码: 12178

严重性: 警告 (WARN)

消息文本: 在 EAP-FAST 的无 PAC 模式中, 意外收到被拒绝的 PAC (Rejected PAC unexpectedly received during PAC-less mode of EAP-FAST)

消息说明: 尽管“允许的协议”已经配置 EAP-FAST 来使用无 PAC 的操作模式, 但客户端的请求方向 ISE 发送了 PAC, 就好像正在使用基于 PAC 的模式一样。

本地目标消息格式: <timestamp> <seq_num> 12178 WARN EAP: Rejected PAC unexpectedly received during PAC-less mode of EAP-FAST, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 12178 WARN EAP: Rejected PAC unexpectedly received during PAC-less mode of EAP-FAST, <log details>

- 消息代码: 12179

严重性: 信息 (INFO)

消息文本: 已成功完成 EAP-FAST 计算机授权 PAC 调配/更新 (Successfully finished EAP-FAST machine authorization PAC provisioning/update)

消息说明: 已成功完成 EAP-FAST 计算机授权 PAC 调配或更新。

本地目标消息格式: <timestamp> <seq_num> 12179 INFO EAP: Successfully finished EAP-FAST machine authorization PAC provisioning/update, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12179 INFO EAP: Successfully finished
EAP-FAST machine authorization PAC provisioning/update, <log details>

- 消息代码: 12200

严重性: 信息 (INFO)

消息文本: 已批准 EAP-FAST 客户端隧道 PAC 请求 (Approved EAP-FAST client Tunnel PAC request)

消息说明: 已批准客户端请求方调配隧道 PAC 的 EAP-FAST 请求。

本地目标消息格式: <timestamp> <seq_num> 12200 INFO EAP: Approved EAP-FAST client Tunnel PAC request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12200 INFO EAP: Approved EAP-FAST client Tunnel PAC request, <log details>

- 消息代码: 12201

严重性: 信息 (INFO)

消息文本: 已批准 EAP-FAST 客户端计算机 PAC 请求 (Approved EAP-FAST client Machine PAC request)

消息说明: 已批准客户端请求方调配计算机 PAC 的 EAP-FAST 请求。

本地目标消息格式: <timestamp> <seq_num> 12201 INFO EAP: Approved EAP-FAST client Machine PAC request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12201 INFO EAP: Approved EAP-FAST client Machine PAC request, <log details>

- 消息代码: 12202

严重性: 信息 (INFO)

消息文本: 已批准 EAP-FAST 客户端授权 PAC 请求 (Approved EAP-FAST client Authorization PAC request)

消息说明: 已批准客户端请求方调配授权 PAC 的 EAP-FAST 请求。

本地目标消息格式: <timestamp> <seq_num> 12202 INFO EAP: Approved EAP-FAST client Authorization PAC request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12202 INFO EAP: Approved EAP-FAST client Authorization PAC request, <log details>

- 消息代码: 12203

严重性: 信息 (INFO)

消息文本: 正使用客户端证书进行身份验证 (Using client certificate for authentication)

消息说明：ISE 在隧道建立期间或在隧道中收到客户端证书。ISE 将验证此证书并用其进行身份验证。

本地目标消息格式：<timestamp> <seq_num> 12203 INFO EAP: Using client certificate for authentication, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12203 INFO EAP: Using client certificate for authentication, <log details>

- 消息代码：12204

严重性：信息 (INFO)

消息文本：已在隧道中收到客户端证书 (Client certificate was received inside the tunnel)

消息说明：请求方在隧道中提供了客户端证书（证书在加密的情况下发送）

本地目标消息格式：<timestamp> <seq_num> 12204 INFO EAP: Client certificate was received inside the tunnel, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12204 INFO EAP: Client certificate was received inside the tunnel, <log details>

- 消息代码：12205

严重性：信息 (INFO)

消息文本：已请求客户端证书，但未在隧道中收到。(Client certificate was requested but not received inside the tunnel.) 将继续使用内部方法。

消息说明：ISE 在隧道中请求客户端证书，但请求方未提供该客户端证书。ISE 将继续运行内部方法来验证请求方身份。

本地目标消息格式：<timestamp> <seq_num> 12205 INFO EAP: Client certificate was requested but not received inside the tunnel. Will continue with inner method., <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12205 INFO EAP: Client certificate was requested but not received inside the tunnel. Will continue with inner method., <log details>

- 消息代码：12206

严重性：信息 (INFO)

消息文本：已在隧道建立期间收到客户端证书 (Client certificate was received during tunnel establishment)

消息说明：请求方在隧道建立期间提供了客户端证书（证书在未加密的情况下发送）

本地目标消息格式：<timestamp> <seq_num> 12206 INFO EAP: Client certificate was received during tunnel establishment, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num> 12206 INFO EAP: Client certificate was received during tunnel establishment, <log details>

- 消息代码: 12207

严重性: 信息 (INFO)

消息文本: 已请求客户端证书, 但未在隧道建立期间收到。(Client certificate was requested but not received during tunnel establishment.) 将重新协商, 并在隧道内部请求客户端证书。

消息说明: ISE 在隧道建立期间请求客户端证书, 但请求方未提供该客户端证书。请求方可能配置为只在加密的情况下才发送客户端证书。ISE 将重新协商, 并在隧道内部请求客户端证书。

本地目标消息格式: <timestamp> <seq_num> 12207 INFO EAP: Client certificate was requested but not received during tunnel establishment. Will renegotiate and request client certificate inside the tunnel., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num> 12207 INFO EAP: Client certificate was requested but not received during tunnel establishment. Will renegotiate and request client certificate inside the tunnel., <log details>

- 消息代码: 12208

严重性: 信息 (INFO)

消息文本: 已收到客户端证书, 但身份验证失败 (Client certificate was received but authentication failed)

消息说明: ISE 在隧道建立期间或在隧道中收到客户端证书, 但身份验证失败。

本地目标消息格式: <timestamp> <seq_num> 12208 INFO EAP: Client certificate was received but authentication failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num> 12208 INFO EAP: Client certificate was received but authentication failed, <log details>

- 消息代码: 12209

严重性: 信息 (INFO)

消息文本: 正启动 EAP 链接 (Starting EAP chaining)

消息说明: ISE 配置为执行 EAP 链接。ISE 正启动 EAP 链接, 并假定客户端也支持 EAP 链接。

本地目标消息格式: <timestamp> <seq_num> 12209 INFO EAP: Starting EAP chaining, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num> 12209 INFO EAP: Starting EAP chaining, <log details>

- 消息代码: 12210

严重性: 信息 (INFO)

消息文本: 已收到用户授权 PAC (Received User Authorization PAC)

消息说明: 已从客户端收到用户授权 PAC。

本地目标消息格式: <timestamp> <seq_num> 12210 INFO EAP: Received User Authorization PAC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12210 INFO EAP: Received User Authorization PAC, <log details>

- 消息代码: 12211

严重性: 信息 (INFO)

消息文本: 已收到计算机授权 PAC (Received Machine Authorization PAC)

消息说明: 已从客户端收到计算机授权 PAC。

本地目标消息格式: <timestamp> <seq_num> 12211 INFO EAP: Received Machine Authorization PAC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12211 INFO EAP: Received Machine Authorization PAC, <log details>

- 消息代码: 12212

严重性: 信息 (INFO)

消息文本: 客户端提供的身份类型等同于请求的身份类型 (Identity type provided by client is equal to requested)

消息说明: ISE 从客户端为当前的内部方法请求了特定的身份类型, 且客户端确认使用此身份类型。

本地目标消息格式: <timestamp> <seq_num> 12212 INFO EAP: Identity type provided by client is equal to requested, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12212 INFO EAP: Identity type provided by client is equal to requested, <log details>

- 消息代码: 12213

严重性: 信息 (INFO)

消息文本: 客户端提供的身份类型不等同于请求的身份类型 (Identity type provided by client is not equal to requested type)

消息说明: ISE 从客户端为当前的内部方法请求了特定的身份类型, 且客户端拒绝使用此身份类型。

本地目标消息格式: <timestamp> <seq_num> 12213 INFO EAP: Identity type provided by client is not equal to requested type, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12213 INFO EAP: Identity type provided
by client is not equal to requested type, <log details>

- 消息代码: 12214

严重性: 信息 (INFO)

消息文本: 客户端建议改用“用户”身份类型 (Client suggested 'User' identity type instead)

消息说明: 客户端建议在当前的内部方法中使用“用户”身份类型。

本地目标消息格式: <timestamp> <seq_num> 12214 INFO EAP: Client suggested 'User' identity type
instead, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12214 INFO EAP: Client suggested 'User'
identity type instead, <log details>

- 消息代码: 12215

严重性: 信息 (INFO)

消息文本: 客户端建议改用“计算机”身份类型 (Client suggested 'Machine' identity type instead)

消息说明: 客户端建议在当前的内部方法中使用“计算机”身份类型。

本地目标消息格式: <timestamp> <seq_num> 12215 INFO EAP: Client suggested 'Machine' identity
type instead, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12215 INFO EAP: Client suggested 'Machine'
identity type instead, <log details>

- 消息代码: 12216

严重性: 信息 (INFO)

消息文本: 客户端提供的身份类型已经用于身份验证 (Identity type provided by client was already
used for authentication)

消息说明: 客户端建议在当前的内部方法中使用之前的内部方法中已经用过的身份类型。ISE
拒绝此身份类型。

本地目标消息格式: <timestamp> <seq_num> 12216 INFO EAP: Identity type provided by client was
already used for authentication, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12216 INFO EAP: Identity type provided
by client was already used for authentication, <log details>

- 消息代码: 12217

严重性: 信息 (INFO)

消息文本: 客户端提供的身份类型当前不受支持 (Identity type provided by client is currently
unsupported)

消息说明：客户端建议在当前的内部方法中使用 ISE 不支持的身份类型。ISE 拒绝此身份类型。

本地目标消息格式：<timestamp> <seq_num> 12217 INFO EAP: Identity type provided by client is currently unsupported, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12217 INFO EAP: Identity type provided by client is currently unsupported, <log details>

- 消息代码：12218

严重性：信息 (INFO)

消息文本：已选择“用户”身份类型 (Selected identity type 'User')

消息说明：ISE 选择在当前的内部方法中使用“用户”身份类型。

本地目标消息格式：<timestamp> <seq_num> 12218 INFO EAP: Selected identity type 'User', <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12218 INFO EAP: Selected identity type 'User', <log details>

- 消息代码：12219

严重性：信息 (INFO)

消息文本：已选择“计算机”身份类型 (Selected identity type 'Machine')

消息说明：ISE 选择在当前的内部方法中使用“计算机”身份类型。

本地目标消息格式：<timestamp> <seq_num> 12219 INFO EAP: Selected identity type 'Machine', <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12219 INFO EAP: Selected identity type 'Machine', <log details>

- 消息代码：12220

严重性：信息 (INFO)

消息文本：客户端不支持 EAP 链接。(Client does not support EAP chaining.) 切换到普通模式

消息说明：ISE 向客户端发送 EAP-Request 中的身份类型 TLV，以执行 EP 链接。但是，客户端响应中没有身份类型 TLV。因此，客户端不支持 EAP 链接。ISE 正切换到普通模式。

本地目标消息格式：<timestamp> <seq_num> 12220 INFO EAP: Client does not support EAP chaining. Switching to usual mode, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12220 INFO EAP: Client does not support EAP chaining. Switching to usual mode, <log details>

- 消息代码：12221

严重性: 信息 (INFO)

消息文本: 客户端不支持 TLS 重新协商。(Client does not support TLS renegotiation.) 将继续使用内部方法

消息说明: ISE 尝试重新协商握手, 请求隧道内部的客户端证书, 但客户端不支持 TLS 重新协商

本地目标消息格式: <timestamp> <seq_num> 12221 INFO EAP: Client does not support TLS renegotiation. Will continue with inner method, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12221 INFO EAP: Client does not support TLS renegotiation. Will continue with inner method, <log details>

• 消息代码: 12222

严重性: 信息 (INFO)

消息文本: EAP-FAST 无 PAC 会话成功恢复 (EAP-FAST PAC-less session resumed successfully)

消息说明: 使用 EAP-FAST 身份验证的无 PAC 模式。使用短时握手成功建立隧道。

本地目标消息格式: <timestamp> <seq_num> 12222 INFO EAP: EAP-FAST PAC-less session resumed successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12222 INFO EAP: EAP-FAST PAC-less session resumed successfully, <log details>

• 消息代码: 12223

严重性: 信息 (INFO)

消息文本: 忽略请求方在回退以进行调配对话期间发送的 PAC (Ignore PAC send by supplicant during fallback to provisioning conversation)

消息说明: ISE 在无效的 PAC 上执行回退以进行调配。但是在此调配对话期间, 请求方重新发送了 PAC。ISE 会忽略此 PAC。

本地目标消息格式: <timestamp> <seq_num> 12223 INFO EAP: Ignore PAC send by supplicant during fallback to provisioning conversation, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12223 INFO EAP: Ignore PAC send by supplicant during fallback to provisioning conversation, <log details>

• 消息代码: 12224

严重性: 信息 (INFO)

消息文本: 由于相同类型的 PAC 已经用于跳过内部方法, 因此忽略用户授权 PAC 请求 (User Authorization PAC request ignored because PAC of the same type was already used to skip inner method)

消息说明: 由于相同类型的 PAC 已经用于跳过内部方法, 因此忽略用户授权 PAC 请求。只能在完整验证对话结束后提供授权 PAC。

本地目标消息格式: <timestamp> <seq_num> 12224 INFO EAP: User Authorization PAC request ignored because PAC of the same type was already used to skip inner method, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12224 INFO EAP: User Authorization PAC request ignored because PAC of the same type was already used to skip inner method, <log details>

• 消息代码: 12225

严重性: 信息 (INFO)

消息文本: 由于当前相同类型的 PAC 已经用于跳过内部方法, 因此忽略计算机授权 PAC 请求 (Ignore Machine Authorization PAC request because of current PAC of the same type was used to skip inner method)

消息说明: 由于当前相同类型的 PAC 已经用于跳过内部方法, 因此忽略计算机授权 PAC 请求。只能在完整验证对话结束后提供授权 PAC。

本地目标消息格式: <timestamp> <seq_num> 12225 INFO EAP: Ignore Machine Authorization PAC request because of current PAC of the same type was used to skip inner method, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12225 INFO EAP: Ignore Machine Authorization PAC request because of current PAC of the same type was used to skip inner method, <log details>

• 消息代码: 12226

严重性: 信息 (INFO)

消息文本: 已开始重新协商 TLS 握手 (Started renegotiated TLS handshake)

消息说明: ISE 已执行 TLS 重新协商, 并开始另一个 TLS 握手。

本地目标消息格式: <timestamp> <seq_num> 12226 INFO EAP: Started renegotiated TLS handshake, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12226 INFO EAP: Started renegotiated TLS handshake, <log details>

• 消息代码: 12227

严重性: 信息 (INFO)

消息文本: 用户授权 PAC 已过期 - 将运行内部方法 (User Authorization PAC has expired - will run inner method)

消息说明: 从客户端收到已过期的用户授权 PAC。已过期的授权 PAC 不能用于快速重新连接, 因此, ISE 将运行内部方法验证用户身份。

本地目标消息格式: <timestamp> <seq_num> 12227 INFO EAP: User Authorization PAC has expired - will run inner method, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12227 INFO EAP: User Authorization PAC
has expired - will run inner method, <log details>

- 消息代码: 12228

严重性: 信息 (INFO)

消息文本: 计算机授权 PAC 已过期 - 将运行内部方法 (Machine Authorization PAC has expired -
will run inner method)

消息说明: 从客户端收到已过期的计算机授权 PAC。已过期的授权 PAC 不能用于快速重新连接, 因此, ISE 将运行内部方法验证计算机身份。

本地目标消息格式: <timestamp> <seq_num> 12228 INFO EAP: Machine Authorization PAC has
expired - will run inner method, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12228 INFO EAP: Machine Authorization
PAC has expired - will run inner method, <log details>

- 消息代码: 12229

严重性: 警告 (WARN)

消息文本: 没有跟调配有关的有效 PAC 请求 (No valid PAC requests on provisioning)

消息说明: 客户端未在 EAP-FAST 调配对话结束时发送有效的 PAC 请求。应始终在调配对话结
束时向客户端发送所请求的一个或多个 PAC。由于在 EAP-FAST 协议的初始草稿中只有一个
PAC 类型, 并且没必要指定此类型, 因此, 旧客户端可能不请求特定的 PAC 在这种情况下,
ISE 会提供旧的隧道 V1 PAC。更高级的客户端可能会请求多个 PAC 类型, 但它们需要符合特
定的规则。例如, 如果未请求隧道 PAC, ISE 就不能提供用户授权 PAC。

本地目标消息格式: <timestamp> <seq_num> 12229 WARN EAP: No valid PAC requests on
provisioning, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12229 WARN EAP: No valid PAC requests
on provisioning, <log details>

- 消息代码: 12230

严重性: 信息 (INFO)

消息文本: 在无 PAC 模式下忽略任何 PAC 请求 (Ignore any PAC requests in PAC-less mode)

消息说明: 当 ISE 配置为无 PAC 模式时, 会忽略任何 PAC 请求

本地目标消息格式: <timestamp> <seq_num> 12230 INFO EAP: Ignore any PAC requests in PAC-less
mode, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12230 INFO EAP: Ignore any PAC requests
in PAC-less mode, <log details>

- 消息代码: 12231

严重性: 信息 (INFO)

消息文本: 在没有任何 EAP 链接时, 忽略计算机授权 PAC 请求 (Ignore Machine Authorization PAC request when there is no EAP chaining)

消息说明: 当对话中没有发生任何 EAP 链接时, ISE 会忽略计算机授权 PAC 请求。计算机授权 PAC 只能在 EAP 链接对话过程中提供。请注意, EAP 链接可以在 ISE 中配置, 但在客户端中被禁用或不受支持, 因此, 对话是在无链模式下进行的。

本地目标消息格式: <timestamp> <seq_num> 12231 INFO EAP: Ignore Machine Authorization PAC request when there is no EAP chaining, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12231 INFO EAP: Ignore Machine Authorization PAC request when there is no EAP chaining, <log details>

- 消息代码: 12232

严重性: 警告 (WARN)

消息文本: 由于未找到指定的主密钥, 因此无法解密 PAC - 拒绝 PAC (Cannot decrypt PAC because of specified master key was not found - rejecting the PAC)

消息说明: 从客户端收到由于未找到指定的主密钥, 因此无法解密 PAC 的消息。拒绝此 PAC。

本地目标消息格式: <timestamp> <seq_num> 12232 WARN EAP: Cannot decrypt PAC because of specified master key was not found - rejecting the PAC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12232 WARN EAP: Cannot decrypt PAC because of specified master key was not found - rejecting the PAC, <log details>

- 消息代码: 12233

严重性: 信息 (INFO)

消息文本: 检测到思科 IP 电话。(Cisco IP Phone detected.) 关闭 EAP 链接

消息说明: 针对思科 IP 电话身份验证关闭 EAP 链接

本地目标消息格式: <timestamp> <seq_num> 12233 INFO EAP: Cisco IP Phone detected. Turn EAP chaining off, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12233 INFO EAP: Cisco IP Phone detected. Turn EAP chaining off, <log details>

- 消息代码: 12234

严重性: 信息 (INFO)

消息文本: 客户端被检测为思科 IP 电话 (Client is detected as Cisco IP Phone)

消息说明: 客户端被检测为思科 IP 电话

本地目标消息格式: <timestamp> <seq_num> 12234 INFO EAP: Client is detected as Cisco IP Phone, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12234 INFO EAP: Client is detected as Cisco IP Phone, <log details>

- 消息代码: 12235

严重性: 警告 (WARN)

消息文本: 在 EAP-FAST 握手过程中意外收到空的 TLS 消息; 视为客户端拒绝 (Unexpectedly received empty TLS message during EAP-FAST handshake; treating as a rejection by the client)

消息说明: 当尝试与 EAP-FAST 隧道内的客户端协商 TLS 握手时, ISE 期望收到非空 TLS 消息或 TLS 警报消息, 但收到空 TLS 消息。这可能是因为 ISE 和请求方在实施协议方面存在不一致。ISE 将异常消息视为客户端拒绝重新协商隧道的信号。

本地目标消息格式: <timestamp> <seq_num> 12235 WARN EAP: Unexpectedly received empty TLS message during EAP-FAST handshake; treating as a rejection by the client, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12235 WARN EAP: Unexpectedly received empty TLS message during EAP-FAST handshake; treating as a rejection by the client, <log details>

- 消息代码: 12236

严重性: 警告 (WARN)

消息文本: 计算机授权 PAC I-ID 与用户身份不匹配。(Machine Authorization PAC I-ID does not match user identity.) 忽略此计算机授权 PAC 请求

消息说明: 计算机授权 PAC I-ID 与用户身份不匹配。忽略此计算机授权 PAC 请求

本地目标消息格式: <timestamp> <seq_num> 12236 WARN EAP: Machine Authorization PAC I-ID does not match user identity. Ignoring this Machine Authorization PAC request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12236 WARN EAP: Machine Authorization PAC I-ID does not match user identity. Ignoring this Machine Authorization PAC request, <log details>

- 消息代码: 12300

严重性: 信息 (INFO)

消息文本: 已准备提议使用 PEAP 和质询的 EAP 请求 (Prepared EAP-Request proposing PEAP with challenge)

消息说明: 已创建一个 EAP 请求数据包, 提议使用 PEAP 协议, 同时提供 PEAP 质询, 用于附加到 RADIUS 消息。建议使用 PEAP 协议的原因在于此协议是“允许的协议”中允许使用的其中一个基于 EAP 的协议。

本地目标消息格式: <timestamp> <seq_num> 12300 INFO EAP: Prepared EAP-Request proposing PEAP with challenge, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12300 INFO EAP: Prepared EAP-Request
proposing PEAP with challenge, <log details>

- 消息代码: 12301

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应/NAK 请求改为使用 PEAP (Extracted EAP-Response/NAK requesting
to use PEAP instead)

消息说明: 从 RADIUS 消息中提取的 EAP 响应/NAK 数据包拒绝之前提议的基于 EAP 的协议,
且根据客户端请求方的配置, 请求改为使用 PEAP。

本地目标消息格式: <timestamp> <seq_num> 12301 INFO EAP: Extracted EAP-Response/NAK
requesting to use PEAP instead, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12301 INFO EAP: Extracted
EAP-Response/NAK requesting to use PEAP instead, <log details>

- 消息代码: 12302

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应包含 PEAP 质询-响应, 且接受将 PEAP 用作协商协议 (Extracted
EAP-Response containing PEAP challenge-response and accepting PEAP as negotiated)

消息说明: 从 RADIUS 消息中提取的 EAP 响应数据包含有 PEAP 质询-响应, 且接受将 PEAP
用作协商协议。

本地目标消息格式: <timestamp> <seq_num> 12302 INFO EAP: Extracted EAP-Response containing
PEAP challenge-response and accepting PEAP as negotiated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12302 INFO EAP: Extracted EAP-Response
containing PEAP challenge-response and accepting PEAP as negotiated, <log details>

- 消息代码: 12303

严重性: 警告 (WARN)

消息文本: 由于 PEAP 未在“允许的协议”中获得允许, 因此 EAP 协商失败 (Failed to negotiate
EAP because PEAP not allowed in the Allowed Protocols)

消息说明: 客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前提议的基于 EAP 的协议, 且请
求改为使用 PEAP。但是, PEAP 未在“允许的协议”中获得允许。

本地目标消息格式: <timestamp> <seq_num> 12303 WARN EAP: Failed to negotiate EAP because
PEAP not allowed in the Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12303 WARN EAP: Failed to negotiate EAP
because PEAP not allowed in the Allowed Protocols, <log details>

- 消息代码: 12304

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应包含 PEAP 质询-响应 (Extracted EAP-Response containing PEAP challenge-response)

消息说明: 继续使用 PEAP 协议; 处理已提取的 EAP 响应中的 PEAP 质询-响应。

本地目标消息格式: <timestamp> <seq_num> 12304 INFO EAP: Extracted EAP-Response containing PEAP challenge-response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12304 INFO EAP: Extracted EAP-Response containing PEAP challenge-response, <log details>

- 消息代码: 12305

严重性: 信息 (INFO)

消息文本: 已准备包含其他 PEAP 质询的 EAP 请求 (Prepared EAP-Request with another PEAP challenge)

消息说明: 为了继续使用 PEAP 协议, 已创建包含其他 PEAP 质询的 EAP 请求数据包, 用于附加到 RADIUS 消息。

本地目标消息格式: <timestamp> <seq_num> 12305 INFO EAP: Prepared EAP-Request with another PEAP challenge, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12305 INFO EAP: Prepared EAP-Request with another PEAP challenge, <log details>

- 消息代码: 12306

严重性: 信息 (INFO)

消息文本: PEAP 身份验证成功 (PEAP authentication succeeded)

消息说明: PEAP 身份验证成功。

本地目标消息格式: <timestamp> <seq_num> 12306 INFO EAP: PEAP authentication succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12306 INFO EAP: PEAP authentication succeeded, <log details>

- 消息代码: 12307

严重性: 信息 (INFO)

消息文本: PEAP 身份验证失败 (PEAP authentication failed)

消息说明: PEAP 身份验证失败。

本地目标消息格式: <timestamp> <seq_num> 12307 INFO EAP: PEAP authentication failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12307 INFO EAP: PEAP authentication failed, <log details>

- 消息代码: 12308

严重性: 警告 (WARN)

消息文本: 客户端发送的 TEAP 结果 TLV 表明失败 (Client sent Result TLV indicating failure)

消息说明: 可能是请求方出现内部错误: 由于客户端发送的 Result TLV 表明失败, 因此 PEAP v0 身份验证失败。客户端指示它不支持加密绑定 TLV

本地目标消息格式: <timestamp> <seq_num> 12308 WARN EAP: Client sent Result TLV indicating failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12308 WARN EAP: Client sent Result TLV indicating failure, <log details>

- 消息代码: 12309

严重性: 警告 (WARN)

消息文本: PEAP 握手失败 (PEAP handshake failed)

消息说明: PEAP 握手失败。

本地目标消息格式: <timestamp> <seq_num> 12309 WARN EAP: PEAP handshake failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12309 WARN EAP: PEAP handshake failed, <log details>

- 消息代码: 12310

严重性: 信息 (INFO)

消息文本: PEAP 完全握手成功完成 (PEAP full handshake finished successfully)

消息说明: PEAP 完全握手成功完成。

本地目标消息格式: <timestamp> <seq_num> 12310 INFO EAP: PEAP full handshake finished successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12310 INFO EAP: PEAP full handshake finished successfully, <log details>

- 消息代码: 12311

严重性: 信息 (INFO)

消息文本: PEAP 会话成功恢复 (PEAP session resumed successfully)

消息说明: PEAP 短时握手成功完成 - 已恢复之前的会话。

本地目标消息格式: <timestamp> <seq_num> 12311 INFO EAP: PEAP session resumed successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12311 INFO EAP: PEAP session resumed successfully, <log details>

- 消息代码: 12312

严重性: 信息 (INFO)

消息文本: PEAP 快速重新连接 - 跳过内部方法 (PEAP fast-reconnect - skipping inner method)

消息说明: PEAP 快速重新连接 - 跳过内部方法。

本地目标消息格式: <timestamp> <seq_num> 12312 INFO EAP: PEAP fast-reconnect - skipping inner method, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12312 INFO EAP: PEAP fast-reconnect - skipping inner method, <log details>

- 消息代码: 12313

严重性: 信息 (INFO)

消息文本: 已开始 PEAP 内部方法 (PEAP inner method started)

消息说明: 已开始 PEAP 内部方法。

本地目标消息格式: <timestamp> <seq_num> 12313 INFO EAP: PEAP inner method started, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12313 INFO EAP: PEAP inner method started, <log details>

- 消息代码: 12314

严重性: 信息 (INFO)

消息文本: PEAP 内部方法成功完成 (PEAP inner method finished successfully)

消息说明: PEAP 内部方法成功完成。

本地目标消息格式: <timestamp> <seq_num> 12314 INFO EAP: PEAP inner method finished successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12314 INFO EAP: PEAP inner method finished successfully, <log details>

- 消息代码: 12315

严重性: 信息 (INFO)

消息文本: PEAP 内部方法以失败告终 (PEAP inner method finished with failure)

消息说明: PEAP 内部方法以失败告终。

本地目标消息格式: <timestamp> <seq_num> 12315 INFO EAP: PEAP inner method finished with failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12315 INFO EAP: PEAP inner method finished with failure, <log details>

- 消息代码: 12316

严重性: 警告 (WARN)

消息文本: PEAP 版本协商失败 (PEAP version negotiation failed)

消息说明: PEAP 版本协商失败, 这显然是因为请求方不支持 v0 和 v1。

本地目标消息格式: <timestamp> <seq_num> 12316 WARN EAP: PEAP version negotiation failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12316 WARN EAP: PEAP version negotiation failed, <log details>

- 消息代码: 12317

严重性: 信息 (INFO)

消息文本: PEAP 快速重新连接失败; 开始内部方法 (PEAP fast-reconnect failed; starting inner method)

消息说明: PEAP 快速重新连接失败, 这可能是由内部缓存相关问题, 或者可能是没有继续为 PEAP 启用之前身份验证中使用的内部方法导致的。ISE 需要在 PEAP 设置中启用快速重新连接时执行完整的 PEAP 身份验证。开始内部方法。

本地目标消息格式: <timestamp> <seq_num> 12317 INFO EAP: PEAP fast-reconnect failed; starting inner method, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12317 INFO EAP: PEAP fast-reconnect failed; starting inner method, <log details>

- 消息代码: 12318

严重性: 信息 (INFO)

消息文本: 已成功协商 PEAP 版本 0 (Successfully negotiated PEAP version 0)

消息说明: 已成功协商 PEAP 版本 0。

本地目标消息格式: <timestamp> <seq_num> 12318 INFO EAP: Successfully negotiated PEAP version 0, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12318 INFO EAP: Successfully negotiated PEAP version 0, <log details>

- 消息代码: 12319
 - 严重性: 信息 (INFO)
 - 消息文本: 已成功协商 PEAP 版本 1 (Successfully negotiated PEAP version 1)
 - 消息说明: 已成功协商 PEAP 版本 1。
 - 本地目标消息格式: <timestamp> <seq_num> 12319 INFO EAP: Successfully negotiated PEAP version 1, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12319 INFO EAP: Successfully negotiated PEAP version 1, <log details>

- 消息代码: 12320
 - 严重性: 警告 (WARN)
 - 消息文本: 客户端未能确认收到成功或失败结果 (Client failed to acknowledge receipt of success or failure result)
 - 消息说明: 可能是请求方出现内部错误: 由于客户端未能确认收到成功或失败结果, 因此 PEAP v1 身份验证失败。
 - 本地目标消息格式: <timestamp> <seq_num> 12320 WARN EAP: Client failed to acknowledge receipt of success or failure result, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12320 WARN EAP: Client failed to acknowledge receipt of success or failure result, <log details>

- 消息代码: 12321
 - 严重性: 警告 (WARN)
 - 消息文本: PEAP 进行 SSL/TLS 握手失败, 因为客户端拒绝 ISE 本地证书 (PEAP failed SSL/TLS handshake because the client rejected the ISE local-certificate)
 - 消息说明: PEAP 进行 SSL/TLS 握手失败, 因为客户端拒绝 ISE 本地证书
 - 本地目标消息格式: <timestamp> <seq_num> 12321 WARN EAP: PEAP failed SSL/TLS handshake because the client rejected the ISE local-certificate, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12321 WARN EAP: PEAP failed SSL/TLS handshake because the client rejected the ISE local-certificate, <log details>

- 消息代码: 12322
 - 严重性: 警告 (WARN)
 - 消息文本: 在客户端发出警报后, PEAP 进行 SSL/TLS 握手失败 (PEAP failed SSL/TLS handshake after a client alert)
 - 消息说明: 在客户端发出警报后, PEAP 进行 SSL/TLS 握手失败

本地目标消息格式: <timestamp> <seq_num> 12322 WARN EAP: PEAP failed SSL/TLS handshake after a client alert, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12322 WARN EAP: PEAP failed SSL/TLS handshake after a client alert, <log details>

- 消息代码: 12323

严重性: 警告 (WARN)

消息文本: PEAP 加密绑定验证失败 (PEAP cryptobinding verification failed)

消息说明: PEAP 加密绑定验证失败。

本地目标消息格式: <timestamp> <seq_num> 12323 WARN EAP: PEAP cryptobinding verification failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12323 WARN EAP: PEAP cryptobinding verification failed, <log details>

- 消息代码: 12324

严重性: 调试 (DEBUG)

消息文本: PEAP 加密绑定验证通过 (PEAP cryptobinding verification passed)

消息说明: PEAP 加密绑定验证通过。

本地目标消息格式: <timestamp> <seq_num> 12324 DEBUG EAP: PEAP cryptobinding verification passed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12324 DEBUG EAP: PEAP cryptobinding verification passed, <log details>

- 消息代码: 12500

严重性: 信息 (INFO)

消息文本: 已准备提议使用 EAP-TLS 和质询的 EAP 请求 (Prepared EAP-Request proposing EAP-TLS with challenge)

消息说明: 已创建一个 EAP 请求数据包, 提议使用 EAP-TLS 协议, 同时提供 EAP-TLS 质询, 用于附加到 RADIUS 消息。建议使用 TLS 协议的原因在于此协议是“允许的协议”中允许使用的其中一个基于 EAP 的协议。

本地目标消息格式: <timestamp> <seq_num> 12500 INFO EAP: Prepared EAP-Request proposing EAP-TLS with challenge, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12500 INFO EAP: Prepared EAP-Request proposing EAP-TLS with challenge, <log details>

- 消息代码: 12501

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应/NAK 请求改为使用 EAP-TLS (Extracted EAP-Response/NAK requesting to use EAP-TLS instead)

消息说明: 从 RADIUS 消息中提取的 EAP 响应/NAK 数据包拒绝之前提议的基于 EAP 的协议, 且根据客户端请求方的配置, 请求改为使用 EAP-TLS。

本地目标消息格式: <timestamp> <seq_num> 12501 INFO EAP: Extracted EAP-Response/NAK requesting to use EAP-TLS instead, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12501 INFO EAP: Extracted EAP-Response/NAK requesting to use EAP-TLS instead, <log details>

- 消息代码: 12502

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应包含 EAP-TLS 质询-响应, 且接受将 EAP-TLS 用作协商协议 (Extracted EAP-Response containing EAP-TLS challenge-response and accepting EAP-TLS as negotiated)

消息说明: 从 RADIUS 消息中提取的 EAP 响应数据包含有 EAP-TLS 质询-响应, 且接受将 EAP-TLS 用作协商协议。

本地目标消息格式: <timestamp> <seq_num> 12502 INFO EAP: Extracted EAP-Response containing EAP-TLS challenge-response and accepting EAP-TLS as negotiated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12502 INFO EAP: Extracted EAP-Response containing EAP-TLS challenge-response and accepting EAP-TLS as negotiated, <log details>

- 消息代码: 12503

严重性: 警告 (WARN)

消息文本: 由于 EAP-TLS 未在“允许的协议”中启用, 因此 EAP 协商失败 (Failed to negotiate EAP because EAP-TLS not enabled in Allowed Protocols)

消息说明: 客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前提议的基于 EAP 的协议, 且请求改为使用 EAP-TLS。但是, EAP-TLS 未在“允许的协议”中获得允许。

本地目标消息格式: <timestamp> <seq_num> 12503 WARN EAP: Failed to negotiate EAP because EAP-TLS not enabled in Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12503 WARN EAP: Failed to negotiate EAP because EAP-TLS not enabled in Allowed Protocols, <log details>

- 消息代码: 12504

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应包含 EAP-TLS 质询-响应 (Extracted EAP-Response containing EAP-TLS challenge-response)

消息说明：继续使用 EAP-TLS 协议；处理已提取的 EAP 响应中的 EAP-TLS 质询-响应。

本地目标消息格式：<timestamp> <seq_num> 12504 INFO EAP: Extracted EAP-Response containing EAP-TLS challenge-response, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12504 INFO EAP: Extracted EAP-Response containing EAP-TLS challenge-response, <log details>

- 消息代码：12505

严重性：信息 (INFO)

消息文本：已准备包含其他 EAP-TLS 质询的 EAP 请求 (Prepared EAP-Request with another EAP-TLS challenge)

消息说明：为了继续使用 EAP-TLS 协议，已创建包含其他 EAP-TLS 质询的 EAP 请求数据包，用于附加到 RADIUS 消息。

本地目标消息格式：<timestamp> <seq_num> 12505 INFO EAP: Prepared EAP-Request with another EAP-TLS challenge, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12505 INFO EAP: Prepared EAP-Request with another EAP-TLS challenge, <log details>

- 消息代码：12506

严重性：信息 (INFO)

消息文本：EAP-TLS 身份验证成功 (EAP-TLS authentication succeeded)

消息说明：EAP-TLS 身份验证成功。

本地目标消息格式：<timestamp> <seq_num> 12506 INFO EAP: EAP-TLS authentication succeeded, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12506 INFO EAP: EAP-TLS authentication succeeded, <log details>

- 消息代码：12507

严重性：信息 (INFO)

消息文本：EAP-TLS 身份验证失败 (EAP-TLS authentication failed)

消息说明：EAP-TLS 身份验证失败。

本地目标消息格式：<timestamp> <seq_num> 12507 INFO EAP: EAP-TLS authentication failed, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12507 INFO EAP: EAP-TLS authentication failed, <log details>

- 消息代码：12508

严重性: 警告 (WARN)

消息文本: EAP-TLS 握手失败 (EAP-TLS handshake failed)

消息说明: EAP-TLS 握手失败。

本地目标消息格式: <timestamp> <seq_num> 12508 WARN EAP: EAP-TLS handshake failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12508 WARN EAP: EAP-TLS handshake failed, <log details>

• 消息代码: 12509

严重性: 信息 (INFO)

消息文本: EAP-TLS 完全握手成功完成 (EAP-TLS full handshake finished successfully)

消息说明: EAP-TLS 完全握手成功完成。

本地目标消息格式: <timestamp> <seq_num> 12509 INFO EAP: EAP-TLS full handshake finished successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12509 INFO EAP: EAP-TLS full handshake finished successfully, <log details>

• 消息代码: 12510

严重性: 信息 (INFO)

消息文本: EAP-TLS 会话成功恢复 (EAP-TLS session resumed successfully)

消息说明: EAP-TLS 短时握手成功完成 - 已恢复之前的会话。

本地目标消息格式: <timestamp> <seq_num> 12510 INFO EAP: EAP-TLS session resumed successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12510 INFO EAP: EAP-TLS session resumed successfully, <log details>

• 消息代码: 12511

严重性: 警告 (WARN)

消息文本: 意外收到 TLS 警报消息; 视为客户端拒绝 (Unexpectedly received TLS alert message; treating as a rejection by the client)

消息说明: 当尝试与客户端协商 TLS 握手时, ISE 收到意外 TLS 警报消息。这可能是由于请求方出于某种原因不信任 ISE 服务器证书造成的。ISE 将意外消息视为客户端拒绝建立隧道的信号。

本地目标消息格式: <timestamp> <seq_num> 12511 WARN EAP: Unexpectedly received TLS alert message; treating as a rejection by the client, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12511 WARN EAP: Unexpectedly received
TLS alert message; treating as a rejection by the client, <log details>

- 消息代码: 12512

严重性: 警告 (WARN)

消息文本: 将意外 TLS 确认消息视为客户端的拒绝 (Treat the unexpected TLS acknowledge message
as a rejection from the client)

消息说明: 将建立隧道过程中收到的意外 TLS 确认消息视为客户端的拒绝

本地目标消息格式: <timestamp> <seq_num> 12512 WARN EAP: Treat the unexpected TLS
acknowledge message as a rejection from the client, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12512 WARN EAP: Treat the unexpected
TLS acknowledge message as a rejection from the client, <log details>

- 消息代码: 12513

严重性: 警告 (WARN)

消息文本: 无法建立 EAP TLS SSL 会话 (Could not establish the EAP TLS SSL session)

消息说明: 无法建立 EAP TLS SSL 会话

本地目标消息格式: <timestamp> <seq_num> 12513 WARN EAP: Could not establish the EAP TLS
SSL session, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12513 WARN EAP: Could not establish the
EAP TLS SSL session, <log details>

- 消息代码: 12514

严重性: 警告 (WARN)

消息文本: EAP-TLS 进行 SSL/TLS 握手失败, 因为客户端证书链中存在未知 CA (EAP-TLS failed
SSL/TLS handshake because of an unknown CA in the client certificates chain)

消息说明: EAP-TLS 进行 SSL/TLS 握手失败, 因为客户端证书链中存在未知 CA

本地目标消息格式: <timestamp> <seq_num> 12514 WARN EAP: EAP-TLS failed SSL/TLS handshake
because of an unknown CA in the client certificates chain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12514 WARN EAP: EAP-TLS failed SSL/TLS
handshake because of an unknown CA in the client certificates chain, <log details>

- 消息代码: 12515

严重性: 警告 (WARN)

消息文本: EAP-TLS 进行 SSL/TLS 握手失败, 因为客户端证书链中存在与 CA 关联的过期 CRL (EAP-TLS failed SSL/TLS handshake because of an expired CRL associated with a CA in the client certificates chain)

消息说明: EAP-TLS 进行 SSL/TLS 握手失败, 因为客户端证书链中存在与 CA 关联的过期 CRL

本地目标消息格式: <timestamp> <seq_num> 12515 WARN EAP: EAP-TLS failed SSL/TLS handshake because of an expired CRL associated with a CA in the client certificates chain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 12515 WARN EAP: EAP-TLS failed SSL/TLS handshake because of an expired CRL associated with a CA in the client certificates chain, <log details>

- 消息代码: 12516

严重性: 警告 (WARN)

消息文本: EAP-TLS 进行 SSL/TLS 握手失败, 因为客户端证书链中存在过期证书 (EAP-TLS failed SSL/TLS handshake because of an expired certificate in the client certificates chain)

消息说明: EAP-TLS 进行 SSL/TLS 握手失败, 因为客户端证书链中存在过期证书

本地目标消息格式: <timestamp> <seq_num> 12516 WARN EAP: EAP-TLS failed SSL/TLS handshake because of an expired certificate in the client certificates chain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 12516 WARN EAP: EAP-TLS failed SSL/TLS handshake because of an expired certificate in the client certificates chain, <log details>

- 消息代码: 12517

严重性: 警告 (WARN)

消息文本: EAP-TLS 进行 SSL/TLS 握手失败, 因为客户端证书链中存在已撤销的证书 (EAP-TLS failed SSL/TLS handshake because of a revoked certificate in the client certificate chain)

消息说明: EAP-TLS 进行 SSL/TLS 握手失败, 因为客户端证书链中存在已撤销的证书

本地目标消息格式: <timestamp> <seq_num> 12517 WARN EAP: EAP-TLS failed SSL/TLS handshake because of a revoked certificate in the client certificate chain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 12517 WARN EAP: EAP-TLS failed SSL/TLS handshake because of a revoked certificate in the client certificate chain, <log details>

- 消息代码: 12518

严重性: 警告 (WARN)

消息文本: EAP-TLS 进行 SSL/TLS 握手失败, 因为客户端证书链中存在坏证书 (EAP-TLS failed SSL/TLS handshake because of a bad certificate in the client certificate chain)

消息说明: EAP-TLS 进行 SSL/TLS 握手失败, 因为客户端证书链中存在坏证书

本地目标消息格式: <timestamp> <seq_num> 12518 WARN EAP: EAP-TLS failed SSL/TLS handshake because of a bad certificate in the client certificate chain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12518 WARN EAP: EAP-TLS failed SSL/TLS
handshake because of a bad certificate in the client certificate chain, <log details>

- 消息代码: 12519

严重性: 警告 (WARN)

消息文本: EAP-TLS 进行 SSL/TLS 握手失败, 因为客户端证书链中存在不受支持的证书 (EAP-TLS failed SSL/TLS handshake because of an unsupported certificate in the client certificate chain)

消息说明: EAP-TLS 进行 SSL/TLS 握手失败, 因为客户端证书链中存在不受支持的证书

本地目标消息格式: <timestamp> <seq_num> 12519 WARN EAP: EAP-TLS failed SSL/TLS handshake because of an unsupported certificate in the client certificate chain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12519 WARN EAP: EAP-TLS failed SSL/TLS
handshake because of an unsupported certificate in the client certificate chain, <log details>

- 消息代码: 12520

严重性: 警告 (WARN)

消息文本: EAP-TLS 进行 SSL/TLS 握手失败, 因为客户端拒绝 ISE 本地证书 (EAP-TLS failed SSL/TLS handshake because the client rejected the ISE local-certificate)

消息说明: EAP-TLS 进行 SSL/TLS 握手失败, 因为客户端拒绝 ISE 本地证书

本地目标消息格式: <timestamp> <seq_num> 12520 WARN EAP: EAP-TLS failed SSL/TLS handshake because the client rejected the ISE local-certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12520 WARN EAP: EAP-TLS failed SSL/TLS
handshake because the client rejected the ISE local-certificate, <log details>

- 消息代码: 12521

严重性: 警告 (WARN)

消息文本: 在客户端发出警报后, EAP-TLS 进行 SSL/TLS 握手失败 (EAP-TLS failed SSL/TLS handshake after a client alert)

消息说明: 在客户端发出警报后, EAP-TLS 进行 SSL/TLS 握手失败

本地目标消息格式: <timestamp> <seq_num> 12521 WARN EAP: EAP-TLS failed SSL/TLS handshake after a client alert, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12521 WARN EAP: EAP-TLS failed SSL/TLS
handshake after a client alert, <log details>

- 消息代码: 12522

严重性: 信息 (INFO)

消息文本: 已为内部方法准备提议使用 EAP-TLS 和质询的 EAP 请求 (Prepared EAP-Request for inner method proposing EAP-TLS with challenge)

消息说明: 已创建一个 EAP 请求数据包, 提议对内部方法使用 EAP-TLS 协议, 同时提供 TLS 质询, 用于附加到 RADIUS 消息。建议使用 EAP-TLS 协议的原因在于此协议是“允许的协议”中允许使用的其中一个基于 EAP 的协议。

本地目标消息格式: <timestamp> <seq_num> 12522 INFO EAP: Prepared EAP-Request for inner method proposing EAP-TLS with challenge, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12522 INFO EAP: Prepared EAP-Request for inner method proposing EAP-TLS with challenge, <log details>

- 消息代码: 12523

严重性: 信息 (INFO)

消息文本: 提取的内部方法 EAP 响应/NAK 请求改为使用 EAP-TLS (Extracted EAP-Response/NAK for inner method requesting to use EAP-TLS instead)

消息说明: 从在外部 EAP 方法中遇到的 EAP 响应数据包中, 提取的 EAP 响应/NAK 数据包拒绝之前为内部方法提议的基于 EAP 的协议, 并根据客户端请求方的配置请求改为使用 EAP-TLS。

本地目标消息格式: <timestamp> <seq_num> 12523 INFO EAP: Extracted EAP-Response/NAK for inner method requesting to use EAP-TLS instead, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12523 INFO EAP: Extracted EAP-Response/NAK for inner method requesting to use EAP-TLS instead, <log details>

- 消息代码: 12524

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应包含内部方法 EAP-TLS 质询-响应, 且接受将 EAP-TLS 用作协商协议 (Extracted EAP-Response containing EAP-TLS challenge-response for inner method and accepting EAP-TLS as negotiated)

消息说明: 从在外部 EAP 方法中遇到的 EAP 响应数据包中, 提取的 EAP 响应数据包含有 EAP-TLS 质询-响应, 且接受将 EAP-TLS 用作内部方法的协商协议。

本地目标消息格式: <timestamp> <seq_num> 12524 INFO EAP: Extracted EAP-Response containing EAP-TLS challenge-response for inner method and accepting EAP-TLS as negotiated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12524 INFO EAP: Extracted EAP-Response containing EAP-TLS challenge-response for inner method and accepting EAP-TLS as negotiated, <log details>

- 消息代码: 12525

严重性: 警告 (WARN)

消息文本: 由于 EAP-TLS 未在“允许的协议”中获得允许, 因此 EAP 协商失败 (Failed to negotiate EAP for inner method because EAP-TLS not allowed in the Allowed Protocols)

消息说明: 客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前为内部方法提议的基于 EAP 的协议, 且请求改为使用 EAP-TLS。但是, EAP-TLS 未在“允许的协议”中获得允许。

本地目标消息格式: <timestamp> <seq_num> 12525 WARN EAP: Failed to negotiate EAP for inner method because EAP-TLS not allowed in the Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12525 WARN EAP: Failed to negotiate EAP for inner method because EAP-TLS not allowed in the Allowed Protocols, <log details>

- 消息代码: 12526

严重性: 信息 (INFO)

消息文本: 提取的内部方法 EAP 响应包含 TLS 质询-响应 (Extracted EAP-Response for inner method containing TLS challenge-response)

消息说明: 继续使用内部 EAP-TLS 协议; 处理已提取的 EAP 响应中的 EAP-TLS 质询-响应。

本地目标消息格式: <timestamp> <seq_num> 12526 INFO EAP: Extracted EAP-Response for inner method containing TLS challenge-response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12526 INFO EAP: Extracted EAP-Response for inner method containing TLS challenge-response, <log details>

- 消息代码: 12527

严重性: 信息 (INFO)

消息文本: 已准备包含其他 EAP-TLS 质询的内部方法 EAP 请求 (Prepared EAP-Request for inner method with another EAP-TLS challenge)

消息说明: 为了继续使用内部 EAP-TLS 协议, 已创建包含其他 EAP-TLS 质询的 EAP 请求数据包, 用于封装到外部 EAP 方法的传出 EAP 请求数据包中, 并最终附加到 RADIUS 消息中。

本地目标消息格式: <timestamp> <seq_num> 12527 INFO EAP: Prepared EAP-Request for inner method with another EAP-TLS challenge, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12527 INFO EAP: Prepared EAP-Request for inner method with another EAP-TLS challenge, <log details>

- 消息代码: 12528

严重性: 信息 (INFO)

消息文本: 内部 EAP-TLS 身份验证成功 (Inner EAP-TLS authentication succeeded)

消息说明: 内部 EAP 方法的 EAP-TLS 身份验证成功。

本地目标消息格式: <timestamp> <seq_num> 12528 INFO EAP: Inner EAP-TLS authentication succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12528 INFO EAP: Inner EAP-TLS authentication succeeded, <log details>

- 消息代码: 12529

严重性: 信息 (INFO)

消息文本: 内部 EAP-TLS 身份验证失败 (Inner EAP-TLS authentication failed)

消息说明: 内部 EAP 方法的 EAP-TLS 身份验证失败。

本地目标消息格式: <timestamp> <seq_num> 12529 INFO EAP: Inner EAP-TLS authentication failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12529 INFO EAP: Inner EAP-TLS authentication failed, <log details>

- 消息代码: 12530

严重性: 警告 (WARN)

消息文本: EAP-TLS 进行 SSL/TLS 握手失败, 因为客户端证书尚未有效 (EAP-TLS failed SSL/TLS handshake because of the client certificate is not yet valid)

消息说明: EAP-TLS 进行 SSL/TLS 握手失败, 因为客户端证书尚未有效

本地目标消息格式: <timestamp> <seq_num> 12530 WARN EAP: EAP-TLS failed SSL/TLS handshake because of the client certificate is not yet valid, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12530 WARN EAP: EAP-TLS failed SSL/TLS handshake because of the client certificate is not yet valid, <log details>

- 消息代码: 12531

严重性: 警告 (WARN)

消息文本: 已成功更新 EAP-TLS 种子密钥 (Successfully updated EAP-TLS seed key)

消息说明: 已成功更新用于进一步生成主密钥的 EAP-TLS 种子密钥。

本地目标消息格式: <timestamp> <seq_num> 12531 WARN EAP: Successfully updated EAP-TLS seed key, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12531 WARN EAP: Successfully updated EAP-TLS seed key, <log details>

- 消息代码: 12532

严重性: 警告 (WARN)

消息文本: 未能更新种子密钥 (Failed to update seed key)

消息说明：内部错误：未能更新进一步生成主密钥所需的 EAP-TLS 种子密钥，这很可能是因为无法正确获取内部配置对象。

本地目标消息格式：<timestamp> <seq_num> 12532 WARN EAP: Failed to update seed key, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12532 WARN EAP: Failed to update seed key, <log details>

- 消息代码：12533

严重性：信息 (INFO)

消息文本：已更新 EAP-TLS 主密钥生成期 (Updated EAP-TLS Master Key Generation period)

消息说明：已更新 EAP-TLS 主密钥生成期。

本地目标消息格式：<timestamp> <seq_num> 12533 INFO EAP: Updated EAP-TLS Master Key Generation period, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12533 INFO EAP: Updated EAP-TLS Master Key Generation period, <log details>

- 消息代码：12534

严重性：信息 (INFO)

消息文本：从请求方收到 EAP-TLS 会话票证 (EAP-TLS session ticket received from supplicant)

消息说明：从请求方收到 EAP-TLS 会话票证。

本地目标消息格式：<timestamp> <seq_num> 12534 INFO EAP: EAP-TLS session ticket received from supplicant, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12534 INFO EAP: EAP-TLS session ticket received from supplicant, <log details>

- 消息代码：12535

严重性：警告 (WARN)

消息文本：从请求方收到的 EAP-TLS 会话票证已过期 (The EAP-TLS session ticket received from supplicant is expired)

消息说明：从请求方收到已过期的会话票证。拒绝此 PAC。

本地目标消息格式：<timestamp> <seq_num> 12535 WARN EAP: The EAP-TLS session ticket received from supplicant is expired, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12535 WARN EAP: The EAP-TLS session ticket received from supplicant is expired, <log details>

- 消息代码：12536

严重性: 警告 (WARN)

消息文本: 未能验证从请求方收到 EAP-TLS 会话票证。(Failed to verify the EAP-TLS session ticket received from supplicant.)

消息说明: 未能验证从请求方收到 EAP-TLS 会话票证。

本地目标消息格式: <timestamp> <seq_num> 12536 WARN EAP: Failed to verify the EAP-TLS session ticket received from supplicant., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12536 WARN EAP: Failed to verify the EAP-TLS session ticket received from supplicant., <log details>

• 消息代码: 12537

严重性: 警告 (WARN)

消息文本: EAP-TLS 会话票证身份与 EAP 身份不匹配 (The EAP-TLS session ticket identity does not match the EAP identity)

消息说明: EAP-TLS 会话票证身份与 EAP 身份不匹配。

本地目标消息格式: <timestamp> <seq_num> 12537 WARN EAP: The EAP-TLS session ticket identity does not match the EAP identity, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12537 WARN EAP: The EAP-TLS session ticket identity does not match the EAP identity, <log details>

• 消息代码: 12538

严重性: 警告 (WARN)

消息文本: 从请求方收到的 EAP-TLS 会话票证包含无效的身份验证代码 (The EAP-TLS session ticket received from supplicant contains an invalid authentication code)

消息说明: 从请求方收到的 EAP-TLS 会话票证包含无效的身份验证代码。

本地目标消息格式: <timestamp> <seq_num> 12538 WARN EAP: The EAP-TLS session ticket received from supplicant contains an invalid authentication code, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12538 WARN EAP: The EAP-TLS session ticket received from supplicant contains an invalid authentication code, <log details>

• 消息代码: 12539

严重性: 警告 (WARN)

消息文本: 未能解密从请求方收到 EAP-TLS 会话票证 (Failed to decrypt the EAP-TLS session ticket received from supplicant)

消息说明: 未能解密从请求方收到 EAP-TLS 会话票证。

本地目标消息格式: <timestamp> <seq_num> 12539 WARN EAP: Failed to decrypt the EAP-TLS session ticket received from supplicant, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12539 WARN EAP: Failed to decrypt the
EAP-TLS session ticket received from supplicant, <log details>

- 消息代码: 12540

严重性: 信息 (INFO)

消息文本: 已成功完成 EAP-TLS 会话票证调配/更新 (Successfully finished EAP-TLS session ticket provisioning/update)

消息说明: 已成功完成 EAP-TLS 会话票证调配/更新,

本地目标消息格式: <timestamp> <seq_num> 12540 INFO EAP: Successfully finished EAP-TLS session ticket provisioning/update, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12540 INFO EAP: Successfully finished EAP-TLS session ticket provisioning/update, <log details>

- 消息代码: 12541

严重性: 信息 (INFO)

消息文本: EAP-TLS 需要主动更新即将到期的会话票证 (EAP-TLS needs to proactively update session ticket that is about to expire)

消息说明: EAP-TLS 需要主动更新即将到期的会话票证。

本地目标消息格式: <timestamp> <seq_num> 12541 INFO EAP: EAP-TLS needs to proactively update session ticket that is about to expire, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12541 INFO EAP: EAP-TLS needs to proactively update session ticket that is about to expire, <log details>

- 消息代码: 12542

严重性: 警告 (WARN)

消息文本: 在无状态会话恢复处于禁用状态时, 从请求方收到 EAP-TLS 会话票证。正执行完全身份验证 (The EAP-TLS session ticket received from supplicant. Inner EAP-TLS does not support stateless session resume. Performing full authentication)

消息说明: 在无状态会话恢复处于禁用状态时, 从请求方收到 EAP-TLS 会话票证。正执行完全身份验证。

本地目标消息格式: <timestamp> <seq_num> 12542 WARN EAP: The EAP-TLS session ticket received from supplicant while the stateless session resume is disabled. Performing full authentication, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12542 WARN EAP: The EAP-TLS session ticket received from supplicant while the stateless session resume is disabled. Performing full authentication, <log details>

- 消息代码: 12543
严重性: 警告 (WARN)
消息文本: 无法生成新的会话票证 (Cannot generate a new session ticket)
消息说明: 尝试发布新会话票证时遇到内部错误。
本地目标消息格式: <timestamp> <seq_num> 12543 WARN EAP: Cannot generate a new session ticket, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12543 WARN EAP: Cannot generate a new session ticket, <log details>
- 消息代码: 12544
严重性: 警告 (WARN)
消息文本: EAP-TLS 会话票证包含无效授权 ID (The EAP-TLS session ticket contains invalid Authority ID)
消息说明: 从客户端收到的会话票证授权 ID 与处理身份验证请求的 ISE 部署的授权 ID 不匹配, 这可能是因为客户端的会话票证是由另一个 ISE 部署创建。
本地目标消息格式: <timestamp> <seq_num> 12544 WARN EAP: The EAP-TLS session ticket contains invalid Authority ID, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12544 WARN EAP: The EAP-TLS session ticket contains invalid Authority ID, <log details>
- 消息代码: 12545
严重性: 信息 (INFO)
消息文本: 客户端请求 EAP-TLS 会话票证 (Client requested EAP-TLS session ticket)
消息说明: 客户端发送了空的 EAP-TLS 会话票证客户端问候消息扩展, 正等待 ISE 的响应中发送新 EAP-TLS 会话票证。
本地目标消息格式: <timestamp> <seq_num> 12545 INFO EAP: Client requested EAP-TLS session ticket, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12545 INFO EAP: Client requested EAP-TLS session ticket, <log details>
- 消息代码: 12546
严重性: 警告 (WARN)
消息文本: 从请求方收到 EAP-TLS 会话票证。Inner EAP-TLS does not support stateless session resume. 正执行完全身份验证 (The EAP-TLS session ticket received from supplicant. Inner EAP-TLS does not support stateless session resume. Performing full authentication)

消息说明：从请求方收到的 EAP-TLS 会话票证。内部 EAP-TLS 不支持无状态会话恢复。正执行完全身份验证。

本地目标消息格式：<timestamp> <seq_num> 12546 WARN EAP: The EAP-TLS session ticket received from supplicant. Inner EAP-TLS does not support stateless session resume. Performing full authentication, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12546 WARN EAP: The EAP-TLS session ticket received from supplicant. Inner EAP-TLS does not support stateless session resume. Performing full authentication, <log details>

- 消息代码：12550

严重性：信息 (INFO)

消息文本：向 CA 的主 OCSP 服务器发送了 OCSP 请求 (Sent an OCSP request to the primary OCSP server for the CA)

消息说明：向 CA 的主 OCSP 服务器发送 OCSP 请求。

本地目标消息格式：<timestamp> <seq_num> 12550 INFO EAP: Sent an OCSP request to the primary OCSP server for the CA, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12550 INFO EAP: Sent an OCSP request to the primary OCSP server for the CA, <log details>

- 消息代码：12551

严重性：信息 (INFO)

消息文本：向 CA 的辅助 OCSP 服务器发送了 OCSP 请求 (Sent an OCSP request to the secondary OCSP server for the CA)

消息说明：向 CA 的辅助 OCSP 服务器发送 OCSP 请求。

本地目标消息格式：<timestamp> <seq_num> 12551 INFO EAP: Sent an OCSP request to the secondary OCSP server for the CA, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12551 INFO EAP: Sent an OCSP request to the secondary OCSP server for the CA, <log details>

- 消息代码：12552

严重性：警告 (WARN)

消息文本：与 OCSP 服务器的对话以失败告终 (Conversation with OCSP server ended with failure)

消息说明：与 OCSP 服务器的对话以失败告终。

本地目标消息格式：<timestamp> <seq_num> 12552 WARN EAP: Conversation with OCSP server ended with failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12552 WARN EAP: Conversation with
OCSP server ended with failure, <log details>

- 消息代码: 12553

严重性: 信息 (INFO)

消息文本: 已收到 OCSP 响应 (Received OCSP response)

消息说明: 已收到 OCSP 响应。

本地目标消息格式: <timestamp> <seq_num> 12553 INFO EAP: Received OCSP response, <log
details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12553 INFO EAP: Received OCSP response,
<log details>

- 消息代码: 12554

严重性: 信息 (INFO)

消息文本: 用户证书的 OCSP 状态为良好 (OCSP status of user certificate is good)

消息说明: OCSP 服务器报告称用户证书的状态为良好。

本地目标消息格式: <timestamp> <seq_num> 12554 INFO EAP: OCSP status of user certificate is
good, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12554 INFO EAP: OCSP status of user
certificate is good, <log details>

- 消息代码: 12555

严重性: 警告 (WARN)

消息文本: 用户证书的 OCSP 状态为已撤销 (OCSP status of user certificate is revoked)

消息说明: OCSP 服务器报告称用户证书的状态为已撤销。

本地目标消息格式: <timestamp> <seq_num> 12555 WARN EAP: OCSP status of user certificate is
revoked, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12555 WARN EAP: OCSP status of user
certificate is revoked, <log details>

- 消息代码: 12556

严重性: 信息 (INFO)

消息文本: 用户证书的 OCSP 状态为未知 (OCSP status of user certificate is unknown)

消息说明: OCSP 服务器报告用户证书的状态为未知, 或者 ISE 无法连接到 OCSP 服务器。

本地目标消息格式: <timestamp> <seq_num> 12556 INFO EAP: OCSP status of user certificate is unknown, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12556 INFO EAP: OCSP status of user certificate is unknown, <log details>

- 消息代码: 12557

严重性: 警告 (WARN)

消息文本: 由于 OCSP 状态为未知, 因此用户身份验证失败 (User Auth failed because OCSP status is unknown)

消息说明: 由于 OCSP 状态为未知, 因此用户身份验证失败。

本地目标消息格式: <timestamp> <seq_num> 12557 WARN EAP: User Auth failed because OCSP status is unknown, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12557 WARN EAP: User Auth failed because OCSP status is unknown, <log details>

- 消息代码: 12558

严重性: 信息 (INFO)

消息文本: 已执行回退到辅助 OCSP 服务器 (Performed fallback to secondary OCSP server)

消息说明: 已执行回退到辅助 OCSP 服务器。

本地目标消息格式: <timestamp> <seq_num> 12558 INFO EAP: Performed fallback to secondary OCSP server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12558 INFO EAP: Performed fallback to secondary OCSP server, <log details>

- 消息代码: 12559

严重性: 警告 (WARN)

消息文本: 在与 OCSP 服务器通信的过程中出现内部错误 (Internal error occurred during communication with the OCSP server)

消息说明: 在与 OCSP 服务器通信的过程中出现内部错误。OCSP 服务器的配置与 ISE OCSP 客户端不匹配。

本地目标消息格式: <timestamp> <seq_num> 12559 WARN EAP: Internal error occurred during communication with the OCSP server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12559 WARN EAP: Internal error occurred during communication with the OCSP server, <log details>

- 消息代码: 12560

严重性: 警告 (WARN)

消息文本: OCSP 服务器 URL 无效 (OCSP server URL is invalid)

消息说明: OCSP 服务器 URL 无效, 无法正确解析。

本地目标消息格式: <timestamp> <seq_num> 12560 WARN EAP: OCSP server URL is invalid, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12560 WARN EAP: OCSP server URL is invalid, <log details>

• 消息代码: 12561

严重性: 警告 (WARN)

消息文本: 连接 OCSP 服务器失败 (Connection to OCSP server failed)

消息说明: 尝试连接 OCSP 服务器失败。

本地目标消息格式: <timestamp> <seq_num> 12561 WARN EAP: Connection to OCSP server failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12561 WARN EAP: Connection to OCSP server failed, <log details>

• 消息代码: 12562

严重性: 警告 (WARN)

消息文本: OCSP 服务器响应无效 (OCSP server response is invalid)

消息说明: OCSP 服务器返回了一个 ISE 无法解析的响应。

本地目标消息格式: <timestamp> <seq_num> 12562 WARN EAP: OCSP server response is invalid, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12562 WARN EAP: OCSP server response is invalid, <log details>

• 消息代码: 12563

严重性: 警告 (WARN)

消息文本: OCSP 服务器返回错误 (OCSP server returned an error)

消息说明: OCSP 服务器在响应 ISE OCSP 请求时返回了错误。

本地目标消息格式: <timestamp> <seq_num> 12563 WARN EAP: OCSP server returned an error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12563 WARN EAP: OCSP server returned an error, <log details>

- 消息代码: 12564
严重性: 警告 (WARN)
消息文本: OCSP 服务器未在响应中提供所需的随机数 (OCSP server did not provide the required nonce in response)
消息说明: ISE 中的特定 OCSP 服务配置为使用随机数进行 OCSP 服务器验证, 但 OCSP 服务器未在响应中提供随机数。
本地目标消息格式: <timestamp> <seq_num> 12564 WARN EAP: OCSP server did not provide the required nonce in response, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12564 WARN EAP: OCSP server did not provide the required nonce in response, <log details>
- 消息代码: 12565
严重性: 警告 (WARN)
消息文本: OCSP 服务器响应随机数验证失败 (OCSP server response nonce verification failed)
消息说明: OCSP 服务器响应中返回的随机数加密验证失败。
本地目标消息格式: <timestamp> <seq_num> 12565 WARN EAP: OCSP server response nonce verification failed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12565 WARN EAP: OCSP server response nonce verification failed, <log details>
- 消息代码: 12566
严重性: 警告 (WARN)
消息文本: OCSP 服务器响应时间验证失败 (OCSP server response time verification failed)
消息说明: 在 OCSP 服务器中, “本次更新” (This Update) 或 “下次更新” (Next Update) 字段的响应验证失败。
本地目标消息格式: <timestamp> <seq_num> 12566 WARN EAP: OCSP server response time verification failed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12566 WARN EAP: OCSP server response time verification failed, <log details>
- 消息代码: 12567
严重性: 警告 (WARN)
消息文本: OCSP 服务器响应签名验证失败 (OCSP server response signature verification failed)
消息说明: OCSP 服务器响应签名验证失败。

本地目标消息格式: <timestamp> <seq_num> 12567 WARN EAP: OCSP server response signature verification failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12567 WARN EAP: OCSP server response signature verification failed, <log details>

- 消息代码: 12568

严重性: 信息 (INFO)

消息文本: 查找 OCSP 缓存中的用户证书状态 (Lookup user certificate status in OCSP cache)

消息说明: 查找 OCSP 缓存中的用户证书状态。

本地目标消息格式: <timestamp> <seq_num> 12568 INFO EAP: Lookup user certificate status in OCSP cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12568 INFO EAP: Lookup user certificate status in OCSP cache, <log details>

- 消息代码: 12569

严重性: 信息 (INFO)

消息文本: 未在 OCSP 缓存中找到用户证书状态 (User certificate status was not found in OCSP cache)

消息说明: 未在 OCSP 缓存中找到用户证书状态; ISE 将对配置好的 OCSP 服务器执行 OCSP 请求。

本地目标消息格式: <timestamp> <seq_num> 12569 INFO EAP: User certificate status was not found in OCSP cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12569 INFO EAP: User certificate status was not found in OCSP cache, <log details>

- 消息代码: 12570

严重性: 信息 (INFO)

消息文本: 查找 OCSP 缓存中的用户证书状态成功 (Lookup user certificate status in OCSP cache succeeded)

消息说明: 在 OCSP 缓存中查找用户证书状态成功; ISE 将使用此状态, 但不执行对配置好的 OCSP 服务器的 OCSP 请求。

本地目标消息格式: <timestamp> <seq_num> 12570 INFO EAP: Lookup user certificate status in OCSP cache succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12570 INFO EAP: Lookup user certificate status in OCSP cache succeeded, <log details>

- 消息代码: 12571
 - 严重性: 信息 (INFO)
 - 消息文本: 如果 ISE 针对特定的 CA 进行配置, 将继续进行 CRL 验证 (ISE will continue to CRL verification if it is configured for specific CA)
 - 消息说明: OCSP 验证失败或者返回了未知的证书状态。如果 ISE 针对特定的 CA 进行配置, 将继续进行 CRL 验证。
 - 本地目标消息格式: <timestamp> <seq_num> 12571 INFO EAP: ISE will continue to CRL verification if it is configured for specific CA, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12571 INFO EAP: ISE will continue to CRL verification if it is configured for specific CA, <log details>

- 消息代码: 12572
 - 严重性: 调试 (DEBUG)
 - 消息文本: 未缓存 OCSP 响应 (OCSP response not cached)
 - 消息说明: OCSP 服务器的响应表明不应缓存响应的内容
 - 本地目标消息格式: <timestamp> <seq_num> 12572 DEBUG EAP: OCSP response not cached, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12572 DEBUG EAP: OCSP response not cached, <log details>

- 消息代码: 12600
 - 严重性: 信息 (INFO)
 - 消息文本: 已准备提议使用 EAP-GTC 和质询的 EAP 请求 (Prepared EAP-Request proposing EAP-GTC with challenge)
 - 消息说明: 已创建一个 EAP 请求数据包, 提议使用 EAP-GTC 协议, 同时提供 GTC 质询, 用于附加到 RADIUS 消息。建议使用 EAP-GTC 协议的原因在于此协议是“允许的协议”中允许使用的其中一个基于 EAP 的协议。
 - 本地目标消息格式: <timestamp> <seq_num> 12600 INFO EAP: Prepared EAP-Request proposing EAP-GTC with challenge, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12600 INFO EAP: Prepared EAP-Request proposing EAP-GTC with challenge, <log details>

- 消息代码: 12601
 - 严重性: 信息 (INFO)
 - 消息文本: 提取的 EAP 响应/NAK 请求改为使用 EAP-GTC (Extracted EAP-Response/NAK requesting to use EAP-GTC instead)

消息说明：从 RADIUS 消息中提取的 EAP 响应/NAK 数据包拒绝之前提议的基于 EAP 的协议，且根据客户端请求方的配置，请求改为使用 EAP-GTC。

本地目标消息格式：<timestamp> <seq_num> 12601 INFO EAP: Extracted EAP-Response/NAK requesting to use EAP-GTC instead, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12601 INFO EAP: Extracted EAP-Response/NAK requesting to use EAP-GTC instead, <log details>

- 消息代码：12602

严重性：信息 (INFO)

消息文本：提取的 EAP 响应包含 EAP-GTC 质询-响应，且接受将 EAP-GTC 用作协商协议 (Extracted EAP-Response containing EAP-GTC challenge-response and accepting EAP-GTC as negotiated)

消息说明：从 RADIUS 消息中提取的 EAP 响应数据包含有 EAP-GTC 质询-响应，且接受将 EAP-GTC 用作协商协议。

本地目标消息格式：<timestamp> <seq_num> 12602 INFO EAP: Extracted EAP-Response containing EAP-GTC challenge-response and accepting EAP-GTC as negotiated, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12602 INFO EAP: Extracted EAP-Response containing EAP-GTC challenge-response and accepting EAP-GTC as negotiated, <log details>

- 消息代码：12603

严重性：警告 (WARN)

消息文本：由于 EAP-GTC 未在“允许的协议”中获得允许，因此 EAP 协商失败 (Failed to negotiate EAP because EAP-GTC not allowed in the Allowed Protocols)

消息说明：客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前提议的基于 EAP 的协议，且请求改为使用 EAP-GTC。但是，EAP-GTC 未在“允许的协议”中获得允许。

本地目标消息格式：<timestamp> <seq_num> 12603 WARN EAP: Failed to negotiate EAP because EAP-GTC not allowed in the Allowed Protocols, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12603 WARN EAP: Failed to negotiate EAP because EAP-GTC not allowed in the Allowed Protocols, <log details>

- 消息代码：12604

严重性：信息 (INFO)

消息文本：提取的 EAP 响应包含 GTC 质询-响应 (Extracted EAP-Response containing GTC challenge-response)

消息说明：继续使用 EAP-GTC 协议；处理已提取的 EAP 响应中的 EAP-GTC 质询-响应。

本地目标消息格式：<timestamp> <seq_num> 12604 INFO EAP: Extracted EAP-Response containing GTC challenge-response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12604 INFO EAP: Extracted EAP-Response
containing GTC challenge-response, <log details>

- 消息代码: 12605

严重性: 信息 (INFO)

消息文本: 已准备包含其他 EAP-GTC 质询的 EAP 请求 (Prepared EAP-Request with another
EAP-GTC challenge)

消息说明: 为了继续使用 EAP-GTC 协议, 已创建包含其他 EAP-GTC 质询的 EAP 请求数据包,
用于附加到 RADIUS 消息。

本地目标消息格式: <timestamp> <seq_num> 12605 INFO EAP: Prepared EAP-Request with another
EAP-GTC challenge, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12605 INFO EAP: Prepared EAP-Request
with another EAP-GTC challenge, <log details>

- 消息代码: 12606

严重性: 信息 (INFO)

消息文本: 已为内部方法准备提议使用 EAP-GTC 和质询的 EAP 请求 (Prepared EAP-Request for
inner method proposing EAP-GTC with challenge)

消息说明: 已创建一个 EAP 请求数据包, 提议对内部方法使用 EAP-GTC 协议, 同时提供 GTC
质询, 用于附加到 RADIUS 消息。建议使用 EAP-GTC 协议的原因在于此协议是“允许的协议”
中允许使用的其中一个基于 EAP 的协议。

本地目标消息格式: <timestamp> <seq_num> 12606 INFO EAP: Prepared EAP-Request for inner
method proposing EAP-GTC with challenge, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12606 INFO EAP: Prepared EAP-Request
for inner method proposing EAP-GTC with challenge, <log details>

- 消息代码: 12607

严重性: 信息 (INFO)

消息文本: 提取的内部方法 EAP 响应/NAK 请求改为使用 EAP-GTC (Extracted EAP-Response/NAK
for inner method requesting to use EAP-GTC instead)

消息说明: 从在外部 EAP 方法中遇到的 EAP 响应数据包中, 提取的 EAP 响应/NAK 数据包拒
绝之前为内部方法提议的基于 EAP 的协议, 并根据客户端请求方的配置请求改为使用 EAP-GTC。

本地目标消息格式: <timestamp> <seq_num> 12607 INFO EAP: Extracted EAP-Response/NAK for
inner method requesting to use EAP-GTC instead, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12607 INFO EAP: Extracted
EAP-Response/NAK for inner method requesting to use EAP-GTC instead, <log details>

- 消息代码: 12608

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应包含内部方法 EAP-GTC 质询-响应, 且接受将 EAP-GTC 用作协商协议 (Extracted EAP-Response containing EAP-GTC challenge-response for inner method and accepting EAP-GTC as negotiated)

消息说明: 从在外部 EAP 方法中遇到的 EAP 响应数据包中, 提取的 EAP 响应数据包含有 EAP-GTC 质询-响应, 且接受将 EAP-GTC 用作内部方法的协商协议。

本地目标消息格式: <timestamp> <seq_num> 12608 INFO EAP: Extracted EAP-Response containing EAP-GTC challenge-response for inner method and accepting EAP-GTC as negotiated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12608 INFO EAP: Extracted EAP-Response containing EAP-GTC challenge-response for inner method and accepting EAP-GTC as negotiated, <log details>

- 消息代码: 12609

严重性: 警告 (WARN)

消息文本: 由于 EAP-GTC 未在“允许的协议”中获得允许, 因此 EAP 协商失败 (Failed to negotiate EAP for inner method because EAP-GTC not allowed in the Allowed Protocols)

消息说明: 客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前为内部方法提议的基于 EAP 的协议, 且请求改为使用 EAP-GTC。但是, EAP-GTC 未在“允许的协议”中获得允许。

本地目标消息格式: <timestamp> <seq_num> 12609 WARN EAP: Failed to negotiate EAP for inner method because EAP-GTC not allowed in the Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12609 WARN EAP: Failed to negotiate EAP for inner method because EAP-GTC not allowed in the Allowed Protocols, <log details>

- 消息代码: 12610

严重性: 信息 (INFO)

消息文本: 提取的内部方法 EAP 响应包含 GTC 质询-响应 (Extracted EAP-Response for inner method containing GTC challenge-response)

消息说明: 继续使用内部 EAP-GTC 协议; 处理已提取的 EAP 响应中的 EAP-GTC 质询-响应。

本地目标消息格式: <timestamp> <seq_num> 12610 INFO EAP: Extracted EAP-Response for inner method containing GTC challenge-response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12610 INFO EAP: Extracted EAP-Response for inner method containing GTC challenge-response, <log details>

- 消息代码: 12611

严重性: 信息 (INFO)

消息文本: 已准备包含其他 EAP-GTC 质询的内部方法 EAP 请求 (Prepared EAP-Request for inner method with another EAP-GTC challenge)

消息说明: 为了继续使用内部 EAP-GTC 协议, 已创建包含其他 EAP-GTC 质询的 EAP 请求数据包, 用于封装到外部 EAP 方法的传出 EAP 请求数据包中, 并最终附加到 RADIUS 消息中。

本地目标消息格式: <timestamp> <seq_num> 12611 INFO EAP: Prepared EAP-Request for inner method with another EAP-GTC challenge, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12611 INFO EAP: Prepared EAP-Request for inner method with another EAP-GTC challenge, <log details>

- 消息代码: 12612

严重性: 信息 (INFO)

消息文本: EAP-GTC 身份验证成功 (EAP-GTC authentication succeeded)

消息说明: EAP-GTC 身份验证成功。

本地目标消息格式: <timestamp> <seq_num> 12612 INFO EAP: EAP-GTC authentication succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12612 INFO EAP: EAP-GTC authentication succeeded, <log details>

- 消息代码: 12613

严重性: 信息 (INFO)

消息文本: EAP-GTC 身份验证失败 (EAP-GTC authentication failed)

消息说明: EAP-GTC 身份验证失败。

本地目标消息格式: <timestamp> <seq_num> 12613 INFO EAP: EAP-GTC authentication failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12613 INFO EAP: EAP-GTC authentication failed, <log details>

- 消息代码: 12614

严重性: 信息 (INFO)

消息文本: 内部 EAP-GTC 身份验证成功 (Inner EAP-GTC authentication succeeded)

消息说明: 内部 EAP 方法的 EAP-GTC 身份验证成功。

本地目标消息格式: <timestamp> <seq_num> 12614 INFO EAP: Inner EAP-GTC authentication succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12614 INFO EAP: Inner EAP-GTC authentication succeeded, <log details>

- 消息代码: 12615
严重性: 信息 (INFO)
消息文本: 内部 EAP-GTC 身份验证失败 (Inner EAP-GTC authentication failed)
消息说明: 内部 EAP 方法的 EAP-GTC 身份验证失败。
本地目标消息格式: <timestamp> <seq_num> 12615 INFO EAP: Inner EAP-GTC authentication failed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12615 INFO EAP: Inner EAP-GTC authentication failed, <log details>
- 消息代码: 12616
严重性: 警告 (WARN)
消息文本: GTC 用户名与内部方法 EAP 响应/身份不匹配 (GTC username doesn't match inner method EAP-Response/Identity)
消息说明: GTC 用户名与内部方法 EAP 响应/身份数据包中收到的用户名不匹配。可能是因为客户端的请求方预配置的另一个用户名与用户输入的用户名不匹配。
本地目标消息格式: <timestamp> <seq_num> 12616 WARN EAP: GTC username doesn't match inner method EAP-Response/Identity, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12616 WARN EAP: GTC username doesn't match inner method EAP-Response/Identity, <log details>
- 消息代码: 12617
严重性: 警告 (WARN)
消息文本: 内部错误: EAP-GTC 状态无效 (Internal error: invalid EAP-GTC state)
消息说明: 内部错误: EAP-GTC 状态无效。
本地目标消息格式: <timestamp> <seq_num> 12617 WARN EAP: Internal error: invalid EAP-GTC state, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12617 WARN EAP: Internal error: invalid EAP-GTC state, <log details>
- 消息代码: 12618
严重性: 信息 (INFO)
消息文本: 未能解析 EAP-GTC 数据包 (Failed to parse EAP-GTC packet)
消息说明: 未能解析 EAP-GTC 数据包。
本地目标消息格式: <timestamp> <seq_num> 12618 INFO EAP: Failed to parse EAP-GTC packet, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12618 INFO EAP: Failed to parse EAP-GTC
packet, <log details>

- 消息代码: 12619

严重性: 信息 (INFO)

消息文本: 接收到包含无效参数的 EAP-GTC 数据包 (Received EAP-GTC packet with invalid
argument)

消息说明: 接收到包含无效参数的 EAP-GTC 数据包。

本地目标消息格式: <timestamp> <seq_num> 12619 INFO EAP: Received EAP-GTC packet with
invalid argument, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12619 INFO EAP: Received EAP-GTC
packet with invalid argument, <log details>

- 消息代码: 12621

严重性: 信息 (INFO)

消息文本: EAP-GTC 密码更改尝试失败 (EAP-GTC password change attempt failed)

消息说明: 尝试更改密码失败, 因为“允许的协议”不允许更改 GTC 内部方法的密码。

本地目标消息格式: <timestamp> <seq_num> 12621 INFO EAP: EAP-GTC password change attempt
failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12621 INFO EAP: EAP-GTC password
change attempt failed, <log details>

- 消息代码: 12622

严重性: 调试 (DEBUG)

消息文本: EAP-GTC 密码更改尝试通过 (EAP-GTC password change attempt passed)

消息说明: 更改 EAP-GTC 密码的尝试已通过。

本地目标消息格式: <timestamp> <seq_num> 12622 DEBUG EAP: EAP-GTC password change
attempt passed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12622 DEBUG EAP: EAP-GTC password
change attempt passed, <log details>

- 消息代码: 12623

严重性: 信息 (INFO)

消息文本: EAP-GTC 身份验证尝试失败 (EAP-GTC authentication attempt failed)

消息说明: EAP-GTC 身份验证尝试已失败。

本地目标消息格式: <timestamp> <seq_num> 12623 INFO EAP: EAP-GTC authentication attempt failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 12623 INFO EAP: EAP-GTC authentication attempt failed, <log details>

- 消息代码: 12624

严重性: 调试 (DEBUG)

消息文本: EAP-GTC 身份验证尝试通过 (EAP-GTC authentication attempt passed)

消息说明: EAP-GTC 身份验证尝试已通过。

本地目标消息格式: <timestamp> <seq_num> 12624 DEBUG EAP: EAP-GTC authentication attempt passed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 12624 DEBUG EAP: EAP-GTC authentication attempt passed, <log details>

- 消息代码: 12625

严重性: 调试 (DEBUG)

消息文本: 收到有效的 EAP-Key-Name 属性 (Valid EAP-Key-Name attribute received)

消息说明: 收到了有效的 EAP-Key-Name 属性。ISE 将提供 EAP-Key-Name 属性, 其中 RADIUS Access-Accept 消息中填充有 EAP-Session-ID。

本地目标消息格式: <timestamp> <seq_num> 12625 DEBUG EAP: Valid EAP-Key-Name attribute received, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 12625 DEBUG EAP: Valid EAP-Key-Name attribute received, <log details>

- 消息代码: 12626

严重性: 警告 (WARN)

消息文本: 收到无效的 EAP-Key-Name 属性 (Invalid EAP-Key-Name attribute received)

消息说明: 收到了无效的 EAP-Key-Name 属性。此属性值必须为空。

本地目标消息格式: <timestamp> <seq_num> 12626 WARN EAP: Invalid EAP-Key-Name attribute received, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 12626 WARN EAP: Invalid EAP-Key-Name attribute received, <log details>

- 消息代码: 12628

严重性: 警告 (WARN)

消息文本: 执行的操作无效 (Invalid operation performed)

消息说明: 内部错误, 执行的操作无效, 无法继续当前对话。请参阅调试日志了解详细信息, 并联系 TAC 工程师报告问题

本地目标消息格式: <timestamp> <seq_num> 12628 WARN EAP: Invalid operation performed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12628 WARN EAP: Invalid operation performed, <log details>

- 消息代码: 12650

严重性: 警告 (WARN)

消息文本: 执行的操作无效 (Invalid operation performed)

消息说明: 内部错误, 执行的操作无效。请参阅调试日志了解详细信息, 并联系 TAC 工程师报告问题

本地目标消息格式: <timestamp> <seq_num> 12650 WARN EAP: Invalid operation performed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12650 WARN EAP: Invalid operation performed, <log details>

- 消息代码: 12651

严重性: 信息 (INFO)

消息文本: 在经过验证的调配时接受客户端 (Accept client on authenticated provisioning)

消息说明: 在经过验证的调配时接受客户端

本地目标消息格式: <timestamp> <seq_num> 12651 INFO EAP: Accept client on authenticated provisioning, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12651 INFO EAP: Accept client on authenticated provisioning, <log details>

- 消息代码: 12652

严重性: 信息 (INFO)

消息文本: 在无效 PAC 回退后调配时接受客户端 (Accept client on provisioning after invalid PAC fallback)

消息说明: 在无效 PAC 回退后调配时接受客户端

本地目标消息格式: <timestamp> <seq_num> 12652 INFO EAP: Accept client on provisioning after invalid PAC fallback, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12652 INFO EAP: Accept client on
provisioning after invalid PAC fallback, <log details>

- 消息代码: 12653

严重性: 警告 (WARN)

消息文本: 由于 EAP-GTC 拒绝匿名 PAC 调配, 因此无法为内部方法协商 EAP (Failed to negotiate
EAP for inner method because EAP-GTC denied for anonymous PAC provisioning)

消息说明: 客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前为内部方法提议的基于 EAP 的
协议, 且请求改为使用 EAP-GTC。但是, EAP-GTC 不能用于匿名 PAC 调配。

本地目标消息格式: <timestamp> <seq_num> 12653 WARN EAP: Failed to negotiate EAP for inner
method because EAP-GTC denied for anonymous PAC provisioning, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12653 WARN EAP: Failed to negotiate EAP
for inner method because EAP-GTC denied for anonymous PAC provisioning, <log details>

- 消息代码: 12700

严重性: 信息 (INFO)

消息文本: 已准备提议使用 LEAP 和质询的 EAP 请求 (Prepared EAP-Request proposing LEAP
with challenge)

消息说明: 已创建一个 EAP 请求数据包, 提议使用 LEAP 协议, 同时提供 LEAP 质询, 用于附
加到 RADIUS 消息。建议使用 LEAP 协议的原因在于此协议是“允许的协议”中允许使用的其
中一个基于 EAP 的协议。

本地目标消息格式: <timestamp> <seq_num> 12700 INFO EAP: Prepared EAP-Request proposing
LEAP with challenge, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12700 INFO EAP: Prepared EAP-Request
proposing LEAP with challenge, <log details>

- 消息代码: 12701

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应/NAK 请求改为使用 LEAP (Extracted EAP-Response/NAK requesting
to use LEAP instead)

消息说明: 从 RADIUS 消息中提取的 EAP 响应/NAK 数据包拒绝之前提议的基于 EAP 的协议,
且根据客户端请求方的配置, 请求改为使用 LEAP。

本地目标消息格式: <timestamp> <seq_num> 12701 INFO EAP: Extracted EAP-Response/NAK
requesting to use LEAP instead, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12701 INFO EAP: Extracted
EAP-Response/NAK requesting to use LEAP instead, <log details>

• 消息代码: 12702

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应包含 LEAP 质询-响应, 且接受将 LEAP 用作协商协议 (Extracted EAP-Response containing LEAP challenge-response and accepting LEAP as negotiated)

消息说明: 从 RADIUS 消息中提取的 EAP 响应数据包含有 LEAP 质询-响应, 且接受将 LEAP 用作协商协议。

本地目标消息格式: <timestamp> <seq_num> 12702 INFO EAP: Extracted EAP-Response containing LEAP challenge-response and accepting LEAP as negotiated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 12702 INFO EAP: Extracted EAP-Response containing LEAP challenge-response and accepting LEAP as negotiated, <log details>

• 消息代码: 12703

严重性: 警告 (WARN)

消息文本: 由于 LEAP 未在“允许的协议”中获得允许, 因此 EAP 协商失败 (Failed to negotiate EAP because LEAP not allowed in the Allowed Protocols)

消息说明: 客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前提议的基于 EAP 的协议, 且请求改为使用 LEAP。但是, LEAP 未在“允许的协议”中获得允许。

本地目标消息格式: <timestamp> <seq_num> 12703 WARN EAP: Failed to negotiate EAP because LEAP not allowed in the Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 12703 WARN EAP: Failed to negotiate EAP because LEAP not allowed in the Allowed Protocols, <log details>

• 消息代码: 12704

严重性: 信息 (INFO)

消息文本: LEAP 已完成。(LEAP completed.) 已发送包含 LEAP 质询-响应的 EAP 响应及包含 LEAP 会话-密钥的 cisco-av-pair

消息说明: 已完成 LEAP 协议。已发送 EAP 响应中的 LEAP 质询-响应及 cisco-av-pair 中的 LEAP 会话-密钥。

本地目标消息格式: <timestamp> <seq_num> 12704 INFO EAP: LEAP completed. Sent EAP-Response containing LEAP challenge-response and cisco-av-pair containing LEAP session-key, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 12704 INFO EAP: LEAP completed. Sent EAP-Response containing LEAP challenge-response and cisco-av-pair containing LEAP session-key, <log details>

• 消息代码: 12705

严重性: 信息 (INFO)

消息文本: LEAP 身份验证已通过; 继续使用协议 (LEAP authentication passed; Continuing protocol)

消息说明: LEAP 身份验证已通过。继续使用 LEAP 协议。

本地目标消息格式: <timestamp> <seq_num> 12705 INFO EAP: LEAP authentication passed; Continuing protocol, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12705 INFO EAP: LEAP authentication passed; Continuing protocol, <log details>

- 消息代码: 12706

严重性: 信息 (INFO)

消息文本: LEAP 身份验证失败; 结束使用协议 (LEAP authentication failed; Finishing protocol)

消息说明: LEAP 身份验证失败。发生故障, 结束使用协议。

本地目标消息格式: <timestamp> <seq_num> 12706 INFO EAP: LEAP authentication failed; Finishing protocol, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12706 INFO EAP: LEAP authentication failed; Finishing protocol, <log details>

- 消息代码: 12707

严重性: 信息 (INFO)

消息文本: LEAP 身份验证错误; 结束使用协议 (LEAP authentication error; Finishing protocol)

消息说明: 发生 LEAP 身份验证错误。出现错误, 结束使用协议。

本地目标消息格式: <timestamp> <seq_num> 12707 INFO EAP: LEAP authentication error; Finishing protocol, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12707 INFO EAP: LEAP authentication error; Finishing protocol, <log details>

- 消息代码: 12708

严重性: 警告 (WARN)

消息文本: LEAP 数据包验证失败 (LEAP packet validation failed)

消息说明: 未能验证 LEAP 数据包。

本地目标消息格式: <timestamp> <seq_num> 12708 WARN EAP: LEAP packet validation failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12708 WARN EAP: LEAP packet validation failed, <log details>

- 消息代码: 12709

严重性: 警告 (WARN)

消息文本: LEAP 数据包解析失败 (LEAP packet parsing failed)

消息说明: 未能解析 LEAP 数据包。

本地目标消息格式: <timestamp> <seq_num> 12709 WARN EAP: LEAP packet parsing failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12709 WARN EAP: LEAP packet parsing failed, <log details>

• 消息代码: 12710

严重性: 警告 (WARN)

消息文本: LEAP 内部错误: 状态无效 (LEAP internal error: Invalid state)

消息说明: LEAP 内部错误: 状态无效。

本地目标消息格式: <timestamp> <seq_num> 12710 WARN EAP: LEAP internal error: Invalid state, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12710 WARN EAP: LEAP internal error: Invalid state, <log details>

• 消息代码: 12711

严重性: 警告 (WARN)

消息文本: LEAP 内部错误: 未创建 LEAP 质询 (LEAP internal error: LEAP challenge not created)

消息说明: LEAP 内部错误: 未创建 LEAP 质询。

本地目标消息格式: <timestamp> <seq_num> 12711 WARN EAP: LEAP internal error: LEAP challenge not created, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12711 WARN EAP: LEAP internal error: LEAP challenge not created, <log details>

• 消息代码: 12712

严重性: 警告 (WARN)

消息文本: LEAP 内部错误: 未创建 LEAP 质询-响应和会话-密钥 (LEAP internal error: LEAP challenge-response and session-key not created)

消息说明: LEAP 内部错误: 未创建 LEAP 质询-响应和会话-密钥。

本地目标消息格式: <timestamp> <seq_num> 12712 WARN EAP: LEAP internal error: LEAP challenge-response and session-key not created, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12712 WARN EAP: LEAP internal error: LEAP challenge-response and session-key not created, <log details>

- 消息代码: 12750

严重性: 警告 (WARN)

消息文本: 由于 EAP-MSCHAP 未在“允许的协议”中的 PEAP 配置下获得允许, 因此无法为内部方法协商 EAP (Failed to negotiate EAP for inner method because EAP-MSCHAP not allowed under PEAP configuration in the Allowed Protocols)

消息说明: 客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前为内部方法提议的基于 EAP 的协议, 且请求改为使用 EAP-MSCHAP。但是, EAP-MSCHAP 未在“允许的协议”中的 PEAP 配置下获得允许。

本地目标消息格式: <timestamp> <seq_num> 12750 WARN EAP: Failed to negotiate EAP for inner method because EAP-MSCHAP not allowed under PEAP configuration in the Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12750 WARN EAP: Failed to negotiate EAP for inner method because EAP-MSCHAP not allowed under PEAP configuration in the Allowed Protocols, <log details>

- 消息代码: 12751

严重性: 警告 (WARN)

消息文本: 由于 EAP-MSCHAP 未在“允许的协议”中的 EAP-FAST 配置下获得允许, 因此无法为内部方法协商 EAP (Failed to negotiate EAP for inner method because EAP-MSCHAP not allowed under EAP-FAST configuration in the Allowed Protocols)

消息说明: 客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前为内部方法提议的基于 EAP 的协议, 且请求改为使用 EAP-MSCHAP。但是, EAP-MSCHAP 未在“允许的协议”中的 EAP-FAST 配置下获得允许。

本地目标消息格式: <timestamp> <seq_num> 12751 WARN EAP: Failed to negotiate EAP for inner method because EAP-MSCHAP not allowed under EAP-FAST configuration in the Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12751 WARN EAP: Failed to negotiate EAP for inner method because EAP-MSCHAP not allowed under EAP-FAST configuration in the Allowed Protocols, <log details>

- 消息代码: 12752

严重性: 警告 (WARN)

消息文本: 由于 EAP-TLS 未在“允许的协议”中的 PEAP 配置下获得允许, 因此无法为内部方法协商 EAP (Failed to negotiate EAP for inner method because EAP-TLS not allowed under PEAP configuration in the Allowed Protocols)

消息说明: 客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前为内部方法提议的基于 EAP 的协议, 且请求改为使用 EAP-TLS。但是, EAP-TLS 未在“允许的协议”中的 PEAP 配置下获得 ISE 允许。

本地目标消息格式: <timestamp> <seq_num> 12752 WARN EAP: Failed to negotiate EAP for inner method because EAP-TLS not allowed under PEAP configuration in the Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12752 WARN EAP: Failed to negotiate EAP for inner method because EAP-TLS not allowed under PEAP configuration in the Allowed Protocols, <log details>

- 消息代码: 12753

严重性: 警告 (WARN)

消息文本: 由于 EAP-TLS 未在“允许的协议”中的 EAP-FAST 配置下获得允许, 因此无法为内部方法协商 EAP (Failed to negotiate EAP for inner method because EAP-TLS not allowed under EAP-FAST configuration in the Allowed Protocols)

消息说明: 客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前为内部方法提议的基于 EAP 的协议, 且请求改为使用 EAP-TLS。但是, EAP-TLS 未在“允许的协议”中的 EAP-FAST 配置下获得 ISE 允许。

本地目标消息格式: <timestamp> <seq_num> 12753 WARN EAP: Failed to negotiate EAP for inner method because EAP-TLS not allowed under EAP-FAST configuration in the Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12753 WARN EAP: Failed to negotiate EAP for inner method because EAP-TLS not allowed under EAP-FAST configuration in the Allowed Protocols, <log details>

- 消息代码: 12754

严重性: 警告 (WARN)

消息文本: 由于 EAP-GTC 未在“允许的协议”中的 PEAP 配置下获得允许, 因此无法为内部方法协商 EAP (Failed to negotiate EAP for inner method because EAP-GTC not allowed under PEAP configuration in the Allowed Protocols)

消息说明: 客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前为内部方法提议的基于 EAP 的协议, 且请求改为使用 EAP-GTC。但是, EAP-GTC 未在“允许的协议”中的 PEAP 配置下获得允许。

本地目标消息格式: <timestamp> <seq_num> 12754 WARN EAP: Failed to negotiate EAP for inner method because EAP-GTC not allowed under PEAP configuration in the Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12754 WARN EAP: Failed to negotiate EAP for inner method because EAP-GTC not allowed under PEAP configuration in the Allowed Protocols, <log details>

- 消息代码: 12755

严重性: 警告 (WARN)

消息文本: 由于 EAP-GTC 未在“允许的协议”中的 EAP-FAST 配置下获得允许，因此无法为内部方法协商 EAP (Failed to negotiate EAP for inner method because EAP-GTC not allowed under EAP-FAST configuration in the Allowed Protocols)

消息说明: 客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前为内部方法提议的基于 EAP 的协议，且请求改为使用 EAP-GTC。但是，EAP-GTC 未在“允许的协议”中的 EAP-FAST 配置下获得 ISE 允许。

本地目标消息格式: <timestamp> <seq_num> 12755 WARN EAP: Failed to negotiate EAP for inner method because EAP-GTC not allowed under EAP-FAST configuration in the Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12755 WARN EAP: Failed to negotiate EAP for inner method because EAP-GTC not allowed under EAP-FAST configuration in the Allowed Protocols, <log details>

- 消息代码: 12800

严重性: 信息 (INFO)

消息文本: 已提取第一个 TLS 记录; TLS 握手开始 (Extracted first TLS record; TLS handshake started)

消息说明: 在当前的 EAP 对话中，第一次从 EAP 响应数据包中提取一条 TLS 记录，相应地可能包含“TLS ClientHello”消息。ISE 将此识别为客户端的请求方希望启动 TLS 握手的尝试。

本地目标消息格式: <timestamp> <seq_num> 12800 INFO EAP: Extracted first TLS record; TLS handshake started, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12800 INFO EAP: Extracted first TLS record; TLS handshake started, <log details>

- 消息代码: 12801

严重性: 信息 (INFO)

消息文本: 已准备“TLS ChangeCipherSpec”消息 (Prepared TLS ChangeCipherSpec message)

消息说明: 作为当前正在进行的 TLS 握手的一部分，已准备包含“TLS ChangeCipherSpec”消息的 TLS 记录，用于封装到传出 EAP 请求数据包中，并最终附加到 RADIUS 消息中。

本地目标消息格式: <timestamp> <seq_num> 12801 INFO EAP: Prepared TLS ChangeCipherSpec message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12801 INFO EAP: Prepared TLS ChangeCipherSpec message, <log details>

- 消息代码: 12802

严重性: 信息 (INFO)

消息文本: 已准备“TLS 完成”消息 (Prepared TLS Finished message)

消息说明：作为当前正在进行的 TLS 握手的一部分，已准备包含“TLS Finished”消息的 TLS 记录，用于封装到传出 EAP 请求数据包中，并最终附加到 RADIUS 消息中。ISE 表示已准备好完成 TLS 握手。

本地目标消息格式：<timestamp> <seq_num> 12802 INFO EAP: Prepared TLS Finished message, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12802 INFO EAP: Prepared TLS Finished message, <log details>

- 消息代码：12803

严重性：信息 (INFO)

消息文本：已提取“TLS ChangeCipherSpec”消息 (Extracted TLS ChangeCipherSpec message)

消息说明：作为当前正在进行的 TLS 握手的一部分，已从 EAP 响应数据包提取包含“TLS ChangeCipherSpec”消息的 TLS 记录。

本地目标消息格式：<timestamp> <seq_num> 12803 INFO EAP: Extracted TLS ChangeCipherSpec message, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12803 INFO EAP: Extracted TLS ChangeCipherSpec message, <log details>

- 消息代码：12804

严重性：信息 (INFO)

消息文本：已提取“TLS 完成”消息 (Extracted TLS Finished message)

消息说明：作为当前正在进行的 TLS 握手的一部分，已从 EAP 响应数据包提取包含“TLS Finished”消息的 TLS 记录。客户端的请求方表示已准备好完成 TLS 握手。

本地目标消息格式：<timestamp> <seq_num> 12804 INFO EAP: Extracted TLS Finished message, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12804 INFO EAP: Extracted TLS Finished message, <log details>

- 消息代码：12805

严重性：信息 (INFO)

消息文本：已提取“TLS ClientHello”消息 (Extracted TLS ClientHello message)

消息说明：作为当前正在进行的 TLS 握手的一部分，已从 EAP 响应数据包提取包含“TLS ClientHello”消息的 TLS 记录。

本地目标消息格式：<timestamp> <seq_num> 12805 INFO EAP: Extracted TLS ClientHello message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12805 INFO EAP: Extracted TLS ClientHello
message, <log details>

- 消息代码: 12806

严重性: 信息 (INFO)

消息文本: 已准备 “TLS ServerHello” 消息 (Prepared TLS ServerHello message)

消息说明: 作为当前正在进行的 TLS 握手的一部分, 已准备包含 “TLS ServerHello” 消息的
TLS 记录, 用于封装到传出 EAP 请求数据包中, 并最终附加到 RADIUS 消息中。

本地目标消息格式: <timestamp> <seq_num> 12806 INFO EAP: Prepared TLS ServerHello message,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12806 INFO EAP: Prepared TLS ServerHello
message, <log details>

- 消息代码: 12807

严重性: 信息 (INFO)

消息文本: 已准备 “TLS 证书” 消息 (Prepared TLS Certificate message)

消息说明: 作为当前正在进行的 TLS 握手的一部分, 已准备包含 “TLS 证书” 消息的 TLS 记
录, 相应地包含 ISE 本地服务器证书, 用于封装到传出 EAP 请求数据包中, 并最终附加到
RADIUS 消息中。

本地目标消息格式: <timestamp> <seq_num> 12807 INFO EAP: Prepared TLS Certificate message,
<log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12807 INFO EAP: Prepared TLS Certificate
message, <log details>

- 消息代码: 12808

严重性: 信息 (INFO)

消息文本: 已准备 “TLS ServerKeyExchange” 消息 (Prepared TLS ServerKeyExchange message)

消息说明: 作为当前正在进行的 TLS 握手的一部分, 已准备包含 “TLS ServerKeyExchange” 消
息的 TLS 记录, 用于封装到传出 EAP 请求数据包中, 并最终附加到 RADIUS 消息中。

本地目标消息格式: <timestamp> <seq_num> 12808 INFO EAP: Prepared TLS ServerKeyExchange
message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12808 INFO EAP: Prepared TLS
ServerKeyExchange message, <log details>

- 消息代码: 12809

严重性: 信息 (INFO)

消息文本: 已准备 “TLS CertificateRequest” 消息 (Prepared TLS CertificateRequest message)

消息说明: 作为当前正在进行的 TLS 握手的一部分, 已准备包含 “TLS CertificateRequest” 消息的 TLS 记录, 用于封装到传出 EAP 请求数据包中, 并最终附加到 RADIUS 消息中。

本地目标消息格式: <timestamp> <seq_num> 12809 INFO EAP: Prepared TLS CertificateRequest message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12809 INFO EAP: Prepared TLS CertificateRequest message, <log details>

- 消息代码: 12810

严重性: 信息 (INFO)

消息文本: 已准备 “TLS ServerDone” 消息 (Prepared TLS ServerDone message)

消息说明: 作为当前正在进行的 TLS 握手的一部分, 已准备包含 “TLS ServerDone” 消息的 TLS 记录, 用于封装到传出 EAP 请求数据包中, 并最终附加到 RADIUS 消息中。

本地目标消息格式: <timestamp> <seq_num> 12810 INFO EAP: Prepared TLS ServerDone message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12810 INFO EAP: Prepared TLS ServerDone message, <log details>

- 消息代码: 12811

严重性: 信息 (INFO)

消息文本: 已提取包含客户端证书的 “TLS 证书” 消息 (Extracted TLS Certificate message containing client certificate)

消息说明: 作为当前正在进行的 TLS 握手的一部分, 已从 EAP 响应数据包提取包含 “TLS 证书” 消息的 TLS 记录, 相应地包含客户端证书。

本地目标消息格式: <timestamp> <seq_num> 12811 INFO EAP: Extracted TLS Certificate message containing client certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12811 INFO EAP: Extracted TLS Certificate message containing client certificate, <log details>

- 消息代码: 12812

严重性: 信息 (INFO)

消息文本: 已提取 “TLS ClientKeyExchange” 消息 (Extracted TLS ClientKeyExchange message)

消息说明: 作为当前正在进行的 TLS 握手的一部分, 已从 EAP 响应数据包提取包含 “TLS ClientKeyExchange” 消息的 TLS 记录。

本地目标消息格式: <timestamp> <seq_num> 12812 INFO EAP: Extracted TLS ClientKeyExchange message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12812 INFO EAP: Extracted TLS
ClientKeyExchange message, <log details>

- 消息代码: 12813

严重性: 信息 (INFO)

消息文本: 已提取 “TLS CertificateVerify” 消息 (Extracted TLS CertificateVerify message)

消息说明: 作为当前正在进行的 TLS 握手的一部分, 已从 EAP 响应数据包提取包含 “TLS
CertificateVerify” 消息的 TLS 记录。

本地目标消息格式: <timestamp> <seq_num> 12813 INFO EAP: Extracted TLS CertificateVerify
message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12813 INFO EAP: Extracted TLS
CertificateVerify message, <log details>

- 消息代码: 12814

严重性: 信息 (INFO)

消息文本: 已准备 “TLS 警报” 消息 (Prepared TLS Alert message)

消息说明: ISE 检测到当前正在进行的 TLS 握手存在问题。已准备包含 “TLS 警报” 消息的 TLS
记录, 封装在传出的 EAP-Request 数据包中, 作为 RADIUS 消息的最终附件。

本地目标消息格式: <timestamp> <seq_num> 12814 INFO EAP: Prepared TLS Alert message, <log
details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12814 INFO EAP: Prepared TLS Alert
message, <log details>

- 消息代码: 12815

严重性: 信息 (INFO)

消息文本: 已提取 “TLS 警报” 消息 (Extracted TLS Alert message)

消息说明: 作为当前正在进行的 TLS 握手的一部分, 已从 EAP 响应数据包提取包含 “TLS 警
报” 消息的 TLS 记录, 表明客户端已经检测到握手存在问题。

本地目标消息格式: <timestamp> <seq_num> 12815 INFO EAP: Extracted TLS Alert message, <log
details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12815 INFO EAP: Extracted TLS Alert
message, <log details>

- 消息代码: 12816

严重性: 信息 (INFO)

消息文本: TLS 握手成功 (TLS handshake succeeded)

消息说明: 客户端的请求方启动的 TLS 握手成功完成。

本地目标消息格式: <timestamp> <seq_num> 12816 INFO EAP: TLS handshake succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12816 INFO EAP: TLS handshake succeeded, <log details>

- 消息代码: 12817

严重性: 信息 (INFO)

消息文本: TLS 握手失败 (TLS handshake failed)

消息说明: 客户端的请求方启动的 TLS 握手失败。

本地目标消息格式: <timestamp> <seq_num> 12817 INFO EAP: TLS handshake failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12817 INFO EAP: TLS handshake failed, <log details>

- 消息代码: 12818

严重性: 警告 (WARN)

消息文本: 期望收到最后一条警报的 TLS 确认消息, 但收到其他消息 (Expected TLS acknowledge for last alert but received another message)

消息说明: ISE 最近向请求方发送了 TLS 警报, 并期望从请求方收到该警报的 TLS 确认消息, 但收到其他消息。这可能是因为 ISE 和请求方之间协议的实施不一致导致的。

本地目标消息格式: <timestamp> <seq_num> 12818 WARN EAP: Expected TLS acknowledge for last alert but received another message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12818 WARN EAP: Expected TLS acknowledge for last alert but received another message, <log details>

- 消息代码: 12819

严重性: 警告 (WARN)

消息文本: 期望收到握手成功的 TLS 确认消息, 但收到其他消息 (Expected TLS acknowledge for handshake succeeded but received another message)

消息说明: ISE 最近成功与请求方完成了 TLS 握手, 并期望从请求方收到 TLS 确认消息以确认握手成功, 但收到其他消息。这可能是因为请求方配置不当, 或者是 ISE 和请求方之间协议的实施不一致导致的。

本地目标消息格式: <timestamp> <seq_num> 12819 WARN EAP: Expected TLS acknowledge for handshake succeeded but received another message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12819 WARN EAP: Expected TLS
acknowledge for handshake succeeded but received another message, <log details>

- 消息代码: 12830

严重性: 警告 (WARN)

消息文本: 已绕过 CRL 验证 (CRL verification bypassed)

消息说明: ISE 无法下载 CRL; 已绕过 CRL 验证

本地目标消息格式: <timestamp> <seq_num> 12830 WARN CRL: CRL verification bypassed, <log
details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12830 WARN CRL: CRL verification
bypassed, <log details>

- 消息代码: 12831

严重性: 警告 (WARN)

消息文本: 无法下载 CRL (Unable to download CRL)

消息说明: ISE 无法下载 CRL; 对应的身份验证失败

本地目标消息格式: <timestamp> <seq_num> 12831 WARN CRL: Unable to download CRL, <log
details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12831 WARN CRL: Unable to download
CRL, <log details>

- 消息代码: 12832

严重性: 警告 (WARN)

消息文本: 使用本地服务器证书建立的隧道尚未生效或已过期 (Tunnel build with local server
certificate is not yet active or it has already expired)

消息说明: 本地服务器证书在一定时期内处于生效状态, 且可以使用。由于证书的“有效起始
日期” (Valid From) 字段在当前日期和时间之后, 或者其“有效截止日期” (Valid To) 在当前日
期和时间之前, 因此证书现在不能使用。

本地目标消息格式: <timestamp> <seq_num> 12832 WARN EAP: Tunnel build with local server
certificate is not yet active or it has already expired, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12832 WARN EAP: Tunnel build with local
server certificate is not yet active or it has already expired, <log details>

- 消息代码: 12833

严重性: 警告 (WARN)

消息文本: EAP-FAST 调配模式仅限匿名模式 (EAP-FAST provisioning mode is restricted to anonymous)

消息说明: 本地服务器证书无效, 因为它尚未生效或已过期。因此, EAP-FAST 调配模式仅限于匿名模式 (如果配置中允许匿名调配)。禁止经过验证的调配 (即使在配置中允许)

本地目标消息格式: <timestamp> <seq_num> 12833 WARN EAP: EAP-FAST provisioning mode is restricted to anonymous, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12833 WARN EAP: EAP-FAST provisioning mode is restricted to anonymous, <log details>

- 消息代码: 12834

严重性: 警告 (WARN)

消息文本: ISE 使用的 CRL 尚未生效或已过期 (ISE used a CRL that is not active yet or has expired)

消息说明: ISE 使用了 CRL (尽管其尚未生效或已过期)。

本地目标消息格式: <timestamp> <seq_num> 12834 WARN CRL: ISE used a CRL that is not active yet or has expired, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12834 WARN CRL: ISE used a CRL that is not active yet or has expired, <log details>

- 消息代码: 12835

严重性: 警告 (WARN)

消息文本: 从客户端接受了过期的证书 (Expired certificate was accepted from the client)

消息说明: ISE 根据配置接受了过期的用户证书或计算机证书

本地目标消息格式: <timestamp> <seq_num> 12835 WARN EAP: Expired certificate was accepted from the client, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12835 WARN EAP: Expired certificate was accepted from the client, <log details>

- 消息代码: 12850

严重性: 警告 (WARN)

消息文本: 收到 NAK TLV。 (Received NAK TLV.) 客户端已拒绝对话

消息说明: ISE 期望继续进行常规对话, 但是客户端在隧道中发送了 NAK TLV。这表示客户端出于 ISE 未知的某种原因拒绝对话。已知问题: CSSC 5.1.1.10 在 EAP-FAST/EAP-GTC 对话过程中发送了 NAK TLV, 以根据用户输入内容拒绝对话。

本地目标消息格式: <timestamp> <seq_num> 12850 WARN EAP: Received NAK TLV. Client rejected the conversation, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12850 WARN EAP: Received NAK TLV.
Client rejected the conversation, <log details>

- 消息代码: 12851

严重性: 警告 (WARN)

消息文本: 收到意外 EAP NAK 消息。(Received unexpected EAP NAK message.) 客户端已拒绝对话

消息说明: ISE 期望继续进行常规对话, 但是客户端发送了外部 EAP 方法 NAK 消息。这表示客户端出于 ISE 未知的某种原因拒绝对话。已知问题: CSSC 5.1.1.10 在 EAP-FAST/EAP-GTC 对话过程中向外部 EAP 方法发送了 NAK, 以根据用户输入内容拒绝对话。

本地目标消息格式: <timestamp> <seq_num> 12851 WARN EAP: Received unexpected EAP NAK message. Client rejected the conversation, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12851 WARN EAP: Received unexpected EAP NAK message. Client rejected the conversation, <log details>

- 消息代码: 12852

严重性: 警告 (WARN)

消息文本: 对收到的缓冲区进行加密处理失败 (Cryptographic processing of received buffer failed)

消息说明: ISE 从客户端收到无效的加密缓冲区。对此缓冲区进行加密处理失败。

本地目标消息格式: <timestamp> <seq_num> 12852 WARN EAP: Cryptographic processing of received buffer failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12852 WARN EAP: Cryptographic processing of received buffer failed, <log details>

- 消息代码: 12853

严重性: 警告 (WARN)

消息文本: 收到空 EAP-GTC 消息 (Empty EAP-GTC message received)

消息说明: ISE 在 EAP-FAST 对话过程中从隧道中收到空 EAP-GTC 消息。已知问题: CSSC 5.1.1.10 在提示用户重新尝试输入密码后发送的 EAP-GTC 消息为空。

本地目标消息格式: <timestamp> <seq_num> 12853 WARN EAP: Empty EAP-GTC message received, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12853 WARN EAP: Empty EAP-GTC message received, <log details>

- 消息代码: 12854

严重性: 警告 (WARN)

消息文本: 无法进行身份验证, 因为密码不存在或为空 (Cannot authenticate because password was not present or was empty)

消息说明: ISE 未收到用户密码或收到的密码为空。在无密码或密码为空的情况下, 无法执行纯密码身份验证

本地目标消息格式: <timestamp> <seq_num> 12854 WARN EAP: Cannot authenticate because password was not present or was empty, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12854 WARN EAP: Cannot authenticate because password was not present or was empty, <log details>

- 消息代码: 12855

严重性: 信息 (INFO)

消息文本: 由于身份验证失败, 因此未发送 PAC (PAC was not sent due to authorization failure)

消息说明: 由于身份验证失败, ISE 未向请求方发送 PAC, 因此整个对话被视为失败

本地目标消息格式: <timestamp> <seq_num> 12855 INFO EAP: PAC was not sent due to authorization failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12855 INFO EAP: PAC was not sent due to authorization failure, <log details>

- 消息代码: 12856

严重性: 信息 (INFO)

消息文本: CRL 验证撤销了用户证书 (User certificate was revoked by CRL verification)

消息说明: CRL 验证返回了已撤销证书状态。

本地目标消息格式: <timestamp> <seq_num> 12856 INFO EAP: User certificate was revoked by CRL verification, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12856 INFO EAP: User certificate was revoked by CRL verification, <log details>

- 消息代码: 12857

严重性: 警告 (WARN)

消息文本: 客户端证书身份验证失败 (Client certificate authentication failed)

消息说明: 客户端证书身份验证失败

本地目标消息格式: <timestamp> <seq_num> 12857 WARN EAP: Client certificate authentication failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12857 WARN EAP: Client certificate authentication failed, <log details>

- 消息代码: 12914
严重性: 信息 (INFO)
消息文本: 正使用弱 TLS 密码 (Using weak TLS cipher)
消息说明: 正使用弱 TLS 密码
本地目标消息格式: <timestamp> <seq_num> 12914 INFO EAP: Using weak TLS cipher, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12914 INFO EAP: Using weak TLS cipher,
<log details>
- 消息代码: 12915
严重性: 警告 (WARN)
消息文本: PEAP 版本协商失败 (PEAP version negotiation failed)
消息说明: PEAP 版本协商失败, 因为请求方建议使用版本 1, 而“仅允许 PEAPv 0”选项处于打开状态。
本地目标消息格式: <timestamp> <seq_num> 12915 WARN EAP: PEAP version negotiation failed,
<log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12915 WARN EAP: PEAP version negotiation
failed, <log details>
- 消息代码: 12916
严重性: 警告 (WARN)
消息文本: 期望收到 TLS 分片的 TLS 确认消息, 但收到其他消息 (Expected TLS acknowledge
for TLS fragment but received another message)
消息说明: ISE 最近向请求方发送了其他 TLS 分片, 并期望从请求方收到 TLS 确认消息以确认
该分片, 然后再发送下一个分片, 但收到其他消息。这可能是因为请求方配置不当, 或者是 ISE
和请求方之间协议的实施不一致导致的。
本地目标消息格式: <timestamp> <seq_num> 12916 WARN EAP: Expected TLS acknowledge for
TLS fragment but received another message, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12916 WARN EAP: Expected TLS
acknowledge for TLS fragment but received another message, <log details>
- 消息代码: 12917
严重性: 警告 (WARN)
消息文本: 期望收到 PEAPv1 保护终止的 TLS 确认消息, 但收到其他消息 (Expected TLS
acknowledge for PEAPv1 protected termination but received another message)

消息说明: ISE 最近向请求方发送了 PEAPv1 保护终止 EAP 成功消息, 并期望从请求方收到 TLS 确认消息对其进行确认, 但收到其他消息。这可能是因为请求方配置不当, 或者是 ISE 和请求方之间协议的实施不一致导致的。

本地目标消息格式: <timestamp> <seq_num> 12917 WARN EAP: Expected TLS acknowledge for PEAPv1 protected termination but received another message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12917 WARN EAP: Expected TLS acknowledge for PEAPv1 protected termination but received another message, <log details>

- 消息代码: 12918

严重性: 警告 (WARN)

消息文本: 请求方发送的 EAP 响应数据包标识符不匹配 (Supplicant sent unmatched EAP Response packet identifier)

消息说明: ISE 向具有特定标识符的请求方发送了 EAP 请求。根据 EAP 规格, 请求方必须使用具有相同标识符的 EAP 响应数据包响应此请求。但是, 响应中的 EAP 标识符与请求中不一样。

本地目标消息格式: <timestamp> <seq_num> 12918 WARN EAP: Supplicant sent unmatched EAP Response packet identifier, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12918 WARN EAP: Supplicant sent unmatched EAP Response packet identifier, <log details>

- 消息代码: 12919

严重性: 警告 (WARN)

消息文本: 请求方发送的内部 EAP 响应数据包标识符不匹配 (Supplicant sent unmatched inner EAP Response packet identifier)

消息说明: ISE 向具有特定标识符的请求方发送了内部 EAP 请求。根据 EAP 规格, 请求方必须使用具有相同标识符的 EAP 响应数据包响应此请求。但是, 响应中的 EAP 标识符与请求中不一样。

本地目标消息格式: <timestamp> <seq_num> 12919 WARN EAP: Supplicant sent unmatched inner EAP Response packet identifier, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12919 WARN EAP: Supplicant sent unmatched inner EAP Response packet identifier, <log details>

- 消息代码: 12929

严重性: 警告 (WARN)

消息文本: NAS 发送 RADIUS 记账更新信息过于频繁 (NAS sends RADIUS accounting update messages too frequently)

消息说明: NAS 发送 RADIUS 记账更新信息过于频繁

本地目标消息格式: <timestamp> <seq_num> 12929 WARN RADIUS: NAS sends RADIUS accounting update messages too frequently, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12929 WARN RADIUS: NAS sends RADIUS accounting update messages too frequently, <log details>

- 消息代码: 12930

严重性: 警告 (WARN)

消息文本: 请求方在向 ISE 发送第一条 PEAP 消息后停止对其进行响应 (Supplicant stopped responding to ISE after sending it the first PEAP message)

消息说明: 请求方在向 ISE 发送第一条 PEAP 消息后停止对其进行响应

本地目标消息格式: <timestamp> <seq_num> 12930 WARN Failed-Attempt: Supplicant stopped responding to ISE after sending it the first PEAP message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12930 WARN Failed-Attempt: Supplicant stopped responding to ISE after sending it the first PEAP message, <log details>

- 消息代码: 12931

严重性: 警告 (WARN)

消息文本: 请求方在向 ISE 发送第一条 EAP-TLS 消息后停止对其进行响应 (Supplicant stopped responding to ISE after sending it the first EAP-TLS message)

消息说明: 请求方在向 ISE 发送第一条 EAP-TLS 消息后停止对其进行响应

本地目标消息格式: <timestamp> <seq_num> 12931 WARN Failed-Attempt: Supplicant stopped responding to ISE after sending it the first EAP-TLS message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12931 WARN Failed-Attempt: Supplicant stopped responding to ISE after sending it the first EAP-TLS message, <log details>

- 消息代码: 12932

严重性: 警告 (WARN)

消息文本: 请求方在向 ISE 发送第一条 EAP-FAST 消息后停止对其进行响应 (Supplicant stopped responding to ISE after sending it the first EAP-FAST message)

消息说明: 请求方在向 ISE 发送第一条 EAP-FAST 消息后停止对其进行响应

本地目标消息格式: <timestamp> <seq_num> 12932 WARN Failed-Attempt: Supplicant stopped responding to ISE after sending it the first EAP-FAST message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12932 WARN Failed-Attempt: Supplicant stopped responding to ISE after sending it the first EAP-FAST message, <log details>

- 消息代码: 12933

严重性: 警告 (WARN)

消息文本: 请求方在建立 EAP-FAST 隧道期间停止响应 ISE (Supplicant stopped responding to ISE during EAP-FAST tunnel establishment)

消息说明: 请求方在建立 EAP-FAST 隧道期间停止响应 ISE

本地目标消息格式: <timestamp> <seq_num> 12933 WARN Failed-Attempt: Supplicant stopped responding to ISE during EAP-FAST tunnel establishment, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12933 WARN Failed-Attempt: Supplicant stopped responding to ISE during EAP-FAST tunnel establishment, <log details>

- 消息代码: 12934

严重性: 警告 (WARN)

消息文本: 请求方在建立 PEAP 隧道期间停止响应 ISE (Supplicant stopped responding to ISE during PEAP tunnel establishment)

消息说明: 请求方在建立 PEAP 隧道期间停止响应 ISE

本地目标消息格式: <timestamp> <seq_num> 12934 WARN Failed-Attempt: Supplicant stopped responding to ISE during PEAP tunnel establishment, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12934 WARN Failed-Attempt: Supplicant stopped responding to ISE during PEAP tunnel establishment, <log details>

- 消息代码: 12935

严重性: 警告 (WARN)

消息文本: 请求方在 EAP-TLS 证书交换期间停止响应 ISE (Supplicant stopped responding to ISE during EAP-TLS certificate exchange)

消息说明: 请求方在 EAP-TLS 证书交换期间停止响应 ISE

本地目标消息格式: <timestamp> <seq_num> 12935 WARN Failed-Attempt: Supplicant stopped responding to ISE during EAP-TLS certificate exchange, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12935 WARN Failed-Attempt: Supplicant stopped responding to ISE during EAP-TLS certificate exchange, <log details>

- 消息代码: 12936

严重性: 警告 (WARN)

消息文本: 请求方在向 ISE 发送内部 EAP 身份请求后停止对其进行响应 (Supplicant stopped responding to ISE after sending it inner EAP Identity Request)

消息说明: 请求方在向 ISE 发送内部 EAP 身份请求后停止对其进行响应

本地目标消息格式: <timestamp> <seq_num> 12936 WARN Failed-Attempt: Supplicant stopped responding to ISE after sending it inner EAP Identity Request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12936 WARN Failed-Attempt: Supplicant
stopped responding to ISE after sending it inner EAP Identity Request, <log details>

- 消息代码: 12937

严重性: 警告 (WARN)

消息文本: 请求方在向 ISE 发送第一条内部 EAP-MSCHAPv2 消息后停止对其进行响应 (Supplicant
stopped responding to ISE after sending it the first inner EAP-MSCHAPv2 message)

消息说明: 请求方在向 ISE 发送第一条内部 EAP-MSCHAPv2 消息后停止对其进行响应

本地目标消息格式: <timestamp> <seq_num> 12937 WARN Failed-Attempt: Supplicant stopped
responding to ISE after sending it the first inner EAP-MSCHAPv2 message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12937 WARN Failed-Attempt: Supplicant
stopped responding to ISE after sending it the first inner EAP-MSCHAPv2 message, <log details>

- 消息代码: 12938

严重性: 警告 (WARN)

消息文本: 请求方在向 ISE 发送第一条内部 EAP-GTC 消息后停止对其进行响应 (Supplicant
stopped responding to ISE after sending it the first inner EAP-GTC message)

消息说明: 请求方在向 ISE 发送第一条内部 EAP-GTC 消息后停止对其进行响应

本地目标消息格式: <timestamp> <seq_num> 12938 WARN Failed-Attempt: Supplicant stopped
responding to ISE after sending it the first inner EAP-GTC message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12938 WARN Failed-Attempt: Supplicant
stopped responding to ISE after sending it the first inner EAP-GTC message, <log details>

- 消息代码: 12939

严重性: 警告 (WARN)

消息文本: 请求方在向 ISE 发送第一条内部 EAP-TLS 消息后停止对其进行响应 (Supplicant stopped
responding to ISE after sending it the first inner EAP-TLS message)

消息说明: 请求方在向 ISE 发送第一条内部 EAP-TLS 消息后停止对其进行响应

本地目标消息格式: <timestamp> <seq_num> 12939 WARN Failed-Attempt: Supplicant stopped
responding to ISE after sending it the first inner EAP-TLS message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12939 WARN Failed-Attempt: Supplicant
stopped responding to ISE after sending it the first inner EAP-TLS message, <log details>

- 消息代码: 12940

严重性: 警告 (WARN)

消息文本: 请求方在执行内部 EAP-MSCHAPv2 方法的过程中停止响应 ISE (Supplicant stopped responding to ISE during conducting inner EAP-MSCHAPv2 method)

消息说明: 请求方在执行内部 EAP-MSCHAPv2 方法的过程中停止响应 ISE

本地目标消息格式: <timestamp> <seq_num> 12940 WARN Failed-Attempt: Supplicant stopped responding to ISE during conducting inner EAP-MSCHAPv2 method, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12940 WARN Failed-Attempt: Supplicant stopped responding to ISE during conducting inner EAP-MSCHAPv2 method, <log details>

- 消息代码: 12941

严重性: 警告 (WARN)

消息文本: 请求方在执行内部 EAP-GTC 方法的过程中停止响应 ISE (Supplicant stopped responding to ISE during conducting inner EAP-GTC method)

消息说明: 请求方在执行内部 EAP-GTC 方法的过程中停止响应 ISE

本地目标消息格式: <timestamp> <seq_num> 12941 WARN Failed-Attempt: Supplicant stopped responding to ISE during conducting inner EAP-GTC method, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12941 WARN Failed-Attempt: Supplicant stopped responding to ISE during conducting inner EAP-GTC method, <log details>

- 消息代码: 12942

严重性: 警告 (WARN)

消息文本: 请求方在执行内部 EAP-TLS 方法的过程中停止响应 ISE (Supplicant stopped responding to ISE during conducting inner EAP-TLS method)

消息说明: 请求方在执行内部 EAP-TLS 方法的过程中停止响应 ISE

本地目标消息格式: <timestamp> <seq_num> 12942 WARN Failed-Attempt: Supplicant stopped responding to ISE during conducting inner EAP-TLS method, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12942 WARN Failed-Attempt: Supplicant stopped responding to ISE during conducting inner EAP-TLS method, <log details>

- 消息代码: 12943

严重性: 警告 (WARN)

消息文本: 请求方在 PEAPv0 保护终止的过程中停止响应 ISE (Supplicant stopped responding to ISE during PEAPv0 protected termination)

消息说明: 请求方在 PEAPv0 保护终止的过程中停止响应 ISE

本地目标消息格式: <timestamp> <seq_num> 12943 WARN Failed-Attempt: Supplicant stopped responding to ISE during PEAPv0 protected termination, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12943 WARN Failed-Attempt: Supplicant
stopped responding to ISE during PEAPv0 protected termination, <log details>

- 消息代码: 12944

严重性: 警告 (WARN)

消息文本: 请求方在 PEAPv1 保护终止的过程中停止响应 ISE (Supplicant stopped responding to ISE during PEAPv1 protected termination)

消息说明: 请求方在 PEAPv1 保护终止的过程中停止响应 ISE

本地目标消息格式: <timestamp> <seq_num> 12944 WARN Failed-Attempt: Supplicant stopped
responding to ISE during PEAPv1 protected termination, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12944 WARN Failed-Attempt: Supplicant
stopped responding to ISE during PEAPv1 protected termination, <log details>

- 消息代码: 12945

严重性: 警告 (WARN)

消息文本: 请求方在 EAP-FAST 保护终止的过程中停止响应 ISE (Supplicant stopped responding to ISE during EAP-FAST protected termination)

消息说明: 请求方在 EAP-FAST 保护终止的过程中停止响应 ISE

本地目标消息格式: <timestamp> <seq_num> 12945 WARN Failed-Attempt: Supplicant stopped
responding to ISE during EAP-FAST protected termination, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12945 WARN Failed-Attempt: Supplicant
stopped responding to ISE during EAP-FAST protected termination, <log details>

- 消息代码: 12946

严重性: 警告 (WARN)

消息文本: 请求方在 LEAP 期间停止响应 ISE (Supplicant stopped responding to ISE during LEAP)

消息说明: 请求方在 LEAP 期间停止响应 ISE

本地目标消息格式: <timestamp> <seq_num> 12946 WARN Failed-Attempt: Supplicant stopped
responding to ISE during LEAP, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12946 WARN Failed-Attempt: Supplicant
stopped responding to ISE during LEAP, <log details>

- 消息代码: 12947

严重性: 警告 (WARN)

消息文本: 请求方在 EAP-MD5 期间停止响应 ISE (Supplicant stopped responding to ISE during EAP-MD5)

消息说明: 请求方在 EAP-MD5 期间停止响应 ISE

本地目标消息格式: <timestamp> <seq_num> 12947 WARN Failed-Attempt: Supplicant stopped responding to ISE during EAP-MD5, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12947 WARN Failed-Attempt: Supplicant stopped responding to ISE during EAP-MD5, <log details>

- 消息代码: 12948

严重性: 警告 (WARN)

消息文本: 请求方在 PEAP 协议中发送了意外未加密 TLS 握手消息, 而非 TLS 应用数据 (Supplicant sent unexpected unencrypted TLS handshake message instead of TLS application data in PEAP protocol)

消息说明: 请求方在 PEAP 协议中发送了意外未加密 TLS 握手消息, 而非 TLS 应用数据

本地目标消息格式: <timestamp> <seq_num> 12948 WARN Failed-Attempt: Supplicant sent unexpected unencrypted TLS handshake message instead of TLS application data in PEAP protocol, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12948 WARN Failed-Attempt: Supplicant sent unexpected unencrypted TLS handshake message instead of TLS application data in PEAP protocol, <log details>

- 消息代码: 12949

严重性: 警告 (WARN)

消息文本: 请求方发送了格式错误的 PEAP 消息 - 错误的分组密码填充 (Supplicant sent malformed PEAP message - wrong block cipher padding)

消息说明: 请求方发送了格式错误的 PEAP 消息 - 错误的分组密码填充

本地目标消息格式: <timestamp> <seq_num> 12949 WARN Failed-Attempt: Supplicant sent malformed PEAP message - wrong block cipher padding, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12949 WARN Failed-Attempt: Supplicant sent malformed PEAP message - wrong block cipher padding, <log details>

- 消息代码: 12950

严重性: 警告 (WARN)

消息文本: 请求方发送了格式错误的 PEAP 消息 - 坏记录 MAC (Supplicant sent malformed PEAP message - bad record MAC)

消息说明: 请求方发送了格式错误的 PEAP 消息 - MAC 不良记录

本地目标消息格式: <timestamp> <seq_num> 12950 WARN Failed-Attempt: Supplicant sent malformed PEAP message - bad record MAC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12950 WARN Failed-Attempt: Supplicant
sent malformed PEAP message - bad record MAC, <log details>

- 消息代码: 12951

严重性: 警告 (WARN)

消息文本: 收到意外重新协商。(Unexpected renegotiation received.) PEAP 不支持重新协商

消息说明: 收到意外重新协商。PEAP 不支持重新协商

本地目标消息格式: <timestamp> <seq_num> 12951 WARN Failed-Attempt: Unexpected renegotiation
received. Renegotiation is not supported in PEAP, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12951 WARN Failed-Attempt: Unexpected
renegotiation received. Renegotiation is not supported in PEAP, <log details>

- 消息代码: 12952

严重性: 警告 (WARN)

消息文本: 在对话过程中收到 EAP 数据包, 但是此 PSN 上的对话并未开始 (Received EAP packet
from the middle of conversation but the conversation was not started on this PSN)

消息说明: 根据主机名, 会话不属于此 PSN。可能是意外的 NAD 行为。可能是 NAD 在对话进
行到一半时使用另一个 PSN 发送了一个数据包。

本地目标消息格式: <timestamp> <seq_num> 12952 WARN EAP: Received EAP packet from the
middle of conversation but the conversation was not started on this PSN, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12952 WARN EAP: Received EAP packet
from the middle of conversation but the conversation was not started on this PSN, <log details>

- 消息代码: 12953

严重性: 警告 (WARN)

消息文本: 在对话过程中收到 EAP 数据包, 其中包含此 PSN 上不存在的会话 (Received EAP
packet from the middle of conversation that contains a session on this PSN that does not exist)

消息说明: 未在此 PSN 上找到会话。可能是意外的 NAD 行为。根据主机名, 会话属于此 PSN,
但可能已因为超时结束了。此数据包到达时间过迟。

本地目标消息格式: <timestamp> <seq_num> 12953 WARN EAP: Received EAP packet from the
middle of conversation that contains a session on this PSN that does not exist, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12953 WARN EAP: Received EAP packet
from the middle of conversation that contains a session on this PSN that does not exist, <log details>

- 消息代码: 12954

严重性: 警告 (WARN)

消息文本: CRL 签名检查失败 (CRL signature check failed)

消息说明: 为特定 CA 找到的 CRL 不适合 CA。可能是使用了具有相同名称的多个 CA, 并且其中一个的 CRL 没有 AKI。因此, ISE 无法确定 CRL 属于哪个 CA。

本地目标消息格式: <timestamp> <seq_num> 12954 WARN EAP: CRL signature check failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12954 WARN EAP: CRL signature check failed, <log details>

- 消息代码: 12955

严重性: 警告 (WARN)

消息文本: 包含 EAP 消息的 RADIUS 请求必须包含 MessageAuthenticator 属性 (RADIUS request that contains EAP message must contain MessageAuthenticator attribute)

消息说明: 包含 EAP 消息的 RADIUS 请求必须包含 MessageAuthenticator 属性

本地目标消息格式: <timestamp><seq_num> 12955 WARN RADIUS: RADIUS request that contains EAP message must contain MessageAuthenticator attribute, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12955 WARN RADIUS: RADIUS request that contains EAP message must contain MessageAuthenticator attribute, <log details>

- 消息代码: 12956

严重性: 警告 (WARN)

消息文本: 由于违反了名称约束允许子树, 客户端证书验证失败 (Client certificate validation failed due to name constraints permitted subtree violation)

消息说明: 由于违反了名称约束允许子树, 客户端证书验证失败

本地目标消息格式: <timestamp> <seq_num> 12956 WARN RADIUS: Client certificate validation failed due to name constraints permitted subtree violation, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12956 WARN RADIUS: Client certificate validation failed due to name constraints permitted subtree violation, <log details>

- 消息代码: 12957

严重性: 警告 (WARN)

消息文本: 由于违反了名称约束排除子树, 客户端证书验证失败 (Client certificate validation failed due to name constraints excluded subtree violation)

消息说明: 由于违反了名称约束排除子树, 客户端证书验证失败

本地目标消息格式: <timestamp> <seq_num> 12957 WARN RADIUS: Client certificate validation failed due to name constraints excluded subtree violation, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num> 12957 WARN RADIUS: Client certificate
validation failed due to name constraints excluded subtree violation, <log details>

- 消息代码: 12958

严重性: 警告 (WARN)

消息文本: 由于违反了最小或最大名称约束值, 客户端证书验证失败 (Client certificate validation
failed due to min or max name constraints values violation)

消息说明: 由于违反了最小或最大名称约束值, 客户端证书验证失败

本地目标消息格式: <timestamp> <seq_num> 12958 WARN RADIUS: Client certificate validation
failed due to min or max name constraints values violation, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num> 12958 WARN RADIUS: Client certificate
validation failed due to min or max name constraints values violation, <log details>

- 消息代码: 12959

严重性: 警告 (WARN)

消息文本: 由于名称约束类型不受支持, 客户端证书验证失败 (Client certificate validation failed
due to unsupported name constraint type)

消息说明: 由于名称约束类型不受支持, 客户端证书验证失败

本地目标消息格式: <timestamp> <seq_num> 12959 WARN RADIUS: Client certificate validation
failed due to unsupported name constraint type, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num> 12959 WARN RADIUS: Client certificate
validation failed due to unsupported name constraint type, <log details>

- 消息代码: 12960

严重性: 警告 (WARN)

消息文本: 由于名称约束语法错误或不受支持, 客户端证书验证失败 (Client certificate validation
failed due to bad or unsupported name constraint syntax)

消息说明: 由于名称约束语法错误或不受支持, 客户端证书验证失败

本地目标消息格式: <timestamp> <seq_num> 12960 WARN RADIUS: Client certificate validation
failed due to bad or unsupported name constraint syntax, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg_num><timestamp> <seq_num> 12960 WARN RADIUS: Client certificate
validation failed due to bad or unsupported name constraint syntax, <log details>

- 消息代码: 12961

严重性: 警告 (WARN)

消息文本: 由于名称约束语法错误或不支持, 客户端证书验证失败 (Client certificate validation failed due to bad or unsupported name syntax of the constraint)

消息说明: 由于名称约束语法错误或不支持, 客户端证书验证失败

本地目标消息格式: <timestamp> <seq_num> 12961 WARN RADIUS: Client certificate validation failed due to bad or unsupported name syntax of the constraint, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12961 WARN RADIUS: Client certificate validation failed due to bad or unsupported name syntax of the constraint, <log details>

- 消息代码: 12962

严重性: 警告 (WARN)

消息文本: 拒绝用户授权 PAC, 原因是它的发起方 ID 与隧道 PAC 发起方 ID 不匹配 (Reject User Authorization PAC since its Initiator-ID does not match the Tunnel PAC Initiator-ID)

消息说明: 拒绝用户授权 PAC, 原因是它的发起方 ID 与隧道 PAC 发起方 ID 不匹配

本地目标消息格式: <timestamp> <seq_num> 12962 WARN RADIUS: Reject User Authorization PAC since its Initiator-ID does not match the Tunnel PAC Initiator-ID, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12962 WARN RADIUS: Reject User Authorization PAC since its Initiator-ID does not match the Tunnel PAC Initiator-ID, <log details>

- 消息代码: 12963

严重性: 警告 (WARN)

消息文本: 收到格式错误的 EAP 负载 TLV (Received malformed EAP Payload TLV)

消息说明: ISE 从请求方收到了格式错误的 EAP 负载 TLV

本地目标消息格式: <timestamp> <seq_num> 12963 WARN RADIUS: Received malformed EAP Payload TLV, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12963 WARN RADIUS: Received malformed EAP Payload TLV, <log details>

- 消息代码: 12964

严重性: 调试 (DEBUG)

消息文本: 发送的 EAP 结果 TLV 表明成功 (Sent EAP Result TLV indicating success)

消息说明: ISE 发送了表明成功的 EAP 结果 TLV

本地目标消息格式: <timestamp> <seq_num> 12964 DEBUG RADIUS: Sent EAP Result TLV indicating success, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12964 DEBUG RADIUS: Sent EAP Result TLV indicating success, <log details>

- 消息代码: 12965
 - 严重性: 调试 (DEBUG)
 - 消息文本: 发送的 EAP 结果 TLV 表明失败 (Sent EAP Result TLV indicating failure)
 - 消息说明: ISE 发送了表明失败的 EAP 结果 TLV
 - 本地目标消息格式: <timestamp> <seq_num> 12965 DEBUG RADIUS: Sent EAP Result TLV indicating failure, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12965 DEBUG RADIUS: Sent EAP Result TLV indicating failure, <log details>

- 消息代码: 12966
 - 严重性: 调试 (DEBUG)
 - 消息文本: 发送的 EAP 中间结果 TLV 表明成功 (Sent EAP Intermediate Result TLV indicating success)
 - 消息说明: ISE 发送了表明成功的 EAP 中间结果 TLV
 - 本地目标消息格式: <timestamp> <seq_num> 12966 DEBUG RADIUS: Sent EAP Intermediate Result TLV indicating success, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12966 DEBUG RADIUS: Sent EAP Intermediate Result TLV indicating success, <log details>

- 消息代码: 12967
 - 严重性: 调试 (DEBUG)
 - 消息文本: 发送的 EAP 中间结果 TLV 表明失败 (Sent EAP Intermediate Result TLV indicating failure)
 - 消息说明: ISE 发送了表明失败的 EAP 中间结果 TLV
 - 本地目标消息格式: <timestamp> <seq_num> 12967 DEBUG RADIUS: Sent EAP Intermediate Result TLV indicating failure, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12967 DEBUG RADIUS: Sent EAP Intermediate Result TLV indicating failure, <log details>

- 消息代码: 12968
 - 严重性: 警告 (WARN)
 - 消息文本: 客户端未提供合适的密码 (Client didn't provide suitable ciphers)
 - 消息说明: 客户端未提供 ISE 上允许的合适密码
 - 本地目标消息格式: <timestamp> <seq_num>12968 WARN EAP Client didn't provide suitable ciphers, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>12968 WARN EAP Client didn't provide
suitable ciphers, <log details>

- 消息代码: 12970

严重性: 信息 (INFO)

消息文本: EAP-TTLS 内部方法以失败告终 (EAP-TTLS inner method finished with failure)

消息说明: EAP-TTLS 内部方法以失败告终。

本地目标消息格式: <timestamp> <seq_num> 12970 INFO EAP: EAP-TTLS inner method finished
with failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12970 INFO EAP: EAP-TTLS inner method
finished with failure, <log details>

- 消息代码: 12971

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应包含 EAP-TTLS 质询-响应 (Extracted EAP-Response containing
EAP-TTLS challenge-response)

消息说明: 继续使用 EAP-TTLS 协议; 处理已提取的 EAP 响应中的 EAP-TTLS 质询-响应。

本地目标消息格式: <timestamp> <seq_num> 12971 INFO EAP: Extracted EAP-Response containing
EAP-TTLS challenge-response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12971 INFO EAP: Extracted EAP-Response
containing EAP-TTLS challenge-response, <log details>

- 消息代码: 12972

严重性: 警告 (WARN)

消息文本: EAP-TTLS 进行 SSL/TLS 握手失败, 因为客户端拒绝 ISE 本地证书 (EAP-TTLS failed
SSL/TLS handshake because the client rejected the ISE local-certificate)

消息说明: EAP-TTLS 进行 SSL/TLS 握手失败, 因为客户端拒绝 ISE 本地证书

本地目标消息格式: <timestamp> <seq_num> 12972 WARN EAP: EAP-TTLS failed SSL/TLS
handshake because the client rejected the ISE local-certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12972 WARN EAP: EAP-TTLS failed
SSL/TLS handshake because the client rejected the ISE local-certificate, <log details>

- 消息代码: 12973

严重性: 警告 (WARN)

消息文本: 在客户端发出警报后, EAP-TTLS 进行 SSL/TLS 握手失败 (EAP-TTLS failed SSL/TLS
handshake after a client alert)

消息说明: 在客户端发出警报后, EAP-TTLS 进行 SSL/TLS 握手失败

本地目标消息格式: <timestamp> <seq_num> 12973 WARN EAP: EAP-TTLS failed SSL/TLS handshake after a client alert, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12973 WARN EAP: EAP-TTLS failed SSL/TLS handshake after a client alert, <log details>

- 消息代码: 12974

严重性: 警告 (WARN)

消息文本: EAP-TTLS 握手失败 (EAP-TTLS handshake failed)

消息说明: EAP-TTLS 握手失败。

本地目标消息格式: <timestamp> <seq_num> 12974 WARN EAP: EAP-TTLS handshake failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12974 WARN EAP: EAP-TTLS handshake failed, <log details>

- 消息代码: 12975

严重性: 信息 (INFO)

消息文本: EAP-TTLS 身份验证成功 (EAP-TTLS authentication succeeded)

消息说明: EAP-TTLS 身份验证成功。

本地目标消息格式: <timestamp> <seq_num> 12975 INFO EAP: EAP-TTLS authentication succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12975 INFO EAP: EAP-TTLS authentication succeeded, <log details>

- 消息代码: 12976

严重性: 信息 (INFO)

消息文本: EAP-TTLS 身份验证失败 (EAP-TTLS authentication failed)

消息说明: EAP-TTLS 身份验证失败。

本地目标消息格式: <timestamp> <seq_num> 12976 INFO EAP: EAP-TTLS authentication failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12976 INFO EAP: EAP-TTLS authentication failed, <log details>

- 消息代码: 12977

严重性: 信息 (INFO)

消息文本: EAP-TTLS 基于较早生成的密钥建立隧道, 这意味着将进行身份验证 (EAP-TTLS built tunnel based on earlier generated keys, this will imply authentication)

消息说明: EAP-TTLS 短时握手成功完成 - 为实现身份验证建立隧道。

本地目标消息格式: <timestamp> <seq_num> 12977 INFO EAP: EAP-TTLS built tunnel based on earlier generated keys, this will imply authentication, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12977 INFO EAP: EAP-TTLS built tunnel based on earlier generated keys, this will imply authentication, <log details>

- 消息代码: 12978

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应包含 EAP-TTLS 质询-响应, 且接受将 EAP-TTLS 用作协商协议 (Extracted EAP-Response containing EAP-TTLS challenge-response and accepting EAP-TTLS as negotiated)

消息说明: 从 RADIUS 消息中提取的 EAP 响应数据包含有 EAP-TTLS 质询-响应, 且接受将 EAP-TTLS 用作协商协议。

本地目标消息格式: <timestamp> <seq_num> 12978 INFO EAP: Extracted EAP-Response containing EAP-TTLS challenge-response and accepting EAP-TTLS as negotiated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12978 INFO EAP: Extracted EAP-Response containing EAP-TTLS challenge-response and accepting EAP-TTLS as negotiated, <log details>

- 消息代码: 12979

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应/NAK 请求改为使用 EAP-TTLS (Extracted EAP-Response/NAK requesting to use EAP-TTLS instead)

消息说明: 从 RADIUS 消息中提取的 EAP 响应/NAK 数据包拒绝之前提议的基于 EAP 的协议, 且根据客户端请求方的配置, 请求改为使用 EAP-TTLS。

本地目标消息格式: <timestamp> <seq_num> 12979 INFO EAP: Extracted EAP-Response/NAK requesting to use EAP-TTLS instead, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 12979 INFO EAP: Extracted EAP-Response/NAK requesting to use EAP-TTLS instead, <log details>

- 消息代码: 12980

严重性: 警告 (WARN)

消息文本: 由于 EAP-TTLS 未在“允许的协议”中获得允许, 因此 EAP 协商失败 (Failed to negotiate EAP because EAP-TTLS not allowed in the Allowed Protocols)

消息说明: 客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前提议的基于 EAP 的协议, 且请求改为使用 EAP-TTLS。但是, EAP-TTLS 未在“允许的协议”中获得允许。

本地目标消息格式: <timestamp> <seq_num> 12980 WARN EAP: Failed to negotiate EAP because EAP-TTLS not allowed in the Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12980 WARN EAP: Failed to negotiate EAP because EAP-TTLS not allowed in the Allowed Protocols, <log details>

- 消息代码: 12981

严重性: 警告 (WARN)

消息文本: 请求方在建立 EAP-TTLS 隧道期间停止响应 ISE (Supplicant stopped responding to ISE during EAP-TTLS tunnel establishment)

消息说明: 请求方在建立 EAP-TTLS 隧道期间停止响应 ISE

本地目标消息格式: <timestamp> <seq_num> 12981 WARN Failed-Attempt: Supplicant stopped responding to ISE during EAP-TTLS tunnel establishment, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12981 WARN Failed-Attempt: Supplicant stopped responding to ISE during EAP-TTLS tunnel establishment, <log details>

- 消息代码: 12982

严重性: 警告 (WARN)

消息文本: 请求方在 EAP-TTLS 明文内部 MSCHAPv2 身份验证流程中停止响应 ISE (Supplicant stopped responding to ISE during EAP-TTLS plain inner MSCHAPv2 authentication flow)

消息说明: 请求方在 EAP-TTLS 明文内部 MSCHAPv2 身份验证流程中停止响应 ISE

本地目标消息格式: <timestamp> <seq_num> 12982 WARN Failed-Attempt: Supplicant stopped responding to ISE during EAP-TTLS plain inner MSCHAPv2 authentication flow, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12982 WARN Failed-Attempt: Supplicant stopped responding to ISE during EAP-TTLS plain inner MSCHAPv2 authentication flow, <log details>

- 消息代码: 12983

严重性: 信息 (INFO)

消息文本: 已准备提议使用 EAP-TTLS 和质询的 EAP 请求 (Prepared EAP-Request proposing EAP-TTLS with challenge)

消息说明: 已创建一个 EAP 请求数据包, 提议使用 EAP-TTLS 协议, 同时提供 EAP-TTLS 质询, 用于附加到 RADIUS 消息。建议使用 EAP-TTLS 协议的原因在于此协议是“允许的协议”中允许使用的其中一个基于 EAP 的协议。

本地目标消息格式: <timestamp> <seq_num> 12983 INFO EAP: Prepared EAP-Request proposing EAP-TTLS with challenge, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12983 INFO EAP: Prepared EAP-Request proposing EAP-TTLS with challenge, <log details>

- 消息代码: 12984
 - 严重性: 警告 (WARN)
 - 消息文本: 收到意外重新协商。(Unexpected renegotiation received.) EAP_TTLS 不支持重新协商
 - 消息说明: 收到意外重新协商。EAP_TTLS 不支持重新协商
 - 本地目标消息格式: <timestamp> <seq_num> 12984 WARN Failed-Attempt: Unexpected renegotiation received. Renegotiation is not supported in EAP_TTLS, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12984 WARN Failed-Attempt: Unexpected renegotiation received. Renegotiation is not supported in EAP_TTLS, <log details>

- 消息代码: 12985
 - 严重性: 信息 (INFO)
 - 消息文本: 已准备包含其他 EAP-TTLS 质询的 EAP 请求 (Prepared EAP-Request with another EAP-TTLS challenge)
 - 消息说明: 为了继续使用 EAP-TTLS 协议, 已创建包含其他 EAP-TTLS 质询的 EAP 请求数据包, 用于附加到 RADIUS 消息。
 - 本地目标消息格式: <timestamp> <seq_num> 12985 INFO EAP: Prepared EAP-Request with another EAP-TTLS challenge, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12985 INFO EAP: Prepared EAP-Request with another EAP-TTLS challenge, <log details>

- 消息代码: 12986
 - 严重性: 警告 (WARN)
 - 消息文本: 客户端请求的 TLSv1.0 或 TLSv1.1 不被允许 (Client requested TLSv1.0 or TLSv1.1 that is not allowed)
 - 消息说明: 客户端请求 TLSv1.0 或 TLSv1.1 作为最高版本, 但安全设置不允许
 - 本地目标消息格式: <timestamp> <seq_num> 12986 WARN EAP: Client requested TLSv1.0 or TLSv1.1 that is not allowed, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12986 WARN EAP: Client requested TLSv1.0 or TLSv1.1 that is not allowed, <log details>

- 消息代码: 12987
 - 严重性: 信息 (INFO)
 - 消息文本: 从客户端证书的 AIA 扩展中获取 OCSP 服务器列表 (Take OCSP servers list from AIA extension of client certificate)
 - 消息说明: 从客户端证书的 AIA 扩展中获取 OCSP 服务器列表

本地目标消息格式: <timestamp> <seq_num> 12987 INFO EAP: Take OCSP servers list from AIA extension of client certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12987 INFO EAP: Take OCSP servers list from AIA extension of client certificate, <log details>

- 消息代码: 12988

严重性: 信息 (INFO)

消息文本: 从 OCSP 服务配置中获取 OCSP 服务器列表 (Take OCSP servers list from OCSP service configuration)

消息说明: 从 OCSP 服务配置中获取 OCSP 服务器列表

本地目标消息格式: <timestamp> <seq_num> 12988 INFO EAP: Take OCSP servers list from OCSP service configuration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12988 INFO EAP: Take OCSP servers list from OCSP service configuration, <log details>

- 消息代码: 12989

严重性: 信息 (INFO)

消息文本: 向列表中的下一个 OCSP 服务器发送了 OCSP 请求 (Sent an OCSP request to the next OCSP server in the list)

消息说明: 向列表中的下一个 OCSP 服务器发送了 OCSP 请求

本地目标消息格式: <timestamp> <seq_num> 12989 INFO EAP: Sent an OCSP request to the next OCSP server in the list, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12989 INFO EAP: Sent an OCSP request to the next OCSP server in the list, <log details>

- 消息代码: 12990

严重性: 警告 (WARN)

消息文本: 未在客户端证书的 AIA 扩展中找到有效的 OCSP 服务器 URL (No valid OCSP server URLs found in the AIA extension of client certificate)

消息说明: 如果 OCSP 服务配置为从客户端证书的 AIA 扩展中获取 OCSP 服务器列表, 那么必须至少存在一个有效的 OCSP 服务器 URL。

本地目标消息格式: <timestamp> <seq_num> 12990 WARN EAP: No valid OCSP server URLs found in the AIA extension of client certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12990 WARN EAP: No valid OCSP server URLs found in the AIA extension of client certificate, <log details>

- 消息代码: 12991
严重性: 信息 (INFO)
消息文本: 客户端证书的 AIA 扩展中不再有 OCSP 服务器 (No more OCSP servers in AIA estension of client certificate)
消息说明: 客户端证书的 AIA 扩展中不再有 OCSP 服务器
本地目标消息格式: <timestamp> <seq_num> 12991 INFO EAP: No more OCSP servers in AIA estension of client certificate, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12991 INFO EAP: No more OCSP servers in AIA estension of client certificate, <log details>
- 消息代码: 12992
严重性: 信息 (INFO)
消息文本: 客户端证书中没有 AIA 扩展 (No AIA extension in client certificate)
消息说明: 客户端证书中没有 AIA 扩展
本地目标消息格式: <timestamp> <seq_num> 12992 INFO EAP: No AIA extension in client certificate, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12992 INFO EAP: No AIA extension in client certificate, <log details>
- 消息代码: 12993
严重性: 警告 (WARN)
消息文本: 由于 OCSP 无法访问, 用户身份验证失败 (User Auth failed because OCSP is unreachable)
消息说明: 由于 OCSP 无法访问, 用户身份验证失败
本地目标消息格式: <timestamp> <seq_num> 12993 WARN EAP: User Auth failed because OCSP is unreachable, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12993 WARN EAP: User Auth failed because OCSP is unreachable, <log details>
- 消息代码: 12994
严重性: 警告 (WARN)
消息文本: EAP-TTLS 内部方法 CHAP 未在“允许的协议”中获得允许 (EAP-TTLS inner method CHAP is not allowed in Allowed Protocols)
消息说明: EAP-TTLS 内部方法 CHAP 未在“允许的协议”中获得允许
本地目标消息格式: <timestamp> <seq_num> 12994 WARN EAP: EAP-TTLS inner method CHAP is not allowed in Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12994 WARN EAP: EAP-TTLS inner method
CHAP is not allowed in Allowed Protocols, <log details>

- 消息代码: 12995

严重性: 警告 (WARN)

消息文本: EAP-TTLS 内部方法 MSCHAPv1 未在“允许的协议”中获得允许 (EAP-TTLS inner
method MSCHAPv1 is not allowed in Allowed Protocols)

消息说明: EAP-TTLS 内部方法 MSCHAPv1 未在“允许的协议”中获得允许

本地目标消息格式: <timestamp> <seq_num> 12995 WARN EAP: EAP-TTLS inner method
MSCHAPv1 is not allowed in Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12995 WARN EAP: EAP-TTLS inner method
MSCHAPv1 is not allowed in Allowed Protocols, <log details>

- 消息代码: 12996

严重性: 警告 (WARN)

消息文本: EAP-TTLS 内部方法 MSCHAPv2 未在“允许的协议”中获得允许 (EAP-TTLS inner
method MSCHAPv2 is not allowed in Allowed Protocols)

消息说明: EAP-TTLS 内部方法 MSCHAPv2 未在“允许的协议”中获得允许

本地目标消息格式: <timestamp> <seq_num> 12996 WARN EAP: EAP-TTLS inner method
MSCHAPv2 is not allowed in Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12996 WARN EAP: EAP-TTLS inner method
MSCHAPv2 is not allowed in Allowed Protocols, <log details>

- 消息代码: 12997

严重性: 警告 (WARN)

消息文本: EAP-TTLS 内部方法 PAP 未在“允许的协议”中获得允许 (EAP-TTLS inner method
PAP is not allowed in Allowed Protocols)

消息说明: EAP-TTLS 内部方法 PAP 未在“允许的协议”中获得允许

本地目标消息格式: <timestamp> <seq_num> 12997 WARN EAP: EAP-TTLS inner method PAP is
not allowed in Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 12997 WARN EAP: EAP-TTLS inner method
PAP is not allowed in Allowed Protocols, <log details>

- 消息代码: 12998

严重性: 警告 (WARN)

消息文本: 由于 EAP-MD5 未在“允许的协议”中的 EAP-TTLS 配置下获得允许, 因此无法为内部方法协商 EAP (Failed to negotiate EAP for inner method because EAP-MD5 not allowed under EAP-TTLS configuration in the Allowed Protocols)

消息说明: 客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前为内部方法提议的基于 EAP 的协议, 且请求改为使用 EAP-MD5。但是, EAP-MD5 未在“允许的协议”中的 EAP-TTLS 配置下获得 ISE 允许。

本地目标消息格式: <timestamp> <seq_num> 12998 WARN EAP: Failed to negotiate EAP for inner method because EAP-MD5 not allowed under EAP-TTLS configuration in the Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12998 WARN EAP: Failed to negotiate EAP for inner method because EAP-MD5 not allowed under EAP-TTLS configuration in the Allowed Protocols, <log details>

- 消息代码: 12999

严重性: 信息 (INFO)

消息文本: 提取的内部方法 EAP 响应/NAK 请求改为使用 EAP-MD5 (Extracted EAP-Response/NAK for inner method requesting to use EAP-MD5 instead)

消息说明: 从在外部 EAP 方法中遇到的 EAP 响应数据包中, 提取的 EAP 响应/NAK 数据包拒绝之前为内部方法提议的基于 EAP 的协议, 并根据客户端请求方的配置请求改为使用 EAP-MD5。

本地目标消息格式: <timestamp> <seq_num> 12999 INFO EAP: Extracted EAP-Response/NAK for inner method requesting to use EAP-MD5 instead, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 12999 INFO EAP: Extracted EAP-Response/NAK for inner method requesting to use EAP-MD5 instead, <log details>

- 消息代码: 11525

严重性: 信息 (INFO)

消息文本: 已向客户端发送 NDAC 身份验证 (Sent NDAC Authentication to client)

消息说明: 已向客户端发送 NDAC 身份验证。

本地目标消息格式: <timestamp> <seq_num> 11525 INFO EAP Sent NDAC Authentication to client, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 11525 INFO EAP Sent NDAC Authentication to client, <log details>

- 消息代码: 11526

严重性: 信息 (INFO)

消息文本: 已从客户端收到 NDAC 身份验证响应 (Received NDAC Authentication response from client)

消息说明：已从客户端收到 NDAC 身份验证响应。

本地目标消息格式：<timestamp> <seq_num>11526 INFO EAP Received NDAC Authentication response from client, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11526 INFO EAP Received NDAC Authentication response from client, <log details>

- 消息代码：11527

严重性：信息 (INFO)

消息文本：已成功完成 TEAP 隧道 PAC 调配/更新 (Successfully finished TEAP tunnel PAC provisioning/update)

消息说明：已成功完成 TEAP 隧道 PAC 调配或更新。

本地目标消息格式：<timestamp> <seq_num>11527 INFO EAP Successfully finished TEAP tunnel PAC provisioning/update, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11527 INFO EAP Successfully finished TEAP tunnel PAC provisioning/update, <log details>

- 消息代码：11528

严重性：信息 (INFO)

消息文本：已成功完成 TEAP 计算机 PAC 调配/更新 (Successfully finished TEAP machine PAC provisioning/update)

消息说明：已成功完成 TEAP 计算机 PAC 调配或更新。

本地目标消息格式：<timestamp> <seq_num>11528 INFO EAP Successfully finished TEAP machine PAC provisioning/update, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11528 INFO EAP Successfully finished TEAP machine PAC provisioning/update, <log details>

- 消息代码：11529

严重性：信息 (INFO)

消息文本：已成功完成 TEAP 用户授权 PAC 调配/更新 (Successfully finished TEAP user authorization PAC provisioning/update)

消息说明：已成功完成 TEAP 用户授权 PAC 调配或更新。

本地目标消息格式：<timestamp> <seq_num>11529 INFO EAP Successfully finished TEAP user authorization PAC provisioning/update, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11529 INFO EAP Successfully finished TEAP user authorization PAC provisioning/update, <log details>

- 消息代码: 11530
严重性: 信息 (INFO)
消息文本: 已成功完成 TEAP 计算机授权 PAC 调配/更新 (Successfully finished TEAP machine authorization PAC provisioning/update)
消息说明: 已成功完成 TEAP 计算机授权 PAC 调配或更新。
本地目标消息格式: <timestamp> <seq_num>11530 INFO EAP Successfully finished TEAP machine authorization PAC provisioning/update, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11530 INFO EAP Successfully finished TEAP machine authorization PAC provisioning/update, <log details>
- 消息代码: 11531
严重性: 信息 (INFO)
消息文本: 已成功完成 TEAP CTS PAC 调配/更新 (Successfully finished TEAP CTS PAC provisioning/update)
消息说明: 已成功完成 TEAP CTS PAC 调配或更新。
本地目标消息格式: <timestamp> <seq_num>11531 INFO EAP Successfully finished TEAP CTS PAC provisioning/update, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11531 INFO EAP Successfully finished TEAP CTS PAC provisioning/update, <log details>
- 消息代码: 11532
严重性: 信息 (INFO)
消息文本: 已成功完成 TEAP 终端安全评估 PAC 调配/更新 (Successfully finished TEAP posture PAC provisioning/update)
消息说明: 已成功完成 TEAP 终端安全评估 PAC 调配或更新。
本地目标消息格式: <timestamp> <seq_num>11532 INFO EAP Successfully finished TEAP posture PAC provisioning/update, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11532 INFO EAP Successfully finished TEAP posture PAC provisioning/update, <log details>
- 消息代码: 11533
严重性: 信息 (INFO)
消息文本: 已成功完成 TEAP PAC 调配/更新 (Successfully finished TEAP PAC provisioning/update)
消息说明: 已成功完成 TEAP PAC 调配/更新。
本地目标消息格式: <timestamp> <seq_num>11533 INFO EAP Successfully finished TEAP PAC provisioning/update, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11533 INFO EAP Successfully finished
TEAP PAC provisioning/update, <log details>

- 消息代码: 11534

严重性: 警告 (WARN)

消息文本: 此对话已请求一个隧道 PAC。(One Tunnel PAC has already been requested in this conversation.) 其他隧道 PAC 请求将被忽略

消息说明: 此对话已请求一个隧道 PAC。其他隧道 PAC 请求将被忽略

本地目标消息格式: <timestamp> <seq_num>11534 WARN EAP One Tunnel PAC has already been requested in this conversation. Another Tunnel PAC request will be ignored, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11534 WARN EAP One Tunnel PAC has already been requested in this conversation. Another Tunnel PAC request will be ignored, <log details>

- 消息代码: 11535

严重性: 警告 (WARN)

消息文本: 此对话已请求一个 CTS PAC。(One CTS PAC has already been requested in this conversation.) 其他隧道 PAC 请求将被忽略

消息说明: 此对话已请求一个 CTS PAC。其他隧道 PAC 请求将被忽略

本地目标消息格式: <timestamp> <seq_num>11535 WARN EAP One CTS PAC has already been requested in this conversation. Another Tunnel PAC request will be ignored, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11535 WARN EAP One CTS PAC has already been requested in this conversation. Another Tunnel PAC request will be ignored, <log details>

- 消息代码: 11536

严重性: 警告 (WARN)

消息文本: 此对话已请求一个隧道 PAC。(One Tunnel PAC has already been requested in this conversation.) 其他 CTS PAC 请求将被忽略

消息说明: 此对话已请求一个隧道 PAC。其他 CTS PAC 请求将被忽略

本地目标消息格式: <timestamp> <seq_num>11536 WARN EAP One Tunnel PAC has already been requested in this conversation. Another CTS PAC request will be ignored, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11536 WARN EAP One Tunnel PAC has already been requested in this conversation. Another CTS PAC request will be ignored, <log details>

- 消息代码: 11537

严重性: 警告 (WARN)

消息文本: 此对话已请求一个 CTS PAC。(One CTS PAC has already been requested in this conversation.) 其他 CTS PAC 请求将被忽略

消息说明: 此对话已请求一个 CTS PAC。其他 CTS PAC 请求将被忽略

本地目标消息格式: <timestamp> <seq_num>11537 WARN EAP One CTS PAC has already been requested in this conversation. Another CTS PAC request will be ignored, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11537 WARN EAP One CTS PAC has already been requested in this conversation. Another CTS PAC request will be ignored, <log details>

- 消息代码: 11538

严重性: 警告 (WARN)

消息文本: 此对话已请求一个计算机 PAC。(One Machine PAC has already been requested in this conversation.) 其他计算机 PAC 请求将被忽略

消息说明: 此对话已请求一个计算机 PAC。其他计算机 PAC 请求将被忽略

本地目标消息格式: <timestamp> <seq_num>11538 WARN EAP One Machine PAC has already been requested in this conversation. Another Machine PAC request will be ignored, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11538 WARN EAP One Machine PAC has already been requested in this conversation. Another Machine PAC request will be ignored, <log details>

- 消息代码: 11539

严重性: 警告 (WARN)

消息文本: 此会话已经请求了一个授权 PAC。(One Authorization PAC has already been requested in this conversation.) 其他授权 PAC 请求将被忽略

消息说明: 此会话已经请求了一个授权 PAC。其他授权 PAC 请求将被忽略

本地目标消息格式: <timestamp> <seq_num>11539 WARN EAP One Authorization PAC has already been requested in this conversation. Another Authorization PAC request will be ignored, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11539 WARN EAP One Authorization PAC has already been requested in this conversation. Another Authorization PAC request will be ignored, <log details>

- 消息代码: 11540

严重性: 警告 (WARN)

消息文本: 请求的 PAC 类型无效。(Invalid PAC type requested.) 忽略此请求

消息说明: 请求的 PAC 类型无效。忽略此请求

本地目标消息格式: <timestamp> <seq_num>11540 WARN EAP Invalid PAC type requested. Ignoring this request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11540 WARN EAP Invalid PAC type
requested. Ignoring this request, <log details>

- 消息代码: 11541

严重性: 信息 (INFO)

消息文本: 忽略请求方在回退以进行调配对话期间发送的 PAC (Ignore PAC send by supplicant during fallback to provisioning conversation)

消息说明: ISE 在无效的 PAC 上执行回退以进行调配。但是在此调配对话期间, 请求方重新发送了 PAC。ISE 会忽略此 PAC。

本地目标消息格式: <timestamp> <seq_num>11541 INFO EAP Ignore PAC send by supplicant during fallback to provisioning conversation, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11541 INFO EAP Ignore PAC send by
supplicant during fallback to provisioning conversation, <log details>

- 消息代码: 11542

严重性: 信息 (INFO)

消息文本: 由于相同类型的 PAC 已经用于跳过内部方法, 因此忽略用户授权 PAC 请求 (User Authorization PAC request ignored because PAC of the same type was already used to skip inner method)

消息说明: 由于相同类型的 PAC 已经用于跳过内部方法, 因此忽略用户授权 PAC 请求。只能在完整验证对话结束后提供授权 PAC。

本地目标消息格式: <timestamp> <seq_num>11542 INFO EAP User Authorization PAC request ignored because PAC of the same type was already used to skip inner method, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11542 INFO EAP User Authorization PAC
request ignored because PAC of the same type was already used to skip inner method, <log details>

- 消息代码: 11543

严重性: 信息 (INFO)

消息文本: 由于当前相同类型的 PAC 已经用于跳过内部方法, 因此忽略计算机授权 PAC 请求 (Ignore Machine Authorization PAC request because of current PAC of the same type was used to skip inner method)

消息说明: 由于当前相同类型的 PAC 已经用于跳过内部方法, 因此忽略计算机授权 PAC 请求。只能在完整验证对话结束后提供授权 PAC。

本地目标消息格式: <timestamp> <seq_num>11543 INFO EAP Ignore Machine Authorization PAC request because of current PAC of the same type was used to skip inner method, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11543 INFO EAP Ignore Machine
Authorization PAC request because of current PAC of the same type was used to skip inner method,
<log details>

- 消息代码: 11544
 - 严重性: 信息 (INFO)
 - 消息文本: 在没有任何 EAP 链接时, 忽略计算机授权 PAC 请求 (Ignore Machine Authorization PAC request when there is no EAP chaining)
 - 消息说明: 当对话中没有发生任何 EAP 链接时, ISE 会忽略计算机授权 PAC 请求。计算机授权 PAC 只能在 EAP 链接对话过程中提供。请注意, EAP 链接可以在 ISE 中配置, 但在客户端中被禁用或不受支持, 因此, 对话是在无链模式下进行的。
 - 本地目标消息格式: <timestamp> <seq_num>11544 INFO EAP Ignore Machine Authorization PAC request when there is no EAP chaining, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11544 INFO EAP Ignore Machine Authorization PAC request when there is no EAP chaining, <log details>

- 消息代码: 11545
 - 严重性: 警告 (WARN)
 - 消息文本: 计算机身份验证已禁用 (Machine Authentication is disabled)
 - 消息说明: TEAP 身份验证失败, 因为计算机身份验证已禁用。
 - 本地目标消息格式: <timestamp> <seq_num>11545 WARN EAP Machine Authentication is disabled, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11545 WARN EAP Machine Authentication is disabled, <log details>

- 消息代码: 11546
 - 严重性: 信息 (INFO)
 - 消息文本: “允许的协议” 不允许无状态会话恢复; 正执行完整身份验证 (Allowed Protocols does not allow Stateless Session Resume; performing full authentication)
 - 消息说明: “允许的协议” 配置不允许无状态会话恢复; 正执行完整身份验证。
 - 本地目标消息格式: <timestamp> <seq_num>11546 INFO EAP Allowed Protocols does not allow Stateless Session Resume; performing full authentication, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11546 INFO EAP Allowed Protocols does not allow Stateless Session Resume; performing full authentication, <log details>

- 消息代码: 11547
 - 严重性: 警告 (WARN)
 - 消息文本: 无法在匿名调配中调配计算机 PAC。(Cannot provision Machine PAC on anonymous provisioning.) 只能在经过验证的调配中调配计算机 PAC
 - 消息说明: 无法在匿名调配中调配计算机 PAC。只能在经过验证的调配中调配计算机 PAC

本地目标消息格式: <timestamp> <seq_num>11547 WARN EAP Cannot provision Machine PAC on anonymous provisioning. Machine PAC can be provisioned only on authenticated provisioning, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11547 WARN EAP Cannot provision Machine PAC on anonymous provisioning. Machine PAC can be provisioned only on authenticated provisioning, <log details>

- 消息代码: 11548

严重性: 警告 (WARN)

消息文本: 当无状态会话恢复功能被禁用时, 无法调配授权 PAC (Cannot provision Authorization PAC when the stateless session resume is disabled)

消息说明: 当无状态会话恢复功能被禁用时, 无法调配授权 PAC。在服务设置中启用无状态会话恢复, 以允许授权 PAC 调配

本地目标消息格式: <timestamp> <seq_num>11548 WARN EAP Cannot provision Authorization PAC when the stateless session resume is disabled, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11548 WARN EAP Cannot provision Authorization PAC when the stateless session resume is disabled, <log details>

- 消息代码: 11549

严重性: 警告 (WARN)

消息文本: 无法在匿名调配中调配授权 PAC。(Cannot provision Authorization PAC on anonymous provisioning.) 只能在经过验证的调配中调配授权 PAC

消息说明: 无法在匿名调配中调配授权 PAC。只能在经过验证的调配中调配授权 PAC

本地目标消息格式: <timestamp> <seq_num>11549 WARN EAP Cannot provision Authorization PAC on anonymous provisioning. Authorization PAC can be provisioned only on authenticated provisioning, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11549 WARN EAP Cannot provision Authorization PAC on anonymous provisioning. Authorization PAC can be provisioned only on authenticated provisioning, <log details>

- 消息代码: 11550

严重性: 警告 (WARN)

消息文本: 授权 PAC 只能与隧道 PAC 一起提供 (Authorization PAC can be provided only with Tunnel PAC)

消息说明: 授权 PAC 只能与隧道 PAC 一起提供

本地目标消息格式: <timestamp> <seq_num>11550 WARN EAP Authorization PAC can be provided only with Tunnel PAC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11550 WARN EAP Authorization PAC can
be provided only with Tunnel PAC, <log details>

- 消息代码: 11551

严重性: 警告 (WARN)

消息文本: 授权 PAC I-ID 与用户身份不匹配。(Authorization PAC I-ID does not match user identity.)
忽略此授权 PAC 请求

消息说明: 授权 PAC I-ID 与用户身份不匹配。忽略此授权 PAC 请求

本地目标消息格式: <timestamp> <seq_num>11551 WARN EAP Authorization PAC I-ID does not
match user identity. Ignoring this Authorization PAC request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11551 WARN EAP Authorization PAC I-ID
does not match user identity. Ignoring this Authorization PAC request, <log details>

- 消息代码: 11552

严重性: 警告 (WARN)

消息文本: 计算机 PAC 请求不包含 I-ID。(Machine PAC request does not contain I-ID.) 忽略此计
算机 PAC 请求

消息说明: 计算机 PAC 请求不包含 I-ID。忽略此计算机 PAC 请求

本地目标消息格式: <timestamp> <seq_num>11552 WARN EAP Machine PAC request does not
contain I-ID. Ignoring this Machine PAC request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11552 WARN EAP Machine PAC request
does not contain I-ID. Ignoring this Machine PAC request, <log details>

- 消息代码: 11553

严重性: 警告 (WARN)

消息文本: 拒绝用户授权 PAC, 原因是它的发起方 ID 与隧道 PAC 发起方 ID 不匹配 (Reject User
Authorization PAC since its Initiator-ID does not match the Tunnel PAC Initiator-ID)

消息说明: 拒绝用户授权 PAC, 原因是它的发起方 ID 与隧道 PAC 发起方 ID 不匹配

本地目标消息格式: <timestamp> <seq_num>11553 WARN RADIUS Reject User Authorization PAC
since its Initiator-ID does not match the Tunnel PAC Initiator-ID, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11553 WARN RADIUS Reject User
Authorization PAC since its Initiator-ID does not match the Tunnel PAC Initiator-ID, <log details>

- 消息代码: 11554

严重性: 信息 (INFO)

消息文本: 已收到授权 PAC (Received Authorization PAC)

消息说明: 已从客户端收到授权 PAC。

本地目标消息格式: <timestamp> <seq_num>11554 INFO EAP Received Authorization PAC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11554 INFO EAP Received Authorization PAC, <log details>

- 消息代码: 11555

严重性: 信息 (INFO)

消息文本: 已收到用户授权 PAC (Received User Authorization PAC)

消息说明: 已从客户端收到用户授权 PAC。

本地目标消息格式: <timestamp> <seq_num>11555 INFO EAP Received User Authorization PAC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11555 INFO EAP Received User Authorization PAC, <log details>

- 消息代码: 11556

严重性: 信息 (INFO)

消息文本: 已收到计算机授权 PAC (Received Machine Authorization PAC)

消息说明: 已从客户端收到计算机授权 PAC。

本地目标消息格式: <timestamp> <seq_num>11556 INFO EAP Received Machine Authorization PAC, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11556 INFO EAP Received Machine Authorization PAC, <log details>

- 消息代码: 11557

严重性: 信息 (INFO)

消息文本: 正使用客户端证书进行身份验证 (Using client certificate for authentication)

消息说明: ISE 在隧道建立期间或在隧道中收到客户端证书。ISE 将验证此证书并用其进行身份验证。

本地目标消息格式: <timestamp> <seq_num>11557 INFO EAP Using client certificate for authentication, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11557 INFO EAP Using client certificate for authentication, <log details>

- 消息代码: 11558
严重性: 信息 (INFO)
消息文本: 已在隧道中收到客户端证书 (Client certificate was received inside the tunnel)
消息说明: 请求方在隧道中提供了客户端证书 (证书在加密的情况下发送)
本地目标消息格式: <timestamp> <seq_num>11558 INFO EAP Client certificate was received inside the tunnel, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11558 INFO EAP Client certificate was received inside the tunnel, <log details>
- 消息代码: 11559
严重性: 信息 (INFO)
消息文本: 已请求客户端证书, 但未在隧道中收到。(Client certificate was requested but not received inside the tunnel.) 将继续使用内部方法。
消息说明: ISE 在隧道中请求客户端证书, 但请求方未提供该客户端证书。ISE 将继续运行内部方法来验证请求方身份。
本地目标消息格式: <timestamp> <seq_num>11559 INFO EAP Client certificate was requested but not received inside the tunnel. Will continue with inner method., <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11559 INFO EAP Client certificate was requested but not received inside the tunnel. Will continue with inner method., <log details>
- 消息代码: 11560
严重性: 信息 (INFO)
消息文本: 已在隧道建立期间收到客户端证书 (Client certificate was received during tunnel establishment)
消息说明: 请求方在隧道建立期间提供了客户端证书 (证书在未加密的情况下发送)
本地目标消息格式: <timestamp> <seq_num>11560 INFO EAP Client certificate was received during tunnel establishment, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11560 INFO EAP Client certificate was received during tunnel establishment, <log details>
- 消息代码: 11561
严重性: 信息 (INFO)
消息文本: 已请求客户端证书, 但未在隧道建立期间收到。(Client certificate was requested but not received during tunnel establishment.) 将重新协商, 并在隧道内部请求客户端证书。
消息说明: ISE 在隧道建立期间请求客户端证书, 但请求方未提供该客户端证书。请求方可能配置为只在加密的情况下才发送客户端证书。ISE 将重新协商, 并在隧道内部请求客户端证书。

本地目标消息格式: <timestamp> <seq_num>11561 INFO EAP Client certificate was requested but not received during tunnel establishment. Will renegotiate and request client certificate inside the tunnel., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11561 INFO EAP Client certificate was requested but not received during tunnel establishment. Will renegotiate and request client certificate inside the tunnel., <log details>

- 消息代码: 11562

严重性: 信息 (INFO)

消息文本: 已收到客户端证书, 但身份验证失败 (Client certificate was received but authentication failed)

消息说明: ISE 在隧道建立期间或在隧道中收到客户端证书, 但身份验证失败。

本地目标消息格式: <timestamp> <seq_num>11562 INFO EAP Client certificate was received but authentication failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11562 INFO EAP Client certificate was received but authentication failed, <log details>

- 消息代码: 11563

严重性: 信息 (INFO)

消息文本: 已跳过 TEAP 内部方法 (TEAP inner method skipped)

消息说明: 已跳过 TEAP 内部方法。

本地目标消息格式: <timestamp> <seq_num>11563 INFO EAP TEAP inner method skipped, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11563 INFO EAP TEAP inner method skipped, <log details>

- 消息代码: 11564

严重性: 信息 (INFO)

消息文本: 已开始 TEAP 内部方法 (TEAP inner method started)

消息说明: 已开始 TEAP 内部方法。

本地目标消息格式: <timestamp> <seq_num>11564 INFO EAP TEAP inner method started, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11564 INFO EAP TEAP inner method started, <log details>

- 消息代码: 11565

严重性: 信息 (INFO)

消息文本: TEAP 内部方法成功完成 (TEAP inner method finished successfully)

消息说明: TEAP 内部方法成功完成。

本地目标消息格式: <timestamp> <seq_num>11565 INFO EAP TEAP inner method finished successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11565 INFO EAP TEAP inner method finished successfully, <log details>

- 消息代码: 11566

严重性: 警告 (WARN)

消息文本: TEAP 内部方法以失败告终 (TEAP inner method finished with failure)

消息说明: TEAP 内部方法以失败告终。

本地目标消息格式: <timestamp> <seq_num>11566 WARN EAP TEAP inner method finished with failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11566 WARN EAP TEAP inner method finished with failure, <log details>

- 消息代码: 11567

严重性: 信息 (INFO)

消息文本: 客户端提供的身份类型等同于请求的身份类型 (Identity type provided by client is equal to requested)

消息说明: ISE 从客户端为当前的内部方法请求了特定的身份类型, 且客户端确认使用此身份类型。

本地目标消息格式: <timestamp> <seq_num>11567 INFO EAP Identity type provided by client is equal to requested, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11567 INFO EAP Identity type provided by client is equal to requested, <log details>

- 消息代码: 11568

严重性: 信息 (INFO)

消息文本: 客户端提供的身份类型不等同于请求的身份类型 (Identity type provided by client is not equal to requested type)

消息说明: ISE 从客户端为当前的内部方法请求了特定的身份类型, 且客户端拒绝使用此身份类型。

本地目标消息格式: <timestamp> <seq_num>11568 INFO EAP Identity type provided by client is not equal to requested type, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11568 INFO EAP Identity type provided by
client is not equal to requested type, <log details>

- 消息代码: 11569

严重性: 信息 (INFO)

消息文本: 客户端建议改用“用户”身份类型 (Client suggested 'User' identity type instead)

消息说明: 客户端建议在当前的内部方法中使用“用户”身份类型。

本地目标消息格式: <timestamp> <seq_num>11569 INFO EAP Client suggested 'User' identity type
instead, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11569 INFO EAP Client suggested 'User'
identity type instead, <log details>

- 消息代码: 11570

严重性: 信息 (INFO)

消息文本: 客户端建议改用“计算机”身份类型 (Client suggested 'Machine' identity type instead)

消息说明: 客户端建议在当前的内部方法中使用“计算机”身份类型。

本地目标消息格式: <timestamp> <seq_num>11570 INFO EAP Client suggested 'Machine' identity
type instead, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11570 INFO EAP Client suggested 'Machine'
identity type instead, <log details>

- 消息代码: 11571

严重性: 信息 (INFO)

消息文本: 客户端提供的身份类型已经用于身份验证 (Identity type provided by client was already
used for authentication)

消息说明: 客户端建议在当前的内部方法中使用之前的内部方法中已经用过的身份类型。ISE
拒绝此身份类型。

本地目标消息格式: <timestamp> <seq_num>11571 INFO EAP Identity type provided by client was
already used for authentication, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11571 INFO EAP Identity type provided by
client was already used for authentication, <log details>

- 消息代码: 11572

严重性: 信息 (INFO)

消息文本: 客户端提供的身份类型当前不受支持 (Identity type provided by client is currently
unsupported)

消息说明：客户端建议在当前的内部方法中使用 ISE 不支持的身份类型。ISE 拒绝此身份类型。

本地目标消息格式：<timestamp> <seq_num>11572 INFO EAP Identity type provided by client is currently unsupported, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>11572 INFO EAP Identity type provided by client is currently unsupported, <log details>

- 消息代码：11573

严重性：信息 (INFO)

消息文本：已选择“用户”身份类型 (Selected identity type 'User')

消息说明：ISE 选择在当前的内部方法中使用“用户”身份类型。

本地目标消息格式：<timestamp> <seq_num>11573 INFO EAP Selected identity type 'User', <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>11573 INFO EAP Selected identity type 'User', <log details>

- 消息代码：11574

严重性：信息 (INFO)

消息文本：已选择“计算机”身份类型 (Selected identity type 'Machine')

消息说明：ISE 选择在当前的内部方法中使用“计算机”身份类型。

本地目标消息格式：<timestamp> <seq_num>11574 INFO EAP Selected identity type 'Machine', <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>11574 INFO EAP Selected identity type 'Machine', <log details>

- 消息代码：11575

严重性：信息 (INFO)

消息文本：客户端不支持 EAP 链接。(Client does not support EAP chaining.) 切换到普通模式

消息说明：ISE 向客户端发送 EAP-Request 中的身份类型 TLV，以执行 EP 链接。但是，客户端响应中没有身份类型 TLV。因此，客户端不支持 EAP 链接。ISE 正切换到普通模式。

本地目标消息格式：<timestamp> <seq_num>11575 INFO EAP Client does not support EAP chaining. Switching to usual mode, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>11575 INFO EAP Client does not support EAP chaining. Switching to usual mode, <log details>

- 消息代码：11576

严重性: 调试 (DEBUG)

消息文本: TEAP 加密绑定验证通过 (TEAP cryptobinding verification passed)

消息说明: TEAP 加密绑定验证通过。

本地目标消息格式: <timestamp> <seq_num>11576 DEBUG EAP TEAP cryptobinding verification passed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11576 DEBUG EAP TEAP cryptobinding verification passed, <log details>

• 消息代码: 11577

严重性: 警告 (WARN)

消息文本: TEAP 加密绑定验证失败 (TEAP cryptobinding verification failed)

消息说明: TEAP 加密绑定验证失败。

本地目标消息格式: <timestamp> <seq_num>11577 WARN EAP TEAP cryptobinding verification failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11577 WARN EAP TEAP cryptobinding verification failed, <log details>

• 消息代码: 11578

严重性: 警告 (WARN)

消息文本: PAC 调配请求遭拒, 因为请求方未能遵守协议 (Rejected PAC provisioning request because supplicant failed to adhere to protocol)

消息说明: 由于客户端的请求方未能正确遵守 TEAP 协议, 因此 PAC 调配请求遭拒。它不仅未能向接近完成调配的 PAC 发送 ACK, 而且未能向隧道 PAC 或计算机 PAC 发送有效的其他请求以继续进行调配。

本地目标消息格式: <timestamp> <seq_num>11578 WARN EAP Rejected PAC provisioning request because supplicant failed to adhere to protocol, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11578 WARN EAP Rejected PAC provisioning request because supplicant failed to adhere to protocol, <log details>

• 消息代码: 11579

严重性: 警告 (WARN)

消息文本: 没有跟调配有关的有效 PAC 请求 (No valid PAC requests on provisioning)

消息说明: 客户端未在 TEAP 调配对话结束时发送有效的 PAC 请求。应始终在调配对话结束时向客户端发送所请求的一个或多个 PAC。由于在 TEAP 协议的初始草稿中只有一个 PAC 类型, 并且没必要指定此类型, 因此, 旧客户端可能不请求特定的 PAC。在这种情况下, ISE 会提供

旧的隧道 V1 PAC。更高级的客户端可能会请求多个 PAC 类型，但它们需要符合特定的规则。例如，如果未请求隧道 PAC，ISE 就不能提供用户授权 PAC。

本地目标消息格式: <timestamp> <seq_num>11579 WARN EAP No valid PAC requests on provisioning, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11579 WARN EAP No valid PAC requests on provisioning, <log details>

- 消息代码: 11580

严重性: 警告 (WARN)

消息文本: 在 TEAP 的无 PAC 模式中，意外收到被拒绝的 PAC (Rejected PAC unexpectedly received during PAC-less mode of TEAP)

消息说明: 尽管“允许的协议”已经配置 TEAP 来使用无 PAC 的操作模式，但客户端的请求方向 ISE 发送了 PAC，就好像正在使用基于 PAC 的模式一样。

本地目标消息格式: <timestamp> <seq_num>11580 WARN EAP Rejected PAC unexpectedly received during PAC-less mode of TEAP, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11580 WARN EAP Rejected PAC unexpectedly received during PAC-less mode of TEAP, <log details>

- 消息代码: 11581

严重性: 信息 (INFO)

消息文本: 在无效的 PAC 上执行回退以进行调配 (Perform fallback on invalid PAC to provisioning)

消息说明: ISE 在身份验证过程中收到无效的 PAC，且执行回退以进行 PAC 调配。

本地目标消息格式: <timestamp> <seq_num>11581 INFO EAP Perform fallback on invalid PAC to provisioning, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11581 INFO EAP Perform fallback on invalid PAC to provisioning, <log details>

- 消息代码: 11582

严重性: 信息 (INFO)

消息文本: 已批准 TEAP 客户端隧道 PAC 请求 (Approved TEAP client Tunnel PAC request)

消息说明: 已批准客户端请求方调配隧道 PAC 的 TEAP 请求。

本地目标消息格式: <timestamp> <seq_num>11582 INFO EAP Approved TEAP client Tunnel PAC request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11582 INFO EAP Approved TEAP client Tunnel PAC request, <log details>

- 消息代码: 11583
严重性: 信息 (INFO)
消息文本: 已批准 TEAP 客户端计算机 PAC 请求 (Approved TEAP client Machine PAC request)
消息说明: 已批准客户端请求方调配计算机 PAC 的 TEAP 请求。
本地目标消息格式: <timestamp> <seq_num>11583 INFO EAP Approved TEAP client Machine PAC request, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11583 INFO EAP Approved TEAP client Machine PAC request, <log details>
- 消息代码: 11584
严重性: 信息 (INFO)
消息文本: 已批准 TEAP 客户端授权 PAC 请求 (Approved TEAP client Authorization PAC request)
消息说明: 已批准客户端请求方调配授权 PAC 的 TEAP 请求。
本地目标消息格式: <timestamp> <seq_num>11584 INFO EAP Approved TEAP client Authorization PAC request, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11584 INFO EAP Approved TEAP client Authorization PAC request, <log details>
- 消息代码: 11585
严重性: 信息 (INFO)
消息文本: 收到隧道 PAC (Received Tunnel PAC)
消息说明: 从客户端收到隧道 PAC。
本地目标消息格式: <timestamp> <seq_num>11585 INFO EAP Received Tunnel PAC, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11585 INFO EAP Received Tunnel PAC, <log details>
- 消息代码: 11586
严重性: 信息 (INFO)
消息文本: 收到计算机 PAC (Received Machine PAC)
消息说明: 从客户端收到计算机 PAC。
本地目标消息格式: <timestamp> <seq_num>11586 INFO EAP Received Machine PAC, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11586 INFO EAP Received Machine PAC, <log details>

- 消息代码: 11587
严重性: 信息 (INFO)
消息文本: 收到 CTS PAC (Received CTS PAC)
消息说明: 从客户端收到 CTS PAC
本地目标消息格式: <timestamp> <seq_num>11587 INFO EAP Received CTS PAC, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11587 INFO EAP Received CTS PAC, <log details>
- 消息代码: 11588
严重性: 警告 (WARN)
消息文本: 请求方未能遵守协议 (Supplicant failed to adhere to protocol)
消息说明: 客户端的请求方未能正确遵守 TEAP 协议。它未能发送正确的结果 Tlv。
本地目标消息格式: <timestamp> <seq_num>11588 WARN EAP Supplicant failed to adhere to protocol, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11588 WARN EAP Supplicant failed to adhere to protocol, <log details>
- 消息代码: 11589
严重性: 信息 (INFO)
消息文本: 匿名 TLS 重新协商成功 (Anonymous TLS renegotiation succeeded)
消息说明: TEAP 匿名 TLS 重新协商成功完成
本地目标消息格式: <timestamp> <seq_num>11589 INFO EAP Anonymous TLS renegotiation succeeded, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11589 INFO EAP Anonymous TLS renegotiation succeeded, <log details>
- 消息代码: 11590
严重性: 警告 (WARN)
消息文本: 匿名 TLS 重新协商失败 (Anonymous TLS renegotiation failed)
消息说明: 匿名 TLS 重新协商失败。
本地目标消息格式: <timestamp> <seq_num>11590 WARN EAP Anonymous TLS renegotiation failed, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11590 WARN EAP Anonymous TLS renegotiation failed, <log details>

- 消息代码: 11591
严重性: 信息 (INFO)
消息文本: 在经过验证的调配时接受客户端 (Accept client on authenticated provisioning)
消息说明: 在经过验证的调配时接受客户端
本地目标消息格式: <timestamp> <seq_num>11591 INFO EAP Accept client on authenticated provisioning, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11591 INFO EAP Accept client on authenticated provisioning, <log details>
- 消息代码: 11592
严重性: 信息 (INFO)
消息文本: 已于带内 PAC 调配成功后准备好“RADIUS 访问-拒绝”(Prepared RADIUS Access-Reject after the successful in-band PAC provisioning)
消息说明: 作为标准带内 PAC 调配行为的一部分, 即使 PAC 请求成功获得批准, 系统也会返回“EAP-失败”和“RADIUS 访问-拒绝”结果。很明显, 这是误导性的结果值, 但这是正常的, 它不表示真正失败, 您可以/应该忽略它, 不会出现安全问题。(当用户尝试使用当前调配的 PAC 实际进行身份验证时, ISE 日志很可能随之显示 EAP 对话。)
本地目标消息格式: <timestamp> <seq_num>11592 INFO EAP Prepared RADIUS Access-Reject after the successful in-band PAC provisioning, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11592 INFO EAP Prepared RADIUS Access-Reject after the successful in-band PAC provisioning, <log details>
- 消息代码: 11593
严重性: 警告 (WARN)
消息文本: TEAP 调配失败。(TEAP provisioning failed.) 常见错误
消息说明: TEAP 调配失败。无法建立安全隧道。
本地目标消息格式: <timestamp> <seq_num>11593 WARN EAP TEAP provisioning failed. General error, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11593 WARN EAP TEAP provisioning failed. General error, <log details>
- 消息代码: 11594
严重性: 警告 (WARN)
消息文本: 客户端证书身份验证失败 (Client certificate authentication failed)
消息说明: 客户端证书身份验证失败

本地目标消息格式: <timestamp> <seq_num>11594 WARN EAP Client certificate authentication failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11594 WARN EAP Client certificate authentication failed, <log details>

- 消息代码: 11595

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应包含 TEAP 质询-响应 (Extracted EAP-Response containing TEAP challenge-response)

消息说明: 继续使用 TEAP 协议; 处理已提取的 EAP 响应中的 TEAP 质询-响应。

本地目标消息格式: <timestamp> <seq_num>11595 INFO EAP Extracted EAP-Response containing TEAP challenge-response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11595 INFO EAP Extracted EAP-Response containing TEAP challenge-response, <log details>

- 消息代码: 11596

严重性: 信息 (INFO)

消息文本: 已准备包含其他 TEAP 质询的 EAP 请求 (Prepared EAP-Request with another TEAP challenge)

消息说明: 为了继续使用 TEAP 协议, 已创建包含其他 TEAP 质询的 EAP 请求数据包, 用于附加到 RADIUS 消息。

本地目标消息格式: <timestamp> <seq_num>11596 INFO EAP Prepared EAP-Request with another TEAP challenge, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11596 INFO EAP Prepared EAP-Request with another TEAP challenge, <log details>

- 消息代码: 11597

严重性: 信息 (INFO)

消息文本: TEAP 身份验证阶段成功完成 (TEAP authentication phase finished successfully)

消息说明: TEAP 身份验证阶段成功完成。

本地目标消息格式: <timestamp> <seq_num>11597 INFO EAP TEAP authentication phase finished successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11597 INFO EAP TEAP authentication phase finished successfully, <log details>

- 消息代码: 11598

严重性: 警告 (WARN)

消息文本: TEAP 身份验证失败 (TEAP authentication failed)

消息说明: TEAP 身份验证失败。

本地目标消息格式: <timestamp> <seq_num>11598 WARN EAP TEAP authentication failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11598 WARN EAP TEAP authentication failed, <log details>

• 消息代码: 11599

严重性: 信息 (INFO)

消息文本: TEAP 调配阶段成功完成 (TEAP provisioning phase finished successfully)

消息说明: TEAP 调配阶段成功完成。

本地目标消息格式: <timestamp> <seq_num>11599 INFO EAP TEAP provisioning phase finished successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11599 INFO EAP TEAP provisioning phase finished successfully, <log details>

• 消息代码: 11600

严重性: 信息 (INFO)

消息文本: TEAP 调配阶段完成 (TEAP provisioning phase finished)

消息说明: 已完成 TEAP PAC 调配阶段。根据标准, 即使 PAC 请求成功获得批准, 也将返回“EAP-失败”和“RADIUS 访问-拒绝”结果。因此, 需要检查 PAC 是否确实出现问题。

本地目标消息格式: <timestamp> <seq_num>11600 INFO EAP TEAP provisioning phase finished, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11600 INFO EAP TEAP provisioning phase finished, <log details>

• 消息代码: 11601

严重性: 警告 (WARN)

消息文本: TEAP 进行 SSL/TLS 握手失败, 因为客户端拒绝 ISE 本地证书 (TEAP failed SSL/TLS handshake because the client rejected the ISE local-certificate)

消息说明: TEAP 进行 SSL/TLS 握手失败, 因为客户端拒绝 ISE 本地证书

本地目标消息格式: <timestamp> <seq_num>11601 WARN EAP TEAP failed SSL/TLS handshake because the client rejected the ISE local-certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11601 WARN EAP TEAP failed SSL/TLS
handshake because the client rejected the ISE local-certificate, <log details>

- 消息代码: 11602

严重性: 警告 (WARN)

消息文本: 在客户端发出警报后, TEAP 进行 SSL/TLS 握手失败 (TEAP failed SSL/TLS handshake after a client alert)

消息说明: 在客户端发出警报后, TEAP 进行 SSL/TLS 握手失败

本地目标消息格式: <timestamp> <seq_num>11602 WARN EAP TEAP failed SSL/TLS handshake after a client alert, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11602 WARN EAP TEAP failed SSL/TLS
handshake after a client alert, <log details>

- 消息代码: 11603

严重性: 警告 (WARN)

消息文本: PAC 验证失败 (PAC verification failed)

消息说明: 从客户端收到未能通过验证的 PAC。

本地目标消息格式: <timestamp> <seq_num>11603 WARN EAP PAC verification failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11603 WARN EAP PAC verification failed,
<log details>

- 消息代码: 11604

严重性: 警告 (WARN)

消息文本: PAC 包含无效的授权 ID (PAC contains invalid Authority ID)

消息说明: 客户端 PAC 的授权 ID 与处理身份验证请求的 ISE 服务器的授权 ID 不匹配, 这可能是因为客户端的 PAC 是由另一个 ISE 创建的。

本地目标消息格式: <timestamp> <seq_num>11604 WARN EAP PAC contains invalid Authority ID, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11604 WARN EAP PAC contains invalid
Authority ID, <log details>

- 消息代码: 11605

严重性: 警告 (WARN)

消息文本: PAC 包含无效的 PAC 类型 (PAC contains invalid PAC type)

消息说明: 从客户端收到包含无效 PAC 类型的 PAC。

本地目标消息格式: <timestamp> <seq_num>11605 WARN EAP PAC contains invalid PAC type, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11605 WARN EAP PAC contains invalid PAC type, <log details>

- 消息代码: 11606

严重性: 警告 (WARN)

消息文本: PAC 已过期 - 拒绝此 PAC

消息说明: 从客户端收到已过期的 PAC。拒绝此 PAC。

本地目标消息格式: <timestamp> <seq_num>11606 WARN EAP PAC has expired - rejecting it, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11606 WARN EAP PAC has expired - rejecting it, <log details>

- 消息代码: 11607

严重性: 信息 (INFO)

消息文本: 用户授权 PAC 已过期 - 将运行内部方法 (User Authorization PAC has expired - will run inner method)

消息说明: 从客户端收到已过期的用户授权 PAC。已过期的授权 PAC 不能用于快速重新连接, 因此, ISE 将运行内部方法验证用户身份。

本地目标消息格式: <timestamp> <seq_num>11607 INFO EAP User Authorization PAC has expired - will run inner method, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11607 INFO EAP User Authorization PAC has expired - will run inner method, <log details>

- 消息代码: 11608

严重性: 信息 (INFO)

消息文本: 计算机授权 PAC 已过期 - 将运行内部方法 (Machine Authorization PAC has expired - will run inner method)

消息说明: 从客户端收到已过期的计算机授权 PAC。已过期的授权 PAC 不能用于快速重新连接, 因此, ISE 将运行内部方法验证计算机身份。

本地目标消息格式: <timestamp> <seq_num>11608 INFO EAP Machine Authorization PAC has expired - will run inner method, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11608 INFO EAP Machine Authorization PAC has expired - will run inner method, <log details>

- 消息代码: 11609
 - 严重性: 警告 (WARN)
 - 消息文本: 由于未找到指定的主密钥, 因此无法解密 PAC - 拒绝 PAC (Cannot decrypt PAC because of specified master key was not found - rejecting the PAC)
 - 消息说明: 从客户端收到由于未找到指定的主密钥, 因此无法解密 PAC 的消息。拒绝此 PAC。
 - 本地目标消息格式: <timestamp> <seq_num>11609 WARN EAP Cannot decrypt PAC because of specified master key was not found - rejecting the PAC, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11609 WARN EAP Cannot decrypt PAC because of specified master key was not found - rejecting the PAC, <log details>

- 消息代码: 11610
 - 严重性: 警告 (WARN)
 - 消息文本: PAC 包含无效的身份验证标签 (PAC contains invalid Authentication Tag)
 - 消息说明: 从客户端收到包含无效身份验证标签的 PAC。
 - 本地目标消息格式: <timestamp> <seq_num>11610 WARN EAP PAC contains invalid Authentication Tag, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11610 WARN EAP PAC contains invalid Authentication Tag, <log details>

- 消息代码: 11611
 - 严重性: 警告 (WARN)
 - 消息文本: 未能解密 PAC (Failed to decrypt PAC)
 - 消息说明: 未能解密从客户端的请求方收到的 PAC。
 - 本地目标消息格式: <timestamp> <seq_num>11611 WARN EAP Failed to decrypt PAC, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11611 WARN EAP Failed to decrypt PAC, <log details>

- 消息代码: 11612
 - 严重性: 警告 (WARN)
 - 消息文本: 未能派生 TEAP 主密钥 (Failed to derive TEAP Master Key)
 - 消息说明: 未能派生 TEAP 主密钥。
 - 本地目标消息格式: <timestamp> <seq_num>11612 WARN EAP Failed to derive TEAP Master Key, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11612 WARN EAP Failed to derive TEAP
Master Key, <log details>

- 消息代码: 11613

严重性: 警告 (WARN)

消息文本: 在无效 PAC 上回退: 服务器上未配置可用的其他密码 (Fallback on invalid PAC: no
available additional cipher configured on server)

消息说明: 在无效 PAC 上回退: 服务器上未配置可用的其他密码。

本地目标消息格式: <timestamp> <seq_num>11613 WARN EAP Fallback on invalid PAC: no available
additional cipher configured on server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11613 WARN EAP Fallback on invalid PAC:
no available additional cipher configured on server, <log details>

- 消息代码: 11614

严重性: 警告 (WARN)

消息文本: 无法执行多个无效的 PAC 回退 (Cannot perform more then one invalid PAC fallback)

消息说明: 客户端的请求方似乎出现内部问题, 正在一次 TEAP 对话过程中不正确地尝试多次
发送无效 PAC。

本地目标消息格式: <timestamp> <seq_num>11614 WARN EAP Cannot perform more then one
invalid PAC fallback, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11614 WARN EAP Cannot perform more
then one invalid PAC fallback, <log details>

- 消息代码: 11615

严重性: 警告 (WARN)

消息文本: 客户端侧没有用于无效 PAC 回退的密码 (No cipher on client side for invalid PAC
fallback)

消息说明: 由于客户端的请求方建议的任何密码套件都与无效的 PAC 回退不兼容, 因此 ISE 无
法完成 TLS 握手。这可能是由手动调配的 PAC 不再有效, 并且“允许的协议”中的配置不允
许使用客户端期望的任何形式的带内 PAC 调配导致的。

本地目标消息格式: <timestamp> <seq_num>11615 WARN EAP No cipher on client side for invalid
PAC fallback, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11615 WARN EAP No cipher on client side
for invalid PAC fallback, <log details>

- 消息代码: 11616

严重性: 警告 (WARN)

消息文本: “允许的协议”不允许进行匿名调配和经过验证的调配 (Neither anonymous nor authenticated provisioning allowed by Allowed Protocols)

消息说明: 由于相关“允许的协议”不允许进行匿名和经过验证的带内 PAC 调配, 因此尝试调配 PAC 失败。

本地目标消息格式: <timestamp> <seq_num>11616 WARN EAP Neither anonymous nor authenticated provisioning allowed by Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>11616 WARN EAP Neither anonymous nor authenticated provisioning allowed by Allowed Protocols, <log details>

- 消息代码: 11617

严重性: 警告 (WARN)

消息文本: 客户端没有为匿名 PAC 调配提供适当的密码 (Client didn't provide suitable ciphers for anonymous PAC-provisioning)

消息说明: 客户端的请求方发出的 TEAP 带内 PAC 调配请求已由内部指定密码。此密码与“允许的协议”配置当前允许的以下调配方法不兼容: 匿名带内 PAC 调配。如果您需要此调配方法, 则此消息表明请求方配置不正确, 或者不能用于使用当前版本的 ISE 执行匿名调配。如果您需要经过验证的调配方法, 则此消息表明“允许的协议”配置当前不允许使用经过验证的带内 PAC 调配。

本地目标消息格式: <timestamp> <seq_num>11617 WARN EAP Client didn't provide suitable ciphers for anonymous PAC-provisioning, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>11617 WARN EAP Client didn't provide suitable ciphers for anonymous PAC-provisioning, <log details>

- 消息代码: 11618

严重性: 警告 (WARN)

消息文本: 客户端没有为经过验证的 PAC 调配提供适当的密码 (Client didn't provide suitable ciphers for authenticated PAC provisioning)

消息说明: 客户端的请求方发出的 TEAP 带内 PAC 配置请求已由内部指定密码, 该密码与“允许的协议”配置当前允许的以下唯一调配方法不兼容: 经过验证的带内 PAC 调配。如果确实需要此调配方法, 则此消息表明请求方配置不正确, 或者不能用于使用当前版本的 ISE 执行经过验证的调配。或者, 如果确实需要匿名调配方法, 则此消息表明“允许的协议”配置当前不允许使用匿名带内 PAC 调配。

本地目标消息格式: <timestamp> <seq_num>11618 WARN EAP Client didn't provide suitable ciphers for authenticated PAC provisioning, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>11618 WARN EAP Client didn't provide suitable ciphers for authenticated PAC provisioning, <log details>

- 消息代码: 11619

严重性: 警告 (WARN)

消息文本: 客户端没有为匿名或经过验证的 PAC 调配提供适当的密码 (Client didn't provide suitable ciphers for either anonymous or authenticated PAC-provisioning)

消息说明: 客户端的请求方发出的 TEAP 带内 PAC 调配请求已由内部指定密码。此密码与“允许的协议”配置当前允许的以下两种调配方法不兼容: 匿名带内 PAC 调配或经过验证的带内 PAC 调配。这表明请求方配置不正确, 或者不能用于使用当前版本的 ISE 执行 PAC 调配。

本地目标消息格式: <timestamp> <seq_num>11619 WARN EAP Client didn't provide suitable ciphers for either anonymous or authenticated PAC-provisioning, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11619 WARN EAP Client didn't provide suitable ciphers for either anonymous or authenticated PAC-provisioning, <log details>

- 消息代码: 11620

严重性: 信息 (INFO)

消息文本: TEAP 完全握手成功完成 (TEAP full handshake finished successfully)

消息说明: TEAP 完全握手成功完成

本地目标消息格式: <timestamp> <seq_num>11620 INFO EAP TEAP full handshake finished successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11620 INFO EAP TEAP full handshake finished successfully, <log details>

- 消息代码: 11621

严重性: 信息 (INFO)

消息文本: TEAP 无 PAC 会话成功恢复 (TEAP PAC-less session resumed successfully)

消息说明: 使用 TEAP 身份验证的无 PAC 模式。使用短时握手成功建立隧道。

本地目标消息格式: <timestamp> <seq_num>11621 INFO EAP TEAP PAC-less session resumed successfully, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11621 INFO EAP TEAP PAC-less session resumed successfully, <log details>

- 消息代码: 11622

严重性: 信息 (INFO)

消息文本: TEAP 为进行 PAC 调配建立了经过验证的隧道 (TEAP built authenticated tunnel for purpose of PAC provisioning)

消息说明: EAP-FAST 完全握手成功完成 - 已为进行第 0 阶段的 PAC 调配建立经过验证的隧道。

本地目标消息格式: <timestamp> <seq_num>11622 INFO EAP TEAP built authenticated tunnel for purpose of PAC provisioning, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11622 INFO EAP TEAP built authenticated tunnel for purpose of PAC provisioning, <log details>

- 消息代码: 11623

严重性: 信息 (INFO)

消息文本: TEAP 为进行 PAC 调配建立了匿名隧道 (TEAP built anonymous tunnel for purpose of PAC provisioning)

消息说明: TEAP 完全握手成功完成 - 已为进行第 0 阶段的 PAC 调配建立匿名隧道。

本地目标消息格式: <timestamp> <seq_num>11623 INFO EAP TEAP built anonymous tunnel for purpose of PAC provisioning, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11623 INFO EAP TEAP built anonymous tunnel for purpose of PAC provisioning, <log details>

- 消息代码: 11624

严重性: 信息 (INFO)

消息文本: TEAP 为进行身份验证建立了基于 PAC 的隧道 (TEAP built PAC-based tunnel for purpose of authentication)

消息说明: TEAP 短时握手成功完成 - 已为进行第 1 阶段的身份验证建立基于 PAC 的隧道。

本地目标消息格式: <timestamp> <seq_num>11624 INFO EAP TEAP built PAC-based tunnel for purpose of authentication, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11624 INFO EAP TEAP built PAC-based tunnel for purpose of authentication, <log details>

- 消息代码: 11625

严重性: 警告 (WARN)

消息文本: 没有用于无 PAC TEAP 身份验证的密码 (No cipher for PAC-less TEAP authentication)

消息说明: 在进行 TEAP 的 TLS 握手部分的过程中, 由客户端的请求方指定的密码与“允许的协议”配置中当前配置的无 PAC 操作模式不兼容。这可能是由于请求方的配置不正确, 甚至本身不能与使用当前版本的 ISE 的无 PAC TEAP 身份验证配合使用。

本地目标消息格式: <timestamp> <seq_num>11625 WARN EAP No cipher for PAC-less TEAP authentication, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11625 WARN EAP No cipher for PAC-less TEAP authentication, <log details>

• 消息代码: 11626

严重性: 警告 (WARN)

消息文本: 在 TEAP 握手过程中意外收到空的 TLS 消息; 视为客户端拒绝 (Unexpectedly received empty TLS message during TEAP handshake; treating as a rejection by the client)

消息说明: 当尝试与 TEAP 隧道内的客户端协商 TLS 握手时, ISE 期望收到非空 TLS 消息或 TLS 警报消息, 但收到空 TLS 消息。这可能是因为 ISE 和请求方在实施协议方面存在不一致。ISE 将异常消息视为客户端拒绝重新协商隧道的信号。

本地目标消息格式: <timestamp> <seq_num>11626 WARN EAP Unexpectedly received empty TLS message during TEAP handshake; treating as a rejection by the client, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11626 WARN EAP Unexpectedly received empty TLS message during TEAP handshake; treating as a rejection by the client, <log details>

• 消息代码: 11627

严重性: 信息 (INFO)

消息文本: 正启动 EAP 链接 (Starting EAP chaining)

消息说明: ISE 配置为执行 EAP 链接。ISE 正启动 EAP 链接, 并假定客户端也支持 EAP 链接。

本地目标消息格式: <timestamp> <seq_num>11627 INFO EAP Starting EAP chaining, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11627 INFO EAP Starting EAP chaining, <log details>

• 消息代码: 11628

严重性: 信息 (INFO)

消息文本: TEAP 需要主动更新即将到期的 PAC (TEAP needs to proactively update PAC that is about to expire)

消息说明: TEAP 需要主动更新即将到期的 PAC。

本地目标消息格式: <timestamp> <seq_num>11628 INFO EAP TEAP needs to proactively update PAC that is about to expire, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11628 INFO EAP TEAP needs to proactively update PAC that is about to expire, <log details>

• 消息代码: 11629

严重性: 警告 (WARN)

消息文本: 计算机授权 PAC I-ID 与用户身份不匹配。(Machine Authorization PAC I-ID does not match user identity.) 忽略此计算机授权 PAC 请求

消息说明: 计算机授权 PAC I-ID 与用户身份不匹配。忽略此计算机授权 PAC 请求

本地目标消息格式: <timestamp> <seq_num>11629 WARN EAP Machine Authorization PAC I-ID does not match user identity. Ignoring this Machine Authorization PAC request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11629 WARN EAP Machine Authorization PAC I-ID does not match user identity. Ignoring this Machine Authorization PAC request, <log details>

- 消息代码: 11630

严重性: 调试 (DEBUG)

消息文本: TEAP 通道绑定验证通过 (TEAP channelbinding verification passed)

消息说明: TEAP 通道绑定验证通过。

本地目标消息格式: <timestamp> <seq_num>11630 DEBUG EAP TEAP channelbinding verification passed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11630 DEBUG EAP TEAP channelbinding verification passed, <log details>

- 消息代码: 11631

严重性: 警告 (WARN)

消息文本: TEAP 通道绑定验证失败 (TEAP channelbinding verification failed)

消息说明: TEAP 通道绑定验证失败。

本地目标消息格式: <timestamp> <seq_num>11631 WARN EAP TEAP channelbinding verification failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11631 WARN EAP TEAP channelbinding verification failed, <log details>

- 消息代码: 11632

严重性: 信息 (INFO)

消息文本: 已为内部方法准备身份类型 Tlv (Prepared Identity Type Tlv for inner method)

消息说明: 已创建身份类型 Tlv 数据包, 用于封装到外部 EAP 方法的传出 EAP 请求数据包中, 并最终附加到 RADIUS 消息中。

本地目标消息格式: <timestamp> <seq_num>11632 INFO EAP Prepared Identity Type Tlv for inner method, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11632 INFO EAP Prepared Identity Type Tlv for inner method, <log details>

- 消息代码: 11633

严重性: 警告 (WARN)

消息文本: 客户端请求的 TLSv1.1 不被允许 (Client requested TLSv1.1 that is not allowed)

消息说明: 客户端请求将 TLSv1.1 作为最高版本, 但不被允许。

本地目标消息格式: <timestamp> <seq_num>11633 WARN EAP Client requested TLSv1.1 that is not allowed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11633 WARN EAP Client requested TLSv1.1 that is not allowed, <log details>

- 消息代码: 11634

严重性: 警告 (WARN)

消息文本: 客户端请求了未知版本的 TLS (Client requested TLS of unknown version)

消息说明: 客户端请求的 TLS 版本不受支持。

本地目标消息格式: <timestamp> <seq_num>11634 WARN EAP Client requested TLS of unknown version, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11634 WARN EAP Client requested TLS of unknown version, <log details>

- 消息代码: 11635

严重性: 警告 (WARN)

消息文本: 不允许从 EMSK 降级到 MSK (Downgrading from EMSK to MSK is not allowed)

消息说明: 客户端发送无 EMSK 复合 MAC 的加密绑定 TLV。TEAP 设置禁止在 EMSK 可用时降级到 MSK (例如, 使用 EAP-TLS 内部方法)。

本地目标消息格式: <timestamp> <seq_num>11635 WARN EAP Downgrading from EMSK to MSK is not allowed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>11635 WARN EAP Downgrading from EMSK to MSK is not allowed, <log details>

- 消息代码: 11636

严重性: 信息 (INFO)

消息文本: 已请求客户端证书, 但未在隧道建立期间收到。(Client certificate was requested but not received during tunnel establishment.)

消息说明: ISE 在隧道建立期间请求客户端证书, 但请求方未提供该客户端证书。请求方可能未配置为明文发送客户端证书。

本地目标消息格式: <timestamp> <seq_num>11636 INFO EAP Client certificate was requested but not received during tunnel establishment., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11636 INFO EAP Client certificate was
requested but not received during tunnel establishment., <log details>

- 消息代码: 11637

严重性: 信息 (INFO)

消息文本: 内部方法支持 EMSK, 但客户端仅提供了 MSK。允许根据配置降级 (Inner method
supports EMSK but the client provided only MSK. Allow downgrade as per configuration)

消息说明: 内部方法支持 EMSK, 但客户端仅提供了 MSK。允许根据配置降级

本地目标消息格式: <timestamp> <seq_num>11637 INFO EAP Inner method supports EMSK but the
client provided only MSK. Allow downgrade as per configuration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>11637 INFO EAP Inner method supports
EMSK but the client provided only MSK. Allow downgrade as per configuration, <log details>

- 消息代码: 12756

严重性: 信息 (INFO)

消息文本: 已准备提议使用 TEAP 和质询的 EAP 请求 (Prepared EAP-Request proposing TEAP
with challenge)

消息说明: 已创建一个 EAP 请求数据包, 提议使用 TEAP 协议, 同时提供 TEAP 质询, 用于附
加到 RADIUS 消息。提议 TEAP 协议是因为它是“允许的协议”中允许的基于 EAP 的协议之
一。

本地目标消息格式: <timestamp> <seq_num>12756 INFO EAP Prepared EAP-Request proposing
TEAP with challenge, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>12756 INFO EAP Prepared EAP-Request
proposing TEAP with challenge, <log details>

- 消息代码: 12757

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应/NAK 请求改为使用 TEAP (Extracted EAP-Response/NAK requesting
to use TEAP instead)

消息说明: 从 RADIUS 消息中提取的 EAP 响应/NAK 数据包拒绝之前提议的基于 EAP 的协议,
且根据客户端请求方的配置, 请求改为使用 TEAP。

本地目标消息格式: <timestamp> <seq_num>12757 INFO EAP Extracted EAP-Response/NAK
requesting to use TEAP instead, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>12757 INFO EAP Extracted
EAP-Response/NAK requesting to use TEAP instead, <log details>

- 消息代码: 12758

严重性: 信息 (INFO)

消息文本: 提取的 EAP 响应包含 TEAP 质询-响应, 且接受将 TEAP 用作协商协议 (Extracted EAP-Response containing TEAP challenge-response and accepting TEAP as negotiated)

消息说明: 从 RADIUS 消息中提取的 EAP 响应数据包含有 TEAP 质询-响应, 且接受将 TEAP 用作协商协议。

本地目标消息格式: <timestamp> <seq_num>12758 INFO EAP Extracted EAP-Response containing TEAP challenge-response and accepting TEAP as negotiated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>12758 INFO EAP Extracted EAP-Response containing TEAP challenge-response and accepting TEAP as negotiated, <log details>

- 消息代码: 12759

严重性: 警告 (WARN)

消息文本: 由于 TEAP 未在“允许的协议”中获得允许, 因此 EAP 协商失败 (Failed to negotiate EAP because TEAP not allowed in the Allowed Protocols)

消息说明: 客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前提议的基于 EAP 的协议, 且请求改为使用 TEAP。但是, TEAP 未在“允许的协议”中获得允许。

本地目标消息格式: <timestamp> <seq_num>12759 WARN EAP Failed to negotiate EAP because TEAP not allowed in the Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>12759 WARN EAP Failed to negotiate EAP because TEAP not allowed in the Allowed Protocols, <log details>

- 消息代码: 12760

严重性: 警告 (WARN)

消息文本: 由于 EAP-MSCHAP 未在“允许的协议”中的 TEAP 配置下获得允许, 因此无法为内部方法协商 EAP (Failed to negotiate EAP for inner method because EAP-MSCHAP not allowed under TEAP configuration in the Allowed Protocols)

消息说明: 客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前为内部方法提议的基于 EAP 的协议, 且请求改为使用 EAP-MSCHAP。但是, EAP-MSCHAP 未在“允许的协议”中的 TEAP 配置下获得允许。

本地目标消息格式: <timestamp> <seq_num>12760 WARN EAP Failed to negotiate EAP for inner method because EAP-MSCHAP not allowed under TEAP configuration in the Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>12760 WARN EAP Failed to negotiate EAP for inner method because EAP-MSCHAP not allowed under TEAP configuration in the Allowed Protocols, <log details>

- 消息代码: 12761

严重性: 警告 (WARN)

消息文本: 由于 EAP-TLS 未在“允许的协议”中的 TEAP 配置下获得允许, 因此无法为内部方法协商 EAP (Failed to negotiate EAP for inner method because EAP-TLS not allowed under TEAP configuration in the Allowed Protocols)

消息说明: 客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前为内部方法提议的基于 EAP 的协议, 且请求改为使用 EAP-TLS。但是, EAP-TLS 未在“允许的协议”中的 TEAP 配置下获得 ISE 允许。

本地目标消息格式: <timestamp> <seq_num>12761 WARN EAP Failed to negotiate EAP for inner method because EAP-TLS not allowed under TEAP configuration in the Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>12761 WARN EAP Failed to negotiate EAP for inner method because EAP-TLS not allowed under TEAP configuration in the Allowed Protocols, <log details>

• 消息代码: 12762

严重性: 警告 (WARN)

消息文本: 由于 EAP-GTC 未在“允许的协议”中的 TEAP 配置下获得允许, 因此无法为内部方法协商 EAP (Failed to negotiate EAP for inner method because EAP-GTC not allowed under TEAP configuration in the Allowed Protocols)

消息说明: 客户端请求方发送的 EAP 响应/NAK 数据包拒绝之前为内部方法提议的基于 EAP 的协议, 且请求改为使用 EAP-GTC。但是, EAP-GTC 未在“允许的协议”中的 TEAP 配置下获得 ISE 允许。

本地目标消息格式: <timestamp> <seq_num>12762 WARN EAP Failed to negotiate EAP for inner method because EAP-GTC not allowed under TEAP configuration in the Allowed Protocols, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>12762 WARN EAP Failed to negotiate EAP for inner method because EAP-GTC not allowed under TEAP configuration in the Allowed Protocols, <log details>

• 消息代码: 12921

严重性: 警告 (WARN)

消息文本: 请求方在建立 TEAP 隧道期间停止响应 ISE (Supplicant stopped responding to ISE during TEAP tunnel establishment)

消息说明: 请求方在建立 TEAP 隧道期间停止响应 ISE

本地目标消息格式: <timestamp> <seq_num>12921 WARN Failed-Attempt Supplicant stopped responding to ISE during TEAP tunnel establishment, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num>12921 WARN Failed-Attempt Supplicant stopped responding to ISE during TEAP tunnel establishment, <log details>

• 消息代码: 12928

严重性: 警告 (WARN)

消息文本: 请求方在 TEAP 保护终止的过程中停止响应 ISE (Supplicant stopped responding to ISE during TEAP protected termination)

消息说明: 请求方在 TEAP 保护终止的过程中停止响应 ISE

本地目标消息格式: <timestamp> <seq_num>12928 WARN Failed-Attempt Supplicant stopped responding to ISE during TEAP protected termination, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>12928 WARN Failed-Attempt Supplicant stopped responding to ISE during TEAP protected termination, <log details>

- 消息代码: 12929

严重性: 警告 (WARN)

消息文本: NAS 发送 RADIUS 记账更新信息过于频繁 (NAS sends RADIUS accounting update messages too frequently)

消息说明: NAS 发送 RADIUS 记账更新信息过于频繁

本地目标消息格式: <timestamp> <seq_num>12929 WARN RADIUS NAS sends RADIUS accounting update messages too frequently, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>12929 WARN RADIUS NAS sends RADIUS accounting update messages too frequently, <log details>

系统统计项

- 消息代码: 70000

严重性: 通知 (NOTICE)

消息文本: ISE 利用率 (ISE Utilization)

消息说明: ISE 利用率

本地目标消息格式: <timestamp> <seq_num> 70000 NOTICE System-Stats: ISE Utilization, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 70000 NOTICE System-Stats: ISE Utilization, <log details>

- 消息代码: 70001

严重性: 通知 (NOTICE)

消息文本: ISE 进程运行状况 (ISE Process Health)

消息说明: ISE 进程运行状况

本地目标消息格式: <timestamp> <seq_num> 70001 NOTICE System-Stats: ISE Process Health, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 70001 NOTICE System-Stats: ISE Process Health, <log details>

- 消息代码: 70002

严重性: 通知 (NOTICE)

消息文本: ISE 进程运行状况不可用 (ISE Process Health Unavailable)

消息说明: ISE 进程运行状况不可用

本地目标消息格式: <timestamp> <seq_num> 70002 NOTICE System-Stats: ISE Process Health Unavailable, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 70002 NOTICE System-Stats: ISE Process Health Unavailable, <log details>

- 消息代码: 70010

严重性: 信息 (INFO)

消息文本: OCSP 统计信息 (OCSP Statistics)

消息说明: OCSP 统计信息

本地目标消息格式: <timestamp> <seq_num> 70010 INFO System-Stats: OCSP Statistics, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 70010 INFO System-Stats: OCSP Statistics, <log details>

- 消息代码: 70011

严重性: 信息 (INFO)

消息文本: ISE 计数器 (ISE Counters)

消息说明: ISE 计数器

本地目标消息格式: <timestamp> <seq_num> 70011 INFO System-Stats: ISE Counters, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 70011 INFO System-Stats: ISE Counters, <log details>

TACACS 计费

- 消息代码: 3300

严重性: 通知 (NOTICE)

消息文本: 包含命令的 TACACS+ 记帐 (TACACS+ Accounting with Command)

消息说明: 已收到包含命令的 TACACS+ 记帐请求

本地目标消息格式: <timestamp> <seq_num> 3300 NOTICE Tacacs-Accounting: TACACS+ Accounting with Command, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 3300 NOTICE Tacacs-Accounting: TACACS+ Accounting with Command, <log details>

- 消息代码: 3301

严重性: 通知 (NOTICE)

消息文本: TACACS+ 记帐开始 (TACACS+ Accounting START)

消息说明: 已收到 TACACS+ 记帐开始请求

本地目标消息格式: <timestamp> <seq_num> 3301 NOTICE Tacacs-Accounting: TACACS+ Accounting START, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 3301 NOTICE Tacacs-Accounting: TACACS+ Accounting START, <log details>

- 消息代码: 3302

严重性: 通知 (NOTICE)

消息文本: TACACS+ 记帐停止 (TACACS+ Accounting STOP)

消息说明: 已收到 TACACS+ 记帐停止请求

本地目标消息格式: <timestamp> <seq_num> 3302 NOTICE Tacacs-Accounting: TACACS+ Accounting STOP, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 3302 NOTICE Tacacs-Accounting: TACACS+ Accounting STOP, <log details>

- 消息代码: 3303

严重性: 通知 (NOTICE)

消息文本: TACACS+ 记帐监视器 (TACACS+ Accounting WATCHDOG)

消息说明: 已收到 TACACS+ 记帐监视器请求

本地目标消息格式: <timestamp> <seq_num> 3303 NOTICE Tacacs-Accounting: TACACS+ Accounting WATCHDOG, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 3303 NOTICE Tacacs-Accounting: TACACS+ Accounting WATCHDOG, <log details>

- 消息代码: 3304
严重性: 通知 (NOTICE)
消息文本: 已拒绝 TACACS+ 记帐请求 (TACACS+ Accounting request rejected)
消息说明: 已收到 TACACS+ 记帐请求, 但已将其拒绝。查看失败原因可了解更多信息
本地目标消息格式: <timestamp> <seq_num> 3304 NOTICE Tacacs-Accounting: TACACS+ Accounting request rejected, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 3304 NOTICE Tacacs-Accounting: TACACS+ Accounting request rejected, <log details>

TACACS 诊断

- 消息代码: 13000
严重性: 警告 (WARN)
消息文本: TACACS+ 授权请求无效 (Invalid TACACS+ authorization request)
消息说明: TACACS+ 授权请求不受 ISE 支持
本地目标消息格式: <timestamp> <seq_num> 13000 WARN TACACS: Invalid TACACS+ authorization request, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13000 WARN TACACS: Invalid TACACS+ authorization request, <log details>
- 消息代码: 13001
严重性: 警告 (WARN)
消息文本: TACACS+ 记帐请求无效 (Invalid TACACS+ accounting request)
消息说明: TACACS+ 记帐请求不受 ISE 支持
本地目标消息格式: <timestamp> <seq_num> 13001 WARN TACACS: Invalid TACACS+ accounting request, <log details>
远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13001 WARN TACACS: Invalid TACACS+ accounting request, <log details>
- 消息代码: 13002
严重性: 信息 (INFO)
消息文本: 已启动 TACACS+ 侦听程序 (Started TACACS+ listener)
消息说明: 已启动 TACACS+ 侦听程序

本地目标消息格式: <timestamp> <seq_num> 13002 INFO TACACS: Started TACACS+ listener, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13002 INFO TACACS: Started TACACS+ listener, <log details>

- 消息代码: 13003

严重性: 信息 (INFO)

消息文本: 已停止 TACACS+ 侦听程序 (Stopped TACACS+ listener)

消息说明: 已停止 TACACS+ 侦听程序

本地目标消息格式: <timestamp> <seq_num> 13003 INFO TACACS: Stopped TACACS+ listener, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13003 INFO TACACS: Stopped TACACS+ listener, <log details>

- 消息代码: 13004

严重性: 错误 (ERROR)

消息文本: TACACS+ 侦听程序失败 (TACACS+ listener failed)

消息说明: TACACS+ 侦听程序失败

本地目标消息格式: <timestamp> <seq_num> 13004 ERROR TACACS: TACACS+ listener failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13004 ERROR TACACS: TACACS+ listener failed, <log details>

- 消息代码: 13005

严重性: 调试 (DEBUG)

消息文本: 已收到 TACACS+ 授权请求 (Received TACACS+ Authorization Request)

消息说明: 已收到 TACACS+ 授权请求

本地目标消息格式: <timestamp> <seq_num> 13005 DEBUG TACACS: Received TACACS+ Authorization Request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13005 DEBUG TACACS: Received TACACS+ Authorization Request, <log details>

- 消息代码: 13006

严重性: 调试 (DEBUG)

消息文本: 已收到 TACACS+ 记帐请求 (Received TACACS+ Accounting Request)

消息说明: 已收到 TACACS+ 记帐请求

本地目标消息格式: <timestamp> <seq_num> 13006 DEBUG TACACS: Received TACACS+ Accounting Request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13006 DEBUG TACACS: Received TACACS+ Accounting Request, <log details>

- 消息代码: 13007

严重性: 警告 (WARN)

消息文本: TACACS+ 数据包信头无效 (Invalid TACACS+ packet header)

消息说明: TACACS+ 数据包的信头解析不正确

本地目标消息格式: <timestamp> <seq_num> 13007 WARN TACACS: Invalid TACACS+ packet header, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13007 WARN TACACS: Invalid TACACS+ packet header, <log details>

- 消息代码: 13008

严重性: 警告 (WARN)

消息文本: 已达到 TACACS+ 最大客户端数量限制 (Reached TACACS+ maximum client limit)

消息说明: 检查该设备和 ISE 之间的网络设备或 AAA 客户端和/或网络是否存在硬件问题

本地目标消息格式: <timestamp> <seq_num> 13008 WARN TACACS: Reached TACACS+ maximum client limit, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13008 WARN TACACS: Reached TACACS+ maximum client limit, <log details>

- 消息代码: 13009

严重性: 警告 (WARN)

消息文本: 无法接受 TACACS+ 客户端连接 (Failed to accept TACACS+ client connection)

消息说明: 尝试接受来自 TACACS+ 客户端的连接请求失败。如果客户端在发起请求后, 在 ISE 接受连接之前已经“挂起”, 就会发生这种情况。如果这种情况频繁发生, 可能表示设备存在故障, 或者可能受到了 DOS 攻击

本地目标消息格式: <timestamp> <seq_num> 13009 WARN TACACS: Failed to accept TACACS+ client connection, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13009 WARN TACACS: Failed to accept TACACS+ client connection, <log details>

- 消息代码: 13010
 - 严重性: 警告 (WARN)
 - 消息文本: 收到的 TACACS+ 数据包的长度无效 (Received TACACS+ packet with invalid length)
 - 消息说明: 收到的 TACACS+ 数据包的长度少于 12 个字节或者超过定义的最大长度
 - 本地目标消息格式: <timestamp> <seq_num> 13010 WARN TACACS: Received TACACS+ packet with invalid length, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13010 WARN TACACS: Received TACACS+ packet with invalid length, <log details>

- 消息代码: 13011
 - 严重性: 警告 (WARN)
 - 消息文本: TACACS+ 请求数据包无效 - 可能是共享密钥不匹配 (Invalid TACACS+ request packet - possibly mismatched Shared Secrets)
 - 消息说明: TACACS+ 请求数据包无效。可能是因为设备上配置的共享密钥与网络设备或 ISE 中的 AAA 客户端上配置的共享密钥不匹配
 - 本地目标消息格式: <timestamp> <seq_num> 13011 WARN TACACS: Invalid TACACS+ request packet - possibly mismatched Shared Secrets, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13011 WARN TACACS: Invalid TACACS+ request packet - possibly mismatched Shared Secrets, <log details>

- 消息代码: 13013
 - 严重性: 调试 (DEBUG)
 - 消息文本: 已收到 TACACS+ 身份验证开始请求 (Received TACACS+ Authentication START Request)
 - 消息说明: 已收到 TACACS+ 身份验证开始请求
 - 本地目标消息格式: <timestamp> <seq_num> 13013 DEBUG TACACS: Received TACACS+ Authentication START Request, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13013 DEBUG TACACS: Received TACACS+ Authentication START Request, <log details>

- 消息代码: 13014
 - 严重性: 调试 (DEBUG)
 - 消息文本: 已收到 TACACS+ 身份验证继续请求 (Received TACACS+ Authentication CONTINUE Request)
 - 消息说明: 已收到 TACACS+ 身份验证继续请求

本地目标消息格式: <timestamp> <seq_num> 13014 DEBUG TACACS: Received TACACS+ Authentication CONTINUE Request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13014 DEBUG TACACS: Received TACACS+ Authentication CONTINUE Request, <log details>

- 消息代码: 13015

严重性: 调试 (DEBUG)

消息文本: 已返回 TACACS+ 身份验证回复 (Returned TACACS+ Authentication Reply)

消息说明: 已返回 TACACS+ 身份验证回复

本地目标消息格式: <timestamp> <seq_num> 13015 DEBUG TACACS: Returned TACACS+ Authentication Reply, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13015 DEBUG TACACS: Returned TACACS+ Authentication Reply, <log details>

- 消息代码: 13017

严重性: 调试 (DEBUG)

消息文本: 已从未知网络设备或 AAA 客户端收到 TACACS+ 数据包 (Received TACACS+ packet from unknown Network Device or AAA Client)

消息说明: 已收到 TACACS+ 数据包, 但源 IP 地址与任何已配置的网络设备或 AAA 客户端不匹配

本地目标消息格式: <timestamp> <seq_num> 13017 DEBUG TACACS: Received TACACS+ packet from unknown Network Device or AAA Client, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13017 DEBUG TACACS: Received TACACS+ packet from unknown Network Device or AAA Client, <log details>

- 消息代码: 13019

严重性: 错误 (ERROR)

消息文本: 无法获取 TACACS+ 设置 (Failed to obtain TACACS+ Settings)

消息说明: 内部错误: 无法从配置数据库获取 TACACS+ 设置

本地目标消息格式: <timestamp> <seq_num> 13019 ERROR TACACS: Failed to obtain TACACS+ Settings, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13019 ERROR TACACS: Failed to obtain TACACS+ Settings, <log details>

- 消息代码: 13020

严重性: 信息 (INFO)

消息文本: 获取 TACACS+ 默认网络设备设置 (Get TACACS+ default network device setting)

消息说明: 获取 TACACS+ 默认网络设备设置。

本地目标消息格式: <timestamp> <seq_num> 13020 INFO TACACS: Get TACACS+ default network device setting, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 13020 INFO TACACS: Get TACACS+ default network device setting, <log details>

- 消息代码: 13021

严重性: 警告 (WARN)

消息文本: 由于系统过载, 已丢弃 TACACS+ 请求 (TACACS+ request was dropped because of system overload)

消息说明: 由于系统过载, 已丢弃 TACACS+ 请求。

本地目标消息格式: <timestamp> <seq_num> 13021 WARN TACACS: TACACS+ request was dropped because of system overload, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 13021 WARN TACACS: TACACS+ request was dropped because of system overload, <log details>

- 消息代码: 13023

严重性: 调试 (DEBUG)

消息文本: 命令符合 Deny-Always 规则 (Command matched a Deny-Always rule)

消息说明: 请求的命令符合其中一个命令集中的 Deny-Always 规则

本地目标消息格式: <timestamp> <seq_num> 13023 DEBUG Device-administration: Command matched a Deny-Always rule, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 13023 DEBUG Device-administration: Command matched a Deny-Always rule, <log details>

- 消息代码: 13024

严重性: 调试 (DEBUG)

消息文本: 命令符合 Permit 规则 (Command matched a Permit rule)

消息说明: 命令符合 Permit 规则

本地目标消息格式: <timestamp> <seq_num> 13024 DEBUG Device-administration: Command matched a Permit rule, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 13024 DEBUG Device-administration: Command matched a Permit rule, <log details>

- 消息代码: 13025
 - 严重性: 调试 (DEBUG)
 - 消息文本: 命令不符合 Permit 规则 (Command failed to match a Permit rule)
 - 消息说明: 请求的命令未能符合其中一个命令集中的 Permit 规则
 - 本地目标消息格式: <timestamp> <seq_num> 13025 DEBUG Device-administration: Command failed to match a Permit rule, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13025 DEBUG Device-administration: Command failed to match a Permit rule, <log details>

- 消息代码: 13027
 - 严重性: 警告 (WARN)
 - 消息文本: TACACS+ 授权请求缺少 User 和 Remote-Address 属性 (TACACS+ authorization request missing both User and Remote-Address attributes)
 - 消息说明: TACACS+ 授权请求缺少 User 和 Remote-Address 属性
 - 本地目标消息格式: <timestamp> <seq_num> 13027 WARN TACACS: TACACS+ authorization request missing both User and Remote-Address attributes, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13027 WARN TACACS: TACACS+ authorization request missing both User and Remote-Address attributes, <log details>

- 消息代码: 13029
 - 严重性: 错误 (ERROR)
 - 消息文本: 请求的权限级别过高 (Requested privilege level too high)
 - 消息说明: TACACS+ 用户请求的权限级别高于在 Shell 配置文件中配置的最大权限级别
 - 本地目标消息格式: <timestamp> <seq_num> 13029 ERROR TACACS: Requested privilege level too high, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13029 ERROR TACACS: Requested privilege level too high, <log details>

- 消息代码: 13030
 - 严重性: 警告 (WARN)
 - 消息文本: TACACS+ 身份验证请求缺少用户名 (TACACS+ authentication request missing a User name)
 - 消息说明: TACACS+ 身份验证请求未提供用户名
 - 本地目标消息格式: <timestamp> <seq_num> 13030 WARN TACACS: TACACS+ authentication request missing a User name, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 13030 WARN TACACS: TACACS+ authentication request missing a User name, <log details>

- 消息代码: 13031

严重性: 警告 (WARN)

消息文本: TACACS+ 身份验证请求缺少用户密码 (TACACS+ authentication request missing user Password)

消息说明: TACACS+ 身份验证请求未提供用户密码

本地目标消息格式: <timestamp> <seq_num> 13031 WARN TACACS: TACACS+ authentication request missing user Password, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 13031 WARN TACACS: TACACS+ authentication request missing user Password, <log details>

- 消息代码: 13032

严重性: 错误 (ERROR)

消息文本: 访问 TACACS+ 配置时出现严重错误 (Fatal error accessing TACACS+ configuration)

消息说明: 内部错误: 无法访问数据库中的访问服务配置

本地目标消息格式: <timestamp> <seq_num> 13032 ERROR TACACS: Fatal error accessing TACACS+ configuration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 13032 ERROR TACACS: Fatal error accessing TACACS+ configuration, <log details>

- 消息代码: 13034

严重性: 调试 (DEBUG)

消息文本: 已返回 TACACS+ 授权回复 (Returned TACACS+ Authorization Reply)

消息说明: 已返回 TACACS+ 授权回复

本地目标消息格式: <timestamp> <seq_num> 13034 DEBUG TACACS: Returned TACACS+ Authorization Reply, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 13034 DEBUG TACACS: Returned TACACS+ Authorization Reply, <log details>

- 消息代码: 13035

严重性: 调试 (DEBUG)

消息文本: 已返回 TACACS+ 记帐回复 (Returned TACACS+ Accounting Reply)

消息说明: 已返回 TACACS+ 记帐回复

本地目标消息格式: <timestamp> <seq_num> 13035 DEBUG TACACS: Returned TACACS+ Accounting Reply, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13035 DEBUG TACACS: Returned TACACS+ Accounting Reply, <log details>

- 消息代码: 13036

严重性: 信息 (INFO)

消息文本: 选定的 Shell 配置文件是 DenyAccess (Selected Shell Profile is DenyAccess)

消息说明: 选定的 Shell 配置文件无法执行此请求

本地目标消息格式: <timestamp> <seq_num> 13036 INFO TACACS: Selected Shell Profile is DenyAccess, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13036 INFO TACACS: Selected Shell Profile is DenyAccess, <log details>

- 消息代码: 13037

严重性: 信息 (INFO)

消息文本: 未正确配置 Shell 配置文件的权限级别 (Shell Profile Privilege Level not configured correctly)

消息说明: 未正确配置 Shell 配置文件的权限级别

本地目标消息格式: <timestamp> <seq_num> 13037 INFO TACACS: Shell Profile Privilege Level not configured correctly, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13037 INFO TACACS: Shell Profile Privilege Level not configured correctly, <log details>

- 消息代码: 13038

严重性: 信息 (INFO)

消息文本: 由于出现严重的日志记录错误, TACACS+ 请求失败 (TACACS+ request failed because of a critical logging error)

消息说明: 由于出现严重的日志记录错误, TACACS+ 请求失败。

本地目标消息格式: <timestamp> <seq_num> 13038 INFO TACACS: TACACS+ request failed because of a critical logging error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13038 INFO TACACS: TACACS+ request failed because of a critical logging error, <log details>

- 消息代码: 13039

严重性: 警告 (WARN)

消息文本: TACACS+ 身份验证请求不包含用户的新密码 (TACACS+ authentication request does not contain the user's new password)

消息说明: TACACS+ 身份验证请求不包含用户的新密码。

本地目标消息格式: <timestamp> <seq_num> 13039 WARN TACACS: TACACS+ authentication request does not contain the user's new password, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 13039 WARN TACACS: TACACS+ authentication request does not contain the user's new password, <log details>

- 消息代码: 13040

严重性: 警告 (WARN)

消息文本: TACACS+ 身份验证请求的“确认新用户密码”(Confirm New User Password) 字段包含空字符串 (TACACS+ authentication request contains an empty string in the Confirm New User Password field)

消息说明: TACACS+ 身份验证请求不包含用户的新密码, 不能确认密码更改请求。

本地目标消息格式: <timestamp> <seq_num> 13040 WARN TACACS: TACACS+ authentication request contains an empty string in the Confirm New User Password field, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 13040 WARN TACACS: TACACS+ authentication request contains an empty string in the Confirm New User Password field, <log details>

- 消息代码: 13041

严重性: 警告 (WARN)

消息文本: TACACS+ 身份验证请求从登录转换为更改密码功能 (TACACS+ authentication request switches from Login to Change Password functionality)

消息说明: TACACS+ 身份验证请求从登录转换为更改密码功能。

本地目标消息格式: <timestamp> <seq_num> 13041 WARN TACACS: TACACS+ authentication request switches from Login to Change Password functionality, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 13041 WARN TACACS: TACACS+ authentication request switches from Login to Change Password functionality, <log details>

- 消息代码: 13042

严重性: 警告 (WARN)

消息文本: 用于确认用户新密码的 TACACS+ 身份验证请求失败 (TACACS+ authentication request to confirm a user's new password has failed)

消息说明: 用于更改用户密码的 TACACS+ 身份验证请求不包含确认密码。

本地目标消息格式: <timestamp> <seq_num> 13042 WARN TACACS: TACACS+ authentication request to confirm a user's new password has failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 13042 WARN TACACS: TACACS+ authentication request to confirm a user's new password has failed, <log details>

- 消息代码: 13043

严重性: 警告 (WARN)

消息文本: 选定的 TACACS+ 身份验证类型不支持质询-响应机制 (Challenge-response mechanism is not supported by the selected TACACS+ authentication type)

消息说明: 选定的 TACACS+ 身份验证类型不支持质询-响应机制。

本地目标消息格式: <timestamp> <seq_num> 13043 WARN TACACS: Challenge-response mechanism is not supported by the selected TACACS+ authentication type, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 13043 WARN TACACS: Challenge-response mechanism is not supported by the selected TACACS+ authentication type, <log details>

- 消息代码: 13044

严重性: 信息 (INFO)

消息文本: TACACS+ 将使用身份存储库返回的密码提示 (TACACS+ will use the password prompt returned by the identity store)

消息说明: TACACS+ 将使用身份存储库返回的密码提示。

本地目标消息格式: <timestamp> <seq_num> 13044 INFO TACACS: TACACS+ will use the password prompt returned by the identity store, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 13044 INFO TACACS: TACACS+ will use the password prompt returned by the identity store, <log details>

- 消息代码: 13045

严重性: 信息 (INFO)

消息文本: TACACS+ 将使用全局 TACACS+ 配置中的密码提示 (TACACS+ will use the password prompt from global TACACS+ configuration)

消息说明: TACACS+ 将使用全局 TACACS+ 配置中的密码提示。

本地目标消息格式: <timestamp> <seq_num> 13045 INFO TACACS: TACACS+ will use the password prompt from global TACACS+ configuration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 13045 INFO TACACS: TACACS+ will use the password prompt from global TACACS+ configuration, <log details>

- 消息代码: 13046

严重性: 信息 (INFO)

消息文本: TACACS+ ASCII 更改密码请求 (TACACS+ ASCII change password request)

消息说明: TACACS+ ASCII 更改密码请求。

本地目标消息格式: <timestamp> <seq_num> 13046 INFO TACACS: TACACS+ ASCII change password request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13046 INFO TACACS: TACACS+ ASCII change password request, <log details>

- 消息代码: 13050

严重性: 错误 (ERROR)

消息文本: TACACS+ MSCHAP 标志值无效。(Invalid TACACS+ MSCHAP flag value.)

消息说明: TACACS+ MSCHAP 标志值无效。

本地目标消息格式: <timestamp> <seq_num> 13050 ERROR TACACS : Invalid TACACS+ MSCHAP flag value. , <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13050 ERROR TACACS : Invalid TACACS+ MSCHAP flag value. , <log details>

- 消息代码: 13051

严重性: 错误 (ERROR)

消息文本: 数据字段大小较小。(Size of data field is small.)

消息说明: 数据字段大小较小。

本地目标消息格式: <timestamp> <seq_num> 13051 ERROR TACACS : Size of data field is small. , <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13051 ERROR TACACS : Size of data field is small. , <log details>

- 消息代码: 13052

严重性: 错误 (ERROR)

消息文本: 数据字段大小较小。(Size of data field is small.)

消息说明: 数据字段大小较小。

本地目标消息格式: <timestamp> <seq_num> 13052 ERROR TACACS : Size of data field is small. , <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13052 ERROR TACACS : Size of data field is small. , <log details>

- 消息代码: 13060

严重性: 警告 (WARN)

消息文本: 无法读取 TACACS 代理配置。(Failed to read TACACS proxy configuration.)

消息说明: ACS 尝试读取 TACACS 代理配置时检测到错误。

本地目标消息格式: <timestamp> <seq_num> 13060 WARN TACACS-Proxy : Failed to read TACACS proxy configuration. , <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 13060 WARN TACACS-Proxy : Failed to read TACACS proxy configuration. , <log details>

- 消息代码: 13061

严重性: 警告 (WARN)

消息文本: 收到记帐请求, 但本地和远程记帐均未配置。(Accounting request received but neither local nor remote accounting is configured.)

消息说明: 收到记帐请求, 但本地和远程记帐均未配置。

本地目标消息格式: <timestamp> <seq_num> 13061 WARN TACACS-Proxy : Accounting request received but neither local nor remote accounting is configured. , <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 13061 WARN TACACS-Proxy : Accounting request received but neither local nor remote accounting is configured. , <log details>

- 消息代码: 13062

严重性: 警告 (WARN)

消息文本: 没有其他外部 TACACS 服务器; 不能执行故障切换。(No more external TACACS servers; cannot perform failover.)

消息说明: 没有配置其他外部 TACACS 服务器, 因此不能执行故障切换。

本地目标消息格式: <timestamp> <seq_num> 13062 WARN TACACS-Proxy : No more external TACACS servers; cannot perform failover. , <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 13062 WARN TACACS-Proxy : No more external TACACS servers; cannot perform failover. , <log details>

- 消息代码: 13063

严重性: 信息 (INFO)

消息文本: 开始将请求转发给远程 TACACS 服务器。(Start forwarding request to remote TACACS server.)

消息说明: 请求正在从为选定的 ACS 代理服务配置的列表中转发到下一个远程 TACACS 服务器。

本地目标消息格式: <timestamp> <seq_num> 13063 INFO TACACS-Proxy : Start forwarding request to remote TACACS server. , <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 13063 INFO TACACS-Proxy : Start
forwarding request to remote TACACS server. , <log details>

- 消息代码: 13064

严重性: 信息 (INFO)

消息文本: TACACS 代理已收到传入的转发请求。(TACACS proxy received incoming request for forwarding.)

消息说明: TACACS 代理已收到传入请求。验证请求并准备将其转发到已配置好的远程 TACACS 服务器。

本地目标消息格式: <timestamp> <seq_num> 13064 INFO TACACS-Proxy : TACACS proxy received
incoming request for forwarding. , <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 13064 INFO TACACS-Proxy : TACACS
proxy received incoming request for forwarding. , <log details>

- 消息代码: 13065

严重性: 信息 (INFO)

消息文本: TACACS 代理已收到传入的有效身份验证请求。(TACACS proxy received valid incoming authentication request.)

消息说明: TACACS 代理已收到传入的有效身份验证请求。

本地目标消息格式: <timestamp> <seq_num> 13065 INFO TACACS-Proxy : TACACS proxy received
valid incoming authentication request. , <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 13065 INFO TACACS-Proxy : TACACS
proxy received valid incoming authentication request. , <log details>

- 消息代码: 13066

严重性: 信息 (INFO)

消息文本: TACACS 代理已收到传入的有效授权请求。(TACACS proxy received valid incoming authorization request.)

消息说明: TACACS 代理已收到传入的有效授权请求。

本地目标消息格式: <timestamp> <seq_num> 13066 INFO TACACS-Proxy : TACACS proxy received
valid incoming authorization request. , <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 13066 INFO TACACS-Proxy : TACACS
proxy received valid incoming authorization request. , <log details>

- 消息代码: 13067

严重性: 信息 (INFO)

消息文本: TACACS 代理已收到传入的有效记帐请求。(TACACS proxy received valid incoming accounting request.)

消息说明: TACACS 代理已收到传入的有效记帐请求。

本地目标消息格式: <timestamp> <seq_num> 13067 INFO TACACS-Proxy : TACACS proxy received valid incoming accounting request. , <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13067 INFO TACACS-Proxy : TACACS proxy received valid incoming accounting request. , <log details>

- 消息代码: 13068

严重性: 信息 (INFO)

消息文本: TACACS 代理执行本地记帐。(TACACS proxy performing local accounting.)

消息说明: TACACS 代理正在基于收到的传入记帐请求执行本地记帐。

本地目标消息格式: <timestamp> <seq_num> 13068 INFO TACACS-Proxy : TACACS proxy performing local accounting. , <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13068 INFO TACACS-Proxy : TACACS proxy performing local accounting. , <log details>

- 消息代码: 13069

严重性: 信息 (INFO)

消息文本: TACACS 代理执行远程记帐。(TACACS proxy performing remote accounting.)

消息说明: TACACS 代理正在基于收到的传入记帐请求执行远程记帐。

本地目标消息格式: <timestamp> <seq_num> 13069 INFO TACACS-Proxy : TACACS proxy performing remote accounting. , <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13069 INFO TACACS-Proxy : TACACS proxy performing remote accounting. , <log details>

- 消息代码: 13070

严重性: 警告 (WARN)

消息文本: 无法将请求转发到当前的远程 TACACS 服务器。(Failed to forward request to current remote TACACS server.)

消息说明: 由于以下任一原因, 当前的远程 TACACS 服务器无法处理转发的请求: 远程 TACACS 服务器关闭; 未正确配置远程 TACACS 服务器; 远程 TACACS 服务器丢弃请求。

本地目标消息格式: <timestamp> <seq_num> 13070 WARN TACACS-Proxy : Failed to forward request to current remote TACACS server. , <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 13070 WARN TACACS-Proxy : Failed to forward request to current remote TACACS server. , <log details>

- 消息代码: 13071

严重性: 警告 (WARN)

消息文本: 继续执行流程 (seq_no > 1)。 (Continue flow (seq_no > 1).)

消息说明: 继续上一流程。请求将发送到服务器, 以此响应之前的请求。

本地目标消息格式: <timestamp> <seq_num> 13071 WARN TACACS-Proxy : Continue flow (seq_no > 1). , <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 13071 WARN TACACS-Proxy : Continue flow (seq_no > 1). , <log details>

- 消息代码: 13072

严重性: 警告 (WARN)

消息文本: 无法将请求转发到当前的远程 TACACS 服务器。 (Failed to forward request to current remote TACACS server.)

消息说明: 无法将请求转发到当前的远程 TACACS 服务器。因为流程继续, 无法将请求转发到下一个 TACACS 服务器。

本地目标消息格式: <timestamp> <seq_num> 13072 WARN TACACS-Proxy : Failed to forward request to current remote TACACS server. , <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 13072 WARN TACACS-Proxy : Failed to forward request to current remote TACACS server. , <log details>

- 消息代码: 13073

严重性: 信息 (INFO)

消息文本: 由于出现严重的日志记录错误, TACACS+ 代理请求失败。 (TACACS+ Proxy request failed because of a critical logging error.)

消息说明: 由于出现严重的日志记录错误, TACACS+ 代理请求失败。

本地目标消息格式: <timestamp> <seq_num> 13073 INFO TACACS : TACACS+ Proxy request failed because of a critical logging error. , <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 13073 INFO TACACS : TACACS+ Proxy request failed because of a critical logging error. , <log details>

- 消息代码: 13074

严重性: 信息 (INFO)

消息文本: 已处理完 TACACS 代理请求。 (Finished to process TACACS Proxy request.)

消息说明：已处理完 TACACS 代理请求。

本地目标消息格式：<timestamp> <seq_num> 13074 INFO TACACS-Proxy : Finished to process TACACS Proxy request. , <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13074 INFO TACACS-Proxy : Finished to process TACACS Proxy request. , <log details>

- 消息代码：13075

严重性：信息 (INFO)

消息文本：TACACS+ 代理请求不会继续。(TACACS+ Proxy request won't continue.)

消息说明：TACACS+ 代理请求不会继续。

本地目标消息格式：<timestamp> <seq_num> 13075 INFO TACACS-Proxy : TACACS+ Proxy request won't continue. , <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 13075 INFO TACACS-Proxy : TACACS+ Proxy request won't continue. , <log details>

- 消息代码：13076

严重性：调试 (DEBUG)

消息文本：未对选定规则设置命令 (No command set for selected rule)

消息说明：nan

本地目标消息格式：<timestamp><seq_num>13076 DEBUG Device-administration No command set for selected rule, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>13076 DEBUG Device-administration No command set for selected rule, <log details>

- 消息代码：13077

严重性：警告 (WARN)

消息文本：TACACS+ 记帐请求数据包无效 - 数据包格式可能错误 (Invalid TACACS+ accounting request packet - possibly malformed packet)

消息说明：nan

本地目标消息格式：<timestamp> <seq_num>13077 WARN Tacacs-Accounting Invalid TACACS+ accounting request packet - possibly malformed packet, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>13077 WARN Tacacs-Accounting Invalid TACACS+ accounting request packet - possibly malformed packet, <log details>

- 消息代码：13078

严重性: 警告 (WARN)

消息文本: TACACS+ 授权请求数据包无效 - 数据包格式可能错误 (Invalid TACACS+ authorization request packet - possibly malformed packet)

消息说明: nan

本地目标消息格式: <timestamp> <seq_num>13078 WARN Device-administration Invalid TACACS+ authorization request packet - possibly malformed packet, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num>13078 WARN Device-administration Invalid TACACS+ authorization request packet - possibly malformed packet, <log details>

以威胁防护为中心的 NAC

- 消息代码: 91001

严重性: 错误 (ERROR)

消息文本: IRF 核心引擎未运行 (IRF Core Engine is not running)

消息说明: IRF 核心引擎未运行

本地目标消息格式: <timestamp> <seq_num> 91001 ERROR IRF: IRF Core Engine is not running, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91001 ERROR IRF: IRF Core Engine is not running, <log details>

- 消息代码: 91002

严重性: 错误 (ERROR)

消息文本: 与适配器的连接断开 (Lost connection to adapter)

消息说明: 与适配器的连接断开

本地目标消息格式: <timestamp> <seq_num> 91002 ERROR IRF: Lost connection to adapter, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91002 ERROR IRF: Lost connection to adapter, <log details>

- 消息代码: 91003

严重性: 信息 (INFO)

消息文本: 适配器实例已停止 (Stopped adapter instance)

消息说明: 适配器实例已停止

本地目标消息格式: <timestamp> <seq_num> 91003 INFO IRF: Stopped adapter instance, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91003 INFO IRF: Stopped adapter instance,
<log details>

- 消息代码: 91004

严重性: 信息 (INFO)

消息文本: 适配器实例已启动 (Started adapter instance)

消息说明: 适配器实例已启动

本地目标消息格式: <timestamp> <seq_num> 91004 INFO IRF: Started adapter instance, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91004 INFO IRF: Started adapter instance,
<log details>

- 消息代码: 91005

严重性: 信息 (INFO)

消息文本: 适配器实例的配置已更改 (Configuration changed for adapter instance)

消息说明: 适配器实例的配置已更改

本地目标消息格式: <timestamp> <seq_num> 91005 INFO IRF: Configuration changed for adapter
instance, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91005 INFO IRF: Configuration changed
for adapter instance, <log details>

- 消息代码: 91006

严重性: 错误 (ERROR)

消息文本: 适配器实例发生错误 (An error occurred for adapter instance)

消息说明: 适配器实例发生错误

本地目标消息格式: <timestamp> <seq_num> 91006 ERROR IRF: An error occurred for adapter
instance, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91006 ERROR IRF: An error occurred for
adapter instance, <log details>

- 消息代码: 91007

严重性: 信息 (INFO)

消息文本: 收到威胁事件 (Threat event received)

消息说明: 收到威胁事件

本地目标消息格式: <timestamp> <seq_num> 91007 INFO IRF: Threat event received, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91007 INFO IRF: Threat event received,
<log details>

- 消息代码: 91008

严重性: 严重 (FATAL)

消息文本: 漏洞扫描失败 (Vulnerability Scan failure)

消息说明: 漏洞扫描失败

本地目标消息格式: <timestamp> <seq_num> 91008 FATAL IRF: Vulnerability Scan failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91008 FATAL IRF: Vulnerability Scan failure, <log details>

- 消息代码: 91009

严重性: 严重 (FATAL)

消息文本: 适配器遇到连接或配置错误 (Adapter had encountered a connection or configuration error)

消息说明: 适配器遇到连接或配置错误

本地目标消息格式: <timestamp> <seq_num> 91009 FATAL IRF: Adapter had encountered a connection or configuration error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91009 FATAL IRF: Adapter had encountered a connection or configuration error, <log details>

- 消息代码: 91010

严重性: 严重 (FATAL)

消息文本: IRF 服务组件报告了一些错误 (An IRF Service component has reported some errors)

消息说明: IRF 服务组件报告了一些错误

本地目标消息格式: <timestamp> <seq_num> 91010 FATAL IRF: An IRF Service component has reported some errors, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91010 FATAL IRF: An IRF Service component has reported some errors, <log details>

- 消息代码: 91011

严重性: 信息 (INFO)

消息文本: IRF 服务组件已发送一些通知 (An IRF Service component has send some notification)

消息说明: IRF 服务组件已发送一些通知

本地目标消息格式: <timestamp> <seq_num> 91011 INFO IRF: An IRF Service component has send some notification, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91011 INFO IRF: An IRF Service component has send some notification, <log details>

- 消息代码: 91012

严重性: 严重 (FATAL)

消息文本: IRF 服务组件关闭 (An IRF Service component is down)

消息说明: IRF 服务组件关闭

本地目标消息格式: <timestamp> <seq_num> 91012 FATAL IRF: An IRF Service component is down, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91012 FATAL IRF: An IRF Service component is down, <log details>

- 消息代码: 91013

严重性: 信息 (INFO)

消息文本: COA 已启动 (COA initiated)

消息说明: 授权更改已启动

本地目标消息格式: <timestamp> <seq_num> 91013 INFO IRF: COA initiated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91013 INFO IRF: COA initiated, <log details>

- 消息代码: 91014

严重性: 信息 (INFO)

消息文本: COA 成功 (COA successful)

消息说明: 授权更改成功

本地目标消息格式: <timestamp> <seq_num> 91014 INFO IRF: COA successful, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91014 INFO IRF: COA successful, <log details>

- 消息代码: 91015

严重性: 错误 (ERROR)

消息文本: COA 已启动 (COA initiated)

消息说明: 授权更改已启动

本地目标消息格式: <timestamp> <seq_num> 91015 ERROR IRF: COA initiated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91015 ERROR IRF: COA initiated, <log details>

- 消息代码: 91016

严重性: 信息 (INFO)

消息文本: 适配器连接已启动 (Adapter connection initiated)

消息说明: 适配器连接已启动

本地目标消息格式: <timestamp> <seq_num> 91016 INFO IRF: Adapter connection initiated, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91016 INFO IRF: Adapter connection initiated, <log details>

- 消息代码: 91017

严重性: 信息 (INFO)

消息文本: 适配器连接成功 (Adapter connection success)

消息说明: 适配器连接成功

本地目标消息格式: <timestamp> <seq_num> 91017 INFO IRF: Adapter connection success, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91017 INFO IRF: Adapter connection success, <log details>

- 消息代码: 91018

严重性: 错误 (ERROR)

消息文本: 适配器连接失败 (Adapter connection failed)

消息说明: 适配器连接失败

本地目标消息格式: <timestamp> <seq_num> 91018 ERROR IRF: Adapter connection failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91018 ERROR IRF: Adapter connection failed, <log details>

- 消息代码: 91019

严重性: 信息 (INFO)

消息文本: 漏洞评估扫描状态 (Vulnerability Assessment Scan Status)

消息说明：漏洞评估扫描状态

本地目标消息格式：<timestamp> <seq_num> 91019 INFO IRF: Vulnerability Assessment Scan Status, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91019 INFO IRF: Vulnerability Assessment Scan Status, <log details>

- 消息代码：91020

严重性：错误 (ERROR)

消息文本：用户的 Active Directory 拨入访问被拒绝。(Active Directory dialin access denied for user.)

消息说明：用户的 Active Directory 拨入访问被拒绝。

本地目标消息格式：<timestamp> <seq_num> 91020 ERROR External-Active-Directory: Active Directory dialin access denied for user., <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91020 ERROR External-Active-Directory: Active Directory dialin access denied for user., <log details>

- 消息代码：91030

严重性：信息 (INFO)

消息文本：RADIUS DTLS 握手开始 (RADIUS DTLS handshake started)

消息说明：RADIUS DTLS 握手开始

本地目标消息格式：<timestamp> <seq_num> 91030 INFO RADIUS: RADIUS DTLS handshake started, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91030 INFO RADIUS: RADIUS DTLS handshake started, <log details>

- 消息代码：91031

严重性：信息 (INFO)

消息文本：RADIUS DTLS：已收到 client hello 消息 (RADIUS DTLS: received client hello message)

消息说明：RADIUS DTLS：已收到 client hello 消息

本地目标消息格式：<timestamp> <seq_num> 91031 INFO RADIUS: RADIUS DTLS: received client hello message, <log details>

远程目标消息格式：<pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91031 INFO RADIUS: RADIUS DTLS: received client hello message, <log details>

- 消息代码：91032

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 已发送 server hello 消息 (RADIUS DTLS: sent server hello message)

消息说明: RADIUS DTLS: 已发送 server hello 消息

本地目标消息格式: <timestamp> <seq_num> 91032 INFO RADIUS: RADIUS DTLS: sent server hello message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91032 INFO RADIUS: RADIUS DTLS: sent server hello message, <log details>

- 消息代码: 91033

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 已发送服务器证书 (RADIUS DTLS: sent server certificate)

消息说明: RADIUS DTLS: 已发送服务器证书

本地目标消息格式: <timestamp> <seq_num> 91033 INFO RADIUS: RADIUS DTLS: sent server certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91033 INFO RADIUS: RADIUS DTLS: sent server certificate, <log details>

- 消息代码: 91034

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 已发送客户端证书请求 (RADIUS DTLS: sent client certificate request)

消息说明: RADIUS DTLS: 已发送客户端证书请求

本地目标消息格式: <timestamp> <seq_num> 91034 INFO RADIUS: RADIUS DTLS: sent client certificate request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91034 INFO RADIUS: RADIUS DTLS: sent client certificate request, <log details>

- 消息代码: 91035

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 已发送 server done 消息 (RADIUS DTLS: sent server done message)

消息说明: RADIUS DTLS: 已发送 server done 消息

本地目标消息格式: <timestamp> <seq_num> 91035 INFO RADIUS: RADIUS DTLS: sent server done message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91035 INFO RADIUS: RADIUS DTLS: sent server done message, <log details>

- 消息代码: 91036
 - 严重性: 信息 (INFO)
 - 消息文本: RADIUS DTLS: 已收到客户端证书 (RADIUS DTLS: received client certificate)
 - 消息说明: RADIUS DTLS: 已收到客户端证书
 - 本地目标消息格式: <timestamp> <seq_num> 91036 INFO RADIUS: RADIUS DTLS: received client certificate, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91036 INFO RADIUS: RADIUS DTLS: received client certificate, <log details>

- 消息代码: 91037
 - 严重性: 信息 (INFO)
 - 消息文本: RADIUS DTLS: 已收到 client key exchange 消息 (RADIUS DTLS: received client key exchange message)
 - 消息说明: RADIUS DTLS: 已收到 client key exchange 消息
 - 本地目标消息格式: <timestamp> <seq_num> 91037 INFO RADIUS: RADIUS DTLS: received client key exchange message, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91037 INFO RADIUS: RADIUS DTLS: received client key exchange message, <log details>

- 消息代码: 91038
 - 严重性: 信息 (INFO)
 - 消息文本: RADIUS DTLS: 已收到 certificate verify 消息 (received certificate verify message)
 - 消息说明: RADIUS DTLS: 已收到 certificate verify 消息
 - 本地目标消息格式: <timestamp> <seq_num> 91038 INFO RADIUS: RADIUS DTLS: received certificate verify message, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91038 INFO RADIUS: RADIUS DTLS: received certificate verify message, <log details>

- 消息代码: 91039
 - 严重性: 信息 (INFO)
 - 消息文本: RADIUS DTLS: 已收到 finished 消息 (RADIUS DTLS: received finished message)
 - 消息说明: RADIUS DTLS: 已收到 finished 消息
 - 本地目标消息格式: <timestamp> <seq_num> 91039 INFO RADIUS: RADIUS DTLS: received finished message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91039 INFO RADIUS: RADIUS DTLS:
received finished message, <log details>

- 消息代码: 91040

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 已发送 change cipher spec 消息 (RADIUS DTLS: sent change cipher spec message)

消息说明: RADIUS DTLS: 已发送 change cipher spec 消息

本地目标消息格式: <timestamp> <seq_num> 91040 INFO RADIUS: RADIUS DTLS: sent change cipher spec message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91040 INFO RADIUS: RADIUS DTLS:
sent change cipher spec message, <log details>

- 消息代码: 91041

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 已发送 finished 消息 (RADIUS DTLS: sent finished message)

消息说明: RADIUS DTLS: 已发送 finished 消息

本地目标消息格式: <timestamp> <seq_num> 91041 INFO RADIUS: RADIUS DTLS: sent finished message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91041 INFO RADIUS: RADIUS DTLS:
sent finished message, <log details>

- 消息代码: 91042

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 已发送 client hello 消息 (RADIUS DTLS: sent client hello message)

消息说明: RADIUS DTLS: 已发送 client hello 消息

本地目标消息格式: <timestamp> <seq_num> 91042 INFO RADIUS: RADIUS DTLS: sent client hello message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91042 INFO RADIUS: RADIUS DTLS:
sent client hello message, <log details>

- 消息代码: 91043

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 已收到 server hello 消息 (RADIUS DTLS: received server hello message)

消息说明: RADIUS DTLS: 已收到 server hello 消息

本地目标消息格式: <timestamp> <seq_num> 91043 INFO RADIUS: RADIUS DTLS: received server hello message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 91043 INFO RADIUS: RADIUS DTLS: received server hello message, <log details>

- 消息代码: 91044

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 已收到服务器证书 (RADIUS DTLS: received server certificate)

消息说明: RADIUS DTLS: 已收到服务器证书

本地目标消息格式: <timestamp> <seq_num> 91044 INFO RADIUS: RADIUS DTLS: received server certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 91044 INFO RADIUS: RADIUS DTLS: received server certificate, <log details>

- 消息代码: 91045

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 已收到服务器证书请求 (RADIUS DTLS: received server certificate request)

消息说明: RADIUS DTLS: 已收到服务器证书请求

本地目标消息格式: <timestamp> <seq_num> 91045 INFO RADIUS: RADIUS DTLS: received server certificate request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 91045 INFO RADIUS: RADIUS DTLS: received server certificate request, <log details>

- 消息代码: 91046

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 已收到 server done 消息 (RADIUS DTLS: received server done message)

消息说明: RADIUS DTLS: 已收到 server done 消息

本地目标消息格式: <timestamp> <seq_num> 91046 INFO RADIUS: RADIUS DTLS: received server done message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 91046 INFO RADIUS: RADIUS DTLS: received server done message, <log details>

- 消息代码: 91047

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 已发送客户端证书 (RADIUS DTLS: sent client certificate)

消息说明: RADIUS DTLS: 已发送客户端证书

本地目标消息格式: <timestamp> <seq_num> 91047 INFO RADIUS: RADIUS DTLS: sent client certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 91047 INFO RADIUS: RADIUS DTLS: sent client certificate, <log details>

- 消息代码: 91048

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 已发送 client key exchange 消息 (RADIUS DTLS: sent client key exchange message)

消息说明: RADIUS DTLS: 已发送 client key exchange 消息

本地目标消息格式: <timestamp> <seq_num> 91048 INFO RADIUS: RADIUS DTLS: sent client key exchange message, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 91048 INFO RADIUS: RADIUS DTLS: sent client key exchange message, <log details>

- 消息代码: 91049

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 读取服务器会话票证 (RADIUS DTLS: read server session ticket)

消息说明: RADIUS DTLS: 读取服务器会话票证

本地目标消息格式: <timestamp> <seq_num> 91049 INFO RADIUS: RADIUS DTLS: read server session ticket, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 91049 INFO RADIUS: RADIUS DTLS: read server session ticket, <log details>

- 消息代码: 91050

严重性: 警告 (WARN)

消息文本: RADIUS DTLS: TLS 握手失败, 因为证书链存在未知 CA (RADIUS DTLS: TLS handshake failed because of an unknown CA in the certificates chain)

消息说明: RADIUS DTLS: SSL 握手失败, 因为证书链存在未知 CA

本地目标消息格式: <timestamp> <seq_num> 91050 WARN RADIUS: RADIUS DTLS: TLS handshake failed because of an unknown CA in the certificates chain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 91050 WARN RADIUS: RADIUS DTLS: TLS handshake failed because of an unknown CA in the certificates chain, <log details>

- 消息代码: 91051
 - 严重性: 警告 (WARN)
 - 消息文本: RADIUS DTLS: TLS 握手失败, 因为证书链中存在损坏的证书 (RADIUS DTLS: TLS handshake failed because of a bad certificate in the certificate chain)
 - 消息说明: RADIUS DTLS: TLS 握手失败, 因为证书链中存在损坏的证书
 - 本地目标消息格式: <timestamp> <seq_num> 91051 WARN RADIUS: RADIUS DTLS: TLS handshake failed because of a bad certificate in the certificate chain, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 91051 WARN RADIUS: RADIUS DTLS: TLS handshake failed because of a bad certificate in the certificate chain, <log details>

- 消息代码: 91052
 - 严重性: 警告 (WARN)
 - 消息文本: RADIUS DTLS: TLS 握手失败, 因为解密错误 (RADIUS DTLS: TLS handshake failed because decryption error)
 - 消息说明: RADIUS DTLS: TLS 握手失败, 因为解密错误
 - 本地目标消息格式: <timestamp> <seq_num> 91052 WARN RADIUS: RADIUS DTLS: TLS handshake failed because decryption error, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 91052 WARN RADIUS: RADIUS DTLS: TLS handshake failed because decryption error, <log details>

- 消息代码: 91053
 - 严重性: 警告 (WARN)
 - 消息文本: RADIUS DTLS: TLS 握手失败, 因为证书已过期 (RADIUS DTLS: TLS handshake failed because certificate has expired)
 - 消息说明: RADIUS DTLS: TLS 握手失败, 因为证书已过期
 - 本地目标消息格式: <timestamp> <seq_num> 91053 WARN RADIUS: RADIUS DTLS: TLS handshake failed because certificate has expired, <log details>
 - 远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 91053 WARN RADIUS: RADIUS DTLS: TLS handshake failed because certificate has expired, <log details>

- 消息代码: 91054
 - 严重性: 警告 (WARN)
 - 消息文本: RADIUS DTLS: TLS 握手失败, 因为证书未知 (RADIUS DTLS: TLS handshake failed because unknown certificate)
 - 消息说明: RADIUS DTLS: TLS 握手失败, 因为证书未知

本地目标消息格式: <timestamp> <seq_num> 91054 WARN RADIUS: RADIUS DTLS: TLS handshake failed because unknown certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91054 WARN RADIUS: RADIUS DTLS: TLS handshake failed because unknown certificate, <log details>

- 消息代码: 91055

严重性: 信息 (INFO)

消息文本: RADIUS 数据包已加密 (RADIUS packet is encrypted)

消息说明: RADIUS 数据包已加密

本地目标消息格式: <timestamp> <seq_num> 91055 INFO RADIUS: RADIUS packet is encrypted, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91055 INFO RADIUS: RADIUS packet is encrypted, <log details>

- 消息代码: 91056

严重性: 警告 (WARN)

消息文本: RADIUS DTLS: TLS 握手失败, 因为协议版本不受支持 (RADIUS DTLS: TLS handshake failed because of unsupported protocol version)

消息说明: RADIUS DTLS: TLS 握手失败, 因为协议版本不受支持

本地目标消息格式: <timestamp> <seq_num> 91056 WARN RADIUS: RADIUS DTLS: TLS handshake failed because of unsupported protocol version, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91056 WARN RADIUS: RADIUS DTLS: TLS handshake failed because of unsupported protocol version, <log details>

- 消息代码: 91057

严重性: 警告 (WARN)

消息文本: RADIUS DTLS CoA: TLS 握手失败, 因为证书链存在未知 CA (RADIUS DTLS CoA: TLS handshake failed because of an unknown CA in the certificates chain)

消息说明: RADIUS DTLS CoA: SSL 握手失败, 因为证书链存在未知 CA

本地目标消息格式: <timestamp> <seq_num> 91057 WARN RADIUS: RADIUS DTLS CoA: TLS handshake failed because of an unknown CA in the certificates chain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91057 WARN RADIUS: RADIUS DTLS CoA: TLS handshake failed because of an unknown CA in the certificates chain, <log details>

- 消息代码: 91058

严重性: 警告 (WARN)

消息文本: RADIUS DTLS CoA: TLS 握手失败, 因为证书链中存在损坏的证书 (RADIUS DTLS CoA: TLS handshake failed because of a bad certificate in the certificate chain)

消息说明: RADIUS DTLS CoA: TLS 握手失败, 因为证书链中存在损坏的证书

本地目标消息格式: <timestamp> <seq_num> 91058 WARN RADIUS: RADIUS DTLS CoA: TLS handshake failed because of a bad certificate in the certificate chain, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 91058 WARN RADIUS: RADIUS DTLS CoA: TLS handshake failed because of a bad certificate in the certificate chain, <log details>

- 消息代码: 91059

严重性: 警告 (WARN)

消息文本: RADIUS DTLS CoA: TLS 握手失败, 因为解密错误 (RADIUS DTLS CoA: TLS handshake failed because decryption error)

消息说明: RADIUS DTLS CoA: TLS 握手失败, 因为解密错误

本地目标消息格式: <timestamp> <seq_num> 91059 WARN RADIUS: RADIUS DTLS CoA: TLS handshake failed because decryption error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 91059 WARN RADIUS: RADIUS DTLS CoA: TLS handshake failed because decryption error, <log details>

- 消息代码: 91060

严重性: 警告 (WARN)

消息文本: RADIUS DTLS CoA: TLS 握手失败, 因为证书已过期 (RADIUS DTLS CoA: TLS handshake failed because certificate has expired)

消息说明: RADIUS DTLS CoA: TLS 握手失败, 因为证书已过期

本地目标消息格式: <timestamp> <seq_num> 91060 WARN RADIUS: RADIUS DTLS CoA: TLS handshake failed because certificate has expired, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 91060 WARN RADIUS: RADIUS DTLS CoA: TLS handshake failed because certificate has expired, <log details>

- 消息代码: 91061

严重性: 警告 (WARN)

消息文本: RADIUS DTLS CoA: TLS 握手失败, 因为证书未知 (RADIUS DTLS CoA: TLS handshake failed because unknown certificate)

消息说明: RADIUS DTLS CoA: TLS 握手失败, 因为证书未知

本地目标消息格式: <timestamp> <seq_num> 91061 WARN RADIUS: RADIUS DTLS CoA: TLS handshake failed because unknown certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91061 WARN RADIUS: RADIUS DTLS
CoA: TLS handshake failed because unknown certificate, <log details>

- 消息代码: 91062

严重性: 警告 (WARN)

消息文本: RADIUS DTLS CoA: TLS 握手失败, 因为协议版本不受支持 (RADIUS DTLS CoA:
TLS handshake failed because of unsupported protocol version)

消息说明: RADIUS DTLS CoA: TLS 握手失败, 因为协议版本不受支持

本地目标消息格式: <timestamp> <seq_num> 91062 WARN RADIUS: RADIUS DTLS CoA: TLS
handshake failed because of unsupported protocol version, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91062 WARN RADIUS: RADIUS DTLS
CoA: TLS handshake failed because of unsupported protocol version, <log details>

- 消息代码: 91063

严重性: 警告 (WARN)

消息文本: RADIUS DTLS CoA: 在系统证书列表中未找到客户端证书 (RADIUS DTLS CoA:
Client Certificate in not found in System certificates list)

消息说明: RADIUS DTLS CoA: 在系统证书列表中未找到客户端证书

本地目标消息格式: <timestamp> <seq_num> 91063 WARN RADIUS: RADIUS DTLS CoA: Client
Certificate in not found in System certificates list, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91063 WARN RADIUS: RADIUS DTLS
CoA: Client Certificate in not found in System certificates list, <log details>

- 消息代码: 91064

严重性: 警告 (WARN)

消息文本: 由于 OCSP 发现已撤销证书, RADIUS DTLS 连接断开 (RADIUS DTLS connection
disconnect due to OCSP found revoked certificate)

消息说明: OCSP 检查结果发现, 已撤销用于 RADIUS DTLS 连接的证书

本地目标消息格式: <timestamp> <seq_num> 91064 WARN RADIUS: RADIUS DTLS connection
disconnect due to OCSP found revoked certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91064 WARN RADIUS: RADIUS DTLS
connection disconnect due to OCSP found revoked certificate, <log details>

- 消息代码: 91065

严重性: 警告 (WARN)

消息文本: 由于 CRL 发现已撤销证书, RADIUS DTLS 连接断开 (RADIUS DTLS connection disconnect due to CRL found revoked certificate)

消息说明: CRL 检查结果发现, 已撤销用于 RADIUS DTLS 连接的证书

本地目标消息格式: <timestamp> <seq_num> 91065 WARN RADIUS: RADIUS DTLS connection disconnect due to CRL found revoked certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 91065 WARN RADIUS: RADIUS DTLS connection disconnect due to CRL found revoked certificate, <log details>

- 消息代码: 91066

严重性: 警告 (WARN)

消息文本: 因为客户端证书尚未生效, RADIUS DTLS 连接断开 (RADIUS DTLS connection disconnect because of the client certificate is not yet valid)

消息说明: OCSP 检查结果发现, 用于 RADIUS DTLS 连接的证书尚未生效

本地目标消息格式: <timestamp> <seq_num> 91066 WARN RADIUS: RADIUS DTLS connection disconnect because of the client certificate is not yet valid, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 91066 WARN RADIUS: RADIUS DTLS connection disconnect because of the client certificate is not yet valid, <log details>

- 消息代码: 91067

严重性: 警告 (WARN)

消息文本: 由于 OCSP 发现已撤销证书, RADIUS DTLS CoA 连接断开 (RADIUS DTLS CoA connection disconnect due to OCSP found revoked certificate)

消息说明: OCSP 检查结果发现, 已撤销用于 RADIUS DTLS CoA 连接的证书

本地目标消息格式: <timestamp> <seq_num> 91067 WARN RADIUS: RADIUS DTLS CoA connection disconnect due to OCSP found revoked certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 91067 WARN RADIUS: RADIUS DTLS CoA connection disconnect due to OCSP found revoked certificate, <log details>

- 消息代码: 91068

严重性: 警告 (WARN)

消息文本: 由于 CRL 发现已撤销证书, RADIUS DTLS CoA 连接断开 (RADIUS DTLS CoA connection disconnect due to CRL found revoked certificate)

消息说明: CRL 检查结果发现, 已撤销用于 RADIUS DTLS CoA 连接的证书

本地目标消息格式: <timestamp> <seq_num> 91068 WARN RADIUS: RADIUS DTLS CoA connection disconnect due to CRL found revoked certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91068 WARN RADIUS: RADIUS DTLS
CoA connection disconnect due to CRL found revoked certificate, <log details>

- 消息代码: 91069

严重性: 警告 (WARN)

消息文本: 因为服务器证书尚未生效, RADIUS DTLS CoA 连接断开 (RADIUS DTLS CoA
connection disconnect because of the server certificate is not yet valid)

消息说明: OSCP 检查结果发现, 用于 RADIUS DTLS CoA 连接的证书尚未生效

本地目标消息格式: <timestamp> <seq_num> 91069 WARN RADIUS: RADIUS DTLS CoA connection
disconnect because of the server certificate is not yet valid, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91069 WARN RADIUS: RADIUS DTLS
CoA connection disconnect because of the server certificate is not yet valid, <log details>

- 消息代码: 91070

严重性: 信息 (INFO)

消息文本: RADIUS DTLS CoA 握手开始 (RADIUS DTLS CoA handshake started)

消息说明: RADIUS DTLS CoA 握手开始

本地目标消息格式: <timestamp> <seq_num> 91070 INFO RADIUS: RADIUS DTLS CoA handshake
started, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91070 INFO RADIUS: RADIUS DTLS
CoA handshake started, <log details>

- 消息代码: 91071

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 向 CA 的主 OSCP 服务器发送了 OSCP 请求 (RADIUS DTLS: Sent
an OSCP request to the primary OSCP server for the CA)

消息说明: RADIUS DTLS: 向 CA 的主 OSCP 服务器发送 OSCP 请求。

本地目标消息格式: <timestamp> <seq_num> 91071 INFO RADIUS: RADIUS DTLS: Sent an OSCP
request to the primary OSCP server for the CA, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91071 INFO RADIUS: RADIUS DTLS:
Sent an OSCP request to the primary OSCP server for the CA, <log details>

- 消息代码: 91072

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 向 CA 的辅助 OSCP 服务器发送了 OSCP 请求 (RADIUS DTLS: Sent
an OSCP request to the secondary OSCP server for the CA)

消息说明: RADIUS DTLS: 向 CA 的辅助 OCSP 服务器发送 OCSP 请求。

本地目标消息格式: <timestamp> <seq_num> 91072 INFO RADIUS: RADIUS DTLS: Sent an OCSP request to the secondary OCSP server for the CA, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 91072 INFO RADIUS: RADIUS DTLS: Sent an OCSP request to the secondary OCSP server for the CA, <log details>

- 消息代码: 91073

严重性: 警告 (WARN)

消息文本: RADIUS DTLS: 与 OCSP 服务器的对话以失败告终 (RADIUS DTLS: Conversation with OCSP server ended with failure)

消息说明: RADIUS DTLS: 与 OCSP 服务器的对话以失败告终。

本地目标消息格式: <timestamp> <seq_num> 91073 WARN RADIUS: RADIUS DTLS: Conversation with OCSP server ended with failure, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 91073 WARN RADIUS: RADIUS DTLS: Conversation with OCSP server ended with failure, <log details>

- 消息代码: 91074

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 已收到 OCSP 响应 (RADIUS DTLS: Received OCSP response)

消息说明: RADIUS DTLS: 已收到 OCSP 响应。

本地目标消息格式: <timestamp> <seq_num> 91074 INFO RADIUS: RADIUS DTLS: Received OCSP response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 91074 INFO RADIUS: RADIUS DTLS: Received OCSP response, <log details>

- 消息代码: 91075

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 用户证书的 OCSP 状态为良好 (RADIUS DTLS: OCSP status of user certificate is good)

消息说明: RADIUS DTLS: OCSP 服务器报告用户证书的状态为良好。

本地目标消息格式: <timestamp> <seq_num> 91075 INFO RADIUS: RADIUS DTLS: OCSP status of user certificate is good, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num> <timestamp> <seq_num> 91075 INFO RADIUS: RADIUS DTLS: OCSP status of user certificate is good, <log details>

- 消息代码: 91076

严重性: 警告 (WARN)

消息文本: RADIUS DTLS: 用户证书的 OCSP 状态为已撤销 (RADIUS DTLS: OCSP status of user certificate is revoked)

消息说明: RADIUS DTLS: OCSP 服务器报告用户证书的状态为已撤销。

本地目标消息格式: <timestamp> <seq_num> 91076 WARN RADIUS: RADIUS DTLS: OCSP status of user certificate is revoked, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 91076 WARN RADIUS: RADIUS DTLS: OCSP status of user certificate is revoked, <log details>

- 消息代码: 91077

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 用户证书的 OCSP 状态为未知 (RADIUS DTLS: OCSP status of user certificate is unknown)

消息说明: RADIUS DTLS: OCSP 服务器报告用户证书的状态为未知, 或者 ISE 无法连接到 OCSP 服务器。

本地目标消息格式: <timestamp> <seq_num> 91077 INFO RADIUS: RADIUS DTLS: OCSP status of user certificate is unknown, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 91077 INFO RADIUS: RADIUS DTLS: OCSP status of user certificate is unknown, <log details>

- 消息代码: 91078

严重性: 警告 (WARN)

消息文本: RADIUS DTLS: 握手失败, 因为 OCSP 状态为未知 (RADIUS DTLS: Handshake failed because OCSP status is unknown)

消息说明: RADIUS DTLS: 握手失败, 因为 OCSP 状态为未知。

本地目标消息格式: <timestamp> <seq_num> 91078 WARN RADIUS: RADIUS DTLS: Handshake failed because OCSP status is unknown, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 91078 WARN RADIUS: RADIUS DTLS: Handshake failed because OCSP status is unknown, <log details>

- 消息代码: 91079

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 已执行回退到辅助 OCSP 服务器 (RADIUS DTLS: Performed fallback to secondary OCSP server)

消息说明: RADIUS DTLS: 已执行回退到辅助 OCSP 服务器。

本地目标消息格式: <timestamp> <seq_num> 91079 INFO RADIUS: RADIUS DTLS: Performed fallback to secondary OCSP server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91079 INFO RADIUS: RADIUS DTLS: Performed fallback to secondary OCSP server, <log details>

- 消息代码: 91080

严重性: 警告 (WARN)

消息文本: RADIUS DTLS: 在与 OCSP 服务器通信的过程中出现内部错误 (RADIUS DTLS: Internal error occurred during communication with the OCSP server)

消息说明: RADIUS DTLS: 在与 OCSP 服务器通信的过程中出现内部错误。OCSP 服务器的配置与 ISE OCSP 客户端不匹配。

本地目标消息格式: <timestamp> <seq_num> 91080 WARN RADIUS: RADIUS DTLS: Internal error occurred during communication with the OCSP server, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91080 WARN RADIUS: RADIUS DTLS: Internal error occurred during communication with the OCSP server, <log details>

- 消息代码: 91081

严重性: 警告 (WARN)

消息文本: RADIUS DTLS: OCSP 服务器 URL 无效 (RADIUS DTLS: OCSP server URL is invalid)

消息说明: RADIUS DTLS: OCSP 服务器 URL 无效, 并且无法正确解析。

本地目标消息格式: <timestamp> <seq_num> 91081 WARN RADIUS: RADIUS DTLS: OCSP server URL is invalid, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91081 WARN RADIUS: RADIUS DTLS: OCSP server URL is invalid, <log details>

- 消息代码: 91082

严重性: 警告 (WARN)

消息文本: RADIUS DTLS: 连接 OCSP 服务器失败 (RADIUS DTLS: Connection to OCSP server failed)

消息说明: RADIUS DTLS: 尝试连接 OCSP 服务器失败。

本地目标消息格式: <timestamp> <seq_num> 91082 WARN RADIUS: RADIUS DTLS: Connection to OCSP server failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91082 WARN RADIUS: RADIUS DTLS: Connection to OCSP server failed, <log details>

- 消息代码: 91083

严重性: 警告 (WARN)

消息文本: RADIUS DTLS: OCSP 服务器响应无效 (RADIUS DTLS: OCSP server response is invalid)

消息说明: RADIUS DTLS: OCSP 服务器返回了一个 ISE 无法解析的响应。

本地目标消息格式: <timestamp> <seq_num> 91083 WARN RADIUS: RADIUS DTLS: OCSP server response is invalid, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91083 WARN RADIUS: RADIUS DTLS: OCSP server response is invalid, <log details>

- 消息代码: 91084

严重性: 警告 (WARN)

消息文本: RADIUS DTLS: OCSP 服务器返回错误 (RADIUS DTLS: OCSP server returned an error)

消息说明: RADIUS DTLS: OCSP 服务器在响应 ISE OCSP 请求时返回了错误。

本地目标消息格式: <timestamp> <seq_num> 91084 WARN RADIUS: RADIUS DTLS: OCSP server returned an error, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91084 WARN RADIUS: RADIUS DTLS: OCSP server returned an error, <log details>

- 消息代码: 91085

严重性: 警告 (WARN)

消息文本: RADIUS DTLS: OCSP 服务器未在响应中提供所需的 Nonce (RADIUS DTLS: OCSP server did not provide the required nonce in response)

消息说明: RADIUS DTLS: ISE 中特定的 OCSP 服务配置为针对 OCSP 服务器验证使用 Nonce, 但 OCSP 服务器未在响应中提供 Nonce。

本地目标消息格式: <timestamp> <seq_num> 91085 WARN RADIUS: RADIUS DTLS: OCSP server did not provide the required nonce in response, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91085 WARN RADIUS: RADIUS DTLS: OCSP server did not provide the required nonce in response, <log details>

- 消息代码: 91086

严重性: 警告 (WARN)

消息文本: RADIUS DTLS: OCSP 服务器响应 Nonce 验证失败 (RADIUS DTLS: OCSP server response nonce verification failed)

消息说明: RADIUS DTLS: OCSP 服务器响应中返回的 Nonce 加密验证失败。

本地目标消息格式: <timestamp> <seq_num> 91086 WARN RADIUS: RADIUS DTLS: OCSP server response nonce verification failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91086 WARN RADIUS: RADIUS DTLS:
OCSP server response nonce verification failed, <log details>

- 消息代码: 91087

严重性: 警告 (WARN)

消息文本: RADIUS DTLS: OCSP 服务器响应时间验证失败 (RADIUS DTLS: OCSP server response time verification failed)

消息说明: RADIUS DTLS: 在 OCSP 服务器中, “本次更新” (This Update) 或 “下次更新” (Next Update) 字段的响应验证失败。

本地目标消息格式: <timestamp><seq_num> 91087 WARN RADIUS: RADIUS DTLS: OCSP server response time verification failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91087 WARN RADIUS: RADIUS DTLS:
OCSP server response time verification failed, <log details>

- 消息代码: 91088

严重性: 警告 (WARN)

消息文本: RADIUS DTLS: OCSP 服务器响应签名验证失败 (RADIUS DTLS: OCSP server response signature verification failed)

消息说明: RADIUS DTLS: OCSP 服务器响应签名验证失败。

本地目标消息格式: <timestamp><seq_num> 91088 WARN RADIUS: RADIUS DTLS: OCSP server response signature verification failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91088 WARN RADIUS: RADIUS DTLS:
OCSP server response signature verification failed, <log details>

- 消息代码: 91089

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 查找 OCSP 缓存中的证书状态 (RADIUS DTLS: Lookup certificate status in OCSP cache)

消息说明: RADIUS DTLS: 查找 OCSP 缓存中的证书状态。

本地目标消息格式: <timestamp> <seq_num> 91089 INFO RADIUS: RADIUS DTLS: Lookup certificate status in OCSP cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91089 INFO RADIUS: RADIUS DTLS:
Lookup certificate status in OCSP cache, <log details>

- 消息代码: 91090

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 未在 OCSP 缓存中找到证书状态 (RADIUS DTLS:Certificate status was not found in OCSP cache)

消息说明: RADIUS DTLS: 未在 OCSP 缓存中找到证书状态; ISE 将对配置好的 OCSP 服务器执行 OCSP 请求。

本地目标消息格式: <timestamp> <seq_num> 91090 INFO RADIUS: RADIUS DTLS:Certificate status was not found in OCSP cache, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 91090 INFO RADIUS: RADIUS DTLS:Certificate status was not found in OCSP cache, <log details>

- 消息代码: 91091

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 在 OCSP 缓存中查找证书状态成功 (RADIUS DTLS: Lookup certificate status in OCSP cache)

消息说明: RADIUS DTLS: 在 OCSP 缓存中查找证书状态成功; ISE 将使用此状态, 但不执行对配置好的 OCSP 服务器的 OCSP 请求。

本地目标消息格式: <timestamp> <seq_num> 91091 INFO RADIUS: RADIUS DTLS: Lookup Certificate status in OCSP cache succeeded, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 91091 INFO RADIUS: RADIUS DTLS: Lookup Certificate status in OCSP cache succeeded, <log details>

- 消息代码: 91092

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 如果 ISE 针对特定的 CA 进行配置, 将继续进行 CRL 验证 (RADIUS DTLS: ISE will continue to CRL verification if it is configured for specific CA)

消息说明: RADIUS DTLS: OCSP 验证失败或者返回了未知的证书状态。如果 ISE 针对特定的 CA 进行配置, 将继续进行 CRL 验证。

本地目标消息格式: <timestamp> <seq_num> 91092 INFO RADIUS: RADIUS DTLS: ISE will continue to CRL verification if it is configured for specific CA, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 91092 INFO RADIUS: RADIUS DTLS: ISE will continue to CRL verification if it is configured for specific CA, <log details>

- 消息代码: 91093

严重性: 调试 (DEBUG)

消息文本: RADIUS DTLS: 未缓存 OCSP 响应 (RADIUS DTLS: OCSP response not cached)

消息说明: RADIUS DTLS: OCSP 服务器的响应表明不应缓存响应的内容

本地目标消息格式: <timestamp> <seq_num> 91093 DEBUG RADIUS: RADIUS DTLS: OCSP response not cached, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 91093 DEBUG RADIUS: RADIUS DTLS: OCSP response not cached, <log details>

- 消息代码: 91094

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 从客户端证书的 AIA 扩展中获取 OCSP 服务器列表 (RADIUS DTLS: Take OCSP servers list from AIA extension of client certificate)

消息说明: RADIUS DTLS: 从客户端证书的 AIA 扩展中获取 OCSP 服务器列表

本地目标消息格式: <timestamp> <seq_num> 91094 INFO RADIUS: RADIUS DTLS: Take OCSP servers list from AIA extension of client certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 91094 INFO RADIUS: RADIUS DTLS: Take OCSP servers list from AIA extension of client certificate, <log details>

- 消息代码: 91095

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 从 OCSP 服务配置中获取 OCSP 服务器列表 (RADIUS DTLS: Take OCSP servers list from OCSP service configuration)

消息说明: RADIUS DTLS: 从 OCSP 服务配置中获取 OCSP 服务器列表

本地目标消息格式: <timestamp> <seq_num> 91095 INFO RADIUS: RADIUS DTLS: Take OCSP servers list from OCSP service configuration, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 91095 INFO RADIUS: RADIUS DTLS: Take OCSP servers list from OCSP service configuration, <log details>

- 消息代码: 91096

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 向列表中的下一个 OCSP 服务器发送了 OCSP 请求 (RADIUS DTLS: Sent an OCSP request to the next OCSP server in the list)

消息说明: RADIUS DTLS: 向列表中的下一个 OCSP 服务器发送了 OCSP 请求

本地目标消息格式: <timestamp> <seq_num> 91096 INFO RADIUS: RADIUS DTLS: Sent an OCSP request to the next OCSP server in the list, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg_num><timestamp> <seq_num> 91096 INFO RADIUS: RADIUS DTLS: Sent an OCSP request to the next OCSP server in the list, <log details>

- 消息代码: 91097

严重性: 警告 (WARN)

消息文本: RADIUS DTLS: 未在客户端证书的 AIA 扩展中找到有效的 OCSP 服务器 URL (RADIUS DTLS: No valid OCSP server URLs found in the AIA extension of client certificate)

消息说明: RADIUS DTLS: 如果 OCSP 服务配置为从客户端证书的 AIA 扩展中获取 OCSP 服务器列表, 那么必须至少存在一个有效的 OCSP 服务器 URL。

本地目标消息格式: <timestamp> <seq_num> 91097 WARN RADIUS: RADIUS DTLS: No valid OCSP server URLs found in the AIA extension of client certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91097 WARN RADIUS: RADIUS DTLS: No valid OCSP server URLs found in the AIA extension of client certificate, <log details>

• 消息代码: 91098

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 客户端证书的 AIA 扩展中不再有 OCSP 服务器 (RADIUS DTLS: No more OCSP servers in AIA extension of client certificate)

消息说明: RADIUS DTLS: 客户端证书的 AIA 扩展中不再有 OCSP 服务器

本地目标消息格式: <timestamp> <seq_num> 91098 INFO RADIUS: RADIUS DTLS: No more OCSP servers in AIA extension of client certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91098 INFO RADIUS: RADIUS DTLS: No more OCSP servers in AIA extension of client certificate, <log details>

• 消息代码: 91099

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 客户端证书中没有 AIA 扩展 (RADIUS DTLS: No AIA extension in client certificate)

消息说明: RADIUS DTLS: 客户端证书中没有 AIA 扩展

本地目标消息格式: <timestamp> <seq_num> 91099 INFO RADIUS: RADIUS DTLS: No AIA extension in client certificate, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91099 INFO RADIUS: RADIUS DTLS: No AIA extension in client certificate, <log details>

• 消息代码: 91100

严重性: 警告 (WARN)

消息文本: RADIUS DTLS: 握手失败, 因为 OCSP 无法访问 (RADIUS DTLS: Handshake failed because OCSP is unreachable)

消息说明: RADIUS DTLS: 握手失败, 因为 OCSP 无法访问

本地目标消息格式: <timestamp> <seq_num> 91100 WARN RADIUS: RADIUS DTLS: Handshake failed because OCSP is unreachable, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91100 WARN RADIUS: RADIUS DTLS: Handshake failed because OCSP is unreachable, <log details>

- 消息代码: 91101

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: CRL 验证撤销了用户证书 (RADIUS DTLS: User certificate was revoked by CRL verification)

消息说明: RADIUS DTLS: CRL 验证返回了已撤销证书状态。

本地目标消息格式: <timestamp><seq_num> 91101 INFO RADIUS: RADIUS DTLS: User certificate was revoked by CRL verification, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91101 INFO RADIUS: RADIUS DTLS: User certificate was revoked by CRL verification, <log details>

- 消息代码: 91102

严重性: 警告 (WARN)

消息文本: RADIUS DTLS: 客户端身份检查失败 (RADIUS DTLS: client Identity check failed)

消息说明: RADIUS DTLS: 客户端身份检查失败。

本地目标消息格式: <timestamp> <seq_num> 91102 WARN RADIUS: RADIUS DTLS: client Identity check failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91102 WARN RADIUS: RADIUS DTLS: client Identity check failed, <log details>

- 消息代码: 91103

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 需要客户端身份检查 (RADIUS DTLS: client Identity check needed)

消息说明: RADIUS DTLS: 需要客户端身份检查。

本地目标消息格式: <timestamp> <seq_num> 91103 INFO RADIUS: RADIUS DTLS: client Identity check needed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91103 INFO RADIUS: RADIUS DTLS: client Identity check needed, <log details>

- 消息代码: 91104

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 无需运行客户端身份检查 (RADIUS DTLS: no need to run Client Identity check)

消息说明: RADIUS DTLS: 无需运行客户端身份检查。

本地目标消息格式: <timestamp> <seq_num> 91104 INFO RADIUS: RADIUS DTLS: no need to run Client Identity check, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91104 INFO RADIUS: RADIUS DTLS: no need to run Client Identity check, <log details>

- 消息代码: 91105

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 已发送 client hello verify 请求 (RADIUS DTLS: sent client hello verify request)

消息说明: RADIUS DTLS: 已发送 client hello verify 请求。

本地目标消息格式: <timestamp> <seq_num> 91105 INFO RADIUS: RADIUS DTLS: sent client hello verify request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91105 INFO RADIUS: RADIUS DTLS: sent client hello verify request, <log details>

- 消息代码: 91106

严重性: 信息 (INFO)

消息文本: RADIUS DTLS: 已收到 client hello verify 请求 (RADIUS DTLS: received client hello verify request)

消息说明: RADIUS DTLS: 已收到 client hello verify 请求。

本地目标消息格式: <timestamp> <seq_num> 91106 INFO RADIUS: RADIUS DTLS: received client hello verify request, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category> <msg_id> <total seg> <seg num><timestamp> <seq_num> 91106 INFO RADIUS: RADIUS DTLS: received client hello verify request, <log details>

- 消息代码: 91107

严重性: 警告 (WARN)

消息文本: RADIUS DTLS: TLS 握手失败, 因为 client hello 验证失败 (RADIUS DTLS: TLS handshake failed because of client hello verification failed)

消息说明: RADIUS DTLS: TLS 握手失败, 因为 client hello 验证失败。

本地目标消息格式: <timestamp> <seq_num> 91107 WARN RADIUS: RADIUS DTLS: TLS handshake failed because of client hello verification failed, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num> 91107 WARN RADIUS: RADIUS DTLS:
TLS handshake failed because of client hello verification failed, <log details>

- 消息代码: 91110

严重性: 警告 (WARN)

消息文本: 一个或多个 Active Directory 诊断测试在计划运行期间失败。(One or more Active Directory diagnostic tests failed during a scheduled run.)

消息说明: 一个或多个 Active Directory 诊断测试在计划运行期间失败。

本地目标消息格式: <timestamp> <seq_num>91110 WARN RADIUS One or more Active Directory diagnostic tests failed during a scheduled run., <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>91110 WARN RADIUS One or more Active Directory diagnostic tests failed during a scheduled run., <log details>

- 消息代码: 91111

严重性: 警告 (WARN)

消息文本: 检测到高身份验证负载 (High authentication load detected)

消息说明: 检测到高身份验证负载

本地目标消息格式: <timestamp> <seq_num>91111 WARN RADIUS High authentication load detected, <log details>

远程目标消息格式: <pri_num> <timestamp> <IP address/hostname> <CISE_logging category>
<msg_id> <total seg> <seg num><timestamp> <seq_num>91111 WARN RADIUS High authentication load detected, <log details>

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

All printed copies and duplicate soft copies of this document are considered uncontrolled. See the current online version for the latest version.

Cisco has more than 200 offices worldwide. Addresses and phone numbers are listed on the Cisco website at www.cisco.com/go/offices.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <https://www.cisco.com/c/en/us/about/legal/trademarks.html>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

© 2019 Cisco Systems, Inc. 保留所有权利。

