

在安全管理裝置上禁用/啟用新GUI橫幅

目錄

[簡介](#)

[NGUI背景](#)

[禁用標語](#)

[重新啟用標語](#)

簡介

本文說明如何禁用安全管理裝置(SMA)上的新Web介面。

NGUI背景

從AsyncOS 12.0開始在SMA裝置上引入了新的Web介面。通過該功能的實現，使用者能夠看到網頁頂部的新標語（當他們登入舊版網路介面時），點選該標語會將使用者路由到新網路介面。可以從以下位置看到橫幅的表示：



附註：子命令NGUIBANNER當前僅在SMA上可用，在郵件安全裝置(ESA)上不可用。

禁用標語

您必須通過安全外殼(SSH)會話連線到裝置。連線後，請登入到CLI並使用命令 `adminaccessconfig` 禁用標語，如下所示：

```
sma.cisco.com> adminaccessconfig
```

```
Select the operation you want to perform:
```

```
BANNER - Configure pre-login message (banner) for the appliance administrator login.
WELCOME - Configure welcome message (post-login banner) for the appliance administrator login.
IPACCESS - Configure IP-based access for appliance administrative interface.
CSRF - Configure web UI Cross-Site Request Forgeries protection.
NGUIBANNER - Enable/Disable the Next Generation User Interface Banner.
XSS - Configure Cross-Site Scripting Attack protection.
ENCRYPTCONFIG - Configure encryption of sensitive data in the appliance.
HOSTHEADER - Configure option to use host header in HTTP requests.
TIMEOUT - Configure GUI and CLI session inactivity timeout.
[> nguibanner
```

```
The Next Generation User Interface is currently enabled.
```

```
Would you like to enable Next Generation User Interface? [Y]N.
```

```
sma.cisco.com> commit
```

提交更改後，在GUI上將看不到標語。

重新啟用標語

要重新啟用標語，您必須按照相同的命令鍵操作，但是這次您必須通過鍵入Y來啟用標語，如下所示：

```
[ ]> nguibanner
```

```
Next Generation User Interface is currently disabled.
```

```
Would you like to enable Next Generation User Interface ? [N]Y
```

```
sma.cisco.com> commit
```