



# Flexible NetFlow IPFIX Export Format

The Flexible NetFlow IPFIX Export Format feature enables sending export packets using the IPFIX export protocol. The export of extracted fields from NBAR is only supported over IPFIX.

- [Information About Flexible NetFlow IPFIX Export Format , on page 1](#)
- [How to Configure Flexible NetFlow IPFIX Export Format , on page 1](#)
- [Configuration Examples for Flexible NetFlow IPFIX Export Format , on page 4](#)
- [Feature Information for Flexible NetFlow: IPFIX Export Format, on page 4](#)

## Information About Flexible NetFlow IPFIX Export Format

### Flexible NetFlow IPFIX Export Format Overview

IPFIX is an IETF standard based on NetFlow v9.

The Flexible NetFlow IPFIX Export Format feature enables sending export packets using the IPFIX export protocol. The export of extracted fields from NBAR is only supported over IPFIX.

## How to Configure Flexible NetFlow IPFIX Export Format

### Configuring the Flow Exporter

Perform this required task to configure the flow exporter.



**Note** Each flow exporter supports only one destination.

You can export to a destination using either an IPv4 or IPv6 address.

#### SUMMARY STEPS

1. `enable`
2. `configure terminal`

## Configuring the Flow Exporter

3. **flow exporter *exporter-name***
4. **description *description***
5. **destination {*ip-address* | *hostname*} [**vrf *vrf-name***]**
6. **dscp *dscp***
7. **source *interface-type* *interface-number***
8. **output-features**
9. **template *data* **timeout** *seconds***
10. **transport udp *udp-port***
11. **ttl *seconds***
12. **end**
13. **show flow exporter *exporter-name***
14. **show running-config flow exporter *exporter-name***

## DETAILED STEPS

	<b>Command or Action</b>	<b>Purpose</b>
<b>Step 1</b>	<b>enable</b>  <b>Example:</b>  Device> enable	Enables privileged EXEC mode.  • Enter your password if prompted.
<b>Step 2</b>	<b>configure terminal</b>  <b>Example:</b>  Device# configure terminal	Enters global configuration mode.
<b>Step 3</b>	<b>flow exporter <i>exporter-name</i></b>  <b>Example:</b>  Device(config)# flow exporter EXPORTER-1	Creates the flow exporter and enters Flexible NetFlow flow exporter configuration mode.  • This command also allows you to modify an existing flow exporter.
<b>Step 4</b>	<b>description <i>description</i></b>  <b>Example:</b>  Device(config-flow-exporter)# description Exports to the datacenter	(Optional) Configures a description to the exporter that will appear in the configuration and the display of the <b>show flow exporter</b> command.
<b>Step 5</b>	<b>destination {<i>ip-address</i>   <i>hostname</i>} [<b>vrf <i>vrf-name</i></b>]</b>  <b>Example:</b>  Device(config-flow-exporter)# destination 172.16.10.2	Specifies the IP address or hostname of the destination system for the exporter.  <b>Note</b> You can export to a destination using either an IPv4 or IPv6 address.
<b>Step 6</b>	<b>dscp <i>dscp</i></b>  <b>Example:</b>  Device(config-flow-exporter)# dscp 63	(Optional) Configures differentiated services code point (DSCP) parameters for datagrams sent by the exporter.  • The range for the <i>dscp</i> argument is from 0 to 63. Default: 0.

	<b>Command or Action</b>	<b>Purpose</b>
<b>Step 7</b>	<b>source interface-type interface-number</b>  <b>Example:</b>  Device(config-flow-exporter) # source ethernet 0/0	(Optional) Specifies the local interface from which the exporter will use the IP address as the source IP address for exported datagrams.
<b>Step 8</b>	<b>output-features</b>  <b>Example:</b>  Device(config-flow-exporter) # output-features	(Optional) Enables sending export packets using quality of service (QoS) and encryption.
<b>Step 9</b>	<b>template data timeout seconds</b>  <b>Example:</b>  Device(config-flow-exporter) # template data timeout 120	(Optional) Configures resending of templates based on a timeout. <ul style="list-style-type: none"> <li>The range for the <i>seconds</i> argument is 1 to 86400 (86400 seconds = 24 hours).</li> </ul>
<b>Step 10</b>	<b>transport udp udp-port</b>  <b>Example:</b>  Device(config-flow-exporter) # transport udp 650	Specifies the UDP port on which the destination system is listening for exported datagrams. <ul style="list-style-type: none"> <li>The range for the <i>udp-port</i> argument is from 1 to 65536.</li> </ul>
<b>Step 11</b>	<b>ttl seconds</b>  <b>Example:</b>  Device(config-flow-exporter) # ttl 15	(Optional) Configures the time-to-live (TTL) value for datagrams sent by the exporter. <ul style="list-style-type: none"> <li>The range for the <i>seconds</i> argument is from 1 to 255.</li> </ul>
<b>Step 12</b>	<b>end</b>  <b>Example:</b>  Device(config-flow-exporter) # end	Exits flow exporter configuration mode and returns to privileged EXEC mode.
<b>Step 13</b>	<b>show flow exporter exporter-name</b>  <b>Example:</b>  Device# show flow exporter FLOW_EXPORTER-1	(Optional) Displays the current status of the specified flow exporter.
<b>Step 14</b>	<b>show running-config flow exporter exporter-name</b>  <b>Example:</b>  Device# show running-config flow exporter FLOW_EXPORTER-1	(Optional) Displays the configuration of the specified flow exporter.

# Configuration Examples for Flexible NetFlow IPFIX Export Format

## Example: Configuring Flexible NetFlow IPFIX Export Format

The following example shows how to configure IPFIX export format for Flexible NetFlow.

This sample starts in global configuration mode:

```
!
flow exporter EXPORTER-1
destination 172.16.10.2
export-protocol ipfix
transport udp 90
exit
!
flow monitor FLOW-MONITOR-1
record netflow ipv4 original-input
exporter EXPORTER-1
!
ip cef
!
interface Ethernet 0/0
ip address 172.16.6.2 255.255.255.0
ip flow monitor FLOW-MONITOR-1 input
!
```

## Feature Information for Flexible NetFlow: IPFIX Export Format

The following table provides release information about the feature or features described in this module. This table lists only the software release that introduced support for a given feature in a given software release train. Unless noted otherwise, subsequent releases of that software release train also support that feature.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to [www.cisco.com/go/cfn](http://www.cisco.com/go/cfn). An account on Cisco.com is not required.

**Table 1: Feature Information for Flexible NetFlow : IPFIX Export Format**

Feature Name	Releases	Feature Information
Flexible NetFlow: IPFIX Export Format	15.2(4)M Cisco IOS XE Release 3.7S  15.2(1)SY	Enables sending export packets using the IPFIX export protocol. The export of extracted fields from NBAR is only supported over IPFIX.  Support for this feature was added for Cisco ASR 1000 Series Aggregation Services routers in Cisco IOS XE Release 3.7S.  The following command was introduced: <b>export-protocol</b> .